DOE/ER/53225--T4

DOE/ER/53225--T4

DE93 002529

PROGRESS REPORT

DOE Grant No. DOE-DE-FG03-86-ER-53225

January 1 - October 31, 1986

Answer 286

STUDIES OF PLASMA CONFINEMENT
IN LINEAR AND RACETRACK MIRROR CONFIGURATIONS

Andras Kuthi
Alfred Y. Wong
University of California
Department of Physics
Los Angeles, CA 90024

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

June 30, 1986

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

So

TABLE OF CONTENTS

	page
INTRODUCTION	1
RACETRACK	3
ECRH generated plasmas.....	3
RF generated plasmas.....	4
Potential structures.....	6
Surface multipole fields	8
LAMEX	10
Hot Electron Physics.....	10
Axial Loss processes.....	12
RF induced effects.....	13
References	16
Figure Captions	17
Figures	19

INTRODUCTION

During the period from october 1985 through june 1986 the UCLA experimental program advanced on a number of fronts. The RACETRACK mirror device has been completed and various diagnostic instruments have been installed (Fig.1,2). Initial experiments were conducted on the quality of the magnetic configuration, and these revealed the important influence of the geomagnetic field. The vertical component of this field causes the field lines of RACETRACK to open up and spiral out of the device. This field error has now been corrected by the installation of vertical field compensating current loops. Electron beam tracing has shown that the main electron losses are now due to the toroidal drifts, with a comparable contribution from horizontal field errors due to toroidal coil misalignment. This alignment problem is now being corrected. Plasmas have been generated by a number of different techniques [1], and the results of these experiments will be described in greater detail in the following sections. The LAMEX device yielded interesting results on a number of fundamental topics concerning mirror confinement. Electron cyclotron resonance heating produced plasmas with a behaviour strikingly similar to that observed in EBT, SM1 and STM, but without a significant hot electron ring population. The lifetime of intermediate warm electron population have been measured and the causes of losses have been investigated.

The spectrum of instabilities have been carefully mapped and the waves are now tentatively identified. Axial plasma loss studies have now been extended to the collisionless electrons, and the scaling with mirror ratio have been compared to the theory of Pastukhov. We carried out experiments on parallel electron heating and found, that contrary to the findings of other laboratories, parallel electron heating leads to enhanced plasma losses in open ended mirrors. Our studies of MHD stability in simple mirrors yielded results showing the strong stabilizing properties of high order multipole fields at the plasma surface even in the absence of magnetic gradient reversal.

Our studies during this period resulted in two papers submitted for publication, one paper in preparation and five papers reported at the meeting of the American Physical Society Division of Plasma Physics. In the following sections we describe some of our results in greater detail.

RACETRACK

ECRH Generated Plasmas

A schematic of the 430 MHz, 5 kW pulsed plasma source is shown in Fig.3. When the magnetic field on the mirror axis is set at 150 G for electron cyclotron resonance with the 430 MHz source, plasma is produced but only in the mirror section which contains the energized antenna. The plasma is restricted to this section, the density in the toroidal sections is about an order of magnitude lower and in the other mirror the density drops a further factor of ten. The source section plasma density can be adjusted by varying the RF power and the neutral pressure in the range of 5 - 5000 W and 5 - 200 microtorr, respectively. The maximum density is 2×10^{10} /cc. The electron temperature depends on the power and the pressure as well, increasing with increasing power and decreasing neutral pressure. The distribution consists of two populations, the bulk with a temperature of 3 - 10 eV and about a 20% fraction of the electrons at a factor five higher temperature. X-ray measurements were negative at all filling pressures and power levels, indicating the low mirror field limits the maximum electron energy below a few keV. The machine can be operated in the symmetrical mode with the help of two ECR antennas, one in each mirror section. In that case, the plasma densities in the two straight sections are equal and about a factor of five to ten higher than the density in the toroidal sections.

RF Produced Plasma

Plasma produced by ECR power is localized to the mirror section containing the power source. This is due to the fact, that cyclotron heating produces a distribution of electrons strongly peaked in the perpendicular direction. These electrons are mirror trapped and do not circulate around the torus. Due to their relatively high energy, they are mostly collisionless, and when they finally do scatter into the loss-cone they are quickly lost by magnetic gradient drifts. Thus, the source distribution, that is, the distribution of ionizing electrons is strongly peaked in the mirror with the ECH power source. The situation is different for the low frequency RF plasma source. This source employs an antenna which produces transverse oscillating magnetic fields and thus parallel electric fields. The antenna conductors run parallel to the mirror axis in a squirrel cage configuration (Fig.3). The plasma produced by this RF source fills the entire torus. Only at high filling pressures is there a toroidal inhomogeneity in plasma density. This is a good indication that the antenna indeed heats electrons mostly in the parallel direction, thus most ionizing electrons are in the mirror loss-cone and circulating. At high neutral pressures the mean free path of the electrons becomes comparable to the mirror length, thus the ionization rate becomes dependent on toroidal position.

Typical profiles of the density and electron temperature are shown in Fig.4. These values have been measured during the RF pulse. This is only possible at RF power levels of 25 W or less. At high RF power levels probe measurements are reliable only in the afterglow, after the termination of the RF pulse. The maximum density of 1×10^{11} /cc has been observed for the highest power of 500 W and an Argon pressure of 0.2 mtorr. No saturation of density has been observed in the power range available at present, 5 - 500 W.

Potential Structures

It has been observed in toroidal confinement experiments that an electrostatic ambipolar potential structure is formed in equilibrium. There have been numerous attempts to explain the observed sign and magnitude of such potentials by using neoclassical transport theory [2]. In bumpy torus experiments the radial electric fields have been measured and found to influence confinement strongly [3]. In tokamaks potential variation along field lines have been observed during strong neutral beam heating [4], and it was noted that such potential variations can significantly degrade confinement [5]. In mirror geometry axial potential variation is the key element in the concept of ambipolar confinement. Stellarator confinement is thought to be strongly influenced by potential surfaces not coincident with magnetic surfaces.

We have started to use the RACETRACK mirror to investigate the potential structures formed in magnetized plasmas due to RF interactions. For a Maxwellian plasma the potential distribution along a field line is given by the Boltzmann relation which states, that for constant density and temperature the field lines are equipotentials. In RACETRACK this clearly not so. As shown in Fig.5, there is a potential difference between the toroidal sections and the straight sections. That this potential difference is about 10 eV, the order of the electron temperature, suggests that the plasma is strongly non-Maxwellian.

This is expected, since the plasma is generated and maintained by RF, which heats electrons parallel to the field lines. At higher power levels the potential difference increases in spite of the constant temperature and that the density is being higher in the toroidal section than in the straight sections.

Surface Multipole Fields

The stability of a high mirror ratio configuration with respect to the low frequency interchange mode is an important issue in any configuration containing magnetic mirrors. A high degree of axisymmetry is desirable in order to reduce neoclassical radial transport. We have shown experimentally, that the curvature driven interchange instability can be suppressed by a high order multipole magnetic field creating differential shear at the plasma boundary [6]. No radial magnetic well is formed, and the configuration is axisymmetric except for a narrow layer at the plasma boundary with width less than 20% of the plasma radius. In a large simple mirror plasma was created by launching ECRH power at 170 MHz, the resonance layer was at the mirror midplane. The mirror ratio was varied from 7 to 35 by varying the throat field. The parameters of the hydrogen plasma were: density 10^{19} /cc, electron temperature 5 eV.

In the simple mirror configuration large amplitude density fluctuations are observed, $dn/n = 0.6$, throughout the plasma, peaking in the frequency range 0.4 - 2 kHz. Azimuthal mode numbers $m = 2 - 10$ have been identified. The particle confinement time was 150 microsec. This is close to the radial expansion time commonly used to estimate radial losses due to the interchange instability. Figure 6 shows the evolution of the density profile as a function of multipole current and the corresponding shear.

The multipole order is 32. As soon as the multipole field exceeds a critical strength a stable surface layer is created and a negative pressure gradient can be supported in the core plasma. This is consistent with the Rosenbluth - Longmire criterion [7]. Figure 7 shows the density fluctuation level dn/n , the line averaged density n and the particle confinement time as a function of the multipole current. Effective stabilization of the plasma is observed for $I_m > 200$ Amperes. The average density and the confinement time increase almost an order of magnitude due to the suppression of flute induced radial losses. The confinement time approaches the classical collisional limit. A linear scaling of this collisional confinement time was confirmed for the range of mirror ratio $5 < 35$.

LAMEX

Hot Electron Physics

We have applied fundamental ECR heating at 430 MHz to plasmas in the LAMEX device. The resulting electron distribution consists of a cold background of a few eV and a hot tail of about 1 keV. This tail is like the intermediate energy population seen in SM-1, EBT and STM rather than being a relativistic ring population. However, the C, T, and M modes as seen on these other devices are also seen on LAMEX [8].

The hot component has a very short lifetime of a few tens of microseconds which is due to rapid radial transport. The density of the hot component increases when the neutral pressure is lowered or the power is raised. When the hot component reaches a certain fraction of the total density low frequency fluctuations are stabilized, at which point cold plasma radial transport is reduced. Because the hot electrons decay very rapidly, the fluctuations reappear in the afterglow. The fraction of hot electrons required for stabilization appears to be less than one per cent, which is somewhat lower than the few per cent predicted by theory for the experimental conditions.

When the hot component fraction is increased further, the T-M transition is reached.

The cold plasma virtually disappears and the hot electron interchange - identified by frequency and wavelength measurements - is active on the M - side of the transition. On the T - side of the transition higher frequency oscillations ($f > 10 f_{ci}$) have been observed which have been tentatively identified as due to the compressional Alfvén mode. It is believed, that the observed rapid radial transport of the hot electrons is caused by these two types of fluctuations, since calculated classical loss processes are about a hundred times too slow.

Axial Loss Processes

We have studied the axial loss of plasmas produced by ECR heating in the simple mirror LAMEX. Typical density is 10^9 /cc and the electron temperature is in the range 2 - 10 eV. The ion temperature is lower than 1 eV. The ions are thus collisional, and we have found, that the axial ion loss, that is, plasma loss, is proportional to the acoustic speed and the confinement time scales linearly with the mirror ratio [9]. Recently we have studied the electron loss in Neon plasmas at the mirror ratios of 2 - 20. The electrons are collisionless, they are confined by both the magnetic mirror field and the ambipolar potential. The axial loss is proportional to the square of the density. This is consistent with the prediction for collisionless electrons. Preliminary results show that the scaling of electron loss with mirror ratio is weaker than linear, but in order to definitively confirm a logarithmic dependence we will have to increase the range of mirror ratios up to about 50 in the near future.

RF Induced Effects

The plasma potential in a simple mirror is usually determined by the axial ambipolar loss condition. The electron speed being much larger than the ion speed a positive potential develops which retards the electrons and accelerates the ions until the loss rates are equal. The magnitude of this plasma potential is about $4 T_e$ when the plasma is Maxwellian and when radial losses can be neglected. If the electron distribution function is driven to anisotropy, for example by ECR heating or by the parallel electric field components of an ICRH antenna, the plasma potential changes, and so does the axial plasma loss rate.

It has been observed in tandem mirror experiments that the application of RF power in the ion cyclotron range of frequencies drastically raised the plasma potential in the anchor cells of a tandem mirror, and the endloss Faraday analyzers registered sudden decrease in collected ion currents during the RF pulse. This reduction in endloss ion currents have been interpreted as tandem confinement of center cell plasma by the increased anchor potential [10,11].

Our experiments on RF heating on LAMEX lead us to a different conclusion. Since the enhanced plasma potentials are caused by parallel electron heating due to the parallel electric fields of the RF antennas, the throat antenna of LAMEX is ideally suited to conduct studies of these nature.

This antenna is of the Nagoya type III design, it is installed in the mirror throat and it produces transverse oscillating magnetic fields and thus parallel RF electric fields. These fields interact mainly with the loss-cone electron population, which are bouncing between the ambipolar potential sheaths. The plasma is created by ECR heating in hydrogen at 4 microtorr filling pressure. Approximately 150 W of ECR power at 430 MHz is applied to a quarter wave antenna. The resulting plasma has a density of 2×10^9 /cc and the electron temperature is about 10 eV. When the 4 MHz, 25 W RF pulse is applied to the throat antenna, the plasma potential immediately rises from about T_e to $4 T_e$ (Fig.8), and the line density as measured by an X - band interferometer starts to decay (Fig.9). The gridded endloss probe, however, shows the same signature as in all the other tandem mirror experiments, an immediate drop in collected ion current (Fig.10). This drop cannot be explained in our experiment as ambipolar plugging of a central cell. In fact, the dropping line density clearly shows, that the confinement is drastically deteriorating during the RF pulse. That this effect is not due to interaction of the ECH source with the RF power is seen in the fact, that the enhanced losses can be observed even when the RF pulse is applied during the afterglow. Changing the negative bias on the endloss collector reveals the real reason of the dropping axial ion current.

When the collector is biased negative only about T_e with respect to the end wall (the front grid is flush with the wall and grounded to it) the collected current changes sign during the RF pulse, clearly showing electron collection in spite of the fourfold increase of plasma potential and thus increased effective electron repulsive bias. This shows, that the reduced end current is due to collected electrons and not due to plugging and increased confinement. The negative bias on the endloss probe could be increased to about $10 T_e$ and still showed electron collection. This is not really surprising, since the RF antenna near fields are of the order of 10 V/cm with total potential difference along the antenna of about 300 V at the applied RF power of 25 W. This near field completely penetrates the plasma due to the low density, and accelerates some electrons to similar energies. It is thus expected, that in the plugging experiments reported the 100 kW of RF power on antennas of similar size to ours could create very high parallel energy electron populations and could cause the apparent decrease of endloss currents. This induced loss effect is not seen in the closed field line RACETRACK device, where these studies are now continuing.

REFERENCES

- [1] "RACETRACK: A Novel Device for Basic Research on Magnetized Plasmas"
A.Kuthi, H.Zwi, L.Schmitz, D.Chelf and A.Y.Wong, UCLA report PPG 979
May 1986, submitted to Rev. Sci. Instr.
- [2] D.E. Hastings and T. Kamimura, Nucl. Fusion 24 (1984) 473.
- [3] F.M. Bienosek and K.A. Connor, Phys. Fluids 26 (1983) 2256.
- [4] C.S. Chang and R.W. Harvey, Nucl. Fusion 23 (1983) 935.
- [5] C.S. Chang, Phys. Fluids 26 (1983) 2140.
- [6] "Stabilization of Interchange Modes in a Mirror by a Sheared Surface
Field"
L. Schmitz, A.Y. Wong and D. Chelf, Bull. Am. Phys. Soc., 30 (1985)
1460, paper 4Q18, and paper submitted to Phys. Rev. Letters.
- [7] M.N. Rosenbluth and C.L. Longmire, Annals of Physics 1, 120 (1957).
- [8] "Hot Electron Instability Observed in a Single Cell Mirror"
L.Olson, K.L.Lam, A.Kuthi, B.J.Leikind, H.Zwi and A.Y.Wong,
Bull. Am. Phys. Soc., 30 (1985) 1381, paper 1R40.
- [9] "Axial Loss of Collisionless and Collisional Plasmas in a Magnetic
Mirror with Electrostatic Potential"
K.L.Lam, L.Olson, B.J.Leikind, A.Kuthi, H.Zwi and A.Y.Wong,
Bull. Am. Phys. Soc., 30 (1985) 1381, paper 1R41.
- [10] "Plasma Potential Enhancement by RF Heating Near the Ion-Cyclotron
Frequency"
D.K.Smith, K.Brau, P.Goodrich, J.Irby, M.E.Mauel, B.D.McVey,
R.S.Post, E.Sevillano and J.Sullivan, Phys. Fluids 29 (1986) 902.
- [12] "Effects of Parallel RF electric Fields on a Mirror Confined Plasma"
A.Kuthi, H.Zwi, L.Olson, K.L.Lam and A.Y.Wong, to be published.

FIGURE CAPTIONS

Fig.1. Schematic of the RACETRACK device.

Fig.2. The RACETRACK Magnetic Field Configuration. Field lines in one quadrant of the machine (a). Magnetic field strength along the axial field line for the typical operating current of 350 A (b).

Fig.3. A schematic of the plasma sources.

Fig.4. Typical plasma density and temperature profiles during a low power RF pulse.

Fig.5. Plasma potential profiles in the straight sections (full line) and in the toroidal sections (dashed line), showing the potential difference along field lines. The toroidal positions have been mapped along the field lines to the midplane of the straight sections.

Fig.6. The evolution of the density profile as a function of the multipole current and the corresponding shear.

Fig.7. The density fluctuation level dn/n , the line averaged density and the particle confinement time as a function of multipole current.

Fig.8. The evolution of the plasma potential during the RF pulse.

Fig.9. The evolution of plasma line density during the RF pulse showing the enhanced losses during parallel electron heating both during the ECH plasma generation pulse and in the afterglow.

Fig.10. The evolution of the collected end probe current for two different collector bias voltages.

Figure 1

Figure 2

Figure 3

Figure 4

Figure 5

Figure 6

Figure 7

Figure 8

Figure 9

Figure 10

IS

CCT Technical Progress From 1/1/86 to 6/30/86.

- (1) Demonstrated that fast wave current drive is most efficient in the vicinity of the lower-hybrid frequency.
- (2) Obtained steady state (DC) current drive using 20 kW of RF power.
- (3) Observed current drive due to electron cyclotron resonance (500 A).
- (4) Initiated e-beam injection for current drive (500 A).
- (5) Investigated wall preparation using filament and RF discharges.
- (6) Installed the FMIT RF system .
- (7) Obtained the distributions of RF driven currents.
- (8) Studied the variation of magnetic turbulence versus the plasma equilibrium.
- (9) Observed the generation of non-resonant fast ions (2 keV).
- (10) Installed additional water cooling on observation ports.
- (11) Installed a 2 volt second capability ohmic transformer into the central area of CCT.
- (12) Initiated the utilization of the 2-D field code developed by ORNL.
- (13) Participated in U. of Wisconsin/DOE ICRF work shop.
- (14) Participated in Surface Science Conference in Princeton.
- (15) Participated in a Current Drive Work Shop in Livermore.
- (16) Attended the American Nuclear Society's meeting on reactor technology in Reno.
- (17) Dr. Pat Pribyl joined the CCT group from MIT to head the CCT device operations.
- (18) Dr. T.K. Mqn is working on modeling (codes) within CCT 50 % of the time from Prof. Conn's group.

The University of California, Los Angeles

TASK IIIA

Project

Far-Infrared Fusion Plasma Diagnostics

N.C. Luhmann, Jr. and W.A. Peebles

FY85	\$295k op	FY86	\$182.k op	FY87	\$256k op
	\$55k equip				

Purpose

The goal of the Task IIIA program is to develop innovative plasma diagnostic techniques and to actively encourage their implementation onto mainline fusion devices. A major effort has involved the successful development of a two dimensional tomographic imaging interferometer for tokamak density profile determination. The primary short term goals are the development of a high resolution polarimeter suitable for accurately measuring tokamak current profiles which will be tested on the TEXT device, a laser fluorescence scattering system for a spatially and temporally localized determination of edge ion temperature and finally the investigation of advanced phase scintillation/far forward scattering techniques for the study of long wavelength phenomena (MHD, fast magnetosonic wave, etc.) in fusion plasmas.

Approach

Two dimensional imaging detector arrays and optical systems are developed within this program and applied to tokamak diagnostics. The major long term goal is tomographic reconstruction of current profiles in tokamak plasmas. Initially a 30 channel Schottky diode array is under development to perform high resolution polarimetry. The system will be tested on the TEXT device.

The use of H α laser fluorescence scattering is being investigated on the PISCES device at UCLA. The goal here is an accurate spatially resolved measurement of edge ion temperature as well as neutral density.

The development of advanced detector arrays under Task IIIB will be utilized to perform so called phase scintillation experiments. This will allow easy correlation of density fluctuations across a fusion plasma. It is particularly useful in contrasting $k_{\perp}$, $k_{\parallel}$ for long wavelength phenomena such as MHD, fast magnetosonic wave, etc. The technique is basically a very high resolution (both in phase and space) interferometer.

Progress

1. First tomographic tokamak density reconstructions using 2-D phase imaging.

2. Movie generated using 2-D imaging data showing time history of Microtor tokamak from start-up through a minor disruption to discharge termination.
3. Developed dye laser fluorescent scattering system for installation on UCLA PISCES device for edge plasma, divertor and limiter studies.
4. Began transfer of FIR interferometry technology to TEXT.
5. Began phase scintillation scattering system design for TEXT, DIII-D.

Plans

1. Two dimensional tomographic reconstruction movies of disruptions sawteeth, oscillating gas-puff, and tokamak start-up.
2. Polarization imaging (≥ 20 channels) to accurately and routinely determine tokamak current profiles.
3. Laser fluorescence measurements on UCLA PISCES experiment - divertor and scrape-off layer studies.

Milestones

1. Neutral measurements on PISCES February 1987
2. Complete 2-D Microtor tomographic imaging movies March 1987
3. Accurate polarization determination of current profile June 1987

Graduate Students

Jeff Corbett 100%

Major Publications

1. H. Park, N.C. Luhmann, Jr., W.A. Peebles, R. Kirkwood, "Observation of Second Harmonic Ion Bernstein Waves Excited by Fast Wave Mode Conversion in the UCLA Microtor Tokamak," Phys. Rev. Letters 52, 1609 (1984).

2. H. Park, P.S. Lee, W.A. Peebles and N.C. Luhmann, Jr., "Tokamak Ion Temperature Determination Via cw Far-Infrared Laser Scattering from Externally Excited Ion Bernstein Waves, Nuclear Fusion 25, 1399 (1985).
3. H. Park, W.A. Peebles, N.C. Luhmann, Jr., R. Kirkwood and R.J. Taylor, "Observation of the Externally Excited Fast Magnetosonic Wave Via Collective Thomson Scattering, Plasma Physics 27, 1195 (1985).
4. N.C. Luhmann, Jr. and W.A. Peebles, "Instrumentation for Magnetically Confined Fusion Plasma Diagnostics," Invited Review Article: Rev. Sci. Inst. 55, 279 (1984).
5. D.L. Brower, W.A. Peebles, Ch.P. Ritz, E.J. Powers, N.C. Luhmann, Jr., "Resolving the Propagation Direction of Tokamak Microturbulence via Homodyne Spectroscopy," Rev. Sci. Inst. 57, 1977 (1986).
6. D.L. Brower, J. Howard, W.A. Peebles, S. Kim, R.L. Savage, Jr., N.C. Luhmann, Jr., J. Wagner, D.B. Rutledge, D.P. Neikirk, P.E. Young, H.K. Park, "Recent Advances in Multichannel Far-Infrared Collective Scattering and Interferometry System," Proc. of 11th Symposium on Fusion Engineering, Austin, TX (1985).
7. J. Howard, W.A. Peebles and N.C. Luhmann, Jr., "Polarimetric Phase Imaging for Plasma Current Profile Measurements," Proc. of 10th Int. Conf. on Infrared and Millimeter Waves, Florida, December 9-13, 1985.
8. J. Howard, W.A. Peebles and N.C. Luhmann, Jr., "The Use of Polarization Transforming Reflectors for Far-Infrared and Millimeter Waves," Int. Jour. of Infrared and Millimeter Waves, 7, 1591 (1986).

The University of California, Los Angeles

TASK III B

Project

Advanced Fusion Plasma Diagnostics

N.C. Luhmann, Jr., W.A. Peebles and D.B. Rutledge

FY85 \$293k op FY86 \$351.2k op FY87 \$384k op

Purpose

Development of advanced diagnostic systems and techniques suitable for mainline fusion devices such as CIT, DIII-D, TFTR and TEXT. Particular emphasis is placed on direct collective Thomson scattering from ECRF waves on TEXT, the development of suitable millimeter wave reflectometry and twin wavelength interferometry systems for CIT and DIII-D. However, the major goal of the program is to develop an innovative yet practical diagnostic capable of yielding the alpha particle velocity distribution in the next operational phase of burning plasmas. In addition, it should be noted that there exists an active diagnostic technology program in the area of millimeter/submillimeter wave sources, detectors and arrays which feeds directly into mainline fusion devices such as TFTR. A blend of advanced technology and instrumentation development together with basic plasma physics expertise from the basis of this program.

Approach

FIR Schottky diode receivers and probe systems will be developed to enable detection of scattered radiation from ECRF waves at frequencies of 60 GHz and higher. In addition, scattering arrangements will be flexible so that $k_{\parallel}$ and $k_{\perp}$ fluctuations can both be probed over a wide range ($0 < k < 100\text{cm}^{-1}$) of wavenumber.

Fast sweep ($\approx 1\mu\text{s}$) millimeter wave reflectometry systems will be developed so that the temporal development of density profiles during, for example, the L to H-mode transition and pellet fueled discharges can be followed. This will require the use of Gunn oscillators and multiplier systems for high density devices such as CIT. Such systems are already under development in the Task IIIB diagnostic technology program which will also aid as required devices such as TFTR, DIII-D and CIT.

The use of far infrared interferometers vibrationally compensated in the visible will not be suitable for radial views on devices such as CIT. It is essential that interferometers be developed utilizing either two far-infrared wavelengths, two CO_2 (9 and $11\mu\text{m}$) wavelengths or possibly a FIR wavelength combined with a CO_2 wavelength.

A novel diagnostic technique is under development to probe the α -particle distribution function. This involves CW collective Thomson scattering from externally excited ion Bernstein waves.

Progress

1. Developed a sensitive 183 GHz receiver system for ECRF scattering. Consists of a tripled 61 GHz Gunn oscillator together with Fabry Perot diplexer, Schottky diode mixer and low noise IF amplifier.
2. Developed new thin membrane (1 μm) microbolometer arrays which eliminate substrate modes and material losses permitting short wavelength operation ($\leq 100\mu\text{m}$) for devices such as CIT.
3. Developed new high power FIR lasers for use in large tokamaks for imaging interferometry and polarimetry as well as scattering. Providing design information to major fusion laboratories such as Los Alamos.
4. Successfully performed laboratory prototype experiment showing the viability of α -particle velocity distribution determination via FIR scattering measurement of wave damping. First use of the broadening of the angular distribution of the scattered radiation to determine wave damping.
5. Development of large (> 2000 elements) GaAs Schottky diode frequency multiplier arrays for applications in tokamak interferometry and polarimetry systems.
6. Conducted development work aimed at a two-color CO_2 interferometer for DIII-D.
7. Initiated laboratory studies of millimeter wave reflectometer systems for CIT and DIII-D.

Plans

1. Provide new thin membrane microbolometer arrays for use on devices such as CIT, TFTR and DIII-D.
2. Continue development of 300 GHz Schottky diode array for scattering and magnetic field fluctuation studies.
3. Provide 119 μm corner cube mixer contacting for Princeton.
4. Continue reflectometry system development for CIT and DIII-D.
5. Develop scattering techniques for probing ECRF waves at frequencies of 60 GHz and higher.

6. Continue development of solid state frequency multiplier arrays.
7. Develop SIS and Josephson junction arrays for plasma diagnostics.
8. Continue advanced α -particle diagnostic development aimed toward CIT.
9. Continue to provide diagnostic technology support for mainline fusion devices.

Graduate Students (% DOE Support)

UCLA

Tom Lehecka 100%
 Calvin Domier 100%
 Christina Jou 0%

CalTech

Wayne Lam 100%
 Gabriel Rabeiz 100%

Milestones

1. Complete narrow band and broadband reflectometer prototype measurements for DIII-D.
 March 1987
2. Test polarimetry techniques on TEXT May 1987
3. Complete solid state frequency multiplier array development June 1987
4. Test ECRF scattering on TEXT August 1987

Major Publications

1. N.C. Luhmann, Jr., W.A. Peebles, "Laser Diagnostics of Magnetically Confined Thermonuclear Plasmas," a chapter in the Laser Handbook, Vol. 5 edited by M.L. Stich and M. Bass, North Holland-Physics Publishing (Amsterdam) (1986).
2. P.T. Tong, D.P. Neikirk, P.E. Young, W.A. Peebles, N.C. Luhmann, Jr., D.B. Rutledge, "Imaging Polarimeter Arrays for Near-Millimeter Waves," IEEE Trans., MTT-32, 507, 1984.
3. P.C. Efthimion, G. Taylor, W. Ernst, M. Goldman, M. McCarthy, H. Anderson, N.C. Luhmann, Jr., "1-Millimeter Wave Interferometer for the Measurement of Line Integrated Electron Density on TFTR," Rev. Sci. Inst., 56, 708, 1985.

4. N.C. Luhmann, Jr., D.B. Rutledge, C.E. Zah, "Near-Millimeter Wave Imaging Arrays," Proc. of URSI Meeting, Vancouver, Canada (1985).
5. N.C. Luhmann, Jr., T. Lehecka, R.L. Savage, Jr., R. Dworak, W.A. Peebles, "High Power, Twin frequency FIR Lasers for Plasma Diagnostic Applications," Rev. Sci. Inst. 57, 1986.
6. N.C. Luhmann, Jr., W.A. Peebles, S. Kim, Zimmerman, P., "ECRH absorption and Propagation Studies via Collective Thomson Scattering," Rev. Sci. Inst. 57, 1980.
7. W.W. Lan, C.F. Jou, N.C. Luhmann, Jr. and D.B. Rutledge, "Diode Grids for Electronic Beam Steering and Frequency Multiplication," Int. Jour. of Infrared and Millimeter Waves, 7, 27 (1986).
8. E.J. Doyle, J. Howard, W.A. Peebles and N.C. Luhmann, Jr., "Determination of the Two-Dimensional Density Distribution in a Tokamak Plasma Using Phase-Imaging Interferometry," Rev. Sci. Inst. 57, 1945 (1986).
9. D.B. Rutledge, D.P. Neikirk, and D.P. Kasilingam, "Integrated-Circuit Antennas," a chapter in Infrared and Millimeter Waves, 10, K.J. Button, ed., Academic Press, New York, 1-100 (1983).
10. N.C. Luhmann, Jr., W.A. Peebles, "Instrumentation for Magnetically Confined Fusion Plasma Diagnostics," Invited Review Article Rev. of Sci. Inst., 55, 279 (1984).
11. P.E. Young, D.P. Neikirk, D.B. Rutledge, P.P. Tony and W.A. Peebles, "Multichannel Far-Infrared Phase Imaging for Fusion Plasmas," Rev. of Sci. Inst. 56, 81 (1985).

TASK IIIA

SECTION I: PROGRESS REPORT

INTRODUCTION

The Task IIIA program at UCLA has been concerned with the development of innovative yet practical plasma diagnostic systems capable of providing detailed information essential to the success of the fusion program but not presently available within the fusion community. Historically, this has involved an initial development in the laboratory, followed by a test of feasibility on the Microtor tokamak prior to transfer of the technique/instrument to main line fusion devices. Strong emphasis has been placed upon the far-infrared (FIR) spectral region where novel diagnostic systems and technology have been developed and then distributed throughout the fusion program.

This trend has been maintained throughout the last six months, with advanced interferometric and scattering systems developed in the labs at UCLA finding ultimate applicability on the TEXT tokamak combined with the promise of imminent implementation on the D-III tokamak at the G.A. facility in San Diego. As indicated in last year's proposal we have undertaken an ambitious program to provide a fully tomographic reconstruction of the plasma density contours in a tokamak plasma through a multi-view implementation of phase imaging interferometry. We have successfully brought the first phase of this program to a close, with fully tomographic reconstructions of the plasma density distribution in the Microtor tokamak having been obtained, and with a movie of the reconstructed data in the production stage. The results of this research are discussed in greater detail in part A of this section. The proposed upgrades and improvements to the imaging system along with a discussion of its enhanced capability are discussed in Sec. II of this report.

As part of the Task IIIA program, the multichannel scattering apparatus developed at UCLA was efficiently transferred to TEXT a few years ago. This apparatus has continued to be employed for investigation of the strong spectral and spatial asymmetries in the microturbulence originally discovered through the unique multichannel and spatial scanning capabilities of the system. In addition to the multichannel scattering development transfer to TEXT we have also partially installed a 20 channel interferometer system so that accurate density profiles can be determined. Already, the system has been used to produce high resolution Abel inverted density profile of the TEXT discharge on a shot to shot basis and under a variety of discharge conditions. As well, MHD phenomena (sawteeth, Mirnov oscillations etc.) have been studied in detail for the first time. The results of the investigations to date are reported in part B of this paper.

When fully installed, the TEXT interferometer will be capable of providing density profiles in a single shot. With the experience obtained on the Microtor imaging interferometer, we hope to implement a number of extra views and so produce tomographic

reconstructions of the plasma profile. These points are addressed in detail in Sec. II of this report.

A. PHASE IMAGING ON MICROTOR

Work commenced in April of 1985 to construct a two-dimensional forty channel heterodyne FIR interferometer to measure the electron density distribution in the minor cross section of the UCLA Microtor Tokamak. The principle of the experiment is to image probe beams occupying the entire plasma cross-section in two orthogonal views, onto two sets of linear microbolometer detector arrays.

A schematic layout of the 2-D imaging interferometer is shown in Fig. 1. The vertical arm is configured as a simple Mach-Zehnder interferometer while the horizontal view is a Michelson arrangement with the probe beam reflecting off the flat inner wall of the vacuum vessel.

A notable feature of the optical system is its use of polarizing optics to separate the incident and reflected beams from the rotating circular grating (used to produce a small frequency offset for IF generation) and from the vessel inner wall. Polarizing reflectors are constructed from a free standing wire grid oriented at 45° to the polarization direction of the incident radiation, followed by a flat copper mirror. The separation of the mirror and grid is adjusted to be one eighth of a wavelength so that the radiation is polarized orthogonally to the incident beam after a double pass. Use of reflecting polarizing optics is preferable to crystal quartz quarter wave plates for reasons of higher efficiency, larger apertures, no spurious etalon effects and continuously variable polarization response. The latter feature enables the polarization distortion produced upon reflection from the grating to be exactly compensated. These polarizing reflectors have been tested experimentally and the results agree well with simple models of their performance. These studies resulted in the acceptance for publication (May, 1986) of a paper submitted to the International Journal of Infrared and Millimeter Waves.

The grating is usually rotated at a rate such as to give an IF frequency of ≈ 20 kHz, which is more than adequate to resolve the fastest changing density variations on Microtor. The IF frequency is monitored using a biconical Schottky barrier diode detector in order to provide a reference phase baseline for comparison with signals from the plasma arms of the interferometer. The raw signals are directly digitized for later processing by a PDP-11 computer. In earlier measurements, at an IF frequency of 85 kHz, the signals were bandpass filtered and then passed to electronic phase comparators. This processing method was abandoned, however, due to the limited bandwidth of the phase comparators.

Signals from the microbolometers are amplified in two stages for a total of 90 dB of gain, and then digitized at a rate of 200 kHz. At this rate the digitizers sample approximately 10 data points per IF cycle. The plasma phase shift is recovered from the digitized waveform entirely by computer processing; the location in time of the maxima and minima of the sinusoids are located by an extremum finding algorithm and the phase determined by subtraction from the reference phase baseline. The measured residual phase noise due to vibration is

Fig. 1 Schematic of the experimental arrangement for the 2-D 40 channel imaging interferometer.

5-10°, corresponding to a density resolution for both views of $\leq 5 \times 10^{10} \text{ cm}^{-3}$. At the maximum phase data rate of 40 kHz (i.e. twice the IF frequency), the phase resolution of the extremum finder is $\sim 5^\circ$. Much better resolution can be obtained at the expense of bandwidth.

Several methods of analysis are employed for recovery of the density distribution from the line integrated density measurements. Conventional Abel inversion,

$$n_e(r) = \frac{-1}{\pi} \int \frac{[d\phi(x)/dx]dx}{(x^2-r^2)^{1/2}} \quad (1)$$

is applied to both views using Barr's method. Barr's method, and Abel inversion in general, assumes that the object to be reconstructed has cylindrical symmetry.

To reduce noise in the differentiation of the profile, data smoothing is incorporated in the method in the form of a 5 point polynomial fit. To deal with the asymmetry of the actual data, the method of Ref. 1 is used. There, it is shown that the profile can be exactly reconstructed if the asymmetry takes the form of a weighting function separable in the direction orthogonal to the direction of observation, i.e. it is assumed that

$$n_e(r,x) = g(x) n_0(r) \quad (2)$$

where $g(x)$ is a weight function describing the degree of asymmetry. The weighting function can be obtained from the data by forming the odd $\phi_1(x)$, and even $\phi_2(x)$, components of the phase profile, and calculating

$$g(x) = 1 + \phi_1(x)/\phi_2(x) \quad (3)$$

The even portion of the profile is Abel inverted as normal and the asymmetric profile recovered from Eq. 2. Figure 2 shows measured chord averaged densities and Abel inverted electron densities during the startup phase as a function of radial position. This data was obtained from the vertical view of the interferometer and shows markedly different plasma behaviour under the two different discharge conditions, viz. with and without filament discharge preionization. The behaviour is highly reproducible, and though not well understood at present, the different time histories may be due to the presence or otherwise of the filament electric field.

Figure 3 displays the plasma evolution on a longer timescale and shows a large density perturbation approximately 20 ms into the shot. As seen in Fig. 4, this behaviour was coincident with a minor disruption in the plasma current and a large increase in the plasma UV emission. Horizontal line density profiles show a similar time history but are more symmetric about the plasma center. The disruption appears to result in an expulsion of plasma from the central regions of the vessel. This behaviour is also observed with the horizontal arm of the interferometer and is confirmed by the tomographic reconstructions.

Two approaches have been followed for tomographic reconstruction of the density profile utilizing information produced by both views of the plasma. Initially a matrix inversion technique was employed. In order to perform the inversion the set of matrix equations must be

WITHOUT FILAMENT DISCHARGE

LINE DENSITY

ABEL INVERSION

WITH FILAMENT DISCHARGE

LINE DENSITY

ABEL INVERSION

Fig. 2 Top: Measured line density and Abel inversion during the startup phase for a discharge without filament preionization. Bottom: As above but with filament preionization. The behaviour in each case is highly reproducible.

Fig. 3 Measured line density and Abel inversion showing the effects on the density profile of a minor disruption approximately 20 ms after the initial breakdown.

Fig. 4 Plot of plasma current, vertical line density and UV emission (at same radial position as interferometer chord) showing effects of minor disruption at $t \approx 20$ ms after breakdown.

overdetermined, which means that the number of pixels must be less than or equal to the number of lines of sight. This severely limits the number of reconstructed pixels, though this limit can be overcome somewhat by using smoothing to extend the data set. Smoothing is in any case required to reduce the reconstruction errors, so in practice reconstructions were obtained using 5x5 and 7x7 element square pixel arrays.

However, the quality of these reconstruction was compromised by three inherent limitations.

- 1) The matrix inversion technique tends to produce reconstructions showing rectangular symmetry due to the disposition of the interferometer views.
- 2) The reconstructions lack resolution and
- 3) Reconstructions may become negative in some circumstances.

All of these problems can be solved or alleviated through the use of the maximum entropy reconstruction technique. The maximum entropy technique, of its nature, enforces positivity and may resolve an arbitrarily large number of pixels (provided that the pixel is in some way constrained by the viewing geometry). Furthermore, by appropriately modifying the pixel "weights" it is possible to build in a certain level of apriori knowledge about the nature of the reconstructed image.

Such a code has now been implemented and extensively tested using trial input functions. The results which have been obtained using a circular array of pixels have, given the limited number of views, exhibited remarkable agreement between the trial and reconstructed images (see Fig. 5). Figure 6 shows a sequence of tomographically reconstructed snapshots of the plasma distribution during the minor disruption described earlier. The plasma appears to radially expand to the walls of the vessel (~ 5 ms) before collapsing (due to the influx of impurities) and subsequently establishing a new equilibrium position close to the inside wall of the vacuum vessel.

Research is still underway towards an improvement of the reconstructions, whilst, a movie showing some of the more important results of this research is being produced.

B. INTERFEROMETRY ON TEXT

The recent installation of a 5 channel high resolution interferometer (channel spacing 2.5 cm) required a large design and development effort at UCLA. Phase comparator electronics including input filters were designed, tested and constructed. Great care was taken to match the phase distortion produced through the filters etc. by variations in the IF so that the resultant phase noise was minimal. In addition a variable video bandwidth of 15 kHz was chosen so that MHD phenomena could be easily studied.

Parabolic cylinder beam expansion optics were designed, tested and constructed using electric discharge machining techniques. the presently installed mirrors expand the output from the laser to an elliptical cross section allowing ~ 25 cm of the plasma diameter to be probed. A larger set of mirrors to view the entire plasma cross section have been designed

Fig. 5 Input and reconstructed contours (using maximum entropy technique) for (a) displaced gaussian distribution and (b) two gaussians symmetrically offset vertically from the center of the pixel array. Fig. (c) shows the equal area pixel grid used for the reconstructions and (d) shows the disposition of the probing chords used for the data presented in Fig. 4.

Fig. 6 Sequence of "snapshots" produced using data from both views of the interferometer, showing the evolution and decay of the plasma profile during a minor disruption.

and are under construction.

The elliptical cross section beam after passage through the plasma is mixed with a reference beam as illustrated in Fig. 7. The mixing elements are quasi optical GaAs Schottky barrier diodes that are designed, constructed and contacted at UCLA. There is no reliance on outside commercial companies who also charge ~ \$5,000 per mixer and provide limited recontacting services. This independence and low cost enable us to contemplate 20-40 channel systems on TEXT to perform simultaneous measurements of line density and Faraday rotation.

The basic design of the corner cube array as illustrated in Fig. 8 is easily extended to 20 channels and is fully compatible with the 'Soltwisch' technique of measuring Faraday rotation. The optical components and corner cubes are mounted on a single structure and so conversion from interferometry to scattering or polarimetry is very simple requiring only a few hours.

Already significant data has been obtained, with the reproducibility of the TEXT discharges allowing full profiles of electron density to be produced on a shot to shot basis. The time evolution of the density profile during a typical TEXT discharge can be seen in Fig. 9. We notice that the profile is initially hollow, but rapidly peaks and relaxes, before slowly developing into a 'parabolic' profile during the plateau. This behaviour is remarkably similar to that shown in Fig. 2 for the Microtor discharge but on a timescale which is longer in almost direct proportion to the ratio of the respective total durations of the plasma pulses. Investigations are underway to uncover the relevant mechanisms and scaling of this behaviour.

Figure 10 shows observations of sawteeth in the vicinity of the $q = 1$ surface with the phase of the oscillations reversing about the inversion layer. It is hoped that with the implementation of the full 30 channel system, the plasma profile during such MHD activity can be completely recovered in a simple shot. We have also obtained important data during oscillating gas puff experiments (see Fig. 11) for particle transport and confinement studies. Future studies will include investigations of profile modification during operation of the EML, impurity injection, point limiter, pellet injection and electron cyclotron heating. It is thus clear that the developmental work undertaken and completed at UCLA is, and should continue to pay handsome dividends in terms of the quality of data obtained and the physics insights revealed.

REFERENCES

Y. Yasutomo, K. Miyata, S. Himeno, T. Enoto and Y. Ozama, IEEE Trans. Plasma Sci. PS-9, 18 (1981).

PUBLICATIONS AND CONFERENCE PROCEEDINGS:

"Two-Dimensional Tokamak Density Distribution Measurements Using Phase-Imaging Interferometry," E.J. Doyle, J. Howard, W.A. Peebles and N.C. Luhmann, Jr., Invited Presentation

Figure 7 Schematic of optical system used during multichannel interferometry on TEXT. Note the parabolic mirrors used to produce elliptical cross section beams for the reference and plasma arms of the interferometer.

Figure 8 (a) Schematic of optical coupling used for interferometry on TEXT. This system is easily extended to 20-40 channels.

(b) Necessary modifications to convert system to allow simultaneous Faraday rotation/line density measurements.

Note: The initial hollow profile at start up slowly develops into a 'parabolic' peaked profile during the plateau.

Start-up

Plateau

Fig. 9 Evolution of inverted density profiles on TEXT using the UCLA multichannel interferometer. Note similarity to startup phase on Microtor shown in Fig. 2(a).

Plasma Center

S.B.D. Monitor

Near inversion layer

S.B.D. Monitor

Outside inversion layer

S.B.D. Monitor

Fig. 10 Interferometer output either side of the inversion layer on the TEXT tokamak during sawtooth activity.

Fig. 11 Output from the UCLA multichannel interferometer on TEXT during oscillating gas puff feed. We note that the edge channel exhibits a very different time behaviour to the other channels. This is important in assessing and evaluating particle confinement in the tokamak geometry.

at the 6th Topical Conf. on High Temperature Plasma Diagnostics, South Carolina, March 9-13, 1986.

"Recent Advances in Multichannel Far-Infrared Collective Scattering and Interferometry System," D.L. Brower, J. Howard, W.A. Peebles, S. Kim, R.L. Savage, Jr., N.C. Luhmann, Jr., J. Wagner, D.B. Rutledge, D.P. Neikirk, P.E. Young, H.K. Park, Proc. of 11th Symposium on Fusion Engineering, Austin, TX, (1985).

"Resolving the Propagation Direction of Tokamak Microturbulence via Homodyne Spectroscopy," D.L. Brower, W.A. Peebles, Ch.P. Ritz, E.J. Powers, N.C. Luhmann, Jr., submitted to Rev. Sci. Inst. (1986).

"Determination of the Two-Dimensional Density Distribution in a Tokamak Plasma Using Phase-Imaging Interferometry," E.J. Doyle, J. Howard, W.A. Peebles, N.C. Luhmann, Jr., Accepted for publication in Review of Scientific Instruments, August 1986.

"The Use of Polarization Transforming Reflectors for Far-Infrared and Millimeter Waves," J. Howard, W.A. Peebles, N.C. Luhmann, Jr., accepted for publication in International Journal of Infrared and Millimeter Waves, October 1986.

"The Application of Homodyne Spectroscopy to the Study of Microturbulence in the TEXT Tokamak," D.L. Brower, W.A. Peebles, N.C. Luhmann, Jr., C.P. Ritz and E.J. Powers, 10th International Conference on Infrared and Millimeter Waves, Florida, December 9-13, 1985.

"Polarimetric Phase Imaging for Plasma Current Profile Measurements," J. Howard, W.A. Peebles and N.C. Luhmann, Jr., 10th International Conference on Infrared and Millimeter Waves, Florida, December 9-13, 1985.

"Two Dimensional Phase Imaging on the Microtor Tokamak," J. Howard, E.J. Doyle, J. Wagner, W.A. Peebles, N.C. Luhmann, Jr., D. Rutledge and W. Lamb, 10th International Conference on Infrared and Millimeter Waves, Florida, December 9-13, 1985.

"Phase Imaging on the TEXT Tokamak," S. Kim, W.A. Peebles, R.L. Savage, Jr., D.L. Brower, J. Howard, E.J. Doyle, N.C. Luhmann, Jr., D. Rutledge and W. Lamb, 10th International Conference on Infrared and Millimeter Waves, Florida, December 9-13, 1985.

"Resolving the Propagation Direction of Tokamak Microturbulence via Homodyne Spectroscopy," D.L. Brower, C.P. Ritz, W.A. Peebles, N.C. Luhmann, Jr. and E.J. Powers, 6th Topical Conf. on High Temperature Plasma Diagnostics, South Carolina, March 9-13, 1986.

"Digital Complex Demodulation Applied to Interferometry," E.J. Powers, R.D. Bengtson, D.L.

Brower, D. Choi, G. Joyce, N.C. Luhmann, Jr. and W.A. Peebles, 6th Topical Conf. on High Temperature Plasma Diagnostics, South Carolina, March 9-13, 1986.

Task IIIB

PROGRESS REPORT, FY86

I. IMAGING ARRAYS

Extensive development efforts continued in this area. One of the major focuses has been on the development of short wavelength arrays ($\approx 100\text{-}200\text{ }\mu\text{m}$) for operation on devices such as DIII-D, TFTR and CIT. The major difficulty has been the substrate lens which has been used to eliminate substrate modes. The substrate mode problems arise due to the fact that the substrate has parallel sides. Therefore, radiation incident at angles greater than the critical angle is trapped (see Fig. 1) and creates trapped substrate modes that produce a large amount of crosstalk between detectors as well as decreasing the amount of radiation coupled into each detector. This situation is prevented by curving the substrate on the incident side with a hyperhemispherical quartz lens as illustrated in Fig. 2. This lens, together with the objective lens (see Fig. 3) produces an aplanatic system. This approach has successfully been employed with our imaging efforts on MICROTOR and is also applicable to medium sized devices such as TEXT. However, at the shorter wavelength absorptive losses in the substrate lens become prohibitive.

The solution to the substrate mode problem and the substrate lens absorption problem has been to utilize a silicon etching technique to thin the substrate sufficiently that the modes are eliminated. The approach is illustrated schematically in Fig. 4. The antenna array rests on a membrane of silicon nitride. The membrane is made by chemically etching a hole through a silicon wafer with a silicon-nitride layer on top. The edge does not attack silicon nitride, so that the membrane remains, supported on the edges by the silicon wafer. This approach eliminates the absorption losses of a substrate lens, in addition to the substrate modes. Recently, this approach was successfully tested at frequencies in excess of 500 GHz.

The thin membrane approach has also been accompanied by a new antenna design. Here we now employ a thin-film metal log-periodic antenna on thin silicon nitride membrane (see Fig. 5). Both the measured E and H-plane patterns of this antenna were excellent with extremely wide bandwidth provided by the spokes. In an array the bandwidth can be sacrificed somewhat by employing only a single spoke as illustrated in Fig. 6.

In addition to the microbolometer arrays we have also begun a collaborative program with Groningen University to employ sensitive cooled SIS or Josephson junction arrays as video detectors for ECE imaging. These devices possess measured sensitivities in the millimeter wave region as low as $\approx 2 \times 10^{-16}\text{ W/Hz}^{1/2}$ making them vastly superior to room temperature Schottky diode heterodyne mixers when predetection bandwidths of $\approx 10\text{ GHz}$ are employed.

Fig. 1 Transmitting antenna on a dielectric substrate showing the rays that are trapped as surface waves.

Schematic of Substrate Lens Configuration for the Elimination of Substrate Modes

Fig. 2

Fig. 3 Optical elements used with the imaging detector array. Note the position of the substrate lens. The objective lens and the substrate lens form an aplanatic system.

Schematic of the use of a thin membrane to support planar antennas while eliminating substrate modes.

Fig. 4

Silicon wafer

Silicon-nitride membrane

1 μm thick

100 μm

Silver
antenna

Fig. 5 Log-periodic antenna on a silicon-nitride membrane designed for a frequency-range from 150 GHz to 1500 GHz.

Photograph of microbolometer array using thin silicon nitride membrane to eliminate substrate modes.

Fig. 6

II. α - PARTICLE DISTRIBUTION DETERMINATION

In a proof-of-principle experimental test we investigated the use of FIR scattering as a means of probing the α -particle distribution. Here we are employing the FIR scattering to determine the damping of waves (i.e. lower hybrid, etc) produced by the α -particles. In our proof-of-principle experiment we have studied the damping of ion acoustic waves due to the formation of a hot ion tail produced by the optical mixing of two intense microwave sources separated in frequency by the ion acoustic frequency (see Fig. 7). The major diagnostic is millimeter wave scattering. Here one is familiar with the standard expression for the scattered electric field given by (see Fig. 8)

$$E_s(\theta_s, k_s) \propto \exp \left[-1/2(k_w - 2k_0 \sin(\theta_s/2))^2 a_0^2 \right] \quad (1)$$

where k_w is the density fluctuation wave number, k_0 is the wavenumber of the millimeter wave probe beam, θ_s the scattering angle, and a_0 the probe beam waist in the scattering volume. The Gaussian term is simply the result of wavenumber matching. When the scattering wavenumber $[k_s = 2k_0 \sin(\theta_s/2)]$ matches k_w , this term is a maximum. If k_w changes so that a mismatch occurs, the scattered electric field rolls off as a Gaussian with an e^{-1} width determined by the beam waist a_0 . This we were able to verify at low power levels where the ion tail was negligible and the wave damping small. Now at high power levels we discovered that the angular distribution of the scattered radiation broadens with increasing power. This is illustrated in Fig. 9 where the Gaussian fits to the scattering data have been renormalized to explicitly display the observed broadening. After deconvolving the known (measured) instrument function the amplitude distribution as a function of wavenumber is determined (see Fig. 10). The increase in broadening with increasing input power is obvious in Fig. 11. Now to obtain the ion damping we assume that the broadening is due to damping which related to broadening as shown in Fig. 12. This then allows us to infer the damping (see Fig. 13). From this we can calculate the tail density which is plotted in Fig. 14. Note that good agreement with the energy analyzer data is obtained validating the use of this scattering technique. In the case of a fusion plasma the ion waves would be produced during ICRF heating or by other external wavelaunching techniques.

III. HIGH POWER FAR INFRARED SOURCE DEVELOPMENT

As part of the high power far infrared source development, work on high power CW optically pumped lasers has continued. Through the use of high power CO₂ pump lasers, buffer gases, and control of the FIR gas temperature, FIR output powers in excess of 100mW are available at a number of wavelengths in the 100–500 μ m range. These are summarized in Table I.

Fig. 7 Arrangement for Millimeter Wave Scattering from

Homodyne Scattering with Gaussian Beams

$$E_s \propto \tilde{n} \exp \left[-1/2 (k_w - 2k_0 \sin \theta_s / 2)^2 / k_0^2 \right]$$

Fig. 8 Arrangement for homodyne scattering from plasma waves employing Gaussian beams.

Fig. 9 Gaussian fits renormalized to display the observed broadening.

Fig. 10 Wave amplitude distribution as a function of wavenumber obtained from the data shown in Fig. 16 after the instrument function has been deconvolved.

Figure 11 Dependence of observed wavenumber broadening as a function of input power.

Figure 12 The correlation between the damping of an ion wave and the broadening of the FFT of the ion wave.

Figure 13. The damping of the ion acoustic wave in excess of the phenomenological damping as inferred from the broadening of the scattered wavenumber resolution (Δk).

Figure 14. The ion wave amplitude and ion tail density predicted by the spatial computer code. Scattering data for $\tilde{n}_1$ and n_t is shown in open and closed circles; the ion energy analyzer data for n_t is in closed triangles.

Table I

FAR INFRARED LASER OUTPUT POWERS

$\lambda_{\text{FIR}} (\mu\text{m})$	Output Power (mW)
118	350
185	400
215	150
393	150
432	100
496	100

The wide range of wavelengths available will allow selection of an optimal operating wavelength for diagnostics on TEXT, D-III-D CIT, or other fusion devices.

Rate equation modeling of the 496 μm CH_3F laser was also performed. Although quantitative agreement with experiment was poor, qualitative behavior of the FIR output power as a function of gas temperature and pump power was adequately described. This provided a great deal of insight into the effect of gas temperature and buffer gases on the FIR laser. Vibrational bottlenecking, which is severe in the CH_3F laser, is predicted by the model, as is the relief of the bottleneck by the addition of hexane or SF_6 buffer gas. Using temperature dependent rates given by Lawandy, the output power as a function of temperature is described. Comparisons of the rate equation model and experimental results are shown in Figs 15 and 16.

We have also been concentrating on the development of tunable sources in the 140-400 GHz region. Such a source must obviously be small, relatively inexpensive, require negligible care and service as well as possessing long life. This eliminates all tube sources and mandates the use of solid state technology. Unfortunately, even InP GUNN diode technology is inadequate and IMPATT diodes are noisy, often are on short lived at such frequencies and only marginal in output power.

An often employed solution to provide local oscillator power for a single diode mixer, etc is to employ frequency multipliers which combine a nonlinear element (i.e. a varactor) with a high power lower frequency source to generate harmonics at millimeter and submillimeter wavelengths. In addition to extending the available local oscillator operating frequency range, a frequency multiplier also allows one to take advantage of the more favorable characteristics of low-frequency sources: lower noise, increased tuning range, lower cost, and better reliability. However, the power output of a single diode multiplier is limited by the diode reverse breakdown voltage and heating. To circumvent this difficulty we are developing completely monolithic Schottky diode multiplier grids of sufficient size and efficiency to provide the required large output powers. Such a monolithic, quasi-optical multiplier array will satisfy

Fig. 15. Comparison of rate equation modeling and experimental results for the variation of $496\mu\text{m}$ output power as a function of pump power.

Fig. 16. Comparison of rate equation modeling and experimental results for the variation of 496 μm output power as a function of temperature.

the DOE need for a compact, long-lived, low cost, low noise local oscillator for large arrays and ECE systems as well as a probe source for active imaging.

The basic concept of the multiplier array is illustrated schematically in Fig. 17. Power at the fundamental frequency enters from the left, through a tuner and a filter. The low frequency pump power then impinges upon a monolithic grid of GaAs Schottky diode varactors, (see Figs. 18 and 19) and the nonlinear capacitance of the diodes generates harmonics. The harmonic output power exits on the right through another filter and tuning network. The filters ensure that the power at each frequency propagates in the proper direction. This approach overcomes the power limitations of a single Schottky diode because power is distributed among many diodes. The total power output is essentially limited only by the size of the array that one is willing to build. Since the diodes made as a single monolithic circuit, eventual devices are anticipated to be both low-priced and reliable. This source array together with our detector arrays will insure that sources are available for devices such as CIT.

IV. TWO COLOR INTERFEROMETER

An interferometer intended for operation on DIII-D is being developed. Vibrational compensation is provided by operation at two wavelengths in the infrared. The first leg is generated by a 10.6 μ m CO₂ laser on loan from G.A. Technologies, while a CO₂ laser built at UCLA provides 9.2 μ m radiation. The two beams are divided by a single acousto-optic cell operating at 40 MHz. The advantage of this arrangement is that the two beams have nearly identical optical paths.

Fig. 17 Design of the Quasi-Optical Harmonic Frequency Multiplier Array

Schematic of inductive grid for diodes. This grid adds 105 Ω of inductive reactance at the fundamental (65 GHz), and 210 Ω at the second harmonic.

Fig. 18

Fig. 19 Photograph of Monolithic GaAs Schottky Diode Multiplier Grid

LIST OF RECENT PUBLICATIONS

"Scattering from ECRF Waves," N.C. Luhmann, Jr., W.A. Peebles, T. Lehecka, P. Zimmerman, Proc. of 10th International Conference on Infrared and Millimeter Waves, Florida, IEEE Cat. No. 85CH2204-6, Pg. 148 (1985).

"Twin Frequency FIR Sources for Plasma Diagnostic Applications," N.C. Luhmann, Jr., W.A. Peebles, J. Howard, E. Dworak, R.L. Savage, Jr., T. Lehecka, C. Domier, P. McDonald, 10th International Conference on Infrared and Millimeter Waves, Florida, IEEE Cat. No. 85CH2204-6, Pg. 199 (1985).

Watt-Level Monolithic Quasi-Optical Diode Frequency Multiplier Grid," N.C. Luhmann, Jr., C.F. Jou, W.W. Lam, D.B. Rutledge, 10th International Conference on Infrared and Millimeter Waves, Florida, IEEE Cat. No. 85CH2204-6, Pg. 56 (1985).

"A Dual Frequency 183/380 GHz Receiver for Airborne Applications," N.C. Luhmann, Jr., P.D. Batelaan, M.A. Frerking, T.B.H. Kuiper, H.M. Pickett, M. Schaefer, P. Zimmerman, Proc. of 10th Int. Conf. on Inf. and Millimeter Waves, Florida (1985) pg. 85.

"Development of High Power Far-Infrared Lasers for Fusion Plasma Diagnostics," N.C. Luhmann, Jr., T. Lehecka, R.L. Savage, Jr., W.A. Peebles, 10th International Conference on Infrared and Millimeter Waves, Florida, IEEE Cat. No. 85CH2204-6, Pg. 150 (1985).

"Near-Millimeter Wave Imaging Arrays," N.C. Luhmann, Jr., D.B. Rutledge, C.E. Zah, Proc. of URSI Meeting, Vancouver, Canada (1985).

"High Power, Twin Frequency FIR Lasers for Plasma Diagnostic Applications," N.C. Luhmann, Jr., T. Lehecka, R.L. Savage, Jr., R. Dworak, W.A. Peebles, submitted to Rev. Sci. Inst. (1986).

"ECRH Absorption and Propagation Studies via Collective Thomson Scattering," N.C. Luhmann, Jr., W.A. Peebles, S. Kim, P. Zimmerman, submitted to Rev. Sci. Inst. (1986).

"Diode Grids for Electronic Beam Steering and Frequency Multiplication," W.W. Lam, C.F. Jou, N.C. Luhmann, Jr. and D.B. Rutledge, Int. Jour. of Infrared and Millimeter Waves, 7, 27 (1986).

DEPARTMENT OF ENERGY GRANT NO. DE-FG03-86ER53225, Task VIa

P R O G R E S S R E P O R T

for period of

January 1, 1986 to June 1, 1986

Principal Investigators: Prof. Burton D. Fried
Prof. George J. Morales

Title: "Stability, Transport & Plasma Heating"

During this period several topics of relevance to RF heating, current drive, and transport have been investigated. They include: 1) intrinsic cross-field transport by fast waves used for current drive; 2) effect of plasma density gradients on ion Bernstein mode propagation and antenna coupling; 3) structure of ion Bernstein modes in the presence of poloidal magnetic fields; 4) cut-off models for distribution functions at the plasma edge; and 5) effect of parallel gradients in the confining magnetic field on cyclotron resonance.

Topics 1) and 2) were presented at the 13th European Conference on Controlled Fusion and Plasma Heating held in Schliersee, Germany, April 14-18, and at the Sherwood meeting held in New York, April 14-16, where topic 3) was also reported. These subjects were also discussed at the ICRF theory and technology workshop held in Madison, Wisconsin, May 20-21.

Copies of the Schliersee papers and abstracts of the Sherwood presentations are enclosed.

DEPARTMENT OF ENERGY GRANT NO. DE-FG03-86ER53225, Task VIb

T E C H N I C A L P R O G R E S S R E P O R T

for period of

January 1, 1986 to June 1, 1986

Principal Investigator: Prof. John M. Dawson

Title: "Computer Applications to CTR"

Since the beginning of this grant we have made significant progress on a number of problems. These are summarized below.

I. Code Development and Computing

A. Subtraction Technique for Studying Subtle Plasman Effects

Simulations of plasma have often been limited to studying strong (instabilities, nonlinearity) effects in plasma. We have developed a technique which allows us to see quite weak effects. The method employs a subtraction technique in which the problem is run once in an equilibrium situation and then a second time with a small perturbing influence; the results are subtracted and what is left is the perturbation. We have used this effectively to look at Debye clouds of magnetized plasmas and the plasma response to a driving antenna.

B. Development of a Code with Vlasov Ions and Zero Mass Electrons

We have generalized our earlier particle MHD code with Hall term to a Vlasov ion model with zero mass electrons. The code runs on ion time scales and shows all the richness of the ion dynamics, Alfvén waves, ion cyclotron waves, Whistler waves (well below the electron cyclotron frequency) and ion Bernstein waves. Both two- and three-dimensional versions of the code exist.

C. Discrete Hamiltonian Particle Simulation (with Curtis Menyuk, SAI)

As a candidate for achieving long time steps in particle simulation while still retaining some high frequency physics, we have developed a code using the discrete Hamiltonian to advance the particles. We are presently testing its limitations. Such a code seems most useful where the non-linearities are weak (where usual particle codes are expensive) and only a few modes are important, such as in modeling of gyrotrons.

D. Optimizing Particle Codes

We have managed to vectorize a number of the loops on our particle codes for the MFE Cray machine. In one dimension we have gained a factor of 2 in speed. We are putting these features into multi-dimensional codes and we expect the gains to be even larger there.

E. Benchmarking New Array Processor Machines

Our experience with the CHI machine led us to write codes which can be run with little modification on the large number of new Array Processing machines now coming on the market. We have benchmarked a large number of these and find they typically have a speed of about 1/4 of a Cray I. The cost effectiveness of these machines appears quite good (typical costs are ~\$100K to \$500K).

II. PHYSICS PROBLEMS

A. Studies of Ion Cyclotron Heated Plasmas

We have been investigating parametric instabilities associated with plasma heating in the ion cyclotron wave frequency range. This uses a 2 1/2 D (x, y, v_x, v_y, v_z) electromagnetic model. We have found that the plasma is subjected to a rich variety of decay instabilities (backscatter, forward

scatter, side scatter, decay instabilities involving quasi-modes of the electrons and the ions). One of the most interesting effects is that the decays appear to be able to drive large electron currents. We are looking into the physics behind the current generation as well as instability thresholds and where the energy goes.

B. Radial Diffusion of Plasma Current Due to Electrostatic Wave Emission

We investigated the transport of current by electrostatic waves using a two-dimensional magnetized plasma with electrostatic particle interactions. The current was initially carried by a Maxwellian plus an energetic electron tail in the center of the plasma. The model geometry prevented electron diffusion. Nevertheless, significant current diffusion took place due to the enhanced electrostatic waves which were also observed. Such current transport could be important to current drive.

C. Surface Bernstein Waves

We have extended our studies of surface Bernstein Waves for a bounded plasma with vacuum outside. These extensions include much larger systems where much better results are obtained. Modes of this type could play an important role in RF heating of a plasma.

III. NON-COMPUTATIONAL ACTIVITIES

In addition to our main computational activities, we have looked at a number of interesting fusion problems that have arisen from our contacts with other areas.

A. Positron Production by Fusion Devices and Potential Applications

A $D\cdot^3\text{He}$ fusion reactor can be a profuse producer of positron emitters through P-N reactions involving such things as ^{18}O . These can be

used for fusion reactor diagnostics and also have potential medical and industrial applications.

B. ^3He on Venus and Mercury

Recently Wittenberg, Santarius and Kulcinski¹ have pointed out that samples of Lunar soil brought back by the Apollo astronauts contain significant amounts of ^3He ; the ^3He is embedded in the Lunar soil by the solar wind. Since Venus has no magnetic field the solar wind embeds itself directly in its atmosphere. We have looked at the data² on He in the atmosphere of Venus and find that the atomic fraction of He there is an order of magnitude larger than in the Earth's atmosphere. If the fraction of ^3He to ^4He is the same as in the solar wind then the atomic percent of ^3He is 3000 times larger for Venus than for Earth. This, combined with the denser atmosphere of Venus would imply that Venus contains a very large source of ^3He ($\sim 4 \times 10^{10}$ GWY of energy if burned in a fusion reactor) if it could be extracted. Data from Mercury³ indicates that it intercepts 6×10^{-4} of the He in the solar wind due to its magnetic field. Because of its nearness to the Sun and a size which is twice that of the Moon it will have intercepted 2% of the ^3He which the moon has (assuming present conditions existed over the age of Mercury). If we assume Mercury is as effective at retaining ^3He as the Moon it should also contain significant supplies of ^3He which might be more concentrated in the polar (Auroral) regions.

Attached are abstracts from the 1986 Sherwood Theory meeting, the 1986 Spring Meeting of the American Physical Society, and miscellaneous preprint abstracts.

NONLINEAR PLASMA RESPONSE TO EXTERNALLY APPLIED FIELDS IN PLASMA SIMULATIONS*

H.C. Huang, V.K. Decyk, R.D. Sydora, J.M. Dawson, and I. Jechart

Department of Physics

UCLA

It is generally difficult to observe subtle processes in a simulation plasma, such as those found in the vicinity of mode conversion layers of an inhomogeneous plasma, due to the enhanced thermal fluctuations. We present a method which is designed to observe these effects when external driving currents outside the plasma boundaries are imposed.

The simplest possible system is chosen to demonstrate the procedure--the plasma response to a test charge. For short times the thermal fluctuations are not greatly affected by the presence of the test particle. Therefore, we perform the simulations twice, once with the test charge and once again without it. Subtracting the potentials from the two runs gives the plasma response. The results give excellent agreement with the theoretical expressions for finite-size particle shielding clouds in an unmagnetized plasma.

We extend this procedure to electromagnetic plasma simulation models where driving currents outside the plasma boundaries are imposed and the plasma responds to a spectrum of modes launched by a particular antenna configuration. Simulation runs with and without the external rf are performed and the resultant fields subtracted. The radiation patterns in the presence of the plasma are compared to the vacuum field patterns. Results are presented for oscillating current sheet and Nagoya Type-III antennas.

* Work supported by USDOE.

Abstract submitted for the 1986 Sherwood Theory Conference; April 14-16, 1986;
New York, New York.

MHD MODEL WITH THE HALL TERM*

F. Kazeminejad, J. N. Leboeuf[†], Richard Sydora, John M. Dawson, F. Brunel^{††}
Department of Physics
University of California, Los Angeles

We have been studying MHD models with the inclusion of the Hall term in the Ohm's law for some time now. This method enriches the physics contained in the MHD calculations of the fusion plasmas by predicting many more wave modes, such as magnetoacoustic, Alfvén, ion cyclotron, and whistler waves. In that connection, we developed 2 and 3 dimensional models for studying infinite plasmas and the wave propagations in them. Simulation results were compared with the theoretical dispersion relations for arbitrary angles of propagation and showed excellent agreement. Recently we have generalized the earlier studies to include kinetic ion rather than fluid elements, and were able to observe Bernstein waves. Theoretical dispersion relations for most cases have been developed and show good agreement with the simulation results. These wave studies demonstrate how the model reproduces a wide variety of modes which would not have shown up in simple MHD.

[†] Institute for Fusion Studies, Austin, Texas

^{††} National Research Council of Canada, Ottawa, Canada

*Work supported by USDOE and NSF.

PARAMETRIC PROCESSES IN ION CYCLOTRON HEATED PLASMAS*

R.D. Sydora and J.M. Dawson

Department of Physics

UCLA

In order to study the parametric instabilities and associated plasma heating with rf waves in the ion cyclotron wave frequency range, a series of particle simulations are performed using an optimized 2-1/2 D ($x - y$, $v_x - v_y - v_z$) electromagnetic model. A circularly polarized, non-dipolar ($k_0 \neq 0$) electromagnetic pump wave ($\omega = \omega_{ci}$) is launched into a uniform strongly magnetized plasma. For very large amplitude pump waves ($v_0 \gtrsim 2v_{thi}$) the field-line averaged ion distribution forms a ring in the perpendicular velocity space which is unstable to electrostatic waves. For lower pump wave amplitude, below the threshold for unstable ion distributions, the decay instabilities are observed. The decay of the long wavelength pump into shorter perpendicular wavelength electrostatic ion cyclotron modes¹ ($k_{\perp} \rho_i \gtrsim 0.8$), as well as into transverse electromagnetic ion cyclotron and ion acoustic modes is found². The decay process occurs mainly through nonlinear ion Landau damping. When waves with opposite phase velocities are generated, strong parallel ion cooling accompanies the perpendicular heating. The heating rate versus pump strength, as well as results for two ion species, will be presented.

* Work supported by USDOE.

1. O.P. Sharma, V.K. Tripathi, and C.S. Liu, Phys. Fl. 25, 1589 (1982).
2. Y.C. Lee and P. Kaw, Phys. Fl., 15, 911 (1972).

**RADIAL DIFFUSION OF PLASMA CURRENT DUE TO SECONDARY EMISSION OF
ELECTROSTATIC WAVES BY TAIL ELECTRONS**

V. K. Decyk, G. J. Morales, J. M. Dawson and H. Abe*
University of California, Los Angeles
Department of Physics
Los Angeles, California 90024

*Kyoto University
Kyoto, Japan

As part of an overall program to study RF current drive, a collaborative series of simulations has been undertaken to examine wave-enhanced spatial diffusion of RF generated current profiles. In the work presented here, a 2-1/2 dimensional, electrostatic particle simulation code is used, which is periodic in one dimension and bounded in the other.¹ An initial current channel is set up in the plasma interior, having a square profile in the bounded direction. The current is initially carried by a long tail in the electron velocity distribution along the magnetic field, and containing about 10% of the total electron density.

As time proceeds, the current profile in space widens, and decays temporally. However, there is no particle diffusion in this geometry, because all the drifts (e.g., $E \times B$) are in the ignorable direction. Therefore, this current diffusion can only come from spontaneous wave activity. Indeed, the frequency spectrum shows that waves with parallel phase velocities corresponding to particle velocities in the non-Maxwellian tail of the distribution are enhanced 3 - 4 times above the thermal fluctuation level. These waves propagate out of the initial current channel and can be absorbed by particles in other regions, resulting in a broadening of the current profile.

The current decay is due to electron-ion collisions, which transfer momentum to the ions. (Momentum of the system is conserved to 1 part in 10^7).

The initial "slideaway" velocity distribution inside the original current channel is found to relax to a half-Maxwellian (the velocity distribution with $v < 0$ remains Maxwellian with the original temperature). Outside the original current channel, the initial Maxwellian first develops a long tail, and later relaxes to a half-Maxwellian.

This simulation shows the importance of current diffusion due to spontaneous wave activity since particle diffusion is not occurring.

Work supported by USDOE and JIFT.

¹V. K. Decyk, G. J. Morales and J. M. Dawson, Proc. of the 2nd Joint Grenoble-Varenna International Symposium on Heating in Toroidal Plasmas, Como, Italy, 1980, Vol. 1, p. 365.

A NEW MODE OF ELECTRON SURFACE WAVE ON A VACUUM-PLASMA INTERFACE*

D. Sultana, V.K. Dacyk, and J.M. Dawson

Department of Physics

UCLA

A new form of surface waves is found on a vacuum-plasma interface which is the surface analog of the well-known Bernstein waves. Using 2-D electrostatic particle-code, the propagation of waves in a plasma-slab has been investigated through simulation techniques. An external magnetic field is imposed parallel to the vacuum-plasma interface and perpendicular to the wave-vector. The existence of these waves in the frequency range between the first two cyclotron harmonics is probably a kinetic effect since it is not predicted by fluid theory. The wave number corresponding to these waves is found to be complex and thus the eigenfunctions have both an evanescent and an oscillating part. Unlike Bernstein waves, these waves are damped. This was observed for a rigid particle reflecting boundary as well as for the case of a free boundary with fixed ions and external magnetic field. Moreover, splitting of spectral lines is observed in both cases. Further, a continuous spectrum has been observed in the case of a free boundary.

* work supported by USDOE and NSF.

Abstract Submitted
for the 1986 Spring Meeting of the
American Physical Society
28 April - 1 May 1986

Physics and Astronomy
Classification Scheme
Number 52.70

Suggested title of session
in which paper should be placed
Fusion Plasma

Positron Production by Fusion Devices and Potential Applications.* J.M. DAWSON and P.L. PRITCHETT, UCLA--A fusion reactor burning D-³He is a profuse producer of 14.5 MeV protons. Such protons are efficient producers of positron emitters through p-n reactions (typical cross sections ~200 mb). Even existing devices (TFTR, JET) can produce significant numbers of positron emitters ($\sim 10^{-3}$ of the number of protons) if suitable nuclei (e.g., ¹⁵N) are added to the plasma. The positron emitters can be used to diagnose the fusion plasma. Some examples are: (1) the number produced measures the energetic proton density, (2) the interaction of the positron emitters with the wall can be used as tracers for impurity wall interactions, and (3) the escape of positron emitters can give a measure of diffusion. Perhaps of greater interest is to use the positrons as tagged electrons to diagnose electron behavior such as confinement time and places of escape. An interesting possibility is that of making a PET image of the plasma; the most critical problem to overcome is the radiation environment. Finally, fusion reactors (including DT reactors through n-2n reactions) could be used as a positron factory (production of proton rich nuclei) which could find many applications in science, medicine, and industry.
*Work supported by USDOE.

- () Prefer Poster Session
(x) Prefer Standard Session
() No preference

Signature of APS Member

John M. Dawson
Same name typewritten
Physics Dept. - UCLA
Los Angeles, CA 90024
Address

BENCHMARK TIMINGS WITH PARTICLE PLASMA SIMULATION CODES

PPG-950

Viktor K. Decyk

Department of Physics
University of California, Los Angeles
Los Angeles, CA 90024
USA

ABSTRACT

These series of benchmarks were performed with the plasma particle simulation codes currently used by the plasma physics group at UCLA¹⁻². The purpose of these measurements was to help us evaluate what kind of commercially available computer would be most suited for these types of calculations. The performance on two classes of computers were measured. The first class consisted of those computers which were the ones of interest. These were generally advertised as "Fortran engines" and included the array processors FPS-164 and FPS-264, the multi-processors ELXSI-6400 and ALLIANT FX/8, and the mini-supercomputer Convex C-1, which are available for about half a million dollars. The second class consisted of those computers on which such problems are currently being done, in order to be able to compare the new computers with those that plasma physicists were acquainted with. These included the CDC7600, Cray 1, Cray X-MP, and Cray 2 at NMFEC in Livermore, the IBM 3033, IBM 3090, and CHI-3 at UCLA, the FACOM M-200, VP-100, and VP-200 at IPPJ in Nagoya, Japan, and the ubiquitous VAX.

CRAY-1 ASSEMBLER AND ITS APPLICATION TO VECTORIZING
PARTICLE SIMULATION PROGRAMS

Lingyu Xu

University of California
Department of Physics
Los Angeles, CA 90024

PPG-905

ABSTRACT

Random memory access takes up a large portion of the computer time in plasma particle simulation. Two assembler subroutines (implemented on CRAY-1) which vectorize this task and cut the computer time by almost half are presented.

END

**DATE
FILMED**

12 / 14 / 92