DOE/MC/25048-T8

RECEIVED
ADMINISTRATIVE SERVICES
99 JAN -5 PM 4:35

Collaborative Research on Fluidization
Employing Computer-Aided Particle Tracking

DOE/MC/25048--T8

DE92 017796

Quarterly Progress Report No. 4
For Period July 1 1989-Sept. 30 1989

Contract DE-FC21-88MC25048

by

Michael M. Chen

Department of Mechanical and Industrial Engineering

University of Illinois at Urbana-Champaign

1206 W. Green Street

Urbana, IL 61801

Submitted to

U.S. Department of Energy

Morgantown Energy Technology Center

Collins Ferry Road

Morgantown, WV 26505

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

7/28/92
MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

Introduction

This report covers the fourth quarter of the subject contract. The primary objective of the first year is construction of a portable computer-aided particle tracking apparatus to be used eventually at the Morgantown Energy Technology Center. Third quarter effort was devoted to software development and system interconnection. These efforts continue in this quarter with hardware compatibility problems corrected. The completed hardware interface has enabled us to verify that the detectors, scalers, and discriminators are all working properly. Software debugging is now proceeding. Progress has also been made in the fabrication of the tracer particle to match the bed particles to be used at METC.

Discussions

I. Hardware Interconnections

The difficulty of connecting LeCroy electronics with a Burr-Brown data-acquisition board became apparent in the last quarter (please see previous report for details), and two solutions were outlined. Analysis of the individual data and address lines has led to the conclusion that the LeCroy auxiliary bus is incompatible with the Burr-Brown interface card due to LeCroy's use of several pins on the auxiliary bus as both data and address bits. After many attempts to circumvent this problem, it was decided to use the second solution, the purchase of a LeCroy 8901A CAMAC

crate controller to be used in conjunction with a National Instruments IEEE-488 standard general purpose interface board (GPIB). This will avoid compatibility problems since the standardized GPIB interface is used for both. Instead of connecting individual pins, one cable connects the entire interface. These units have been delivered, installed, and successfully tested.

The GPIB interface provides us with much in the way of system control. The databus is very easily accessed using simple commands. Using commands provided with the software (see part II), we can easily control the LeCroy 4434 scaler, loading buffers, resetting counters, reading data, etc. The LeCroy 4413 discriminator can also be accessed through the GPIB, allowing simplified threshold setting and other necessary functions that would otherwise have to be done manually.

The crate controller has several front panel LEDs that allow the user to see whether commands are correctly executed, and to a small degree the results of those commands. Connection between the controller and the GPIB card within the computer consists of a Amphenol brand 24 pin GPIB cable.

After successfully testing the interface, it is now possible to test the other hardware components assembled thus far. We are happy to report that these -- detectors, scalers, discriminators -- have also been found to work as designed.

II. Software Development

The new interfacing system uses a new set of commands, but the data-acquisition program remains essentially the same. The only changes will be made in the interrupt routine where data is actually transferred. The subroutine is called by a clock generated interrupt after a fixed counting period. Since we are no longer using the Burr-Brown board and its on board pacer clock, it is necessary to program the computer's own clock for this interrupt. Initialization of the GPIB interface requires six (6) commands. The 'IBFIND' command sets the access codes for the GPIB board and its device, the CAMAC 8901A crate controller. The 'IBPAD' command sets the primary addresses for the GPIB and the 8901A. The 'IBSIC' and 'IBCAC' commands set up the GPIB card as the controller in charge. Now the system is ready to take data.

The process of taking data is done by loading the LeCroy 4434 scaler's control register. This register contains information about which channels are to be read and in what order. It also controls the loading of data into buffers and the clearing and resetting of the counter channels. This register is loaded by using the 'IBCMD' command to set up the GPIB as the "talker" and the 8901A as the "listener". Then the 'IBWRT' command is used to write the commands to the 8901A needed to set the control register. After every command written to the 8901A, the 8901A must be set as a "talker" to execute the CAMAC cycle. At this setting, a data byte can be read which gives the status of the command, i.e. is it executable? did it run?

Once the command register has been set up, the transfer mode must be set. This is done in much the same way, by setting the "listener" and "talker" and writing the command, then reversing roles and reading the status byte. The transfer mode determines the size of the words to be read, either 8, 16, or 24 bits.

The final process is within a loop which is executed once for each channel read. The read command is sent to the 8901A using 'IBWRT' with the 8901A as listener. Then the GPIB board is made the listener and the 8901A the talker. The final count of the present channel is read from the LeCroy 4434 scaler's buffer into the software buffer, and later onto the disk as data.

This routine is used in both calibration and data-taking programs in the exact same format. The GPIB standard makes reading and writing to and from the LeCroy modules very easy and extremely efficient. Using an interface program provided with the program, commands may be entered one at a time to see how the system will work during an actual run. With this program we have taken actual data from the system corresponding to photon counts. The actual software is complete but will require extensive debugging and testing. These efforts are in progress at this time.

III. Tracer Particle Development

Fabrication of a tracer particle matching the size and weight of the 1/8th inch nylon particles to be used at METC is in progress. The method selected involves drilling a hole in the

particle and placing a small quantity of scandium metal inside. The hole will then filled, either with epoxy or with melted nylon. As of the time of this writing, a 1 mm through hole has been successfully drilled in a particle, verifying the feasibility of the method. However, since we are awaiting the delivery of a new supply of scandium, scandium installation and sealing has not yet been accomplished. As soon as the particle is completed, it will be shipped to METC, in preparation for activation in a nuclear reactor.

END

**DATE
FILMED**

9 / 3 / 92