MASTER

UCRL-85480
PREPRINT

CONF-810523-1

**MICROPROCESSOR-CONTROLLED DATA-ACQUISITION INSTRUMENT
FOR NEUTRON-ACTIVATION MEASUREMENTS**

Bobby A. Jones

This Paper was Prepared for Submittal to
Topical Conference on Computerized Data
Acquisition in Particle & Nuclear Physics
Oak Ridge, Tennessee May 28-30, 1981

Lawrence
Livermore
Laboratory

This is a preprint of a paper intended for publication in a journal or proceedings. Since changes may be made before publication, this preprint is made available with the understanding that it will not be cited or reproduced without the permission of the author.

DISCLAIMER

Microprocessor-Controlled Data-
Acquisition Instrument for Neutron-Activation
Measurements, Bobby A. Jones, Lawrence Livermore
National Laboratory--This paper describes a
microprocessor controlled data acquisition
instrument designed at Lawrence Livermore
National Laboratory to provide experimenters with
a diagnostic tool for measuring the performance
of laser imploded fusion targets via neutron
activation techniques.

This instrument features the ability to count
four independent inputs simultaneously while
providing a front panel readout of these inputs,
plus a time of day clock. A hardcopy printout of
the data is also provided by a built-in thermal
printer. All running modes and parameters are
user selectable via a front panel keypad, and a
complete set of internal self-testing diagnostics
are available for debug.

Submitted by:
Bobby A. Jones
Lawrence Livermore National Laboratory
P.O. Box 5508 L-473
Livermore, California 94550
(415) 422-0829
Submitted for POSTER SESSION

*This work was performed under the auspices of the U.S. Department of
Energy by Lawrence Livermore Laboratory under contract No. W-7405-Eng-48.

In the laser fusion research program at Lawrence Livermore National laboratory we routinely expose deuterium-tritium filled micro-spheres to a short (less than 1 ns) high power laser pulse. To measure the target shells' areal density we have developed a new density diagnostic^(1,2) based on neutron activation of selected materials in these targets. We use the aluminum-28 formed in the target by the bombardment of silicon-28 with 14.1 MeV neutrons from the D-T reaction. Our system collects a known fraction of the aluminum-28 formed and rapidly (15 secs) transports it (via a rabbit) to a shielded detector assembly where its radioactive decay is measured in a beta-gamma coincidence counting system (see fig. 1). The counts from this detector assembly are amplified and conditioned by standard Ortec nims modules and then connected to a micro-processor controlled data acquisition instrument³. This unit is based on an Intel 8-bit microprocessor. The circuit design for this instrument relies extensively on the family of Intel support devices that provide input-output, counter-timers and memory functions (fig.2).

This instrument is capable of handling four independent detector inputs simultaneously including an anti-coincidence input for background reduction. Also provided is a built in real-time clock to facilitate the recording of shot time and to record the time of arrival of the sample to the detector assembly. This time is critical since the aluminum-28 we are measuring is short lived (2-min half-life).

A local readout is available on the front panel to allow the operator to monitor the counts in real-time. A hardcopy printout (via a built-in thermal printer) of the data can also optionally be obtained. Some

limited computational ability is provided to compute and record averages of the input counts.

The operator may optionally select a Run Number, the Sample Rate and the Sample Interval for an experiment and arm the unit from the front panel key pad. Once the unit is armed it waits for a zero-time signal at shot time via a fiber optic trigger. A built in real time clock records shot time.

The operator then manually loads the collection sample into the detector assembly and initiates counting from the key pad. When the system is activated it records the sample loading time (time interval between the shot and the commencement of counting) turns on the high voltage to the detector assembly, and starts counting. The accumulated number of counts for each input is both displayed on the front panel and recorded on a built-in thermal printer.

Some special features were incorporated into this unit at design time to facilitate initial debug and for future diagnosis of possible circuit problems.

DiagnostiCS reside in memory to check out the printer, keyboard, display, ram memory, internal counters and the remote EIA interface. When under normal operation when the unit is not being debugged, the internal firmware is continually encoding a 16 bit, proprietary, check character on the internally stored firmware and comparing this check character to a previously computed check character which was stored when the unit was initially built. If the two check characters do not match an error code is reported to the operator via the front panel.

Optionally this instrument can be connected to a remote computer for both control and data retrieval.

This unit is now an integral part of a much larger data acquisition and analysis system under development here.

References:

1. Stephen M. Lane et al., Appl. Phys. Lett. 37(7)600
2. Laser Program Annual Report-1978, Lawrence Livermore Laboratory
Livermore, Calif., UCRL-50021-78(1979)
3. Bobby A. Jones, Rad Chem Data Acquisition Chassis Users Manual,
Lawrence Livermore Laboratory Livermore, Calif., UCID-18570,
Jan. 24, 1980

DISCLAIMER

This document was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor the University of California nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial products, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government thereof, and shall not be used for advertising or product endorsement purposes.

Fig. 1 Block diagram of neutron-activation counting system.

Fig. 2 Block diagram of microprocessor controlled data acquisition instrument.