G. D. Alton and J. W. McConnell
Oak Ridge National Laboratory
Oak Ridge, Tennessee 37831, USA

CONF-870498--7

DE87 008802

The emittances of high-intensity ion beams extracted from cesium sputter negative ion sources equipped with cylindrical and ellipsoidal solid tungsten and spiral-wound tantalum (General Ionex Corporation, Model 860) cesium surface ionizers have been measured for several ion species, including $^{12}\text{C}^-$, $^{28}\text{Si}^-$, $^{58}\text{Ni}^-$, and $^{197}\text{Au}^-$. While certain sets of data from the ellipsoidal and cylindrical geometry ionizer sources suggest a moderate growth in emittance with increasing negative ion beam intensity I over the range of intensities investigated ($5 < I < 60 \mu\text{A}$) of perhaps 20%, not all data exhibit this dependence, especially those from the Model 860 source. As well, no evidence of an emittance dependence on ion mass of a monotonic nature was found. The emittances of ion beams at the 80% intensity level from the Model 860 source are found to be higher on the average by factors of 1.8 and 1.7, respectively, than those from sources equipped with ellipsoidal and cylindrical geometry cesium surface ionizers.

Brief descriptions of the emittance-measuring device and the sources investigated will be given. Emittance and brightness data for dc operation of each of the sources considered are presented and comparisons made of the results.

*Research sponsored by the Division of Basic Energy Sciences, U.S. Department of Energy, under contract DE-AC05-84OR21400 with Martin Marietta Energy Systems, Inc.

The submitted manuscript has been authored by a contractor of the U.S. Government under contract No. DE-AC05-84OR21400. Accordingly, the U.S. Government retains a nonexclusive royalty-free license to publish or reproduce the published form of this contribution, or allow others to do so, for U.S. Government purposes.

MASTER

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

1.0 Introduction

The quality of a particle beam is usually measured in terms the emittance ϵ and brightness B of the beam. These quantities are figures of merit which are frequently used to determine the compatibility of beams with a given beam transport system and to predict their behavior in a particular ion optical system. These qualities are related to each other through the ion beam intensity I and are direct consequences of Liouville's theorem. This fundamental theorem postulates that the motion of a group of particles under the action of conservative force fields is such that the local number density in the six-dimensional phase space (x, y, z, p_x, p_y, p_z) (hypervolume) everywhere remains constant. An ion beam can be represented by a group of points, all of which lie within the six-dimensional hypervolume. The phase space volume of an ion beam may increase due to interactions with residual gas particles and/or gas and foil strippers, beam transport and acceleration system aberrational effects, and space charge effects, but can never be less than its value immediately following extraction from the source. Thus, the magnitude of the phase space volume or quantity proportional to the phase space volume (emittance) measured immediately following extraction is a unique characteristic of the particular ion source.

The technology for producing high-intensity negative ion beams with improved beam qualities from sources based on the sputter principle¹ has advanced significantly during the past few years. A number of single-aperture sputter-type sources have been reported in the

literature,²⁻⁸ including two of those utilized in the present studies⁶⁻⁸ (the source equipped with a solid tungsten ellipsoidal geometry ionizer has not been reported previously). In such sources, the sample material is mounted on a negatively biased probe which is maintained at a potential difference with respect to the housing of 1-5 kV negative in a controlled flux of a neutral Group IA element, usually cesium, which effects a lowering of the work function and enhances the probability for negative ion formation during the sputter ejection process.^{1,9} Sputtering of the sample material is effected by bombardment with positive Group IA element ions which are formed by direct surface ionization during collisions with a hot, high-work-function ionizer or by electron impact ionization. Negative ion sources, based on the sputter principle, thus all share in common the influences of the intrinsic energy and angular distribution characteristics of the sputter process on the emittance of extracted ion beams.¹⁰

Still other factors influence the qualities of beams extracted from such sources, such as the optics of the positive ion/sputter probe region of the source, the size and shape of the sputter erosion crater formed during sample bombardment, the spacing of the sputter probe in relation to the ion exit aperture, and the ion exit aperture size. The positive ion current density distribution at the sample surface, which defines the negative ion generation region, is determined by the ionizer geometry and potential distribution within the ionizer/sputter probe region of the source.

Due to the rather high negative ion current capabilities of state-of-the-art negative ion sources based on the sputter principle, such as those used in the present investigations, the question of whether space-charge influences the emittances of ion beams extracted from such sources is often raised. In addition, the long-standing question of the presence or lack thereof of a mass effect remains. We attempt to shed light on these issues by measuring the emittances of dc ion beams over a range of negative ion currents for several negative ion species. The studies were conducted with two of the high-intensity negative ion sources developed at the Oak Ridge National Laboratory^{7,8} and a commercially available version¹¹ of the source described in Ref. 6. Studies of the emittances of beams from other types of negative ion sources and descriptions of other emittance measuring devices have been previously reported.^{2,12,13,14}

2.0 Definitions

Perhaps the most important attribute of an ion beam is that it have properties compatible with the beam transport system that it must pass through. The quality of an ion beam in this regard is usually expressed in terms of the emittance ϵ and brightness B . Both are related through the ion current I and are direct consequences of Liouville's theorem. The acceptance A for a beam transport system is the complement of the emittance ϵ and thus must be greater than ϵ to ensure beam transport through the system.

2.1 Emittance

If the transverse components of motion of a group of particles are

mutually independent in configuration space (i.e., neglecting space charge and spin-dependent interactions), the motion of the particles in the orthogonal planes (x, P_x) , (y, P_y) , and (z, P_z) will be uncoupled and therefore can be treated separately. For uncoupled motion in which a beam is moving along the z direction under the action of conservative forces, the four-dimensional hyperarea (x, P_x, y, P_y) or transverse phase space is a conserved quantity, according to Liouville's theorem.

For the case where P_z is constant, the transverse momenta P_x, P_y can be replaced by corresponding angular components, since

$$\frac{P_x}{P_z} = \tan \theta_x \approx \frac{dx}{dz} = x' \quad (1)$$

and

$$\frac{P_y}{P_z} = \tan \theta_y \approx \frac{dy}{dz} = y' \quad (2)$$

in the small-angle approximation. The respective transverse phase space areas then are proportional to the areas (x, x') and (y, y') .

To account for changes in the axial momentum P_z of an ion beam, the concept of normalized emittance is often used. We define the orthogonal normalized emittances as

$$\epsilon_{nx} = \pi x x' \sqrt{E} \quad (3)$$

and

$$\epsilon_{ny} = \pi y y' \sqrt{E}, \quad (4)$$

where E is the energy of the ion beam. The units of emittance are often given in terms of π mm mrad (MeV)^{1/2}.

We define the two-dimensional normalized emittance as the square root of the product of the normalized emittances associated with the (x, x') and (y, y') areas, or $\epsilon_n = (\epsilon_{nx}\epsilon_{ny})^{1/2}$.

2.2 Brightness

Another figure of merit often used for evaluating the quality of ion beams is the brightness B . Brightness is defined in terms of the ion current dI per unit area dS per unit solid angle $d\Omega$ or

$$B = \frac{dI}{dS d\Omega} . \quad (5)$$

According to Walsh,¹⁵ brightness can be related to the normalized emittance of the ion beam through the following expression:

$$B = \frac{2I}{\epsilon_{nx}\epsilon_{ny}} = \frac{2I}{(\epsilon_n)^2} . \quad (6)$$

3.0 Emittance Measurement Facility

Emittance measurements of the ion beams extracted from the subject sources were determined by use of the equipment and procedures described in the following parts of this section. The sources were mounted on a test stand equipped with capabilities for accelerating negative ion beams up to energies of 30 keV with energies of 20 keV typical of all measurements. The facility, shown in Fig. 1, consists of a negative ion source, a conventional three-cylinder einzel lens, a double-focusing magnet, the emittance-measuring device, beam line component valves, turbomolecular pumping stations, and auxiliary power supplies required for system operation. Negative ion beams are extracted from the source and focused by means of the einzel lens onto the object plane of the magnet. Ions of the desired mass are then

deflected through 90° and focused at the image position of the system. The intensity of the negative ion beam can be monitored prior to and following momentum analysis by insertion of remotely actuatable Faraday cups; the Faraday cups are located immediately behind variable slit-type apertures which are positioned at the object and image planes of the momentum analysis system. With the Faraday cups removed, the beam can be focused downstream onto the slit detector unit of the emittance-measurement device and determinations made of the emittances and brightnesses of dc or pulsed negative ion beams. (During the present measurements, the emittance detector unit was located $\sim .3$ m behind the focal plane of the system when operated in the symmetric object/image distance mode.) Emittance measurements were effected automatically through the use of the microcomputer CAMAC-based data acquisition and hardware control system described below.

3.1 The Emittance-Measuring Apparatus

The emittance-measurement device consists of a vacuum housing, two identical stepping motor-driven detector units for determining the emittances of an ion beam in either the x or y directions, and a control unit for driving the detector hardware.¹⁶ The control unit consists of an IBM personal computer¹⁷ (PC) which is interfaced to a Transiac model 6001 CAMAC-crate controller,¹⁸ an input/output register; a stepping motor controller, and a 12-bit analog-to-digital converter (ADC). The CAMAC-crate control modules communicate with the emittance-measurement hardware via an external electronics unit. The

electronics unit consists of a relay unit for x,y direction selection, fast switches for stepping motor brake control, a current-to-voltage converter for processing detector current signals, current range logic circuitry, current integrators, and an analog multiplexer.

The ion beam diagnostic unit, shown in Fig. 2, consists of an electrically isolated slit aperture, positioned 0.4 m in front of a detector unit which is made up of 32 electrically isolated plates. The current striking each of the detectors is used to determine the differential angular divergence of the ion beamlet which is allowed to pass through the slit aperture at a given x or y position.

An emittance measurement consists of stepping the slit-detector system through an ion beam in a chosen direction while monitoring the total ion current striking the slit unit and the differential ion currents striking each of the 32 detectors during a menu selectable integration time period. For dc ion beams, the number of samples which are taken at a given position may also be selected. By averaging several measurements, the effect of beam fluctuations can be reduced. For pulsed mode operation, the integration time is fixed. A menu selectable choice of the number of pulses over which the data is averaged for a given position is available. The position at which data are accumulated is determined by the voltage signal from a precision linear potentiometer. The ion currents from the slit unit and each of the 32 detection plates are converted to voltage signals and, along with the position voltage signals for each of 50 positions, are digitized and stored as a file on hard disk. The data set can be

called from file for data analysis. A complete set of x or y data, including background data, can be acquired and stored in memory in less than five minutes. An additional 20 minutes is required to process the data and extract emittance values. Modifications to the control program and electronics unit permit measurement of emittances of negative ion beams extracted from negative ion sources operated in pulsed mode.

3.2 The emittance hardware control and data acquisition electronics.

The block diagram of the electronics used for both dc and pulsed negative ion beam emittance measurements is shown in Fig. 3.

For pulsed beam emittance measurements, it was necessary to modify both the control program and the electronics used to drive the IBM-PC/CAMAC-based emittance-measuring device in order to increase the signal to background and, therefore, to minimize contributions to the detector signal by the dc beam and time-varying background effects. The electronics were modified by addition of a digital gate and timing module to the CAMAC crate which is used under software control to trigger the high-voltage pulse generator by means of a fiber optic link and to gate the current integrator electronics on during the pulse arrival time of the negative ion beam. The gate and timing module also permit multiple sampling of dc beams. For pulsed mode operation, a time window of 200 μ s is symmetrically spaced around the 100- μ s negative ion beam pulse in order to reduce background effects due to the companion dc beam component and thereby increase the signal-to-noise ratio.

3.3 Data analysis

A menu-selectable option permits a three-dimensional monitor display of the xx' or yy' versus intensity data set prior to data storage or analysis for both dc and pulsed measurements. After visual inspection, if the data set is worthy of keeping, it is first of all subjected to point-by-point background subtraction by use of a background data file taken immediately after the beam measurement. For dc background measurements, the background data set is taken without beam but with the same integration time and number of samples used during the actual beam-on measurement. For pulsed-mode measurements, the dc component of the beam required to maximize pulsed negative ion beam intensities is used as an integral part of the background data set. In order to reduce the effects of pulse-to-pulse fluctuations in beam intensity due to the high-voltage pulse generator, an average over a menu-selectable number of beam pulses (typically 20) is made for data collected at each position of the emittance detector unit. A symmetrically spaced time window of 200 μ s in width, placed about the pulsed beam is used to eliminate unwanted contributions to the background and thereby increase the signal-to-noise ratio. The pulsed-beam data-accumulation measurement is immediately followed by a background measurement with the high voltage triggered at zero voltage; only the dc beam component is present during the background measurement. The relevant beam on and background data sets are then subtracted and stored on disk for further analysis. In order to compensate for variations in beam intensity during a particular measurement, the data set is then normalized by multiplying each of the 32

detector channel readings by the ratio of the maximum slit current reading to the slit current reading at each of 50 positions. The data set is then ready for extraction of emittance information. By selecting the appropriate option, emittance contours are calculated and automatically plotted. The contour levels are determined by performing a Simpson's rule integration over the xx' or yy' versus intensity data set. Contour levels which contain 10-80% of the total beam are calculated iteratively in increments of 10% to an accuracy of 0.1%. The contour level information is then passed to a topographical graphics program which produces contour plots from the data. The area within a particular contour is just the emittance for that particular beam fraction.

4.0 Negative Ion Source Descriptions

The negative ion sources utilized in the present studies are shown schematically in Figs. 4, 5, and 6. With the exception of the ellipsoidal ionizer geometry source, which will be the subject of a future report, (Fig. 4), the other sources have been described in detail in the literature,^{6,7,8} and therefore only a brief reiteration of their principles of operation will be given here. The sources differ only in the details of construction, geometries of the positive and negative ion generation regions, and the material type and geometries of the ionizers. These sources all utilize identical principles for both positive and negative ion formation. Table 1 lists the spatial positions of the samples in relation to the ion extraction aperture, aperture sizes, and estimated emittances based on simple geometrical

arguments for each of these sources. As we shall see, the estimated emittances shown in Table 1 agree reasonably well with those measured for the 80% contour levels from the sources.

4.1 The ellipsoidal and cylindrical geometry ionizer sources.

These sources, designed and developed at the Oak Ridge National Laboratory, are equipped with solid tungsten ionizers and share in common the same mechanical design features; in these sources, the ionizer/sputter probe electrode geometry and the consequent potential distribution determines the current density characteristics of the cesium ion beam at impact with the sample surface, which in turn determines an area from which negative ions are extracted. Computational simulation techniques were utilized in designing the ionizer/sputter probe regions of these sources. The observed sample wear patterns agree almost in detail with those computationally predicted. For standard geometry operation, the sample is placed at the focal point of the positive cesium ion beam; the positive ion current density distribution on the sample surface determines the region of negative ion generation, which, in conjunction with the aperture size, the aperture position from the sample surface, and characteristics of the sputter process, essentially determines the emittance of extracted ion beams. Therefore, the characteristics of the positive ion distribution at impact with the sample are very important in determining the emittances of a particular source as would be expected.

Table 1. Estimated emittances of negative ion sources equipped with ellipsoidal and cylindrical geometry cesium ionizers and the Model 860 negative ion source

Source	Sample Distance to Aperture	Ion Exit Aperture Diameter	Assumed Sample Wear Pattern Diameter	Ion Emission Half Angle	Estimated Emittance
	$l(\text{mm})$	$\phi(\text{mm})$	$s(\text{mm})$	$\alpha(\text{mrad})$	$\epsilon(\frac{\pi \text{mm}}{\text{mrad}} (\text{MeV})^{1/2})$
Ellipsoidal Geometry Ionizer	29.7	4.76	1.25	101	9.06
Cylindrical Geometry Ionizer	23.0	4.76	1.0	124	8.72
Model 860	14.3	6.36	1.0	257	17.8

The ellipsoidal geometry cesium ionizer has a high perveance for cesium ion beam formation. The size and shape of the observed wear patterns, as well as those computationally predicted for the source equipped with an ellipsoidal geometry ionizer (Fig. 4) are very sensitive to sample position because of the strongly convergent nature of the electrode system. The wear pattern at the focal point of the electrode system has a diameter of $\varnothing \approx 1.25$ mm. If, for example, the probe is too close or too far removed from the focal point, an annular wear pattern results. The source is routinely placed at the focal position during normal source operation.

The observed wear pattern from the cylindrical geometry ionizer source^{7,8} (Fig. 5) is composed of two parts: a region of concentrated wear with full diameter of ~ 0.75 mm, and a low-density uniform wear region with a diameter of ~ 4.5 mm.

4.2 The Model 860 Source

The sample wear patterns from the Model 860 source (Fig. 6) were found to be considerably more complex than those of the other sources. Computational studies were not made for this source. Typically, the central region of the sample was found to be strongly worn with a wear diameter of $\varnothing = \sim 1$ mm; the concentrated wear pattern was characteristically surrounded by a large diameter ($\varnothing \approx 8$ mm) asymmetrically worn halo. The asymmetrical wear pattern within the halo region is attributable to the spiral character of the tantalum ionizer.

5.0 Emittance and Brightness Determinations

The previously described equipment and procedures were used in determining the emittances of dc ion beams extracted from sources equipped with ellipsoidal and cylindrical solid tungsten cesium surface ionizers and from the Model 860 negative ion source. Emittance measurements were made for negative ion beams of a variety of species ($^{12}\text{C}^-$, $^{28}\text{Si}^-$, $^{58}\text{Ni}^-$, and $^{197}\text{Au}^-$) over a range of ion beam intensities $5 < I < 60 \mu\text{A}$ in an effort to investigate the dependence of emittance on ion mass and beam intensity. Due to the large amount of data accumulated, it will not be possible to show all of the results of these studies. Therefore, only a selected number of examples, representative of all accumulated data, will be presented in this report.

5.1 Emittance Data

5.1.1 The ellipsoidal geometry ionizer source. Emittance versus percentage negative ion beam intensity data for various negative ion beams of $^{12}\text{C}^-$, $^{28}\text{Si}^-$, $^{58}\text{Ni}^-$, and $^{197}\text{Au}^-$ extracted from the ellipsoidal geometry ionizer source (Fig. 4) are displayed in Figs. 7, 8, 9, and 10. These data suggest a moderate increase in the emittance for the 80% contour level with increasing ion beam intensity of perhaps 20% over an intensity range $5 < I < 50 \mu\text{A}$. These findings are in contrast to the rather large increases in emittance with ion beam intensity found by Doucas, Hyder, and Knox for ion beams extracted from the cone geometry source.¹² However, for other data sets, not shown, the effect, if it exists, is obscured by statistical fluctuations. No evidence of a dependence of emittance on ion mass of a monotonic

nature was found. These findings, thus, support those made earlier by Doucas, Hyder, and Knox.¹² The emittances for the 80% contour levels from $^{12}\text{C}^-$ and $^{28}\text{Si}^-$ are found to be lower than those from $^{58}\text{Ni}^-$ and $^{197}\text{Au}^-$ ion beams by $\sim 18\%$. This finding for Si^- is consistent with earlier emittance measurements of beams extracted from sources equipped with spherical and cylindrical geometry ionizers which were performed prior to mass analysis.¹⁹

5.1.2 Cylindrical geometry ionizer source. Emittance data for $^{12}\text{C}^-$, $^{28}\text{Si}^-$, and $^{58}\text{Ni}^-$ ion beams extracted from the source equipped with a cylindrical geometry cesium ionizer (Fig. 5) are displayed in Figs. 11, 12, and 13. These data also show the presence of a moderate increase in emittance with increasing ion beam intensity over the range of intensities investigated ($20 < I < 50 \mu\text{A}$). For example, the effect is seen to be $\sim 9\%$ for $^{12}\text{C}^-$ at the 80% contour level over an intensity range of $20 < I < 40 \mu\text{A}$ while an increase of $\sim 20\%$ occurs over an intensity range of $20 < I < 50 \mu\text{A}$ for $^{58}\text{Ni}^-$. A similar increase was also noted for $^{197}\text{Au}^-$ data (not shown) over an intensity range $20 < I < 50 \mu\text{A}$. (It should be pointed out that changes in the emittance $\Delta\epsilon$ due to space charge effects in negative ion beams of the same energy should be mass M dependent, i.e., $\Delta\epsilon \propto \sqrt{M}$.) However, the increase may, in fact, be attributable to changes in the size of the cesium beam at impact with the sample surface, in which case, the overall effect would be independent of negative ion species but would change with cesium ion energy. The probe voltages used during these measurements were those required to maintain the

desired negative ion beam intensity. The data from this source also exhibit no evidence of emittance dependence on mass. The results from the present measurements for this source geometry which were made with momentum analysis are in close agreement with previous measurements performed without momentum analysis.¹⁹

5.1.3 The Model 860 source. Emittance data similar to those shown previously for the ellipsoidal and cylindrical geometry ionizer sources are displayed in Figs. 14, 15, and 16 for $^{12}\text{C}^-$, $^{28}\text{Si}^-$, and $^{58}\text{Ni}^-$ ion beams extracted from the Model 860 source (Fig. 6). These data exhibit no evidence of significant intensity or mass dependence.

5.2. Comparative Average Emittance and Brightness Data.

If we ignore the presence of intensity or mass dependent effects and perform a weighted average of all emittance contour data regardless of intensity and ion species, we obtain the average emittance versus percentage average negative ion beam intensity data shown in Fig. 17. The emittance for a given contour of a beam extracted from the Model 860 source is observed to be considerably higher than that for the same contour associated with beams extracted from the ellipsoidal or cylindrical ionizer geometry negative ion sources. For example, the emittances for the 80% contour level of the Model 860 source are factors of 1.8 and 1.7 higher, respectively, than those for the same contour from sources equipped with ellipsoidal and cylindrical geometry cesium ionizers. These average data are representative and typical of all values derived from measurements associated with a particular ion species and ion beam intensity. Without exception, the

ellipsoidal and cylindrical geometry sources exhibit emittances nominally lower by the values shown in Fig. 17.

It is interesting to note that the emittance values for the 80% contours for the three sources agree closely with the estimations based on simple geometrical arguments made in Table 1; i.e., the full width of the high density portion of the cesium ion beam at impact with the probe surface and the angular divergence limitations imposed by the exit aperture of the particular ion source.

Fig. 18 displays weighted average brightness B versus percentage average negative ion beam intensity for the three subject sources. The accepted average emittance data (discussed above) was used in conjunction with the average ion beam intensity to compute the brightness B . At the 10% contour level, the ellipsoidal geometry source has an average brightness of ~ 5.4 times and at the 80% level an average brightness of ~ 3.5 times that of the Model 860 source. On the other hand, the cylindrical geometry ionizer source has a brightness at the 10% contour level of ~ 4.3 times and at the 80% level ~ 3 times that of the Model 860 source. Of the sources, the ellipsoidal ionizer geometry source has the lower emittance on average and consequently the highest brightness. This source is brighter than the cylindrical ionizer geometry source at the 10% and 80% contour levels by factors of ~ 1.2 .

6.0 Summary and Conclusions

An automated emittance measurement facility has been designed, fabricated, and utilized in the determination of emittances of state-of-the-art negative ion sources based on the sputter principle.

Specifically, the emittances of a variety of negative ion beams ($^{12}\text{C}^-$, $^{28}\text{Si}^-$, $^{58}\text{Ni}^-$, and $^{197}\text{Au}^-$) have been measured for a range of negative ion beam intensities ($5 < I < 60 \mu\text{A}$) extracted from sources equipped with ellipsoidal and cylindrical solid tungsten cesium ionizers and from the commercially available Model 860 negative ion source. The principle motivation for the measurements was to investigate the presence or lack thereof of an emittance dependence on ion beam intensity and mass over a range of ion beam intensities and masses commensurate with tandem accelerator applications.

While certain data, particularly from the ellipsoidal and cylindrical geometry ionizer sources, suggest a moderate increase in emittance with ion beam intensity (perhaps 20% for $5 < I < 60 \mu\text{A}$), the data from the Model 860 source show no evidence, in general, of an emittance increase over a comparable range of negative ion beam intensities. These findings support those made previously for beams extracted from sources equipped with spherical and cylindrical geometry cesium ionizers.¹⁹ Many, however, are in contrast to the rather large increases in emittances with increasing ion beam intensity found by Doucas, Hyder, and Knox for beams extracted from the cone geometry source.¹² This effect may, in fact, depend on the particular ion source. The ellipsoidal geometry ion source is highly convergent and therefore increases in positive ion beam current may enlarge the size of the positive ion beam at impact with the sample surface through space charge effects and thereby the area from which negative ions are generated. On the other hand, the beam generation

region in the Model 860 source is already large, even at low positive beam intensities ($\emptyset = 8$ mm) and perhaps insensitive to further changes in positive beam size due to space charge effects. For the ellipsoidal and cylindrical geometry sources, a number of data suggest the effect to be of the order of 20% for beam intensities $5 < I < 60 \mu\text{A}$. Still other data show no intensity effect, thus the results of these measurements are not clearly definitive. These measurements do not reveal evidence of an emittance dependence on ion mass; similar findings were made previously by Doucas, Hyder, and Knox.¹²

On the average, the emittances of ion beams from the Model 860 source at the 80% contour level are larger by factors of 1.8 and 1.7, respectively, than ion beams extracted from sources equipped with ellipsoidal and cylindrical geometry cesium surface ionizers. These differences are clearly associated with the geometries of the respective ion sources in terms of the positions of the sample in relation to the ionizer (anode) and to the ion exit aperture, the size and shape of the negative ion generation region of the source, as well as the size of the ion exit aperture. If the size of the negative ion generation region is known from computer simulation studies or by observation of sample wear patterns, this information, coupled with the distance to the ion exit aperture and aperture size, can be used to accurately estimate the full emittance of a particular source as evidenced by the close agreement of the values shown in Table 1 with those measured from the subject sources.

The analogous brightnesses of ion beams extracted from the ellipsoidal geometry ionizer source are found to be on the average 5.4 times at the 10% contour level and 3.5 times at the 80% level than those from the Model 860 source at the same contours while those extracted from the source equipped with a cylindrical geometry ionizer are found to be ~ 4.3 times at the 10% contour and ~ 3 times those of the Model 860 source at the 80% contour level. According to all emittance and brightness measurements, the ellipsoidal geometry source is consistently substantially better than the Model 860 source and slightly better than the source equipped with a cylindrical geometry ionizer when these sources are operated in their standard geometries.

ACKNOWLEDGEMENTS

The authors are indebted to Ms. Jeanette McBride for skillful typing of the manuscript and to Mr. Gerald Mills for assistance with the emittance facility and negative ion sources.

REFERENCES

1. V. E. Krohn, Jr., Appl. Phys. 33 (1962) 3523.
2. H. H. Andersen and P. Tykesson, IEEE Trans. Nucl. Sci. NS-22 (1975) 1632; P. Tykesson, H. H. Anderson, and J. Heinemeier, IEEE Trans. Nucl. Sci., NS-23, No. 2 (1976) 1104.
3. G. D. Alton and G. C. Blazey, Nucl. Instr. and Meth. 166 (1979) 105; G. D. Alton, R. M. Beckers, and J. W. Johnson, *ibid*, 148.
4. G. T. Caskey, R. A. Douglas, H. T. Richards, and H. V. Smith, Jr., Nucl. Instr. and Meth. 157 (1978) 1.
5. G. D. Alton, IEEE Trans. Nucl. Sci. NS-26 (3) (1979) 3708.

6. R. Middleton, Nucl. Instr. and Meth. 214 (1982) 139.
7. G. D. Alton, Nucl. Instr. and Meth. A244 (1986) 133.
8. G. D. Alton and G. D. Mills, IEEE Trans. Nucl. Sci. NS-32 (5) (1985) 1822.
9. G. D. Alton, Surf. Sci. 175 (1986) 226.
10. R. Behrisch, ed. 1981 Sputtering by Particle Bombardment, Vol. 47 (New York: Springer).
11. The General Ionex Corporation, Newburyport, MA.
12. G. Doucas and H. R. Mck. Hyder, Nucl. Instr. and Meth. 119 (1974) 413; G. Doucas, H. R. Mck. Hyder, and A. B. Knox, Nucl. Instr. and Meth. 124 (1975) 11.
13. J. H. Billen, Rev. Sci. Instrum. 46 (1975) 33.
14. P. W. Allison, J. B. Sherman, and D. B. Holtkamp, IEEE Trans. Nucl. Sci. No-30 (4) (1983) 2204.
15. T. R. Walsh, J. Nucl. Energy, Pt.C. 4 (1962) 53; T. R. Walsh, J. Nucl. Energy, Pt.C. 5 (1963) 17.
16. Nukleartechnik, Gelnhausen-Hailer, West Germany.
17. International Business Machine Corporation, Boca Raton, FL.
18. Transiac, Inc., Mountain View, CA.
19. G. D. Alton, J. W. McConnell, S. Tajima, and G. J. Nelson, to be published in Nucl. Instr. and Meth.

Figure Captions

1. Schematic representation of the emittance measurement facility.
2. Schematic drawing of the emittance measurement detector unit.
3. Block diagram for the emittance measurement hardware control and data acquisition system electronics.
4. Schematic drawing of the ion formation and extraction region of the negative ion source equipped with a solid tungsten ellipsoidal geometry cesium ionizer.
5. Schematic drawing of the ion formation and extraction region of the negative ion source equipped with a solid tungsten cylindrical geometry cesium ionizer.
6. Schematic drawing of the ion formation and extraction region of the Model 860 negative ion source.
7. Emittance ϵ versus percentage of negative ion beam for various negative ion beam intensities of $^{12}\text{C}^-$ extracted from the source equipped with an ellipsoidal geometry ionizer.
8. Emittance ϵ versus percentage of negative ion beam for various negative ion beam intensities of $^{28}\text{Si}^-$ extracted from the source equipped with an ellipsoidal geometry ionizer.
9. Emittance ϵ versus percentage of negative ion beam for various negative ion beam intensities of $^{58}\text{Ni}^-$ extracted from the source equipped with an ellipsoidal geometry ionizer.
10. Emittance ϵ versus percentage of negative ion beam for various negative ion beam intensities of $^{197}\text{Au}^-$ extracted from the source equipped with an ellipsoidal geometry ionizer.
11. Emittance ϵ versus percentage negative ion beam for various beam intensities of $^{12}\text{C}^-$ extracted from the source equipped with a cylindrical geometry cesium ionizer.
12. Emittance ϵ versus percentage negative ion beam for various beam intensities of $^{28}\text{Si}^-$ extracted from the source equipped with a cylindrical geometry cesium ionizer.
13. Emittance ϵ versus percentage negative ion beam for various beam intensities of $^{58}\text{Ni}^-$ extracted from the source equipped with a cylindrical geometry cesium ionizer.

14. Emittance ϵ versus percentage negative ion beam for various beam intensities of $^{12}\text{C}^-$ extracted from the Model 860 ion source.
15. Emittance ϵ versus percentage negative ion beam for various beam intensities of $^{28}\text{Si}^-$ extracted from the Model 860 ion source.
16. Emittance ϵ versus percentage negative ion beam for various beam intensities of $^{58}\text{Ni}^-$ extracted from the Model 860 ion source.
17. Weighted average emittance ϵ versus percentage average negative ion beam intensity for beams extracted from sources equipped with ellipsoidal and cylindrical geometry cesium ionizers and the Model 860 negative ion source.
18. Weighted average brightness B versus percentage average negative ion beam for beams extracted from sources equipped with ellipsoidal and cylindrical geometry cesium ionizers and the Model 860 negative ion source.

Figure 1

Figure 2

Figure 3

Figure 4

Figure 5

Figure 6

Figure 8

Figure 9

Figure 10

Figure 11

Figure 12

Figure 13

*A PRODUCT OF GENERAL IONEX CORPORATION

^{*}A PRODUCT OF GENERAL IONEX CORPORATION

Figure 15

Figure 16

⁺A PRODUCT OF GENERAL IONEX CORPORATION

Figure 17

*A PRODUCT OF GENERAL IONEX CORPORATION

*A PRODUCT OF GENERAL IONEX CORPORATION