Distribution Category:
Magnetic Fusion Energy Systems
(UC-424)

ANL/FPP/TM-273

ARGONNE NATIONAL LABORATORY
9700 South Cass Avenue
Argonne, Illinois 60439-4801

**RADIOACTIVITY COMPUTATION OF
STEADY-STATE AND PULSED FUSION REACTORS
OPERATION**

by

Hosny Attaya

Fusion Power Program/Technology Development Division

November 1994

Work supported by
Office of Fusion Energy
U.S. Department of Energy

The submitted manuscript has been authored
by a contractor of the U. S. Government
under contract No. W-31-109-Eng-38.
Accordingly, the U. S. Government retains a
nonexclusive, royalty-free license to publish
or reproduce the published form of this
contribution, or allow others to do so, for
U. S. Government purpose.

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

GF

 

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, make any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

TABLE OF CONTENTS

	<u>Page</u>
ABSTRACT	1
1 Introduction	1
2 The Transmutation System of Equations	2
3 Methods of Solutions	4
3.1 Linear Chain Method	4
3.2 Ordinary Differential Equation Methods	5
3.3 Series Methods	5
4 Matrix Decomposition Methods	5
4.1 Eigenvector Decomposition	6
4.2 Schür Decomposition	6
4.3 Matrix Decomposition Algorithm	7
4.4 The Padé Approximation	8
5 Triangular Systems	8
6 Pulsed Operation	10
7 An Example Problem	11
8 Conclusions	13
Acknowledgment	13
References	16

List of Figures

	<u>Page</u>
1 The transmutation matrix of the ^{50}Cr problem	12

List of Tables

	<u>Page</u>
1 Solution Comparison- Transmutation of ^{50}Cr after one year of continuous operation	14
2 Transmutation of ^{50}Cr after 10000 pulses	15

RADIOACTIVITY COMPUTATION OF STEADY-STATE AND PULSED FUSION REACTORS OPERATION

Hosny Attaya

ABSTRACT

Different mathematical methods are used to calculate the nuclear transmutation in steady-state and pulsed neutron irradiation. These methods are the Schür decomposition, the eigenvector decomposition, and the Padé approximation of the matrix exponential function. In the case of the linear decay chain approximation, a simple algorithm is used to evaluate the transition matrices.

1. Introduction

The International Thermonuclear Reactor (ITER) is expected to operate in a pulsed operational mode. Accurate radioactivity calculations, that take into account this mode of operation, are required in order to determine precisely the different safety aspects of ITER. We previously examined analytically the effect of pulsed operation in ITER and showed how it depends on the burn time, the dwell time, and the half-lives[1]. That analysis showed also that for ITER's low duty factor, using the continuous operation assumption would considerably overestimate the radioactivities, for a wide range of half-lives.

At the same time, the large improvements in the quality and the quantity (number of isotopes) of the decay and the cross-section data libraries[2] has considerably increased the computation times of the radioactivity calculations. For both reasons it is imperative to seek different methods of solution that reduce the computational time and can be easily adopted to the treatment of the pulsed operation.

In this work, we have developed algorithms based on several mathematical methods that were chosen based on their generality, reliability, stability, accuracy, and efficiency. These methods are the matrix Schür decomposition, the eigenvector de-

composition, and the Padé approximation for the matrix exponential functions. In Section 2, the characteristics of the transmutation system of equation are discussed. Section 3 presents a brief review of the currently used methods. In Section 4, the new methods are presented. A new method for solving linear chains is introduced in Section 5. The pulsed operation is discussed in Section 6. In Section 7, a simple problem is used to demonstrate the results of the different methods in the steady-state operation. The same problem is used to show the results of the pulsed operation algorithm which is based on the matrix decomposition methods.

2. The Transmutation System of Equations

The radioactivity inventory in a nuclear reactor is described by a set of simultaneous first-order linear differential equations. These equations can be written in a matrix notation as:

$$\dot{y} = Ay = (\phi C + D)y, \quad (1)$$

where

y = the concentration vector of all the nuclides involved,

ϕ = the position-averaged and energy-averaged neutron flux,

C = the microscopic cross-section matrix whose off-diagonal elements $c_{ij} = \sigma_{ij}$ are the spectrum-averaged microscopic cross-sections of the nuclide j forming nuclide i . The diagonal elements, $c_{ii} = -\sigma_i^t$, are the negative of the total destruction microscopic cross-section of the nuclide i ,

D = the decay matrix whose diagonal elements, d_{ii} , are the negative of the decay constant of the nuclides, and the off-diagonal elements, d_{ij} is the partial decay constant of the j^{th} nuclide decaying to the i^{th} nuclide,

$A = \phi C + D$ during operation, and $A = D$ during shutdown.

The elements of C and D are constants. The neutron flux may, however, change with time. In fission reactors the radioactive inventory is primarily due to the production of the fission products and thus depends strongly on the fuel burn-up that

in turn changes the neutron flux. In fusion reactors, the neutron flux is due to the external plasma neutron source. As the materials interact with neutrons, the isotopes inventory changes. Such change could, in theory, alter the neutron spectrum. However, this change in the neutron spectrum, for all practical purposes, is small and can be neglected. As a result, the coefficients in Eq. 1 are considered constants.

The i^{th} row in Eq. 1 represents the rate of change of the i^{th} nuclide due to its destruction and the transmutations of the other nuclides to it. The off-diagonal elements of the j^{th} column in the matrix A are the different transmutations of the j^{th} nuclide to the other nuclides. Since a_{jj} is the negative of the total destruction cross-section, the summation of each column must equal zero, i.e. $\sum_i a_{ij} = 0$. Apart from the fission reaction, this condition implies the conservation of the total number of nuclides in the transmutation reactions. Accordingly, the sum of the concentration vector y at any time must equal the sum of the initial concentration vector, i.e. $\sum y_i(t) = \sum y_i(t_0)$.

The decay matrix D is a triangular matrix, but the cross-section matrix C is, in general, not triangular. This is due to reactions such as $(n, 2n)$ that lead to feedback loops. Therefore, the diagonal elements of A are not generally identical to the eigenvalues of A .

The solution of Eq. 1 is given by[3]:

$$y(t) = \exp((t - t_0)A)y(t_0) = R(t, t_0)y(t_0), \quad (2)$$

where $y(t_0)$ is the initial concentration vector, and matrix $R \equiv \exp(tA)$ is called the **resolvent** or the **transition matrix**. The function $\exp(tA)$ can be formally defined by the convergent power series:

$$\exp(tA) = I + tA + \frac{t^2 A^2}{2!} + \cdots = \sum_{i=0}^{\infty} \frac{t^i A^i}{i!}, \quad (3)$$

where I is the identity matrix.

3. Methods of Solutions

The solution of Eq. 1 can be found with many different methods. For a review of many of these methods, the reader is referred to the article by Moler and Van Loan[4]. In this section, we first review briefly historical and popular methods that have been used in the transmutation calculations. Then, in the next sections, we describe the matrix decomposition methods, the Padé approximation method, and a special method for lower triangular transmutation matrices.

3.1. Linear Chain Method

When Rutherford[8] established the possibility of the spontaneous transmutation of elements about a century ago, he deduced mathematically the solutions of the densities of the atoms involved in a successive radioactive-decay series. Rutherford considered limited cases in which there are only two products in addition to the primary substance. Bateman[9] introduced a more generalized mathematical method that can treat unlimited number of consecutive products.

The applicability of Bateman's method is confined to naturally occurring or artificially produced radioactive substances with linear successive transmutations ($A.B.C...$). The linearity, in this context, means a unique path from nuclide to nuclide with no feedbacks from daughters to parents. The linearity breaks down when the nuclides in the chain are subjected to nuclear reactions e.g. neutron reactions. In this case, different paths can lead to the same isotope with possible feedback (loops) from the products to their parents (e.g. $A(n, \gamma)B(n, 2n)A$; or $A(n, p)B(\beta^-)A$) or grandparents (e.g. $A(n, \gamma)B(n, d)C(\beta^-)A$). The system of differential equations then becomes highly coupled. This is indeed the case in fission and particularly in fusion reactors, where the high energy neutrons are capable of producing many loops.

In order to use the linear chain method to calculate the transmutations in a nuclear reactor, approximations have to be made. One may either neglect the loops altogether[10], or deal with only isolated first order loops[11], or ignore many nuclides and introduce fictitious chains and fictitious nuclides to decouple the differential equations[12]. These approximations can be justified for particular problems or chains, but can not be generalized.

3.2. Ordinary Differential Equation Methods

Another approach for calculating the nuclear transmutation is the direct numerical integration of the radioactivity differential equations using an ordinary differential equation solver. The transmutation system of equations is an extremely stiff system with time constants that vary from fractions of a second to thousands of years. This requires the use of specialized methods such as the backward differentiation formulas (BDF) used in the well-tested GEAR package[13] which has automatic step size control.

Such methods, however, are designed for general nonlinear differential equations and thus do not take advantage of the linearity and the constant coefficient nature of Eq. 1. Nonetheless, these methods provide more accurate accounting of the transmutations than the linear chain method. The radioactivity code RACC[5] uses the GEAR method. Another version of RACC[6] makes use of the LSODES solver[7] which is based also on the BDF method but designed for sparse systems.

3.3. Series Methods

The power series definition of $\exp(tA)$, Eq. 3, is the basis of these methods. Direct calculation of the series expansion is inefficient and unsatisfactory. However, using the identity

$$e^A = (e^{A/m})^m, \quad (4)$$

can improve the efficiency and the accuracy of these methods[14]. This is done by scaling the matrix by m , which is taken as a power of two, $m = 2^k$, such that $\|A\|/m \leq 1$. The series is calculated for the scaled matrix and the result is then squared repeatedly. This scaling and squaring technique has been used in the ORIGEN code[15] to calculate Eq. 3.

4. Matrix Decomposition Methods

The matrix decomposition methods are based on the transformation of a matrix to a form that can be easily used. Generally this takes the form:

$$A = SBS^{-1}. \quad (5)$$

Since $SS^{-1} = I$, any power i of A can be written as

$$A^i = SB^iS^{-1}. \quad (6)$$

Using this in the above power series definition of e^{tA} , Eq. 3, we find:

$$e^{tA} = Se^{tB}S^{-1}. \quad (7)$$

The closer B is to diagonal form, with invertible and well-conditioned S , the easier is the evaluation of e^{tB} .

4.1. Eigenvector Decomposition

If A is an $n \times n$ matrix that has n independent eigenvectors $[v_1 | \dots | v_n] = V$ with corresponding eigenvalues $\lambda_1, \dots, \lambda_n$, then S and B can be set to V , and Λ , respectively. Where $\Lambda = \text{diag}(\lambda_1, \dots, \lambda_n)$. Then:

$$e^{tA} = V \text{diag}(e^{t\lambda_1}, \dots, e^{t\lambda_n}) V^{-1}. \quad (8)$$

The difficulties in this approach are that A does not always have a full set of independent eigenvectors and V , even if it is invertible, can behave very badly[16]. Another problem that has been encountered is that A can sometimes have complex eigenvalues thus forcing the costly use of complex arithmetic in Eq. 8.

4.2. Schür Decomposition

For any real matrix A , there exists an orthogonal matrix Q (the Schür vectors of A), and a block upper triangular matrix T (the Schür form of A) such that:

$$Q^T A Q = \begin{bmatrix} T_{11} & T_{12} & \cdots & T_{1n} \\ 0 & T_{22} & \cdots & T_{2n} \\ \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & \cdots & T_{nn} \end{bmatrix}, \quad (9)$$

where each T_{ii} is either a 1-by-1 block matrix or 2-by-2 matrix having complex conjugate eigenvalues. This means that $A = QTQ^T$, and substituting this equation in Eq. 3, we get

$$e^{tA} = Qe^{tT}Q^T. \quad (10)$$

This requires the evaluation of the exponential of a triangular matrix.

Using the properties of triangular matrices, Parlett[17] showed that for any analytic function Φ of a block upper triangular matrix T , $\Phi(T) \equiv F$, is a also block upper triangular matrix with the same block structure as T and commutes with T , i.e.

$$FT = TF. \quad (11)$$

The diagonal blocks of F can be obtained from $F_{ii} = \Phi(T_{ii})$ and the upper diagonal blocks $i < j$ may be computed one diagonal at a time, moving out from the main diagonal, from the recursive relation:

$$T_{ii}F_{ij} - F_{ij}T_{jj} = \sum_{k=0}^{j-i+1} (F_{i,i+k}T_{i+k,j} - T_{i,j-k}F_{j-k,j}), \quad i < j. \quad (12)$$

If the transmutation matrix A has only real eigenvalues, T and F will have only 1x1 blocks, i.e. simple triangular matrices, and the computation of F is straightforward. If A possesses some complex eigenvalues, the F_{ij} blocks may be 1x1, 2x1, 1x2, or 2x2, depending on the structure of T . The 2x2 case requires the solution of four linear algebraic equations. The case of confluent eigenvalues requires special treatment[18] that uses the derivatives of the function Φ .

4.3. Matrix Decomposition Algorithm

The algorithm uses different routines from the mathematical library LAPACK[20]. The transmutation matrix is balanced and reduced to the Hessenberg matrix H , which is zero below the first subdiagonal, giving $A = GHG^T$, where G is orthogonal. The Hessenberg matrix is then reduced to the Schür form T as $H = STS^T$, where S is the Schür vectors of H . Thus, $A = GST(GS)^T$ and GS equals Q in Eq. 9.

At this point, all the eigenvalues of A are known (the diagonal of T). If required and if the eigenvalues are all real, the eigenvectors, may be computed and Eq. 8 is used to compute the resolvent. Otherwise, Eqs. 12 and 10 are used. In either case, most of the computation time is spent in the decomposition stage and is independent of the time t . Only at the last stage, the time t is used to compute e^{tT} (or $e^{t\Lambda}$). This makes these methods more valuable and amenable to the treatments of pulsed operation in terms of computational time saving as is discussed shortly.

4.4. The Padé Approximation

In this work, the Padé approximation of the matrix exponential may be used to compute the exponential of the 2x2 diagonal blocks in Eq. 9, or may be used to calculate the resolvent e^{tA} directly. In both cases, the method proved to be efficient and reliable. The p^{th} diagonal Padé approximation of e^A is giving by:

$$N_p^{-1}(-A) N_p(A),$$

where

$$N_p(A) = \sum_{k=0}^p c_k A^k, \quad c_k = \frac{(2p-k)!p!}{(2p)!k!(p-k)!}.$$

Ward[21] developed an algorithm that balances the matrix and makes use of the scaling and squaring technique (Eq. 4) to compute the exponential of an arbitrary matrix using the above equation. In addition, the algorithm provides an estimate of the accuracy of the results. We have used Ward's algorithm and a modified version written by Van Loan[22] that provides more control on the degree of the approximation (p) and the accuracy.

5. Triangular Systems

Naturally, if the transmutation matrix has a special shape, one can exploit such shape in order to reduce the computation time. As described above, during shutdown and in the linear chain method, the transmutation matrices are triangular having their eigenvalues on the diagonal. One can then make use of Eq. 12 directly to evaluate the resolvents. In fact, this equation is an elegant form of the Bateman equations that

allows for the simultaneous solution of the system of equations, even with multiple paths to the same nuclide, without the need of the artificial break of the system as in the linear chain method.

Rewriting Eq. 12 for a lower triangular matrix, we have:

$$f_{ij} = \frac{1}{t_{ii} - t_{jj}} [t_{ij}(f_{ii} - f_{jj}) + \sum_{k=j+1}^{i-1} (f_{ik}t_{kj} - t_{ik}f_{kj})], \quad i > j. \quad (13)$$

Consider for example the following transmutation matrix and the corresponding resolvent for the following linear chain

$$T = \begin{matrix} & \begin{matrix} y_1 & y_2 & y_3 \end{matrix} \\ \begin{matrix} y_1 \\ y_2 \\ y_3 \end{matrix} & \begin{pmatrix} -d_1 & 0 & 0 \\ d_{12} & -d_2 & 0 \\ d_{13} & d_2 & -d_3 \end{pmatrix} \end{matrix}, \quad F = e^{tT} = \begin{matrix} & \begin{matrix} y_1 & y_2 & y_3 \end{matrix} \\ \begin{matrix} y_1 \\ y_2 \\ y_3 \end{matrix} & \begin{pmatrix} f_{11} & 0 & 0 \\ f_{21} & f_{22} & 0 \\ f_{31} & f_{32} & f_{33} \end{pmatrix} \end{matrix},$$

truncated for only three isotopes. The diagonal elements f_{ii} are $f_{11} = e^{-td_1}$, $f_{22} = e^{-td_2}$, and $f_{33} = e^{-td_3}$. The off-diagonal elements can then be found recursively, one subdiagonal after another, using Eq.13 as:

$$\begin{aligned} f_{21} &= \frac{t_{21}}{t_{22} - t_{11}} (f_{22} - f_{11}) = \frac{d_{12}}{d_1 - d_2} (e^{-td_2} - e^{-td_1}), \\ f_{32} &= \frac{t_{32}}{t_{33} - t_{22}} (f_{33} - f_{22}) = \frac{d_2}{d_2 - d_3} (e^{-td_3} - e^{-td_2}), \\ f_{31} &= \frac{1}{t_{33} - t_{11}} [t_{31}(f_{33} - f_{11}) + f_{32}t_{21} - t_{32}f_{21}] \\ &= \frac{1}{d_1 - d_3} [d_{13}(e^{-td_3} - e^{-td_1}) + \frac{d_{12}d_2}{d_2 - d_3} (e^{-td_3} - e^{-td_2}) - \frac{d_2d_{12}}{d_1 - d_2} (e^{-td_2} - e^{-td_1})]. \end{aligned}$$

The same procedure can be used to evaluate the power of the triangular matrix, say R^m , with the diagonal elements $f_{ii} = r_{ii}^m$.

6. Pulsed Operation

For a few number of pulses, the nuclear transmutations can be computed by any of the methods described above by solving the transmutation equations for each pulse and shutdown periods. For a large number of periodic sequences of pulses, one can save a significant amount of computing time by taking advantage of the regularity in the pulse sequence. This can be done if the solutions are obtained in terms of the resolvents of the different periods. As seen in Eq. 2, the resolvent is constant for the same transmutation matrix and the same time difference.

For a uniform sequence of pulses, suppose that $R_p(t_p)$ is the resolvent during the pulse time t_p , and $R_d(t_d)$ is the resolvent during the decay time t_d between pulses. Using Eq. 2 the solution at the end of t_d is

$$y(t_d + t_p) = R_d R_p y(0) \equiv R_c y(0), \quad (14)$$

where R_c is the resolvent for one cycle of a pulse and a decay period. If this cycle is repeated m times, the solution at the end of the m^{th} pulse is

$$y(mt_p + (m - 1)t_d) = R_p R_c^{m-1} y(0). \quad (15)$$

This requires at most $2[\log_2(m)]$ matrix multiplications[23].

Depending on the size of the matrix n and the number of pulses m , computing cost could be reduced by decomposing R_c itself using the matrix decomposition methods discussed above. Using the eigenvector decomposition

$$R_c^{m-1} = V \text{diag}(\lambda_1^{m-1} \dots \lambda_n^{m-1}) V^{-1}, \quad (16)$$

where V and $\lambda_1 \dots \lambda_n$ are the eigenvectors and the eigenvalues of R_c , and using the Schür decomposition

$$R_c^{m-1} = Q T^{m-1} Q^T, \quad (17)$$

where Q and T are the Schür vectors and form of R_c . The same matrix decomposition algorithm described above is used with the function $\Phi(x) = x^m$.

For triangular transmutation systems, R_p and R_d , are triangular and Eq. 13 can then be used to evaluate the powers of the resolvent of the cycle R_c , which is also triangular. Thus, the decomposition stage including the calculation of the eigenvalues of the triangular matrices[24] is totally unnecessary.

7. An Example Problem

The above algorithms described above have been coded for the CRAY computers which have 64-bit word and 47-bit mantissa. We demonstrate the results of the different methods for a problem used to compare different transmutation codes[25] utilizing reduced cross-section and decay data libraries and a specified neutron flux. The problem is the evaluation of the transmutation of ^{50}Cr after one year of irradiation. The initial atomic concentration of ^{50}Cr is set to 10. The transmutation matrix, with the reaction modes, is shown in Fig. 1.

Notice that the submatrix of the Cr isotopes is triangular and the analytical solutions of these isotopes can be found using Eq. 13. Table 1 shows this analytical solution, the results of the different methods, the deviations from the initial concentration giving in particles per million, and the CPU times in milli seconds. The results of the Cr isotopes from the different methods are shown as the percentage differences from the analytical solutions. For the other isotopes, the results are given in absolute values.

For the Cr isotopes, the solutions of the matrix decomposition methods are the closest to the analytical solutions. The differences from the analytical solutions of these methods are orders of magnitude less than the other methods. The Schür method is the most accurate method. There is considerable reduction in the CPU times by using the decomposition methods and the Padé method. The LSODES method has the largest CPU time. However, this could be balanced, to some extent, by the fact that this method requires the minimum memory. It should be noted that the CPU time depends on the size of the matrix and the saving in computing time

$$10^{-13} \begin{matrix} & {}^{50}\text{Cr} & {}^{51}\text{Cr}^* & {}^{52}\text{Cr} & {}^{53}\text{Cr} & {}^{54}\text{Cr} & {}^{49}\text{V}^* & {}^{50}\text{V} & {}^{51}\text{V} & {}^{48}\text{Ti} & {}^{49}\text{Ti} \\ \begin{matrix} {}^{50}\text{Cr} \\ {}^{51}\text{Cr}^* \\ {}^{52}\text{Cr} \\ {}^{53}\text{Cr} \\ {}^{54}\text{Cr} \\ {}^{49}\text{V}^* \\ {}^{50}\text{V} \\ {}^{51}\text{V} \\ {}^{48}\text{Ti} \\ {}^{49}\text{Ti} \end{matrix} & \left(\begin{array}{cccccccccc} \frac{-2921}{\sigma 1} & & & & \vdots & & & & & & \\ \frac{495.9}{n,\gamma} & \frac{-2898000}{\sigma 2 + \lambda} & & & \vdots & & & & & & \\ & \frac{914.8}{n,\gamma} & \frac{-649.6}{\sigma 3} & & \vdots & & & & & & \\ & & \frac{191.8}{n,\gamma} & \frac{-548.3}{\sigma 4} & \vdots & & & & & & \\ & \dots & \dots & \dots & \frac{546}{n,\gamma} & 0 & & & & & \\ & \frac{1197}{n,np} & & & & & \frac{-244600}{\sigma 6 + \epsilon} & \frac{2442}{n,2n} & & & \\ & \frac{1227}{n,p} & \frac{138.5}{n,np} & \frac{.1178}{n,t} & & & \frac{434.5}{n,\gamma} & \frac{-8846}{\sigma 7} & \frac{2004}{n,2n} & & \\ & & \frac{2897000}{\epsilon + n,p} & \frac{314}{n,d} & \frac{2.321}{n,t} & & & \frac{5525}{n,\gamma} & \frac{-2007}{\sigma 8} & & \\ & & \frac{307}{n,\alpha} & & & & \frac{429.4}{n,np} & \frac{.1161}{n,nd} & & \frac{-321.8}{\sigma 9} & \frac{2667}{n,2n} \\ & & \frac{.006628}{n,{}^3\text{He}} & \frac{143.7}{n,\alpha} & & & \frac{243700}{\epsilon} & \frac{197.3}{n,np} & \frac{2.917}{n,t} & \frac{321.8}{n,\gamma} & \frac{-2667}{\sigma 10} \end{array} \right) \end{matrix}$$

Figure 1: The transmutation matrix of the ${}^{50}\text{Cr}$ problem.

could be greater for larger problems by using the decomposition methods.

Consider now the same problem for pulsed operation. To reach the same fluence used in the continuous irradiation calculations above, we assume 10000 pulses with a pulse width and a dwell time of 3156 and 2000 seconds, respectively. Table 2 shows the results, using the eigenvector decomposition, at the end of the first pulse, at the end of the first decay period, and at the end of the 10000th pulse. The computing time was only 31 ms. This is remarkably orders of magnitude less than that for the backward differentiation formulas (BDF) methods which can be estimated from Table~1 as at least $10000 \times 2 \times 13 = 260000$ ms.

8. Conclusions

We have demonstrated the use of different mathematical methods for solving the transmutation system of equations in steady-state and pulsed operation fusion reactors. Considerable accuracy and efficiency can be achieved by using the matrix decomposition methods. A simple recursive relation has been developed to calculate the resolvents in triangular transmutation systems (linear chain methods). The results for a simple problem show the accuracy and the efficiency of the different methods, and the saving in computing times by using the matrix decomposition methods in pulsed operation.

Acknowledgment

The author is indebted to Dr. X. Sun of the Mathematical and Computer Science Division at Argonne National Laboratory and Dr. A. Tsao of the Supercomputing Research Center at Maryland for helpful and fruitful discussions during the course of this work. The author likes to thank Dr. J. Brooks of the Fusion Power Program at ANL for reviewing this paper.

Table 1: Solution Comparison- Transmutation of ^{50}Cr after one year of continuous operation^a

Isotope	Analytical	Schür	Eigenvector
^{50}Cr	9.90824823398	0.0 %	0.0 %
$^{51}\text{Cr}^*$	1.69666077856E-03	-1.77085549354E-10 %	-1.77085549354E-10 %
^{52}Cr	4.37693012077E-06	-1.13945844595E-10 %	-1.13945844595E-10 %
^{53}Cr	1.19872826563E-09	4.17120502630E-09 %	-2.26072577552E-07 %
^{54}Cr	6.29810678824E-13	-7.19772138009E-07 %	8.83054064462E-04 %
$^{49}\text{V}^*$	NA	2.63103404748E-02	2.63103404748E-02
^{50}V	NA	3.80864589509E-02	3.80864589509E-02
^{51}V	NA	1.41676438411E-02	1.41676438410E-02
^{48}Ti	NA	5.54928385814E-05	5.54928383281E-05
^{49}Ti	NA	1.13900571692E-02	1.13900571714E-02
Error-ppm ^b	0.0	-4.07338371247	-4.07338350783
CPU(ms)	~ 0	4	5

Isotope	Padé	GEAR	LSODES
^{50}Cr	0.0 %	0.0 %	0.0 %
$^{51}\text{Cr}^*$	6.30849143866E-05 %	-5.19315949417E-05 %	-4.94088313428E-07 %
^{52}Cr	-7.71967986919E-06 %	6.35502480098E-06 %	5.99739090522E-08 %
^{53}Cr	1.01357411537E-06 %	-2.39086670990E-06 %	-7.43287647805E-07 %
^{54}Cr	1.59468124902E-03 %	1.59707117337E-03 %	1.59571711576E-03 %
$^{49}\text{V}^*$	2.63103404748E-02	2.63103404719E-02	2.63103404678E-02
^{50}V	3.80864589516E-02	3.80864589504E-02	3.80864589502E-02
^{51}V	1.41676427705E-02	1.41676447224E-02	1.41676438497E-02
^{48}Ti	5.54928394367E-05	5.54928396125E-05	5.54928396451E-05
^{49}Ti	1.13900571682E-02	1.13900571712E-02	1.13900571751E-02
Error-ppm ^b	-4.07338370678	-4.07338372383	-4.07338367268
CPU(ms)	3	13	55

(a) Values in % are $(y_{\text{meth}} - y_{\text{anal}})/y_{\text{anal}} * 100$.

(b) Error= $10^6(\sum y_i(t) - \sum y_i(0))/\sum y_i(0)$.

Table 2: Transmutation of ^{50}Cr after 10000 pulses^a.

Isotope	End Pulse	End Dwell	10000 Pulse
^{50}Cr	9.999991	9.999991	9.908248
$^{51}\text{Cr}^*$	1.564205E-06	1.563300E-06	1.038884E-03
^{52}Cr	2.258176E-13	2.258176E-13	2.806988E-06
^{53}Cr	2.032879E-17	2.032879E-17	7.977416E-10
^{54}Cr	0.0	0.0	1.819256E-13
$^{49}\text{V}^*$	3.778731E-06	3.778547E-06	2.148223E-02
^{50}V	3.873765E-06	3.873765E-06	3.808704E-02
^{51}V	7.185008E-10	1.624175E-09	1.482433E-02
^{48}Ti	0.0	0.0	6.830789E-05
^{49}Ti	1.477929E-10	3.315157E-10	1.620743E-02
Error-ppm ^b	4.445155E-6	4.439471E-6	-4.072662
CPU(ms)	4	3	31

(a) Burn time=3156 seconds and dwell time=2000 seconds.

(b) Error= $10^6(\sum y_i(t) - \sum y_i(0))/\sum y_i(0)$.

References

- [1] H. Attaya, Y. Gohar, and D. Smith. US-ITER activation analysis. Fusion Technology 19(1991)1837.
- [2] H. Attaya. Improvement of decay and cross sections data libraries for activation calculation. DOE/ER-0313/14 (July 1993).
- [3] R. Bellman. Introduction to matrix analysis. (2nd Edition, McGraw-Hill, New York, 1970) pp. 163-174.
- [4] C. Moler and C. Van Loan. Nineteen dubious ways to compute the exponential of a matrix. SIAM Review 20(1978)801-36.
- [5] J. Jung. Theory and use of the radioactivity code RACC. Argonne National Laboratory. ANL/FPP/TM-122 (May 1979).
- [6] H. Attaya. Input instructions for RACC-P. Argonne National Laboratory. ANL/FPP/TM-270 (March 1994).
- [7] A. Hindmarsh. ODEPACK, a systematized collection of ODE solvers, in: Scientific Computing, eds. R. Stepleman et al. (IMACS/North-Holland, Amsterdam, 1983) pp. 55-64.
- [8] E. Rutherford. Radio-activity, (2nd Edition, Cambridge University Press, 1905.) pp. 330-337.
- [9] H. Bateman. The solution of a system of differential equations occurring in the theory of radio-activity transformations. Proc. Cambridge Phil. Soc. 15(1910)423.
- [10] T. Y. Sung and W. F. Vogelsang,. DKR: A radioactivity calculation code for fusion reactors. University of Wisconsin . UWFDm-170 (September 1976).
- [11] D. Henderson and O. Yasar. DKRICF: A radioactivity and dose rate calculation code package. University of Wisconsin. UWFDm-714 (April 1987).
- [12] T. England, W. Wilson, and M. Stamatelatos. Fission products data for thermal reactors, Part1: A data set for EPRI-CINDER using ENDF/B-IV. Electric Power Research Institute. EPRI NP-356 (ERDA E(29-2)-3608) (December 1976).

- [13] A. Hindmarsh. GEAR: Ordinary differential equation system solver. LLNL report, UCID-30001, Rev. 3 (December 1974).
- [14] L. Lapidus and R. Luus. Optimal control of engineering process. (Blaisdell, Waltham, Mass., 1967) pp.45-49.
- [15] M. Bell. ORIGEN - the ORNL isotope generation and depletion code. Oak Ridge National Laboratory. ORNL-4628 (May 1973).
- [16] E. Hairer, S. Norsett, and G. Wanner. Solving ordinary differential equations I. (Springer-Verlag, Berlin 1987) p. 70.
- [17] B. Parlett. A recurrence among the elements of functions of triangular matrices. Lin. Alg. and Its Applic. 14(1976)117.
- [18] B. Parlett. Computation of functions of triangular matrices. Electronics Research Laboratory, University of California, Berkeley. Memorandum No. ERL-M481(November 1974).
- [19] J. Wilkinson. The algebraic eigenvalue problem. (Clarendon Press, Oxford, England 1965) pp
- [20] E. Anderson et al. LAPACK users' guide. (SIAM, Philadelphia, 1992).
- [21] R. Ward. Numerical computation of the matrix exponential with accuracy estimate. SIAM J. Numer. Anal. 14(1977)600.
- [22] C. Van Loan. Computing integrals involving the matrix exponential. IEEE Trans. Auto. Cont. AC-23(1978)395.
- [23] G. Golub and C. Van Loan. Matrix computations. (2nd Edition, The Johns Hopkins University Press, Baltimore, 1989) p. 552
- [24] S. Spangler, J. Sisolak, and D. Henderson. Calculational models for the treatment of pulsed/intermittent activation within fusion energy devices. Fusion Engineering and Design 22(1993)349-366.
- [25] E. Cheng, R. Forrest, and A. Pashchenko. Report on the Second International Activation Calculation Benchmark Comparison Study. TSI Research Inc. TSIR-21 (December 1993).

DISTRIBUTION LIST FOR ANL/FPP/TM-273

Internal

H. Attaya (10)	T. Hua	B. Picologlou
S. Bhattacharyya	A. Hull	C. Reed
M. Billone	C. Johnson	Dale L. Smith
J. Brooks	T. Kassner	Donald L. Smith
O. Chopra	J. Kopasz	D.-K. Sze
H. Chung	A. Krauss	S.W. Tam
D. Diercks	B. Loomis	H. Tsai
D. Ehst	M. Lineberry	L. Turner
Y. Gohar	S. Majumdar	W. Woodruff
I. Gomes	R. Mattas	T. Yule
D. Gruen	B. Micklich	
A. Hassanein	K. Natesan	FPP Files (10)
H. Herman	J.H. Park	TIS Files (1)

External

DOE/OSTI for distribution per UC-424 (41)
Manager, Chicago Operations Office
ANL-E Libraries (2)
ANL-W Library
M. Abdou, University of California, Los Angeles
J. Anderson, Los Alamos National Laboratory
C. Baker, University of California, San Diego
J. Bartlit, Los Alamos National Laboratory
P. Batistoni, ENEA, Italy
S. Berk, U.S. Department of Energy
A.I. Blokhin, Fiziko-Energeticheskij Institut, Russian Federation
L. Bühler, Kernforschungszentrum Karlsruhe, Germany
T. Burchell, Oak Ridge National Laboratory
R. Causey, Sandia National Laboratories, Livermore
E.T. Cheng, TSI Research, Inc., California
M. Cohen, U.S. Department of Energy
C. Croessman, Sandia National Laboratories, Albuquerque
W. Daenner, The Net Team, Max-Planck-Institut fuer Plasmaphysik, Germany
J. Davis, McDonnell Douglas Astronautics Company
J. Doggett, Lawrence Livermore National Laboratory
L. El-Guebaly, University of Wisconsin
U. Fischer, Kernforschungszentrum Karlsruhe, Germany
R.A. Forrest, AEA, Fusion, United Kingdom
S. Ganesan, International Atomic Energy Agency (IAEA), Austria
D. Gelles, Pacific Northwest Laboratories
N. Ghoneim, University of California, Los Angeles
L. Greenwood, Battelle Pacific Northwest Laboratory
D. Henderson, University of Wisconsin
A. Hogenbirk, Netherlands Energy Research Foundation (ECN), Netherlands

A.V. Ignatyuk, Fiziko-Energeticheskij Institut, Russian Federation
 Y. Ikeda, Japan Atomic Energy Research Institute (JAERI), Japan
 K. Ilieva, Institute for Nuclear Research and Nuclear Energy, Bulgaria
 T. James, U.S. Department of Energy
 Y. Kikuchi, Japan Atomic Energy Research Institute (JAERI), Japan
 J. Kopecky, Netherlands Energy Research Foundation (ECN), Netherlands
 G. Kulcinski, University of Wisconsin
 D.C. Larson, Oak Ridge National Laboratory
 D. Lousteau, Fusion Engineering Design Center
 R.E. MacFarlane, Los Alamos National Laboratory
 H. Maekawa, Japan Atomic Energy Research Institute, Japan
 S. Malang, Kernforschungszentrum Karlsruhe, Germany
 F.M. Mann, Westinghouse Hanford Company, Washington
 D.V. Markovskij, Institut Atomnoi Energii I.V. Kurchatova, Russian Federation
 M. Mattes, Institut fuer Kernenergetik der Universitaet Stuttgart, Germany
 C. Maynard, University of Wisconsin
 R. McGrath, Sandia National Laboratories, Albuquerque
 E. Menapace, ENEA, Italy
 G. Moses, University of Wisconsin
 D. Muntz, Kernforschungszentrum Karlsruhe, Germany
 R. Nygren, Sandia National Laboratories, Albuquerque
 A. Opdenaker, U.S. Department of Energy
 Y. Oyama, Japan Atomic Energy Research Institute (JAERI), Japan
 G.-C. Panini, ENEA, Italy
 R. Parker, ITER JCT, Garching, Germany
 A.B. Pashchenko, International Atomic Energy Agency (IAEA), Austria
 S. Pelloni, Paul Scherrer Institute, Switzerland
 S. Piet, ITER JCT, San Diego, California
 D. Post, ITER JCT, San Diego, California
 R.W. Roussin, Oak Ridge National Laboratory
 R. Price, U.S. Department of Energy
 A. Raffray, ITER JCT, Garching, Germany
 A. Santamarina, Commissariat a' l'Energie Atomique, France
 R.T. Santoro, ITER JCT, Garching, Germany
 M. Sawan, University of Wisconsin
 K. Schultz, General Atomic
 M. Seki, Japan Atomic Energy Research Institute, Japan
 D. Steiner, Rensselaer Polytechnic Institute
 I. Sviatoslavsky, University of Wisconsin
 A. Takahashi, Osaka University, Japan
 M. Tillack, University of California, Los Angeles
 J. Vetter, Kernforschungszentrum Karlsruhe, Germany
 G. Vieider, ITER, Germany
 W. Vogelsang, University of Wisconsin
 H.K. Vonach, Institut fuer Radiumforschung und Kernphysik der Universitaet
 Wien, Austria
 R. Watson, Sandia National Laboratories, Albuquerque
 F.W. Wiffen, U.S. Department of Energy
 L. Wittenberg, University of Wisconsin

K. Wilson, Sandia National Laboratories, Livermore
P.G. Young, Los Alamos National Laboratory
M. Youssef, University of California, Los Angeles
Bibliothek, Max-Planck-Institute fur Plasmaphysik, Germany
C.E.A. Library, Fontenay-aux-Roses, France
Librarian, Culham Laboratory, England
Thermonuclear Library, Japan Atomic Energy Research Institute, Japan