BNL-47356
Informal Report

**CONCEPTUAL DESIGN STUDY OF AN INTENSE
X-RAY SOURCE FOR CORONARY ANGIOGRAPHY**

L.N. Blumberg

March 1992

NATIONAL SYNCHROTRON LIGHT SOURCE

**BROOKHAVEN NATIONAL LABORATORY
ASSOCIATED UNIVERSITIES, INC.**

Under Contract No. DE-AC02-76CH00016 with the

UNITED STATES DEPARTMENT OF ENERGY

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency, contractor or subcontractor thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency, contractor or subcontractor thereof.

BNL--47356

DE92 013011

CONCEPTUAL DESIGN STUDY OF AN INTENSE X-RAY SOURCE FOR
CORONARY ANGIOGRAPHY

L.N. Blumberg

March 1992

NATIONAL SYNCHROTRON LIGHT SOURCE
BROOKHAVEN NATIONAL LABORATORY, ASSOCIATED UNIVERSITIES, INC.
UPTON, LONG ISLAND, NEW YORK 11973

BNL
11/10/92

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

Preface

This work was originally completed in the Spring of 1983 at the suggestion of Drs. E. Rubinstein and R. Hofstadter while the author was on leave of absence at Stanford University and SSRL. The initial studies of Digital Subtraction Angiography at SSRL on phantom and animal hearts were in progress and showed encouraging results in imaging occlusions of vessels comparable in diameter to human coronary arteries. It therefore seemed an appropriate time to study the prospect of designing a dedicated compact x-ray source which could yield adequate intensity of iodine K-edge 33.16 KeV X-Rays and be affordable for a major medical center and of sufficient small size to be located within or adjacent to such an urban setting. Subsequently, studies on human subjects were initiated at SSRL and have continued at BNL and the Deutsches Elektronen-Synchrotron (DESY/ HASYLAB) NIKOS project, Hamburg, Germany. Initial results from these studies are encouraging - the image quality is now adequate to resolve major arterial blockages although not yet of comparable quality to replace the existing invasive catheterization method for clinical applications. Concurrently, additional studies of suitable x-ray sources have been pursued in the U.S., Germany and Japan, and renewed interest has recently been evident at the National Institute of Health (NHLBI) to develop such sources. It therefore seems appropriate at this time to reissue this Stanford (HEPL) report as a BNL report to provide wider distribution of the (unpublished) study.

L. Blumberg, March 1992

TABLE OF CONTENTS

ABSTRACT	1
I. INTRODUCTION AND ANALYSIS	2
II. RESULTS	9
III. DISCUSSION	16
IV. PRELIMINARY COST ESTIMATE	20
V. ACKNOWLEDGEMENTS	22
REFERENCES	23
TABLES AND FIGURES	25

ABSTRACT

Calculations are presented for several 1.4 GeV electron storage ring designs which, with an ultra-high field (80 kG) superconducting wiggler magnet and beam current $I = 400$ mA, will generate a 33.16 keV x-ray beam at 20 m from the wiggler of adequate intensity ($6 \cdot 10^9/\text{mm}^2 \text{sec}^{-1}$) and areal size for iodine K-edge coronary dichromography in humans. The preferred design is a 54 m circumference, 4 superperiod ring with 3.6 m long straight sections for wigglers, 0.7 m straight sections for injection kickers, RF cavities, harmonic cavities and feedback devices, and 0.46 m straight sections for chromaticity-correcting sextupoles S_d and S_p . Bending magnets are short (0.6 m) 15° bend "window frame" conventional dipoles operated at high (20 kG) field. A 500 MHz RF system is proposed to obtain a high harmonic number, $h = 90$, and large peak RF voltage $V_m = 2.4$ MV to optimize the Touschek lifetime at injection energy. Injection with a 100 MeV Microtron is proposed without use of an intermediate Booster synchrotron. The gas scattering lifetime at 100 MeV and 10^{-10} Torr, $\tau_c = 46$ sec, is adequate and the transverse damping time $\tau_x = 0.63$ sec with the additional damping provided by the wiggler is sufficiently small. The bremsstrahlung lifetime τ_b is more than adequate; however, the Touschek lifetime without a wiggler is only $\tau_T = 0.37$ sec at 100 MeV but can be increased to ≈ 15 sec if the wiggler is used to increase damped emittance and thus beam size. The Touschek lifetime for the assumed 400 mA beam appears to be the limiting factor for low energy injection. In the present study we have not addressed the photon beam line design problems posed by the 50.8 kw power output of the wiggler, nor have tracking calculations been performed to determine the decrease in dynamic aperture when the sextupoles are energized. A preliminary cost estimate is presented based on an extrapolation from existing or contemplated machines in the same energy range. Without a Booster ring, wiggler and beam line, and building for support staff (but including shielding) the overall facility cost is \$7.35 M.

I. Introduction and Analysis

We anticipate that a clinical demonstration of non-invasive digital subtraction coronary angiography (DSA) with tunable X-rays (dichromography) will create a need for many tunable X-ray sources that are intense, affordable and compact. These sources will be required near to urban medical centers throughout the world and therefore readily accessible to the patient population and to the medical community. Specifically, the dichromographic method under development at Stanford, involving the subtraction of digital X-ray images obtained at energies immediately above and below the iodine K-absorption edge (33.16 keV) uses radiation from a wiggler beam at the electron storage ring SPEAR at the Stanford Synchrotron Radiation Laboratory. The 33.16 keV photon intensity from the 8-pole, 18 kg peak field wiggler magnet in beam line IV, with SPEAR operating at 3 GeV electron energy and 100 mA of circulating electron beam, is about 6×10^9 photons $\text{mm}^{-2} \text{sec}^{-1}$ in the forward direction at 20 m in a photon energy interval of 17 eV (obtained by Bragg scattering on a Si(220) crystal¹). After passage through ≈ 20 cm of tissue in a 5 msec exposure a flux of about 3.5×10^4 photons mm^{-2} is incident on a Si(Li) detector and provides a signal-to-noise ratio of about 7.5 in a $0.5 \times 0.5 \text{ mm}^2$ pixel for an iodine arterial thickness of 2.5 mg cm^{-2} .

In the present study we have adopted the above intensity as a design criterion, although we note that the intensity desired by the Hamburg group³, $4.0 \times 10^{10} \text{ mm}^{-2} \text{sec}^{-1}$, is somewhat higher. Also, in the present context, we do not regard the size of the SPEAR machine (circumference $C = 234 \text{ m}$) or other recently completed high energy synchrotron radiation sources, as small. These include the Brookhaven (NSLS) 2.5 GeV X-ray ring⁴ ($C = 170 \text{ m}$), the Daresbury (U.K.) 2.0 GeV SRS⁵ ($C = 96 \text{ m}$), and the KEK (Japan) 2.5 GeV PF⁶ ($C = 178 \text{ m}$).

The following considerations have guided the present study.

As small a ring as possible with conventional magnets is required. This implies that we choose a bending magnet with the highest field practicable. We therefore choose a window frame design. Such magnets have operated in high energy particle spectrometers at 20 kG, with field tolerance comparable to the uniformity required in storage rings; about 1 part in 10^4 . We are particularly encouraged in this choice by the recent successful operation of the SLAC Damping Ring⁷ using magnets of similar design and strength. A consequence of small machine size is that we choose the lowest electron energy consistent with the required photon intensity. Since we plan to use a wiggler source, the photon intensity is also a function of the peak wiggler field. The photon spectrum from a wiggler is completely characterized by the critical energy

$$E_c \approx 0.665 B_0(T) E_e^2(\text{GeV}^2) \text{ keV} \quad (1)$$

with $B_0(T)$ the peak wiggler field in Tesla and E_e the electron energy in GeV. We desire the strongest wiggler field possible (to minimize the beam energy) that will yield a critical energy near the value $E_c = 10.77 \text{ keV}$ of the SSRL wiggler. In this regard we make an extrapolation and choose a wiggler with superconducting coils and a peak field of $B_0 = 80 \text{ kG}$. The first superconducting wiggler fabricated at BNL yielded $B_0 = 60 \text{ kG}$, and improvements in its design to better constrain the movement of the superconducting braid are readily envisioned.⁸ Thus, 80 kG seems a possible goal in this technology. In Fig. (1) we show the 33.16 keV photon intensity from such a device at

various electron energies compared to the 60 kG NSLS wiggler and the 18 kG SSRL wiggler. The curves were calculated using the expression given by Green⁹

$$\frac{dN}{dt} = \frac{3.69465 \times 10^{11} \Delta E(\text{eV}) \Delta \theta(\text{mr}) I(\text{mA}) N_p}{B(\text{kG}) E_e(\text{GeV})} \int_{E/E_c}^{\infty} K_{5/3}(y) dy \quad (2)$$

where $\Delta \theta(\text{mr})$ is the angle increment in the plane of the bend in milliradians, $\Delta E(\text{eV})$ is the photon energy increment in electron volts at energy E , $I(\text{mA})$ is the circulating electron beam current in the ring in milliamps, N_p is the number of poles of the wiggler, $K_{5/3}$ is the modified Bessel function of the second kind, and the field is obtained from the assumption that the electron trajectory and the magnetic field in the wiggler are sinusoidal

$$X = X_0 \sin(2\pi z/\lambda_0) \quad B = B_0 \sin(2\pi z/\lambda_0) \quad (3)$$

λ_0 is the length of the wiggler period, and the amplitude of the oscillation X_0 is given in terms of the wiggler strength parameter K as¹⁰

$$X_0 = (K/\gamma)^2 \rho_0 \quad (4)$$

with γ the electron energy in units of $m_0 c^2$, i.e. $\gamma = E_e/m_0 c^2$, ρ_0 the bending radius of the electron at the point where the wiggler field is B_0 , and $B_0 \rho_0 = 33.35 E_e(\text{GeV})$. The wiggler strength parameter (dimensionless) is $K = 0.934 \lambda_0(\text{cm}) B(\text{T})$. The wiggler wavelength chosen for Fig. (1) is $\lambda_0 = 17.4 \text{ cm}$ and the angle is given by:

$$\tan \theta = \frac{dx}{dz} = \left(\frac{2\pi x_0}{\lambda_0} \right) \cos \left(\frac{2\pi z}{\lambda_0} \right) \quad (5)$$

For our choice of field and λ_0 , $K = 130$. We choose an energy for the medical X-ray source of $E_e = 1.4 \text{ GeV}$ on the basis of these results. The angular distributions for the lower energy rings in Fig. (1) are broader than for the NSLS or SSRL sources since the maximum angle from Eq. (5) is (K/γ) . For our choice of energy the full width of the radiation cone at half intensity is $\Delta \theta \approx 60 \text{ mrad}$. The peak intensity is seen to be down by a factor of 2 from the SSRL case, but it is clear from the performance of present day storage rings with low longitudinal impedance (smooth vacuum chamber) that the ring current will exceed the SPEAR value of 100 mA by at least a factor of 2. The Daresbury SRS has attained¹¹ $I_{\text{max}} = 600 \text{ mA}$, the KEK(Japan) PF group reports¹² $I_{\text{max}} = 200 \text{ mA}$ (after vacuum system bakeout and argon discharge cleaning), and the NSLS VUV ring¹³ has reached $I_{\text{max}} = 400 \text{ mA}$ without the use of any of several means of damping instabilities or of eliminating the sources which excite the instabilities. In Fig. (2) we show the wiggler photon spectrum for the 1.4 GeV machine from Eq. (2) compared to the NSLS and SSRL sources. This shows that for the SSRL wiggler and the high field wiggler of the present

design, the 33.16 keV X-rays are well above the critical energy $\mathcal{E}_c$ and are in the portion of the spectrum where the intensity is decreasing exponentially¹⁴

$$\left(\frac{d^2 I}{d\omega d\Omega} \right)_{\theta=0^\circ} \approx \frac{3e^2}{2\pi c} \gamma^2 \left(\frac{\omega}{\omega_c} \right) e^{-2(\omega/\omega_c)} \quad (6)$$

Eq. (6) gives the energy per turn radiated by an electron in a frequency interval $d\omega$ and into solid angle $d\Omega$. If we divide by the energy per photon $\hbar\omega$ and note that $e^2/\hbar c = \alpha \approx 1/137$ and multiply by the number of electrons per second $I(\text{amps})/e(\text{coulombs})$ and the fraction $(\Delta\theta)/2\pi$ of electrons in an increment $\Delta\theta$, then Eq. (6) is a good approximation to our Eq. (2).

The ring should contain more than one wiggler straight section. It seems unreasonable to limit the machine capability to one beam line (although a 60 mrad beam could be split into several, perhaps five, beams for simultaneous patient use). The incremental cost of adding straight sections is small in comparison to the total machine cost, since the same number of magnets and power supplies would be required in the storage ring and the same investment in pre-injector accelerator(s), conventional facilities, real estate and foundations are involved. We choose a 4-superperiod machine with four long straight sections; three for wigglers and one for injection magnets.

The length of the long straight sections should be adequate to accommodate bump magnets at either end of the wiggler to provide a local orbit deformation in the event that the method of sweeping the electron beam vertically in the wiggler¹⁵ to move the horizontal fan of synchrotron radiation across the area of interest should prove feasible. As presently envisioned, the bumps would consist of four dipoles, two at either end of the wiggler and powered by a common pulsed capacitor discharge power supply with full sine wave excitation. Approximately one meter would be required at either end of the wiggler to provide the ≈ 5 mrad beam deflection. Since the present 3-period, $\lambda_0 = 17.4$ cm BNL superconducting wiggler¹⁶ requires 1.4 m of straight section length, we estimate that the 5-period, $\lambda_0 = 17.4$ cm wiggler contemplated here will at least use 1.8 m. Thus, the long straight section should be ≈ 3.8 m.

The X-ray beam should be removed from the machine as soon as possible since the radiation fan of 60 mrad divergence is already 8.4 cm wide at the end of the straight section. This implies that there should be no more than a quadrupole singlet at the end of the straight section, followed by a speci C-type bending magnet to allow the photon beam to be extracted from the ring. The quadrupole should be of the horizontally converging (F) type since we desire a large and parallel horizontal beam (high horizontal β -function) but small vertical beam (low vertical β -function) in the straight section. The latter requirement is a consequence of our choice of a horizontally bending, small vertical gap wiggler, and the theorem¹⁷ that the smallest size beam one can have in a given length $\mathcal{L}$ occurs when $\beta_0 = \mathcal{L}/2$ at the center of the aperture. This can be seen by noting that the β function in the straight section is

$$\beta(s) = \beta_0 + s^2/\beta_0 \quad (7)$$

and $d\beta/ds = 0$ at $\beta_0 = s = \lambda/2$. Thus we desire $\beta_0(v) \approx 0.75$ m. Another, and perhaps more compelling reason for small β_v at the wiggler, is the beam lifetime from gas scattering. Electrons are removed from the beam either by coulomb scattering and subsequently striking an aperture as a result of their angle deflection, or by inelastic scattering from the gas nuclei with emission of bremsstrahlung and subsequent energy loss sufficient to remove them from the stable RF bucket. If the cross section for the electron removal process is σ then the rate of particle loss is

$$dN/dt = -Nn\sigma \quad (8)$$

where c = velocity of light = $2.9979 \cdot 10^{10}$ cm/sec, n = density of gas nuclei, and N = number of electrons in the ring. Eq. (8) leads to the $1/e$ lifetime of the beam of

$$\tau = 1/n\sigma \quad (9)$$

For coulomb scattering we can integrate the Rutherford differential cross-section

$$\left(\frac{d\sigma}{d\Omega}\right)_R = \left(\frac{Ze^2}{2mc^2}\right)^2 \frac{1}{\sin^4(\theta/2)} \quad (10)$$

from $\theta = \pi$ to some angle $\theta_{\min}$ such that electrons scattering with angles $\theta < \theta_{\min}$ remain in the machine. We obtain

$$\sigma_c = 2\pi \int_{\theta_{\min}}^{\pi} \left(\frac{d\sigma}{d\Omega}\right)_R \sin\theta d\theta = \frac{Z^2 \pi r_0^2}{2\gamma^2} \left(\frac{1+\cos\theta_{\min}}{1-\cos\theta_{\min}} \right) \quad (11)$$

where $m = m_0 c^2 \gamma$ has been used and $r_0 = e^2/m_0 c^2 \approx 2.81 \cdot 10^{-13}$ cm is the classical electron radius. Using a small angle approximation for $\cos \theta_{\min}$, we obtain $\sigma_c \approx 2Z^2 \pi r_0^2 / \gamma^2 \theta_{\min}^2$. A particle starting with an angle $\theta_{\min}$ will undergo betatron oscillations of amplitude¹⁸

$$x = \theta_{\min} \sqrt{\beta_s \beta} \sin\psi \quad (12)$$

where ψ is the betatron phase angle, β_s the beta function at the scattering point and β at the azimuth ψ . From Eq. (12) the aperture $x = a$ will occur at some point with $\sin\psi = 1$ and $\beta = \beta_a$. Thus, $\theta_{\min}^2 = a^2 / \beta_s \beta_a$ and the coulomb lifetime from Eq. (9) is¹⁹

$$\tau_c \approx \frac{\gamma^2 a^2}{2Z^2 n c \pi r_0^2 \beta_s \beta_a} \quad (13)$$

It is customary to replace the β value at the scattering point by the average $\beta_s = \langle \beta \rangle$ in the ring. The point of the present discussion is that we want small β_s at the wiggler so that the wiggler gap a can be small and the field thereby large.

The beam lifetime should be as large as possible. Another factor affecting beam lifetime is bremsstrahlung production as noted above. The cross-section for this process is given by Bethe and Ashkin²⁰

$$d\sigma_B = 4Z^2\alpha r_o^2 \frac{d\varepsilon}{\varepsilon} \left\{ \left[1 + \left(\frac{E}{E_e} \right)^2 - \frac{2}{3} \left(\frac{E}{E_e} \right) \right] \ln(183/Z^{1/3}) + \frac{1}{9} \left(\frac{E}{E_e} \right) \right\} \quad (14)$$

(for complete screening) with $E = E_e - \varepsilon$, ε = photon energy, and where X_0 is the radiation length given by

$$X_0 = \left[4\pi\alpha r_o^2 Z(Z+2) \ln \left(\frac{183}{Z^{1/3}} \right) \right]^{-1} \quad (15)$$

The total cross-section for electron loss via bremsstrahlung emission can be obtained by integrating Eq. (14) over photon energy from the electron energy E_e to the maximum energy size ΔE_{rf} of the RF bucket

$$\begin{aligned} \sigma_B &= \frac{1}{X_0 n} \frac{4}{3} \left\{ \ln \left(\frac{E_e}{\Delta E_{RF}} \right) - \frac{(E_e - \Delta E_{RF})}{E_e} + \frac{3}{8} \frac{(E_e^2 - \Delta E_{RF}^2)}{E_e^2} \right\} \\ &\approx \frac{16}{3} Z^2 \alpha r_o^2 \ln \left(\frac{183}{Z^{1/3}} \right) \left\{ \ln \left(\frac{E_e}{\Delta E_{RF}} \right) - \frac{5}{8} \right\} \end{aligned} \quad (16)$$

In Eq. (16), α is the fine structure constant and r_o is the classical electron radius as previously defined. Also we have made the obvious approximation that $E_e \gg \Delta E_{rf}$. The RF bucket size is given by

$$\Delta E_{RF} = \sqrt{\frac{2eV_m E_e}{\pi h \alpha_p}} \quad (17)$$

where V_m is the peak RF voltage across the accelerating cavity, h = harmonic number of ring = number of RF wavelengths in the circumference L of the synchronous particle of energy E_e , and α_p is the momentum compaction factor of

the ring defined as

$$\alpha_p \equiv (\Delta L/L)/(\Delta p/p_e) \quad (18)$$

Obviously we cannot evaluate ΔE_{rf} and thus σ_b and r_b until we know the design values for the ring but, as an example, the values for SPEAR are $\alpha_p = 0.0418$ and $h = 280$ with $V_m = 2.4\text{MV}$.²¹ Thus, at $E_e = 3\text{ GeV}$, $\Delta E_{rf} = 19.79\text{ MeV}$.

Can we eliminate the need for a Booster synchrotron? This would clearly represent a significant cost saving and make the facility more reliable. When we note the choices made by other laboratories, we see that Daresbury and Brookhaven use Boosters with approximately 1/3 the full energy of the storage ring and the KEK machine (as well as the SLAC storage rings) use full energy injection from a Linac. The Hefei (China) group plans²² 200 MeV injection into an 800 MeV ring, and the University of Wisconsin SRC will inject at 100 MeV into the 1 GeV ring ALLADIN. The recent success in beam storage and acceleration at Wisconsin²³ encourages us to look carefully at the possibility of a 100 MeV microtron injector directly into our 1.4 GeV ring. There are three significant factors to be evaluated: gas scattering as mentioned in (4) above which has an energy dependence of γ^2 , the transverse and longitudinal damping times²⁴ which vary as $1/\gamma^3$, and the Touschek lifetime²⁵ which increases as γ^5 . Damping times will be considered when we discuss machine designs and, in particular, we will show that the presence of wigglers can have important beneficial effects in reducing them at low energy. For the Touschek effect we follow the formulation of Wiedemann²⁶ and write for the Touschek lifetime

$$\tau_{\text{tou}} \approx \frac{V(\Delta p_m)^2}{4\pi r_0^2 c \mathcal{D} N_0} \quad (19)$$

where N_0 is the number of electrons per bunch, V is the volume of the bunch which, for present purposes, we take as $8\sigma_x\sigma_y\sigma_z$ with σ_x and σ_y the standard deviation of the assumed Gaussian transverse profile and σ_z the longitudinal standard deviation. Δp_m is the momentum acceptance of the ring in units of m_0c , which if we neglect the electron rest energy and set $\beta = v/c = 1$, is just $\Delta\gamma$, the energy extent E_{rf} of the RF bucket of Eq. (17) if that quantity is expressed in units of m_0c^2 . The quantity $\mathcal{D}$ is a dimensionless integral given on Fig. (4) and parameterized in terms of $\eta \equiv (\Delta p_m/\gamma_e)$ and σ_p , the standard deviation of the electron momentum distribution in units of m_0c . Wiedemann shows that to good approximation $\mathcal{D}$ is a function of η/σ_p . However, we will want to look carefully at τ_{tou} at low (100 MeV) injection energy where σ_p is small. We have, therefore, calculated the integral for various η and σ_p in Fig. (4). With regard to the γ_e^5 energy dependence of τ_{tou} mentioned earlier, this can be seen from Eq. (19) and the dependence²⁷ σ_x, σ_y , and $\sigma_z \sim \gamma_e$ and $\Delta p_m \sim \gamma_e$ if we assume that $\eta = \text{constant}$, i.e. that the accelerating voltage V_m in Eq. (17) is always adjusted so that the energy acceptance is the maximum allowed by the vacuum chamber where the dispersion function η_x of the machine is maximum. Again, we cannot evaluate τ_{tou} without a specific machine design and, as with the damping time, the presence of wigglers and our ability to set a non-zero value of the dispersion function η_x at the wiggler position, and thus increase the beam size can have a beneficial effect on the Touschek

lifetime at injection energy. It should also be pointed out that the bremsstrahlung lifetime dependence on V_m obtained from Eqs. (16) and (17), as well as the Touschek lifetime dependence on bucket size $(\Delta p_m)^2$ and particles per bunch $1/N_0$, both argue for high RF frequency. However, high harmonic number h resulting from high RF frequency supports the opposite conclusion. We can have both high f_{rf} and low h if the ring circumference is small. As a numerical example of the Touschek effect for the 700 MeV NSLS VUV ring we have $\gamma_e = 1369.85$, $\eta = 0.0267$, $\sigma_p = 4 \times 10^{-4} \gamma_e$, $\sigma_z = 3.84$ cm, $\sigma_x = 0.66$ cm, $\sigma_y = 0.0066$ cm (10% coupling), and $N_0 = 1.1 \times 10^{11}$ electrons/bunch. From Fig. (4) $\mathcal{J} \approx 0.58$ and $\tau_{\text{tou}} = 9426$ sec. In practice, accelerator designers do not accept the numerical result of Eq. (19) literally since it does not contain many effects such as, increase in bunch size due to space charge effects, trapped ions in the vacuum chamber, instabilities, etc. In any case τ_{tou} increases with time as N_0 decreases. A factor of ignorance of at least two is applied.

Since we have chosen a window-frame bending magnet to obtain maximum field, it follows that the magnet must be straight unless we select a design (solid core) which can be disassembled to install the vacuum chamber and coils. It would be undesirable to build a solid-core magnet since this would limit the rate at which the magnet could be ramped, due to Eddy currents, for the no-Booster option. In the present design we will assume that the magnets have laminated cores and are straight. The penalty for this choice is that we must then allow aperture for the curvature of the beam.

For a magnet of bending radius ρ and bend angle θ_B the departure of the particle trajectory from a straight line, usually called the sagitta S (see above sketch) is

$$S = \rho \left(1 - \cos \frac{\theta_B}{2} \right) \quad (20)$$

where ρ can be evaluated from the magnetic rigidity $R = B\rho \approx 33.35E$ (GeV) kG m. For our case with $B = 20$ kG and $E = 1.4$ GeV $B\rho = 46.69897$ kG m and $\rho = 2.33495$ m. The effective length of the magnet is then $\mathcal{L} = \rho\theta$. The sagitta for several designs we have considered is $S(\theta_b = 9^\circ) = 0.72$ cm, $S(\theta_b = 11.25^\circ) = 1.12$ cm and $S(\theta_b = 15^\circ) = 2.0$ cm. Although we do not presently know the aperture requirement of the magnet vacuum chamber, a good estimate would be the NSLS chamber of 8 cm width. It then seems unwise to exceed $\theta_b = 15^\circ$ for the bend angle. Therefore, we have limited our lattice search to $\theta_b \leq 15^\circ$. Also, the special C-magnet immediately downstream of the wiggler straight will be limited to $B = 15$ kG in accord with NSLS experience.²⁰ This implies that the C-magnet will be 4/3 the length of the window-frame magnet. It should also be noted that the present design is not limited to 1.4 GeV should the wiggler fail to attain 80 kG; we can increase the bending magnet field beyond 20 kG if a high quality steel such as VITRENAMEL is used. In Fig. (3) we show data of Allinger and Jackson²⁹ on B vs H . If, for example, we consider a conductor of 2.5 cm width x 5 cm high at 15 kA cm⁻² and neglect H in the core we have $H = 3.75 \times 10^6$ Amp/m⁻¹ ($B = 47.124$ kG) in the gap. From Fig. (3) this gives $H \approx 26000$ oersteds or permeability $\mu = 1.8$. Thus, the steel is not saturated even at this high field.

To summarize the above, we have studied lattices of 4-superperiods, 4 long (3.8 m) straight sections at 1.4 GeV and present some of the more favorable designs for $\theta_b = 11.25^\circ$ and 15° dipoles. The lattice design code COMFORTS³⁰ which is an improved version of the SLAC storage ring design code MAGIC³¹ and the lattice design code LAMP³² were used. An RF frequency of 500 Mhz was assumed and peak RF voltage of 2.4 MV.

II. Results

A. Lattices with 15° Dipoles, $L = 50.96$ m, $h = 85$

The smallest machine considered in this study is sketched below. The effective length of the wiggler is taken as 1m and the quadrupoles are assumed to be 8 cm

aperture and 24 cm effective length. The 70 cm straight section centered at K is allowed for the injection kicker (one either side of the injection straight section). The remaining six 70 cm straight sections are for RF cavities (2 assumed), stripline beam detector (1), harmonic RF cavity for bunch lengthening (1), longitudinal tune splitting or feedback cavity (1), and transverse feedback deflection plates (1). We assume that there will be additional space in one or more of these short straights for a beam current transformer. The beam position monitors are assumed to be of the 1 cm diameter capacitive pick-ups which have been used successfully at SLAC and BNL and can fit under the coils of the quadrupoles. We also assume that trim windings about the quadrupole poles such as are used successfully at SPEAR will suffice for closed orbit correction. The $d = 46$ cm straights are for correction sextupoles S_d and S_f which are required to correct the natural chromaticity from negative values to a value $+3$ as required to suppress the head-tail transverse instability. ν_x and ν_y are the horizontal and vertical "tune" of the machine defined¹⁰ as $\nu = (2\pi)^{-1} f ds / \beta$. The sextupoles are envisioned as 8 cm aperture, 16 cm effective length.

We have restricted the lattice search to tunes which are far from integer and half-integer resonances and also the sum resonance $\nu_x + \nu_y = \text{integer}$. We have particularly avoided the integer "structure" resonances $\nu = 4, 8, \dots$. In general, we constrained the solutions to tunes $(\nu_x, \nu_y) = (3.25, 3.25)$, $(5.25, 3.25)$, $(5.25, 5.25)$, $(7.25, 3.25)$ and $(7.25, 5.25)$. We do not wish to imply from the above that the machine must operate at the linear coupling line $\nu_x - \nu_y = \text{integer}$, but it should be capable of doing so if one desires 100% coupling. In Table (I) we summarize the properties of several interesting solutions. Quadrupole strengths are normalized, i.e. $g = G/B\rho$ with the gradient G in kG/m and $B\rho$ in kG m. The sign convention used here is that positive quadrupole strength means horizontally focussing. Since we have only three quadrupole strengths to vary, the programs were successful only when the number of constraints was ≤ 3 . We chose ν_x , ν_y and $\eta_x^* = 0$ where η_x^* is the dispersion function in the long straight. With very strong wigglers, the beam emittance ϵ and hence size $\sigma = \sqrt{\epsilon\beta}$ will increase; an undesirable result for most storage ring applications. However, for the present application it would be desirable to increase the size, particularly at injection energy, and thereby increase the Touschek lifetime in Eq. (19). If this can be accomplished without a serious increase in the momentum compaction factor α_p and thus a decrease in RF bucket size in Eq. (17) on which the bremsstrahlung lifetime of Eqs. (9) and (16) depend, we may be able to avoid a Booster synchrotron and inject directly into the storage ring at low energy. We have studied the case of $\eta_x^* \neq 0$ and will discuss the results later. For the present we are limiting the lattice search to the subset $\eta_x^* = 0$. Only two basic solutions were found with the conditions previously stated: $(3.25, 3.25)$ and $(5.25, 3.25)$. Solution A of Table I is a slight improvement over solution B only with regard to less negative natural chromaticities ξ_x and ξ_y . We must increase the chromaticity to positive values, as previously noted, with sextupoles of strength S_f and S_d in the d_f straight section; the required strength is related to the chromaticity change $\Delta\xi$ by¹¹

$$\begin{aligned}\Delta\xi_x &= \xi_x - \xi_x^0 = -\frac{N_s}{4\pi} \left[N_f \beta_{xf} \eta_{xf} S_f + N_d \beta_{xd} \eta_{xd} S_d \right] \\ \Delta\xi_y &= \xi_y - \xi_y^0 = \frac{N_s}{4\pi} \left[N_f \beta_{yf} \eta_{xf} S_f + N_d \beta_{yd} \eta_{xd} S_d \right]\end{aligned}\quad (21)$$

where N_s = number of superperiods
 N_d = number of "D" sextupoles per superperiod
 N_f = number of "F" sextupoles per superperiod

η_{xd} and η_{xf} are the horizontal eta functions at the indicated sextupoles, β_{xf} , β_{xd} and β_{yf} , β_{yd} are the horizontal and vertical beta functions at the indicated sextupole, S_f and S_d are the sextupole strengths $S_{d,f} = B''l/B\rho$ with l = effective length and $B = 1/2 B'' x^2$ the sextupole field in the median plane. Eq. (21) can be solved for S_f and S_d to obtain

$$S_f = (4\pi \Delta\epsilon_y \beta_{xd} + \Delta\epsilon_x \beta_{yd}) / N_s N_f \eta_{xf} (\beta_{xd} \beta_{yf} - \beta_{xf} \beta_{yd}) \quad (22)$$

$$S_d = -4\pi (\Delta\epsilon_x \beta_{yf} + \Delta\epsilon_y \beta_{xf}) / N_s N_d \eta_{xd} (\beta_{xd} \beta_{yf} - \beta_{xf} \beta_{yd})$$

It is well known from particle tracking calculations³⁴ that introduction of nonlinear elements such as sextupoles into the lattice will decrease the dynamic aperture of the machine--the aperture required to contain electrons which acquire large amplitude betatron oscillations following photon emission. With sufficient sextupole strength it is indeed possible to increase the growth rate of the oscillation amplitude to values greater than the radiation damping rate, in which case the solution becomes unstable. So we will be looking for solutions with small ξ^0 .

Another consideration is the kicker strength required for the injection "bump". We desire a local orbit deformation of the circulating beam at the injection septum magnet in order to minimize the oscillation amplitude of the injected beam relative to the beam already stored in the machine. This condition is most easily achieved with a "bump" which extends for one-half of a betatron wavelength λ_B centered about the injection septum. A perfect orbit deformation would then consist of two "kicker" magnets at $\lambda_B/4$ on either side of the septum (a betatron phase shift of $\psi = 0.25 \times 2\pi$ radians). However, it is seldom possible to attain this condition and a third kicker is usually required³⁵ preferably near the septum, to obtain a local deformation. We have allowed space in the upstream end of the injection straight for this correction kicker. In any case, the amplitude k of the "kick" at point K in the d_4 straight is related to the amplitude d of the deformation at the center of the long straight (approximately the septum position) by¹⁸

$$d = k \sqrt{\beta_{xK} \beta_x^*} \sin \psi_K \quad (23)$$

Although the $\psi_K/2\pi = 0.19$ of solution A is closer to the optimum value of 0.25, the values of $\beta_{xK} = 1.5$ m and $\beta_x^* = 10.12$ m of solution B are sufficiently larger than in solution A to yield a smaller kick requirement k

for a given deformation in Eq. (23). For a typical value $d = 4$ cm the required kicks would be $k_a = 16.7$ mrad and $k_b = 12.2$ mrad. These values are readily attainable with a full aperture (window-frame) ferrite kicker outside of a ceramic vacuum chamber. For example, consider a kicker magnet of 8 cm aperture with a field of 2.5 kG which is attainable with good quality ferrite.³⁶ If the magnet effective length is $\lambda = 0.5$ m and the magnetic rigidity at $E_0 = 0.1$ GeV injection energy is $46.7/14 = 3.335$ kG m we obtain a peak deflection of $k_{max} = 375$ mrad. Even if we inject at full energy the kicker capability is $k_{max} = 26.8$ mrad. We can therefore tolerate much smaller values of β_{xk} , β_x^* and $\sin \psi_k$ than in either solutions A or B.

For solution B we also give the values of several key parameters at a tentative injection energy of 0.1 GeV; $\tau_x = 9.73$ sec, $\sigma_x^* = 0.13$ mm and $\sigma_e = 5$ keV. These values are of course completely unreasonable for injection into the storage ring. In Fig. (5) we show the energy dependence of the parameters and note that they are changing rapidly at low energy. Solutions C and D show the effect of the wiggler on the damping time τ_x , beam sizes σ_x^* and σ_z and energy spread σ_e . The decrease in τ_x at 0.1 GeV to 0.6 sec when the wigglers are turned up to twice their nominal value ($2 \times 80/14 = 11.4$ kG) is a significant improvement. Note that the computer code assumes a symmetric machine with reflectional symmetry about the center of QF₂. Hence, it assumes that four wigglers of the indicated strength are present. If we have only one wiggler, it would be at four times the quoted strength. Note also that, in solution D, the value of β_y^* has decreased to 0.05 m as a result of the strong vertical fringe field focussing introduced by the wiggler (and accompanying vertical tune shift $\Delta \nu_y$ which accounts for the reduction in QD₁ strength from solutions B to D). At slightly over $2 \times$ nominal strength, $\beta_y \rightarrow 0$ and the vertical tune $\nu_y = 1/2\pi f_{ds}/\beta_y$ diverges at which point no stable solutions exist. The energy dependence of the injection parameters with the wigglers on is shown in Fig. (6) and exhibit the same rapid change in parameters at low energy noted in Fig. (5).

For the $\nu_x, \nu_y = (5.25, 3.25)$ solutions E, F and G, there appears to be no advantage relative to the lower tune solutions. The more favorable phase shift $\psi_k/2\pi = 0.27$ does not compensate for the much smaller value of $\sqrt{\beta_{xk}\beta_x^*}$ in Eq. (23) and the natural chromaticities $\xi_x^0, \xi_y^0 = -10.22, -24.75$ are too negative. Also, the peak value $\beta_y = 66.64$ m would give a significant decrease in the coulomb scattering lifetime in Eq. (13). Therefore, the best $L = 51$ m ring we found is solution B. We are not satisfied with the large value of $\alpha_p = 0.087$, however. The NSLS VUV ring³³ for example, has $\alpha_p = 0.023$. One final comment on Table I. The largest quadrupole strength encountered is 4.57 m^{-2} . At $\beta_p = 46.69$ kG m this corresponds to a gradient of 2.134 kG cm^{-1} . If we intend to use quadrupoles of 4 cm half aperture, then the pole-tip field is 8.53 kG. For the NSLS X-ray ring³⁷ the peak field specified is 5 kG and will increase to 6 kG for 3 GeV operation. For the proposed³⁸ low emittance SPEAR configuration at 3 GeV, the maximum gradient will be 0.84 kG/m and the corresponding pole-trip field $B_t = 6.3$ kG. It is expected³⁹ that the SPEAR quadrupoles have this capability based on previous experience with 4 GeV SPEAR operation. We are, however, again encouraged by the successful operation of the SLAC damping ring⁷ using $B_t = 8.06$ kG quadrupoles and are making the bold extrapolation to $B_t \leq 10$ kG.

B. Lattices with 15° dipoles, $L = 53.96$ m, $h = 90$

The $h = 90$ lattice is a 4 quadrupole (per half superperiod) variant of the A lattice. Its geometry is given in the sketch below.

The addition of an extra quadrupole could be an important aid in finding new solutions; however, we again limited the search to 3 constraints; ν_x, ν_y and η_x^* . Some of these solutions are presented in Table II. We first note that the computer program desires a horizontally focussing quadrupole for QD_2 in spite of an initial negative guess value and numerous attempts to find a solution with vertically focussing QD_2 . Thus, solutions A, B and C are, in a sense, equivalent to the $L = 51$ m ring as is evident from comparison of I B and II A. However, the kicker parameters are nearly optimal with $\psi_k/2\pi = 0.27$, $\beta_{xk} = 1.53$ m and $\beta_{xk}^* = 11.59$ m. The momentum compaction factor $\alpha_p = 0.072$ is somewhat smaller than solution I.B. The required quadrupole strengths are smaller, which is helpful. The parameter which argues most strongly in favor of solution II A is the maximum value of the eta function, $\hat{\eta}_x = 1.35$ m, which is a factor of more than two smaller than for the I B ring. Since the equilibrium orbit shift of an off-momentum particle is

$$(\Delta x)_{E.O.} = \eta_x (\Delta p/p_0) \quad (24)$$

ring II A is capable of twice the momentum acceptance of ring I B if one is able to increase the RF bucket size of Eq. (17) with a sufficiently large peak RF voltage V_m .

In solutions II B and II C we give the results for the same ring with the wigglers on at normal and $2\times$ normal values, respectively. The results are similar to Table I C and I D solutions. We did not compute the $E_0 = 0.1$ GeV case for II A and II B. It should also be pointed out that all solutions in this report were calculated with a peak RF voltage of $V_m = 2.4$ MV and thus the energy loss of 2.166 MeV/turn for solution II C at $E_0 = 1.4$ GeV gives values for parameters dependent on the RF bucket size (and phase-stable angle $\phi_s = 115.5^\circ$ in II C) such as σ_z and σ_e which are smaller than in a realistic machine design with adequate RF overvoltage. For example, solution II C gives 2×10^{-6} min for the quantum lifetime τ_q whereas the value of that parameter is essentially infinite (2×10^{31} min in solution II A) when the overvoltage V_m is generous. Solution II A is the best solution we have found in the present

study and we therefore present the computer input for the case in Table III, the computed betatron functions in Table IV and the resulting parameters in Table V. We have also studied the effect of non-zero η_x^* with the wiggler on at 2x nominal strength at a possible injection energy of 100 MeV to observe the beam blow-up effects associated with non-zero momentum dispersion in a region of large electron energy changes due to radiation. (The RF cavity is another region of large electron energy changes.) The results for beam sizes σ_x^*, σ_y^* (with 100% coupling assumed) and σ_z and the momentum compaction factor α_p are given in Fig. (7). In the interval $0 \leq \eta_x^* \leq 1.5$ m the values σ_x^* and σ_y^* increase by a factor of ≈ 3 . The increase in σ_z is smaller but we distrust this result for the reasons previously discussed. A small increase in α_p results. These changes are accomplished by a relatively small change in quadrupole strengths and we could presumably realize much larger changes in beam size. Thus, we can realize at least an order of magnitude increase in Touschek lifetime of Eq. (19) at injection energy. The calculation does not indicate an increase in energy spread $\sigma E/E$ vs η_x^* so presumably the integral of Eq. (19) remains constant.

One remark on the wiggler bend angles stated in Tables I and II. In the sketch below we show one half of the assumed wiggler geometry with reflectional symmetry. A full pole has an effective length of 8 cm with drift spaces of 2 cm between poles. The total half length of the wiggler is 50 cm and includes a half pole BWPH and BWMH at either end. With magnetic rigidity $B\rho = 46.69897333$ kG m and a field of 80 kG, the bend radius is $\rho = 0.583737167$ m. The bend angle of a full pole is then $\theta = 0.137047981$ rad = 7.85227090° .

For the $L = 53.96$ m, $h = 90$, 15° dipole ring we also looked for solutions at $\nu_x, \nu_y = (5.25, 3.25)$ with the expectation that a higher horizontal tune would yield a smaller dispersion function η_x and smaller momentum compaction factor α_p than solution II A. It was first apparent that, with larger ν_x the tune shift from the kicker to the injection septum (center of the long straight) was much too large. We therefore did the calculations with the kicker straight section d_4-d_4 located immediately downstream of the BC magnet (interchange of d_3 with d_4-d_4 in sketch of MXI lattice). This resulted in a

nearly optimum phase of $\psi_k = 0.27 \times 2\pi$. The α_p and $\hat{\eta}_x$ values do decrease slightly but two parameters change in a detrimental manner; the value of β_x^* decreases from 11.59 m in II A to 0.29 m in II D which implies that the injection kicker would require a $k = 55.2$ mr deflection to give a 4 cm displacement at the septum, a value which exceeds the kicker capability if we elect to inject at full 1.4 GeV energy. Further, the maximum vertical β value $\hat{\beta}_y$ has increased to 47.7 m from 29.1 m which will decrease the gas scattering lifetime of Eq. (13). We attempted increasing the value of β_x^* by imposing a constraint in case II G but the value of $\hat{\beta}_y$ increased still further to 53.80 m and the kicker phase increased to $\psi_k = 0.40 \times 2\pi$ as a result. The value of ψ_k is unacceptably large. Since we have 4 variable quadrupoles, we tried imposing 4 constraints; on $\beta_x^* = 0.5$ m and $\eta_x^* = -0.5$ in addition to v_x and v_y but this result (not shown) increased $\hat{\beta}_y$ to 119 m, α_p to 0.135, and natural chromaticity ξ_y^0 to -25.3; all unacceptably large. Hence solution II A is the only $L = 53.96$ m solution which meets our requirements.

C. Lattices with 11.25° dipoles, $L = 58.76$, $h = 98$

The $h = 98$ lattice has 5 quadrupoles and 4 dipoles per half-superperiod as shown in the sketch below. Again, the addition of one additional quadrupole gives the machine designer another degree of freedom in choosing constraints.

We have generally used 4 constraints $v_x, v_y, \eta_x^* = 0$ and $\beta_y^* = 0.5$ m and we have searched for solutions with $v_x, v_y = (3.25, 3.25), (5.25, 3.25), (5.25, 5.25)$ and $(7.25, 3.25)$. The solution at $v_x, v_y = 3.25, 3.25$ (VI A) is acceptable in all respects. The most significant improvement relative to the results of Table II is the smaller eta function $\hat{\eta}_x = 1.10$ and momentum compaction factor $\alpha_p = 0.053$. The injection situation is quite favorable even with a somewhat small kicker phase $\psi_k = 0.16 \times 2\pi$ because the beta functions $\beta_x^* = 20.04$ m and $\beta_{xk} = 15.26$ m are so large. The results of solution VI B with the wigglers on are equally acceptable. For solution VI C at $v_x, v_y = 5.25, 3.25$ we have relaxed the constraint β_y^* from the optimum 0.5 m to 1.0 m to avoid a solution (5/24-7, not shown) for which the $\beta_y^* = 0.5$ m constraint resulted in an unacceptably large peak value $\hat{\beta}_y = 62.57$ m. The excessively large kicker phase $\psi_k = 0.43 \times 2\pi$ somewhat improved by relocating the kicker in solution

VI D downstream of the QD₁ quadrupole and could no doubt be improved still more by further movement of the kicker upstream. The solutions VI C and D are particularly attractive because of the very small value of the eta function $\eta_x = 0.90$ m, but this advantage is somewhat offset by a decrease in chromaticity $\xi_y = -16.15$. We feel that VI D is a usable solution. For the $v_x, v_y = 5.25, 5.25$ case we found only one solution, VI E, and this result appears unacceptable to us because of the kicker parameters $\psi_k = 0.47 \times 2\pi$, $\beta_{xk} = 0.58$ m and $\beta_x^* = 0.12$ m. Also, $\alpha_p = 0.144$ is much too large. The maximum quadrupole strength of 5.17 m^{-2} would result in a pole tip field of $B_t = 9.65$ kG which is high but within our previously stated limit of ≤ 10 kG. No doubt the injection situation could be improved at this tune by moving the kicker upstream (it was back in the original location given on the MXH lattice sketch for VI E) but this case was not pursued in the present study.

Finally we looked briefly at the $v_x, v_y = 7.25, 3.25$ possibility. In VI F the search was constrained to only v_x and v_y . The resulting kicker phase $\psi_k = 0.68 \times 2\pi$ is, of course, impossible but for this run the kicker position was as given in the MXH lattice sketch; just upstream of QF₂. We, therefore, moved it as far upstream as possible--between the BC dipole and QD₁ quadrupole for solution VI G. Constraints $\beta_y^* = 1.0$ m and $\eta_x^* = 0$ were also imposed. The resulting $\psi_k = 0.46 \times 2\pi$ is still unacceptably large and $\beta_{xk} = 0.17$ m and $\beta_x^* = 0.5$ m are too small for efficient injection. Also, the uncorrected chromaticities $\xi_x = -24.14$ and $\xi_y = -34.53$ are too negative and the peak vertical beta function $\beta_y = 72.32$ m is too large. We, therefore, rule out this solution.

III. Discussion

We will restrict this discussion to evaluation of the required aperture of the machine, the coulomb scattering and bremsstrahlung lifetimes of the Table II A 5/29-16 53.96 m MXI ring and the beam current limit for an adequate Touschek lifetime at injection and operating energy. The 53.96 m ring is our preferred choice of machine from among the (large) subset of possible designs because it is less costly than the MXH 58.76 m design but technically better in several respects than the 50.96 m ring. Choice number 2 is the Table VI A MXH 5/24-1 58.76 m ring which provides the designer with smaller η_x and α_p values and considerably more flexibility in optimization of the lattice. Perhaps most important is that the MXH design uses 11.25° dipoles and a sagitta of $S \approx 1$ cm; we are uncomfortable with the $S = 2$ cm of the 15° dipole rings. Choice number 3 is the Table I A 50.96 m MXJ design 5/22-7 in Table I A because it is the least expensive and smallest and appears to satisfy the requirements; however the larger η_x and α_p of that machine are points of discomfort. We will not know the full significance of these factors, as well as the affect of nonlinearities such as the chromaticity-correcting sextupoles, without tracking calculations which evaluate the dynamic aperture of the machine with nonlinearities but are at present beyond the scope of this report. Our goal has been to find a suitable linear lattice configuration. It is perhaps useful to note that we have been unable to find a configuration with α_p as low as the present SPEAR value of 0.0417 or the projected value of 0.0166 for the low emittance SPEAR configuration²⁰ or the $\alpha_p = 0.0234$ of the NSLS VUV ring²¹; this problem appears intrinsic to our basic geometric choice of quadrupole singlets in the long straights.

We first require the RF bucket size of MXI 5/29-16 from Eq. (17) with $V_m = 2.4$ MV, $E_0 = 1.4$ GeV, $h = 90$ and $\alpha_p = 0.072$. The RF bucket from these parameters is given in Fig. (8) and we compute $\Delta E_{rf} = 18.18$ MeV from Eq. (17); thus $\pm \Delta E_{rf}/E_0 = \pm 1.30\%$. (The computer result from Fig. (8) is 17.38 MeV, probably due to inaccuracy in single precision arithmetic on the VAX.) Here is where we would have profited from a factor of four smaller α_p since larger V_m is hard to obtain. The peak value $\hat{\eta}_x$ is at Qf_2 from Table IV, at which point we can accommodate equilibrium orbits with a momentum spread

$$(\Delta p/p_0)_{\max} \approx (\Delta E/E_0)_{\max} \approx a/\hat{\eta}_x$$

We can then accommodate $\pm 2.97\%$ spread in equilibrium orbits in this machine in the "zero beam size" limit. The amount of aperture actually required about the equilibrium orbit can be determined accurately only by tracking calculations with a realistic model of the machine which would include higher order multipole content in the dipoles (mostly sextupole) and quadrupoles. We can, however, estimate the aperture requirement by first calculating the emittance $\mathcal{E}_x$ of the damped beam from the definition $\sigma = \sqrt{\mathcal{E}\beta}$ and the values σ_x^* of the damped beam size and β_x^* in Table IV. We will be conservative here and use the value $\sigma_{x0}^* = 2.633$ mm (no coupling--the values of σ_x^* in Tables I, II and VI are for 100% coupling) from Table V. We then obtain for the damped emittance $\mathcal{E}_{x0} = 0.5981$ mm mr--a rather large damped emittance for present day electron storage rings. For comparison we normalize $\mathcal{E}_{x0}$ by dividing it by E_0^2 since this is the energy dependence of the emittance; then $(\mathcal{E}_{x0})_n = 0.305$ mm mr GeV⁻² whereas the present SPEAR normalized emittance is $(\mathcal{E}_{x0})_n = 0.049$ mm mr GeV⁻², the NSLS VUV ring³³ is 0.180 mm mr GeV⁻² (with solutions down to 0.041 mm mr GeV⁻²), the new low-emittance³⁸ SPEAR configuration is 0.014 mm mr GeV⁻², the NSLS X-ray ring³⁷ is 0.013 mm mr GeV⁻² and the proposed very low emittance ALS ring for the Berkeley NCAM project⁴⁰ is 0.003 mm mr GeV⁻². Thus, the MXI 5/29-16 configuration is a high emittance one; fortunately we do not require a low emittance configuration for the present application. In the absence of tracking, we can use a "rule of thumb" estimate⁴¹ which we used initially for the dynamic aperture A_d requirement for the NSLS:

$$A_{DH} = 10\sigma_x + 10 \text{ mm (horizontal)} \quad (25)$$

$$A_{DV} = 10\sigma_y + 5 \text{ mm (vertical)}$$

The largest β_x value from Table IV is at Qf_1 with $\hat{\beta}_x = 11.869$ m. With the $\mathcal{E}_{x0} = 0.5981$ mm mr we get $(\sigma_x)_{\max} = 2.664$ mm and $A_{d4} = 36.64$ mm. Since $\eta_x = 0$ at Qf_1 from Table IV we require no additional aperture at this point for off-set of the equilibrium orbit $\eta_x(\Delta p/p_0)$ due to momentum off-set. So our prior use of 4 cm for the half aperture of the quadrupoles appears to be a good choice. Note in Eq. (25) that the addition of 10 mm to $10\sigma_x$ is an

estimate of the additional aperture required by closed orbit error and betatron oscillation amplitude of the initially injected beam before it damps down to the values used above.

We can now estimate the coulomb scattering lifetime from Eq. (13). It is generally the case in storage rings that the physical aperture is smallest in the vertical plane because it is the vertical gap of bending magnets and horizontally deflecting wigglers that one wishes to minimize for reason of cost. The maximum vertical $\beta_y = 29.14$ m is at quadrupole QD₁. For the purpose of this calculation we will assume that the vacuum chamber is a rectangular, thin-walled stainless steel chamber which has been used successfully at Daresbury rather than the thicker walled (4 mm) extruded aluminum chamber used elsewhere; thus, the inside dimensions can be approximately 8 cm horizontal and 4 cm vertical. We further assume that nearly all of the residual gas is hydrogen; this conclusion for a well-conditioned ultra-high vacuum system after baking and desorption of gas from the walls is substantiated by results of vacuum experts at several laboratories.^{42 43 44 45} Thus $Z = 1$. For $\langle \beta_y \rangle$ we use the weighted average of 9.5 m. The final quantity required is the particle density of scattering nuclei n . An estimate of n requires knowledge not only of the static pressure ($\approx 10^{-11}$ Torr) but also the desorption rate of molecules from the chamber wall due to synchrotron radiation which is a function of beam current, and finally the density of trapped ions created by the beam. This is a difficult quantity to estimate with confidence. I, therefore, will scale from knowledge⁴⁶ of the 24 hr beam lifetime of SPEAR at 3 GeV when the machine is well conditioned and the vertical aperture at the QD cell quadrupoles where the vertical half-size of the chamber is 22 mm and $\beta_y = 20.6$ m. For $\langle \beta_y \rangle$ for SPEAR we use 12.5 m. Then Eq. (13) gives $n = 5.04 \cdot 10^{10}$ nuclei cm^{-3} which corresponds to an impressively low value of $p = 6.36 \cdot 10^{-11}$ Torr. If the observed lifetime is not limited by gas scattering, then this is an upper limit on the SPEAR pressure. For a higher current machine with smaller spacing between bunches (the effective distance between the "four" SPEAR bunches is 58.5 m) the ion density will be larger so we will use 10^{-10} Torr ($n \approx 8 \cdot 10^{10}/\text{cm}^3$). The gas scattering lifetime at 1.4 GeV for our machine is then

$$\tau_0 = 9110 \text{ sec} \quad (26)$$

At 0.1 GeV we scale by γ^2 and have $\tau_0 (0.1 \text{ GeV}) = 46.5 \text{ sec}$. Thus, τ_0 does not rule out 100 MeV injection if the injector is fast-pulsing. The pulse rate of the injector, however, is limited by the damping time which we have seen, in Table I, can be reduced with use of wigglers to 0.6 sec. Hence gas scattering is not the limiting factor for low energy injection.

One final point on scattering. We have tried throughout this study to keep the value of β_y^* at the wiggler small and, where possible, near the optimum value of 0.5 m to obtain the smallest vertical beam through a 1 m long wiggler. In solution II A 5/29-16 we came close with $\beta_y = 0.79$ m without constraint on that parameter. The coupled vertical emittance from Table IV is then

$$\epsilon_{y(A)} = (\sigma_{y(A)}^*)^2 / \beta_y^* = .301 \text{ mm mrad}$$

and the vertical beam width (standard deviation) at the end of the wiggler is, from Eq. (7), $\sigma_y = \sqrt{\epsilon_{y(a)}} \beta_y = 0.310$ mm. Then the aperture requirement from Eq. (25) is $\pm A_{dv} = \pm 8.1$ mm. The present 60 kG NSLS wiggler⁸ has a vertical aperture of ± 9 mm and is thus adequate for this machine at full energy. At injection energy the damped vertical beam size will be even smaller since $\epsilon \propto E^2$ and the problem we will encounter is the emittance of the injected beam. If we use the typical value of 1 mm mr which pertains¹⁷ for the Wisconsin 100 MeV microtron, the σ_y of the injected beam increases by a factor of 1.796 to $\sigma_y = 0.557$ mm and the aperture requirement becomes $A_{dv} = \pm 10.57$ mm at the wiggler. This problem may constitute an argument for a Booster synchrotron injector in which the beam from the pre-injector will damp to values comparable to those of the storage ring cited above, particularly if the pre-injector is a 100 MeV linac with a large emittance $\epsilon = E/\pi = 6.37$ mm mr which pertains¹⁸ for the NSLS 100 MeV linac pre-injector. The alternative to the wiggler as an injection aperture is to build a variable gap wiggler or one that moves out of the machine aperture at injection. It seems to us that this is a formidable mechanical problem for a superconducting device of the type contemplated here and we reject that method as a viable alternative.

The next parameter to be evaluated is the bremsstrahlung lifetime of Eq. (9) with the cross-section of Eq. (16). The dependence of the cross-section on electron energy is weak; thus, if the lifetime is large enough at operating energy, it should suffice at injection energy. We use the RF bucket size of $\Delta E_{rf} = 18.18$ MeV calculated earlier in this chapter and the particle density of $n = 8 \times 10^{10}$ cm⁻³ used in the estimate of gas scattering lifetime. Eq. (16) gives at 1.4 GeV $\sigma_b = 59.582$ millibarns and Eq. (9) gives the lifetime

$$\tau_b = 6993 \text{ sec} \quad (27)$$

If we assume that the same RF peak voltage is maintained at 100 MeV injection energy, then the RF bucket size at that energy is, from Eq. (17), $\Delta E_{rf} = 4.858$ MeV, the bremsstrahlung cross-section is $\sigma_b = 38.445$ mb and $\tau_b = 10838$ sec.

Finally, we evaluate the Touschek lifetime of Eq. (19), first at 1.4 GeV and then at the proposed 0.1 GeV injection energy. The maximum momentum acceptance Δp_m in units of $m_0 c$ is, at relativistic energy, numerically equal to the maximum RF bucket acceptance ΔE_{rf} divided by $m_0 c^2$ i.e. $\Delta p_m = 18.18/0.511 = 35.577$. The integral is given in terms of the parameter $\eta = \Delta p_m / \gamma_e = 0.013$ at $\gamma_e = 2739.7$. Similarly, the parameter σ_p is, relativistically, equal to the energy width of the beam which from Table II is $\sigma_e = 7.6 \cdot 10^{-4}$ (1400) = 1.064 MeV. In units of $m_0 c$, σ_p is the dimensionless number $\Delta \gamma = \gamma(E_0 + \sigma_e) - \gamma(E_0) = 2.0822$. From Fig. (4) we then get $\mathcal{J} \approx 0.805$. Then, from Table V we get the values $\sigma_{x(A)}^* = 0.186$ cm, $\sigma_{y(A)}^* = 0.049$ cm and $\sigma_z = 1.119$ cm. The subscript A means the value with 100% coupling which we have been using (the zero coupling value of σ_y is zero). The number of particles per bunch N_0 is related to the beam current I and RF frequency f_{rf} by $I(\text{AMPS}) = e N_0 f_{rf}$ with $e = 1.602 \cdot 10^{-19}$ coulombs/electron. Note that N_0 is then proportional to $1/f_{rf}$ and thus the Touschek lifetime is proportional to f_{rf} . Substituting $I = 0.4$ Amp, our desired current, and the $f_{rf} = 500$ Mhz which was chosen for this study (following Daresbury, The DESY storage rings DORIS and PETRA and the proposed LBL ALS ring), we have $N_0 = 4.994 \times 10^9$ electrons/bunch. The Touschek lifetime is then

$$\tau_{\text{tou}} = 2.709 \times 10^6 \text{ sec at } 1.4 \text{ GeV} \quad (28)$$

Of greater interest is the lifetime at 100 MeV. We can scale Eq. (28) by γ^3 and obtain $\tau_{\text{tou}} \approx 5 \text{ sec}$. Done more carefully we first note that the energy bucket cannot realistically be increased to as large as the spread $\Delta p/p_0$ of equilibrium orbits of $\pm 3\%$ previously estimated from η_x . If we maintain V_m at 2.4 MV we would get 4.8 MeV which is too large. So we arbitrarily set the RF bucket $\Delta E_{\text{rf}} = 2 \text{ MeV}$ (2%). This gives $\Delta p_m = 2/0.511 = 3.914$. Next, the values of $\sigma_{x(a)} = 0.0122 \text{ cm}$, $\sigma_{y(a)} = 6.0 \cdot 10^{-4} \text{ cm}$ and $\sigma_z = 0.0589 \text{ cm}$ can be obtained from Fig. (7) for $\eta_x = 0$. Then the parameters of the Touschek integral are $\eta = \Delta E_{\text{rf}}/\gamma_e = 0.02$ and σ_p is obtained from the Table II C value of $\sigma_e = 1.5 \cdot 10^{-4} \times 100 = 0.015 \text{ MeV}$ and the result $\sigma_p = \Delta\gamma = \gamma(100.015) - \gamma(100) = 0.029$. This value of σ_p is too small to obtain from the $\eta = 0.02$ curve of Fig. (4) but we estimate $\mathcal{D} \approx 3$. Then, with the same value of N_0 for $I = 400 \text{ mA}$ Eq (19) gives

$$\tau_{\text{tou}} = 0.37 \text{ sec at } 0.1 \text{ GeV} \quad (29)$$

We require an increase in τ_{tou} of at least 10^2 to even contemplate this injection energy. We have seen from Fig. (7) that simply changing the η_x^* value with the wigglers on can increase σ_x^* and σ_y^* by factors of three. We have made provision for an harmonic cavity which can increase σ_z by a factor of about two. Also, we think that we can use an addition "experience factor" of two in Eq. (19) as previously noted. We cannot reasonably decrease the integral $\mathcal{D}$ by either an increase in the Touschek η factor or in σ_p unless our calculation of beam energy spread is in error due to use of $V_m = 2.4 \text{ MV}$ at injection which we have seen leads to an unrealistically large energy bucket. Therefore, we conclude that the estimate of τ_{tou} at 100 MeV is marginal for injection.

One final remark on Touschek lifetime. We have intentionally avoided any discussion of the numerous transverse and longitudinal instabilities. This subject, endemic to all storage rings, could readily comprise a separate study and is germane to the present work only with regard to the effect of instabilities on beam size and hence Touschek lifetime. Instabilities generally increase beam size, to the detriment of colliding beam experiments, but perhaps an advantage for this application by increasing τ_{tou} .

IV. Preliminary Cost Estimate

The results are given in Table VII. Here we will discuss each item separately, noting at the outset that this cost estimate does not include cost of a building and that the estimate for a possible Booster is done separately, as is the cost of a superconducting wiggler plus associated beam line. First, the ring magnet system is directly scaled from the NSLS VUV ring ($E = 0.7 \text{ GeV}$, $L = 51 \text{ m}$) value of \$445.9K multiplied by four years of inflation at 10%/year. The result, \$652.8K, is well below the SLAC Damping ring ($E = 1.2 \text{ GeV}$, $L = 34 \text{ m}$) estimate of \$1.31M, but their estimate includes power supplies and, more imperatively, an extensive transport system from the Linac to the Damping ring and back. Our estimate is also well below the LBL ALS ring ($E = 1.3 \text{ GeV}$, $L = 182.4 \text{ m}$) of \$2.71M; however, LBL is using 84 quadrupoles rather than our 24 and 36 sextupole magnets compared to our 16. In general, we feel more comfortable in scaling from actual (NSLS) rather than estimated costs.

The magnet power supplies are again directly scaled from the NSLS \$151.2K value with a factor of 1.464 inflation and an additional factor of 1.25 to account for our need for 4 rather than 3 quadrupole power supplies. The addition of the resulting \$276.7K brings us closer to the SLAC result; again, we are lower than the LBL ALS value of \$645K but they include one additional quadrupole power supply and 72 ring steering supplies (we will also need steering supplies, but a lesser number--32 as in the NSLS VUV--and include the item under diagnostic equipment).

The ring vacuum system is one of the easier items; we will scale directly from the NSLS cost of \$430K since the rings are of comparable circumference; including the 1.464 inflation factor, the vacuum system estimate is \$630K.

For computer control the NSLS cost is \$723.8K. However, this includes the cost of two larger control computers (DG Eclipse) and at least 3 times the number of micro-computers (Intel 80/80) for their 3 rings as will be needed here. It is unclear to us whether we will even require a larger computer (of the order of a VAX-11/780) for machine control but we strongly suspect that the analysis of the angiography data will require it. So we multiplied the NSLS number by 0.5 and then used the 1.464 inflation factor to obtain \$529.8K.

The NSLS shielding costs also included survey but we believe that the value of \$1.511M is primarily shielding and will scale linearly with circumference. Their three rings have a total circumference of 249 m so we multiplied the NSLS number by $54/249$ and the 1.464 inflation factor to obtain \$479.9K.

For the rings diagnostic plus security system, the NSLS value is \$464.4K. We have added an additional \$30K for the two main power supplies plus pole tip secondary windings of the orbit correction system, then multiplied by $\$1.945M/\$7.79M = 0.25$ which is the fraction of the total capital cost expended on the VUV ring, and again used the 1.464 inflation factor to get \$181.0K.

The total capital cost to this point is \$2.75M. The final capital item is the RF system. We note first that the low frequency (53 Mhz) NSLS X-ray ring RF system with power capability of approximately 700 KW cost \$611.6K or, with the inflation factor, \$895.4K. One of the factors affecting the choice of RF frequency is certainly the lower cost of a 50 Mhz compared to a 500 Mhz system. The trade-off may well be the factor of 10 higher Touschek lifetime at injection which the 500 Mhz system gives us if that factor is the one that determines whether or not a Booster synchrotron is required. For the present we have no better estimate than the \$1.765M from the LBL proposal. Thus, the RF system is $\approx 40\%$ of the capital cost of the machine. It was not possible here to give consideration to the rather low estimate of \$140K for the SLC Damping ring RF; that system is a high frequency one also, but low power--16 KW for radiation plus cavity losses--and there were mitigating circumstances in obtaining surplus UHF transmitting equipment.

The direct labor cost of construction for the NSLS VUV was \$438.3K and, with inflation, \$641.7K is used in Table VII. We have no reason to assume that this item would be different elsewhere.

Finally, the design cost for the NSLS project, listed as Engineering Design and Inspection (EDI) is 23.5% of the total project capital cost or, in our case, $0.235 \times (\$4.515M) = \$1.061M$. Then we add 10% contingency of \$621.8K for an overall total of \$6.84M for the ring.

In the present cost estimate of the facility we are assuming no Booster. Thus, the final item is the pre-injector and associated beam transport system to the ring. We choose a 100 MeV microtron which cost \$275K at the University of Wisconsin.⁵⁰ With a 5-year inflation factor we obtain \$443K. For the microtron-to-ring transport system, we note that the NSLS cost for a 700 MeV transport system to the VUV ring was \$321.5K. We assume that the present transport system will include as many dipoles (2) and quadrupoles (9), but that the cost scales with energy. Including the inflation factor, this gives \$67.2K.

V. Acknowledgements

It is a pleasure to thank R. Hofstadter and E.B. Hughes for providing the facilities of the Hansen Laboratories of Physics at Stanford University, for helpful discussions and encouragement in the present work, and for suggesting an investigation of the problem of designing an X-ray source appropriate for clinical use. It is also a pleasure to acknowledge my gratitude to H. Winick and A. Bienenstock for providing the facilities of the Stanford Synchrotron Radiation Laboratory and to M.J. Lee and M. Woodley for making available the SLAC linear lattice design code COMFORTS which was used for much of the study, to S. Goldberg for getting the program running on the SSRL VAX, and to R.Z. Liu for use of his lattice search program LAMP. We thank G. Brown of SSRL and S. Krinsky of BNL for important advice on wiggler spectra, and W. Foyt of BNL for providing the budget data on which the present cost estimate is largely based. We would indeed be remiss if we failed to acknowledge the considerable programming effort of my wife, S. Blumberg, for all programs used in this report except the above mentioned lattice design codes. It is indeed a pleasure to thank G. Hinshaw of the Hansen Laboratories of Physics at Stanford University, for her excellent work in typing and editing this manuscript. Finally, we wish to thank M. Blume, J. McTague and A. van Steenberg for making possible this leave of absence from BNL to work with the Stanford Angiography group.

REFERENCES

1. E. Rubenstein, E.B. Hughes, L.E. Finman, R. Hofstadter, R.L. Kirk, T.J. Krolicki, J.P. Stone, S. Wilson, H.D. Zeman, W.R. Brody, A. Macovski, and A.C. Thompson, Synchrotron Radiation and its Application to Digital Subtraction Angiography, SPIE, 314 (1981).
2. Ibid
3. W.R. Dix, C.C. Glüer, W. Graeff, K.H. Höhne and W. Kupper, Deutsches Elektronen-Synchrotron report DESY-SR-82/24 (1982).
4. Proposal for a National Synchrotron Light Source, ed. J.P. Blewett, BNL-50595 (1977).
5. Design Study for a Dedicated Source of Synchrotron Radiation, D.J. Thompson, et. al. Daresbury (U.K.) report DL/SRF/R2 (1975).
6. S. Kamada, Y. Kamiya and M. Kihara, National Laboratory for High Energy Physics KEK (Japan) report KEK-77-16 (1977).
7. Stanford Linear Accelerator Center report SLAC-229 (1980).
8. H.C.H. Hsieh, private communication, 1982.
9. Spectra and Optics of Synchrotron Radiation. G.K. Green, BNL-50522, Eq. (22), p.9 (1976). See also J. Schwinger, Phys. Rev. 75, 1912 (1949).
10. G. Brown, K. Halbach, J. Harris and H. Winick, Proc. Int. Conf. on X-ray and VUV Synch. Rad. Instr., Hamburg (1982) to be published in Nucl. Instr. & Meth.; S. Krinsky, W. Thomlinson and A. van Steenbergen, BNL-31989 (1982).
11. V.P. Suller, N. Marks, M.W. Poole and R.P. Walker, Proc. of the U.S. Particle Accel Conf., Santa Fe, NM (1983) and private communication (1983).
12. Matsushita, Kitamura and Ishikawa, private communication (March, 1983).
13. J. Galayda, et.al., Proc. of the U.S. Particle Accel. Conf., Santa Fe, NM (1983). To be published in IEEE Trans. Nucl. Sci.
14. J.D. Jackson, Classical Electrodynamics (2nd edition), J. Wiley & Sons, Inc., (1975) Chapt. 14, Eq. (14.88). Note that Jackson defines the critical frequency as $\omega_c = 3\gamma^3(c/p)$ which is a factor of 2 larger than as defined by Schwinger (ref. 8) and used by all other references cited in this report. We use the Schwinger definition in this report.
15. Suggested independently by myself (1982) and V. Kulipanov of the Novosibirsk group and communicated to E.B. Hughes (1982).
16. S. Krinsky, W. Thomlinson, and A. van Steenbergen, BNL-31989 (1982), p.27, Table 4.1.
17. See, for example, L. Blumberg, et. al. Brookhaven National Laboratory report AGS-71/02 and IEEE Trans. Nucl. Sci. NS-18, 1009 (1971).
18. E.D. Courant and H.S. Snyder, Ann. Phys. 3, 1 (1958).
19. This result was communicated to me by C. Pellegrini (1981). A similar result is obtained by J. LeDuff, Laboratoire de l'Accelérateur Lineaire report LAL 82/42, Orsay, France (1982); however, LeDuff's result is missing a factor of a/β_s .
20. A good discussion of this process is contained in H. Bethe and J. Ashkin, Experimental Nuclear Physics (ed E. Segre), Vol. I, Part II, p. 260, Eq. (57). J. Wiley and Sons, Inc. (1953). An application to the BNL NSLS rings is given in L. Blumberg and M. Perlman, NSLS Tech. Memo (1980).
21. J. Harris, private communication (1983).
22. Y. Yan and R.Z. Liu, private communication, 1983 and Y. Yan, Proc. of the

- U.S. Particle Accel Conf., Santa Fe, NM (1983).
23. E. Rowe, private communication (1983).
 24. M. Sands, The Physics of Electron Storage Rings, Stanford Linear Accelerator Report, SLAC-121 (1970).
 25. A good discussion of the Touschek Effect can be found in H. Bruch, Circular Particle Accelerators, (translation) Los Alamos National Laboratory report LA-TR-72-10 (1972). Chapt. XXX.
 26. H. Wiedemann, Stanford Linear Accelerator Center internal report PEP-NOTE-27 (1973). The subject has also been treated by V. Volkel, Deutsches Elektronen-Synchrotron internal report DESY-67/5 (1967) and B. Gittelmann and D.M. Ritson, Stanford University, Physics Dept. internal report HEPL-291 (1963).
 27. A.S. King and M.J. Lee, SLAC internal report SPEAR-201 (1977) and reference 24.
 28. R. Heese, private communication (1980).
 29. J. Allinger and J. Jackson, private communication (1981).
 30. M.J. Lee and M. Woodley, private communication (1982).
 31. A.S. King, M.J. Lee and W.W. Lee, Stanford Linear Accel. Center report SLAC-183 (1975).
 32. R.Z. Liu, private communication (1983).
 33. See, for example, L. Blumberg, et.al., IEEE Proc. Nucl. Sci. NS-26, 3842 (1979) and BNL-25777 (1979).
 34. See, for example, L. Blumberg, SSRL informal report SSRL-TM-83/02 (1983) and references therein such as H. Wiedemann, SLAC informal report PEP-TN-220 (1981).
 35. See, for example, L. Blumberg, BNL informal note NSLS-TN-16 (1979).
 36. M. Plotkin, private communication (1979).
 37. S. Krinsky, et al., IEEE Proc. Nucl. Sci. NS-26, 3806, (1979).
 38. L.N. Blumberg and R.Z. Liu, SSRL informal report SSRL-TM-83/01 (1983).
 39. J. Harris, private communication (1983).
 40. Conceptual Design Report for the National Center for Advanced Materials, Vol. I, LBL informal report PUB-5084 (1983).
 41. H. Wiedemann, private communication (1978).
 42. J. Kouptsidis and A.G. Mathewson, Deutsches Elektronen-Synchrotron internal report DESY 76/49 (1976).
 43. A.G. Mathewson, G. Horikoshi and H. Mizuno, National Laboratory for High Energy Physics KEK (Japan) report KEK-78-9 (1978).
 44. J.C. Schuchman, BNL NSLS report BNL-32167 (1982).
 45. J. LeDuff, Laboratoire de l'Accelérateur Lineaire (Orsay) report LAL 82/42 (1982).
 46. J. Harris and R. Stege, private communication (1983).
 47. E. Rowe, private communication (1983).
 48. NSLS Design Handbook, Chapt. 3, p. 37, Table 3.3-I, unpublished (1978).
 49. W. Foyt, private communication (1982).
 50. E. Rowe, private communication (1983).

TABLE II. Parameters of L=53.96m, h=90, 15° Dipole Lattice

	A. 5/29-16	B. 5/29-20	C. 5/29-23	D. 6/1-3	E. 6/1-4	F. 6/1-5	G. 6/1-6
$g_{QF1} (m^{-2})$	1.87364	1.84578	1.78643	4.15900	4.12846	4.08471	4.95437
$g_{QD1} (m^{-2})$	-2.77610	-2.56596	-2.18089	-3.29873	-2.87862	-2.72317	-2.37643
$g_{QF2} (m^{-2})$	2.51201	2.52811	2.57074	3.58612	3.41876	3.12434	2.85113
$g_{QD2} (m^{-2})$	1.25049	1.24557	1.22020	-.35989	0.11203	0.71130	-1.11724
$g_{QF3} (m^{-2})$							
v_x	(3.25)	(3.25)	(3.25)	(5.25)	(5.25)	(5.25)	(5.25)
v_y	(3.25)	(3.25)	(3.25)	(3.25)	(3.25)	(3.25)	(3.25)
$\beta_x^* (m)$	11.59	10.95	9.77	.29	.29	.28	(.5)
$\beta_y^* (m)$	.79	.71	.02	1.24	1.35	.06	1.71
$\eta_x^* (m)$	(0)	(0)	(0)	(0)	(0)	(0)	-1.0
$\beta_x (m)$	11.87	10.96	10.10	11.72	11.49	12.24	17.12
$\beta_y (m)$	29.14	23.30	19.98	47.74	42.56	36.02	53.80
$\eta_x (m)$	1.35	1.32	1.26	1.28	1.23	1.21	4.90
ξ_x^o	-3.77	-3.55	-3.16				-5.43
ξ_y^o	-11.93	-9.81	-19.50				-18.54
$U_o^{(1.4)} (keV)$	133.4	641.6	2166.0				
$U_o^{(.1)} (keV)$			.056				.017
α_p	.072	.070	.067	.069	.067	.068	.27
$\Psi_k/2\pi$	.270	.266	.256	.27	.27	.27	.40
$\beta_x^k (m)$	1.53	1.54	1.58	1.84	1.87	2.05	.31
$\tau_x^{(1.4)} (ms)$	3.75	.78	.23				
$\tau_x^{(.1)} (ms)$			634.5				215
$\sigma_x^{*(1.4)} (mm)$	1.86	1.02	1.71				
$\sigma_x^{*(.1)} (mm)$			.12				.10
$\sigma_z^{(1.4)} (mm)$	11.20	21.4	47.0				
$\sigma_z^{(.1)} (mm)$			.59				
$\frac{\sigma_E}{E} \times 10^4 (1.4)$	7.6	14.4	21.7				
$\frac{\sigma_E}{E} \times 10^4 (0.1)$			1.5				

C MXI LATTICE 90TH HARMONIC C=53.96264244M
 C 1.4GEV 4-SUPERPERIOD RING, 80KG WIGGLER, 24 15-DEG DIPOLES
 C

NUM	CONV	NSTP	ANL	PRT					
	8	5	1	0					
BBX *	BC		BB		BWPH		BWMH		
	0.		0.		0.		0.		
	.815050843		.611288132		.04		.04		
	15.		15.		3.92613545		-3.9261354		
QUA *	QF1		QD1		QF2		QD2		
	-1.87354		2.82441		-2.50802		-1.25161		
	.24		.24		.24		.12		
DRF *	D1		D2		D3		D4		DW
	1.29770320		.15		.46		.35		.02
EDG *	EB		EBB		EWP		EWM		
	7.5		7.5		3.92613545		-3.9261354		
RPL.	EBE	EB	BC	EB					
	EBBE	EBB	BB	EBB					
	WPHE	BWPH	EWP						
	EWP	EWP	BWPH						
	WMHE	BWMH	EWM						
	EWMH	EWM	BWMH						
	WIG	WPHE	DW	EWMH	WMHE	DW	EWP	WPHE	DW
		DW	EWP	WPHE	DW	EWMH			
FIT	K								
CEL H	DWIG	D1	QF1	D2	EBE	D3	QD1	D2	EBBE
	D4	QF2	D3	EBBE	D2	QD2			K
VAR	QF1	QD1	QF2	QD2					
FUN	BEG	AX	AY	BX	BY	EX	EY	EXP	EYP
		0.	0.	0.	0.	1.	0.	0.	0.
		0.	0.	5.	1.	0.	0.	0.	0.
FUN	FIT	XNU							
		0.							
		.25							
FUN	END	XNU	YNU						
		1.	1.						
		.4062	.4062						
PAR	P	A	V	H	NBML				
	1.4	1.	2.4	90	8				
FIN

TABLE III. INPUT DATA FOR PROGRAM
 COMFORTS FOR SOLUTION II A 5/29-16

*VALUE OF MACHINE FUNCTIONS AT THE EXIT OF EACH ELEMENT:

ELEM	SCM	PHI(DEG)	K ₁₁ /M ₂₁	NUX	NUY	EX(M)	EY(M)	AX	AY	EX'	EY'
REG	0.0000	0.0000	0.000000	0.00000	0.00000	0.00000	0.00000	0.00000	0.00000	0.00000	0.000
PHI0	0.5000	0.0000	0.000000	0.00686	0.09021	0.00000	0.00000	-0.04314	-0.63649	0.00000	0.000
U1	1.7977	0.0000	0.000000	0.02449	0.18443	0.00000	0.00000	-0.15511	-2.28846	0.00000	0.000
QF1	2.0377	0.0000	-1.873641	0.02782	0.19122	0.00000	0.00000	4.81919	-5.49357	0.00000	0.000
D2	2.1877	0.0000	0.000000	0.03021	0.19439	0.00000	0.00000	4.47983	-6.19132	0.00000	0.000
EB	2.1877	7.5000	0.000000	0.03021	0.19439	0.00000	0.00000	4.08603	-5.83375	0.00000	0.000
BC	3.0028	15.0000	0.000000	0.05255	0.20420	0.10608	0.00000	2.80743	-9.21065	0.25882	0.000
EB	3.0028	7.5000	0.000000	0.05255	0.20420	0.10608	0.00000	2.65680	-8.33455	0.26331	0.000
D3	3.4628	0.0000	0.000000	0.08345	0.20718	0.22770	0.00000	1.61607	-9.89912	0.26331	0.000
QU1	3.7028	0.0000	2.776097	0.11266	0.20846	0.31050	0.00000	0.37763	-9.75898	0.40008	0.000
D2	3.8528	0.0000	0.000000	0.13452	0.20932	0.37651	0.00000	0.22753	9.26360	0.44008	0.000
EB	3.8528	7.5000	0.000000	0.13452	0.20932	0.37651	0.00000	0.16827	10.74576	0.46131	0.000
BB	4.4640	15.0000	0.000000	0.22754	0.21425	1.14152	0.00000	-0.31284	5.03730	0.66268	0.000
EB	4.4640	7.5000	0.000000	0.22754	0.21425	1.14152	0.00000	-0.37720	8.87207	0.70339	0.000
D4	4.8140	0.0000	0.000000	0.27022	0.21901	0.96822	0.00000	-0.72743	6.98762	0.70339	0.000
K	4.8140	0.0000	0.000000	0.27022	0.21901	0.96822	0.00000	-1.07767	5.98762	0.70339	0.000
B4	5.1640	0.0000	0.000000	0.30108	0.22719	1.21440	0.00000	0.18194	5.10317	0.70339	0.000
QF2	5.4040	0.0000	-2.512012	0.31753	0.23664	1.29237	0.00000	0.18194	1.90337	-0.06150	0.000
D3	5.8640	0.0000	0.000000	0.34892	0.26513	1.26408	0.00000	-0.01724	1.28117	-0.06150	0.000
EB	5.8640	7.5000	0.000000	0.34892	0.26513	1.26408	0.00000	-0.14750	1.39127	0.00977	0.000
BB	6.4753	15.0000	0.000000	0.38946	0.34571	1.30647	0.00000	-0.13857	0.47233	0.12814	0.000
EB	6.4753	7.5000	0.000000	0.38946	0.34571	1.30647	0.00000	-0.27892	0.51820	0.20180	0.000
D2	6.6253	0.0000	0.000000	0.49848	0.37771	1.33674	0.00000	-0.34387	0.28433	0.20180	0.000
QU2	6.7453	0.0000	-1.250490	0.40620	0.40620	1.34887	0.00000	0.00000	0.00000	0.00000	0.000

TABLE IV. CALCULATED BETATRON FUNCTIONS FROM PROGRAM COMFORTS
FOR SOLUTION II A 5/19-16, L=53.96 m, $\lambda=90^\circ$, 15° DIPOLES.

*MACHINE PARAMETERS:

NUX= 3.24961
 NUY= 3.24960
 BX*= 11.58986 (M)
 BY*= 0.78555 (M)
 ETAX*= 0.00000 (M)
 ETAY*= 0.00000 (M)

L= 53.96264 (M CIRCUM)
 IO=0.180000-06 (SEC/REV)
 (BL/L)/(DF/F)= 0.07194
 JX= 1.00575
 JY= 1.00000
 JF= 1.99425

BNX/(DE/E)=-.377460+01
 BNY/(DE/E)=-.119350+02
 BJX/(DE/E)=-.151770+02
 BJY/(DE/E)=0.000000+00
 BJE/(DE/E)=0.151770+02

*BEAM PARAMETERS:

E= 1.40000 (GeV)
 A= 1.00000 (CMUFL)
 TAU=0.375450-02 (SEC)
 SIGX(0)= 0.26328 (CM)
 SIGY(0)= 0.00000 (CM)

BRHO= 46.69896 (KG-M)
 IU=0.113470+00 (MeV/REV)
 TAU= 0.37760-02 (SEC)
 SIGX(A)= 0.18616 (CM)
 SIGY(A)= 0.04861 (CM)

SIRE= 0.00074 (DE/E)
 TAU=0.189350-02 (SEC)
 SIGX(I)= 0.18616 (CM)
 SIGY(I)= 0.04861 (CM)

*RF-RELATED PARAMETERS:

FRF/F0= 90
 PHIS=174.81195 (DEG)
 DE/E= (4.--)0.124130-01
 *** TAU= 100 LARGE ***

VRF=0.240000+01 (MeV)
 NUS=0.419990-01
 SIGZ=0.111860+01

FRF=0.500000+03 (MHZ)
 FS=0.233330+03 (MHZ)
 TAU=0.197430+32 (MIN)

TABLE V. CALCULATED PARAMETERS FROM PROGRAM COMFORTS

FOR SOLUTION II A 5/29-16, L=53.96 m, h=90, 15° DIPOLES.

TABLE VI. Parameters of the L=58.76m, h=98, 11.25° Dipole Lattices

	A. 5/24-1	B. 6/1-9	C. 5/26-1	D. 5/26-2	E. 5/24-4	F. 5/26-4	G. 5/26/11
$g_{QF1} (m^{-2})$	0.65902	0.94059	3.12421	3.59028	4.36722	4.91320	5.62073
$g_{QD1} (m^{-2})$	-2.74342	-2.62454	-3.39039	-3.55676	-4.67515	-3.71578	-3.83018
$g_{QF2} (m^{-2})$	3.73336	3.68575	4.77114	4.21461	1.16638	5.20274	4.55218
$g_{QD2} (m^{-2})$	-1.24726	-1.49245	-1.75813	-1.95343	-5.16879	-1.24817	-0.18811
$g_{QF3} (m^{-2})$	2.87698	3.08889	2.17921	4.05342	4.71748	0.75634	1.17242
v_x	(3.25)	(3.25)	(5.25)	(5.25)	(5.25)	(7.25)	(7.25)
v_y	(3.25)	(3.25)	(3.24)	(3.25)	(5.25)	(3.25)	(3.29)
$\beta_x^*(m)$	3.25	3.73	4.93	1.51	.12	.20	.50
$\beta_y^*(m)$	(.5)	(.5)	(1.0)	(1.0)	1.76	1.12	(1.00)
$\eta_x^*(m)$	(0)	(0)	(0)	(0)	-.12	.03	(0)
$\beta_x(m)$	20.04	13.86	5.67	5.37	43.35	18.33	31.37
$\beta_y(m)$	27.69	20.23	32.32	36.40	31.65	46.41	72.32
$\eta_x(m)$	1.10	1.17	.86	.90	5.69	.78	.86
ϵ_x^o	-7.35	-5.14	-6.96	-4.76			-24.14
ϵ_y^o	-11.53	-9.02	-14.89	-16.15			-34.53
$U_o^{(1.4)} (keV)$	136.5	644.7	136.5	136.5			136.5
$U_o^{(.1)} (keV)$		2336					
α_p	.053	.053	.052	.052	.144	.036	.043
$\Psi_k/2\pi$	.16	.16	.43	.37	.47	.68	.46
$\beta_x^k(m)$	15.26	10.77	4.79	1.56	.58	6.84	.17
$\tau_x^{(1.4)} (ms)$	4.01	.85	4.01	4.01			4.01
$\tau_x^{(.1)} (ms)$		2331.5					
$\sigma_x^{*(1.4)} (mm)$	1.75	.78	.75	.52			.42
$\sigma_x^{*(.1)} (mm)$		.056					
$\sigma_z^{(1.4)} (mm)$	10.07	19.40	9.26	10.00			9.09
$\sigma_z^{(.1)} (mm)$		.021					
$\frac{\sigma_E}{E} \times 10^4 (1.4)$	7.7	14.4	7.7	7.7			7.7
$\frac{\sigma_E}{E} \times 10^4 (0.1)$		1.0					
COLLER	OFF	3.926°	OFF	OFF	OFF	OFF	OFF

TABLE VII. Preliminary Cost Estimate of Medical X-Ray Source
(in thousands of dollars)

I.	Storage Ring	
A.	Magnet system (24 dipole, 28 quadrupole and 16 sextupole magnets)	\$ 652.8
B.	Magnet power supplies (1 dipole, 4 quadrupole, 2 sextupole)	276.7
C.	Vacuum System	630.0
D.	Computer control	529.8
E.	Shielding/Survey/Misc. (including cooling water and concrete pad of machine)	479.9
F.	Beam diagnostics (including security system, transverse and longitudinal feedback components)	181.0
G.	Ring RF system	<u>1,765.0</u>
	total capital	\$4,515.2
H.	Associated labor and misc.	641.7
I.	Eng. Design & Inspect. (EDI)	<u>1,061.0</u>
	ring sub total	\$6,217.9
J.	Contingency at 10%	<u>621.8</u>
	total for Storage Ring	\$6,839.7
II.	Pre-Injector (100 MeV Microtron)	\$ 443.0
	Microtron-to-ring transport system	<u>67.2</u>
	overall facility cost	\$7,349.9

1000

FIG. 1

FIG. 2

X-RAY INTENSITY AT $\theta = 0^\circ$
VS PHOTON ENERGY FOR VARIOUS
WIGGLERS AND BEAM ENERGIES

(ANGLE INTEGRATED IN VERTICAL PLANE)

10

9

8

7

6

5

4

3

2

1.0

9

8

7

6

5

4

3

2

1

0

0

1

2

3

4

5

6

7

8

9

10

FIG. 4

TOUSCHER INTEGRAL $\mathcal{I}$ VS. σ_p
FOR VARIOUS VALUES OF PARAMETER η

$$\mathcal{I} = \int_{\eta}^{\infty} \left\{ \frac{(1+3p^2)}{p\sqrt{1+p^2}} - \eta^2 G(p) \right\} F(p) dp$$

$$G(p) = \frac{p}{\sqrt{1+p^2}} - \eta \frac{(1+p^2)^{3/2}}{p^3} - \frac{2\sqrt{1+p^2}}{p} + \frac{(1+4p^2)}{p^3\sqrt{1+p^2}} \ln \left[\frac{\eta\sqrt{1+p^2}}{p} \right]$$

$$F(p) = \frac{1}{2\sqrt{\pi} \sigma_p} e^{-(p/\sigma_p)^2} \quad \sigma_p = \text{rms width of momentum distribution}$$

$$\eta \equiv \frac{\Delta p_m}{\gamma_0} \quad \Delta p_m = \text{maximum momentum acceptance}$$

p, σ_p AND η IN UNITS OF $m_0 c$

H. WIEDEMANN, SLAC REPORT PEP-27 (1973)

FIG. 6. ENERGY VARIATION OF STORAGE
RING PARAMETERS FOR $L=50.96\text{ m}$ $n=85$
MACHINE. 5/23-4

WIGGLERS ON AT STANDARD
EXCITATION (80 KG AT 1.4 GeV)

TRANSVERSE DAMPING TIME T_x (OR T_y) (msec) $\rightarrow$

WIDTH σ_E/E OF ENERGY DISTRIBUTION σ_0 ($\times 10^4$) $\rightarrow$

ENERGY LOSS PER ELECTRON PER TURN U_0 (keV) $\rightarrow$

ELECTRON BEAM ENERGY (GeV) $\rightarrow$

END

**DATE
FILMED
6/16/92**