PNL-SA--19533

DE93 009127

EXTREMELY HIGH RATE DEPOSITION OF
POLYMER MULTILAYER OPTICAL THIN
FILM MATERIALS

12/11/1983

COTI

J. D. Affinito

DISCLAIMER

Handout

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Prepared for
the U.S. Department of Energy
under Contract DE-AC06-76RLO 1830

Pacific Northwest Laboratory
Richland, Washington 99352

MASTER

cha
DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

EXECUTIVE SUMMARY

The following paper concerns a new and unique technology that has been developed for the vacuum deposition of polymer multilayer thin films. The intent, at Battelle's Pacific Northwest Laboratory, is to apply this technology to multilayer optical filters comprised of thousands of layers of either linear or non-linear optical materials. Application to non-linear optical materials alone is also anticipated. To date this, Polymer Multilayer, technology has only been commercialized for the production of polymer/aluminum electrical capacitors - where the polymer and evaporated aluminum are deposited on a rotating drum, in-line, in the same vacuum chamber, at pressures from 10^{-4} torr to 10^{-6} torr.

In the continuous web coating capacitor applications, the Polymer Multilayer technique is being used to deposit films at line speeds up to 750 linear feet per minute. The capacitor films are deposited in multilayer configurations from a few to more than 10,000 layers, with total stack thicknesses as great as 2 millimeters. Due to the low tech capacitor application, no attempts have yet been made to optimize layer to layer thickness uniformity. Nevertheless, at speed, individual layer thicknesses are controlled to roughly 2% uniformity in the range from a few hundred angstroms to more than two microns. Thicker layers, of a single material, may be deposited as two or more separate layers of the same material. Also, with some work, better uniformity is very likely attainable.

The current, Polymer Multilayer, technique involves the flash evaporation of an acrylic monomer onto a moving substrate. The monomer is subsequently cured by an electron beam. The types of acrylic polymers that have been deposited to date are very clear for wavelengths between $\sim .35 \mu\text{m}$ and $\sim 2.5 \mu\text{m}$. In this wavelength range, the polymers have extinction coefficients of $k \approx 10^{-7}$, while conventional optical materials only have $k \approx 10^{-4}$. Use of highly fluorinated acrylate monomers should extend the high transparency region at both ends of the wavelength range. The

technique has not yet been attempted in batch coating applications, although there is every reason to believe the technique will work every bit as well in batch coating applications as it does in web coating applications.

Preliminary optical modelling results indicate that Polymer Multilayer reflection filters will have two to three orders of magnitude higher, reflected, optical density than multilayer reflection filters comprised of conventional optical materials.

Non-linear optical Polymer Multilayer materials can also be deposited. There is ample literature concerning the attachment of optically non-linear functional groups to acrylic monomers of the type employed in the Polymer Multilayer technology. When polymerized, these modified monomers produce polymers with the same type of non-linear optical properties as possessed by the attached functional groups. As well, application of an electric field during the cross linking process can polarize, or "pole", the film to greatly enhance the non-linear optical properties.

"Poling" films with the Polymer Multilayer technique should offer great advantages over conventional approaches. Conventionally, a polymer material is heated above its glass transition temperature in the presence of an electric field. As the polymer softens, the polar groups partially align with the electric field. Maintaining the electric field as the polymer cools back down below the glass transition temperature helps the material to maintain some of the induced polarization when the electric field is removed. Polymer materials prepared in this way exhibit some of the largest non-linear optical properties in the literature. However, since the polymer is actually a solid throughout this conventional "poling" process, steric considerations make alignment difficult and incomplete. Furthermore, all reports are that the induced polarization decays, quite rapidly, over time (usually in weeks to months, with one report of two years). As the polarization decays, of course, the non-linear optical properties decay as well.

With the Polymer Multilayer technique, the polarization would be induced in the liquid material. As a liquid there is much more freedom for the molecules to properly orient with the electric field. With the liquid monomer properly oriented, or "poled", the cross linking of the monomer into the polymer will be initiated with the electric field maintaining the orientation throughout the cross linking process. In this way, the proper orientation of the polymer backbone and polar groups will be frozen in place. *The polarization should not decay over time in a polymer prepared in this fashion.*

It will be demonstrated that the potential optical performance of Polymer Multilayer filters is staggering compared to conventional multilayer filters. As well, the economics of implementing, and operating, the process appears considerably less costly than for conventional deposition technologies.

Battelle's Pacific Northwest Laboratory is well known for its accomplishments in multilayer optical filter technology - particularly large area optical filters. We also have strong programs in polymer materials development, both organic and inorganic. Less widely known is our strong track record of developing deposition processes and, successfully, transferring the technology into the manufacturing environment. Additionally, we now have personnel that have developed, and put into manufacturing production, the Polymer Multilayer technology as well as various optical multilayer web coating processes. We believe that this assembly of personnel and technology is perfectly suited to bringing linear and non-linear Polymer Multilayer optical filter technology to manufacturing production status for batch and wide area web applications.

TABLE OF CONTENTS

INTRODUCTION:	page 1
THE POLYMER MULTILAYER FILM DEPOSITION PROCESS:	page 3
The Monomer Evaporation Process:	page 5
UV Curing of Polymer Multilayer Films:	page 6
Economics of Polymer vs. Conventional Multilayer	
Deposition Processes:	page 7
NON-LINEAR OPTICAL MATERIALS AND POLYMER MULTILAYER	
TECHNOLOGY:	page 10
"Poled" Non-Linear Polymer Multilayer Materials:	page 10
Heterogeneous Non-Linear Polymer Multilayer Material:	page 11
Heterogeneous Non-Linear, "Poled", Polymer Multilayer Material: .	page 14
A LITTLE OPTICS BACKGROUND:	page 14
Two Media and One Boundary:	page 15
Three Media and Two Boundaries:	page 16
Multilayer Films:	page 18
n and k For Various Materials:	page 21
Thin Film Morphology:	page 23
Polymer vs. Conventional Interference Filter Performance:	page 24
General Considerations:	page 24
Specific Polymer Multilayer Filter Designs:	page 26
CONCLUSIONS:	page 34

INTRODUCTION:

This paper will highlight an exciting, and new, technique for the extremely high rate deposition of optical dielectric films. Presently, stacks of several to over 10,000 (0.05 μm to 4 μm thick) layers of these films are being successfully, and routinely, deposited in a commercial manufacturing process for electrical capacitor fabrication. The capacitor deposition takes place in vacuum and in-line with an Aluminum evaporation process in the same chamber. The result is alternating dielectric/aluminum layers. Dielectric only multilayer films have been deposited as well.

In the above mentioned manufacturing process, the dielectric material is deposited onto a rotating drum that has been coated with a soap solution release layer. The resultant multilayer stack is a "strap" that is roughly 3 meters long by 25 cm wide and, depending on the individual layer thicknesses, has been as much as 2 mm thick. There is no physical reason to limit the dimensions to those given above other than convenience for post deposition processing. The width and length can easily be scaled up. Thicker films are only a matter of adding more layers. The linear speed of the drum surface is 500 feet per minute. The speed is limited by the required aluminum thickness, necessary sheet resistance, and aluminum deposition rate - speed is not limited by the dielectric deposition rate. The ultimate, linear, speed attainable for the dielectric deposition process has not yet been determined. Dielectric deposition speeds as high as 750 feet per minute have been used successfully though.

The strap can be removed from the drum as a free standing multilayer stack. If a flexible substrate is attached to the drum prior to deposition, without the release layer, the multilayer/substrate combination can be removed. Attention has not been directed toward improving the dielectric film thickness uniformity because of the low tech application. However, thickness uniformity is within $\sim 2\%$ according to Scanning Electron Micrograph photographs.

The extension of this technique to a continuous web, roll coating, process is obvious.

This new method involves the flash evaporation (in a vacuum chamber) of an acrylic monomer on to a moving substrate. The monomer is subsequently "cured" by an electron beam. The term "cure" means that the individual monomer molecules chemically cross link to form a polymer. These acrylic polymers, the "space age" plastics of the 1970's, are the dielectric film material.

Polymer Multilayer films have high potential in many optical filter applications. Specific applications include; high reflectance laser mirrors; high reflectance, multi-line, RUGATE laser mirrors; visible transparent/IR and microwave reflecting coatings for IR/RCS treatments of canopies and radomes; single line, and multi-line, laser goggles; a very long list of commercial, optical filter, applications; and all of the above where the thin film materials have non-linear optical properties as well.

Various implementations of the deposition process will be reviewed. In particular, the possible use of ultra-violet (UV) light, instead of electron beams, to cure the monomer will be discussed. Of the many and varied potential uses for these films, the applications to multilayer optical filters will be the main focus. More particularly, the application to large area optical filters (1 to 6 foot wide webs by thousands of feet long) will be emphasized. Consequently, some comparisons of deposition techniques, thin film material properties, optical performance, and deposition rates between the polymer method and standard optical film deposition methods will be in order. Some particular Polymer Multilayer optical filter designs, performances, and applications will be given as well.

Also to be discussed is the potential for using monomers with non-linear optical properties. There is ample literature that discusses the attachment of optically non-linear functional groups to the types of monomers that this, monomer flash evaporation, technique uses. As well, Battelle staff have experience, and process patents, in the synthesis of appropriate monomers with optically non-linear groups attached. The polymers, created from the monomers with non-linear optical groups attached, demonstrate the same non-linear properties as the non-linear group alone. It is well known that alignment of polar groups leads to non-linear optical

properties. With the Polymer Multilayer technique, the material can be "poled" by the application of an electric field during the cross linking process. Also, co-deposition of polymer and metal, giving metal inclusions in a polymer matrix, enhances any non-linear optical performance that the matrix alone may provide. Battelle has personnel experienced in vacuum deposition of similar metal inclusion/ceramic matrix composite materials. Combining the above experience with our polymer vacuum deposition experience should allow for creating new optically non-linear metal/polymer composite materials. The potential definitely exists for high rate deposition of optical filters composed of thin films of optically non-linear materials.

THE POLYMER MULTILAYER FILM DEPOSITION PROCESS:

Figure 1 shows the geometry of a system used to deposit alternating layers of polymer and aluminum for the capacitor application discussed above. Figure 2 is one of many possible web coating configurations for the polymer film process.

One possible filter type, that could be made with the configuration of figure 2, is a high visible transmission/high IR reflection device. Such a filter could be of the dielectric/metal/dielectric variety. For such a filter, the metal could be sputter deposited silver or gold. Applications of such a filter would be IR/RCS treatment of an aircraft canopy, while maintaining greater than 90% visible transmission, or something as low tech as winter window film. The window film product is being commercially produced by The Southwall Corporation under the trade name "Heat Mirror". At Southwall they deposit ITO/Ag/ITO "Heat Mirror" films at ~6 feet per minute. Their line speed is limited by the ITO rate. The Ag rate can easily be brought to several hundred feet per minute. Using polymer dielectrics, for the "Heat Mirror" or canopy RCS applications, the line speed could easily be pushed to the Ag rate limit.

It is not necessary to include the metallization steps shown in figures 1 and 2. Polymer only multilayers can be deposited as easily. Further, there is not a 1 layer/1 cure gun restriction.

Figure 1. Schematic of deposition system used to deposit polymer/aluminum capacitor material.

The cure restriction is based upon electron beam voltage and film thickness (or UV dose and film thickness). For a 10 kV accelerating potential, depending on the particular monomer, thicknesses from $\sim 2 \rightarrow \sim 4 \mu\text{m}$ can be cured. For an optical quarter wave at $5000 \text{ \AA}$ ($\sim 833 \text{ \AA}$ of $n=1.5$ polymer) this corresponds to $\sim 24 \rightarrow \sim 48$ layers. Many different layers could be deposited in sequence and then cured all at once, instead of curing after each layer. Regardless of the curing sequence, each layer cross links with the layers on either side of it to produce excellent inter-layer adhesion. It follows that films thicker than the maximum single cure thickness are easily deposited as multiple layers of the same monomer.

Figure 2. Schematic of possible configuration of deposition system to make polymer/metal/polymer multilayers.

The Monomer Evaporation Process:

The technique used to evaporate the monomer is really quite simple. Monomer fluid is sprayed into a very hot tube that has a very hot, pressure baffling, expansion nozzle on one end. By very hot, it is meant that the tube is hot enough to instantly vaporize the monomer spray, yet not hot enough to crack and/or polymerize the monomer on contact. Under these conditions, the monomer evaporates as quickly as it is introduced into the tube - there is no pool of liquid in the tube. The baffles in the tube/nozzle system serve to build the pressure (of the molecular gas of monomer molecules) in the nozzle expansion chamber. Building the pressure serves to make the molecular gas stream, exiting the slit in the nozzle, more uniform.

The flow of monomer, into the hot tube, is controlled with a precision metering pump. The monomer spray can be created with an ultrasonic atomizer, fuel injector, or by dripping onto a high speed rotating disc. However, 2% uniformity has been attained on capacitor runs of several thousand layers, by just allowing the precision metered monomer flow to drip into the hot tube.

UV Curing of Polymer Multilayer Films:

Remarkably, the capacitor manufacturing process has, to date, been the only application attempted with this Polymer Multilayer technology. When this technology was developed, more than 10 years ago, UV curing technology was still in its infancy. At that time, attempts to UV cure the polymer could not attain the high line speeds that electron beam curing permitted (800→1000 feet per minute), and the market costs for capacitors demanded the highest possible line speed. At the present time, line speeds for UV cure systems are still much lower than for electron beam systems. However, line speeds of 400→500 feet per minute are regularly reported with UV systems. As well, these reported high speed applications are for much greater than 1 μm thick layers. The much thinner optical quarter wave layers would be expected to cure much faster. Consequently, it now appears likely that, with proper UV initiators added to the monomer and the newer high intensity sources, UV curing for optical film applications is very practical. There are three reasons why UV curing is preferable to electron beam curing:

- 1) The initial cost of the electron gun and power supply is higher than for a UV cure system.
- 2) The higher energies associated with the electron beam can cause fragmentation of the polymer chains. This can lead to a degradation in many physical properties.
- 3) For many hundreds of layers, electron beam cured polymer only films can build up significant charge. This tends to cause localized distortions that degrade optical clarity (for a few hundred layers this does not seem to be a problem).

The second and third reasons are the ones of main concern since, compared to competing technologies, the electron beam cured Polymer Multilayer film technology is comparable in initial capital cost. Either polymer cure technology should be far less expensive to operate than conventional web coaters.

The lower rate of UV, compared to electron beam, curing is the price paid to solve the problem of polymer chain fragmentation mentioned as the second reason above. While UV light is not energetic enough to cause fragmentation damage, it is also not energetic enough to directly initiate high rate polymerization. An intermediate, the photoinitiator, is required to cause high rate polymerization in the presence of UV light. The extra time needed for the intermediate chemical reaction is the reason why UV cure rates are lower than electron beam cure rates. However, today's UV cure speeds, of 400 to 500 feet per minute, far exceed the highest attainable rates for any conventional optical film deposition process. Therefore, it would be very useful to revisit the use of UV curing at this time.

Economics of Polymer vs. Conventional Multilayer Deposition Processes:

The main difference between a conventional web coater and a Polymer Multilayer web coater is the replacement of the sputtering, or evaporation, sources with monomer evaporators and cure systems. In terms of initial hardware investment there is not much "real" cost difference. Most likely though, the big names in the roll coater construction business would charge much more for the Polymer Multilayer coater. This is understandable since, to them, it is "new" technology - they have never built or operated one.

The operational costs should be much lower for the polymer system than for the conventional roll coaters. Compare several hundred to ~1000 feet per minute for polymer coatings to 1 to 20 feet per minute for conventional dielectric coatings. It is true that some of the newer metallizers can flash evaporate aluminum at 2000→3000 feet per minute, depending on thickness. However, they can not deposit optical grade dielectric materials, of useable thicknesses, at even 50 feet per minute - usually much less than 25 feet per minute.

What value can be placed on being able to increase the rate of a manufacturing process more than 100 fold? Particularly a process where there are such large initial capital and ongoing maintenance costs as with vacuum roll coating.

The material costs are much lower for polymer films than for conventional dielectric films as well. For instance, the per pound costs for optical grades of indium oxide, magnesium fluoride, or silicon dioxide are ~\$500, ~\$700, and ~\$500, respectively. Many acrylic monomers, unlike standard optical grade materials, are commodities. With, in some cases very few, additives, acrylic monomers are polymerized into such things as floor wax, disposable diapers, or the smooth coating on many types of paper. HDODA (Hexane Diol DiAcrylate, $n \approx 1.5$ for the cross linked polymer) costs ~\$3 per pound. For monomers containing only carbon, hydrogen, and oxygen, prices are in the \$3-\$10 per pound range. Most of the polymers, created from these monomers, have $1.45 < n < 1.55$. Adding fluorine atoms to the monomer molecules can lower the refractive index to the 1.31 range, while adding bromine atoms can raise n to the 1.7 range.

The fluorinated, and brominated, monomers are not in mass production at the present time. The fully fluorinated monomers are commercially available from the 3M company though. The 3M monomers, which are not mass produced, are comparable in price to conventional optical grade starting materials. In addition, Battelle has a great deal of expertise, including several patents, in synthesizing the appropriate kinds halogenated acrylate monomers. Therefore, obtaining larger than ~0.1 refractive index variations is something that Battelle can readily address.

THICKNESS	REFRACTIVE INDEX	d_{33}	d_{31}	d_{31}/d_{33}
(μm)	$\lambda=0.8\mu\text{m}$	(10^{-9}esu)	(10^{-9}esu)	
1.8	1.58	51	17	1/3

page 9

NON-LINEAR OPTICAL MATERIALS AND POLYMER MULTILAYER TECHNOLOGY:

"Poled" Non-Linear Polymer Multilayer Materials:

Market analysts believe the non-linear materials/devices industry development is mirroring the history of the semiconductor industry - only shifted 30 years in time. They believe the non-linear optics industry is currently set for explosive growth, much like the expansion of the semiconductor industry since 1960. The primary road block to this expansion is obtaining materials with the proper physical properties.

Organic materials give some of the highest non-linear optical coefficients measured to date. However, there are problems attendant to processing these materials into a form useful for devices. Many of the non-linear molecules have been incorporated into polymer materials by attachment, as side chains, to the backbone monomer molecules that form polymers. However, for these non-linear polymer materials to exhibit useful non-linear optical properties they must be "poled". An example of such a "poled" side chain polymer, with non-linear optical properties, is shown in figure 3. Unfortunately, the non-linear optical properties of, conventionally, "poled" materials decay over time.

Conventionally, "poling" a polymer material is accomplished as follows. A polymer material is heated above its glass transition temperature in the presence of an electric field. As the polymer softens, the polar groups partially align with the electric field. Maintaining the electric field as the polymer cools back down below the glass transition temperature helps the material to maintain some of the induced polarization when the electric field is removed. This, semi-permanent, induced polarization insures that the molecular structure has no inversion symmetry. Polymer materials prepared in this way exhibit some of the largest non-linear optical properties in the literature. However, since the polymer is actually a solid throughout this conventional "poling" process, steric considerations make alignment difficult and incomplete.

Furthermore, all reports are that the induced polarization decays, quite rapidly, over time (usually in weeks to months, with one report of two years). This is because the various molecular groups in the polymer matrix relax back to the orientations they had prior to being re-oriented by the electric field. Because the "poling" occurred when the polymer was a solid, the basic structure of the polymer matrix could not have been radically altered. Therefore, the "pre-poling" configuration was the minimum energy orientation that the polymer cross linked into initially - and the backbone remains largely in that orientation even after "poling". Therefore, the depolarizing fields, due to the induced polarization itself, act to return the material to the initial, non-polarized, state. As the polarization decays, of course, the non-linear optical properties decay as well.

With the Polymer Multilayer technique, the polarization would be induced in the liquid material. As a liquid there is much more freedom for the, backbone monomer, molecules to properly orient with the electric field. With the liquid monomer molecules properly oriented, or "poled", the cross linking of the monomer into the polymer will be initiated while the electric field maintains the orientation throughout the cross linking process. In this way, the proper orientation of the polar groups, and the polymer backbone, should be frozen in place. **The polarization should not decay over time in a polymer prepared in this fashion.**

The potential for permanently non-linear "poled" polymers with the Polymer Multilayer technology is very important for the industry.

Heterogeneous Non-Linear Polymer Multilayer Material:

In linear optics, it is well known that enhancements of the dielectric constant of a material can be obtained by the inclusion of small particles of another material into the bulk matrix of the original material. The enhancement is due to the polarization of the included particle, and the cavity surrounding it, by external electric fields (i.e. light).

To demonstrate this enhancement effect, an extension of the linear optical enhancement to the non-linear regime will be given. This will be a scalar treatment and will not take account of the vector nature of the electromagnetic field of the incident light. However, the essential elements of the effect will become clear, and the extension to vector fields is straight forward (it just takes a lot more space to write down the results). With the aforementioned caveats, for particles of dielectric constant ϵ_i , embedded in a matrix of material of dielectric constant ϵ_m , one finds the effective dielectric constant of the composite mixture, ϵ_{eff} , to be given as

$$\epsilon_{eff} = \epsilon_m \left[1 + f \frac{(\epsilon_i - \epsilon_m)}{L\epsilon_i + (1-L)\epsilon_m - fL(\epsilon_i - \epsilon_m)} \right]$$

or

$$\epsilon_{eff} = \epsilon_m + \epsilon_m \left[f \frac{(\epsilon_i - \epsilon_m)}{L\epsilon_i + (1-L)\epsilon_m - fL(\epsilon_i - \epsilon_m)} \right] \quad (\text{eq 1})$$

where f is the volume fraction of included particles and L is the geometry dependent depolarization factor for the particles.

$$\text{If } \epsilon_m = (\epsilon_{m0} + \chi_m^{(2)}|E| + \chi_m^{(3)}|E|^2) \text{ with } \epsilon_i = (\epsilon_{i0} + \chi_i^{(2)}|E| + \chi_i^{(3)}|E|^2)$$

where $|E|$ is the magnitude of the electric field and the $\chi^{(j)}$ are the j^{th} order susceptibilities, then

$$\epsilon_{eff} = \left(\epsilon_{m0} + \chi_m^{(2)}|E| + \chi_m^{(3)}|E|^2 \right) +$$

$$\left(\epsilon_{m0} + \chi_m^{(2)}|E| + \chi_m^{(3)}|E|^2 \right) \times$$

$$f \frac{(\epsilon_i - \epsilon_m) + (\chi_i^{(2)} - \chi_m^{(2)})|E| + (\chi_i^{(3)} - \chi_m^{(3)})|E|^2}{[L\epsilon_i + (1-L)\epsilon_m - fL(\epsilon_i - \epsilon_m)] + [L\chi_i^{(2)} + (1-L)\chi_m^{(2)} - Lf(\chi_i^{(2)} - \chi_m^{(2)})]|E| + [L\chi_i^{(3)} + (1-L)\chi_m^{(3)} - Lf(\chi_i^{(3)} - \chi_m^{(3)})]|E|^2}$$

(eq 2)

In equation 2, the subscripts _m and _i again refer to the matrix and inclusion materials respectively.

Note that, in either of equations 1 or 2, the effective dielectric constant is the dielectric constant of the matrix material (including higher order susceptibilities) plus the dielectric constant of the matrix material (including higher order susceptibilities) multiplied by another term. This other term is a function of the volume fraction of the inclusion particles, the dielectric constant (including higher order susceptibilities) of the matrix material, the dielectric constant (including higher order susceptibilities) of the inclusion material, and the shape of the inclusion particles. Therefore, any non-linear optical properties of the matrix material can be enhanced, as shown in equation 2, by the inclusion of particles of another material. Also note that the inclusion material need not have any non-linear properties of its own. Calculations have been performed[†] that indicate that a polystyrene matrix containing 2%, by volume, of Al inclusions, would have its phase conjugate reflectivity increased by a factor of $\sim 6 \times 10^5$!! Similar effects have been demonstrated, by measurements, for CdS_xSe_{1-x} doped glasses^{††}.

[†]A.E. Neeves and M.H. Birnboim in the 1988 TECHNICAL DIGEST SERIES-VOLUME 9, on Non-Linear Optical Properties of Materials, August 22-25, Troy, NY. pages 219-222.

^{††}J. Yumoto, S. Fukushima, and K. Kubodera, Opt. Lett. 12, 832 (1987).

At Battelle's Pacific Northwest Laboratory, we have personnel with experience in co-deposition of metallic inclusions in a ceramic matrix with magnetron sputtering techniques. Part of the work dealt with studying the, observed, optical behaviour predicted by equation 1. We are confident that we can combine this experience with our Polymer Multilayer experience to place metallic inclusions within a polymer matrix.

Heterogeneous Non-Linear, "Poled", Polymer Multilayer Material:

It is a natural evolution to combine the advantages of the above two techniques in a single material. The matrix material can be a "poled" Polymer Multilayer polymer with co-deposited metallic, ceramic, or semiconductive inclusions. Potentially, some very large optical nonlinearities could result.

A LITTLE OPTICS BACKGROUND:

The following sections are likely to be very familiar. They are included because they precisely highlight the advantages, and disadvantages, of using polymer thin films as opposed to conventional dielectric films in optical interference filters.

Optical interference filters, by definition, obtain performance from the linear superposition of (i.e. interference between) multiple reflected light waves. These multiple reflections are usually within a multilayered stack of materials in thin film form. Mechanical/operational considerations usually dictate that the multilayer stack be supported on a substrate of some kind. Optical performance does not require the substrate though and may be obtained with free standing multilayer structures.

Two Media and One Boundary:

Optical reflections do not occur, when light passes from one medium to another, unless the refractive indices (n_1 and n_2) and/or the extinction coefficients (k_1 and k_2) of the two media are different. The larger the differences ($\delta_n = n_2 - n_1$ or $\delta_k = k_2 - k_1$) the larger the reflection will be at the interface between the two materials. By the above definition, interference filter performance requires that at least 2 different refractive index and/or extinction coefficient materials be incorporated in the multilayer stack design.

As the light travels within the individual layers of the multilayer structure, the materials absorb energy from the light all along the path (the absorption analog of refractive index is the extinction coefficient, k). The degree of attenuation of the light is given as

$$E = E_0 e^{-\left(\frac{4\pi}{\lambda} k d\right)}, \quad \text{where } \lambda = \frac{\lambda_0}{n}. \quad (\text{eq 3})$$

In equation 3, E_0 is the light intensity at position 0, E is the light intensity after traveling a distance d (from 0) through a material of refractive index n and extinction coefficient k , and λ is the wavelength of the light in the material. Note that λ is shorter than λ_0 , the free space wavelength, by the factor $1/n$. Accordingly, one could re-write equation 3 as

$$E = E_0 e^{-\left(\frac{4\pi}{\lambda_0} k n d\right)}. \quad (\text{eq 4})$$

In equation 4, the "physical path length", d , of the light has been replaced by the "optical path length", nd , and the free space wavelength is used. Either of equations 3 or 4 is valid. Two points are of interest though. First, the number of wavelengths the light wave travels in a material, for the same "physical path length", becomes greater as the refractive index of the

material increases. Second, the light absorption, per wavelength travelled in the material, becomes greater as the extinction coefficient increases.

When light, at normal incidence, crosses a boundary between two media, of refractive indices n_1 and n_2 with extinction coefficients k_1 and k_2 , the power reflectance is given as

$$R = \left(\frac{N_2 - N_1}{N_2 + N_1} \right) \left(\frac{N_2 - N_1}{N_2 + N_1} \right)^* , \quad (\text{eq 5})$$

where the $N_j = (n_j + ik_j)$ are the complex refractive indices of the two materials, i is the square root of -1 , and $*$ denotes the complex conjugate. Note that R is indeed larger for greater δ_n and/or δ_k .

Three Media and Two Boundaries:

If a thin film of thickness d is placed between two semi-infinite media, the reflection and transmission of light at the boundary is more complicated than it was in the preceding discussion with no film present. With the thin film between the two media:

- 1) Incident light is partially reflected from the interface between medium 1 and the film, and partially transmitted into the film.
- 2) The transmitted light travels through the film and is partially reflected at the second interface, and partially transmitted into the second medium.
- 3) The reflected light travels back through the film to be partially reflected from the first interface, again, and be partially transmitted into medium 1.
- 4) The reflected light travels back through the film and is partially reflected at the second interface, and

partially transmitted into the second medium.

The above process is illustrated in figure 4, with $k=0$ for the film. With $k=0$, steps 3 and 4 will repeat until every last photon of the incoming light is either reflected back into medium 1 or transmitted to medium 2. The total light intensity (E) will be less on each pass through the film. The reduction will be due to the transmission loss at each reflection. The fraction of the light that will be transmitted, and the fraction that will be reflected, is determined by the relative magnitudes of the refractive indices of the 3 materials - and the thickness of the film and the wavelength of the light. Plotted against λ , R and T (transmittance)

are oscillatory functions whose sum, at any given wavelength, equals 1 ($R+T=1$). The maxima in the reflection oscillations (and minima for transmission) occur when the optical thickness of the film, n_d , is an odd multiple of $\lambda_0/4$. The reflectance minima, and transmission maxima, occur when the optical thickness of the film is an even multiple of $\lambda_0/4$. These maxima and minima are due to

Figure 4. Multiple reflections within a single film separating 2 media.

constructive and destructive interference between the incident light and the multiple reflections. Manipulating this effect is the basis of all interference filter design.

If $k \neq 0$, for the film in figure 4, absorption losses occur on each pass through the film in addition to the transmission losses upon each reflection. This results in additional losses due to absorption and $R+T \neq 1$. The difference between $R+T$ and 1 is the fraction of the light absorbed in the film (A). **Since light is absorbed on each pass through the film according to the rule of equation 3, the total amount of light absorbed can be greater than would be absorbed on a single pass through the film.**

Multilayer Films:

There are many different types of dielectric only multilayer filters. Some give high reflection, or transmission, in one or more wavelength bands. Some give a high transmission notch in the center of a band of high reflection. The layer structures of several filters can be deposited over each other to produce different results in different wavelength bands. All of these types of filters have 4 things in common:

- 1) The band widths are proportional to δ_n .
- 2) The band widths are proportional to $1/\langle n \rangle$, where $\langle n \rangle$ is the average refractive index of all of the layers.
- 3) The shift in the wavelength of any design feature (i.e. R band center, T band center, etc) is given as

$$\lambda \sim \lambda_0 \sqrt{1 - \left(\frac{n_i}{\langle n \rangle} \sin \theta_i \right)^2}, \quad (\text{eq 6})$$

where n_i and θ_i are the refractive index and angle of incidence in the incident medium and λ_0 is λ at $\theta=0$.

- 4) The more absorption in the multilayer stack (i.e. the higher $\langle k \rangle$ is) the more poorly the filter performs the design function.

An important example of the effect of number 4 is in high reflectance filters like QWOT's or RUGATES. A QWOT is composed of a pair of layers that is repeated P times. At the design wavelength for high reflection, each of the layers has an optical thickness of $\lambda_0/4$. Consequently, the layer pair has a combined optical thickness of $\lambda_0/2$ at the design wavelength. In a RUGATE, instead of a pair of quarter wave layers the fundamental period is a refractive index profile that varies sinusoidally. The optical thickness of one full sine period is $\lambda_0/2$ and there are P periods. Both of these types of filters have 4 additional things in common:

- 1) For $k=0$, the transmitted and/or reflected optical density at the design wavelength is proportional to δ_n .
- 2) For $k=0$, the transmitted and/or reflected optical density at the design wavelength is proportional to $1/\langle n \rangle$.
- 3) For $k=0$, the transmitted and/or reflected optical density at the design wavelength is proportional to P .
- 4) For $k \neq 0$, as $\langle k \rangle$ increases for constant P , the reflected optical density decreases while the transmitted optical density remains unchanged.

This last statement means that, as $\langle k \rangle$ increases: R decreases; A increases; $R+A$ remains constant; and T remains constant. In such a filter, if attenuating transmitted light is all that matters the presence of some absorption in the thin film layer materials does not matter. If maximum reflection is required, the thin film layer materials must have minimum absorption. The concept of optical density, introduced above, is defined as

$$T_{od} = \log_{10} \left(\frac{1}{T} \right), \quad (\text{eq 7a})$$

and

$$R_{od} = \log_{10} \left(\frac{1}{1-R} \right), \quad (\text{eq 7b})$$

where T and R are the usual, fractional, Transmittance and Reflectance. Optical densities are used in plots to reveal differences in highly non-transmitting filters. If only R or T are plotted, most filters with less than 1 % transmission look the same - a flat topped peak. Optical Density is a logarithmic scale. When $\langle k \rangle = 0$ in high reflectance filters, transmittances of .1, .01, .001, .0001, ... , etc have $T_{od}=R_{od}$ values of 1, 2, 3, 4, ... , etc. However, if $\langle k \rangle \neq 0$, the interpretation for a QWOT reflection filter, with $T_{od}=10$ and $R_{od}=5$, is that 99.999% of the

incident light is reflected, 0.00000001% of the incident light is transmitted, and the rest of the incident light, 0.00099999%, is absorbed. As will be seen shortly, for very high powered lasers the difference between R_{OD} values of 4 and 6 can be critical. Reflectance plots, of equivalent filters with $R=99.99\%$ and $R=99.9999\%$, would appear identical whereas R_{OD} plots would clearly show the difference.

For a QWOT reflection filter, it can be shown that $\delta_R=(1-R)$, of a stack with $P=\infty$, is

$$\delta_R = \frac{2\pi\langle k \rangle}{\delta_n \langle n \rangle} \quad (\text{eq 8})$$

This indicates, precisely, the reflectance limitation imposed by a non-zero $\langle k \rangle$ for a QWOT reflection filter. This limiting reflectance can not be exceeded with even an ∞ number of layers.

In the visible spectrum, vacuum deposited SiO_2 typically can have $n \approx 1.5$ and $k \approx 10^{-4}$. By equation 8, this implies that the maximum possible reflectance of a QWOT, with $\delta_n=.2$ and $\langle n \rangle$ and $\langle k \rangle$ like vacuum deposited SiO_2 , is $\sim 99.79\%!!$ Further, for $P = 10, 15, 20, 30, 40$, and 50 , $R \approx 75.4\%, 92.5\%, 97.6\%, 99.4\%, 99.52\%$, and 99.53% respectively. If $k=0$, then for $P = 25, 30, 40$, and 50 , one finds $R \approx 99.5\%, 99.9\%, 99.99\%$, and 99.999% respectively.

For high power laser reflectors, the above example implies that controlling absorption is extremely important. For $P=50$, both cases transmit $\sim 0.0001\%$ of the light (i.e. ~ 1 watt from a 1 megawatt laser). With $\langle k \rangle = 10^{-4}$, one finds $\sim .47\%$ of the light is absorbed while no light is absorbed with $\langle k \rangle = 0$. For a 1 megawatt laser, 0.47% of the power is 4.7 kilowatts! This would, no doubt, burn through the filter and permit transmission of the full megawatt. For $\langle k \rangle = 10^{-6}$, only $\sim .0047\%$ (47 watts) would be absorbed - a much better chance of survival results.

Also, for $P=50$ ($8.333 \mu\text{m}$ total thickness), equation 5 says that for a single pass through a material of $\langle n \rangle = 1.5$ and $\langle k \rangle = 10^{-4}$ the absorption should be $\sim 3.1\%$. This is more absorption than either of the 3 cases cited above. Even for $\langle k \rangle = 10^{-4}$, the effective number of free space wavelengths travelled, according to the absorption equation 5, is only ~ 3.75 (i.e. P is effectively only $\sim 7.5 \lambda/2$ pairs, instead of the actual 50). This is because, at the resonant wavelength of the filter, much of the light is reflected out of the filter before it can travel anywhere close to all the way through. The initial reflections are very important for getting the light reflected out of the film before absorption can occur. Implied in equation 3, and explicitly stated in equation 8, is the fact that the greater $\langle n \rangle$ and δ_n are the less absorption per unit of $\langle k \rangle$ there will be.

All of these arguments apply equally as well to RUGATE reflectors as to QWOT reflectors, with one exception. Due to the gradual changing of the index in a RUGATE filter, compared to the discontinuities in a QWOT filter, the reflection per period is less than for a QWOT. This means that more absorption will occur per unit of $\langle k \rangle$ for a RUGATE reflector than for a QWOT of equal $\langle n \rangle$, δ_n , and P . Therefore, a RUGATE reflector has a lower maximum attainable, theoretical as well as actual, reflectance and a higher absorption than a QWOT with the same δ_n , $\langle n \rangle$, P , and $\langle k \rangle$. Note though that the RUGATE filter will have lower electric field maxima within the filter. The lower electric fields are less likely to induce dielectric breakdown within the filter. Thus, the effects of higher absorption may be offset by the lower electric fields.

n and k For Various Materials:

Typical sputtered or evaporated, visible spectrum, optical dielectric films have $\sim 1.35 < n < \sim 2.5$, with $\sim .1 < k < \sim 10^{-4}$. Polymer Multilayer materials have $\sim 1.31 < n < \sim 1.7$. To date, no materials that have been deposited with the Polymer Multilayer technology have had k value measurements made. However, many materials in the same class as already deposited Polymer Multilayer materials have been characterized for k values. PMMA

(Poly Methyl Methacrylate), for instance, is a methacrylate material that is used for plastic optical elements. PMMA, and many similar materials, have been well characterized and, for wavelengths from $\sim 0.35 \mu\text{m}$ to $\sim 2.5 \mu\text{m}$, are found to have $k \approx 10^{-7}$. Therefore, for purposes of evaluating the relative performances of Polymer Multilayer and conventional interference filters, the following conservative parameters will be assumed.

	$\langle n \rangle$	δn	$\langle k \rangle$	Pmax
Polymer	1.31→1.7	0→.3	$\sim 10^{-6}$	~ 5000
Conventional	1.35→2.5	0→1.2	$\sim 10^{-4}$	~ 40

Due to the ionic nature of the conventional, vacuum deposited materials, co-deposition of different materials, to attain an intermediate index, leads to added absorption. This makes it preferable to stick with the discrete set of indices of the pure materials.

Due to the molecular nature of the bonding, monomers can be mixed, evaporated, and cross linked with no additional absorption introduced. Therefore, any index between ~ 1.31 and ~ 1.7 could be reached with blends of only two types of monomers. As well, as discussed earlier, functional groups with non-linear optical properties may be attached to all, or some, of the monomer molecules. The resultant polymer would have non-linear optical properties in proportion to the fraction of monomeric units that had optically non-linear functional groups attached. Figure 3 showed a case where an optically non-linear functional group was attached to a methacrylate monomer. At Battelle, we have experience in the synthesis of the kinds of monomers illustrated in figure 3. Another type of optically non-linear polymer film that we can deposit is metallic inclusions in a polymer matrix. This approach, while giving better non-linear performance than a non-linear polymer alone, will increase the effective linear extinction coefficient of the metal/polymer composite. Depending on the exact volume fraction and geometric properties of the composite, and the wavelength of interest, the "linear" extinction coefficients could range between 10^{-2} and 10^{-5} . Therefore, these optically non-linear composite

materials can still have "linear" extinction coefficients as low, or sometimes lower, than conventional optical thin film materials. They are, at least, visually transparent in any event.

Thin Film Morphology:

Another factor that affects power absorption, and interference filter performance, is the microstructure of the thin film material. Grain boundaries associated with micro-crystallites, are known to decrease the laser damage threshold due to enhanced absorption of light energy at the grain boundaries. Also, particulates on the substrate decrease the laser damage threshold in the same way. Both effects also decrease performance for low power applications by introducing incoherent scattering (i.e. reflections without a fixed phase relative to the multiple reflected light). The incoherently scattered light does not interfere, constructively or destructively, with the multiple reflections from the designed layers in any pre-determined way - it interferes randomly. For, say, a reflection filter, this randomly scattered light may pass through the filter. This creates two problems: it allows unwanted light through the filter; and, as seen above, more absorption occurs for a straight pass through the film than for the "properly" reflected light.

The conventional materials are all thin film forms of crystalline solids. Often times, the thin film forms are micro-crystalline in nature. By altering deposition conditions, many of the conventional materials can be made nearly amorphous. This is not always possible though. As well, micro-crystalline and amorphous thin films of bulk crystalline or amorphous materials have more absorption than do the bulk forms. That is why vacuum deposited SiO_2 is likely to have $k \approx 10^{-4}$, instead of $k \approx 10^{-6} \rightarrow 10^{-7}$ like bulk quartz or vitreous silica can be.

The polymer materials are naturally amorphous with low k . Grain boundary effects are not a problem in these materials.

The danger due to particulates that are incorporated during film growth is the same for polymer and conventional film depositions in a web coating system. It is, primarily, a function of operational and housekeeping techniques. Initial particulates, adhered to the substrate, can be made less in batch coaters than in web coaters with, current, standard substrate cleaning techniques. Furthermore, particulate contamination during deposition can be kept lower in a batch coater than in a web coater, with current standard techniques. At this time there is no experience with Polymer Multilayer depositions in a batch coating mode. There is no fundamental reason why the Polymer Multilayer technique could not be used in a batch coating process. The extremely high deposition rates, inherent in the Polymer Multilayer web coating process, could make batch operation difficult to control. However, the rate can easily be reduced to controllable levels. These controllable rates would still be much higher than conventional deposition techniques though.

Polymer vs. Conventional Interference Filter Performance:

General Considerations:

From the preceding discussions, the following general, qualitative, conclusions can be drawn concerning the relative merits of Polymer Multilayer and conventional vacuum deposited interference filters.

- 1) Broader Band filters can be attained, with fewer layers, with conventional deposition techniques due to the larger span of refractive indices than with the polymer method.
- 2) Narrow band filters are more easily made with the polymer method due to the ability to blend monomers to reach any intermediate refractive index.
- 3) The economics (i.e. throughput) definitely favors the polymer method.
- 4) Bulk absorption, in polymer films, should be

considerably less than in conventional films. This translates into higher, achievable, performance for polymer web coated filters compared with conventional web coated filters.

- 5) Due to a broader index range, angle of incidence performance can be better with conventional film materials. The cost, of course, is the blotting out of transmission for large wavelength regions around the design wavelength.
- 6) For high power, weapons grade, laser mirrors it is desirable to have amorphous films with low bulk absorption and as few particulate impurities as possible. Web coated Polymer Multilayers clearly excel in the first two categories. The third category is better optimized with a batch coating process, with current, standard, techniques. Currently, the polymer method has not been implemented in a batch mode.
- 7) RUGATE type filters may be much more easily deposited with the Polymer Multilayer technology than with conventional deposition processes. The index profile could be easily modulated, in a batch process, by controlling two, separate, monomer flows into the same evaporator tube.
- 8) For protection against lower energy lasers, like laser designators and range finders, the web coated polymer film process seems ideally suited. The sheer throughput attainable with the polymer technique almost demands it be used in such applications.
- 9) All of the above threat applications might be addressed by non-interference methods with non-linear

optical Polymer Multilayer materials/techniques. The integration of non-linear optical Polymer Multilayer materials/techniques with Polymer Multilayer interference filter designs seems a practical approach as well.

Specific Polymer Multilayer Filter Designs:

To better visualize some practical differences between the Polymer Multilayer and conventional deposition methods, some QWOT interference filter designs will now be examined. Figures 5 through 10 show the transmitted, and reflected, optical densities for 6 different QWOT filters as a function of incident angle.

Figure 5 depicts the performance of a 20 pair (40 layer) QWOT filter comprised of alternating TiO_2 and SiO_2 layers. At the design wavelength, of $.53 \mu\text{m}$, the refractive indices of TiO_2 and SiO_2 are ~ 2.7 and ~ 1.46 respectively. This gives the rather large value of $\delta_n \approx 1.2$. For this filter, at the design wavelength the transmission is barely greater than 0.0000001% , while the reflectance is only $\sim 99.97 \%$. The difference between $R + T$ and 1 is absorption. The increase in absorption, for wavelengths shorter than $\sim .4 \mu\text{m}$, is due to the onset of the UV absorption in both TiO_2 and SiO_2 coupled with a relatively high $\langle n \rangle$. A very obvious property of this filter is that it blocks nearly the entire visible portion of the spectrum.

It should be noted that making a 40 layer QWOT by standard techniques can be extremely difficult. The process would take a long time. Also, stress in the film could fracture the multilayer stack unless great care is taken. Most often, when structures with this many layers are deposited, the materials have to be selected such that stress in the layers alternates between tensile and compressive. This keeps the overall stress low enough that the films do not fracture.

However, placing film stress requirements on the materials, in addition to refractive index requirements, further limits your design options.

Figure 5. Performance of an all dielectric, $\text{TiO}_2/\text{SiO}_2$ QWOT reflection filter. The difference between the transmitted and reflected OD's is due to absorption.

Figure 6 depicts the performance of a 43 pair (86 layer) QWOT filter comprised of alternating AlN and Al_2O_3 layers. At the design wavelength, of .53 μm , the refractive indices of AlN and Al_2O_3 are ~ 2.16 and ~ 1.46 respectively. This gives the value of $\delta_n \approx .5$. For this filter, at the design wavelength the transmission is also barely greater than 0.00000001 % while the reflectance is only ~ 99.93 %. Since δ_n is less for this filter than for the filter of figure 5, for an equal transmitted OD the reflectance is less. The difference between $R+T$ and 1 is absorption. The increase in absorption, for wavelengths shorter than $\sim .4 \mu\text{m}$, is due to the onset of the UV absorption in both AlN and Al_2O_3 . In this filter, $\langle n \rangle$ is less and AlN and Al_2O_3 are less absorbing below $\sim .4 \mu\text{m}$ than are TiO_2 and SiO_2 . Therefore, the short wavelength

absorption is less than in the previous filter. This design allows more visible transmission than did the previous filter - at the cost of less angle of incidence bandwidth.

Even more so than for the previous filter, it should be noted that making an 86 layer QWOT by standard techniques is extremely difficult. It is likely that this filter would be impractical to fabricate for many applications.

Figure 6. Performance of an all dielectric, $\text{AlN}/\text{Al}_2\text{O}_3$ QWOT reflection filter. The difference between the transmitted and reflected OD's is due to absorption.

Figure 7 depicts the performance of a 90 pair (180 layer) QWOT filter comprised of alternating Al_2O_3 and SiO_2 layers. At the design wavelength, of .53 μm , the refractive indices of Al_2O_3 and SiO_2 are ~ 1.66 and ~ 1.46 respectively. This gives the moderate value of $\delta_n \approx .2$. For this filter, at the design wavelength the transmission is also barely greater than 0.00000001 % while the reflectance is only ~ 99.79 %. The smaller δ_n for this filter, compared to the

Figure 7. Performance of an all dielectric, $\text{Al}_2\text{O}_3/\text{SiO}_2$ QWOT reflection filter. The difference between the transmitted and reflected OD's is due to absorption.

previous two filters, is responsible for the lesser reflectance for an equal transmitted OD. The difference between $R+T$ and 1 is absorption. The increase in absorption for wavelengths shorter than $\sim .4 \mu\text{m}$ is due to the onset of the UV absorption in both Al_2O_3 and SiO_2 . These two materials are the least absorbing, below $\sim .4 \mu\text{m}$, of any of the other materials used so far. Consequently, the short wavelength absorption is the least so far. This lower absorption, coupled with narrower bandwidth, gives this design the most visible transmission of any of the filters discussed to this point. Of course, the angle of incidence bandwidth is the worst so far also.

The number of layers used in this filter was chosen to give a transmitted OD comparable to the previous two filters. However, this is definitely not a practical filter to fabricate - unless time and money are truly no object.

Figures 8, 9, and 10 depict Polymer Multilayer QWOT reflectance filters. In each case

Figure 8. Performance of an all dielectric, Polymer Multilayer QWOT reflection filter. The difference between the transmitted and reflected OD's is due to absorption.

it was assumed that $\langle n \rangle = 1.5$ and $\langle k \rangle = 0.000001$. The values of δ_n were varied from .2 to .05 in order to observe the effect on reflectance and angle of incidence performance.

It should be pointed out that, in Polymer Multilayer materials, there is also an increase in absorption below $\sim .4 \mu\text{m}$. This short wavelength dispersion was not included in the design since it is not precisely known. However, the increase in $\langle k \rangle$ is comparable to that found in the previous materials, and is dependent on precisely which monomer is used.

Figure 8 is the Polymer Multilayer filter with $\delta_n = .2$. The performance is nearly identical to the $\text{Al}_2\text{O}_3/\text{SiO}_2$ filter. The main differences are the lower short wavelength absorption,

attributable to less intrinsic absorption, and the higher reflectance ($\sim 99.998\%$). The higher reflectance is also attributable to lower $\langle k \rangle$.

Figure 9. Performance of an all dielectric, Polymer Multilayer QWOT reflection filter. The difference between the transmitted and reflected OD's is due to absorption.

Figure 9 is the Polymer Multilayer filter with $\delta_n=.1$. The angle of incidence performance is worse than for the $\delta_n=.2$ filter and the bandwidth is narrower as well. The reflectance is slightly less too ($\sim 99.996\%$). The slight reduction in reflectance is due to the smaller value of δ_n .

Figure 10 is the Polymer Multilayer filter with $\delta_n=.05$. The bandwidth is the most narrow of all of the filters to be discussed. Of the Polymer Multilayer filters, this also has the lowest reflectance ($\sim 99.991\%$). Again, the reduced δ_n is responsible for the lower reflectance.

Figure 10. Performance of an all dielectric, Polymer Multilayer, QWOT reflectance filter. The difference between the transmitted and reflected OD;s is due to absorption.

Note that all of the filters discussed had, roughly, the same Optical Density in transmission at the design wavelength. However, variations in $\langle n \rangle$, δ_n , and $\langle k \rangle$ made major differences in reflected Optical Density, bandwidth, short wavelength absorption, and angle of incidence performance. Some specific conclusions are:

- 1) All of the conventional deposition filters discussed were extremely difficult, or impractical, to fabricate because of the large number of layers required. In contrast, the number of layers required for the Polymer Multilayer filters, though greater, would be very easy to deposit with the new process.

- 2) There is considerable overlap in the attainable bandwidths for the two deposition processes. The $\text{TiO}_2/\text{SiO}_2$ filter has nearly the largest δ_n value that one will encounter for, visible spectrum, optical materials. For Polymer Multilayer films, roughly 0.3 is the maximum attainable δ_n - giving a considerably larger bandwidth than in the $\text{Al}_2\text{O}_3/\text{SiO}_2$ filter. The minimum δ_n is near zero for the Polymer Multilayer process.
- 3) Since maximum angle of incidence performance is obtained with maximum $\delta_n / \langle n \rangle$, conventional materials can give better performance for this filter property. The cost of this performance is, of course, the wider bandwidth that may, or may not, be a problem when out of band transmission is a requirement.
- 4) Compared to conventional processes, the Polymer Multilayer process permits the deposition of nearly unlimited numbers of layers with very small values of δ_n and $\langle k \rangle$. This permits much narrower bandwidth, higher reflectivity, filters to be fabricated with the new process.
- 5) While reflected Optical Density is limited by $\langle k \rangle$ transmitted Optical Density is not - the more layers the greater the transmitted OD will be. Consequently, higher in band Optical Densities, and out of band transmissions, are achievable with the Polymer Multilayer process.
- 6) Due to the molecular nature of the bonding, Polymer Multilayer monomers can be blended to obtain precise control over refractive index, without increasing

absorption.

- 7) Optically non-linear functional groups can be attached to the starting monomers to give Polymer Multilayer films non-linear optical properties. Again, due to the molecular nature of the bonding, this can be expected to have no impact on absorption - provided, of course, that the non-linear group has no intrinsic absorption of its own.
- 8) At the expense of higher extinction coefficients, improved non-linear properties can be obtained with metal inclusion/polymer matrix composite thin film materials.
- 9) "Poling" of polar groups attached to the monomer chain is easily achieved in the Polymer Multilayer process. This permits yet another avenue to non-linear optical properties with the Polymer Multilayer method. Furthermore, it is expected that "poled" Polymer Multilayer material will resist the tendency to relax back to the non-polarized state like conventionally poled polymers do.

CONCLUSIONS:

There are a great many factors to consider when designing a multilayer filter for a particular task. There are, obviously, some applications better serviced by conventional deposition processes. Some applications seem likely to obtain a great advantage from Polymer Multilayer deposition. For some applications, like low particulate batch coating, experimentation is needed to determine whether the Polymer Multilayer process has an advantage or not. For the

fabrication of, large area, optically non-linear devices, the Polymer Multilayer process promises unprecedented advancement in performance, deposition rates, and practical applications.

Like many other institutions, Battelle's Pacific Northwest Laboratory has a good deal of general thin film deposition experience, and a lot of optical filter design and fabrication background. We also have expertise in non-linear polymers - both organic and inorganic. Additionally, we have, perhaps, the largest area optical batch coating facility in the world. This last feature is important, however, it is only a matter of degree. **Battelle is the only institution, anywhere, that has any understanding of optical filters and understands the Polymer Multilayer process.** In fact, there is only one other facility that understands the Polymer Multilayer process, and they are only concerned with electrical capacitors.

There appear to be many areas of optical filter design and fabrication that can be greatly advanced through the use of this new technology. At Battelle, we are capable of making these advancements.

END

DATE
FILMED

4 129/93