DOE/ID/13283--T1-App.C-Pt.1

Hybrid Aerocapacitor™-Battery Power Sources

M.J. Isaacson¹, B.J. Kraemer¹, T.J. Laramore¹, S.T. Mayer¹ and L.C. Josephs²¹PolyStor Corp., 6948 Sierra Court, Dublin, CA 94568²Power-One, Inc., 740 Calle Plano, Camarillo, CA 93012

PolyStor, Power-One, LLNL and Aerojet are participants in a Technology Reinvestment Program contract supported by the Advanced Research Project Agency for developing carbon aerogel-based Electrolytic Double Layer Capacitors (Aerocapacitors). This paper reports some recent results for organic-electrolyte Aerocapacitors developed under this contract and initial results on their use in electrolytic double layer capacitor (EDLC)-battery power sources.

EDLC-battery hybrid power sources offer the potential for increased discharge time,^{1,2} improved low temperature performance and longer cycle life vis-a-vis batteries in pulse discharge applications. We previously presented performance results for AA Aerocapacitors³ but this is the first report of our work on hybrid power sources.

Prototype organic-electrolyte Aerocapacitors exhibit low equivalent series resistance (ESR), high capacitance, excellent rate capability at room temperature and low temperatures, and long life. The AA-size devices assembled for testing have ESRs of 20-30 mΩ at 1000 Hz and capacitances of about 6 Farads. As shown in Fig. 1, they are capable of being discharged at very high rates. The capacity at 15 Amps is about 71 % of the capacity at 1 Amp. The capacity at 1 Amp and -40°C is 57 % of the room-temperature 1 Amp capacity. AA Aerocapacitors have demonstrated 32,000 cycles in cycle life testing. After an initial capacity decrease of about 17 % the capacity remained almost constant between cycle 10,000 and cycle 32,000.

Fig. 2 shows complex impedance and phase angle frequency response data for an AA Aerocapacitor. Experimental measurements were made over a frequency range of 100 Hz to 1 MHz. For comparison, the calculated complex impedance and phase angle of a simple series resistor-capacitor-inductor model is shown. The complex impedance is constant and the phase angle is close to 0° between 100 Hz and 10 kHz. Above this frequency, the phase angle and complex impedance increase because of the increasing contribution of the induction. Measurements were not made at sufficiently low frequencies to obtain the capacitance limited region of the data. However, the model shows that the phase angle decreases to -90° and the complex impedance increases to 300 mΩ at 0.1 Hz.

Hybrid power source testing was performed with commercial 4/3A (2800 mAh) nickel-metal hydride (NiMH) cells and AA Aerocapacitors. NiMH cells were chosen for initial experiments because of: (1) The simplicity of the NiMH hybrid system, which consists of only two NiMH cells and one Aerocapacitor. (2) Their widespread use in portable electronics. (3) Their limited power density. A hybrid device, consisting of a series string of two NiMH cells in parallel with a single AA Aerocapacitor, was chosen for charge/discharge testing because of the good match in the rated voltages. The control was two NiMH cells in series. The discharge regimen was a 30 second discharge at 280 mA (10-hour rate) followed by a 30 millisecond pulse at 8400 mA (20-minute rate). This was repeated until the voltage during the 280 mA, 30 second discharge reached 2.0 V.

MASTER

FC07-94ID13283

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

nj

Prior to charge-discharge testing the impedance of the individual capacitors and NiMH cells was characterized with a Fluke 6304 LCR meter and with DC current steps on a Maccor cycler. Based on the DC results, the ESRs of the hybrid and control devices were calculated to be 32 and 76 m Ω , respectively.

Fig. 3 shows discharge-voltage curves for both the hybrid and control devices. The four curves in the figure are: (1) The voltage of the hybrid device at the 280 mA rate immediately prior to the current pulse. (2) The voltage of the hybrid device at the end of the 8400 mA pulse. (3) The voltage of the control device at the 280 mA rate immediately prior to the current pulse. (4) The voltage of the control device at the end of the 8400 mA pulse.

All of the discharge curves are similar in shape. The voltages of the two 280 mA discharge curves are similar, but because of the lower resistance of the hybrid device, its 8400 mA curve lies at an average potential of about 380 mV higher than that of the control device. This is in good agreement with the IR drop difference of 366 mV calculated from the ESR measurements.

The lower resistance and higher pulse discharge-voltage curve of the hybrid device yield a higher discharge capacity for applications which specify a minimum pulse discharge voltage. This is quantified in Fig. 4. The left axis of Fig. 4 shows the volumetric capacity of the hybrid and control devices as a function of the pulse discharge cutoff voltage and the right axis shows the difference in volumetric capacity between the hybrid and control devices. (A positive volumetric capacity difference means that the volumetric capacity of the hybrid device is greater than the control.) At a nominal cutoff of 2.0 V, the hybrid device had a capacity of 2845 mAh (78 mAh/cc) while the control had a capacity of only 925 mAh (32 mAh/cc). This yielded an increase in the volumetric capacity of 46 mAh/cc - a value 245 % that of the control.

The Aerocapacitor is an ideal candidate EDLC for hybrid power sources because of its low ESR and good frequency response characteristics. An example, using NiMH cells and AA Aerocapacitors, has demonstrated that an EDLC used in a hybrid power source can greatly increase the discharge capacity of a battery. Additional experimental and theoretical work is being performed in our laboratory to characterize the performance of hybrid power sources. This work will include investigation of the cycle life and temperature performance of hybrid systems and examination of hybrid systems using lithium-ion, zinc-air, and fuel cells.

1. J.R. Miller, in *Proceedings of the 188th Meeting of the Electrochemical Society*, Chicago, Illinois, October 8-13, 1995.
2. S. Andrieu and C. Rouverand, in *Proceedings of the Fifth International Seminar on Double Layer Capacitors and Similar Energy Storage Devices*, Deerfield Beach, Florida, December 4-6 (1995)
3. M.J. Isaacson, J.L. Kaschmitter, B.J. Kraemer, T.J. Laramore, S.T. Mayer, R.W. Pekala, L.C. Josephs and D. Gregory, in *Proceedings of the Fifth International Seminar on Double Layer Capacitors and Similar Energy Storage Devices*, Deerfield Beach, Florida, December 4-6 (1995).

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

**Portions of this document may be illegible
in electronic image products. Images are
produced from the best available original
document.**

Fig. 1. Discharge voltage curves for a AA, organic-electrolyte Aerocapacitor. The temperature is 20°C.

Fig. 2. Frequency response of an AA Aerocapacitor. Individual data points are experimental measurements. Solid lines are predictions of a simple model consisting of a resistor, capacitor and inductor in series. All measurements were made at room temperature.

Fig. 3. Comparison of the voltage discharge curves for a hybrid and a control power source. The hybrid power source consists of a series string of two nickel-metal hydride batteries in parallel with an AA Aerocapacitor. The control consists of two nickel-metal hydride cells in series. All measurements were made at 20°C.

Fig. 4. Comparison of the volumetric capacity of a hybrid and a control power source. The capacity difference is the difference between the volumetric capacity of the hybrid power source and the control power source.