RECEIVED BY DTIC JUL 24 1970

SNAP-21 INSULATION SYSTEM

TID-25482

**3M COMPANY
SPACE AND DEFENSE PRODUCTS**

ST. PAUL, MINNESOTA

FINAL REPORT

MASTER

**UNION CARBIDE CORPORATION
LINDE DIVISION**

TONAWANDA, N.Y.

THIS DOCUMENT CONFIRMED AS
UNCLASSIFIED
DIVISION OF CLASSIFICATION
BY *9 H. Kahn/amb*
DATE *8/25/70*

*Patent cleared
per telegram
1/24/70
Reg. Tervis/H. Kline*

PG:88

JUNE 1970

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

rsht

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

TID--25482

SNAP-21 INSULATION SYSTEM

MASTER

3M COMPANY
SPACE AND DEFENSE PRODUCTS

ST. PAUL, MINNESOTA

FINAL REPORT

BY

UNION CARBIDE CORPORATION

LINDE DIVISION

TONAWANDA, N.Y.

- SUBCONTRACTOR

To 3M Co.

JUNE 1970

FINAL REPORT

THE DESIGN, DEVELOPMENT AND DELIVERY OF HIGH TEMPERATURE

VACUUM INSULATION SYSTEMS

FOR

SNAP-21 THERMOELECTRIC POWER SYSTEM

by

L. R. Niendorf

Prepared for

Minnesota Mining and Manufacturing Company
Space and Defense Products
St. Paul, Minnesota

Contract AT(30-1)-3691-5511

Union Carbide Corporation
Linde Division
Tonawanda, New York

FOREWORD

This is the final report of a development effort performed by Union Carbide Corporation, Linde Division under Contract No. AT(30-1)-3691-5511. The contract work was performed under the direction of the 3M Company, Space and Defense Products, St. Paul, Minnesota. Mr. Vic Yanish, Mr. James Brandt, and Mr. Robert Pannemann were successively the 3M Program Managers.

The major contract activities were performed during the period from August, 1966 to July, 1969 under the Project Management of Mr. L. R. Niendorf. He was assisted by Messrs. A. F. Axelson, A. W. Bailey, A. K. Chatterjee, N. C. Gibbon, C. F. Gottzmann, C. M. Heath, A. Hooton, P. N. Massing, D. Molnar, G. E. Nies, R. L. Reid, B. M. Shields, J. O. Spragge, D. H. Stellrecht, T. M. Tetreault, N. P. Theophilos, D. J. Webster, A. A. Wolfson.

TABLE OF CONTENTS

<u>Section No.</u>	<u>Title</u>	<u>Page</u>
1.0	SUMMARY	1
2.0	INTRODUCTION	2
3.0	TECHNICAL REPORT	3
3.1	BASIC DEVELOPMENT ACTIVITIES	3
3.1.1	Offgassing Investigation	3
3.1.1.1	Experimental Procedure	3
3.1.1.2	Offgassing of Tested Materials	6
3.1.1.2.1	Hastelloy-X.	6
3.1.1.2.2	Ug Moly Radiation Shield Material	6
3.1.1.2.3	Quartz Paper	12
3.1.1.2.4	Type 304 Stainless Steel	12
3.1.1.3	Determination of Total Offgassing Load and Getter Requirements	18
3.1.2	Getter Evaluation Test	18
3.1.2.1	Experimental Procedure	23
3.1.2.2	Experimental Test Results	23
3.1.3	Getter Retainer Investigation	27
3.1.3.1	Retention Capability Tests	28
3.1.3.2	Gas Flow Conductance Test	29
3.1.3.3	Retainer Formability and Weldability	33
3.1.3.4	Hydrocarbon Getter Enclosure Development	35
3.1.4	Seal-Off Device Development	42
3.1.4.1	Temporary O-Ring Seal-Off	42
3.1.4.2	Seal-Off Weld Parameters	46
3.1.4.3	Demonstration of Getter Fill and Seal-Off	48
3.1.5	Weld Development Tests	52
3.1.5.1	Automatic Girth Weld	52
3.1.5.2	Semi-Automatic Neck Tube Weld	67
3.1.5.3	Manual Receptacle Weld	72
3.1.5.4	Manual Seal-Off Plug Weld	75

TABLE OF CONTENTS
(Cont'd.)

<u>Section No.</u>	<u>Title</u>	<u>Page</u>
3.1.6	Neck Tube Static Proof Test	75
3.1.7	Material Compatability Investigation	87
3.1.8	Tension Rod Preload Evaluation Tests	97
3.1.8.1	Preload Determination with Strain Gauge on Tension Rod	97
3.1.8.2	Preload Determination with Strain Gauge on Tension Rod Receptacle	97
3.2	ANALYSIS ACTIVITIES	103
3.2.1	Dynamic Criteria Study	103
3.2.1.1	Heat Loss Determination for Proposed Support Systems .	103
3.2.1.1.1	Bellows with Six Compression Rod Support System . . .	106
3.2.1.1.2	Neck Tube with Three Compression Rod Support System .	106
3.2.1.1.3	Neck Tube with Three Tension Rods Support System . . .	108
3.2.1.1.4	Neck Tube Support System	108
3.2.1.1.5	Bellows with Six Tension Rods Support System	108
3.2.1.1.6	Bellows with Six Stacked Disk Compression Rods Support System	108
3.2.1.1.7	Bellows with Compressed Multi-Layer Insulation Support System	113
3.2.1.2	Allowable System 'g' Loading with a Directly Supported Nuclear Radiation Shield	113
3.2.1.3	Determination of Expected Dynamic Loading During Unit Transportation and Handling	113
3.2.1.3.1	Literature Survey to Determine Expected Dynamic Loading	113
3.2.1.3.2	Estimation of HTVIS Unit 'g' Loadings During Fabrication, Testing and Packaging	118
3.2.1.3.3	HTVIS Unit Handling on a Fork-Lift Truck, Experimental Tests	118
3.2.2	Material Selection Study	118
3.2.2.1	Neck Tube Material	119
3.2.2.2	Tension Rod Materials	119
3.2.2.3	Enclosure Shell Material	120
3.2.2.4	Insulation Materials	120
3.2.3	Calculation to Determine Tension Rod Installation Angle	120

TABLE OF CONTENTS
(Cont'd.)

<u>Section No.</u>	<u>Title</u>	<u>Page</u>
3.2.3.1	Temperature Profile of Hastelloy-X Neck Tube	120
3.2.3.2	The Thermal Expansion of the Neck Tube by Numerical Integration	121
3.2.3.3	Temperature Profile of Inconel-625 Male Tension Rod .	123
3.2.3.4	Thermal Expansion of Inconel-625 Male Rod by Numerical Integration	125
3.2.3.5	Temperature Profile of Inconel-718 Female Tension Rod	126
3.2.3.6	Thermal Expansion of Inconel-718 Female Tension Rod .	127
3.2.3.7	Thermal Expansion of U ₈ Moly Shield and Hastelloy-X Spider	129
3.2.3.8	Thermal Expansion of Tension Rods	129
3.2.3.9	Calculation of Tension Rod Angle	130
3.2.4	Support Structure Stress Analysis	131
3.2.4.1	Design of Tension Rod System Parts	131
3.2.4.1.1	Design of Tension Rod Threads	131
3.2.4.1.2	Design of Female Tension Rod Outside Diameter	133
3.2.4.1.3	Design of Spherical Washer	133
3.2.4.2	Calculation of Area of Female Support Rod to Achieve 1000°F at Connection of Support Rods	134
3.2.4.3	Calculation of Support System Spring Constants	135
3.2.4.3.1	Female Support Rod Spring Constant	136
3.2.4.3.2	Male Support Rod Spring Constant	137
3.2.4.3.3	Spherical Washer Spring Constant	137
3.2.4.3.4	Receptacle Spring Constant	139
3.2.4.3.5	Enclosure Shell Spring Constant	140
3.2.4.3.6	Spider Spring Constant	141
3.2.4.3.7	Radiation Shield Spring Constant	142
3.2.4.4	Design of Neck Tube and Tension Rods	143
3.2.4.4.1	Unit in Horizontal Position	143
3.2.4.4.1.1	Loading Condition I	145
3.2.4.4.1.2	Loading Condition II	147
3.2.4.4.2	Vertical Position (Neck Tube Open End Up)	148
3.2.4.4.3	Vertical Position (Neck Tube Open End Down)	149
3.2.4.4.3.1	Strength in Combined Compression and Internal Pressure	150
3.2.4.4.3.2	Buckling in Combined Compression and Internal Pressure	150
3.2.4.5	Thermal Load and Stresses Developed in the Tension Rods Due to Tension Rod Angle Tolerance	151
3.2.4.6	Effect of Temperature Difference Between Spider and Emitter Plate Temperature on Tension Rod Looseness and Tightness	152

TABLE OF CONTENTS
(Cont'd.)

<u>Section No.</u>	<u>Title</u>	<u>Page</u>
3.2.5	Support Structure Vibration Analysis	152
3.2.5.1	Vibration Analysis Model	155
3.2.5.2	Amplification Factor for Unit in Horizontal Position .	156
3.2.5.3	Amplification Factor for Unit in Vertical Position (Neck Tube Open End Up)	160
3.2.5.4	Amplification Factor for Unit in Vertical Position (Neck Tube Open End Down)	161
3.2.6	Enclosure Analysis	161
3.2.6.1	Top Flange	162
3.2.6.2	Upper Head	165
3.2.6.3	Cylindrical Shell	168
3.2.6.4	Bottom Head	169
3.2.7	Rupture Life Analysis	171
3.2.7.1	Rupture Life Neck Tube	171
3.2.7.2	Rupture Life of Tension Rods	172
3.2.8	Unit Heat Loss Calculation	172
3.2.8.1	Neck Tube Heat Loss Calculations	172
3.2.8.2	Tension Rod Heat Loss Calculation	173
3.2.8.2.1	Tension Rod Heat Loss Under Test Conditions	175
3.2.8.2.2	Tension Rod Heat Loss Under Operating Conditions . . .	177
3.2.8.3	Heat Loss Calculations Through Insulation	178
3.2.8.3.1	Insulation Heat Loss for Ni-Cu-Al Insulation at Test Temperature	179
3.2.8.3.2	Insulation Heat Loss for Ni-Cu-Al Insulation at Operating Temperature	182
3.2.8.3.3	Insulation Heat Loss for Cu-Al Insulation at Test Temperature	183
3.2.8.3.4	Insulation Heat Loss for Cu-Al Insulation at Operating Temperature	184
3.2.8.3.5	Insulation Joint Heat Loss	185
3.2.8.3.6	Calculation of System Heat Loss at Test Temperature Which is Equivalent to 45 Watts of Operating Temperature	188
3.3	UNIT DEVELOPMENT ACTIVITIES	189

TABLE OF CONTENTS
(Cont'd.)

<u>Section No.</u>	<u>Title</u>	<u>Page</u>
3.3.1	Prototype Unit	189
3.3.1.1	Prototype Unit Design	189
3.3.1.2	Prototype Unit Fabrication	189
3.3.1.3	Prototype Unit Conditioning and Thermal Test	198
3.3.1.4	Prototype Unit Shipping Container	207
3.3.2	Development Units	210
3.3.2.1	Development Unit Design	210
3.3.2.2	Development Unit B10-D1	212
3.3.2.2.1	Unit Fabrication	212
3.3.2.2.2	Thermal Testing	220
3.3.2.2.3	Dynamic Testing	221
3.3.2.2.4	Thermal Retest	222
3.3.2.2.5	Dynamic Test to Failure	223
3.3.2.3	Development Unit B10-D2	224
3.3.2.3.1	Unit Fabrication	224
3.3.2.3.2	Thermal Test	226
3.3.2.3.3	Dynamic Testing	227
3.3.2.4	Development Unit B10-D3	230
3.3.2.4.1	Unit Fabrication	230
3.3.2.4.2	Thermal Testing	230
3.3.2.4.3	Dynamic Testing	231
3.3.2.5	Development Unit B10-D4	231
3.3.2.5.1	Unit Fabrication	231
3.3.2.5.2	Thermal Test	231
3.3.2.5.3	Dynamic Testing	233
3.3.2.5.4	Failure Analysis Unit B10-D4	233
3.3.2.5.4.1	Unit Disassembly and Dimensional Inspection	234
3.3.2.5.4.2	Material Composition of Unit Components	242
3.3.2.5.4.3	Microscopic Examination of Neck Tube	242
3.3.2.5.4.4	Thermal Expansion of Unit Components	243
3.3.2.5.4.5	Radiation Shield Phase Change	245
3.3.2.5.4.6	Radiation Shield Spider End Temperature Variation	246
3.3.3	Tension Rod Thermal Force Cycles	248
3.3.3.1	Test Unit and Instrumentation	248
3.3.3.2	First Thermal Force Cycle - Unit B10-Q1	251
3.3.3.2.1	Unit Closure	251

TABLE OF CONTENTS
(Cont'd.)

<u>Section No.</u>	<u>Title</u>	<u>Page</u>
3.3.3.2.2	Test Set-Up	252
3.3.3.2.3	Test Cycle Conduct	252
3.3.3.2.4	Post Test Disassembly	257
3.3.3.2.5	Conclusions Drawn from the First Thermal Force Cycle .	257
3.3.3.3	Second Thermal/Force Cycle - Unit B10-Q1	258
3.3.3.3.1	Unit Closure	258
3.3.3.3.2	Test Cycle Conduct	259
3.3.3.3.3	Post Test Disassembly	262
3.3.3.3.4	Conclusions Drawn from the Second Thermal/Force Cycle	265
3.3.3.4	Third Thermal Force Cycle - Unit B10-Q1	265
3.3.3.4.1	Unit Closure	265
3.3.3.4.2	Test Cycle Conduct - Run 3	266
3.3.3.4.3	Test Cycle Conduct - Run 4	272
3.3.3.5	Recommendation Resulting from Thermal Force Cycles . .	277
3.4	HTVIS DELIVERY UNITS	279
3.4.1	Unit Fabrication	279
3.4.2	Unit Acceptance Testing	279
3.4.2.1	Unit Thermal Testing	279
3.4.2.2	Unit Dynamic Testing	282
3.4.2.2.1	Dynamic Tests - Unit B10-DL1	282
3.4.2.2.2	Dynamic Tests - Unit B10-DL2	286
3.4.2.2.3	Dynamic Tests - Unit B10-DL3	288
3.5	SHIPPING CONTAINER	290
4.0	CONCLUSIONS AND RECOMMENDATIONS	293

LIST OF APPENDICES

<u>Appendix</u>	<u>Title</u>	<u>Page</u>
A	Calculation of Unit Getter Requirements	A-1
B	Static Proof Test Calculations	B-1
C	Physical Properties of Materials Used in Model A Insulation System	C-1
D	Derivation of Equation for Temperature Distribution in a Rod With One Dimensional Heat Conduction and Variable Thermal Conductivity	D-1
E	Calculation of Neck Tube Temperature Profile in an Operating Unit	E-1
F	Derivation of Load Sharing Equation	F-1
G	Derivation of Spring Constant for Three Tension Rod Support System	G-1
H	SNAP 21 Prototype Unit Thermal Performance Test -- Calculation of Unit Heat Loss	H-1
I	Thermal Performance Test Heat Loss Calculations	I-1
J	Functional Performance Acceptance Test Plan	J-1
K	List of Drawings	K-1

LIST OF TABLES

<u>Table No.</u>	<u>Title</u>	<u>Page</u>
1	Offgassing Composition Data - Hastelloy-X Tests	11
2	Offgassing Composition Data - Quartz Paper Tests	17
3	Offgassing Composition Data - Type 304 Stainless Steel	21
4	Summary of Offgassing Test Data and Calculated Getter Requirements	22
5	Mass-Spectrometer Analysis Getter Evaluation Test	28
6	Specification for Getter Retainer Materials	28
7	Getter Retainer Material Weld Parameters	36, 37, 38
8	Hydrocarbon Getter Enclosure Weld Parameters	39
9	Seal-Off Apparatus - Gold Ring Seal Tests	45
10	Seal-Off Device Edge Weld Parameters	46
11	Preparatory Automatic Heliarc Welding Information (Flat Plate)	59
12	Preparatory Heliarc Automatic Welding (Pipe)	60
13	Details of Automatic Heliarc Welding, Enclosure Weld	62, 63
14	Weld Parameter for Semi-Automatic Neck Tube Edge Weld	70
15	Receptacle to Enclosure Head Weld Data - Manual Heliarc Weld - Argon at 25 cfh	76
16	Seal-Off Plug to Receptacle Weld Data - Manual Heliarc Weld - Argon at 25 cfh	79
17	Results of Parametric Study for Bellows with Six Compression Rod Support System	107
18	Results of Parametric Study for Neck Tube and Three Compression Rod Support System	109
19	Results of Parametric Study for Neck Tube with Three Tension Rod Support System	110, 111
20	Results of Parametric Study for Neck Tube Support System	112
21	Estimated 'g' Loading for Shipping and Handling of Insulation System, Fueled Insulation System, and Complete System	116, 117
22	Insulation Materials on SNAP 21B Prototype	191
23	Fabrication Data SNAP 21B Prototype - Enclosure Welding and Leak Rate Check (Manual Heliarc with 25 cfh Argon Shielding Gas)	197
24	Summary of Thermal and Dynamic Performance of Development HTVIS Units	211
25	Insulation Composition Unit B10-D1	215
26	Recorded Accelerations - Unit B10-D2 (Ambient) Vibration Test	229
27	Insulation Composition Unit 10-D4	232
28	Dimensional Comparison of Unit B10-D4 Structural Components Before and After Failure	240
29	Summary of HTVIS Unit Thermal Performance	281
30	Summary of Dynamic Tests on Model A (10 Watt) HTVIS Units	283
31	Shipping Container Drop Test Data - Container No. 1	292

LIST OF FIGURES

Figure No.	Title	Page
1	Schematic of Offgassing Test Apparatus	4
2	Typical Pressure Rise (Torr) Versus Time (Hours) Curve	5
3	Schematic Offgassing Cycles (Operating Temperature) .	7
4	Schematic Offgassing Cycles (Ambient)	8
5	Hastelloy-X and Empty Chamber Pressure Rise Curves for Slope Determination	9
6	Offgassing Rate of Hastelloy-X Versus Pressure at 1400°F	10
7	End View of Nuclear Radiation Shield Material Samples After Offgassing Test	13
8	Nuclear Radiation Shield Material and Empty Chamber Pressure Rise Curves for Slope Determination	14
9	Quartz Paper and Empty Stainless Steel Chamber Pressure Rise Curves for Slope Determination	15
10	Offgassing Rate Versus Pressure for Quartz Paper at 1400°F Conditioned at 1550°F for 16-1/2 Hours	16
11	Stainless Steel and Empty Chamber Pressure Rise Curves for Slope Determination	19
12	Offgassing Rate of Stainless Steel Versus Pressure at 100°F	20
13	Getter Evaluation Test Apparatus	24
14	Getter Evaluation Test System Pressure Versus Time .	25
15	Test Fixture for Retainer Vibration Tests	30
16	Schematic of Test Apparatus for Determining Gas Conductance Through a Porous Metal Sheet	31
17	Conductance Versus Average Pressure for Tested Retainer Materials	32
18	Getter Retainer Material Weld Specimens	34
19	Micrograph of Hydrocarbon Getter Enclosure Weld . . .	40
20	Hydrocarbon Getter Enclosure - Welded in Enclosure Head	41
21	Getter Seal-Off Device	43
22	Schematic of Gold O-Ring Seal-Off Test Apparatus . .	44
23	Simulated Seal-Off Edge Weld Joint	47
24	Seal-Off Device Showing Final Seal-Off Weld	49
25	Schematic of Getter Installation and Seal-Off Apparatus	50
26	Getter Fill Apparatus - Demonstration Test No. 1 . .	53
27	Installed Getter - Demonstration Test No. 1	54
28	Getter Fill Apparatus - Demonstration Test No. 2 . .	55
29	Installed Getter - Demonstration Test No. 2	56
30	Automatic Heliarc Welding Apparatus	58
31	Enclosure Girth Weld Joint - 45° Bevel	61
32	Automatic Heliarc Welded Enclosure Joints - 6 Inch Pipe	64
33	Tensile Specimens from Enclosure Joints on 6 Inch Pipe	65
34	Failed Tensile Specimens from Enclosure Joints on 6 Inch Pipe	66

LIST OF FIGURES
(Cont'd.)

<u>Figure No.</u>	<u>Title</u>	<u>Page</u>
35	Micrograph of Enclosure Girth Joint Weld Specimen No. 4	68
36	Neck Tube Weld Joint Geometry	69
37	Simulated Neck Tube Weld Joints - 2.5 Inch Diameter .	71
38	Simulated Neck Tube Weld Joints - 5 Inch Diameter . .	73
39	Receptacle Weld Development Fixture	74
40	Receptacle Weld Specimen No. 3 Before Failure	77
41	Receptacle Weld Specimen No. 1 After Failure	78
42	Receptacle Seal-Off Plug Weld Specimen No. 4	80
43	Static Proof Test Apparatus - Failed Neck Tube . . .	81
44	Strain Versus Applied Load in Tension Rod (Static Proof Test)	83
45	Deflection Versus Load for Neck Tube and Tension Rod (Static Proof Test)	84
46	Simulated Tension Rod Assembly for Load Deflection Test	85
47	Schematic View Showing the Insulation and Radiation Shield Material in Test Chamber	88
48	Insulation Material Test Zones of Compatibility Test After 500 Hours at 1400°F	89
49	Nuclear Radiation Shield Material Samples After 500 Hours at 1400°F	90
50	Tantalum Foil (.0003 Inch Thick) After 500 Hours at 1400°F	92
51	Insulation Material Test Zones of Compatibility Test After 2000 Hours at 1400°F	94
52	Nuclear Radiation Shield Material After 2000 Hours at 1400°F	95
53	Strain Gauge Applied to Long Side of Receptacle . . .	98
54	Receptacle Strain Gauge Load Versus Strain Data Unit B10-D1	99
55	Calibration of Tension Rod Receptacles - Unit B10-D1 Load Versus Strain in Receptacle Extrapolated	101
56	Tension Rod Torque Versus Strain in Receptacle Unit B10-D1	102
57	Effect of 'g' Loading on Total System Heat Leak for Different Support Systems	104
58	Schematic Diagram of Different Support Systems	105
59	'g' Loading Permitted on HTVIS System During Shipping When Shield is Rigidly Supported	114
60	Temperature Distribution of Inconel-625 Male Rod . .	124
61	Temperature Distribution of Inconel-718 Female Rod .	128
62	Load and Stresses in the Tension Rods at Operating Temperature Due to Tension Rod Angle Tolerance . . .	153

LIST OF FIGURES
(Cont'd.)

<u>Figure No.</u>	<u>Title</u>	<u>Page</u>
63	Effect of Temperature Difference Between Spider and Emitter Plate Temperatures on Tension Rod Looseness and Tightness	154
64	Thermal Conductivity Variation in the Neck Tube (Hastelloy-X)	174
65	Average Insulation Area Versus Insulation Thickness	180
66	Effect of Segments on Insulation Heat Loss for Nickel-Copper-Aluminum System (1360°F - 110°F)	186
67	Effect of Segments on Insulation Heat Loss for Copper-Aluminum System (1360°F - 110°F)	187
68	SNAP 21B Prototype Unit Prior to Insulation Application	190
69	SNAP 21B Prototype - Cylindrical Insulation Installed	192
70	SNAP 21B Prototype - Installation of Upper Head Insulation	193
71	SNAP 21B Prototype - Installation of Lower Head Insulation	194
72	SNAP 21B Prototype - Completed Insulation Application	195
73	SNAP 21B Prototype - Alignment Fixture for Neck Tube Weld	196
74	SNAP 21B Prototype - Hold Down Ring and Top Works Installed	199
75	3M SNAP 21B Prototype Thermal Performance No. 1	201
76	3M SNAP 21B Thermal Performance Test No. 2	202
77	3M SNAP 21B Prototype Thermal Test No. 3	204
78	3M SNAP 21B Prototype Unit Offgassing Pressure Rise Test	206
79	Completed SNAP 21B Prototype Unit	208
80	SNAP 21B Prototype Unit in Shipping Container	209
81	Effect of Temperature on Radial Clearance Between Inner Liner and Radiation Shield	213
82	Installed Insulation Unit B10-DL1	216
83	Alignment of Bottom Heat Unit B10-D1	218
84	Failed Inner Liner Unit B10-D1	225
85	Oscillograph Recording of Accelerations During Vibration Test of Unit B10-D4 (Note Machine Dump)	235
86	View Inside Failed Neck Tube Unit B10-D4	236
87	Side View of Loose Spider Unit B10-D4	238
88	Effect of Axial Thermal Expansion of Shield, and Neck Tube on Tension Rod Looseness, and Tightness	244
89	Effect of Temperature of Shield at Spider End on Tension Rod Looseness, or Tightness	247
90	View of Thermocouples Installed on Spider of Thermal Force Cycle Unit	249

LIST OF FIGURES
(Cont'd.)

<u>Figure No.</u>	<u>Title</u>	<u>Page</u>
91	Unit B10-Q1 First Heat - Cool Cycle	253
92	Unit B10-Q1 First Head - Cool Cycle	254
93	Unit B10-Q1 Second Thermal/Force Cycle	260
94	Unit B10-Q1 Second Thermal/Force Cycle Emitter Plate and Spider Plate Temperature Differential	261
95	Unit B10-Q1 Second Thermal Force Cycle	263
96	Unit B10-Q1 Third Thermal Force Cycle Run No. 3 . . .	267
97	Unit B10-Q1 Third Thermal Force Cycle Run No. 3 . . .	269
98	Third Thermal Force Cycle Run No. 3	270
99	Unit B10-Q1 Third Thermal Force Cycle Run No. 4 . . .	273
100	Unit B10-Q1 Third Thermal Force Cycle Run No. 4 . . .	275
101	Unit B10-Q1 Third Thermal Force Cycle Run No. 4 . . .	276
102	Completed HTVIS Delivery Unit (B10-DL2)	280
103	Accelerometer Trace During Vibration Machine Malfunction Resulting in Failure of Unit B10-DL1 . .	285
104	Unit B10-DL1 - Buckled Neck Tube Caused by Vibration Machine Malfunction Z-Z Axis	287
105	HTVIS Model A (10 Watts) Shipping Container	291

ABSTRACT

The high temperature vacuum insulation system developed for the SNAP-21 10 watt Thermoelectric Power System has the dual purpose of supporting the 265-pound biological shield while allowing minimum heat loss from the nuclear fuel. It is hermetically sealed and incorporates chemical getters to maintain a hard vacuum for five years. The biological radiation shield is supported by a thin walled neck tube at the generator end and three ball joint tension support rods at the other end.

The insulation has demonstrated design ruggedness by withstanding vibration loadings of 3 'g' up to 50 Hz and 6 'g' shock loadings at 6 milliseconds duration (saw tooth peak) while at an operating temperature of 1285°F. A thermal heat loss for the insulation system of less than 50 watts has been achieved.

1.0 SUMMARY

The high performance thermal insulation system developed by Linde Division of Union Carbide Corporation for the SNAP-21 system under this contract uses an evacuated multi-layer insulation. The system size specification permits only 1.5 inches of insulating material around the biological shield. The evacuated multi-layer insulation system was chosen to obtain maximum thermal efficiency in this limited space. The multi-layer insulation consists of copper foils with quartz paper separators in the temperature range 1400°F to 900°F and aluminum foils with glass paper separators in the temperature range 900°F to ambient. The insulation materials are preprocessed before installation and conditioned after final assembly to reduce offgassing to acceptable limits. Chemical getters are used to maintain the vacuum required (< 10 microns) for optimum insulation performance for a minimum of five years.

The biological shield is located within and supported by the insulation system. The shield support is provided by a thin wall Hastelloy-Alloy-X neck tube at one end and three tension tie rods at the other end. The tension rod support system uses ball and socket connections combined with a precise tension rod angle so that thermal expansion of the system components during heatup does not induce stresses in the support elements. The tension rods are fabricated from two nickel alloy materials threaded together to reduce heat loss. The portion of the rod adjacent to the biological shield is fabricated from Inconel 625 which has good creep strength properties and has a yield strength of approximately 30,000 psi at 1400°F. The portion of the tension rod adjacent to the vacuum enclosure was designed to have a maximum temperature of 1000°F that allowed the use of Inconel 718 which has a yield strength of approximately 120,000 psi. The use of Inconel 718 allows a significant reduction in cross-sectional area, reducing this portion of the tension rod heat loss. The required tension rod preload, to ensure that the rods remain tight, is provided by threading the two rod elements together and then locking. Experimental work was performed to measure the tension rod strains during a system heat and cool cycle to demonstrate that the tension tie rods are not overstressed due to the thermal expansions of the system components.

Tests to determine the offgassing rate and gas composition were performed on the materials within the vacuum enclosure at operating temperature after conditioning. Over 99.4% of the offgas is hydrogen. The chemical getters were tested for gettering capacity using a sample gas simulating the offgassing composition. The getter is installed in the system in bulk form, under vacuum, just prior to making a temporary gold "O" ring seal-off. The final seal is a welded seal-off.

The insulation system has demonstrated design ruggedness by withstanding vibration loadings of up to 3 'g' in the 5 to 50 Hz range and shock loadings of 6 'g' at 6 milliseconds duration (saw-tooth peak) on each of the three mutually perpendicular axes while at operating temperature. Internal pressures of less than one micron within the insulation system after over two years of operation has demonstrated maintenance of vacuum integrity. A thermal heat loss of less than 50 watts has been achieved on operating systems.

2.0 INTRODUCTION

This Final Report describes the development and design work performed to develop a high performance thermal insulation system for the SNAP-21 10 watt Thermoelectric Power System.

This report is organized into functional work areas rather than presenting the work in chronological order as performed. The major work areas include: Basic Development Activities, Analysis Activities, Unit Development Activities, and Delivery Units Fabrication. The basic development activities discussion of Section 3.1 presents the pre-unit bench type development work conducted in the areas of offgassing, getters evaluation, welding parameters, materials compatibility, seal-off device evaluation, and tension rod and neck tube strength tests. The analysis activities in Section 3.2 includes the work on materials selection, determination of tension rod angle, determination of tension rod and neck tube dimensions based on vibration and shock analysis, enclosure analysis, rupture life analysis, and unit heat loss analysis.

The unit development activities of Section 3.3 includes the development work performed on the prototype unit and the four development units. The fabrication and testing of each development unit is discussed. The performance of the eight fabricated delivery units is presented in Section 3.4 while in Section 4.0 the contract Conclusions and Recommendations are presented.

3.0 TECHNICAL REPORT

3.1 BASIC DEVELOPMENT ACTIVITIES

3.1.1 Offgassing Investigation

The objective of the offgassing investigation was to determine the offgassing rate and gas composition for materials which are enclosed in the vacuum envelope after various stages of conditioning. The knowledge gained during this work allowed the chemical getter requirements to be determined as well as to specify the conditioning cycle which the materials within the vacuum envelope should be subjected prior to seal-off. The materials evaluated under this contract included Hastelloy-X, U₈ Moly radiation shield material, quartz paper, and Type 304 stainless steel. Offgassing tests on the other insulation materials to include nickel foil, copper foil, aluminum foil, and Type 106 glass paper were conducted on Contract AT(29-2)-2832 and the results as presented in the Phase I Final Report of that contract were used to determine the getter requirements.

3.1.1.1 Experimental Procedure

The experimental apparatus used during the offgassing investigation was composed of a 5 inch O.D. Hastelloy-X vacuum tube furnace with a high vacuum flange. A diffusion pump in conjunction with a liquid nitrogen cold trap was used to produce the vacuum environment. Cold cathode and thermocouple type vacuum gauges were used to monitor the pressure in the test chamber. A sampling type mass spectrometer was used to determine the offgassing gas composition during the tests. A schematic of the offgassing test apparatus is shown in Figure 1.

The offgassing rates of materials tested during this experimental work were determined by the pressure rise method. In this method the empty test chamber is evacuated and subjected to a heating cycle and then valved off. Pressure-time data is taken as the pressure rises in the chamber. The material to be evaluated is then loaded into the test chamber and the heating cycle is duplicated, again valving off the chamber and recording the pressure time data as the pressure rises in the chamber. The pressure rise curves for both the empty chamber and chamber with sample are then plotted as shown in Figure 2.

The offgassing rate equals the difference in the instantaneous slopes of the pressure rise versus time curve at the same pressure for the chamber with sample and for the empty chamber, multiplied by the chamber volume, divided by the surface area of the sample to yield an offgassing rate in micron liters per hour-ft²

$$\text{Offgassing rate} = \frac{\text{chamber volume}}{\text{sample surface area}} \left[\frac{\Delta P}{\Delta t} (\text{chamber} + \text{sample}) - \frac{\Delta P}{\Delta t} (\text{empty chamber}) \right]$$

As used in this work, surface area is defined as the exposed area of a material, in the vacuum space. For example, a piece of material measuring one foot square has a surface area of 2 ft².

SCHEMATIC OF
OFFGASSING
TEST APPARATUS

FIGURE- 1

FIGURE 2

5.

The test cycle used for the Hastelloy-X, quartz paper, and U₈ Moly radiation shield material is shown schematically on Figure 3. The cycle consists of 16.5 hours of pumping while at 1550°F followed by a pressure rise at 1500°F. The chamber is then evacuated and cooled to 1400°F and a second pressure rise tests is performed at 1400°F. The chamber is then heated to 1550°F for further conditioning and maintained at this temperature for an additional 16.5 hours. The chamber is then cooled to and maintained at 1400°F for a third pressure rise test.

The test cycle used for the Type 304 stainless steel is similar to the cycle used for the other materials except the conditioning temperature is limited to 350°F while test temperature 100°F rather than 1400°F. A schematic of this test cycle is shown in Figure 4. At the conclusion of each test temperature pressure rise, the offgassing gas constituents and relative percentages thereof were determined with the mass-spectrometer.

3.1.1.2 Offgassing of Tested Materials

3.1.1.2.1 Hastelloy-X

Following the determination of the empty chamber pressure rise characteristics when subjected to the test cycle (Figure 3), 20.8 ft² (both sides) of Hastelloy-X sheet, .012 inch thick, was cleaned with isopropyl alcohol, rolled, and inserted into the test chamber. The test cycle (Figure 3) was performed thus determining the pressure versus time characteristics for the Hastelloy-X in the test chamber. Figure 5 presents the corrected pressure versus time for both the empty test chamber and the test chamber with Hastelloy. The offgassing rate was calculated using the $\Delta P/\Delta t$ slopes shown on Figure 5 and is presented on Figure 6 as offgassing rate versus the test chamber pressure. It can be seen that the additional 16.5 hours at 1550°F decreased the offgassing rate of the Hastelloy-X. Considering 33 hours of conditioning at 1550°F, the offgassing rate to be used in determining the total amount of offgassing is 2.3×10^{-3} micron liters per hour-ft².

The percentage composition of the offgassing gas for both the empty test chamber and the test chamber with the Hastelloy-X sample are presented on Table 1. Since the sample line and test chamber was broken back to atmospheric pressure with argon at the end of each run, this was assumed to be the source of argon that appeared as a small percentage in the gas analysis. Furthermore, at the test temperature it is unlikely that the percentage water that appeared in the analysis came from the sample. It is more probable that this water vapor originated in the sampling lines. Taking these facts into consideration, the offgassing composition was deduced by subtracting the argon and water percentages from the sample plus test chamber analysis and then adjusting the numbers on the basis of the remaining total percentages.

3.1.1.2.2 U₈ Moly Radiation Shield Material

For the offgassing tests of the nuclear radiation shield material, 15 pieces (1/2 inch diameter x 3 inches long) of depleted uranium - 8% Molybdenum, copper coated were cleaned with isopropyl alcohol and loaded into the test

FIGURE 3

SCHEMATIC OFF-GASSING CYCLES (OPERATING TEMP.)

EMPTY CHAMBER OFF-GASSING CYCLE

OFF-GASSING CYCLE OF CHAMBER WITH HASTELLOY-X, QUARTZ PAPER,
OR NUCLEAR RADIATION SHIELD MATERIAL SAMPLE

FIGURE 4

SCHEMATIC OFF-GASSING CYCLES (AMBIENT)

EMPTY CHAMBER OFF-GASSING CYCLE (AMBIENT)

OFF-GASSING CYCLE OF CHAMBER WITH TYPE 304 STAINLESS STEEL SAMPLE

OFFGASSING RATE
MICRON-LITER/HR. FT²

FIGURE 6

OFFGASSING RATE OF HASTELLOY-X VERSUS PRESSURE

@ 1400°F

TABLE 1

OFFGASSING COMPOSITION DATA - HASTELLOY-X TESTS
SEE FIGURE 3 FOR CYCLE IDENTIFICATION

<u>Test Chamber</u>	<u>Pressure Rise</u>	<u>Temp. °F</u>	<u>H₂O</u>	<u>Hydrocarbons</u>	<u>CO₂</u>	<u>N₂-C_O</u>	<u>H₂</u>	<u>Ar</u>
Empty	A	1150	8.94	11.55	20.72	47.22	11.55	--
Empty	B	1400	8.75	5.60	14.03	35.81	34.76	--
Empty	C	1400	16.58	4.05	17.29	27.40	31.85	2.81
Hastelloy-X Sample	D	1550	24.03	--	0.21	11.84	62.24	1.54
Hastelloy-X Sample	E	1400	2.21	--	--	0.98	91.20	5.55
Hastelloy-X Sample	F	1400	15.87	--	--	3.88	80.24	--
Conditioned Test Chamber for 72 Hours at 1800°F								
Empty	A	1550	14.20	--	.33	--	81.12	4.28
Empty	B	1400	17.36	--	--	8.51	68.06	5.67
Empty	C	1400	20.24	--	--	8.93	65.64	5.19
Hastelloy-X Sample	D	1550	7.57	.21	--	10.78	75.29	5.79
Hastelloy-X Sample	E	1400	7.58	--	.24	2.52	84.34	5.11
Hastelloy-X Sample	F	1400	11.10	.60	--	3.17	79.34	5.77

chamber. The test cycle as shown on Figure 3 was performed to determine the characteristics of the empty chamber, followed by the test run with the radiation shield material sample followed by another empty chamber run. Figure 7 is a photograph showing an end view of the material samples following the offgassing test. The copper cladding experienced some damage on the ends of the rods and in addition it appeared that the center of the rods were void of copper cladding.

It was determined during the offgassing tests that the nuclear radiation shield material did not offgas at 1400°F after conditioning at 1550°F for 16.5 and 33 hours. This material exhibits an adsorption characteristic rather than offgassing. The pressure rise curves for the empty chamber and chamber with sample have been corrected for both gauge calibration and hydrogen content and are presented in Figure 8. The pressure rise data is plotted on rectangular coordinates to determine the slope of empty chamber and chamber with sample at equal pressures. After 33 hours of conditioning at 1550°F, it can be seen that the slope of the empty chamber was $.0104 \times 10^{-6}$ torr/min., while the slope of the chamber with sample was only $.00666 \times 10^{-6}$ torr/min.

3.1.1.2.3 Quartz Paper

A 160 ft² sample (both sides) of processed quartz paper was evaluated for offgassing using a stainless steel test chamber. The offgassing test cycle to which the quartz paper was subjected was the same as used for the Hastelloy-X and radiation shield material sample as shown on Figure 3. Following the quartz paper offgassing cycle, an empty test chamber cycle was performed to determine the base pressure rise characteristics of the test chamber.

The quartz paper offgassing tests conducted at 1400°F after conditioning at 1550°F showed that this material offgasses after conditioning for 16.5 hours. However, after conditioning for 33 hours the material exhibits the characteristics of an adsorber. The pressure rise data is plotted on Figure 9 for the pressure rise after 16.5 hours of conditioning at 1550°F to determine the slopes in order to calculate the offgassing rate. The calculated offgassing rate versus pressure is plotted on Figure 10 for the quartz paper conditioned for 16.5 hours at 1550°F. After 33 hours of 1550°F conditioning exhibited the properties of an adsorber which is the same as having a negative offgassing rate.

The mass spectrometer analysis of the gas components taken during the quartz paper offgassing cycle and the empty chamber offgassing cycle is presented in Table 2.

3.1.1.2.4 Type 304 Stainless Steel

Tests to determine the offgassing characteristics of Type 304 stainless steel were performed following the test cycle presented on Figure 4. Following two empty test chamber runs, 20 ft² (both sides) of Type 304 stainless steel was loaded into the offgassing test chamber and the test cycle was

FIGURE 7

END VIEW OF NUCLEAR RADIATION SHIELD MATERIAL SAMPLES AFTER OFFGASSING TEST
(81-67)

FIGURE 8

NUCLEAR RADIATION SHIELD MATERIAL
& EMPTY CHAMBER PRESSURE RISE
CURVES FOR SLOPE DETERMINATION.

FIGURE 9

QUARTZ PAPER & EMPTY STAINLESS STEEL CHAMBER
PRESSURE RISE CURVES FOR SLOPE DETERMINATION

15.

FIGURE 10

OFFGASSING RATE
VERSUS PRESSURE
FOR QUARTZ PAPER AT 1400°F
CONDITIONED AT 1550°F
FOR 16-1/2 HOURS

TABLE 2

OFFGASSING COMPOSITION DATA - QUARTZ PAPER TESTS

See Figure 3 for Cycle Identification

<u>Test Chamber</u>	<u>Pressure Rise</u>	<u>Temperature °F</u>	<u>Percent Composition</u>					
			<u>H₂O</u>	<u>Hydrocarbons</u>	<u>CO₂</u>	<u>N₂-CO</u>	<u>H₂</u>	<u>Ar</u>
Quartz Paper Sample	E	1400	8.33	.77	.21	4.44	82.98	3.26
Quartz Paper Sample	F	1400	8.90	1.09	.22	6.48	82.06	1.25
Empty	B	1400	4.13	1.33	.09	4.23	89.63	.59
Empty	C	1400	4.44	1.25	.11	4.60	89.19	.42

conducted up to pressure rise L (Figure 4) when the test chamber temperature controller malfunctioned causing the chamber to be rapidly heated to 950°F thus terminating the offgassing run. It was decided not to rerun rise L as the empty chamber cycles would have to be rerun and in addition, the surface area of the stainless steel in the actual units is small, therefore, to be conservative the getter requirements for the stainless steel offgassing can be based on the rise K which was taken after 16.5 hours of conditioning. Furthermore, the data taken before the malfunction on pressure rise L showed initially a substantially reduced offgassing rate.

The pressure rise data is plotted on Figure 11 for the pressure rise at 100°F after 16.5 hours of conditioning at 350°F. Because the empty chamber pressure rise was low compared to the chamber with stainless steel, it was not possible to subtract the empty chamber slope from the chamber with sample slope at an equal pressure. For calculating the stainless steel offgassing rates as shown on Figure 12 plotted against pressure, the slope of the empty chamber was assumed as zero. Both empty chamber runs exhibited characteristics different from the empty chamber runs recorded during the other material offgassing tests in that when the chamber was valved off at the start of the run, the pressure was sharply reduced initially before it started a gradual rise. This phenomenon may be explained by the fact that the chamber had been conditioned at 1550°F and was therefore very clean for the runs at 100°F. For the low temperature offgassing cycle of stainless steel (condition at 350°F - run at 100°F), the chamber was most probably initially acting as an absorber.

The mass spectrometer analysis of the gas components taken during the stainless steel offgassing cycle and empty chamber offgassing cycle is presented in Table 3.

3.1.1.3 Determination of Total Offgassing Load and Getter Requirements

The offgassing rates presented in this report for stainless steel, Hastelloy-X, nuclear radiation shield material (Ug Moly), and quartz paper along with the offgassing rates for nickel foil, copper foil, aluminum foil and 106 paper taken from the Linde Division Final Report of Research and Development in a Thermal Insulation Study (Phase I), ALO 3632-20, UC-33, Propulsion Systems and Energy Conversion, AEC Research and Development Report, November, 1967, were used to calculate the HTVIS unit getter requirements and the gas composition to be used for the getter evaluation test. Table 4 presents the compiled offgassing data in summary form giving for each material the surface area used in a HTVIS unit, the offgassing rate at operating temperature, the total offgassing during a five-year period, the offgassing component percent, and the total offgassing subdivided in gas components for getter calculation. The acceptable leak rate was calculated to be 6×10^{-8} std. cc air/sec. assuming a 10 micron pressure rise over a five-year period due to non-getterable argon buildup. The getterable portion of air leakage has been factored into the getter requirement. The total getter requirement for a five-year period has been calculated to be 6.43 grams plus 0.10 grams of hydrocarbon getter.

3.1.2 Getter Evaluation Test

The purpose of the getter evaluation test was to determine the useful capacity of a known quantity of getter for removing gases found in the insulation system resulting from offgassing and leakage after the unit evacuation and seal-off.

FIGURE 11

19.

STAINLESS STEEL & EMPTY CHAMBER

PRESSURE RISE CURVES FOR SLOPE DETERMINATION

FIGURE 12
OFFGASSING RATE OF STAINLESS STEEL
VS.
PRESSURE
@ 100°F

TABLE 3

OFFGASSING COMPOSITION DATA - TYPE 304 STAINLESS STEEL

See Figure 4 for Cycle Identification

Test Chamber	Pressure Rise	Temperature °F	Percent Composition						
			H ₂ O	Hydrocarbons	CO ₂	N ₂ -CO	H ₂	Ar	O ₂
Empty	G	350	53.60	-	.63	9.66	35.40	-	.68
Empty	H	100	60.60	-	-	18.68	20.65	-	-
Empty	I	100	68.90	-	.61	8.85	21.20	.44	-
Empty	G	350	59.50	-	-	11.26	28.16	.97	-
Empty	H	100	73.60	-	.54	5.82	19.40	.53	-
Empty	I	100	70.00	-	-	8.54	20.60	.80	-
304 Stainless Sample	J	350	48.70	-	3.75	14.20	33.30	-	-
304 Stainless Sample	K	100	16.46	-	1.30	5.47	76.75	-	-

TABLE 4
SUMMARY OF OFFGASSING TEST DATA AND CALCULATED GETTER REQUIREMENTS

Calculated Results	Nickel Foil	Copper Foil	Aluminum Foil	Quartz Paper	106 Glass Paper	Hastelloy-X	Stainless Steel	Nuclear Radiation Shield	Total
Surface area based on both sides of the material-ft ² .	291	465	566	857	366	0.875	4.26	--	2750
Offgassing rates based on surface area (both sides) Micron-liters/hr.ft ² .	0	0	0.0225	0	0	.0023	.0095	0	--
Total offgassing during 5 year period - Micron-liters.	0	0	557,793	0	0	88	1773	0	559,654
Mass spectrometer analysis on gas composition of the material -%.	--	--	H ₂ - 99.43% N ₂ -CO - 0.15% CH ₄ .42%	--	--	H ₂ - 95.46% N ₂ -CO - 3.81% CH ₄ - .72%	H ₂ = 91.89% N ₂ -CO - 6.55% CO ₂ - 1.56%	--	--
Gas constituents from test material Micron-liters.	--	--	H ₂ =554,614 N ₂ -CO = 837 CH ₄ = 2343	--	--	H ₂ = 84 N ₂ -CO = 3 CH ₄ = 1	H ₂ = 1629 N ₂ -CO = 116 CO ₂ = 28	--	H ₂ = 556,327 CO ₂ = 28 N ₂ -CO = 956 CH ₄ = 2344 ..

Leakage air based on allowable pressure rise of the system due to the presence of argon only of 10 μ at the end of 5 years period = 7225 μ -liters. This corresponds to an allowable leakage rate of 6.03×10^{-8} atm. cc/sec.air.

Gas composition of the leakage air - N₂ = 5642 μ -liters, O₂ = 1515 μ -liters, CO₂ = 2.16 μ -liters, Ar = 163 μ -liters

Total system gas composition @ 5 years period.

H ₂ = 556,327	μ -liter - 98.12%	O ₂ = 1,515	μ -liter - 0.267%
CO ₂ = 30	μ -liter - .0053%	CH ₄ group = 2,344	μ -liter - 0.413%
N ₂ -CO = 6,598	μ -liter - 1.16%	Argon = 163	μ -liter - 0.0287%

Amount of getter requirement based on the following getter capacity.

H ₂	- 100,000 μ -liter/gm
CO	- 8,000 μ -liter/gm
N ₂	- 45,000 μ -liter/gm
O ₂	- 40,000 μ -liter/gm
CO ₂	- 5,000 μ -liter/gm
CH ₄ group	- 23,000 μ -liter/gm
Getter for H ₂	- 5.56 ³ gm
N ₂ -CO based on all CO	- .825 gm
CO ₂	- 0.006 gm
O ₂	- 0.038 gm

Total getter for above = 6.43 gms

Total Hydrocarbon getter = 0.10 gm

3.1.2.1 Experimental Procedure

For the test, 1.00 gram of regular getter and .103 grams of hydrocarbon getter were tested for useful capacity using the test apparatus shown in Figure 13. The test gas which was gettered was prepared to simulate the composition and percentage of the offgassing and leakage constituents that are calculated as shown on Table 4 to be present in a HTVIS unit. The unit getter calculations are presented in Appendix A.

The getter evaluation test was conducted in three parts by successively loading the same getter sample with the test gas. After each part of the test, the residual gas was analyzed on the mass spectrometer to determine the gas constituents and percentage composition. After the analysis the residual gas was evacuated from the system in order to start the next part of the test at a low pressure. The test gas flow rate control valve was calibrated before the first and second part of the test and after the third part of the test.

In the test apparatus the hydrocarbon getter was heated in order to maintain a reasonable CH_4 equilibrium pressure. At room temperature the getter pumping speed is sufficient to maintain a 1 micron CH_4 pressure for the CH_4 flow predicted in the HTVIS unit. In the getter test, however, the CH_4 flow was considerably higher in order to complete the getter test in a reasonable length of time. As a consequence, the equilibrium CH_4 pressure will also be higher according to the equation:

$$P = (Q/S)^2$$

P = Equilibrium CH_4 pressure

Q = CH_4 flow rate

S = Getter pumping speed

For example, the test flow was approximately 2000 times higher than the actual flow. As shown by the preceding equation, the only way to keep the equilibrium pressure at a reasonable level is to obtain a corresponding increase in S . This was accomplished by heating the hydrocarbon getter to 300°C .

3.1.2.2 Experimental Test Results

During this getter evaluation test it was demonstrated that the getter exhibited a useful capacity of 110,732 micron-liters per gram of getter while gettering a test gas which simulates the gas expected to be present in HTVIS units.

After each of the first two parts of the test where 52,170 micron-liters and 25,503 micron-liters were gettered as shown on Figure 14, the gas analysis taken (Table 5) showed the residual gas to be essentially all argon

FIGURE 13

GETTER EVALUATION TEST APPARATUS
(1453-67)

TABLE 5

MASS-SPECTROMETER ANALYSIS
GETTER EVALUATION TEST

Analysis No.	Description	Gas Composition Percent						
		H ₂	Ar	CO-N ₂	CO ₂	O ₂	CH ₄ Group	H ₂ O
1	Analysis of System Prior to Part I	3.20	-----	4.20	-----	----	-----	92.6
2	After Getter- ing 52,170 u-1 Test Gas	1.42	84.65	1.53	1.88	----	6.2	4.32
3	Analysis of System Prior to Part II	3.34	-----	6.17	.40	.23	-----	89.86
4	After Getter- ing 25,503 u-1 Additional Test Gas	1.84	88.34	.94	1.54	----	2.03	5.31
5	After Getter- ing 33,059 u-1 Additional Test Gas	1.38	10.64	86.52	.11	.26	.19	.90
6	Analysis of Test Gas (No. 4701)	97.07	.0244	1.36	.0115	.102	.328	1.10
7	Gas Lab Test Gas Analysis	98.4	.026	1.20	.0065	.22	.41	-----

Note: The H₂O percentage shown in this table results from residual H₂O in the line connecting the analyzer to the system as seen in Analysis No. 1 and No. 3.

which is not gettered. After Part III of the test where the getter capacity was completely used, as evidenced by rapidly increasing pressure, the predominate residual gas was carbon monoxide showing that the getter had used up its capacity for this gas.

The settle out pressure at the end of each part of the test compares well with the expected pressure that is caused by the non-getterable argon in the test gas. For example, at the end of Part I there was a settle out pressure of 10.5 microns. The argon pressure expected is calculated by multiplying the total gas admitted (micron-liters) by the fraction of argon composition and dividing by the system volume (liters).

$$\begin{aligned}\text{Expected Argon Pressure} &= \frac{52,170 \text{ micron-liters} \times .00026}{1.415 \text{ liter}} \\ &= 9.59 \text{ microns}\end{aligned}$$

The actual argon pressure as determined by multiplying the total settle out pressure by the percentage of argon as determined by the mass spectrometer analysis (Table 5) is calculated as follows: *

$$\begin{aligned}\text{Actual Argon Pressure} &= 10.5 \text{ micron} \times .8465 \times \frac{100}{95.68} \\ &= 9.29 \text{ microns}\end{aligned}$$

The higher than 10 micron pressure shown on the pressure rise curves (see Figure 14) for the test is caused by the high flow rate used in order to conduct the test in a reasonable length of time. The flow rate used in this test for the regular getter (472.8 micron-liters per minute) is approximately 2000 times greater than is expected in an actual HTVIS unit. The useful getter capacity of 110,732 micron-liters is in good agreement with the design getter capacity of 88,089 micron-liters determined by dividing the total gas expected by the specified grams of getter as presented in Table 4.

3.1.3 Getter Retainer Investigation

The purpose of this development effort was to qualify a material to retain the getter and prevent exposure to other system materials operating at high temperature because of possible incompatibility. In addition to retaining all getter particles, the getter retainer must exhibit an adequate gas flow conductance so the gettering rate will not be reduced and so that the system can be evacuated through the retainer. Finally, methods were determined for forming and fabricating the selected retainer material.

* This term is used to account for the percentage of H₂O in the test line.

Three materials were evaluated as candidates for the getter retainer. The specifications for the tested retainer materials is presented in Table 6.

TABLE 6
SPECIFICATION FOR GETTER RETAINER MATERIALS

Vendor	Union Carbide Corp.	Huyck Metals Co.	Huyck Metals Co.
Material	Nickel	Type 347 S.S.	Type 347 S.S.
Product Name	NU-40	Felt Metal	Felt Metal
Vendor Identification	UCC-NU-40	FM 627, Type 30 Fiber	FM 215 W/S.S. Screen
Density	60 Per Cent	35 Per Cent	N/A
Average Pore Size	13 microns	11.7 microns	13 microns
Pore Size Range	2-25 microns	5-23 microns	N/A
Thickness	0.011 inch	0.065 inch	0.050 inch
Unit Weight	0.325 lb/sq. ft.	0.8 lb/sq. ft.	N/A
Tensile Strength	3500 psi	2800 psi	5800 psi

The Huyck Metals Co. FM 215 was selected for use in the HTVIS units because it exhibited the required strength and stiffness, in addition to excellent getter particle retention, and adequate flow conductance.

3.1.3.1 Retention Capability Tests

Vibration tests were conducted to determine the effectiveness of the candidates retainer materials listed on Table 6 to retain the getter. For the vibration testing, it was necessary to simulate the getter in terms of particle size since actual getter could not be used as it would react with the atmospheric air resulting in a change of properties. A sample of getter in vacuum was analyzed for particle size and it was found that the sample was composed of agglomerates which range in diameter from less than 3 microns to about 1/8 inch. A more accurate measurement of the individual particles (which are less than 3 microns diameter) could not be obtained because the glass tube containing the getter was too thick to use a more powerful objective. Platinum oxide was finally selected to simulate the getter as it was composed of agglomerates which range in size from less than 3 microns to 30 microns. The individual particles which form the agglomerates all look to be less than 3 microns in diameter. Other materials considered as a simulated getter were: iron oxide, Sanlocel-A, and talcum powder, however, evaluation of these materials showed a particle size larger than desired.

A schematic drawing of the getter retainer particle retention test equipment is shown on Figure 15. The simulated getter particles were loaded into the test apparatus and vibration tests were conducted both normal and parallel to the retainer material sample as per the following schedule:

For 3 'g' tests: Sweep 10-26 Hz at 1.3 'g' in 1-1/2 minutes.
Sweep 26-40 Hz .036 inches double amplitude in 2-1/2 minutes.
Sweep 40-50 Hz at 3 'g' in 3-1/2 minutes.
Sweep 50-10 Hz in 7-1/2 minutes reverse of 10-50 Hz sweep.

Total test time 15 minutes.

For 10 'g' tests: Sweep 10-15.5 Hz at 1.3 'g' in 1-1/2 minutes.
Sweep 15.5-40 Hz at .0529 inches double amplitude in 2-1/2 minutes.
Sweep 40-50 Hz at 10 'g' in 3-1/2 minutes.
Sweep 50-10 Hz in 7-1/2 minutes, reverse of 10-50 Hz sweep.

Total test time 15 minutes.

Following each vibration test, the plastic reservoir in the test apparatus was examined and no platinum oxide particles were observed to have passed through any of the tested retainer materials. As a result all candidate materials on Table 6 are acceptable from the standpoint of retaining the getter.

3.1.3.2 Gas Flow Conductance Test

Vacuum conductance tests were performed on all three candidate porous metals listed on Table 6 using the test apparatus shown schematically on Figure 16. During a conductance test a gas flow is throttled through the needle bleed valve into the vacuum chamber. This gas must pass through the getter retainer material, through the vacuum pump and be measured with either a wet drum meter or a positive displacement meter depending on the gas flow rate. The differential pressure across the getter retainer is measured by the differential pressure gauge while the absolute pressure is measured by the vacuum gauges at low pressure and the absolute pressure gauge for higher pressures.

The vacuum conductance is calculated from the relationship $F = Q/\Delta P$ (A) = Flow rate (μ -l/sec.)/Differential pressure (μ) x Area ft^2 . Figure 17 presents the measured vacuum conductance of the tested retainer materials. In the free molecular flow range, the vacuum conductance of the NU-40 material was 80 liters per sec. ft^2 , while the FM 627 was 36 liters per sec. ft^2 , and the FM 215 was 22 liters per sec. ft^2 . For all of the materials as the average pressure increases, the conductance shifts to the transition regime with corresponding higher conductances.

TEST EQUIPMENT (VERTICAL SET UP)

30

FIGURE 15 TEST FIXTURE FOR RETAINER VIBRATION TESTS

FIGURE 16

SCHEMATIC OF TEST APPARATUS FOR DETERMINING GAS CONDUCTANCE THROUGH A POROUS METAL SHEET

FIGURE 17

CONDUCTANCE VERSUS AVERAGE PRESSURE FOR TESTED RETAINER MATERIALS

All materials tested are satisfactory from a vacuum conductance criteria when it is considered that approximately $.2 \text{ ft}^2$ of retainer material is used in the unit, as the maximum pumping speed of the getter is approximately 2 liters per second and during unit evacuation, the piping from the vacuum pump to the unit will have a free molecular flow conductance of approximately 2 liters per second.

3.1.3.3 Retainer Formability and Weldability

As a result of the good tensile strength, structural stiffness, the getter retention tests, and vacuum conductance tests, Huyck Metal Co. Felt-metal No. FM-215 porous metal sheet (Type 347) stainless steel - .050 inch thick - 13 microns average pore size - Type 347 stainless steel screen sinter bonded on one side was selected to be used for the HTVIS units and for the tests to determine methods to weld the getter retainer into the lower enclosure head.

The weld development was started by welding a 1-1/2 inch long by 1 inch wide FM 215 sample directly to a 3/8 inch thick Type 304 stainless steel plate. The FM 215 material was placed at a 30° angle with the stainless plate to simulate the retainer to head angle and a manual heliarc fillet weld was performed on the screen side of the sample. This weld is shown in Figure 18 as 1. Because of the characteristics of this material to not wet the surface and ball up during welding, severe cracks were noted along the weld joint which could possibly allow the leakage of getter into the insulation space.

It was felt that if a sufficient heat sink could be provided for the specimen during welding, or the amount of heat reduced, the cracking could be avoided. For this reason, a thin strip (0.050 inch thick) 9 inches long by 1/2 inch wide Type 304 stainless steel was welded directly to the FM 215 sample. During welding, sufficient heat sink was provided by placing the weld specimen over a copper block. This weld was very satisfactory with no cracks being observed. This type of weld using a transition strip at a 30° angle was performed on both the plain and screen side of the specimen with equally successful results - Figure 18 as 3. The stainless steel transition strip was then fillet welded to the 3/8 inch thick Type 304 stainless steel plate with good results as shown in Figure 18 as 2. In order to use this method on a HTVIS unit, the stainless steel transition piece would be cut and formed into a conical section to fit the diameter of the lower enclosure head before welding the FM 215 specimen.

To simplify the above process of making a transition piece, a washer type transition piece was cut from Type 304 stainless steel 1-3/4 inch O.D. x 1.0 inches I.D. x .050 inch thick and the FM 215 retainer material was flat fillet welded to the washer using a chill on the porous metal sample. This method also produced an acceptable weld and is shown in Figure 18 as 5.

In order to simulate the weld at the radius of the lower enclosure head, two getter retainers were welded in 4 inch I.P.S. schedule 40 pipe caps. Transition rings made of 304 stainless steel material were fillet welded to the porous metal sheet. One of the transition rings was formed into a conical section and the other ring was made like a flat washer type transition ring.

FIGURE 18
GETTER RETAINER MATERIAL WELD SPECIMENS
(563-67)

The detail descriptions of the porous metal test weld development program are presented on Table 7. The quality of the welds were checked only by optical instruments as the weld only provides a seal for the getter and is not a structural type joint.

As a result of the retainer weld development effort, it was decided to use the FM 215 porous metal with a flat washer type stainless steel transition ring for the HTVIS unit getter retainer. The final designed getter retainer assembly is presented on Drawing B-664044 where fabrication instructions and weld specifications are given.

3.1.3.4 Hydrocarbon Getter Enclosure Development

It was shown in the reduction of the offgassing data (Table 4) that a hydrocarbon getter is required in the HTVIS units in addition to the regular getter. The hydrocarbon getter to be used for this application cannot be physically mixed with the regular getter and therefore requires a separate getter enclosure. This separate getter enclosure must be located in the unit so that the hydrogen gas constituent of the system offgassing will be gettered by the regular getter before it reaches the hydrocarbon getter as a hydrocarbon getter also has a capacity for hydrogen gas.

To meet the above requirements, the hydrocarbon getter is located within a 3/8 inch O.D. Type 304 stainless steel tube formed into a partial ring to fit around the circumference of the female seal-off device which projects into the enclosure head. The getter tube is welded to the bottom enclosure head with the use of stainless steel tabs. The getter is retained within the tube by welding the getter retainer material (FM 215) over each end of the tube. This retainer material with its somewhat low vacuum conductance and small area will insure that the hydrogen gas from the offgassing will be gettered by the regular getter before it can reach the hydrocarbon getter. The conductance of the retainer material covering the ends of the tube is, however, three orders of magnitude greater than required to provide adequate pumping speed to remove the hydrocarbons.

Four getter retainer disks (FM 215) were welded to the 3/8 inch O.D. Type 304 stainless steel tube to determine the required weld parameters. The welds were performed as discussed in Table 8. Figure 19 shows a micrograph of the weld with the screen next to the tube and of the weld with the screen away from the tube. It was found that the weld with the screen away from the tube was most satisfactory.

To secure the hydrocarbon getter enclosure tube to the head, three lugs made from .048 inch thick Type 304 stainless steel formed in an angle shape (5/16 inch x 5/16 inch) were welded to the enclosure tube at approximately a 120° spacing. The weld parameters for this weld are also presented in Table 8.

The final designed hydrocarbon getter enclosure assembly (Figure 20) is presented on Drawing B-664067 where fabrication instructions and weld specifications are given.

TABLE 7

GETTER RETAINER MATERIAL WELD PARAMETERS

Test Sample No.	Description	Amps	Volts Approx.	Travel Speed I.P.M. Approx.	Remarks
1	Sample: 9" x 1" x .050" FM-215 porous metal sheet; Transition strip - 1/2" x 9" x 0.050" 304 stainless steel. Copper bar used as heat sink, argon shield, 25 CFH.	30-35	9-11	6	Transition band pulled up even though it was tacked. No cracks. Inside does not have full penetration. Too much chill from copper bar. Tacked on stainless steel screen side. Manual weld.
2	Same material only the copper bar used for heat sink was bevelled 30° to give relief at edge of porous metal sheet. Argon shield - 25 CFH	35-40	9-11 Approx.	6	Penetration not complete, some bowing, no cracks. Tacked on stainless steel screen side. Manual weld.
3	Sample - same as No. 1. Transition strip - 9/16" x 9" x .050", 304 stainless steel. Chill copper bar - 45° bevel. Plain side of the porous metal up.	40-50	10-11	4-5 Approx.	Tacked on plain side of porous metal. Penetration was complete except 1" near center. One small crack on porous metal strip. Bowed in two directions. Manual weld.
4	Same as No. 3 except stainless steel screen side up.	40-50	10-11	4-5	Weld bead rather heavy. Penetration not complete in several places. Sample and transition band both bowed. Manual weld.
5	Sample same as No. 1 Transition strip 1/2" x 9" x 0.050", 304 stainless steel strip set 30° off vertical same clamping method as as No. 4 but tighter over strip. Argon gas shield 25 CFH. Bevelled 45° copper hold down bar used to chill the weld.	32-38	10-11	4 Approx.	Good penetration except for 2" intermittent penetration near center. Bowing not severe. This strip was welded to 3/8" - 304 stainless steel plate after repair weld at the center. No cracks. Manual weld.

TABLE 7 (Cont'd.)

<u>Test Sample No.</u>	<u>Description</u>	<u>Amps</u>	<u>Volts Approx.</u>	<u>Travel Speed I.P.M. Approx.</u>	<u>Remarks</u>
6	Sample: 1-1/4" dia. x 0.050" thick. FM-215 porous metal disc. transition disc: 1-3/4 O.D. x 1" I.D. x .050" - 304 stainless steel Fillet weld. Bevelled copper hold down disc used to chill. Filler wire .045" dia. - 308 ELC.	32-40	9-10	2 Approx.	Sample remains flat, no cracks visible. Manual weld. Stainless steel screen side up.
7a	Sample: FM-215 porous metal disc 3-1/2" dia. x .050" stainless steel screen side up. Transition band - 3-5/8" O.D. x .050" - 304 stainless steel; shaped in conical form. The stainless steel band was tacked to 4 steel tabs, then the steel tabs were clamped to steel plate. HW-20 torch with argon 25 CFH shielding. Filler wire - .045" - 308 ELC. Argon shield 25 CFH.	27-33	9.5 - 10.5	3-4	Eight hold down tacks were made with porous metal screen side to S.S. band before weld except that filler had to be added to two small areas. A small crack was noted where filler was added. Manual weld.
7b	Sample: 4" IPS - schedule 40 pipe cap. Specimen - 7a welded disc with 304 stainless steel band HW-20 torch, 25 CFH Argon Shield, filler wire - 0.045" - 308 ELC.	65-80	11-12	2-3 Approx.	The fillet weld caused the porous metal disc to distort somewhat. The plain side of the porous metal disc was up for this weld.

TABLE 7 (Cont'd.)

<u>Test</u> <u>Sample No.</u>	<u>Description</u>	<u>Amps</u>	<u>Volts</u> Approx.	<u>Travel</u> <u>Speed</u> <u>I.P.M.</u> Approx.	<u>Remarks</u>
8a	Sample: 2-5/8" dia. x .050", FM-215 porous metal disc, transition disc: 2-1/8" I.D. x 3-5/8" O.D. x 0.050" - 304 stainless steel. A copper disc 2-5/8" dia. used as chill plate. HW-20 torch, 25 CFH Argon shield, filler wire - 0.045" - 308 ELC.	30-42	9 - 10.5	2 Approx.	Ring and disc remain flat, no wrappage. No cracks on screen side. Plain side is not visible near weld interface because of transition ring.
8b	Sample: 4" IPS schedule 40 pipe cap, specimen 8a welded disc to 304 stainless steel band, HW-20 torch, 25 CFH Argon Shield.	72-84	10.5 - 12.5	2-3	Composite disc remain flat. No cracks. No bowing. Good weld.

TABLE 8

HYDROCARBON GETTER ENCLOSURE WELD PARAMETERS

Test Sample No.	Description	Amps	Volts (Approximately)	Remarks
1	Sample tube No. 1: Type 304 stainless steel, .275 inch I.D. x .375 inch O.D., 2 inches long. Retainer: Huyck Metal Company, porous stainless steel sheet, Type FM215 all test samples. Screen side of retainer out, plain side next to tube. Heat sink supplied by a copper rod equal to diameter of retainer (.375 inch), clamped over retainer material. 25 cfh argon shield gas. Filler .045 inch diameter, Type 308 ELC	10 - 20	9.5 - 10	Good Weld
2	Sample tube No. 2: Type 304 stainless steel, .275 inch I.D. x .375 inch O.D., formed into a ring of 1-7/8 inch I.D., two ends of tube separated by 1 inch. Screen side of retainer out as per Sample No. 1	15 - 20	9.5 - 10.5	Good Weld
3	Sample tube No. 1: Screen side of retainer next to tube. Heat sink as per Sample No. 1	16 - 22	9 - 10	Did not weld as well as sample with screen side out. Top edge of retainer tended to melt and not fill in.
4	Sample tube No. 2: Screen side of retainer next to tube. Heat sink as per Sample No. 1	16 - 24	9 - 10	Weld with screen next to tube not as good a quality as weld with screen away from tube.
5	Weld of lugs to retainer tube. HW-20 torch. 1/16 Tungsten tip. 25 cfh argon gas shield. .045 inch diameter Type 308 ELC filler wire.	20 - 26	9 - 10	Good Weld
6	Weld of lugs to enclosure head. HW-20 torch. 1/16 Tungsten tip. 25 cfh argon gas shield.	60 - 65	10 - 11	Good Weld

FIGURE 19
MICROGRAPH OF HYDROCARBON GETTER ENCLOSURE WELD
(1251-67)

FIGURE 20
HYDROCARBON GETTER ENCLOSURE - WELDED IN ENCLOSURE HEAD
(1177-67)

3.1.4 Seal-Off Device Development

The purpose of this development effort was to develop a vacuum seal-off device for use on the HTVIS that could be employed during the getter fill operation. The designed seal-off device is shown on Drawings B-664014 and B-664015 and on Figure 21. The seal-off device is composed of two components -- the female portion is welded into the HTVIS bottom enclosure head, while the male portion is in the form of a threaded plug with a gold O-ring for making a temporary seal. After the temporary seal is completed, the final seal is made by edge welding the two seal-off components together.

The development work performed included determining the torque required to produce a leak free O-ring seal, determining the weld parameters to be used to weld the seal-off to the head and to provide the final seal-off weld, and demonstrating the workability of the getter fill apparatus.

3.1.4.1 Temporary O-Ring Seal-Off

Temporary seal-off tests were conducted to determine the torque required to make a leak-tight seal while using the gold O-ring. A schematic diagram of the apparatus used to evaluate the seal is shown in Figure 22. The test was conducted by applying torque to the male component with a torque wrench until the vacuum in the enclosure was acceptable as determined by the vacuum gauge on the Veeco MS-9 leak detector. Helium was then applied to the seal and the leak rate was determined. It was thought initially that it would be possible to determine the relationship between leak rate and torque applied; however, with torques less than that required to achieve a minimum detectable leak, it was found that the leak rate was greater than the capacity of the leak detector.

Table 9 presents the torque required to effect a leak-tight seal-off for each ring tested and shows the measured seal leak rate. With the first three rings tested, it was found that an excellent leak-tight seal could be made. It was noted, however, that there was quite a variation in torques required to produce a leak-tight seal. It was first thought that this was due to the initial flattening of the weld joint on the gold O-ring. In light of this, the previously tested O-rings were retested as shown on Table 9 with similar results being obtained, except for ring No. 1. The second set of tests showed that the variation was not due to the weld joint in the gold wire as this had been flattened in the first test; therefore, most probably the torque variation was due to the difference in ring hardness due to fabrication.

Eight additional temporary seal gold O-rings were fabricated by Linde and annealed. These rings were tested to determine the torque required to produce a leak-tight seal with the test data presented in Table 9 as ring number 4 through 11. As in the previous tests, it was found that there was a wide variation in torque required to effect a seal depending on the O-ring. It is felt that this variation in torque was due to imperfections in the form of metal buildup and scratches adjacent to the ring weld. In an attempt to provide a more reproducible torque to seal relationship fabricated O-rings were obtained from a vendor with the specification that the area of the weld be smoothed to the diameter of the wire used in the ring.

FIGURE 21

GETTER SEAL OFF DEVICE

FIGURE 22 SCHEMATIC OF GOLD O-RING SEAL-OFF TEST APPARATUS

TABLE 9

45.

SEAL-OFF APPARATUS - GOLD RING SEAL TESTS

Ring Number	Torque Required (Ft.-Lb.) For Seal	Remarks
1	17.5	Linde Fabricated
1 Repeat	62.5	" "
2	42.5	" "
2 Repeat	42.5	" "
3	95	" "
3 Repeat	110	" "
4	27.5	Linde Fabricated Batch annealed at 750°F
4 Repeat	22.5	for 30 minutes in a salt bath and air
5	22.5	cooled.
5 Repeat	25	
6	50	Repeat Tests conducted using second seal-
6 Repeat	40	off device.
7	37.5	" "
7 Repeat	No seal at 65.	" "
8	No seal at 50	" "
8 Repeat	75	" "
9	70	" "
9 Repeat	25	" "
10	37.5	" "
10 Repeat	55	" "
11	50	" "
11 Repeat	30	" "
12	25	Supplied by Aero-Vac Corporation per
13	40	Drawing A-664032.
14	30	" "
15	30	" "
16	15	" "
17	45	" "
18	30	" "

Seven additional temporary seal gold O-rings were tested to determine the torque required to achieve a minimum detectable leak seal. The gold O-rings used for this test were supplied by Aero-Vac Corporation as per Linde Drawing A-664032. Of the O-rings delivered, not all were of acceptable quality. Any of the following defects causes the O-ring to be of unacceptable quality: 1) inside diameter not within tolerance, 2) melt down pot mark at the weld joint, 3) raised bead at the weld joint, 4) saw cut marks near the weld joint. Five O-rings of acceptable quality (No. 12-16) and two O-rings of unacceptable quality (No. 17 and 18) were tested. The test results presented in Table 9 show that the torque range required for an acceptable O-rings to achieve a minimum detectable leak seal is from 15 to 40 ft-lbs. The maximum torque required to seal an O-ring judged of unacceptable quality was only 45 ft-lbs.

As a result of the torque-leak rate tests performed on the Aero-Vac gold O-rings, Table 9, Nos. 12 - 18, the torque used to provide the temporary seal on the HTVIS units was specified to be 75 ft-lbs.

3.1.4.2 Seal-Off Weld Parameters

Edge weld tests were performed to determine the parameters for hand Heliarc welding the seal-off device ; into the bottom head of the vacuum enclosure and for providing the edge weld type permanent vacuum seal-off. Four simulated edge weld joints were machined from Type 304 stainless steel tubing to simulate the edge weld joint geometry (Figure 23). The first sample was used to determine the required current. The weld parameters used for welding these joints are presented in Table 10.

TABLE 10

SEAL-OFF DEVICE EDGE WELD PARAMETERS

<u>Sample</u>	<u>Amps</u>	<u>Volts</u>	<u>Weld Speed</u> <u>I.P.M.</u>	<u>Shield Gas</u>	<u>Comments</u>
Exp.	32	11.0	--	25 cfh argon	--
	40	11.2	--	25 cfh argon	--
	48	11.2-11.5	--	25 cfh argon	Selected as best
1.	47-50	11.25-11.5	8	25 cfh argon	Good weld
2.	46-48	11.25-11.5	9	25 cfh argon	Good weld
3.	47-49	11.25-11.5	8	25 cfh argon	Good weld

Following the welding, the edge weld joints were leak checked. Each of the joints showed a leak rate of less than 5×10^{-11} std-cc per second of air as determined on a Veeco MS-9 leak detector. An excellent leak-tight edge-type joint can be produced using the weld parameters presented in Table 10.

FIGURE 23 SIMULATED SEAL-OFF EDGE WELD JOINT

A test using an actual seal-off device was performed to determine if the welding for the permanent seal-off would cause any leakage of the gold O-ring type temporary seal-off. It was found that the leak rate of the temporary seal-off did not change either during or after the final seal-off weld was performed.

To perform the test, a female seal-off unit (Drawing No. B-664015) was edge welded to an 8 x 8 x 3/8 inch - Type 304 stainless steel flange, and a male seal-off unit (Drawing No. B-664014) fabricated. A gold O-ring (Drawing No. A-664032) supplied by Aero-Vac Corporation was used for this test. The torque loading on the gold O-ring seal was increased gradually from 5 to 40 ft-lbs. to make an acceptable leak tight seal. A Veeco leak detector was used to check the leak rate of the seal at a torqued 40 ft-lbs. indicated an acceptable leak-tight joint (less than 3.86×10^{-11} std. cc air/sec.). The torque loading on the gold O-ring was increased to 75 ft-lbs. and a leak rate of less than 3.77×10^{-11} std. cc air/sec. was indicated.

During the welding operation, the Veeco leak detector was connected to the seal-off system to detect any leakage of the gold O-ring seal. The final seal-off edge welding was started with approximately 2 cfh of helium in the shielding gas to allow detection of any gross leakage on the detector. After welding approximately 1 inch length of the edge weld, the welding was stopped and 100% helium was sprayed around the joint. No leakage was indicated at this point.

Because of the existence of the torque rod in the male component, continuous welding could not be performed. Three short runs of weld were made and after each case run, a helium leak check was made. With approximately 3/4 inch length of joint left to be welded, the joint area was bagged in helium for 10 minutes and leak rate at this point was found to be less than 3.86×10^{-11} std. cc air/sec. The weld was then completed, following this leak check, and is shown in Figure 24 as the inside weld.

Weld parameters for above edge weld were as follows:

HW-20 torch, 1/16 tungsten with gas lens, 20 cfh argon and 2 cfh helium, manual weld. Current - 50 to 52 amps; voltage - 9.5 to 11.5 volts. Speed - 6 to 7 IPM.

To determine the leak rate of the gold O-ring seal and weld seal, a small hole (No. 56 drill, .046 inch diameter) was drilled through the male seal-off unit between the two seals. The volume between the two seals was evacuated and a leak check was performed on each seal individually. The leak rate for the welded joint was less than 4.14×10^{-11} std. cc air/sec. while the leak rate of the gold O-ring seal was less than 4.2×10^{-11} std. cc air/sec., showing excellent leak tightness.

3.1.4.3 Demonstration of Getter Fill and Seal-Off

The apparatus used to insert the getter and provide the temporary seal-off is shown schematically on Figure 25 (Drawings No. D-664076). This apparatus was used to determine the acceptability of the getter fill technique and temporary seal-off.

FIGURE 24
SEAL-OFF DEVICE SHOWING FINAL SEAL-OFF WELD
(967-67)

FIGURE 25 SCHEMATIC OF GETTER INSTALLATION & SEAL-OFF APPARATUS

The glass getter enclosure is shown on the right side of Figure 25 in the upper portion. The valve below the getter container is used to allow the getter to be transferred by gravity into the unit after the unit has been evacuated. Prior to inserting the getter, the glass tube which traverses through the O-ring seal is inserted all the way into the test apparatus as shown. After the getter has been inserted, the glassware is raised through the O-ring type joint shown and the male component of the seal-off device with the gold O-ring is threaded into the female portion mounted on the unit. The required torque to implement the seal-off is applied by turning the drive rod shown in the middle of the seal-off apparatus. The unit is evacuated through the vacuum valve on the left side of the apparatus.

A simulated getter fill and seal-off was performed using the getter installation and seal-off apparatus shown on Figure 25. For this test, a simulated getter was prepared using 35 grams of talcum powder plus 5 grams of santocel powder to give a bulk density of .34 grams/cc. The bulk density of the getter is in the range of .30 to .35 grams/cc. Simulated getter was used in place of actual getter because getter cannot be exposed to air without a reaction. It was, therefore, decided that for this test it would be safer to use a simulated getter until the apparatus performance had been demonstrated.

During this test it was observed that the simulated getter powder tended to pack just above the glass valve, stopping the flow into the unit. To resume the flow an electric Vibograder tool was applied to the quick connect coupling sealing the glass tube, causing the flow to be resumed. It has been observed qualitatively that the actual getter flows much more freely than the simulated powder used for this test, therefore, this packing should not be a problem in the actual units, however the remedy to resume flow if required is as above.

To provide the temporary seal for this test, the seal-off torque was 70 ft-lbs. After the evacuation, getter fill and seal-off, the apparatus was removed and the temporary seal was leak checked using a Veeco MS-9 leak detector. The leak rate was determined to be 2.81×10^{-10} std. cc air/sec. which is excellent.

Upon opening the test unit, it was noted that the simulated getter powder was piling up in the getter enclosure in the form of a pyramid directly below the fill hole and was thus obstructing the flow path of the simulated getter. Further development work was performed to determine methods to distribute the getter in the getter enclosure and thus preclude a getter pile up as described in the succeeding paragraphs.

Two getter fill demonstration tests were performed to check out the operation of the seal-off device and associated getter fill hardware. A bottom enclosure head similar to that to be used for the HTVIS units was machined to the required dimensions for the seal-off device -- female portion (B-664015). The seal-off device was then edge welded to the head using the following weld parameters: Current - 50-52 amps; Volts - 8.5-10; Speed - 6-7 IPM.

A 5/8 inch thick plexiglass sheet, beveled on its edge to the inside head contour, was adhered to the inside of the head to simulate the getter retainer material. A spacing of 1/2 inch was provided between the inside edge of the female seal-off unit and the surface of the plexiglass sheet.

The first getter installation demonstration test was started by mounting the enclosure head on a tilt table and securing the getter fill apparatus to the head as shown in Figure 26. The glass getter feeding device was filled with 15 grams of regular getter and evacuated before insertion into the getter fill apparatus. The object of the test was to demonstrate that the getter is being inserted through the female seal-off unit and that it flows freely and does not pile just below the seal-off unit and thereby stop the flow. The getter fill was accomplished with the axis of the test head parallel to the direction of gravity. Figure 27 shows the spread of getter as it was discharged from the feed tube. The spread of the getter blackened the plexiglass surface and the experiment was not conclusive enough to make the statement that the problem of pile-up does not exist. At this point, the table containing the test setup was tilted gradually from 0 to $\pm 25^\circ$ angle from the direction of gravity. It was noted that the getter spread was substantial in these tilted conditions.

For the second demonstration test, the inside of the plexiglass sheet was located a distance of 3/8 inch from the inside flat of the female seal-off unit. The volume available for getter was calculated to be 12.5 inch³. Ten grams of regular getter will occupy a volume of ~ 1.22 inch³, therefore, sufficient getter space is available.

The enclosure head with associated getter fill hardware was mounted to a tilt table as shown in Figure 28. The angle between the axis of the head and the direction of gravity was approximately 60° . The grams of regular getter was inserted into the getter cavity. Figure 29 shows the getter after installation into the getter cavity. It can be seen that the getter did not pile up under the female seal-off device causing any restriction in flow. When the glass valve on the getter fill tube was opened, the getter flowed smoothly into the unit. This test demonstrated that the required amount of getter can be inserted into the unit if the unit is oriented with the unit axis at approximately a 60° angle with the direction of gravity.

3.1.5 Weld Development Tests

The purpose of the weld development test work was to develop weld parameters to be used for the automatic girth enclosure weld, semi-automatic neck tube (inner liner) weld, manual receptacle weld, and manual seal-off plug weld.

3.1.5.1 Automatic Girth Weld

The determination of automatic Heliarc welding parameters for the girth weld on the vacuum enclosure shell was started by automatically welding eight flat plate specimens employing both 30° and 45° bevel joints.

FIGURE 26
GETTER FILL APPARATUS - DEMONSTRATION TEST NO. 1
(999-67)

FIGURE 27
INSTALLED GETTER - DEMONSTRATION TEST NO. 1
(1001-67)

FIGURE 28
GETTER FILL APPARATUS - DEMONSTRATION TEST NO. 2
(1144-67)

FIGURE 29

INSTALLED GETTER - DEMONSTRATION TEST NO 2.
(1143-67)

The purpose for the flat plate specimens was to determine the starting weld parameters for the simulated joints and to evaluate the weldability of the 30° and 45° bevel joint. The apparatus used for the automatic welding is shown in Figure 30. Table 11 presents the data collected while performing the welds on the eight flat plate specimens. In general, it was found that the 45° bevel joint weld with no gap was the most satisfactory weld to perform.

Following the flat plate weld work, four 3 inch O.D. Type 304 stainless steel pipes were machined for weld evaluation. Two of the pipes were machined with the 30° bevel and two pipes with the 45° bevel. The weld parameters developed for the flat plates (shown on Table 11) were used as a starting point for performing the 3 inch pipe welds. Table 12 presents the data collected during the welds. It should be noted that the welds using the 30° bevel were not successful. During the welding, the backup strip burned through. The two 45° bevel joints were satisfactorily welded. These two welds were X-rayed, helium leak checked and found to be acceptable.

At this point, the zero gap joint with the 45° bevel was selected for further evaluation. The zero gap joint prevents potential burn-through of the backup plate, and in addition this joint is self-aligning and, therefore, does not require the use of spacers during the initial fabrication tacking operation.

To further define the automatic girth weld parameters and to demonstrate the repeatability of welding this joint, five 6 inch O.D. Type 304 stainless steel pipes were first machined as shown on Figure 31 for welding. The 6 inch pipes were then tack welded (hand) and dimensional measurements were taken to determine the initial measurements prior to welding. Table 13 presents the details of the automatic welding of the five 6 inch diameter pipe joints and Figure 32 shows the welded pipes. After welding the joints were X-rayed, and helium leak checked. The X-ray film showed satisfactory welds for all joints except No. 1 where some unfilled pores were detected. The leak rate tests, however, showed all five joints to be leak-tight within the limits determinable by the Veeco MS-9 leak detector. Leak rates were in the order of less than 5×10^{-11} std. cc air/sec. which is excellent leak tightness.

Two inch wide strips were cut from each of the 6 inch pipes perpendicular to the weld joints and prepared for tensile specimens as shown in Figure 33. The specimens thus prepared were too short (7-1/2 inches long) to provide an adequate tensile test machine jaw grip area so a 6 inch long x 3/8 inch thick 304 stainless steel plate was butt welded to the end of each specimen for the test.

Each specimen was tensile tested and the results are presented in Table 13 with Figure 34 showing the failed specimens. All failures were through the weld joint which exhibits the minimum cross section area. The welds were not built up higher than the parent material in order to eliminate any need for grinding the weld to meet dimensional tolerances. The ultimate stress, which in all specimens was greater than 87,600 psi, was based on thickness measurements through the weld in the estimated fractured area.

FIGURE 30

AUTOMATIC HELIARC WELDING APPARATUS
(1875-66)

TABLE 11

PREPARATORY AUTOMATIC HELIARC WELDING INFORMATION (FLAT PLATE)

AUTOMATIC WELDER DETAILS: -

P6H-H.W.-27 torch with wire feed attachment set up on OM-48 carriage using
SEH-2 wire feeder 3/64 (.045") - 308 elc. wire filler

WELD DETAILS

Specimen Number	Specimen Details And Geometry	Gap	Arc Length	Filler Wire Feed IPM	Travel Speed IPM	Power		Shield Gas		Heat Input Kilo Joules	Remarks
						Amps	Volts	Ar- CFH	He		
1	3/16" x 2" x 6" - 2 Such 304 s.s.; with 16 GA - 304 backup strip, 1/32 Nose - 30° Bevel	3/32"	3/32" to bottom of the joint	Pass I 30	10	200	12.5	30			One small hole 1/32" diameter on side away from ground Several holes, center on side away from ground Bead not flush, needs more filler
				Pass II 90	10	224	12.5	30			
2	Same	3/32"	Same	Pass I 90	10	240	13.5	40		19.4	Joint filled to within 1/16" of flush. X-Ray showed dark lines as though edges not melted in. Second Pass - Good bead 3/8" wide.
				Pass II 140	10	244	14.0	40		20.4	
3	Same only 1/16" Nose	3/32"	Pass I - 1/8	100	15	240	14.5	Stopped after 1-1/4" Bead to narrow, No wire added for first 1-1/4"			Joint filled to within 1/32" of flush, slightly heavier first half of weld. Wire feed started after 1-1/4" - not enough current - bead too narrow.
			Pass II - 3/32	100	15	320	13				
4	Same only 1/32" Nose	3/32"	Pass I - 3/32	100	15	312	12.5	40			First Pass - Several holes at start. Second half of weld o.k. Not enough current - Discontinued. Second Pass to try helium-argon mixture shielding.
			Pass II - 1/8	125	15	304	14.8	20	40	17.4	
5	Plate same, weld geometry 45° Bevel, 1/32" Nose	None	Pass I - 1/8	80	15	245-250	11-12	25	75	11.4	First Pass - Wire feed stuffing first 1/2 weld. First 1/2 filled to within 1/32" of flush. Second Pass - good cover bead first 1/2 of weld not filled enough second half of weld.
			Pass II - 1/8	80	15	240-242	13-13.5	25	75	12.8	
6	Same	None	Pass I - 1/8	80	15	288	14	25	75	16.2	First Pass - Good bead within 1/32" of flush - No penetration thru backup plate. Second Pass - Good bead, did not quite fill near one edge 80% pene- tration to backup plate.
			Pass II - 1/8	125	15	284	15	25	75	17.0	
7	Same	None	Pass I - 1/8	100	15	320-322	13.5-14	25	75	17.9	Good heavy pass 3/8" to 7/16" wide. No penetration to backup plate.
			Pass II - 3/32	100	15	312	15	25	75	18.7	
8	Same with 30° Bevel and 1/16" Nose	3/32"	Pass I - 3/32	100	15	256-262	13-15	25	75	15.4	Several small holes along near edge. No penetration Good cover pass - not much crown but filled in.
			Pass II - 1/8	100	15	280	15	25	75	16.8	

TABLE 12

PREPARATORY HELIARC AUTOMATIC WELDING (PIPE)

Equipment: Same as used for automatic flatplate welding (Table 2)

Specimen Number	Pass Number	Pipe Size And Type	Edge Prep.	Filler Wire	Gap	Arc Length	Filler Wire IPM	Travel Speed IPM	Shielding Gas (cfh)		Power		Heat Input Kilo- Joules	Remarks
									Ar	He	Amps	Volts		
1	1	304 S.S. 3" Dia. Pipe	30° Bevel 1/16" Nose	3/64"-308L	3/32"	3/32"	60	15	25	75	320-330	14.5-15.0	-	Burn Through
2	1	304 S.S. 3" Dia. Pipe	30° Bevel 1/16" Nose	3/64"-308L	3/32"	3/32"	80	15	25	75	288	15.5	17.9	Burn Through
1	1	304 S.S. 3" Dia. Pipe	45° Bevel 1/32" Nose	3/64"-308L	None	1/8"	80	15	25	75	290-292	13.5-13	15.5	Good weld filled to within 1/32" of flush
	2					1/8"	125	15	25	75	292-296	15.0	17.5	
2	1	304 S.S. 3" Dia. Pipe	45° Bevel 1/32" Nose	3/64"-308L	None	3/32"	80	15	25	75	296-300	13.5-14	16.2	Smooth bead on surface - wire stuffed against tacks causing torch wire assembly to jiggle.
	2					3/32"	125	15	25	75	288-290	16.0	18.5	Good second pass for edge weld not completely filled.

FIGURE 31 ENCLOSURE GIRTH WELD JOINT - 45° BEVEL

TABLE 13

DETAILS OF AUTOMATIC HELIARC WELDING, ENCLOSURE WELD

SPECIMEN:	- 6" O.D. 304 S.S. Pipe
WELD JOINT:	- 45° Bevel, 90° included, 1/32" Nose, No gap
FILLER WIRE:	- 0.045" Diameter - 308 L
SHIELDING GAS:	- Argon - 25 CFH, Helium - 75 CFH
SPECIMEN TRAVEL SPEED:	- 15 Inch Per Minute
WELD PREPARATION:	- All welds held by 4 tacks prior to automatic welding
ARC LENGTH:	- 1st Pass: - 3/32" + .01 - 2nd Pass: - 1/8" + .015"
EQUIPMENT:	- P&H - HW-27 Torch with wire feeder attachment set on OM-48 carriage using SEH-2 wire feeder located in Metallurgical Development Laboratory, Building 52, Linde Division, Tonawanda, New York

TABLE 13 (Cont'd)

DETAILS OF AUTOMATIC HELIARC WELDING, ENCLOSURE WELD

Specimen No.	Pass No.	Filler Wire Feed IPM	Power		Shrinkage Data					Tensile Test Data					Comments
					Pipe Dia. (In.)		Across Weld at 4 Points			Cross Sectional			Fail Load (Pounds)	Ultimate Stress (PSI)	
					Before Weld	After Weld	90° Apart	Width (In.)	Thick (In.)	Area (In. ²)					
			Amps	Volts			Before	After	Change						
1	1	80	296-300	14	6.506	6.440	.782	.742	.040	1.502	.186	.279	25,100	89,900	1st Pass - Arc somewhat erratic. Did not fill all points. Many small deep holes
	2	100	288-294	15			.776	.720	.066						2nd Pass - Cover pass weld ran o.k. Good flat bead, slight crown. Some buildup at finish point.
							.775	.710	.065						
2	1	80	296-304	12.5-13.0	6.506	6.455	.774	.730	.044	1.502	.199	.298	26,100	87,600	1st Pass - Good bead, no mechanical trouble.
	2	125	292-297	14.5-15.0			.721	.682	.039						2nd Pass - Good bead-excess of filler-did not crown over clearance limit.
							.722	.682	.040						
3	1	80	296-304	12.5-13.0	6.499	6.442	.701	.656	.045	1.499	.201	.301	26,650	88,200	1st Pass - Good bead, no mechanical trouble.
	2	100	292-296	14.5-15.0			.714	.666	.047						2nd Pass - Good bead, filled but not excessive.
							.711	.663	.048						
4	1	80	296-302	12.5-13.0	6.501	6.447	.723	.674	.049	1.499	.194	.290	25,700	88,600	1st Pass - Good bead, seemed to go in well. No mechanical trouble, heavy side favored by 1/32"
	2	100	292-296	14.0-14.5			.711	.670	.041						2nd Pass - Good cover pass, no excessive crowning.
							.710	.669	.041						
5	1	80	302-306	12.5	6.492	6.445	.709	.670	.039	1.502	.195	.292	26,050	89,200	Good beads on both passes.
	2	100	290-294	14.5-15.0			.668	.615	.053						
							.673	.632	.041						

FIGURE 32

AUTOMATIC HELIARC WELDED ENCLOSURE JOINTS - 6 INCH PIPE
(127-67)

FIGURE 33

TENSILE SPECIMENS FROM ENCLOSURE JOINTS ON 6 INCH PIPE
(147-67)

FIGURE 34

FAILED TENSILE SPECIMENS FROM ENCLOSURE JOINTS ON 6 INCH PIPE
(620-67)

To show the enclosure weld joint in greater detail, micrograph specimens were cut from the 6 inch O.D. pipe weld specimens No. 3, 4, and 5. The micrograph shown in Figure 35 is typical of all the micrographs. The micrographs showed that penetration into the backup strip was accomplished without burn-through. It can also be seen that there is no porosity or gross cracking in the weld zone and that there is good penetration of the second pass into the first pass without cold shuts or cracking. The enclosure girth weld parameters to be used on the HTVIS units are presented on Drawing D-664034.

To demonstrate a leak repair technique, one of the 3 inch diameter pipe girth weld joints was drilled with a No. 43 drill through the weld bead to cause a leak. To repair the leak, the drilled hole area was ground out to a depth of approximately 3/16 inches and 1-1/4 inches long. Repair was made by manual heliarc welding using an HW-20 torch with 25 cfh argon shielding and 3/32 inches diameter type 308 filler wire. Three passes were required to repair the leak with the weld parameters as follows:

<u>Pass Number</u>	<u>Amps</u>	<u>Volts</u>
1	114 - 126	12.5 - 13.5
2	150 - 168	11.5 - 13.0
3	102 - 108	10.5 - 11.5

After the repair was accomplished, the joint was leak checked with a Veeco MS-9 helium leak detector and found to be leak tight within the sensitivity of the leak detector.

3.1.5.2 Semi-Automatic Neck Tube Weld

Simulated neck tube joint welds between the Hastelloy-X neck tube material and the Type 304 stainless steel enclosure material were performed to determine the required weld parameters for an acceptable joint. Three joints each of 2-1/2 inch diameter and 5 inch diameter were semi-automatic heliarc welded. In the semi-automatic welding process, a welder manually holds the torch with the aid of a steady rest while the specimen rotates providing the weld travel speed. The neck tube edge weld joint geometry used to develop weld parameters is shown in Figure 36.

The three 2-1/2 inch O.D. simulated joints No. 1, 2, and 3 were semi-automatically welded changing the weld parameters for each weld as shown on Table 14 to achieve desirable weld conditions. The three specimens (Figure 37) were then leak checked with a Veeco MS-9 leak detector with no indicated leakage within the sensitivity of detector (less than 4.9×10^{-11} std. cc air/sec.).

To demonstrate the capability to repair a leak in the neck tube weld joint, simulated weld specimen No. 3 was drilled with a No. 57 drill through the center of the weld to a depth of 3/16 inches thus causing a leak. The leak

FIGURE 35

MICROGRAPH OF ENCLOSURE GIRTH JOINT WELD SPECIMEN NO. 4
(740-67)

FIGURE 36 NECK TUBE WELD JOINT GEOMETRY

TABLE 14

WELD PARAMETER FOR SEMI-AUTOMATIC NECK TUBE EDGE WELD

General Note: - All welds contain 4 tacks. Melt down pass, no filler added, edge set flush

Specimen No.	Hastelloy-X Neck Tube Size			304 Stainless Steel Flange Size			Travel I.P.M.	Power		Avg. Heat Input Kilojoules	Maximum Load Lbs.	Comments
	O.D.	I.D.	Wall	I.D.	O.D.	Wall		Amps	Volts			
1	2.498" to 2.500"		0.063" to 0.065"	2.506"	2.632"	0.063"	5	80-82	10.5-12.5	11.18	34,700	Weld bead heavy-considerable roll over on I.D., poor gas cover on I.D. S.S. flange edge favored during weld.
2	2.502"	2.374"	0.062" to 0.063"	2.500" to 2.510"	2.633" to 2.630"	0.061" to 0.062"	10	70-72	10.5-11.5	4.69	24,900	Weld bead medium light-very little roll over, 5 CFH argon auxiliary flow on I.D. of tube.
3	2.478"	2.350"	0.063" to 0.065"	2.483"	2.667"	0.063" to 0.064"	7.5	70-72	9-11	5.69	23,600	Weld bead heavy-roll over on I.D., some high points along I.D., auxiliary argon flow 5 CFH on I.D.
4	4.904"	4.780"	0.062"	4.910"	5.034"	0.062"	7.5	71-73	11.0-12.5	6.7	No Tensile Test Made	Excessive roll over, some high spots, S.S. side melted down to bottom of groove.
5	4.904"	4.780"	0.062"	4.910"	5.034"	0.062"	10	71-73	11.0-12.5	5	No Tensile Test Made	Uniform bead-slight roll over on Hastelloy-X side, S.S. side melted down approximately 1/32"
6	4.904"	4.780"	0.062"	4.910"	5.034"	0.062"	10	71-73	11.0-12.5	5	No Tensile Test Made	Uniform bead same as Specimen No. 5 Beautiful weld.

FIGURE 37
SIMULATED NECK TUBE WELD JOINTS - 2.5 INCH DIAMETER
(652-67)

was prepared for repair by grinding the weld bead 1/16 inch deep by 3/8 inches in length. The repair was made by manual heliarc welding using a .045 inch diameter 308 ELC filler rod, 25 cfh argon shield gas with an HW-20 torch. Two passes were required each employing 36-42 amps and 8.0 - 9.0 volts. Following the leak repair, the specimen was again leak checked with the result of no detectable leakage.

The three 2-1/2 inch diameter neck tube joint specimens No. 1, 2, and 3 were tensile tested. All the specimens exhibited maximum loads greater than 23,600 pounds. Specimen No. 3 was not properly aligned in the tensile test machine and therefore failed at a load somewhat lower than would be expected. The ultimate stress for these weld specimens was not calculated due to inability to accurately determine the cross section area of the weld prior to testing. For the purpose of this development, testing the maximum load per inch of weld is all that is required to determine that the joint has sufficient strength capability to support the nuclear radiation shield under 6 'g' dynamic shock conditions.

Following the weld parameter development and tests on the 2-1/2 inch diameter neck tube joints, the 5 inch diameter edge weld joints were welded to further refine the weld parameters for the actual size weld joint. Three 5 inch O.D. specimens (No. 4, 5, and 6) were semi-automatic heliarc welded with the parameters as presented in Table 14. The welded specimens are shown in Figure 38. In this figure, specimen No. 5 is shown prepared for a leak check with a flat plate soldered to the Hastelloy-X neck tube material to seal-off the open end of the tube.

All three weld specimens were leak checked with the Veeco MS-9 leak detector with the result that there was not detectable leakage (leak rate less than 5.57×10^{-11} std. cc air/sec.). The 5 inch O.D. specimens were not tensile tested but were X-rayed. The X-rays taken at a 45° angle were clear, indicating that there was not porosity in the weld.

The selected weld parameters for the semi-automatic neck tube weld are presented on Drawing D-664034.

3.1.5.3 Manual Receptacle Weld

To determine the weld parameters for welding the receptacle to the enclosure head, six development welds were performed. For this program, receptacles were machined to simulate the unit receptacles (same inside and outside diameters). The enclosure head was simulated by a 5 inch square stainless steel plate, 5/16 inches thick. A 1 inch diameter hole was bored in the center of the flat plate at a 30° angle to simulate the angle at which the receptacle intersects the enclosure head. A special angle type fixture was machined to aid in the welding, leak checking, shrinkage measurements, and tensile testing. This fixture is shown in Figure 39.

The weld parameters were changed for each of the first three specimens to determine the best weld. Each specimen was measured before and after welding to determine the axial shrinkage. Following the welding, each

FIGURE 38

SIMULATED NECK TUBE WELD JOINTS - 5 INCH DIAMETER
(713-67)

FIGURE 39

RECEPTACLE WELD DEVELOPMENT FIXTURE
(1873-67)

specimen was helium leak checked and tensile tested to failure. Table 15 presents the receptacle weld data. Weld specimen No. 2 was selected as best based on minimum leak rate and shrinkage. Three additional specimens were welded using the parameters of specimen No. 2. These welds were also measured for shrinkage, leak rate, and ultimate load with the results also presented on Table 15.

Figure 40 shows weld specimen No. 3 just prior to failure. It can be seen that the bottom flat of the receptacle is deflected outward. Figure 41 shows weld specimen No. 1 after failure. The failures occurred in the cylindrical wall of the receptacle, as expected, with no failure observed in any of the six welds. The measured load to failure is approximately twelve times the load required to yield the tension rod, showing an adequate design factor in the receptacles.

The weld parameters for welding the receptacle to the enclosure head on the HTVIS units are presented on Drawing D-664071.

3.1.5.4 Manual Seal-Off Plug Weld

Six development welds were performed to determine the weld parameters for welding the seal-off plug to the receptacle. The receptacles for this test were machined to have the same outside diameter, inside diameter, and cut-off angle as the unit receptacles. The seal-off plugs were actual unit seal-off plugs machined to Drawing A-664043. The weld parameters were varied on the first three specimens welded in order to select the best weld. Following the welding, shrinkage and leak rates were determined. Although all of the first three specimens were acceptable, specimen No. 3 was selected as best based on minimum shrinkage and leak rate. Table 16 presents the weld parameters for the seal-off plug weld development. Three additional specimens were welded using the parameters of specimen No. 3 as a guide. These specimens were measured for shrinkage and helium leak checked and found to be acceptable. Figure 42 shows the completed seal-off weld on specimen No. 4.

The weld parameters for welding the seal-off plug to the receptacle on the HTVIS units are presented on Drawing D-664034.

3.1.6 Neck Tube Static Proof Test

The purpose of the neck tube static proof test was to experimentally determine the static strength of a neck tube and compare the test results with that predicted by analysis based on literature data. The test apparatus used in this development is shown in Figure 43. A static load (increased by increments) was applied by a hydraulic jack at the center of gravity of the support system (neck tube and one tension rod) until failure occurred in the neck tube. The neck tube failed in shear buckling when the total load on the support system was 4072 pounds. The calculated load to fail the neck tube in shear buckling was 4017 pounds with the calculations presented in Appendix B.

TABLE 15

Receptacle to Enclosure Head Weld DataManual Heliarc WeldArgon at 25 cfh

<u>Specimen Number</u>	<u>Fillet Size (Inch)</u>	<u>Speed (IPM)</u>	<u>Amps</u>	<u>Volts</u>	<u>Filler Wire</u>	<u>Average Shrinkage (Inch)</u>	<u>Leak Rate Std. cc Air/Sec.</u>	<u>Fail Load (Pounds)*</u>	<u>Remarks</u>
1	5/32	1-3	75-110	9.5-11.0	308 ELC .094 dia.	.0225	16.5×10^{-11}	19,825	
2	1/8	1-3	80-96	9.5-10.5	308 ELC .045 dia.	.0177	9.15×10^{-11}	20,780	Selected for specimens 4, 5, and 6
3	3/32	1-3	65-88	9.5-11.0	308 ELC .045 dia.	.0204	9.35×10^{-11}	21,380	
4	1/8	1-3	80-88	9.5-11.0	308 ELC .045 dia.	.0165	11.0×10^{-11}	19,680	
5	1/8	1-3	80-88	9.5-11.0	308 ELC .045 dia.	.0200	3.57×10^{-11}	19,500	
6	1/8	1-3	76-88	9.5-11.0	308 ELC .045 dia.	.0223	11.0×10^{-11}	19,520	

* Weld did not fail on any specimen. Failure occurred in cylindrical wall of receptacle.

FIGURE 40
RECEPTACLE WELD SPECIMEN NO. 3 BEFORE FAILURE
(1546-67)

FIGURE 41
RECEPTACLE WELD SPECIMEN NO. 1 AFTER FAILURE
(1547-67)

TABLE 16

Seal Off Plug to Receptacle Weld DataManual Heliarc WeldArgon at 25 cfh

<u>Specimen Number</u>	<u>Fillet Size (Inch)</u>	<u>Speed (IPM)</u>	<u>Amps</u>	<u>Volts</u>	<u>Filler Wire</u>	<u>Average Shrinkage (Inch)</u>	<u>Leak Rate Std. cc Air/Sec.</u>	<u>Remarks</u>
1	1/8	2-3	44-56	9.0-10.0	308 ELC .045 Dia.	.0027	7.32×10^{-11}	
2	3/32	2-3	40-52	8.5-9.5	308 ELC .045 Dia.	.0031	7.50×10^{-11}	
3	3/32	2-3	38-44	8.5-10.0	308 ELC .030 Dia.	.0020	7.30×10^{-11}	Selected for speci- mens 4, 5, and 6
4	3/32	2-3	42-50	9.0-10.5	308 ELC .030 Dia.	.0015	5.25×10^{-11}	
5	3/32	2-3	44-48	9.0-10.0	308 ELC .030 Dia.	.0022	7.14×10^{-11}	
6	3/32	2-3	46-50	8.5-10.5	308 ELC .030 Dia.	.0018	7.24×10^{-11}

FIGURE 42
RECEPTACLE SEAL-OFF PLUG WELD SPECIMEN NO. 4
(1565-67)

FIGURE 43
STATIC PROOF TEST APPARATUS - FAILED NECK TUBE
(1483-67)

The neck tube failed by forming 45° wrinkles, which indicates that the mode of failure was shear buckling. The 45° wrinkles on the neck tube are shown on Figure 43. The calculated stress in the tension rod at the load when the neck tube failed was 37,200 psi, which is above the proportional limit (30,000 - 32,000 psi at room temperature) of the tension rod material.

The strain measured in the tension rod indicated that the stress in the tension rod exceeded the proportional limit and that the proportional limit of the material was about 30,000 psi. The strain measured in the tension rod is shown on Figure 44.

The stress in the tension rod was expected to exceed the proportional limit of the material for the static proof test because the neck tube and tension rod was tested to failure at ambient temperature. Since the neck tube is stronger at ambient temperature than in the hot condition, the neck tube was designed to fail in the hot condition at the 9 'g' design load of 3121 pounds. When the neck tube is failed at ambient temperature, the calculated load to fail the .011 inch thick Inconel-750X neck tube used in the static proof test was 4017 pounds and the load to fail the .012 inch thick Hastelloy-X neck tube in the actual unit was 4435 pounds. The stress in the tension rod in the actual unit was calculated to be 36,770 psi at 4435 pounds applied load and 30,000 psi at the 9 'g' design load.

The deflections of the neck tube and the tension rod in the radial direction were .019 inches and .028 inches, respectively, at failure of the neck tube. The calculated deflections of the neck tube and tension rod were .0055 inches and .0045 inches, respectively. The measured and calculated deflections are shown in Figure 45 as a function of the applied load. It can be seen from this figure that the measured deflections of the neck tube and tension rod varied linearly with the applied load from 0 to 3700 pounds. In this load range, the measured deflections of the neck tube and tension rod were 3.2 and 4.8 times larger than the calculated deflections.

Because the measured deflections of the neck tube and tension rod were larger than the calculated deflections, a separate tensile test was run on the tension rod alone, to determine the stress-strain relationship for the tension rod. One sample of Inconel-625 solution annealed male rod and one sample of Inconel-718 age hardened female rod were assembled into a tension rod and subjected to a tensile test in a Baldwin Tensile Tester. The simulated tension rod tested is shown on Figure 46. The elongation of the tension rod was measured by an extensometer and load versus strain was recorded on a stress-strain recorder. The load was first applied to 1600 pounds or 27,350 psi stress, which is somewhat below the 30,000 psi proportional limit, and then the load was released to zero. It was found that in this load range, the tension rod did not exhibit any permanent deflection. The test was repeated several times with the same results. The load then was increased to 2895 pounds or 49,490 psi stress, which is above the proportional limit. From this test, the actual proportional limit of the tension rod was determined to be 31,600 psi.

FIGURE 44
STRAIN VS. APPLIED LOAD IN TENSION ROD
(STATIC PROOF TEST)

FIGURE 45
DEFLECTION VS. LOAD FOR NECK TUBE AND
TENSION ROD (STATIC PROOF TEST)

FIGURE 46
SIMULATED TENSION ROD ASSEMBLY FOR LOAD DEFLECTION TEST
(1485-67)

To determine if a permanent deflection was occurring in the spherical washer, a spherical washer was carefully measured for length and diameter and loaded with 1850 pounds force using a 1/2 inch diameter ball to transmit the hydraulic jack load to the spherical washer. Measurements taken on the spherical washer after the test showed no change in diameter and only .0001 inch change in length.

The theoretical and measured load sharing between the tension rod and the neck tube are also shown on Figure 44 as a function of the applied load. The measured load sharing (ratio of load in tension rod to applied load) averaged 30.1 per cent higher than the theoretical load sharing in the load range from 0 to 1800 pounds. The measured and theoretical load sharing were in good agreement in the load range from 1800 pounds to 3100 pounds. The 12 strain gauges located on the four sides of the neck tube measured tensile and compressive strains. The maximum measured tensile strain on the top side was 120 micro-inch/inch and the maximum measured compressive strain on the bottom side was 400 micron-inch/inch. The calculated tensile and compressive strains on the top and bottom sides were 323 micron-inch/inch and 478 micro-inch/inch, respectively.

Length measurements taken on the male and female tension rods before and after the test indicates that the male rod took a permanent set of .003 inches to .006 inches and the female rod took a permanent set of .004 inches to .007 inches. The total permanent set for the two rod halves was .007 inches to .013 inches. The deflection in the test fixture was .001 inch under the maximum load applied, which indicates that the deflection in the test fixture was negligible.

Results of the static test showed that the mode of failure of the neck tube is shear buckling as predicted by the analysis of the support system and that the load to fail the neck tube in shear buckling was predicted very accurately by using the design information and experimental data available in the literature. The experimental and theoretical load sharing between the tension rod and the neck tube showed good agreement in the load range where the neck tube failed.

The deflections of the neck tube and tension rod were 3.2 and 4.8 times larger than the calculated deflections for the neck tube and tension rod, respectively. The cause of the large deflections obtained in the experiment are not exactly known, however, the load deflection test performed on the tension rod in the tensile test machine indicated that the rod halves deflected as predicted by calculations, and the large deflections measured in the static proof test at the tension rod ends were not caused by the two tension rod halves. It is believed that the large deflections measured in the static proof test was caused by movement in the test fixture, specifically in the center plate or simulated spider which connected the tension rod to the shield. It was calculated that if this center plate was only one degree off from the vertical center line, which was entirely possible, the movement of this plate back to the vertical position under the applied load would have permitted the tension rod end to deflect .008 inch. The .007 to .013 inch permanent set measured in the tension rod is believed to be caused by loading the tension rod much above the proportional limit during buckling of the neck tube. The sum of the permanent deflections in the tension rod and the deflection caused by the possible movement of the center plate could well account for the difference between the calculated and measured deflections.

3.1.7 Material Compatability Investigation

The purpose of this investigation was to determine if there is any unfavorable interaction between the materials used in the HTVIS, including insulation materials, enclosure material, radiation shield material, and neck tube material. A schematic view showing the orientation of the various materials within the test apparatus is shown on Figure 47. It was intended that each of the materials contact the materials they will contact in the HTVIS units and in addition the materials were maintained at the operating temperatures and pressures. The compatability test was conducted with an operating temperature of 1400°F for a total of 2000 hours. The test materials were examined after 500 hours and 2000 hours test time.

The test insulation section is composed of three test zones each approximately 4 inches long. Each zone was insulated with the materials as shown on Figure 47. Quartz string was used to secure the multi-layer insulation in place. The nickel and aluminum foils were unprocessed while the copper foil, quartz paper, and 106 glass paper were processed prior to application. The water cooled stainless tube holding the test insulation zones was insulated with a multi-layer guard insulation adjacent to the test zones.

A sheet of Hastelloy-X, .012 inch thick x 12-1/2 inches long x 7-1/2 inches wide was rolled to fit the inside diameter of the Hastelloy-X vacuum chamber. Tantalum compatability barrier sheet (3 inches x 6 inches) was rolled to fit the Hastelloy-X sheet and located 1 inch from the edge of the Hastelloy-X sheet. Two thicknesses of tantalum foil .0003 inch thick covered the remaining exposed area of the Hastelloy-X sheet. Fifteen radiation shield material rods approximately 1/2 inch diameter by 3 inches long were placed on the tantalum and contacted the tantalum and the outside layers of quartz paper during the compatibility test.

The test chamber was evacuated, heated to and maintained at 1400°F for 500 hours. While shutting off the power at the conclusion of the 500 hour test, the temperature controller malfunctioned allowing the chamber to reach 1980°F in the hour before the malfunction was detected. The power plug was disengaged at this point and the chamber was force cooled and then back filled with argon gas to one atmosphere pressure. The chamber flange was removed and the water cooled pipe carrying the test insulation was removed. The rear 15 inch section of the guard insulation remained in the furnace when the tube was taken out. The insulation appeared to have been caught by the nuclear radiation rods. The condition of the insulation test zone as removed from the chamber is shown in Figure 48. While the indentation due to the nuclear radiation rods on the test zone is apparent in this figure.

Figure 49 shows the nuclear radiation rods as taken out of the furnace. It was observed that two of the rods were virtually unchanged in color, and appeared to have no reaction on the copper coatings after 500 hours of run. It was also observed that on several nuclear radiation shield rods, the copper sheathing failed at several points and thereby showed spotty holes. It is felt that these rods may have been pushed off the tantalum tray and were in contact with bare Hastelloy-X furnace wall or were in contact with the

FIGURE 47 SCHEMATIC VIEW SHOWING THE INSULATION AND RADIATION SHIELD MATERIAL IN TEST CHAMBER

FIGURE 48

INSULATION MATERIAL TEST ZONES OF COMPATIBILITY TEST AFTER 500 HOURS AT 1400°F
(847-67)

FIGURE 49

NUCLEAR RADIATION SHIELD MATERIAL SAMPLES AFTER 500 HOURS AT 1400°F
(849-67)

Hastelloy-X sheet under the .0003 inch tantalum foil. One rod was adhered to the nickel foil wrapping. The tantalum foil (.0003 inch thick) under the nuclear radiation rods was brittle and shredded easily as shown in Figure 50. This is possibly due to the inherent characteristics of tantalum to form compounds of tantalum chloride, tantalum nitride, etc. from the offgassing contaminated environment. The thicker tantalum sheet showed two spotty burn marks.

The entire wrapping of Zone "B" (Figure 47 center zone) was removed. While unwrapping "B", the physical condition of the insulation materials was observed as:

Nickel: Material was wrinkled and quartz paper material clung to the nickel foil particularly on the highest temperature layers.

Copper: Copper foils welded together in several spots where successive layers touched. Discoloration of the copper foil was noted where inner end of the copper foil overlapped the aluminum foil. Copper and quartz paper were discolored over a few inches of length.

Aluminum: The 106 glass paper was discolored. The dark color was uniform all over the width of the roll but did not extend to the edges (approximately 1/4 inch from the edge). The dark brown (tobacco color) lightened gradually from the hotter to the cooler region until the true white color of the paper was noted again for approximately the last 25 layers of 106 glass paper. Some slight grayish discoloration also appeared intermittently along the edge on aluminum foil. The 106 glass paper taken from "B" was analyzed and the chemical analysis revealed the following:

<u>Sample Identification</u>	<u>Description</u>	<u>Contents</u>
No. 47589	106 paper-color-white	C - $0.23\% \pm 0.01\%$ Na- 0.03%
No. 47590	106 paper-Spots of brown	C - $0.17 \pm 0.01\%$ Na- $1.24 \pm 0.05\%$
No. 47591	106 paper-Brown	C - $0.08\% \pm 0.01\%$ Na- 6.9 $\pm 0.3\%$ -First test 1.7 $\pm 0.1\%$ -Second test

An emission spectorgraphic analysis was also conducted on Sample No. 47591, showing that this sample contains 1 to 9% sodium and boron. It is not known what caused the sodium and/or boron in the brown-colored Type 106 paper.

FIGURE 50

TANTALUM FOIL (.0003 INCH THICK) AFTER 500 HOURS AT 1400°F
(848-67)

Insulation test Zone "B" (Figure 47) was replaced using new insulation materials. The guard insulation that came off during removal from the chamber after 500 hours was reinstalled. Except for test Zones A and C all of the insulation was recovered with processed quartz paper as the original quartz paper was badly bruised during handling for installation and removal from the test chamber. Test Zone A and C were recovered with quartz paper salvaged from the inner portion of the removed test Zone "B". The nuclear radiation shield material rods were installed in the vacuum chamber as before using the tantalum sheet and new .0003 inch thick tantalum foil. With the malfunctioning furnace controller replaced, the vacuum furnace was heated to 1400°F and maintained at this temperature for 1500 additional hours to complete the specified 2000 hours material compatibility test.

When the test chamber was cooled to ambient temperature and back filled with argon, the vacuum flange was opened and the test materials were removed. The rear 15 inch section of guard insulation again remained in the chamber. Figure 51 shows the insulation test zones with the indentations made by the sample radiation shield material rods. Shown on Figure 52 are the nuclear radiation material rods as taken out of the chamber and restacked on the tantalum sheets. It was noted that two of the rods which were virtually unchanged in color at the end of 500 hours of test, has discolored to some extent. The failure of copper sheathing at several points on some of the nuclear radiation material rods as noted at the end of 500 hours of test, was found not to have been aggravated to any extent at the end of the additional 1500 hours of test. The spot holes on the radiation rods were of approximately same dimensions as noted at the end of 500 hours of test run. The tantalum foil (0.0003 inch thick) under the nuclear radiation rods were not shredded as much as at the end of 500 hours of test. The Hastelloy-X sheet was discolored in several spots. An overall increased discoloration of the copper sheathing of the nuclear radiation material rods was noted compared to 500 hours of test.

The entire wrapping from each of the test Zones, A, B, and C were removed. The "START" section indicates first material put on as the insulation was originally wrapped on the stainless tube, i.e., the "START" section is closet to the tube for any given material. As a roll is unwrapped, the "FINISH" section comes off first and "START" section is the last portion of the individual wrapping. While unwrapping the rolls, the physical conditions of the insulations were observed as:

Zone A: Test Run Time - 2000 Hours

Nickel Foil: Similar in appearance from start to finish, part way into the roll, quartz paper adheres to the nickel foil and leaves fuzzy surfaces.

Copper Foil: Difficult to unwrap due to welding together effect at many little spots. Material looks bright except for 5 to 10 inches length adjacent to aluminum foil.

FIGURE 51

INSULATION MATERIAL TEST ZONES OF COMPATIBILITY TEST AFTER 2000 HOURS AT 1400°F
(1158-67)

FIGURE 52

NUCLEAR RADIATION SHIELD MATERIAL AFTER 2000 HOURS AT 1400°F
(1156-67)

Aluminum Foil: The 106 glass paper spacer was dark brown, gradually lightens until fading completely (~ 1 foot from the start). Aluminum foil is found to be thin at "FINISH" section and aluminum powder deposit was noted on 106 glass paper. The thinness of the aluminum foil was evident by the fact that light can be seen through the foil at "FINISH" section. The 106 glass paper roll edges were not as dark brown as at the center.

Nickel Foil - 5 Turns: Uniform in color.

Zone B: Test Run Time - 1500 Hours

Nickel Foil: Quartz material adhering to foil to form fuzzy surface until shortly before start of roll. Slight discoloration on edges. Heat leak due to discontinuous zone between A and B and between B and C may have caused discoloration.

Copper Foil: Welding effect same as noted for Zone A. Not discolored at "START" portion of the foil.

Aluminum Foil: The 106 glass paper had a brown color but not as dark as Zone A. Aluminum foil at "FINISH" section is porous and light could be seen through it, but seems not as porous as Zone A.

Nickel Foil - 5 Turns: Slight discoloration where it touches the stainless steel mandrel.

Zone C: Test Run Time - 2000 Hours

Nickel Foil: Quartz paper sticking to foil. This continued, however, for short distance only. Other features same as Zone A.

Copper Foil: Color was bright, but welding effect similar to Zones A and B were noted. Six inches in length at the "START" section was discolored where the copper came in contact with aluminum foil and 106 glass paper.

Aluminum Foil: Same features as observed for Zone A.

Nickel Foil - 5 Turns: Same as for Zone A.

Samples of the radiation shield insulation materials were collected from the insulation test zones both initially and after the specified test time. The foil materials were tested for relative reflectance in an attempt to gain some insight into the potential change in reflectivity during the tests. It was found, however, that with the infrared spectrophotometer used in the investigation that the surface condition of the foil (degree of wrinkles and flatness of the surface) has an overriding influence on the relative reflectance measured. The attempt to determine degradation or improvement of the radiative properties of the shield materials by the infrared spectrophotometric method was not successful. For heat transfer characteristics of the foils (emissivity), hemispherical reflectance is a much better indicator of performance than the spectral reflectance which was used in this test.

It was found in general during this compatability test that there were no serious material incompatibilities that would preclude the use of any of the tested materials in the HTVIS units.

3.1.8 Tension Rod Preload Evaluation Tests

The purpose of this development effort was to determine the relationship between the loading in the tension rods and the applied torque. It is necessary to preload the tension rods in order to maintain support system tightness and to allow for some tolerance in the tension rod set angle which could cause some system looseness when the unit is heated to operating temperature if it were not for the tension rod preload.

3.1.8.1 Preload Determination With Strain Gauge on Tension Rod

The male and female tension rod and the spherical washers used in the static proof test were also used for the prestressing investigation. The spherical washers were restrained from axial movement while the tension rods were tightened using a torque wrench. The rod was torqued in increments and the apparent rod load was calculated from the strain measurement. It was found that the rod load versus the applied torque was linear and that it required 40 in./lbs. of torque to achieve the desired preload in the tension rod of 193 pounds (3300 psi).

3.1.8.2 Preload Determination with Strain Gauge on Tension Rod Receptacle

To determine the applicability of mounting a strain gauge on each of the tension rod receptacles of the first development unit (B10-D1) to measure the applied tension rod preload, an investigation was performed utilizing receptacle weld development specimens No. 4, 5, and 6. A strain gauge (Type SR-4) was applied to the long side of each receptacle as shown in Figure 53. During the tensile test of the receptacles, a load was applied in 50 pound increments to a maximum of 300 pounds (tension rod preload - 193 pounds) to determine the load versus strain relationship as shown on Figure 54. As can be seen from the figure, each specimen test produced a different load versus strain relationship. It is felt that this difference was caused by the simulated enclosure head (square plate) not being perfectly flat on the angle fixture during the test due to some warpage of the plate during welding. With the plate not flat on the fixture, some bending stresses were most likely transferred to the receptacle strain gauge during this low applied load test.

The results of this test indicate that strain gauges may be useful if mounted on the receptacles, however, each receptacle strain gauge must be individually calibrated after the receptacle is welded into the enclosure head. Once the calibration is performed, it is felt that the strain versus load relationship will be repeatable for each receptacle.

To further establish the required torque to achieve the desired tension rod preload the receptacles on unit B10-D1 were each instrumented with a strain gauge (Type SR-4) mounted on the long side of the receptacle.

FIGURE 53
STRAIN GAUGE APPLIED TO LONG SIDE OF RECEPTACLE
(1545-67)

FIGURE 54

RECEPTACLE STRAIN GAUGE
LOAD VS. STRAIN DATA
UNIT B10-D1

The calibration of each receptacle was performed using a Statham load cell which was anchored to the unit assembly fixture bar. A solid pin passed through the tension rod angle hole in the bar and contacted the bottom of the receptacle on one end and an adjusting screw on the load cell on the other end. Force was produced in the rod by tightening the adjusting screw. To prevent loading the inner liner during the calibration, two bands circumscribed the unit to securely anchor the unit to the unit assembly fixture bar. Loading for each receptacle was applied in 20 pound increments recording the strain at each load unit a load of 190 pounds was reached. The calibration of the three receptacles is shown on Figure 55. Receptacle No. 1 and 2 exhibited a similar load strain relationship while receptacle No. 3 was markedly different for no apparent reason.

It was felt that the band securing the unit to the unit assembly bar may be affecting the load versus strain relationship because of strains produced by the bands. The bands were removed and the calibration was repeated for each receptacle, however, each receptacle was only loaded to 100 pounds because without the bands the load was transferred directly to the neck tube. This second calibration is also shown on Figure 55. It can be seen that the load strain relationship was changed for each receptacle. The calibration with no bands is the most valid as it simulates the load as applied by tightening a tension rod.

Next, the torque versus strain relationship was determined for each receptacle by sequentially applying torque to each tension rod and recording the receptacle strain. This calibration was performed with the tension rod in each of three locations in the receptacle, namely, tension rod on short side of receptacle, tension rod on long side of receptacle (strain gauge side), and tension rod centered in the receptacle. Figure 56 presents the results of the calibration for each loading condition for each receptacle. The calibration for the tension rod on the short side of the receptacle and the center of the receptacle corresponds quite closely.

With the use of Figures 55 and 56, the torque required to apply a 193 pound preload on the tension rods can be determined. From Figure 55 the receptacles must be strained as follows: No. 1 = 51×10^{-6} inch/inch, No. 2 = 46×10^{-6} inch/inch, and No. 3 = 23×10^{-6} inch/inch. From Figure 56, which presents the torque versus the strain, it is seen that the required torques are as follows: No. 1 = 24 in-lb., No. 2 = 22.5 in-lb., and No. 3 = 13 in-lb.

While preloading the rods, it is required to sequentially torque in small increments in order not to cause a directional load on the inner liner. Because of the possibility of strain gauge error on receptacle No. 3 (significantly different torque required than for receptacle No. 1 and No. 2) all three tension rods on all units were torqued to 22.5 in-lb. during assembly.

FIGURE 56

102.

TENSION ROD TORQUE VS.
STRAIN IN RECEPTACLE
UNIT B10-D1

3.2 ANALYSIS ACTIVITIES

3.2.1 Dynamic Criteria Study

To establish design load levels and system support configuration, a study was performed to determine: 1) the system heat loss resulting from increased dynamic loading on the design of the HTVIS unit considering various support concepts, and 2) the magnitude of the 'g' loading to which the unit will be subjected during shipping and handling. A parametric study was conducted to determine how the increased 'g' loading will affect the system heat leak for a number of proposed support concepts to include neck tube support, neck tube with three tension rod supports, neck tube with three compression rod supports, bellows with six compression rod supports, bellows with six tension rod supports, bellows with stacked disc compression supports, and bellows with compressed multi-layer insulation supports.

An additional study was performed to determine the allowable input 'g' loading to the unit during shipping for the various support concepts for the specific case where the unit is directly supported by rigid attachment to the nuclear radiation shield.

An investigation of the 'g' loading to which the unit will be subjected during shipping and handling was conducted to include: 1) a literature survey on the dynamic loads normally encountered by similar items during shipping and handling, 2) preparation of a flow plan for fabrication and testing of the unit which indicated estimated 'g' loading encountered during each operation, and 3) experimental testing conducted with fork-lift trucks to determine dynamic loading encountered during fork-lift truck operations, since a large portion of the unit handling is expected to be accomplished by fork-lift trucks.

3.2.1.1 Heat Loss Determination for Proposed Support Systems

A parametric study was conducted to determine how increased unit 'g' loading will effect the total system heat leak for a number of proposed support systems to include: neck tube support, neck tube with three tension rod supports, neck tube with three compression rod supports, bellows with six compression rod supports, bellows with six tension rod supports, bellows with stacked disc compression rod supports, and bellows with compressed multi-layer insulation supports.

The support systems were analyzed in the range of 3 'g' to 20 'g' and/or a maximum of 70 watts total system heat leak. Figure 57 is a graphical presentation showing the effect of 'g' loading on total system heat leak for the different support systems. A schematic diagram of each of the support systems is shown on Figure 58. The reason only the first four support systems are shown on Figure 57 is that the other three systems were found not suitable for this application because of geometry considerations or insufficient property data to permit an evaluation. The support systems were designed for both shock and vibration loadings at 50 cps. The effect of increased fuel loading on shield weight for systems with a heat loss greater than 30 watts has been factored into the structural strength of the different support systems.

FIGURE 57
EFFECT OF g -LOADING ON TOTAL SYSTEM HEAT LEAK
FOR DIFFERENT SUPPORT SYSTEMS

FIGURE 58
SCHEMATIC DIAGRAM OF DIFFERENT SUPPORT SYSTEMS

NECK TUBE

NECK TUBE PLUS
THREE TENSION RODS

NECK TUBE PLUS
THREE COMPRESSION RODS

BELLOWS WITH SIX
TENSION OR COMPRESSION RODS

BELLOWS WITH SIX
STACKED DISC COMPRESSION
SUPPORTS

BELLOWS WITH COMPRESSED
MULTI-LAYER INSULATION

NOTE: TENSION AND COMPRESSION RODS ARE LOCATED 120° APART

The following simplifying assumptions were made for the parametric study:

1. The amplification factor due to shock was assumed to be between 1.2 and 1.3 for the support systems investigated. The amplification factor due to shock for a cantilever beam with a weight on its end ranges from 0.85 to 1.3. By using the 1.2 or 1.3 amplification factor for this parametric study, the calculations are on the conservative side.

2. The end temperatures of the tension and compression rods were assumed to be the same as the end temperatures of the neck tube. By making this assumption, it was not necessary to solve for the temperature distribution in the neck tube and in the tension or compression rods separately. The end temperatures of the neck tube and support rods were 1325°F and 150°F.

3.2.1.1.1 Bellows With Six Compression Rod Support System

The support system utilizing the bellows (Hastelloy-X) with six compression rods (zirconium dioxide) offers the best thermal performance among the support systems investigated. The compression rods were designed for 1.5 safety factor based on the compressive yield strength and were checked for buckling in compression. The compression rods would be installed approximately 45° to the axial centerline to support the shield both in the hot and cold conditions. It was found that the highest stress in the compression rods occurred when the unit was in the horizontal position. The amplification factors due to vibration at 50 cps for different 'g' loadings were calculated for the unit being in the horizontal position and ranged from 1.0 to 1.2 depending on the 'g' loading. The amplification factor due to shock loading was assumed to be 1.2 for all input 'g' loadings. The 0.008 inch wall thickness of the bellows was determined based on vacuum service reliability and minimum manufacturing capabilities. The stresses in the bellows due to the 2 atm. outside pressure were calculated and were found safe. Results of the calculations for 3, 10, and 20 'g' dynamic loading are summarized in Table 17.

3.2.1.1.2 Neck Tube With Three Compression Rods Support System

The support system utilizing a straight or tapered neck tube (Hastelloy-X) and three compression rods (zirconium dioxide) offers the second best thermal performance among the systems investigated. In this support system, the neck tube carries about 40 per cent of the total load. The balance of the load is carried by the three compression rods. The neck tube wall thickness of 0.0096 inch at 3 'g' dynamic loading was selected based on minimum manufacturing capabilities. The neck tube at 3 'g' dynamic loading had a safety factor higher than 1.5 in shear buckling. Since the compression rods were designed for a 1.5 safety factor in compression, the mode of failure shifted from the neck tube in shear buckling to the compression rods in compression. At 10 'g' dynamic loading, the straight neck tube with 0.0095 inch wall thickness determined for the 3 'g' loading had to be changed to a tapered neck tube with 0.013 inch and 0.017 inch wall thicknesses at top and bottom, respectively, in order to design the neck tube for a 1.5 safety factor in shear buckling.

TABLE 17

107.

RESULTS OF PARAMETRIC STUDY FOR BELLOWS WITH
SIX COMPRESSION ROD SUPPORT SYSTEM

G-Loading	<u>3</u>	<u>10</u>	<u>20</u>
Natural Frequency rad/sec	755	1405	1940
Amplification Factor Due To Vibration At 50 cps	1.2	1.03	1.0
Amplification Factor Due To Shock Loading	1.2	1.2	1.2
Angle Between Compression Rods And Axial Center Line (Degrees)	45	45	45
Allowable Stress In Compression Rods For 1.5 Safety Factor (psi)	16,666	16,666	16,666
Maximum Applied Stress In Compression Rods (psi)	14,910	14,415	15,032
Maximum Load Carried By Compression Rod (Lbs)	560	1866	3733
Bellows ¹ Wall Thickness (Inches)	.008	.008	.008
Compression ² Rod Diameter Required For 1.5 Safety Factor (Inches)	7/32	13/32	9/16
Heat Leak Through Bellows (Conduction Plus Radiation) (Watts)	6.9	6.9	6.9
Heat Leak Through Six Compression Rods (Watts)	2.2	7.4	14.3
Heat Leak Through Bellows Plus Six Compression Rods (Watts)	9.1	14.4	21.2
Heat Leak Through Insulation (Watts)	9	9	9
Total System Heat Leak (Watts)	18.1	23.4	30.2

1) Material - Hastelloy-X

2) Material - Zirconium Dioxide

In this support system, the compression rods will be installed about 73° to the axial centerline to support the shield both in the hot and cold conditions. The amplification factor due to vibration at 50 cps was assumed to be unity. The amplification factor due to shock loading was assumed to be 1.2. Results of the calculations for 3, 10, 15 and 20 'g' dynamic loading are summarized in Table 18.

3.2.1.1.3 Neck Tube With Three Tension Rods Support System

The support system incorporating a straight or tapered neck tube (Hastelloy-X) and three tension rods (Hastelloy-X) was found thermally less efficient than the previously presented support concepts. The straight neck tube with 0.0095 inch wall thickness was used for the 3 'g' and 5 'g' design cases. The 0.0095 inch wall thickness was selected based on minimum manufacturing capabilities. With dynamic loading over 5 'g' the neck tube was designed for a 1.5 safety factor in shear buckling. The tension rods in this support system will be installed at 60° to the axial centerline to support the load in both the cold and hot conditions. The neck tube carries about 40 per cent of the total load, and the balance of the load is carried by the tension rods. The amplification factor due to vibration at 50 cps for the different 'g' loadings ranged from 1.06 to 1.10. The amplification factor due to shock was assumed the maximum 1.3 for all 'g' loadings. Results of the calculations at 3, 5, and 10 'g' dynamic loadings are presented in Table 19.

3.2.1.1.4 Neck Tube Support System

The support system using only a tapered neck tube (Hastelloy-X) has the highest heat leak among the systems investigated. The neck tube was designed for a 1.5 safety factor for buckling in combined bending and internal pressure at the cold end and combined transverse shear and internal pressure at the hot end. The amplification factor due to vibration at 50 cps for this support system ranged from 1.4 to 1.8, depending on the 'g' loading. Since the maximum amplification factor due to shock was 1.3, this system was designed for the higher amplification factors obtained due to vibration. Results of the calculations at 3, 5, and 8 'g' are summarized in Table 20.

3.2.1.1.5 Bellows With Six Tension Rods Support System

The support system which uses bellows with six fixed length tension rods was found not capable of supporting the shield in both the hot and cold conditions due to the large thermal expansion of the Hastelloy-X tension rods compared to the thermal expansion of the shield. The thermal expansion coefficient of the tension rods (Hastelloy-X) is about twice that for the compression rods (zirconium dioxide).

3.2.1.1.6 Bellows With Six Stacked Disk Compression Rods Support System

The support system which uses the bellows with six stacked disc compression supports is not able to support the shield in both the hot and cold conditions for the same reason as was explained for the bellows with six tension rod system.

TABLE 18

109.

RESULTS OF PARAMETRIC STUDY FOR NECK TUBE AND THREE
COMPRESSION ROD SUPPORT SYSTEM

G-Loading	<u>3</u>	<u>10</u>	<u>15</u>	<u>20</u>
Fuel Load Increase (Watts)	0	12	28	45
Weight of Shield Plus Full Capsule (Lbs.)	264	268	274	279
Amplification Factor Due To Shock Loading (.85 - 1.3)	1.2	1.2	1.2	1.2
Angle Between Compression Rods And Axial Center Line (Degrees)	73.3	73.3	73.3	73.3
Top And Bottom Neck Tube Wall Thickness Required For 1.5 Safety Factor (Inches)	T .0095 B .0095	T .013 B .017	T .019 B .026	T .026 B .035
Allowable Stress In The Compression Rod For 1.5 Safety Factor (psi)	16,666	16,666	16,666	16,666
Maximum Applied Stress In The Compression Rod (psi)	12,180	12,295	13,365	13,435
Maximum Load Carried By The Compression Rod (Lbs)	457	1,592	2,460	3,337
Compression Rod Diameter Required For 1.5 Safety Factor (Inches)	7/32	13/32	31/64	9/16
Heat Leak Through Neck Tube ¹ (Watts)	17.0 - 18.3	26.9 - 28.3	40.5 - 41.8	55.0 - 56.3
Heat Leak Through Three Compression Rods ² (Watts)	1.4	4.9	6.9	9.3
Heat Leak Through Neck Tube Plus Three Compression Rods (Watts)	18.4 - 19.7	31.8 - 33.2	47.4 - 48.7	64.3 - 65.6
Heat Leak Through Insulation (Watts)	9	9	9	9
Total System Heat Leak (Watts)	27.4 - 28.7	40.8 - 42.2	56.4 - 57.7	73.3 - 74.6

1) 1.5 mil variation on outside diameter is allowed for manufacturing tolerances (Material, Hastelloy-X)

2) Material, Zirconium Dioxide

TABLE 19

RESULTS OF PARAMETRIC STUDY FOR NECK TUBE WITH
THREE TENSION ROD SUPPORT SYSTEM

G-Loading	<u>3</u>	<u>5</u>	<u>10</u>
Fuel Load Increase (Watts)	6	13	40
Weight of Shield Plus Fuel Capsule (Lbs)	266	269	278
The Angle Between The Tension Rods and The Axial Center Line (Degrees)	60	60	60
Top and Bottom Neck Tube Wall Thickness Required For 1.5 Safety Factor (Inches)	T .0095 B .0095	T .0095 B .0095	T .013 B .017
Natural Frequency rad/sec	1006	1130	1226
Deflection of The Shield At The Center of Gravity (Inches)	1.1×10^{-3}	1.52×10^{-3}	2.57×10^{-3}
Amplification Factor Due To Vibration At 50 cps	1.1	1.07	1.06
Amplification Factor Due To Shock	1.3	1.3	1.3
Tension Rod Diameter Required For 1.5 Safety Factor (Inches)	11/64	15/64	11/32
Maximum Load Carried By The Tension Rod (Lbs)	453	809	1704
Allowable Stress In The Tension Rod (psi)	19,958	19,958	19,958
Maximum Applied Stress In The Tension Rod (psi)	19,545	18,770	18,371
Heat Leak Through Neck Tube ¹ (Watts)	17.0 - 18.4	17.0 - 18.4	26.9 - 28.3

TABLE 19 (Cont'd)

RESULTS OF PARAMETRIC STUDY FOR NECK TUBE WITH
THREE TENSION ROD SUPPORT SYSTEM

G-Loading	<u>3</u>	<u>5</u>	<u>10</u>
Heat Leak Through Three Tension Rods ² (Watts)	7.9	15.0	32.3
Heat Leak Through Neck Tube Plus Three Tension Rods (Watts)	24.9 - 26.3	32.0 - 33.4	59.2 - 60.6
Heat Leak Through Insulation (Watts)	9	9	9
Total System Heat Leak (Watts)	33.9 - 35.3	41.0 - 42.4	68.2 - 69.6

- 1) 1.5 mil variation on outside diameter is allowed for manufacturing tolerances
(Material - Hastelloy-X)
- 2) Material - Hastelloy-X

TABLE 20RESULTS OF PARAMETRIC STUDY FOR NECK TUBESUPPORT SYSTEM

G-Loading	<u>3</u>	<u>5</u>	<u>8</u>
Fuel Load Increase (Watts)	19	39	59
Weight Of Shield Plus Fuel Capsule (Lbs)	271	280	285
Top and Bottom Neck Tube ¹ Wall Thickness Required For 1.5 Safety Factor (Inches)	T .024 B .020	T .033 B .030	T .045 B .044
Natural Frequency rad/sec	461	509	553
Deflection Of The Shield At The Center Of Gravity (Inches)	$.54 \times 10^{-3}$	$.71 \times 10^{-3}$	$.92 \times 10^{-3}$
Amplification Factor Due To Vibration At 50 cps	1.86	1.60	1.47
Heat Leak Through Neck Tube ² (Watts)	39.6 - 40.9	56.8 - 58.2	80.5 - 81.9
Heat Leak Through Insulation (Watts)	9	9	9
Total System Heat Leak (Watts)	48.6 - 49.9	65.8 - 67.2	89.5 - 90.9

1) Hastelloy-X

2) 1.5 mil variation on the outside diameter is allowed for manufacturing tolerances

3.2.1.1.7 Bellows With Compressed Multi-Layer Insulation Support System

The support system utilizing the bellows with compressed multi-layer insulation is not recommended for this application. Calculations based on the static load material properties show that this support system will withstand these static loads; however, experimental data are not available on the load-bearing capacity of multi-layer compressed insulation under dynamic loading conditions.

3.2.1.2 Allowable System 'g' Loading With A Directly Supported Nuclear Radiation Shield

Calculations were performed to determine the allowable 'g' loading on the HTVIS system during handling or shipping when the nuclear radiation shield is rigidly supported and directly receives the dynamic loads. This study showed that, with direct support of the nuclear shield, dynamic loads significantly higher than the design loading (based on loading of the enclosure) can be safely applied to the unit. The greater loading capacity resulting from directly loading the nuclear shield derives from the fact that the unit support system must only support the relatively lightweight enclosure shell instead of the heavy nuclear radiation shield. Figure 59 is a graphical presentation of the results of this shield as applied to the four potential support concepts.

3.2.1.3 Determination of Expected Dynamic Loading During Unit Transportation and Handling

3.2.1.3.1 Literature Survey to Determine Expected Dynamic Loading

In order to select a HTVIS unit support system for further analysis, the magnitude of the expected loadings which are normally received during shipping and handling must be determined. Two options exist for shipping or handling a unit: 1) the unit can be shipped in a shipping container which will reduce the loads experienced by the unit, or 2) the unit can be shipped without a shipping container and be designed to withstand the shipping and handling dynamic loads. In either case, an estimate of the dynamic loads produced during shipping and handling must be made in order to either design a unit or a shipping container.

Dynamic loads produced by the four major modes of transportation (air, truck, ship and rail) are well documented in the literature. For example: "Transportation Shock and Vibration Design Criteria Manual", NAS 8-1145, September, 1965, General American Transportation Corporation, and "Shock and Vibration Handbook", C. M. Harris and C. E. Cred, McGraw-Hill Book Company, 1961. A great deal of experimental data is presented in these references pertaining to the environmental loads transmitted to the cargo areas for each mode of transportation. Less well defined is the environmental load that can be expected while handling a unit either prior to or subsequent to the actual transport. Categories to be considered under handling include fork-lift truck, hand truck, and shop hoist or winch. Literature sources which present experimental

data for these handling conditions could not be located. Because it is expected that much of the handling will be by fork-lift truck as shown in Section 3.2.1.3.2, fork-lift truck tests to determine the expected loadings to a unit were performed and the results are presented in Section 3.2.1.3.3.

The expected system loads were estimated considering both a wood shipping platform and a metal shipping platform with both supervised and unsupervised shipping and handling. Supervised handling requires an inspector on hand to observe and control the handling methods and equipment used in load and unload operations with the transport vehicles. The presence of an inspector is not required during actual transport from one location to another. For unsupervised handling, an inspector is not required.

The estimated 'g' loadings for transport and handling of the HTVIS are presented in Table 21. The values presented in this table are estimated to be maximum values. The frequency of occurrence of these maximum values could not be determined because of the lack of correlating test data. The assumptions used in the presentation of Table 21 are as follows:

1. 'g' loadings are dynamic loads. Static loads must be added where applicable for design purposes.
2. The system platform receives same 'g' loading as transport carrier cargo floor.
3. The system has no horizontal movement when on truck cargo floor. If system is free to move, the 'g' loading would be 70 per cent the value of an equivalent distance free fall.
4. Other items on the cargo floor are not free to impact the system.
5. The wooden platform rise-time is 0.010 seconds vertical and 0.020 seconds horizontal.
6. The equivalent free fall distance for a known velocity was established from the relationship: $\text{distance} = (\text{velocity})^2 / 2 \text{ 'g'}$.

Transportation by rail was not considered because of the extremely high 'g' loads experienced when coupling standard railroad cars.

From Table 21, it can be seen that supervised transportation and shipment with the system or a wooden platform provides the lowest dynamic loading to the system with a maximum of only 7 'g' predicted. During unsupervised transport and handling with the system on the wood platform, the maximum predicted 'g' load is 20 'g'. The maximum supervised metal platform shipping and handling 'g' load is estimated to be 29 'g' while the unsupervised maximum 'g' load for the metal platform is predicted to be 100 'g'. All the 'g' loads experienced by the unit can be reduced by using shock mitigation methods in a shipping container, if necessary.

TABLE 21

ESTIMATED "G" LOADING FOR SHIPPING AND HANDLING OF INSULATION SYSTEM,
FUELED INSULATION SYSTEM AND COMPLETE SYSTEM

Means of Transport and Description of Load	System in Wood Container on Wood Pallet		System in Metal Container on Metal Skids		
	Unsupervised	Supervised	Unsupervised	Supervised	
1) Air Shipment					
a) Jet	2.5 @ 800 cps 0.1 @ 50 cps	Same	Same	Same	From: "Transportation Shock and Vibration Design Criteria Manual" NASA NAS 8-1145 - Figure 1
b) Prop	6.0 @ 400 cps 1.0 @ 50 cps				
2) Truck					
a) Smooth Road	0.2 @ 50 cps 0.35 @ 4 cps 0.3 @ 50 cps 2.0 @ 10 cps	Same	Same	Same	Figure 24
3) Ship					
a) Rough Sea	0.5 @ 50 cps 0.9 @ 12 cps	Same	Same	Same	Figures 20, 21, 22, and 23
b) Slam & Emergency	3.0 @ 2.5 cps 3.0 @ 50 cps				
4) Fork Lifts - Motorized					
a) Ramming Skid	16	3	200	20	8 fps, unsupervised; 1 fps supervised From: "Shock and Vibration Handbook", C.M. Harris & C.E. Crede, McGraw-Hill, 1961, Figure 41.1 1 fps unsupervised; 1/4 fps supervised Figure 41.1 Because of cushioning of lift truck, container not important. Because of cushioning of lift truck, container not important.
b) Drop to Floor	6	1	25	12	
c) Jerking Load on Forks	2	1	2	1	
d) Transit Over Rough Surfaces	10	2	10	2	
5) Fork Lifts - Manual					
a) Ramming Skid	3	1	20	3-1/2	2.5 fps fork lift speed unsupervised 1/2 fps fork lift speed supervised Considering weight fork lift 1/2 weight of load. Figure 41.1

TABLE 21 (cont'd)

<u>Means of Transport and Description of Load</u>	<u>System in Wood</u>		<u>System in Metal</u>		
	<u>Container on Wood Pallet</u>	<u>Supervised</u>	<u>Container on Metal Skids</u>	<u>Supervised</u>	
b) Drop to Floor	6	1	25	12	Considered same values as motorized unit.
c) Transit over Rough Surfaces	11	6	58	29	1" vertical drop, unsupervised 1/4" vertical drop, supervised Fig 41.1
6) Hand Truck, Rubber Wheels					
a) Ram into solid object	7	1-1/2	70	12	3 fps ram speed unsupervised 1/2 fps ram speed supervised Fig 41.1
b) Transit over Rough Floor	10	5	17	8	2" drop unsupervised; 1/2" drop supervised, assuming .008 time rise plus .010 wood container & .002 metal container time rise; Fig 41.1
7) Hand Truck, Steel Wheels					
a) Ram into Solid Object	7	1-1/2	70	12	Assumed same values as rubber wheel truck
b) Transit over Rough Floor	15	7	40	20	2" drop unsupervised, 1/2" drop supervised, assuming .002 time rise plus .010 wood container & .002 metal container time rise; Fig 41.1
8) Elevator	2.5	2.5	2.5	2.5	Emergency deceleration Table 44.5
9) Hoist, shop type (chain, elec. hydraulic)					
a) Setting down on solid floor	1-1/2	1-1/2	8	8	1/2 fps velocity both supervised & unsupervised. Fig 41.1
10) Winch - dockside	?	?	?	?	No values assigned due to lack of available data and knowledge.
11) Free fall due to normal handling	20	6	100	28	6" edge drop (3" free fall) unsupervised; 1/2" edge drop (1/4" free fall) supervised. Fig 41.1

3.2.1.3.2 Estimation of HTVIS Unit 'g' Loadings During Fabrication, Testing and Packaging

To determine the expected 'g' loadings during unit fabrication, testing, and packaging, a flow plan was prepared to show each operation on the unit, the tooling required, and the estimated dynamic load encountered. The dynamic load values of Table 21 were extensively used in estimating the loads for each operation on the unit. The maximum 'g' loading estimated was 7.5 'g' for the operation of picking up the unit with a chain hoist and setting the unit on the test stand. The loads produced during these operations could, however, be reduced by use of cushioning devices.

3.2.1.3.3 HTVIS Unit Handling on a Fork-Lift Truck, Experimental Tests

Because no fork-lift truck handling data could be found in the literature, fork-lift truck tests were performed to determine the magnitude of dynamic loads that are produced during handling. To conduct these tests, a mock-up HTVIS unit was fabricated to simulate both 300 pound and 500 pound units. This unit was mounted on a standard wood pallet, instrumented with accelerometers and tested using a commercial fork-lift truck. Dynamic loadings were determined for handling in the following modes: 1) ram pallet with fork-lift truck; 2) jerk unit up from floor (pallet on truck forks); 3) stop unit on forks; 4) drop unit on floor (pallet on truck forks); 5) traverse obstacles on the floor at normal speeds (pallet on truck forks). These tests and results should not be considered all-comprehensive in that they are representative only of the weights of the units tests, the type of pallet used, and the model of the fork-lift truck used.

The largest dynamic 'g' loads measured were produced during ramming the pallet with the fork-lift truck to simulate the fork engagement with the pallet. As an example, at a ram velocity of 8 ft/sec., a horizontal 'g' loading of 16.3 'g's were experienced by the unit. Perhaps a more realistic maximum ram speed would be 4 ft/sec., which produced 'g' loads ranging from 4 to 10 'g's. When dropping the unit on the floor with the pallet on the truck forks, the vertical 'g' load was not greater than 6 'g's regardless of the drop height. During a simulated, normal handling operation (supervised), the maximum horizontal dynamic load measured was 1.6 'g's. When traversing obstacles 1-3/4 inches high at a normal speed, the vertical 'g' loads measured ranged from 2.8 'g' to 8.4 'g' depending on the obstacle width, spacing and weight of the unit. Jerking the unit resulted in 'g' loadings of less than 1.1 'g' while stopping the unit on the forks resulted in 'g' loadings of approximately 1.5 'g' regardless of the distance traversed because the fork lowering speed is velocity limited.

3.2.2 Material Selection Study

This section presents the basis upon which specific materials were selected for use in the HTVIS units.

3.2.2.1 Neck Tube Material

Based on yield strength, stress rupture life, oxidation resistance, weldability and thermal conductivity at operating temperature, the following three candidate neck tube materials were recommended in the presented order:

Inconel-625
Hastelloy-X
Inconel-600

Inconel-625: exhibits a typical yield strength at 1350°F of 44,500 psi. The stress rupture at 1350°F and 50,000 hours is 16,000 psi. This material has better oxidation resistance than Inconel-600 or Inconel-X-750.

Hastelloy-X: exhibits a typical yield strength at 1350°F of 38,200 psi. The rupture stress at 1350°F and 50,000 hours is 10,000 psi. This material has better oxidation resistance than Inconel-600.

Inconel-600: exhibits a typical yield strength at 1350°F of 19,500 psi. The rupture stress at 1350°F and 50,000 hours is 5000 psi. This material is considered one of the most stable superalloys for long-term use.

Inconel-X-750 is not particularly recommended because it is a precipitation hardening alloy. This property may cause brittleness or a change in properties with long-term use.

All the above mentioned materials are weldable, and all exhibit thermal conductivities that vary by only a few per cent. Subsequent to selecting the above three candidate materials, an availability survey was conducted. During this survey it was found that Inconel-625 was relatively non-available as a stock item and that long-term waiting periods up to 30 weeks would be required after ordering components. In view of this availability problem, Hastelloy-X was selected as the material to be used in the HTVIS neck tubes.

3.2.2.2 Tension Rod Materials

Two materials were selected for the tension rods. Inconel-625 solution annealed material was selected for the male rod since this material has excellent high temperature creep properties in the operating temperature range of the male rod from 1000°F to 1400°F. Inconel-718 solution annealed and age hardened material was selected for the female rod because this material has much higher proportional limit than Inconel-625 solution annealed material. The reason it was possible to use Inconel-718 for a portion of the tension rod was that in the operating temperature range of the female rod from ambient to 1000°F the excellent creep strength of Inconel-625 solution annealed material was not needed.

3.2.2.3 Enclosure Shell Material

Type 304 stainless steel is recommended for the enclosure shell material because of availability and weldability to itself and to Hastelloy-X. Type 304 stainless steel exhibits a typical yield strength of 35,000 psi at 100°F.

3.2.2.4 Insulation Materials

Based on the insulation temperature range (ambient to approximately 1350°F) and thermal performance requirements, it is required that a multi-component, multi-layer insulation system be utilized in order to allow each insulation material to operate in a favorable temperature range. The insulation materials selected for use on the HTVIS units based on Linde developed high temperature insulation experience include the following:

1/2 mil nickel foil	A-664005
5 mil quartz fabric	A-664006
1 mil nickel foil	A-664008
quartz paper	A-664009
106 glass paper	A-664010
1/2 mil copper foil	A-664011
1/4 mil aluminum foil	A-664012

The number following the material description above is the Linde specification number which describes the material and provides the ordering specification.

3.2.3 Calculation to Determine Tension Rod Installation Angle

The following sections present the calculation of the tension rod angle required in order to maintain the tension rod preload when the unit is heated to operating temperature.

3.2.3.1 Temperature Profile of Hastelloy-X Neck Tube

Thermal conductivity versus temperature curve for Hastelloy-X is a straight line and is shown on Figure C-1 in Appendix C. The equation of the straight line is:

$$k = \frac{k_2 - k_1}{t_2 - t_1} (t - t_1) + k_1$$

at $t_1 = 150^\circ\text{F}$, $k_1 = 71 \text{ Btu-in./sq.ft.-hr.-}^\circ\text{F}$

at $t_2 = 1325^\circ\text{F}$, $k_2 = 161 \text{ Btu-in./sq.ft.-hr.-}^\circ\text{F}$

$$k = 0.07659t + 59.511$$

The temperature distribution in the neck tube is given by the equation derived in Appendix D.

$$t\left(\frac{X}{L}\right) = \frac{-b \pm [b^2 + a^2 t_1^2 + 2abt_1 - 2ak_m(t_1 - t_2)\frac{X}{L}]^{1/2}}{a}$$

where:

$$t_1 = 1285^\circ\text{F}$$

$$t_2 = 150^\circ\text{F}$$

$$t_m = 1285 + 150/2 = 717.5^\circ\text{F}$$

$$k_m = 0.07659 (t_m) + 59.511 = 114.46$$

$$a = 0.07659 \text{ Btu-in./hr.sq.ft.-}^\circ\text{F}^2$$

$$b = 59.511 \text{ Btu-in./hr.sq.ft.-}^\circ\text{F}$$

The temperature calculated for various X/L ratio ' was as follows:

X/L	0	0.2	0.4	0.6	0.8	1.0
t	1285	1113	929	711	463	150

The temperatures calculated above were plotted on Figure E-1 and the curve is referred to as the "neck tube profile with conduction only". The calculated neck tube profile shown on Figure E-1 is a more accurate solution for the temperature distribution in the neck tube since this solution includes the effect of heat transfer to the neck tube from the multi-layer insulation and from the Min-K neck tube insulation when the unit has the thermoelectric element in place. The analysis for the calculated neck tube profile is presented in Appendix E.

3.2.3.2 The Thermal Expansion of the Neck Tube by Numerical Integration

$$\Delta \ell = \sum_{X/L=0}^{X/L=1} \alpha \left[T\left(\frac{X}{L}\right) \right] \left[T\left(\frac{X}{L}\right) - T_{\text{initial}} \right] \Delta \left(\frac{X}{L}\right)$$

α as a function of temperature is shown on Figure C-2.

$$\text{Steps} \quad \alpha \left[T\left(\frac{X}{L}\right) \right] \left[T\left(\frac{X}{L}\right) - T_{\text{in}} \right]$$

	α in./in.-°F	$(T-T_1)$ °F		$\alpha (T-T_1)$ in./in.
1	7.71×10^{-6}	(220 - 70)	=	$1,156.5 \times 10^{-6}$
2	7.83×10^{-6}	(350 - 70)	=	$2,192.4 \times 10^{-6}$
3	7.92×10^{-6}	(465 - 70)	=	$3,128.4 \times 10^{-6}$
4	8.03×10^{-6}	(600 - 70)	=	$4,255.9 \times 10^{-6}$
5	8.15×10^{-6}	(720 - 70)	=	$5,297.5 \times 10^{-6}$
6	8.25×10^{-6}	(840 - 70)	=	$6,352.5 \times 10^{-6}$
7	8.35×10^{-6}	(950 - 70)	=	$7,348.0 \times 10^{-6}$
8	8.42×10^{-6}	(1050 - 70)	=	$8,251.6 \times 10^{-6}$
9	8.49×10^{-6}	(1120 - 70)	=	$8,914.5 \times 10^{-6}$
10	8.52×10^{-6}	(1170 - 70)	=	$9,372.0 \times 10^{-6}$
11	8.57×10^{-6}	(1218 - 70)	=	$9,838.3 \times 10^{-6}$
12	8.62×10^{-6}	(1250 - 70)	=	$10,171.6 \times 10^{-6}$
13	8.68×10^{-6}	(1280 - 70)	=	$10,502.8 \times 10^{-6}$

Total steps (1 - 12) = $76,279.2 \times 10^{-6}$ in./in.

Total step (13) = $10,502.8 \times 10^{-6}$ in./in.

(Steps 1 - 12) $\Delta (X/L) = 0.4$ inch out of 5 inches on Figure E-1 (Appendix E)

(Step 13) $\Delta (X/L) = 0.2$ inch out of 5 inches on Figure E-1

$$\begin{aligned}
 76,279.2 \times 0.4/5 &= 6102.3 \times 10^{-6} \\
 10,502.8 \times 0.2/5 &= 420.1 \times 10^{-6} \\
 \hline
 6522.4 \times 10^{-6} &= .006522 \text{ in./in.}
 \end{aligned}$$

Multiply by neck tube length to obtain thermal expansion.

$$\Delta l = .006522 \text{ in./in. (2 497 inch)} = 0.01628 \text{ inch}$$

The expansion of the thick portion of the neck tube at the cold end,

$$\alpha = 7.67 \times 10^{-6} \text{ in./in. From Appendix C, Figure C-2}$$

$$l = 0.283$$

$$\Delta T = (150 - 70)$$

$$\Delta l = 7.67 \times 10^{-6} (0.282) (150 - 70) = 0.000173 \text{ inch}$$

The expansion of the thick portion of the neck tube at the hot end,

$$\Delta l = \alpha l \Delta T$$

$$\Delta l = 8.68 \times 10^{-6} (0.374) (1285 - 70) = 0.003944$$

Total expansion of the neck tube,

$$0.01628 + 0.000173 + 0.003944 = 0.020397$$

$$\underline{0.0204} \text{ inch}$$

3.2.3.3 Temperature Profile of Inconel-625 Male Tension Rod

The thermal conductivity versus temperature curve for Inconel-625 is a straight line and is shown on Figure C-9 (Appendix C). The equation of the straight line is:

$$k = \frac{k_2 - k_1}{t_2 - t_1} (t - t_1) + k_1$$

$$\text{at } t_2 = 1400^\circ\text{F} \quad k_2 = 144$$

$$\text{at } t_1 = 1000^\circ\text{F} \quad k_1 = 121$$

$$k = 0.0575t + 63.5 \text{ Btu-in./hr.sq.ft.}^\circ\text{F}$$

The temperature distribution is given by the formula derived in Appendix D,

$$t \left(\frac{X}{L} \right) = \frac{-b \pm [b^2 + a^2 t_1^2 + 2abt_1 - 2ak_m(t_1 - t_2) \frac{X}{L}]^{1/2}}{a}$$

where,

$$k = .0575 t + 63.5 \text{ Btu-in./ft.-hr.}^\circ\text{F}$$

$$a = .0575 \text{ Btu-in./hr.-ft}^2\text{-}^\circ\text{F}^2$$

$$b = 63.5 \text{ Btu-in./hr.-ft}^2\text{-}^\circ\text{F}$$

$$k_m = .0575 t_m + 63.5 = 131.3 \text{ Btu-in./ft.-hr.}^\circ\text{F}$$

$$t_m = (t_1 + t_2)/2 = (1385 + 974)/2 = 1179.5^\circ\text{F}$$

$$t_1 = 1385^\circ\text{F}$$

$$t_2 = 974^\circ\text{F} \text{ (See calculations of temperature of the rods at the threads.)}$$

The temperatures calculated for various X/L ratios were as follows:

X/L	0	.2	.4	.6	.8	1.0
t ^{°F}	1385	1308	1229	1147	1062	974

The temperature profile of the male rod is plotted on Figure 60.

FIGURE 60
TEMPERATURE DISTRIBUTION OF
INCONEL 625 MALE ROD

3.2.3.4 Thermal Expansion of Inconel-625 Male Rod by Numerical Integration

The thermal expansion coefficient versus temperature for Inconel-625 material is shown on Figure C-10 (Appendix C). The thermal expansion of the male rod is calculated by numerical integration using temperatures from Figure 60 and expansion coefficients from Figure C-10 (Appendix C).

Steps	(T - T _i)	in./in. α - °F	α (T - T _i) in./in.
1	992 - 70	7.79 x 10 ⁻⁶	7,173.1 x 10 ⁻⁶
2	1030 - 70	7.84 x 10 ⁻⁶	7,526.4 x 10 ⁻⁶
3	1062 - 70	7.91 x 10 ⁻⁶	7,846.7 x 10 ⁻⁶
4	1095 - 70	8.02 x 10 ⁻⁶	8,220.5 x 10 ⁻⁶
5	1130 - 70	8.05 x 10 ⁻⁶	8,533.0 x 10 ⁻⁶
6	1162 - 70	8.10 x 10 ⁻⁶	8,845.2 x 10 ⁻⁶
7	1195 - 70	8.18 x 10 ⁻⁶	9,202.5 x 10 ⁻⁶
8	1230 - 70	8.22 x 10 ⁻⁶	9,535.2 x 10 ⁻⁶
9	1260 - 70	8.29 x 10 ⁻⁶	9,865.1 x 10 ⁻⁶
10	1292 - 70	8.32 x 10 ⁻⁶	10,167.0 x 10 ⁻⁶
11	1322 - 70	8.39 x 10 ⁻⁶	10,504.2 x 10 ⁻⁶
12	1355 - 70	8.42 x 10 ⁻⁶	10,819.7 x 10 ⁻⁶
			<hr/> 108,238.6 x 10 ⁻⁶

13	1375 - 70	8.46 x 10 ⁻⁶	11,040.3 x 10 ⁻⁶
----	-----------	-------------------------	-----------------------------

(Steps 1 - 12) Δ (X/L) = .4 inch out of 5 inches on Figure 60 (Steps 1 - 12)

(Step 13) Δ (X/L) = .2 inch out of 5 inches on Figure 60 (Step 13)

$$\begin{aligned}
 108,238.6 \times .4/5 &= 8659 \times 10^{-6} \\
 11,040.3 \times .2/5 &= 441 \times 10^{-6} \\
 \hline
 &9100 \times 10^{-6} \text{ in./in. of Inconel-625}
 \end{aligned}$$

Calculations of the rod temperature at the threads.

$$q_{\text{male rod}} = q_{\text{female rod}} = \frac{\Delta T (\text{Male})}{R (\text{Male})} = \frac{\Delta T (\text{Female})}{R (\text{Female})}$$

where,

$$\begin{aligned}
 R &= \frac{\text{Rod Length}}{\text{Thermal Conductivity} \times \text{Area}} \\
 &\quad \quad \quad 1.76 \quad (144) \\
 T_{\text{hot}} - T_{\text{thread}} &/ \left[\frac{(.0575) (T_H + T_{\text{THR}})}{2} + 63.5 \right] .0585 =
 \end{aligned}$$

$$T_{\text{thread}} - T_{\text{cold}} \left/ \frac{(.85) \quad (144)}{[.06129 \frac{T_{\text{cold}} + T_{\text{thread}}}{2} + 74.7](.01584)} \right.$$

By trial and error solution,

T_{hot} °F	T_{cold} °F	Threads, °F (Assume)	Heat Loss, Btu/Hr. (Male Rod)	Heat Loss, Btu/Hr. (Female Rod)
1385	70	980	12.29	12.58
1385	70	978	12.34	12.55
1385	70	975	12.43	12.49
1385	70	974	12.45	12.48
1385	70	973	12.48	12.46

The calculated rod temperature at the threads is, therefore, 974°F.

3.2.3.5 Temperature Profile of Inconel-718 Female Tension Rod

The thermal conductivity versus temperature curve for Inconel-718 is a straight line and is shown on Figure C-14 (Appendix C). The equation of the straight line is:

$$k = \frac{k_2 - k_1}{t_2 - t_1} (t - t_1) + k_1$$

$$\text{at } t_2 = 1000^\circ\text{F} \quad k_2 = 137$$

$$\text{at } t_1 = 200^\circ\text{F} \quad k_1 = 88$$

$$k = .06129t + 74.7 \text{ Btu-in./hr.-sq.ft.-}^\circ\text{F}$$

The temperature distribution in the rod is given by (Appendix D)

$$t \left(\frac{x}{L} \right) = \frac{-b \pm [b^2 + a^2 t_1^2 + 2abt_1 - 2ak_m(t_1 - t_2) x/L]^{1/2}}{a}$$

where,

$$k = .06129 t + 74.7 \text{ Btu-in.ft.-hr.-}^\circ\text{F (reference: Figure C14, Appendix C)}$$

$$a = .06129 \text{ Btu-in./hr.-ft}^2\text{-}^\circ\text{F}^2$$

$$b = 74.7 \text{ Btu-in./hr.-ft}^2\text{-}^\circ\text{F}$$

$$k_m = .06129 t_m + 74.7 = 106.69 \text{ Btu-in./ft.-hr.-}^\circ\text{F}$$

$$t_m = (t_1 + t_2)/2 = (974 + 70)/2 = 522^\circ\text{F}$$

$$t_1 = 974^\circ\text{F}$$

$$t_2 = 70^\circ\text{F}$$

The temperature distribution is,

X/L	0	.2	.4	.6	.8	1.0
t°F	074	825	665	490	294	70

The temperature profile of the Inconel-718 female rod is shown on Figure 61.

3.2.3.6 Thermal Expansion of Inconel-718 Female Tension Rod

The thermal expansion coefficient versus temperature for Inconel-718 material is shown on Figure C-15 (Appendix C). The thermal expansion of the female rod is calculated by numerical integration using the temperatures from Figure 61 and expansion coefficients from Figure C-15.

Steps	$T - T_i$ °F	α in./in.-°F	$\alpha (T - T_i)$ in./in.
1	125 - 70	6.96×10^{-6}	382.8×10^{-6}
2	215 - 70	7.24×10^{-6}	$1,049.8 \times 10^{-6}$
3	295 - 70	7.48×10^{-6}	$1,683.0 \times 10^{-6}$
4	375 - 70	7.72×10^{-6}	$2,354.6 \times 10^{-6}$
5	452 - 70	7.85×10^{-6}	$2,998.7 \times 10^{-6}$
6	525 - 70	7.93×10^{-6}	$3,608.1 \times 10^{-6}$
7	590 - 70	7.99×10^{-6}	$4,194.7 \times 10^{-6}$
8	665 - 70	8.04×10^{-6}	$4,783.8 \times 10^{-6}$
9	730 - 70	8.07×10^{-6}	$5,326.2 \times 10^{-6}$
10	795 - 70	8.10×10^{-6}	$5,872.5 \times 10^{-6}$
11	855 - 70	8.13×10^{-6}	$6,382.0 \times 10^{-6}$
12	915 - 70	8.16×10^{-6}	$6,895.2 \times 10^{-6}$
			<hr/> $45,531.4 \times 10^{-6}$
13	962 - 70	8.18×10^{-6}	$7,296.5 \times 10^{-6}$

(Steps 1 - 12) $\Delta (X/L) = .4$ inches out of 5 inches on Figure 61.

(Step 13) $\Delta (X/L) = .2$ inches out of 5 inches on Figure 61 (Step 13)

$$45,531.4 \times .4/5 = 3642.5 \times 10^{-6}$$

$$7,296.5 \times .2/5 = 291.9 \times 10^{-6}$$

$$\frac{3934}{10^{-6}} \text{ in./in. of Inconel-718 female tension rod}$$

FIGURE 61
TEMPERATURE DISTRIBUTION OF
INCONEL 718 FEMALE ROD

3.2.3.7 Thermal Expansion of U₈ Moly Shield and Hastelloy-X Spider

Expansion of shield in the axial direction,

$$\Delta l = \alpha l \Delta T = (8.48) 10^{-6} (8.0) (1335 - 70) = .0858 \text{ inch}$$

where,

$$\alpha = 8.48 \cdot 10^{-6} \text{ in./in.-}^\circ\text{F at } 1335^\circ\text{F}$$

Reference: Figure C-20, Appendix C.

The mean temperature of the shield is $t_m = (1385 + 1285)/2 = 1335^\circ\text{F}$

Expansion of Hastelloy-X Spider in the axial direction,

$$\Delta l = \alpha l \Delta T = 8.80 (10^{-6}) (.448) (1385 - 70) = .00518 \text{ inch}$$

The expansion of the spider in the radial direction,

$$\Delta l = 8.80 (10^{-6}) (3.125) (1385 - 70) = .0361 \text{ inch}$$

where,

$$\alpha = 8.80 (10^{-6}) \text{ in./in.-}^\circ\text{F at } 1385^\circ\text{F}$$

Reference: Figure C-2, Appendix C.

The sum of the expansions of neck tube, shield, and spider in the axial direction,

$$b = .0204 + .0858 + .0051 = .1113 \text{ inch}$$

3.2.3.8 Thermal Expansion of Tension Rods

The cold rod length is,

$$l_{(\text{cold})} = 2r + l_1 + l_2 = 2(.16) + (.851) + 1.768 = 2.939 \text{ inch}$$

where,

l_1 = straight section of female rod and l_2 = straight section of male rod. The rod length with the unit at operating temperature is:

$$\begin{aligned} l_{(\text{hot})} &= r + a_1 l_1 + a_2 l_2 + a_3 r = \\ &= (.16) + (1.00393) (.851) + 1.00910 (1.768) + \\ &+ (.16) (1.01113) = 2.9602 \text{ inch} \end{aligned}$$

where,

$$a_1 = 1.00393 \text{ (Female rod) Section 3.2.3.6}$$

$$a_2 = 1.00910 \text{ (Male rod) Section 3.2.3.4}$$

$$a_3 = 1.01113 \text{ (Male rod hot end)}$$

$$a_3 = 1 + \alpha_3 \Delta T = 1 + (8.47) 10^{-6} (1385 - 70) = 1.01113$$

$$\alpha_3 = 8.47 \cdot 10^{-6} \text{ in./in.}^\circ\text{F for Inconel-625 at } 1385^\circ\text{F}$$

Reference: Figure C-10, Appendix C.

3.2.3.9 Calculation of Tension Rod Angle

The tension rod angle is calculated from the requirement that the load in the tension rod must be the same in the cold and hot conditions. If the rod length is known ($l_{\text{cold}} = 2.939 \text{ in.}$, and $l_{\text{hot}} = 2.960 \text{ in.}$) the solution of the rod angle involves the determination of the projected rod lengths in the axial direction (X) and the radial direction (C_1 or C_2).

From the above triangles, we obtain two equations with two unknowns (X and C_1 or C_2).

$$x^2 + C_1^2 = (2.939)^2$$

$$(x + b)^2 + C_2^2 = (2.960)^2$$

Solving for X and C_1

$$x^2 + C_1^2 = (2.939)^2$$

$$(x + .1113)^2 + (C_1 - .0361)^2 = (2.960)^2$$

$$x^2 = (2.939)^2 - C_1^2 ; \quad x = \sqrt{(2.939)^2 - C_1^2}$$

$$\sqrt{(2.939)^2 - C_1^2} + (.1113)^2 + (C_1 - .0361)^2 - (2.960)^2 = 0$$

The above equation is solved for C_1 by trial and error solution.

$$C_1 = 2.61425$$

The accuracy of $C_1 = 2.61425$ is checked by substituting C_1 into the original two equations. Solving the X from the first equation,

$$X = \sqrt{(2.939)^2 - C_1^2} = 1.34291$$

Substituting X and C_1 into the second equation

$$(1.34291 + .1113)^2 + (2.61425 - .0361)^2 = 8.76158$$

$$(8.76158)^{1/2} = 2.95999 \approx 2.960$$

$$\tan = \frac{x}{C_1} = \frac{1.34291}{2.61425} = .51368$$

$\alpha = 27^\circ 11'$ which is initial set angle for the tension rods to provide equal preload in both the ambient temperature and operating temperature conditions.

$$\cos \alpha \text{ (at operating conditions)} = \frac{C_1 - C}{\text{hot rod length}} = \frac{2.61425 - .0361}{2.9602} = .8709$$

$$\alpha \text{ (at operating temperature)} = 29^\circ 26'$$

3.2.4 Support Structure Stress Analysis

3.2.4.1 Design of Tension Rod System Parts

3.2.4.1.1 Design of Tension Rod Threads

The diameter of the male rod is calculated in Section 3.2.4.4 rod = .273 inch. The required thread size to get .273 inch in root diameter is 5/16 - 32 UNEF thread. The fillet radius at the thread ends from Fairies, "Design of Machine Elements", Macmillan, page 145.

$$.2D \leq R \leq .5D$$

$$R \sim (.4) (.3125) = .125 \text{ inch}$$

The stress concentration factor from Fairies, "Design of Machine Elements", page 119; is calculated using the graph with the following inputs:

$$r/d = .125/.273 = .45$$

$$D/d = .312/.273 = 1.14$$

$$K \sim 1.2$$

The maximum local stress in the male rod at the fillet for 6 'g' loading with 1.2 amplification factor due to shock:

$$\sigma = K (AF) \frac{\text{max. rod load}}{\text{rod area}} = (1.2) (1.2) \frac{1035 \text{ lb.}}{.0585 \text{ in.}^2} = 25,476 \text{ psi}$$

The .2 per cent yield stress for Inconel-625 material between 1000°F and 1400°F is 37,000 psi, from technical Bulletin T-42, Huntington Alloy Products Division, The International Nickel Company - 1966. The calculated safety factor is therefore:

$$\text{Safety Factor} = \frac{37,000}{25,476} = 1.45$$

The minimum length of thread engagement is calculated from Machinery's Handbook, 16th Edition, The International Press, page 1050.

$$L_e = \frac{2A_t}{\pi K_n \max. [.5 + .57735 n (E_s \min. - K_n \max.)]}$$

L_e = minimum length of engagement, inch

n = number of threads per inch

$K_n \max.$ = maximum minor diameter of internal thread, inch

$E_s \min.$ = minimum pitch diameter of external thread

A_t = tensile stress area, $\text{inch}^2 = .7854 (D - \frac{.9743}{n})^2$

D = basic major diameter of thread

For 5/16 - 32 UNEF, Class 2 thread

D = .311

n = 24

$K_n \max.$ = .277 inch

$E_s \min.$ = .285 inch

$A_t = .7854 (.311 - \frac{.9743}{24})^2 = .0574 \text{ inch}^2$

$$L_e = \frac{2 (.0574)}{\pi (.277) (.5 + .57735 (24) (.285 - .277))} = .216 \text{ inch}$$

For conservative design, let L_e app. .250 inch thread engagement.

3.2.4.1.2 Design of Female Tension Rod Outside Diameter

The minimum gross-sectional area equals the area of the rod determined to be .0158 inch² in Section 3.2.4.4.

The outside diameter required over the threads is calculated as follows:

$$D^2 (\pi/4) - (.316)^2 (\pi/4) = .0158 \text{ inch}^2$$

$$D = \sqrt{[.0158 + (.316)^2 \pi/4] 4/\pi} = \sqrt{.1199} = .346 \text{ inch}$$

The outside rod diameter required between the threads and the sphere with a .201 inch diameter bore in the rod is:

$$D = \sqrt{[.0158 + (.201)^2 \pi/4] 4/\pi} = \sqrt{.0605} = .246 \text{ inch}$$

3.2.4.1.3 Design of Spherical Washer

The support rod rotates 2° 17' during unit heat up due to thermal expansions. The clearance between the spherical washer and the support rod is calculated from the following angular relationships:

$$\begin{aligned} c &= (.312) \\ &\quad \tan 2^\circ 17' \\ &= (.312) (.03987) \\ &= .012 \text{ inch} \end{aligned}$$

Allowing .015 clearance on the side

$$d_1 = .246 + 2 (.012) + 2 (.015) = .300 \text{ inch}$$

$d_1 = .300$ inch minimum. The actual inside diameter of the spherical washer was selected to be .358 inch.

The diameter of the sphere (D) is calculated by allowing two times the cross-sectional area of the female support rod for bearing surface.

$$D = \sqrt{[(.358)^2 \pi/4 + 2 (.0158)] 4/\pi} = .41 \text{ inch}$$

Let $D = .5$ inch

Checking the safety factor at the fillet radius on the support rod female end adjacent to the spherical end, it follows from Fairies Design of Machine Elements, page 119, that a .033 inch radius will yield a 1.2 safety factor

$$\frac{r}{d} = \frac{.033}{.246} = .13 \quad K = 1.6 \text{ from Fairies}$$

The maximum stress with 1.2 amplification factor

$$\sigma = K (AF) \frac{\text{max. rod load}}{\text{rod area}} = (1.6) (1.2) \frac{1035}{.0158} = 125,772 \text{ psi}$$

The .2 per cent yield stress of Inconel-718 material at ambient temperature from Figure C-17 in Appendix C is 150,000 psi. The local safety factor is therefore:

$$\text{Safety Factor} = \frac{150,000}{125,772} = 1.2$$

Calculation of the support rod opening diameters through the receptacle is calculated as follows:

$$\begin{aligned} c &= .412 \tan 2^{\circ}17' \\ &= .412 (.03987) \\ &= .016 \text{ inch} \end{aligned}$$

Allowing .015 inch clearance on the side.

$$d = .246 + 2 (.016) + 2 (.062) + 2 (.015) = d = .432 \text{ inch}$$

The actual inside diameter of the receptacle of .45 inch was selected.

3.2.4.2 Calculation of Area of Female Support Rod to Achieve 1000°F At Connection of Support Rods

The length of the male and female rods were determined to be:

$$l_1 \text{ (female)} = .85 \text{ inch}$$

$$l_2 \text{ (male)} = 1.76 \text{ inch}$$

The proportional limit for the materials used for the male and female rod halves.

Female rod, Inconel-718 annealed and aged, proportional limit = 117,000 psi at 1000°F from Figure C-17, Appendix C.

Male rod, Inconel-625 solution annealed, proportional limit 30,000 psi between 1400°F and 1000°F from Figure C-12, Appendix C.

The thermal resistance of the male rod

$$R_2 = \frac{l_2}{K_2 A_2} = \frac{1.768 (144)}{133.36 \cdot 0.0585} = 32.63 \frac{\text{hr.}^\circ\text{F}}{\text{Btu}}$$

If the temperature is 1000°F, at the joint of the two rod halves, the heat flow through the male rod is

$$q = \frac{\Delta T_2}{R_2} = \frac{1430 - 1000}{32.63} = 13.17 \frac{\text{Btu}}{\text{hr.}} = 3.86 \text{ watt}$$

The thermal resistance of the female rod is

$$R_1 = \frac{\Delta T}{q} - R_2 = \frac{1430 - 70}{13.17} - 32.63 = 70.63 \frac{\text{hr.}^\circ\text{F}}{\text{Btu}}$$

The area of the female rod is

$$A_1 = \frac{l_1}{R_1 K_1} = \frac{.851 (144)}{70.63 \cdot 107.5} = .0161 \text{ inch}^2$$

The allowable stress in the female rod with 1.5 safety factor and 1.2 amplification factor is

$$\sigma_{\text{allowable}} = \frac{117,000}{1.5 \times 1.2} = 65,000 \text{ psi}$$

The stress in the female rod at 6 'g' loading is

$$\sigma = \frac{\text{maximum load}}{A_1} = \frac{1035}{.0161} = 64,285 \text{ psi}$$

3.2.4.3 Calculation of Support System Spring Constants

The following sections present the calculations of the support system elements spring constants. The reciprocals of the spring constants are summarized as follows:

<u>Part Name</u>	<u>$\frac{1}{K'} \frac{\text{inch}}{\text{pounds}}$</u>	<u>Calculation in Section</u>
Female Rod	$\frac{.1164}{A_2} 10^{-6}$	3.2.4.3.1
Male Rod	$\frac{.0730}{A_2} 10^{-6}$	3.2.4.3.2
Spherical Washer	$\frac{.0038}{A_2} 10^{-6} + .141 10^{-6}$	3.2.4.3.3
Receptacle	$.062 10^{-6} + .084 10^{-6}$	3.2.4.3.4
Outside Shell	$.024 10^{-6}$	3.2.4.3.5
Spider	$.027 10^{-6}$	3.2.4.3.6
Shield	$.073 10^{-6}$	3.2.4.3.7

The sum of the reciprocal of spring constants = $\frac{1}{K} = [\frac{.1933}{A_2} + .411] 10^{-6}$

3.2.4.3.1 Female Support Rod Spring Constant

The female support rod spring constant reciprocal is calculated from the relationship

$$\frac{1}{K_1} = \frac{\ell_1}{E_1 A_1}$$

where,

ℓ_1 = .851 inch, length of female rod

E_1 = $27 \cdot 10^{-6}$ psi, average modulus of elasticity for female rod between ambient and 1000°F from Figure C-16 (Appendix C)

A_1 = $.0158 \text{ inch}^2$, area of female rod

A_2 = $.0585 \text{ inch}^2$, area of male rod

$A_1 = (A_1/A_2) = (.0158/.0585)A_2 = .27 A_2$

$$\frac{1}{K_1} = \frac{\ell_1}{E_1 A_1} = \frac{.851}{27 \cdot 10^6 (.27) A_2} = \frac{.1164 \cdot 10^{-6}}{A_2} \text{ (in./lb.)}$$

3.2.4.3.2 Male Support Rod Spring Constant

The male support rod spring constant reciprocal is calculated in the same manner as the female support rod where:

$$l_2 = 1.76 \text{ inch, length of male rod}$$

$E_2 = 24.2 \cdot 10^6$ psi, average modulus of elasticity for male rod between 1000°F and 1435°F from Figure C-11 (Appendix C)

$$\frac{1}{K_2} = \frac{l_2}{E_2 A_2} = \frac{1.768}{24.2 \cdot 10^6 A_2} = \frac{.0370 \cdot 10^{-6}}{A_2} \text{ (in./lb.)}$$

3.2.4.3.3 Spherical Washer Spring Constant

The spherical washer spring constant reciprocal is calculated by considering the displacements in the load direction caused by direct axial load and also by radial load. The spring constant reciprocal based on axial loading is calculated from the relationship $\frac{1}{K} = \frac{l}{EA}$ where:

$$l = \text{effective length} = (0.312 - 0.16) + 0.16/2 = .232 \text{ inch}$$

$A = 2A_2$ the load bearing area of the spherical seat is twice the area of the male support rod

$E = 29.8 \cdot 10^6$ psi at ambient. The modulus of elasticity for Hastelloy-X from Figure C-3 (Appendix C)

$$\frac{1}{K} = \frac{l}{EA} = \frac{.232}{29.8 \times 10^6 (2 A_2)} = \frac{.116}{29.8 \cdot 10^6 A_2} = \frac{(.0038 \cdot 10^{-6})}{A_2}$$

Calculation of tension rod displacement in the direction of the load due to the radial deflection of the spherical washer is calculated as follows:

The radius where the concentrated load is applied is:

$$R = \left(\frac{.5 - .392}{2} \right)^{1/3} + \frac{.392}{2} = .216 \text{ inch}$$

[.392 inch reflects the 1/64 corner break allowed on .358 inch diameter.]

The radial component of the load P_r , at radius R per 1000 pounds load is:

$$P_r = 1000 \tan 57^\circ 49' = 1550 \text{ lb.}$$

The average pressure in the radial direction is

$$P_i = \frac{P_r}{\pi DL} = \frac{1550}{\pi (.216) 2 (.250)} = 4570 \text{ psi}$$

The maximum tangential stress due to the internal pressure P_i is;

$$\sigma_t = \frac{a^2 P_i}{b^2 - a^2} \left[1 + \frac{b^2}{r^2} \right] = \frac{(.216)^2 4570}{(.352)^2 - (.216)^2} \left[1 + \frac{(.352)^2}{(.216)^2} \right] = 10,091 \text{ psi}$$

where,

$$a = R = .216 \text{ inch}$$

$$b = .352 \text{ inch (outside radius of washer)}$$

The deflection of the spherical washer in the radial direction at $r = a = R$

$$u_r \bigg|_{r=a} = \frac{a P_i}{E} \left[\frac{a^2 + b^2}{b^2 - a^2} + \mu \right] = \frac{.216 (4570)}{29.8 \cdot 10^6} \left[\frac{(.216)^2 + (.352)^2}{(.352)^2 - (.216)^2} + .3 \right] = 82 \cdot 10^{-6} \text{ inch}$$

From Roark Table XIII Case 33

The displacement of the rod in the direction of the load is:

$$y_v = y_r \tan 60 = 82 \cdot 10^{-6} (1.73) \\ = 141 \cdot 10^{-6} \text{ inch}$$

$$\frac{1}{K} = \frac{141 \times 10^{-6}}{1000} = .141 \cdot 10^{-6} \text{ in./lb.}$$

The sume of the reciprocal of spring constants for the spherical washer is therefore:

$$\frac{1}{K \text{ (compression)}} + \frac{1}{K \text{ (radial deflection)}} = \frac{.0038 \cdot 10^{-6}}{A_2} + .141 (10^{-6})$$

3.2.4.3.4 Receptacle Spring Constant

The receptacle spring constant reciprocal is calculated by considering the displacements of the cylindrical section and considering the displacements of the cylindrical section and considering the displacements for the receptacle flange. The spring constant reciprocal based on the cylindrical portion deflection is calculated from the relationship $\frac{1}{K} = \frac{\ell}{EA}$

where,

$$\ell = \text{effective length} = \frac{.1 + .8}{2} = .45 \text{ inch}$$

A = area of cylindrical portion of receptacle

$$= \frac{\pi}{4} (1^2 - .830^2) = .2442 \text{ inch}^2$$

$E = 29.8 \cdot 10^6$ stainless steel at ambient temperature

$$\frac{1}{K} = \frac{.45}{29.8 \cdot 10^6 (.2442)} = .062 \cdot 10^{-6} \frac{\text{inch}}{\text{pound}}$$

The reciprocal of the spring constant for the receptacle flange is calculated in the following manner using the deflection equation as presented in Formulas for Stress and Strain, R. J. Roark, McGraw Hill, 1954, Case 18, page 221.

$$a = .830 \text{ inch}$$

$$b = .705 \text{ inch}$$

$$E = 29.8 \cdot 10^6 \text{ psi}$$

$$m = \frac{1}{\nu} = \frac{1}{.308} = 3.24$$

$$3W = 960 \text{ pounds}$$

The maximum deflection

$$y = \frac{3W (m^2 - 1)}{4\pi m^2 E t^3} \left[a^2 - b^2 + \frac{2mb^2(a^2 - b^2)}{a^2(m-1) + b^2(m+1)} - \frac{8ma^2b^2 \log \frac{a}{b} + 4a^2b^2(m+1) \left(\log \frac{a}{b} \right)^2}{a^2(m-1) + b^2(m+1)} \right]$$

From Roark Table X Case 18

$$y = \frac{.081 \cdot 10^{-6}}{t^3}$$

$$\text{for } t = .1 \text{ inch } y_m = 81 \cdot 10^{-6} \text{ inch}$$

$$\frac{1}{K} = \frac{y_m}{P} = \frac{81 \cdot 10^{-6}}{960} = .084 \cdot 10^{-6} \text{ in./lb.}$$

3.2.4.3.5 Enclosure Shell Spring Constant

The spring constant reciprocal for the enclosure shell in the area of the receptacles was calculated by the method presented in "Computation of the Stresses from Local Loads in Spherical Vessels or Pressure Vessel Head", P. B. Bijloard, Welding Research Council.

The deflection of the enclosure shell in the radial direction at the receptacle for an applied load of 1000 pounds was calculated to be .000024 inch.

The reciprocal of the spring constant is therefore:

$$\frac{1}{K} = \frac{.000024}{1000} = .024 \cdot 10^{-6} \frac{\text{inch}}{\text{pound}}$$

3.2.4.3.6 Spider Spring Constant

To determine the stress and deflections in the spider under the loading of the three tension rods would require a two dimensional stress analysis. To avoid the complexity of solution involved with a two dimensional analysis, simplifying assumptions are made to the problem in order to reduce the solution to one dimensional analysis.

If the full load of one tension rod acts on a concentrated area of the spider, the stress in the spider is

$$\sigma = \frac{\text{Rod load}}{\text{Area spider}} = \frac{950 \text{ lb.}}{(.5) (.5) \text{ in}^2} = 3800 \text{ psi}$$

If we assume that this tensile stress acts all around the spider, which is a solid disc, the radial deflection in the spider can be calculated by

$$U_{(r=b)} = \frac{b \cdot p}{E} \left[\frac{b^2 + a^2}{b^2 - a^2} - \mu \right] = \frac{(3.125) (3800)}{21 (10^6)} \left[\frac{(3.125)^2 + (.5)^2}{(3.125)^2 - (.5)^2} - .32 \right]$$

$$= .000414 \text{ inch}$$

From Roark Table XIII Case 33

Since the load acts actually only on a small portion of the circumference, an approximate value for the actual deflection can be obtained by

$$y = \frac{l}{2 \pi b} [U_{r=b}] = \frac{.5}{2 \pi 3.125} .000414 = 10 \times 10^{-6} \text{ inch}$$

Calculation of shear deflection of the ring portion of the spider

P rod $\approx$ 950 pounds

The shear deflection

$$y = \frac{2 P \ell}{AG} = \frac{2 (950) (.250) (2.64)}{3.32 (21) 10^6} = 17 \times 10^{-6} \text{ inch}$$

where,

$$G = \frac{E}{2 (1 + \mu)} = \frac{E}{2 (1 + .32)} = \frac{E}{2.64}$$

$$A = (4.5^2 - 4^2) \pi/4 = 3.32 \text{ inch}^2$$

$$E = 21 \times 10^6 \text{ for Hastelloy-X at } 1430^\circ\text{F, from Figure C-3, Appendix C.}$$

The reciprocal of the spring constant for the spider is found by summing the reciprocals of the spring constant due to radial stress and due to shear.

$$\frac{1}{K} = \frac{1}{K (\text{radial})} + \frac{1}{K (\text{shear})} = \frac{10}{950} 10^{-6} + \frac{17}{950} 10^{-6} = .027 10^{-6} \frac{\text{inch}}{\text{pound}}$$

3.2.4.3.7 Radiation Shield Spring Constant

The shear deflection of the ring on the shield

$$y = \frac{2 P \ell}{AG} = \frac{2 (950) (.250) 2.6}{7 (2.5) 10^6} = 70 \cdot 10^{-6} \text{ inch}$$

where,

$$A = (5.4^2 - 4.5^2) \pi/4 = 7 \text{ inch}^2$$

$$E = 2.5 \cdot 10^6 \text{ psi for U-8 Moly at } 1430^\circ\text{F, Figure C-22 Appendix C}$$

$$G \cong E/2.6$$

The reciprocal of the radiation shield spring constant is therefore:

$$\frac{1}{K} = \frac{70}{950} \cdot 10^{-6} \text{ in./lb.}$$

3.2.4.4 Design of Neck Tube and Tension Rods

The following sections present the design considerations and calculations to size the neck tube and the tension rods. Both the axis horizontal and axis vertical loading conditions were considered with a 6 'g' shock loading.

3.2.4.4.1 Unit in Horizontal Position

Using the load sharing equation derived in Appendix F, the tension rod loading can be determined from the following relationship.

$$P_\alpha = \frac{W}{\cos \alpha} \frac{X_1 + X_2 + X_3}{\frac{1}{K} \frac{1}{\cos^2 \alpha} + X_4 + X_5 + X_6}$$

$$X_1 = \frac{\ell_1^2 (2\ell_1 + 3\ell_2 + 3\ell_3) + 3\ell_1\ell_2 (\ell_1 + 2\ell_2 + 2\ell_3)}{6 E_{NT} I_{NT}}$$

$$X_2 = \frac{2 \ell_1}{AG}$$

$$X_3 = \frac{2 (\ell_{in} + \ell_2) (\ell_{in} + \ell_2 + \ell_3)}{64.9 \cdot 10^6}$$

$$X_4 = \frac{\ell_1^2 (2\ell_1 + 3\ell_2 + 3\ell_3) + 3 \ell_1 (\ell_1 + 2\ell_2 + 2\ell_3) (\ell_2 + \ell_3 + e \tan \alpha)}{6 E_{NT} I_{NT}}$$

$$X_5 = X_2$$

$$X_6 = \frac{2 (\ell_{in} + \ell_2 + \ell_3 + e \tan \alpha) (\ell_{in} + \ell_2 + \ell_3)}{64.9 \cdot 10^6}$$

where,

P	=	tension rod load	$\frac{1}{K}$	=	$[\frac{.1933}{A_2} + .411] 10^{-6}$
W	=	289 pounds (6 'g') = 1734 pounds			
α	=	tension rod angle $27^\circ 30'$	l_1	=	2.497 inch
$s_{in} \alpha$	=	.46175	l_{in}	=	2.78 inch
$\cos \alpha$	=	.88701	l_2	=	4.43 inch
$\tan \alpha$	=	.52057	l_3	=	4.385 inch
E_{NT}	=	$25 \cdot 10^6$ psi	e	=	3.125 inch
A_2	=	area of male tension rod	G	=	$E/2.64$
A	=	area of neck tube			
I_{NT}	=	moment of inertia of neck tube			

Calculating the tension rod load from the load sharing equation using a .012 inch thick neck tube wall thickness

$$I_{NT} = [D + .024]^4 - D^4 \cdot \frac{\pi}{64} = .5582 \text{ inch}^4$$

$$A = [(D + .024)^2 - D^2] \cdot \frac{\pi}{4} = .1850 \text{ inch}^2$$

$$X_1 = \frac{2.497^2 [2(2.497) + 3(4.43) + 3(4.385)] + 2(2.497)(4.43) [(2.497 + 2(4.43) + 2(4.385))]}{6 (25) 10^6 (.5582)}$$

$$= 10.31 \cdot 10^{-6}$$

$$X_2 = \frac{2 (2.497) 2.64}{(.1850) (25) 10^6} = 2.85 \cdot 10^{-6}$$

$$X_3 = \frac{2 (2.78 + 4.43) (2.78 + 4.43 + 4.385)}{64.9 \cdot 10^6} = 2.57 \cdot 10^{-6}$$

$$X_4 = (2.497)^2 [(2(2.497) + 3(4.43) + 3(4.385)) + 3(2.497) [(2.497) + 2(4.43) + 2(4.385)]$$

$$[4.43 + 4.385 + 3.125 (.52057)]] / 6(25) 10^6 (.5582) = 21.17 \cdot 10^{-6}$$

$$X_5 = X_2 = 2.85 \cdot 10^{-6}$$

$$X_6 = \frac{2[2.78 + 4.43 + 4.385 + 3.125 (.52057)](2.78 + 4.43 + 4.385)}{64.9 \cdot 10^6} = 4.73 \cdot 10^{-6}$$

Substituting the above to determine the tension rod load, P as a function of the rod area A_2

$$P\alpha = 1955 \frac{15.73 \cdot 10^{-6}}{\left[\frac{.1933}{A_2} \cdot 10^{-6} + .411 \cdot 10^{-6} \right] \frac{1}{\cos^2 \alpha} + 28.75 \cdot 10^{-6}}$$

3.2.4.4.1.1 Loading Condition I

This is the loading condition where two of the tension rods share equal loading. Under this condition the neck tube is subjected to the greatest loadings. The rod loadings relative to rotation of the unit are calculated and presented in Appendix G.

For a male tension rod diameter of .273 inches,

$$A_2 = \frac{\pi}{4} (.273)^2 = .0585 \text{ inch}^2$$

$$\frac{1}{K} = \left[\frac{.1933}{.0585} \cdot 10^{-6} + .411 \cdot 10^{-6} \right] \frac{1}{.5} = 7.431 \cdot 10^{-6}$$

Where $(1/.5)$ represents the change in spring constant for loading conditions (Appendix G).

$$P\alpha = 1955 \frac{15.73 \cdot 10^{-6}}{7.431 \cdot 10^{-6} / (.88701)^2 + 28.75 \cdot 10^{-6}} = 805 \text{ pounds}$$

The shear load on the neck tube:

$$W - P = 1734 - 805 (.88701) = 1020 \text{ pounds}$$

The applied shear stress on the neck tube:

$$\tau = \frac{W - P}{\pi R t} = \frac{1020}{3.14 (2.462) (.012)} = 10993 \text{ psi}$$

For the unit at operating temperature the tension rod angle α is $29^\circ 26'$.

$$P\alpha = 807 \text{ pounds}$$

$$W - P = 1030 \text{ pounds}$$

$$\tau = 11107 \text{ psi}$$

The moments at the top and bottom of the neck tube are

$$\begin{aligned}
 M_{(\text{top end})} &= W(\ell_1 + \ell_2) - P(\ell_1 + \ell_2 + \ell_3 + e \tan \alpha) \\
 &= 1734 (2.497 + 4.43) - 714 [2.497 + 4.43 + 4.385 \\
 &\quad + 3.125(.52057)] = 2773 \text{ in.-lb.} \\
 M_{(\text{bottom end})} &= W \ell_2 - P(\ell_2 + \ell_3 + e \tan \alpha) \\
 &= 1734 (4.43) - 714 [4.43 + 4.385 + 3.125 (.52057)] \\
 &= 227 \text{ in.-lb.}
 \end{aligned}$$

The compressive stress due to bending moment

$$\begin{aligned}
 \sigma_{(\text{top end})} &= \frac{MC}{I} = \frac{2773 (2.462)}{.5582} = 12230 \text{ psi} \\
 \sigma_{(\text{bottom end})} &= \frac{227 (2.462)}{.5582} = 1001 \text{ psi}
 \end{aligned}$$

Calculate the critical shear stress for the neck tube at failure in shear buckling.

$$\frac{R}{t} = \frac{2.462}{.012} = 205 \qquad \frac{L}{R} \sim 1$$

From "Review of Design Information on Buckling of Unstiffened Thin Walled Circular Cylindrical Shells - Bertram Klein" ARS 13th Annual Meeting, New York, New York, November, 1959, Figure 2

$$\frac{\tau_{cr}}{E_r} \times 10^3 = .72$$

Calculate the ratio of critical shear stress to critical torsion stress f_v/S_s

$$\begin{aligned}
 \tau_{cr \text{ shear}} &= \left(\frac{f_v}{S_s}\right) .72 \cdot 10^{-3} E_R \\
 \left(\frac{M}{RV}\right)_{\text{top end}} &= \frac{2773}{2.452 (1020)} = 1.1 \\
 \left(\frac{M}{RV}\right)_{\text{bottom end}} &= \frac{227}{2.462 (1020)} = .09
 \end{aligned}$$

From "Strength Tests of Thin-Walled Duralamin Cylinders in Carbined Transverse Shear and Bending - Eugene E. Lundquist" NACA Technical Note 523, Washington 1935, Figure 7.

$$\frac{fv}{S_s \text{ (top end)}} = .88$$

$$\frac{fv}{S_s \text{ (bottom end)}} = 1.2$$

The reduced modulus of elasticity is the same as Youngs modulus of elasticity at these low compressive stresses and are from Figure C-3, Appendix C,

$$E_r \text{ (top end)} = 28.3 \cdot 10^6$$

$$E_r \text{ (bottom end)} = 21.7 \cdot 10^6$$

The critical shear stress is

$$\tau_{cr} \text{ (top end ambient and operating)} = (.9) .72 \cdot 10^{-3} 28.3 \cdot 10^6 = 18338 \text{ psi}$$

$$\tau_{cr} \text{ (bottom end operating)} = 1.2 (.72) 10^{-3} 21.7 \cdot 10^6 = 18748 \text{ psi}$$

$$\tau_{cr} \text{ (bottom end ambient)} = 1.2 (.72) 10^{-3} 28.3 \cdot 10^6 = 24451$$

The safety factor including a 1.2 amplification factor is shock is:

$$\text{Safety factor (top end ambient)} = \frac{18338}{1.2 (10993)} = 1.39$$

$$\text{Safety factor (top end operation)} = \frac{18339}{1.2 (1107)} = 1.38$$

$$\text{Safety factor (bottom end ambient)} = \frac{24451}{1.2 (10993)} = 1.85$$

$$\text{Safety factor (bottom end operating)} = \frac{18748}{1.2 (11107)} = 1.41$$

3.2.4.4.1.2 Loading Condition II

The most severe loading condition for the tension rods is the orientation of the tension rods shown on the sketch above. The maximum load in the tension rod occurs at 45° and is 1035 pounds under 6 'g' loading. Calculations of the loads for various rod orientations are presented in Appendix G and results are tabulated in Table G-1.

The applied stress in the male tension rod with 1.2 amplification due to shock is

$$\sigma = 1.2 \frac{1035 \text{ lb.}}{.0585 \text{ in}^2} = 21,230 \text{ psi}$$

The safety factor based on 30,000 psi proportional limit of the male rod (Inconel 625 solution annealed material between 1400°F and 1000°F, Figure C-12, Appendix C.

$$\text{Safety factor} = \frac{30,000}{21,230} = 1.41$$

(tension rod)

3.2.4.4.2 Vertical Position (Neck Tube Open End Up)

The weight on the neck tube and three tension rods acting downward under 6 'g' acceleration is

$$W = 289 \times 6 = 1734 \text{ pounds}$$

The load carried by the neck tube and three tension rods are calculated from knowing that the deflection of the neck tube in the vertical direction is the same as the deflection of the tension rods in the vertical direction.

$$\delta_{rv} = \frac{\partial r}{\sin \alpha} = \frac{P_v l_r}{E_r A_r \sin^2 \alpha} = \delta_{nt}$$

$$\delta_{nt} = \frac{P_{nt} l_{nt}}{E_{nt} A_{nt}} = \frac{P_v l_r}{E_r A_r \sin^2 \alpha}$$

$$\frac{P_{nt}}{P_v} = \frac{E_{nt} A_{nt}}{E_r A_r} \frac{l_r}{l_{nt} \sin^2 \alpha}$$

For the two rod halves

$$\frac{l_r}{E_r A_r} = \frac{l_1}{E_1 A_1} + \frac{l_2}{E_2 A_2}$$

$$\frac{P_{nt}}{P_v} = \frac{E_{nt} A_{nt}}{E_1 A_1 + E_2 A_2} \left(\frac{l_1}{E_1 A_1} + \frac{l_2}{E_2 A_2} \right) \frac{1}{\sin^2 \alpha}$$

for $t = .012$ inch, $\alpha = 29^\circ 26'$ operating temperature rod angle.

$$\frac{P_{nt}}{P_v} = \frac{25 \cdot 10^6 (.1850)}{2.497} \left[\frac{.851}{27 \cdot 10^6 (.0158)} + \frac{1.768}{24.2 \cdot 10^6 (.0585)} \right] \frac{1}{(.4914)^2} = 24.88$$

$P_{nt} + 3 P_{rv} = 1734$ (where P_{rv} is vertical load in each rod)

$$24.88 P_{rv} + 3 P_{rv} = 1734$$

$$27.88 P_{rv} = 1734$$

$$P_{rv} = 62.2 \text{ pounds } 3 P_{rv} = 187 \text{ pounds}$$

$$P_{nt} = 1734 - 187 = 1547 \text{ pounds}$$

$$P_r = P_{rv} / \sin \alpha = 62.2 / .4914 = 127 \text{ pounds}$$

Neglecting the reduction in neck tube load due to tension rod pretension the load in the neck tube is therefore 1547 pounds. When the unit is subjected to a 6 'g' shock loading.

The tensile stress in the neck tube ($t = .012$) with a 1.2 shock amplification factor is

$$\sigma_t = \frac{P_{nt} \times 1.2}{A_{nt}} = \frac{1547 \times 1.2}{.1850} = 10,035 \text{ psi}$$

The tensile stress due to one atmosphere internal pressure is

$$\sigma_p = \frac{PR}{2t} = \frac{14.7 \times 2.462}{2 (.012)} = 1508 \text{ psi}$$

The maximum tensile stress in the neck tube

$$\sigma_{\max} = 10,035 + 1508 = 11,543 \text{ psi}$$

The safety factor based on a 30,000 psi proportional limit for Hastelloy-X, Figure C-12, Appendix C

$$\text{Safety factor} = \frac{30,000}{11,543} = 2.6$$

3.2.4.4.3 Vertical Position (Neck Tube Open End Down)

For this loading conditon, the neck tube is checked for strength in combined compression and internal pressure and for buckling in combined compression and internal pressure.

3.2.4.4.3.1 Strength in Combined Compression and Internal Pressure

The compressive stress in the neck tube is caused by the weight of the shield 289 lb. (6 'g') = 1734 lb., and by the preload in the tension rods. The prestress requires in the tension rods is 3300 psi for the male rod and 12,150 psi for the female rod. The tensile stress in the rod due to the tolerance allowance on the angle α is from 0 to 4000 psi for the male rod and 0 to 15,000 psi for the female rod. The total stress in the male tension rod varies from 3300 psi to 7300 psi. The tensile force in the rod due to the initial stress is

$$Pr = (.0585) 3300 = 193 \text{ pounds minimum per rod}$$

$$Pr = (.0585) 7300 = 427 \text{ pounds maximum per rod}$$

The maximum force caused by the preload in the three tension rods is $3 (427 \text{ lb.}) \sin 29^\circ 26' = 629 \text{ pounds.}$

The compressive force in the neck tube is

$$Pnt = 1734 + 629 = 2362 \text{ pounds}$$

The compressive stress in the neck tube

$$\sigma_c = \frac{2362 \text{ lb.}}{.1850 \text{ in}^2} = 12,775 \text{ psi}$$

The tensile stress due to one atmosphere internal pressure is 1508 psi, therefore the maximum compressive stress in the neck tube is

$$\sigma_{\max} = 12,775 - 1508 = 11,267 \text{ psi}$$

The safety factor in compression with a 1.2 shock amplification factor is

$$\text{Safety factor} = \frac{30,000}{11,267 (1.2)} = 2.2$$

3.2.4.4.3.2 Buckling in Combined Compression and Internal Pressure

The critical buckling stress is determined from "Review of Design Information on Buckling of Unstiffened Thin Walled Circular Cylindrical Shells - Bertram Klein", ARS 13th Annual Meeting, New York, New York, November, 1958, Figure 4a.

$$\frac{PR}{Et} = \frac{14.7 (2.462)}{21.7 \cdot 10^6 \cdot .012} = .0198$$

$$\frac{.007}{.007}$$

From the graph

$$\frac{\sigma_c c r}{E_r} \frac{R}{t} = .28$$

$$\sigma_c c r = \frac{t}{R} E_r (.28) = \frac{.012}{2.462} 21.7 \cdot 10^6 (.28) = 29,610 \text{ psi}$$

The safety factor for buckling with a 1.2 shock amplification factor is

$$\text{Safety factor} = \frac{29,610}{11,267 (1.2)} = 2.2$$

3.2.4.5 Thermal Load and Stresses Developed in the Tension Rods Due to Tension Rod Angle Tolerance

$$\begin{aligned} \alpha &= 27^\circ 11' \\ b &= .1113 \text{ inch} \\ a_1 &= 1.00393 \\ l_1 &= 0.851 \text{ inch} \\ a_2 &= 1.0091 \\ l_2 &= 1.768 \text{ inch} \\ a_3 &= 1.01113 \\ r &= 0.16 \text{ inch} \\ C_1 &= 2.61425 \text{ inch} \\ C &= .0361 \text{ inch} \\ C_2 &= 2.5781 \text{ inch} \\ x &= 1.34291 \text{ inch} \end{aligned}$$

For axial tolerance of $\Delta X = .060$ inch

$$\tan (\alpha + \Delta \alpha) = \frac{x + \Delta x}{C_1} = \frac{1.34291 + .060}{2.61425} = .5366$$

$$(\alpha + \Delta \alpha) = 28^\circ 13'$$

$$\Delta \alpha = 28^\circ 13' - 27^\circ 11' = 1^\circ 02'$$

$1^\circ 02'$ is the angle tolerance equivalent to the .060 inch axial length tolerance.

$$(\ell + \Delta \ell)_{\text{cold}} = [(x + \Delta x)^2 + C_1^2]^{1/2} = [(1.34291 + .060)^2 + (2.61425)^2]^{1/2} = 2.9668 \text{ inch}$$

Calculating the original length $\ell + \Delta \ell$ from the hot condition using the triangles above.

$$(\ell + \Delta \ell)_{\text{hot}} = \frac{[(x + \Delta x + b)^2 + C_2^2]^{1/2} - r(1 + a_3)}{a_1 (.325) + a_2 (.675)} + 2r = 2.9685 \text{ inch}$$

The required length $\ell + \Delta\ell$ calculated from the hot condition is longer than that of calculated from the cold condition, thus indicating tension rod tightness.

$$\delta = (\ell + \Delta\ell)_{\text{hot}} - (\ell + \Delta\ell)_{\text{cold}} = 2.9685 - 2.9668 = .0017 \text{ inch}$$

The force in the rod is calculated from

$$P = \frac{\delta}{\frac{\ell_1}{A_1 E_1} + \frac{\ell_2}{A_2 E_2}} = \delta / 3.23 (10^{-6}) = .0017 / 3.23 (10^{-6}) = 528 \text{ pounds}$$

where,

$$A_1 = \text{area of female tension rod} = .0158 \text{ inch}^2$$

$$A_2 = \text{area of male tension rod} = .0585 \text{ inch}^2$$

$$E_1 = \text{modulus of female rod} = 27 \times 10^6 \text{ psi}$$

$$E_2 = \text{modulus of male rod} = 24.2 \times 10^6 \text{ psi}$$

$$\sigma_{\text{male}} = P/A = 528/.0585 = 9025 \text{ psi}$$

The stress in the female rod,

$$\sigma_{\text{female}} = P/A = 528/.01584 = 33,333 \text{ psi}$$

The load and the corresponding stresses in the tension rods due to different rod angle tolerances ranging from 0 to 1° 02' were calculated and results are shown on Figure 62.

3.2.4.6 Effect of the Temperature Difference Between Spider and Emitter Plate Temperature on Tension Rod Looseness and Tightness

Calculations were performed to determine the effect of temperature difference between the spider and emitter plate with a tension rod set angle of 27° 11' as was calculated in Section 3.2.3.9 for a 100°F temperature difference with the emitter plate at 1285°F.

The results of the calculations which were performed in the same manner as those in Section 3.2.3 are presented on Figure 63. This figure shows that the tension rods will remain tight as long as the spider is less than 1385°F with the emitter plate at a 1285°F operating temperature.

3.2.5 Support Structure Vibration Analysis

This section presents the dynamic vibration analysis performed to assure that the components selected in Section 3.2.4 based on a 6 'g' shock loading are also adequate for a 3 'g' vibration loading in the frequency range 5 - 50 Hz.

FIGURE 62

LOAD AND STRESSES IN THE TENSION RODS AT OPERATING TEMPERATURE
DUE TO TENSION ROD ANGLE TOLERANCE

FIGURE 63

EFFECT OF TEMPERATURE DIFFERENCE BETWEEN SPIDER AND
EMITTER PLATE TEMPERATURES ON TENSION ROD
LOOSENESS AND TIGHTNESS

3.2.5.1 Vibration Analysis Model

For the vibration analysis the HTVIS was considered simply by modeling it as a cantilever beam.

The vibration model for the cantilever beam is

The equation of resonance for the case of forced vibration without damping from Mechanical Vibrations, Den Hartog, McGraw Hill, 1956, page 45.

$$\frac{y_o}{a_o} = \frac{\left(\frac{w}{w_n}\right)^2}{1 - (w/w_n)^2}$$

where,

y_o = the relative motion between the mass and the fixed end of the spring

a_o = the amplitude of motion at the fixed end of the spring

w = frequency of motion at fixed end

w_n = natural frequency of spring mass system

The maximum vibration frequency is 50 Hz at 3 'g' peak acceleration as specified in the dynamic vibration test. The amplitude of motion at 50 Hz and 3 'g' peak acceleration is calculated from the relationship

$$X = a_o \sin wt$$

$$\dot{X} = a_o w \cos wt$$

$$\ddot{X} = -a_o w^2 \sin wt$$

$$3 'g' = a_o w^2$$

$$a_o = \frac{3 'g'}{w^2} = \frac{3 'g'}{(2\pi f)^2} = \frac{3 \times 32.2 \times 12}{4\pi^2 50^2} = 0.01175 \text{ inch}$$

The natural frequency of the system

$$w_m = \sqrt{\frac{k}{M}}$$

where,

k = the spring constant of the support system

$$k = \frac{W}{\delta_2}$$

W = the force acting at the center of gravity of the support system

δ_2 = the deflection at the center of gravity (equation for δ_2 is derived in Appendix F)

The amplification factor is given by

$$AF = \frac{y_o}{\delta_2}$$

where,

$$y_o = a_o \left(\frac{y_o}{a_o} \right)$$

$$\frac{y_o}{a_o} = \frac{(w/w_n)^2}{1 - (w/w_n)^2}$$

3.2.5.2 Amplification Factor for Unit in Horizontal Position

The amplification factor is calculated by first determining the deflections of the system at the center of gravity using the equations developed for load sharing as presented in Appendix F. Using the determined deflections, the natural frequency is calculated and used to calculate the amplification factor with the equations of Section 3.2.5.1.

$$\delta_2 = W \left[\frac{l_1^2 (2l_1 + 3l_2) + 3l_1 l_2 (l_1 + 2l_2)}{6EI} + \frac{2l_1 (2.64)}{EA} + \frac{2(l_{in} + l_2)^2}{64.9 \cdot 10^6} \right] \\ - P \left[\frac{l_1^2 (2l_1 + 3l_2) + 3l_1 (l_1 + 2l_2) (l_2 + l_3 + e \tan \alpha)}{6EI} + \frac{2l_1 (2.64)}{EA} + \frac{2(l_{in} + l_2 + l_3 + e \tan \alpha) (l_{in} + l_2)}{64.9 \cdot 10^6} \right]$$

Calculating each term in the above equation, for a 0.012 inch thick neck tube, (see Section 3.2.4.4.1 for system geometry)

$$x_1 = \frac{l_1^2 (2l_1 + 3l_2) + 3l_1 l_2 (l_1 + 2l_2)}{6EI} \\ = \frac{(2.497)^2 [2(2.497) + 3(4.43)] + 3(2.497)(4.43)[2.497 + 2(4.43)]}{6(25) \cdot 10^6 (0.5582)} \\ = 5.86 \cdot 10^{-6} \text{ in./lb.}$$

$$x_2 = \frac{2l_1 (2.64)}{EA} = \frac{2(2.497)(2.64)}{25 \cdot 10^6 (0.1850)} = 2.85 \cdot 10^{-6} \text{ in./lb.}$$

$$x_3 = \frac{2(l_{in} + l_2)^2}{64.9 \cdot 10^6} = \frac{2(2.78 + 4.43)^2}{64.9 \cdot 10^6} = 1.60 \cdot 10^{-6} \text{ in./lb.}$$

$$x_4 = \frac{l_1^2 (2l_1 + 3l_2) + 3l_1 (l_1 + 2l_2) (l_2 + l_3 + e \tan \alpha)}{6EI} \\ = (2.497)^2 [2(2.497) + 3(4.43)] + 3(2.497)[2.497 + 2(4.43)][4.43 \\ + 4.385 + 3.125 (0.52057)] / 6(25) \cdot 10^6 (0.5582) = 11.97 \cdot 10^{-6} \text{ in./lb.}$$

$$x_5 = x_2$$

$$x_6 = \frac{2(l_{in} + l_2 + l_3 + e \tan \alpha) (l_{in} + l_2)}{64.9 \cdot 10^6} \\ = \frac{2[2.78 + 4.43 + 4.385 + 3.125 (.52057)] (2.78 + 4.43)}{64.9 \cdot 10^6} \\ = 2.94 \cdot 10^{-6} \text{ in./lb.}$$

The deflection with 6 'g' loading applied is

$$\begin{aligned}\delta_2 &= 1734(5.86 + 2.85 + 1.60) 10^{-6} - P(11.97 + 2.85 + 2.94) 10^{-6} \\ &= 17,877 10^{-6} - P(17.76) 10^{-6}\end{aligned}$$

For loading condition I, the spring constant of the three tension rod changes as the vibration cycle goes from positive to negative. For upward and downward loading, the spring constant of the tension rods is as follows:

For upward loading,

$$\delta_2 = 17,877 10^{-6} - 813 (17.76) 10^{-6} = 0.00343 \text{ inch at } 6 \text{ 'g'}$$

For downward loading,

$$\delta_2 = 17,877 10^{-6} - 712(17.76) 10^{-6} = 0.00523 \text{ inch at } 6 \text{ 'g'}$$

The natural frequency is calculated from the following expression

$$w_n = \left[\frac{W/\delta_2}{m} \right]^{1/2} = \left[\frac{W/\delta_2}{W/g} \right]^{1/2} = \left[\frac{g}{\delta_2} \right]^{1/2}$$

Since δ_2 was evaluated under a 6 'g' loading

$$w_n = \left[\frac{6-g}{\delta_2} \right]^{1/2} = \left(\frac{6(32.2)}{0.00343} \right)^{1/2} = 823 \text{ rad/sec.} = 131 \text{ Hz (upward loading)}$$

$$w_n = \left[\frac{6(32.2)(12)}{0.00523} \right]^{1/2} = 667 \text{ rad/sec.} = 106 \text{ Hz (downward loading)}$$

W is the driven frequency of 50 Hz = 314 rad/sec.

$$\frac{w}{w_n} = \frac{314}{823} = 0.381 \text{ (upward loading)}$$

$$\frac{w}{w_n} = \frac{314}{667} = 0.470 \text{ (downward loading)}$$

$$\frac{y_o}{a_o} = \frac{\left(\frac{W}{W_n}\right)^2}{1 - \left(\frac{W}{W_n}\right)^2} = \frac{.1452}{1 - .1452} = .170 \text{ (upward loading)}$$

$$y_o = (.170) (.01175) = .0020$$

$$\frac{y_o}{a_o} = \frac{.221}{1 - .221} = .283 \text{ (downward loading)}$$

$$y_o = (.283) (.01175) = .0033$$

Amplification factor is defined as y_o/δ_2 and is

$$AF = \frac{0.0020}{0.00343/2} = 1.17 \text{ (upward loading)}$$

$$AF = \frac{0.0033}{0.00523/2} = 1.27 \text{ (downward loading)}$$

The amplification factor is expected to be between these two values. The amplification being less than 2 (6 'g' design/3 'g' design) shows that the largest loading condition is produced by the 6 'g' shock and therefore the component design is correct as presented in Section 3.2.4.

The maximum shock level which the unit has to withstand is the following

t_d = nominal duration of
shock = 6 ms

Determine shock response by Figure 5.9, page 117, Shock and Vibration Engineering, Vol. 1, Charles Morrow, Wiley and Sons, 1963.

Fig. 5.9. Shock spectra for a terminal-pulse sawtooth of peak acceleration A and duration t_d .

For loading condition I

$$\begin{aligned} f_n &= 130 \text{ Hz} && \text{upward loading} \\ f_n &= 106 \text{ Hz} && \text{downward loading} \end{aligned}$$

$$\begin{aligned} 2 f_n t_d &= 2 \times 130 \times 6 \times 10^{-3} = 1.56 \text{ cycles} \\ 2 f_n t_d &= 2 \times 106 \times 6 \times 10^{-3} = 1.2 \text{ cycles} \end{aligned}$$

From the Figure the acceleration is

$$\begin{aligned} a &= 1.2 \times 6 \text{ 'g'} = 7.2 \text{ 'g'} && \text{upward loading} \\ a &= 1.1 \times 6 \text{ 'g'} = 6.6 \text{ 'g'} && \text{downward loading} \end{aligned}$$

The maximum amplification factor in shock is 1.2.

3.2.5.3 Amplification Factor for Unit in Vertical Position (Neck Tube Open End Up)

The maximum tensile stress in the neck tube using the method presented in Section 3.2.4.4.2 is

$$\sigma_{\max} = \frac{(3)(289) - 187}{.185} + 1508 = 5184 \text{ psi}$$

$$\sigma = E\epsilon = E \delta/L$$

$$\delta = \frac{\sigma L}{E} = \frac{5184 (2.497)}{25 \times 10^6} = 518 \times 10^{-6} \text{ inch}$$

$$W_n = \left[\frac{3 (32.2) (12)}{518 \cdot 10^{-6}} \right]^{1/2} = 1496 \text{ rad/sec.} = 238 \text{ Hz}$$

$$\frac{W}{W_n} = \frac{314}{1496} = .210$$

$$\frac{y_o}{a_o} = \frac{(.210)^2}{1 - (.210)^2} = .046$$

$$y_o = \frac{3 'g' (32.2) 12}{(314)^2} (.046) = .000541 \text{ inch}$$

$$AF = \frac{y_o}{\delta} = \frac{541 \cdot 10^{-6}}{518 \cdot 10^{-6}} = 1.05$$

3.2.5.4 Amplification Factor for Unit in Vertical Position (Neck Tube Open End Down)

The maximum compressive stress in the neck tube using the method as presented in Section 3.2.4.4.3.1 is

$$\sigma_{\max} = \frac{3 (289) + 629}{.185} - 1508 = 6578 \text{ psi}$$

$$\text{Deflection} = \delta = \frac{\sigma L}{E} = \frac{6578 (2.497)}{25 \cdot 10^6} = 657 \cdot 10^{-6} \text{ inch}$$

$$W_n = \left[\frac{3 (32.2) (12)}{657 \cdot 10^{-6}} \right]^{1/2} = 1332 \text{ rad/sec.} = 212 \text{ Hz}$$

$$\frac{W}{W_n} = \frac{314}{1332} = .236$$

$$\frac{y_o}{a_o} = \frac{(.236)^2}{1 - (.236)^2} = .059$$

$$y_o = \frac{3 'g' (32.2) 12}{(314)^2} (.059) = .000694$$

$$AF = \frac{y_o}{\delta} = \frac{694 \cdot 10^{-6}}{657 \cdot 10^{-6}} = 1.06$$

3.2.6 Enclosure Analysis

This section presents the analysis of the top flange, upper head, cylindrical wall, and bottom head. These components define the HTVIS outer vacuum enclosure.

3.2.6.1 Top Flange

The top flange design is based primarily on limiting the deflection of the flange so that the deflection of the neck tube caused by rotation is small compared to the deflection of the neck tube by the force and moment acting on it.

The rotation of the neck tube due to the deflection of the flange is calculated by means of (Formulas for Stress and Strain, Raymond J. Roark, McGraw Hill, 1954, Table X, Case 10).

$$\text{Max } \theta = \frac{M}{\alpha E t^3} \text{ (at center)}$$

$$\frac{r_o}{a} = \frac{2.52}{3.74} = .674 \quad \alpha = 44$$

$$a = 3.74 \text{ inch}$$

$$r_o = 2.52 \text{ inch}$$

Solve for t

The maximum θ was found for several flange thicknesses. It was found that for 3/8 flange thickness, the rotation of the necktube due to the deflection of the flange is negligible compared to the deflection of the necktube due to the force and moment acting on it.

$$t = .375 \text{ inch}$$

$$\text{Maximum } \theta = \frac{M}{\alpha E t^3} = \frac{7.3 (3) 289}{48 (28 \times 10^6) (.375)^3} = .00088 \text{ rad.}$$

$$E = 28 \times 10^6 \text{ psi} \quad \text{For 304 Stainless Steel at } 200^\circ\text{F}$$

$$\delta = .000088 \times 2.5 = .00022 \text{ inch at bottom of necktube}$$

The rotation δ of the necktube with flange thicknesses less than 3/8 inch were calculated as follows

t	.312 inch	.250 inch	.187 inch
δ	.00038 inch	.00075 inch	.00179 inch

To avoid lowering the natural frequency of the system which would increase the amplification factor in vibration, a 3/8 inch thick flange was selected.

The stresses in the top flange were checked for .375 inch flange thickness.

The loading conditions are:

1. Uniform outside pressure.
2. Moment, unit being in horizontal position.
3. Uniform load along the inner edge of the flange due to inside pressure in the necktube.

1. Uniform Outside Pressure

Roark, Table X, Case 17

$$\begin{aligned} a &= 3.74 \\ b &= 2.52 \\ t &= .375 \end{aligned}$$

Maximum radial stress at the outer edge

$$S_r = \frac{3\omega}{4t^2} \left[a^2 - 2b^2 + \frac{b^4(m-1) - 4b^4(m+1) \ln \frac{a}{b} + a^2 b^2 (m+1)}{a^2(m-1) + b^2(m+1)} \right]$$

$$\omega = \text{Uniform load (lbs./in}^2\text{)} = 2 \text{ atmosphere design} \times 14.7 = 29.4 \text{ lbs./in}^2$$

$$m = \frac{1}{\nu} = \frac{1}{.28} = 3.57 \text{ Reciprocal of Poisson's ratio where Poisson's Ratio } \nu = .28$$

$$S_r = \frac{(3)29.4}{(4)(.375)^2} \left[\frac{3.74^2 - 2(2.52)^2 + 2.52^4(2.57) - 4(2.52^4)(4.57) \ln \frac{3.74}{2.52} + (3.74)^2(2.52)^2(4.57)}{(3.74)^2(2.57) + (2.52)^2(4.57)} \right]$$

$$S_r = 534 \text{ psi}$$

2. Moment - Unit Horizontal Position

Roark, Table X, Case 10

$$\text{Maximum stress } S = \frac{\beta M}{at^2} \text{ at center}$$

$$\frac{r_o}{a} = .673$$

$$\beta = .568$$

$$S = \frac{(.568)(7.3)(3)(289)}{3.74(.375)^2} = 7052 \text{ psi}$$

3. Uniform Load Inner Edge of Flange

Roark, Table X, Case 18

Maximum stress occurs at outer edge where $\frac{a}{b} < 2.4$

$$\frac{a}{b} = \frac{3.74}{2.52} = 1.48 < 2.4$$

$$S_{\text{maximum}} = \frac{3w}{2\pi t^2} \left[1 - \frac{2mb^2 - 2b^2(m+1) \ln \frac{a}{b}}{a^2(m-1) + b^2(m+1)} \right]$$

$$w = 2 \times 14.7 (\pi) (2.52)^2 = 586.2 \text{ lbs.}$$

$$S_{\text{maximum}} = \frac{3 \times 586}{2\pi(.375)^2} \left[1 - \frac{2(3.75)(2.52)^2 - 2(2.52)^2 4.57(.392)}{(3.74)^2(2.57) + (2.57)^2(4.57)} \right] = 1311 \text{ psi}$$

Maximum stress by superposition

$$S_{\text{maximum}} = 534 + 7052 + 1311 = 8897 \text{ psi}$$

$$\text{Safety Factor} = \frac{\text{Yield Strength}}{\text{Max. Applied Stress}} = \frac{33,000}{8,897} = 3.7$$

3.2.6.2 Upper Head

- $R = 2.45$
 $V =$ Vacuum load
 $F =$ Spring Force
 $P =$ Flange Force
 $W =$ Weight of shield plus vacuum load on top flange

Assume the upper head may be treated as a beam with unit width. Including the force P from the flange, the problem becomes statically undeterminate.

By Castigliano's theorem, from Advanced Mechanics of Materials, Seeley and Smith, Wiley, 1957.

$$\delta_p = \int \frac{M}{EI} \frac{\partial M}{\partial P} dx = 0$$

Consider the flange completely stiff in the radial direction $\delta_p = 0$ and value for P .

The moment between $0 < \theta < \frac{\pi}{4}$

$$M = Ma + W R (1 - \cos \theta) - PR \sin \theta$$

$$\frac{\partial M}{\partial P} = -R \sin \theta$$

The moment between $\frac{\pi}{4} < \theta < \frac{\pi}{2}$

$$M = Ma + WR (1 - \cos \theta) - PR \sin \theta + (F + V) R \sin (\theta - 45)$$

$$\frac{\partial M}{\partial P} = -R \sin \theta \quad \pi/4$$

$$\delta P = 0 = \int \frac{M}{EI} \frac{\partial M}{\partial P} R d\theta = \int_0^{\pi/2} [Ma + WR (1 - \cos \theta) - PR \sin \theta] (-R \sin \theta) R d\theta +$$

$$\int_{\pi/4}^{\pi/2} [Ma + WR (1 - \cos \theta) - PR \sin \theta + (F+V)R \sin (\theta - 45)] (-R \sin \theta) R d\theta =$$

$$\int_0^{\pi/4} (-R^2 \sin \theta Ma - WR^3 (1 - \cos \theta) \sin \theta + PR^3 \sin^2 \theta) d\theta + \int_{\pi/4}^{\pi/2} [-R^2 \sin \theta Ma - WR^3 (1 - \cos \theta) \sin \theta + PR^3 \sin^2 \theta - (F+V)R^3 \sin (\theta - 45) \sin \theta] d\theta$$

From Table of Integrals

$$\int -R^2 \sin \theta \, d\theta = R^2 \cos \theta$$

$$\int -WR^3 \sin \theta \, d\theta = WR^3 \cos \theta$$

$$\int -WR^3 \cos \theta \sin \theta \, d\theta = WR^3 \frac{1}{2} \sin^2 \theta$$

$$\int -PR^3 \sin^2 \theta \, d\theta = PR^3 \left[\frac{1}{2} \theta - \frac{1}{4} \sin 2\theta \right]$$

$$\begin{aligned} \int -(F+V) R^3 \sin \left(\theta - \frac{\pi}{4} \right) \sin \theta \, d\theta &= \int -(F+V) R^3 (\sin^2 \theta \cos 45^\circ - \\ &\sin 45^\circ \sin \theta \cos \theta) \, d\theta = -(F+V) R^3 (.7071) \int \sin^2 \theta - \cos \theta \sin \theta \\ &d\theta = -(F+V) R^3 (.7071) \left[\frac{1}{2} \theta - \frac{1}{4} \sin^2 \theta - \frac{1}{2} \sin^2 \theta \right] \end{aligned}$$

$$0 = R^2 Ma [\cos \theta]_0^{\pi/4} + WR^3 [\cos \theta + \frac{1}{2} \sin^2 \theta]_0^{\pi/4} + PR^3 \left[\frac{\theta}{2} - \frac{\sin 2\theta}{4} \right]_0^{\pi/4} + R^2$$

$$Ma [\cos \theta]_{\pi/4}^{\pi/2} + WR^3 [\cos \theta + \frac{1}{2} \sin^2 \theta]_{\pi/4}^{\pi/2} + PR^3 \left[\frac{\theta}{2} - \frac{\sin 2\theta}{4} \right]_{\pi/4}^{\pi/2}$$

$$- (F+V) R^3 (.7071) \left[\frac{\theta}{2} - \frac{\sin 2\theta}{2} \right]_{\pi/4}^{\pi/2} = R^2 Ma (.7071-1)$$

$$+ WR^3 [.7071-1 + \frac{1}{2} (.7071)^2] + PR^3 (\pi/8 - 1/4) + R^2 Ma (-.7071)$$

$$+ WR^3 [-.7071 + \frac{1-.7071^2}{2}] + PR^3 \left[\frac{\pi}{4} - \frac{\pi}{8} + \frac{1}{4} \right] - (F+V) R^3 (.7071)$$

$$\left[\frac{\pi}{4} - \frac{\pi}{8} + \frac{1}{4} - \frac{1}{2} + \left(\frac{.7071}{2} \right)^2 \right]$$

Solve for P

$$P = \frac{Ma + (.5) WR + (.277) (F+V) R}{(.643) R}$$

Calculate Ma from the maximum stress in the flange - Sr maximum
= 8897 psi from Section 3.2.6.1

$$Ma = Sr Z = 8897 \frac{1 (.375)^2}{6} = 208 \text{ in.-lbs./in.}$$

$$WR = (3 \times 289 + 3.74^2 \pi 29.4) 2.45 = 5288 \text{ in.-lbs.}$$

$$\frac{WR}{\text{Perimeter}} = 2\pi (3.74) \frac{5288}{\pi 2 (3.74)} = 225 \text{ in.-lb./in.}$$

$$\frac{V}{\text{Perimeter}} = \frac{29.4 (6.19^2 - 3.74^2) \pi}{2\pi 4.965} = 72 \text{ lbs./in.}$$

$$\frac{F}{\text{Perimeter}} = \frac{2400}{2\pi(4.965)} = 76.9 \text{ lbs./in.}$$

$$P = \frac{188 + (.5) 225 + (.277) (72 + 76.9) 2.450}{.643 (2.450)} = 257 \text{ lbs./in.}$$

$$\begin{aligned} P &= 257 \text{ lbs./in.} \\ W &= 91.8 \text{ lbs./in.} \\ M_a &= 208 \text{ lbs./in.} \\ V+F &= 148.9 \text{ lbs./in.} \\ t &= .250 \text{ inch thick} \end{aligned}$$

Bending stress at the top

$$\sigma_B = \frac{M_a}{Z} = \frac{208}{.0104} = 20,000 \text{ psi}$$

where,

$$Z = \frac{1(.250)^2}{6} = .0104$$

$$SF = \frac{33,000}{20,000} = 1.65$$

Bending stress at the center

$$\begin{aligned} M_c &= -PR \sin 45 + WR (1 - \cos 45) + M_a + -257 (2.450) (.7071) \\ &\quad + 91.8 (2.45) (1 - .7071) + 208 = -171 \text{ in.-lbs./in.} \end{aligned}$$

$$\sigma_B = \frac{M_c}{Z} = \frac{-171}{.0104} = 16,468 \text{ psi}$$

$$SF = \frac{33,000}{16,468} = 2.00$$

Bending stress at the bottom

$$\begin{aligned} M_D &= M_a + WR + (V+F)R \cos 45 - PR = 208 + 225 + 148.9 (2.45) (.7071) \\ &\quad - 257 (2.45) = 61 \text{ in.-lbs./in.} \end{aligned}$$

$$\sigma_D = \frac{61}{.0104} = 5865 \text{ psi}$$

$$SF = \frac{33,000}{5865} = 5.63$$

Checking the shear stresses at the top

$$t = \frac{257}{1 (.250)} = 1028 \text{ psi}$$

3.2.6.3 Cylindrical Shell

The wall thickness of the cylindrical shell was calculated considering the loadings due to - two atmosphere external pressure, weight of the shield, and the hold-down spring force.

$$\begin{aligned} R_i &= 6.101 \text{ inch} \\ R_o &= 6.21 \text{ inch} \\ L &= 7.988 \text{ inch} \\ t &= .109 \text{ inch} \\ D_o &= 12.42 \text{ inch} \end{aligned}$$

Stress due to outside pressure (compression)

$$\sigma_1 = \frac{PR}{2t} = \frac{2 \times 14.7 \times 6.21}{2 (.109)} = 837 \text{ psi}$$

Stresses due to weight and spring force

$$P = W + F + E = 6(289) + 2400 = 4134$$

Cross-sectional area of cylinder,

$$A = (R_o^2 - R_i^2) \pi = (6.21^2 - 6.101^2) \pi = 4.21 \text{ in}^2$$

$$\sigma_{\text{comp}} = \frac{4134}{4.21} = 982 \text{ psi}$$

Total compressive stress

$$\sigma_{T_{\text{comp}}} = 982 + 837 = 1819 \text{ psi}$$

$$\text{Safety Factor based on compressive stress } SF = \frac{33,000}{1819} = 18$$

Checking for buckling while under two atmosphere external pressure. Using Section VIII ASME Boiler and Pressure Vessel Code

$$L = 10.438 + \frac{4.59}{3} = 11.96 \text{ inch}$$

$$T = 150^{\circ}\text{F}$$

$$D_o = 12.42 \text{ inch}$$

Step 1

$$\frac{L}{D_o} = \frac{11.96}{12.42} = .962$$

$$\frac{D_o}{t} = \frac{12.42}{.109} = 113.9$$

Step 2 Using Figure UHA 28.1

$$B = 10,000$$

$$P_{\text{allowable}} = \frac{B}{D_o/t} = \frac{10,000}{113.9} = 87.7 \text{ psi}$$

$$SF = \frac{87.7}{29.4} = 2.98$$

3.2.6.4 Bottom Head

$$R_1 = 6.21$$

$$R_1 = 6.5 \text{ inch} = L_1$$

$$t = .250 \text{ inch}$$

$$r = 1 \text{ inch}$$

Determine stress at the bottom due to 4134 pound load using the procedures and figures presented in "Computation of the Stresses from Local Loads in Spherical Pressure Vessels or Pressure Vessel Head", P. B. Bijloard, Welding Research Council Bulletin 34, 1957.

For a .250 inch thick head, the parameter is

$$s = 1.82 \frac{r}{R} \left(\frac{R}{t} \right)^{1/2} = 1.82 \frac{1}{6.21} \left(\frac{6.21}{.250} \right)^{1/2} = 1.45$$

$$\frac{M_x}{p} = .04 \quad M_x = (.04) 4134 = 165 \text{ in.lbs.}$$

$$\frac{M_y}{p} = .025 \quad M_y = .025 (4134) = 103 \text{ in.lbs.}$$

$$N_x / P/t = -.085 \quad N_x = (-.085) \frac{4134}{.250} = -1405 \text{ lbs.}$$

From reference Figure 6

$$N_y / P/t = -.03 \quad N_y = (-.03) \frac{4134}{.250} = -496 \text{ lbs.}$$

The combined stress,

$$\sigma_x = \frac{M_x}{Z} + \frac{N_x}{A} = \frac{165}{.0104} + \frac{1405}{1(.250)} = 21,485 \text{ psi Tension}$$

where,

$$Z = \frac{1(.250)^2}{6} = .0104 \text{ in}^3$$

$$SF = \frac{33,000}{21,485} = 1.54$$

$$\sigma_y = \frac{M_y}{Z} + \frac{N_y}{A} = \frac{496}{1(.250)} = 11,888 \text{ psi}$$

$$SF = \frac{33,000}{11,888} = 2.78$$

Checking for buckling due to external pressure using Section VIII ASME Code, page 10

$$\frac{L_1}{th} = \frac{6.5}{.250} = 26$$

$$\frac{L_1}{100 th} = \frac{6.50}{25.0} = .26 \quad B = 12,500$$

From Figure UHA 28.1

$$P_a = B / L_1 / th$$

$$P_a = \frac{12,500}{26} = 480 \text{ psi}$$

Assume the total load in the axial direction evenly distributed on the sphere. The axial pressure is $\frac{4134}{\pi (6.5)^2} + 2 (14.7) = 60.6 \text{ psi}$

$$SF = \frac{480}{60.6} = 7.9$$

3.2.7 Rupture Life Analysis

This section presents the calculations to show that the neck tube and tension rods will not fail by stress rupture during the five year service life of the insulation system.

3.2.7.1 Rupture Life of Neck Tube

The rupture stress of Hastelloy-X at 1350°F for five years is 9300 psi as shown on Figure C-8, Appendix C. The thickness of surface oxidation at the hot end of the neck tube was determined to be .0005 inch based on the data shown on Figure C-7, Appendix C. This reduction in thickness yields a neck tube wall with a thickness of .0115 inch.

Vertical Position: The maximum tensile stress in the neck tube under a 1 'g' loading is determined from the stress calculated in Section 3.2.4.4.2 for the 6 'g' loading as follows:

$$\sigma_{\text{tensile}} = \frac{10,035}{6 \times 1.2} + 1508 = 1652 \text{ psi}$$

max.

Since 1652 << 9300 psi the life of the neck tube under this loading condition is over five years.

Vertical Upside Down Position: The maximum compressive stress in the neck tube under a 1 'g' loading is determined from the stress calculated in Section 3.2.4.4.3.1 as follows:

$$\sigma_{\text{compression}} = \frac{289 + 629}{.1850} - 1508 = 3454 \text{ psi}$$

max.

Since 3454 psi << 9300 psi the life of the neck tube under this loading condition is over five years.

Horizontal Position: The maximum shear stress in the neck tube under a 1 'g' loading is determined from the stress calculated in Section 3.2.4.1.1 as follows:

$$\tau_{\text{shear}} = \frac{11,107 \text{ psi}}{6} = 1851 \text{ psi}$$

max.

Since 1851 psi << 9300 psi the life based on maximum shear is over five years.

3.2.7.2 Rupture Life of Tension Rods

The stress rupture life for the Inconel-625 male tension rod material is shown on Figure C-13, Appendix C. The extrapolated rupture stress for five years at 1400°F is 8200 psi.

Vertical Position: The maximum tensile stress in the tension rods under a 1 'g' loading is determined from Section 3.2.4.4.2 and Section 3.2.4.4.3.1 as follows:

$$\begin{aligned}\sigma_{\text{tensile}} &= \frac{127 \text{ pounds}}{6(.0585 \text{ in}^2)} + 7300 \text{ psi} \\ \text{max.} \\ &= 7662 \text{ psi}\end{aligned}$$

Since 7662 psi < 8200 psi the life of the tension rod under this loading condition is over five years.

Vertical Upside Down Position: The maximum tensile stress in this position is equivalent to the tension rod prestress which is a maximum of 7300 psi. The life of the tension rod in this position is therefore over five years.

Horizontal Position: The maximum applied stress in the tension rod under 1 'g' loading is determined from Section 3.2.4.4.1.2:

$$\begin{aligned}\sigma_{\text{tensile}} &= \frac{21,230}{6 (1.2)} = 2949 \text{ psi} \\ \text{max.}\end{aligned}$$

In the horizontal position, however, the stress in the tension rod cancels out the initial stress of 7300 psi, therefore, the maximum stress in the rods under 1 'g' loading is 7300 psi. The life of the rod is over five years since 7300 psi < 8200 psi.

3.2.8 Unit Heat Loss Calculations

The following sections present the calculation of the heat loss contributions of the individual unit components to include neck tube, tension rods, and insulation system.

3.2.8.1 Neck Tube Heat Loss Calculations

The minimum neck tube wall thickness is .012 inch. Allowing 1.5 mil variation over the diameter for manufacturing tolerances the maximum neck tube thickness is .01275 inch.

The heat loss is

$$q_{\text{min}} = k_{\text{av}} A_{\text{min}} \frac{\Delta T}{L} = 119.3 \frac{.1850}{144} \frac{1285 - 150}{2.497} \frac{1}{3.41} = 20.4 \text{ watt}$$

$$q_{\max} = k_{\text{av}} A_{\max} \frac{\Delta T}{L} = 119.3 \frac{.1966}{144} \frac{1285 - 150}{2.497} \frac{1}{3.41} = 21.7 \text{ watt}$$

where,

$$t_{\min} = .012 \text{ inch}$$

$$A_{\min} = .1850 \text{ inch}^2$$

$$t_{\max} = .01275 \text{ inch}$$

$$A_{\max} = .1966 \text{ inch}^2$$

$$k_{\text{av}} = 119.3 \text{ Btu-in./ft.-hr.-}^\circ\text{F} \quad \text{From Figure 64}$$

The mean thermal conductivity shown on Figure 64 was obtained by numerical integration. The curve shown on Figure 64 was obtained by calculating the thermal conductivity for the temperature profile of the neck tube determined in Appendix E.

3.2.8.2 Tension Rod Heat Loss Calculations

The heat loss through the tension rod was calculated for both the test condition and the unit operating condition. The dimensions for the two piece tension rod are as shown

The heat loss of the rod is calculated based on the fact that the heat loss through each element of the rod must be equal and will equal the total heat loss.

$$q_1 = q_2 = q_3 \quad \frac{T_1 - T_0}{R_1} = \frac{T_2 - T_1}{R_2} = \frac{T_3 - T_2}{R_3}$$

where,

$$\frac{T_2 - T_1}{R_2} = \frac{T_2 - T_1}{R_{2,7}} + \frac{T_2 - T_1}{R_{2,6}}$$

FIGURE 64

THERMAL CONDUCTIVITY VARIATION IN THE NECK TUBE
(HASTELLOY X)

$$R_2 = \frac{(R_{2,7}) (R_{2,6})}{(R_{2,7}) + (R_{2,6})}$$

where,

$R_{2,7}$ is the thermal resistance of the female rod (Inconel-718) between T_1 and T_2 .

$R_{2,6}$ is the thermal resistance of the male rod (Inconel-625) between T_1 and T_2 .

$$R_1 (T_2 - T_1) = R_2 (T_1 - T_o)$$

$$R_2 (T_s - T_2) = R_3 (T_2 - T_1)$$

$$R_1 T_2 - R_1 T_1 = R_2 T_1 - R_2 T_o$$

$$R_2 T_s - R_2 T_2 = R_3 T_2 - R_3 T_1$$

$$(R_1 + R_2) T_1 - R_1 T_2 = R_2 T_o - R_3 T_1 + (R_2 + R_3) T_2 = R_2 T_s$$

There are two equations with two unknown T_1 and T_2 . Since the thermal resistances are functions of the temperatures, to solve for T_1 and T_2 an iterative procedure is used. First, assume the intermediate temperatures T_1 and T_2 and calculate R_1 , R_2 , R_3 and solve for T_1 and T_2 . Second, recalculate R_1 , R_2 , R_3 for the temperatures T_1 and T_2 and solve for the temperatures T_1 and T_2 . Repeat this procedure until T_1 and T_2 is obtained.

3.2.8.2.1 Tension Rod Heat Loss Under Test Conditions

Assume the following temperatures:

$$T_o = 110^\circ\text{F} \text{ (known from thermocouple measurements)}$$

$$T_1 = 903^\circ\text{F} \text{ assumed}$$

$$T_2 = 974^\circ\text{F} \text{ assumed}$$

$$T_s = 1285^\circ\text{F} \text{ (bottom temperature of shield under test conditions)}$$

The mean thermal conductivities of Inconel-625 and Inconel-718 materials are obtained from Figures C-9 and C-14 respectively, Appendix C.

$$k_1 = 105.7 \frac{\text{Btu-inch}}{\text{ft.-hr.-}^\circ\text{F}} \text{ at } \frac{110^\circ\text{F} + 903^\circ\text{F}}{2} = 506.5^\circ\text{F} \text{ mean temperature}$$

$$k_{2,7} = 132.2 \frac{\text{Btu-inch}}{\text{ft.-hr.-}^\circ\text{F}} \text{ at } \frac{903^\circ\text{F} + 974^\circ\text{F}}{2} = 938^\circ\text{F} \text{ mean temperature}$$

$$k_{2,6} = 117.4 \frac{\text{Btu-inch}}{\text{ft.-hr.-}^\circ\text{F}} \text{ at } 938.5^\circ\text{F} \text{ mean temperature}$$

$$k_3 = 128.4 \frac{\text{Btu-inch}}{\text{ft.-hr.-}^\circ\text{F}} \text{ at } \frac{974 + 1285^\circ\text{F}}{2} = 1129.5^\circ\text{F} \text{ mean temperature}$$

$$R_1 = \frac{\ell_1}{k_1 A_1} = \frac{0.960 (144)}{(105.7)(.0159)} = 82.2 \frac{\text{hr.-}^\circ\text{F}}{\text{Btu}}$$

$$R_{2,7} = \frac{\ell_2}{k_{2,7} A_1} = \frac{(.375)(144)}{(132.2)(.0159)} = 25.6 \frac{\text{hr.-}^\circ\text{F}}{\text{Btu}}$$

$$R_{2,6} = \frac{\ell_2}{k_{2,6} A_2} = \frac{(.375)(144)}{(117.4)(.0585)} = 7.8 \frac{\text{hr.-}^\circ\text{F}}{\text{Btu}}$$

$$R_2 = \frac{(R_{2,7})(R_{2,6})}{R_{2,7} + R_{2,6}} = \frac{(25.6)(7.8)}{25.6 + 7.8} = 6.0 \frac{\text{hr.-}^\circ\text{F}}{\text{Btu}}$$

$$R_3 = \frac{\ell_3}{k_3 A_3} = \frac{1.284 (144)}{(128.4)(.0585)} = 24.6 \frac{\text{hr.-}^\circ\text{F}}{\text{Btu}}$$

$$88.2 T_1 - 82.2 T_2 = 660 - 24.6 T_1 + 30.6 T_2 = 7710$$

$$T_1 = \left| \begin{array}{r} 660 - 82.2 \\ 7710 + 30.6 \\ 88.2 - 82.2 \\ -24.6 + 30.6 \end{array} \right| = 966^\circ\text{F}$$

$$T_2 = \left| \begin{array}{r} 88.2 - 660 \\ -24.6 + 7710 \\ 88.2 - 82.2 \\ -24.6 + 30.6 \end{array} \right| = 1028^\circ\text{F}$$

The above calculations were repeated with the following temperatures:

$$T_o = 110^\circ\text{F}$$

$$T_1 = 966^\circ\text{F}$$

$$T_2 = 1028^\circ\text{F}$$

$$T_s = 1285^\circ\text{F}$$

The thermal resistances obtained were as follows:

$$R_1 = 80.8 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_{2,7} = 25.0 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_{2,6} = 7.6 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_2 = 5.8 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_3 = 24.3 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

The second calculations for T_1 and T_2 gives $T_1 = 966^\circ\text{F}$ and $T_2 = 1027^\circ\text{F}$ which are the corrected intermediate temperatures.

The heat loss through the rod

$$q_1 = \frac{\Delta T}{R_1} = \frac{966 - 110}{80.8} \left(\frac{1}{3.41} \right) = 3.1 \text{ watt}$$

$$q_2 = \frac{\Delta T}{R_2} = \frac{1027 - 966}{5.8} \left(\frac{1}{3.41} \right) = 3.08 \text{ watt} \sim 3.1 \text{ watt}$$

$$q_3 = \frac{\Delta T}{R_3} = \frac{1285 - 1027}{24.3} \left(\frac{1}{3.41} \right) = 3.1 \text{ watt}$$

$$q_1 = q_2 = q_3 = q = 3.1 \text{ watt per rod}$$

The total heat loss for three tension rods is $3 (3.1) = 9.3$ watts at test conditions.

3.2.8.2.2 Tension Rod Heat Loss Under Operating Conditions

Under operating conditions, the hot end of the rod is at 1430°F , and the cold end is maintained at 50°F .

Assuming the following intermediate temperatures:

$$T_o = 50^\circ\text{F} \text{ (given by specifications)}$$

$$T_1 = 1067^\circ\text{F} \text{ assumed}$$

$$T_2 = 1137^\circ\text{F} \text{ assumed}$$

$$T_s = 1430^\circ\text{F} \text{ (given by specifications)}$$

Computing the mean thermal conductivities:

$$k_1 = 109.5 \text{ Btu-inch/ft.} \cdot \text{hr.} \cdot ^\circ\text{F at } \frac{50 + 1067}{2} = 559^\circ\text{F mean temperature}$$

$$k_{2,7} = 142.8 \text{ Btu-inch/ft.} \cdot \text{hr.} \cdot ^\circ\text{F at } \frac{1067 + 1137}{2} = 1102^\circ\text{F mean temperature}$$

$$k_{2,6} = 128.2 \text{ Btu-inch/ft.} \cdot \text{hr.} \cdot ^\circ\text{F at } \frac{1067 + 1137}{2} = 1102^\circ\text{F mean temperature}$$

$$k_3 = 138.7 \text{ Btu-inch/ft.} \cdot \text{hr.} \cdot ^\circ\text{F at } \frac{1137 + 1430}{2} = 1283^\circ\text{F mean temperature}$$

$$R_1 = 79.4 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_{2,7} = 23.8 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_{2,6} = 7.2 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_2 = 5.5 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$R_3 = 22.8 \text{ hr.} \cdot ^\circ\text{F/Btu}$$

$$84.9T_1 - 79.4 T_2 = 5.5 (50) = 275 - 22.8T_1 - 28.3T_2 = 5.5 (1430) = 7865$$

$$T_1 = \frac{\begin{vmatrix} 275 - 79.4 \\ 7865 + 28.3 \\ 84.9 - 79.4 \\ -22.8 + 28.3 \end{vmatrix}}{\begin{vmatrix} 84.9 - 79.4 \\ -22.8 + 28.3 \end{vmatrix}} = 1067^\circ\text{F}$$

$$T_2 = \frac{\begin{vmatrix} 84.9 + 275 \\ -22.8 + 7865 \\ 84.9 - 79.4 \\ -22.8 + 28.3 \end{vmatrix}}{\begin{vmatrix} 84.9 - 79.4 \\ -22.8 + 28.3 \end{vmatrix}} = 1136^\circ\text{F}$$

The heat loss is

$$q_1 = \frac{\Delta T}{R_1} = \frac{1067 - 50}{79.4} \left(\frac{1}{3.41} \right) = 3.75 \text{ watts}$$

$$q_2 = \frac{\Delta T}{R_2} = \frac{1137 - 1067}{5.5} \left(\frac{1}{3.41} \right) = 3.73 \text{ watts}$$

$$q_3 = \frac{\Delta T}{R_3} = \frac{1430 - 1137}{22.8} \left(\frac{1}{3.41} \right) = 3.76 \text{ watts}$$

The total heat loss for the three tension rods is $3 (3.7) = 11.1$ watts at operating conditions.

3.2.8.3 Heat Loss Calculations Through Insulation

The heat loss through the insulation was calculated for the nickel-copper-aluminum systems and for the copper-aluminum systems considering both test conditions and operating conditions. The calculated heat losses do not include the additional losses which must be included for insulation joints made necessary during installation and for penetrations through the insulation as made by the tension rods. A discussion in this section presents the methods used to estimate the joint and penetration heat losses.

3.2.8.3.1 Insulation Heat Loss for Ni-Cu-Al Insulation at Test Temperature

The heat loss is given by:

$$q_{Ni} = q_{Cu} = q_{Al} = \frac{T_s - T_1}{R_{Ni}} = \frac{T_1 - T_2}{R_{Cu}} = \frac{T_2 - T_e}{R_{Al}}$$

where,

$$R_{Ni} = \frac{L_{Ni}}{k_{Ni} A_{Ni}} \quad R_{Cu} = \frac{L_{Cu}}{k_{Cu} A_{Cu}} \quad R_{Al} = \frac{L_{Al}}{k_{Al} A_{Al}}$$

The mean surface area A_{Ni} , A_{Cu} , and A_{Al} were calculated for the layer thickness shown on the sketch above as per dimensions given by the Drawing on Insulation Assembly D-664057. For the different insulation sections shown on Drawing D-664057, the calculated mean surface areas were as follows:

Section		$A_{Ni},$ Ft ²	$A_{Cu},$ Ft ²	$A_{Al},$ Ft ²
A-B } B-C } C-E }	Top Head	.080 .265 .332	.080 .404 .436	.080 .535 .551
E-F	Cylindrical Portion	.695	.774	.852
F-H } H-I } I-J } J-K } K-L }	Bottom Head Curved Portion	.161 .382 .016 .089 .020	.211 .432 .074 .100 .088	.268 .477 .127 .109 .157
L-N } N-M }	Bottom Disc	.223 .005	.223 .005	.223 .005
TOTAL		2.26	2.82	3.38

Figure 65 was prepared from this data and shows the relationship between insulation thickness and average surface area of the insulation.

FIGURE 65
AVERAGE INSULATION AREA VS INSULATION THICKNESS

The thermal conductivity of the different insulation materials is from Final Report of Research and Development In A Thermal Insulation Study - Phase I, AEC Research and Development Report, Union Carbide Corporation - Linde Division, March 28, 1966, September 27, 1967 - ALO 3632-20.

Ni - Quartz Paper

$$k_{Ni} = (.20) 10^{-6} \frac{T_1^2 - T_2^2}{T_1 - T_2} + 1.23 10^{-13} \frac{T_1^4 - T_2^4}{T_1 - T_2} \text{ Btu/hr.-ft.-}^\circ\text{R}$$

Copper-Quartz Paper

$$k_{Cu} = (.095) 10^{-6} \frac{T_1^2 - T_2^2}{T_1 - T_2} + 0.52 10^{-13} \frac{T_1^4 - T_2^4}{T_1 - T_2} \text{ Btu/hr.-ft.-}^\circ\text{R}$$

Aluminum - 106 Paper

$$k_{Al} = (.053) 10^{-6} \frac{T_1^2 - T_2^2}{T_1 - T_2} + 0.52 10^{-13} \frac{T_1^4 - T_2^4}{T_1 - T_2} \text{ Btu/hr.-ft.-}^\circ\text{R}$$

The method of determining the intermediate temperatures was the same as presented in Section 3.2.8.2. The temperatures were as follows:

$$T_{\text{shield}} = 1285^\circ\text{F}$$

$$T_1 = 1187^\circ\text{F}$$

$$T_2 = 802^\circ\text{F}$$

$$T_{\text{enclosure}} = 110^\circ\text{F}$$

The thermal conductivities of the different insulation layers between the above temperatures are:

$$k_{Ni} = (.20) 10^{-6} \frac{1745^2 - 1647^2}{1745 - 1647} + 1.23 10^{-13} \frac{1745^4 - 1647^4}{1745 - 1647} = 3.08 10^{-3} \text{ Btu/ft.-hr.-}^\circ\text{F}$$

$$k_{Cu} = .095 10^{-6} \frac{1647^2 - 1262^2}{1647 - 1262} + (.52) 10^{-13} \frac{1647^4 - 1262^4}{1647 - 1262} = .927 10^{-3} \text{ Btu/ft.-hr.-}^\circ\text{F}$$

$$k_{Al} = (.053) 10^{-6} \frac{1262^2 - 570^2}{1262 - 570} + (.52) 10^{-13} \frac{1262^4 - 570^4}{1262 - 570} = .279 (10^{-3}) \text{ Btu/ft.-hr.-}^\circ\text{F}$$

The thermal resistances are:

$$R_{Ni} = .422/12 (3.08) 10^{-3} (2.26) = 5.05 \text{ hr.-}^\circ\text{F/Btu}$$

$$R_{Cu} = .625/12 (.927) 10^{-3} (2.82) = 19.92 \text{ hr.}-^{\circ}\text{F/Btu}$$

$$R_{Al} = .406/12 (.279) 10^{-3} (3.38) = 35.87 \text{ hr.}-^{\circ}\text{F/Btu}$$

The heat loss:

$$q_{Ni} = \frac{\Delta T}{R_{Ni}} = \frac{1285 - 1187}{5.05} = 19.3 \text{ Btu/hr.} = 5.6 \text{ watts}$$

$$q_{Cu} = \frac{\Delta T}{R_{Cu}} = \frac{1187 - 802}{19.92} = 19.3 \text{ Btu/inch} = 5.6 \text{ watts}$$

$$q_{Al} = \frac{\Delta T}{R_{Al}} = \frac{802 - 110}{35.87} = 19.3 \text{ Btu/inch} = 5.6 \text{ watts}$$

The calculated heat loss through the insulation is 5.6 watts.

3.2.8.3.2 Insulation Heat Loss for Ni-Cu-Al Insulation at Operating Temperature

The insulation geometry is the same as presented in Section 3.2.8.2.1.

The temperatures are as follows:

$$T_{\text{shield}} = (1285 + 1435)/2 = 1360^{\circ}\text{F}$$

$$\left. \begin{array}{l} T_1 = 1258^{\circ}\text{F} \\ T_2 = 855^{\circ}\text{F} \end{array} \right\} \text{calculated by iteration procedure}$$

$$T_{\text{enclosure}} = 110^{\circ}\text{F}$$

The thermal conductivities of the different insulation layers between the above temperatures are:

$$k_{Ni} = (.20) 10^{-6} \frac{1820^2 - 1719^2}{1820 - 1719} + 1.23 10^{-13} \frac{1820^4 - 1719^4}{1820 - 1719} = 3.43 (10^{-3}) \text{ Btu/ft.}-\text{hr.}-^{\circ}\text{F}$$

$$k_{Cu} = .095 10^{-6} \frac{1719^2 - 1315^2}{1719 - 1315} + (.52) 10^{-13} \frac{1719^4 - 1315^4}{1719 - 1315} = 1.027 (10^{-3}) \text{ Btu/ft.}-\text{hr.}-^{\circ}\text{F}$$

$$k_{Al} = (.053) 10^{-6} \frac{1315^2 - 570^2}{1315 - 570} + (.52) 10^{-13} \frac{1315^4 - 570^4}{1315 - 570} = .301 (10^{-3}) \text{ Btu/ft.}-\text{hr.}-^{\circ}\text{F}$$

The thermal resistances are:

$$R_{Ni} = .422/12 (3.43) (10^3) (2.26) = 4.53 \text{ hr.}-^{\circ}\text{F/Btu}$$

$$R_{Cu} = .625/12 (1.027) 10^3 (2.82) = 17.98 \text{ hr.}-^{\circ}\text{F/Btu}$$

$$R_{Al} = .406/12 (.301) 10^3 (3.38) = 33.25 \text{ hr.}-^{\circ}\text{F/Btu}$$

The heat loss:

$$q_{Ni} = \frac{\Delta T}{R_{Ni}} = \frac{1360 - 1258}{4.53} = 22.4 \text{ Btu/hr.} = 6.5 \text{ watts}$$

$$q_{Cu} = \frac{\Delta T}{R_{Cu}} = \frac{1258 - 855}{17.98} = 22.4 \text{ Btu/hr.} = 6.5 \text{ watts}$$

$$q_{Al} = \frac{\Delta T}{R_{Al}} = \frac{855 - 110}{33.25} = 22.4 \text{ Btu/hr.} = 6.5 \text{ watts}$$

The calculated heat loss through the insulation is 6.5 watts.

3.2.8.3.3 Insulation Heat Loss for Cu-Al Insulation at Test Temperature

For the copper-aluminum insulation system the temperature of the hottest aluminum layers was specified to be 900°F and the relative insulation thickness was computed. The system geometry is as follows:

$$\begin{aligned} T_s &= 1285^\circ\text{F} \\ T_l &= 900^\circ\text{F} \\ T_e &= 110^\circ\text{F} \end{aligned}$$

$$q = \frac{\Delta T_{Cu}}{R_{Cu}} = \frac{\Delta T_{Al}}{R_{Al}} \quad \text{and} \quad R_{Cu} \Delta T_{Al} = \Delta T_{Cu} R_{Al}$$

$$\frac{X_{Cu}}{k_{Cu} A_{Cu}} \Delta T_{Al} = \frac{1.5 - X_{Cu}}{k_{Al} A_{Al}} \Delta T_{Cu}$$

Solving for X_{Cu}

$$X_{Cu} = \frac{\frac{1.5 \Delta T_{Cu}}{k_{Al} A_{Al}}}{\frac{\Delta T_{Al}}{k_{Cu} A_{Cu}} + \frac{\Delta T_{Cu}}{k_{Al} A_{Al}}}$$

The thermal conductivities of the insulation layers are:

Cu - Quartz paper - between 1285°F and 900°F

$$k_{Cu} = (.095) 10^{-6} \frac{1745^2 - 1360^2}{1745 - 1360} + (.52) 10^{-13} \frac{1745^4 - 1360^4}{1745 - 1360} = 1.08 (10^{-3}) \text{ Btu/hr.-ft.-}^\circ\text{F}$$

Al - Quartz paper - between 900°F and 110°F

$$k_{Al} = (.053) 10^{-6} \frac{1360^2 - 570^2}{1360 - 570} + (.52) 10^{-13} \frac{1360^4 - 570^4}{1360 - 570} = (.32) 10^{-13} \text{ Btu/ft.-hr.-}^\circ\text{F}$$

The average surface area of insulation was determined from Figure 65, assume that:

$$X_{Cu} \approx .83 \text{ inch}$$

$$X_{Al} \approx .67 \text{ inch}$$

From Figure 65:

$$A_{Cu} = 2.47 \text{ ft}^2$$

$$A_{Al} = 3.27 \text{ ft}^2$$

$$X_{Cu} = \frac{1.5 \cdot 385}{12(3.27)(.32)(10^{-3})} \bigg/ \frac{790}{12(2.46)(1.08)(10^{-3})} + \frac{385}{12(3.27)(.32)10^{-3}} = .83 \text{ inch}$$

The heat loss is:

$$q_{Cu} = \frac{\Delta T_{Cu}}{R_{Cu}} = \frac{1285 - 900}{.83/12(1.08)10^{-3}(2.47)} = 14.8 \text{ Btu/hr.} = 4.3 \text{ watts}$$

$$q_{Al} = \frac{\Delta T_{Al}}{R_{Al}} = \frac{900 - 110}{(.67)/12(.32)10^{-3}(3.27)} = 14.8 \text{ Btu/hr.} = 4.3 \text{ watts}$$

The calculated heat loss through the insulation is 4.3 watts

3.2.8.3.4 Insulation Heat Loss for Cu-Al Insulation at Operating Temperatures

$$T_{\text{shield}} = 1360^\circ\text{F}$$

$$T_1 = 900^\circ\text{F}$$

$$T_e = 110^\circ\text{F}$$

The thermal conductivities of the insulation layers are:

Copper-Quartz paper between 1360°F and 900°F

$$k_{Cu} = (.095) 10^{-6} \frac{1820^2 - 1360^2}{1820 - 1360} + (.52) 10^{-13} \frac{1820^4 - 1360^4}{1820 - 1360} = 1.15 \cdot 10^{-3} \text{ Btu/hr.-ft.-}^\circ\text{F}$$

Aluminum-Quartz paper between 900°F and 100°F

$$k_{Al} = (.053) 10^{-6} \frac{1360^2 - 570^2}{1360 - 570} + (.52) 10^{-13} \frac{1360^4 - 570^4}{1360 - 570} = .32 \cdot 10^{-3} \text{ Btu/ft.-hr.-}^\circ\text{F}$$

From Figure 65:

$$A_{Cu} = 2.47 \text{ ft}^2 \text{ for } X_{Cu} = .92 \text{ inch}$$

$$A_{Al} = 3.27 \text{ ft}^2 \text{ for } X_{Al} = .58 \text{ inch}$$

$$X_{Cu} = \frac{1.5 \cdot 460}{12(3.27)(.32) 10^{-3}} \bigg/ \frac{790}{12(2.47)(1.15) 10^{-3}} + \frac{460}{12(3.27)(.32) 10^{-3}} = .92 \text{ inch}$$

The heat loss is:

$$q_{Cu} = \frac{\Delta T_{Cu}}{R_{Cu}} = \frac{1360 - 900}{.92/12(2.47)(1.15) 10^{-3}} = 17.0 \text{ Btu/hr.} = 5.0 \text{ watts}$$

$$q_{Al} = \frac{\Delta T_{Al}}{R_{Al}} = \frac{900 - 110}{.58/12(3.27)(.32) 10^{-3}} = 17.1 \text{ Btu/hr.} = 5.0 \text{ watts}$$

The calculated heat loss through the insulation is 5.0 watts.

3.2.8.3.5 Insulation Joint Heat Loss

The effect of number of segment joints on insulation heat loss for Ni-Cu-Al insulation and for Cu-Al insulation is shown on Figure 66 and 67, respectively. These figures were prepared using the data as presented in the Final Report of Research and Development in a Thermal Insulation Study - Phase I Union Carbide Corporation - Linde Division, March 28, 1966 - September 27, 1967, (Appendices Figures B-1, B-2). It is seen on Figure 66 that for about .035 inch gap width the insulation heat loss is 12 watts, while using a 9 segment insulation. For the size of the HTVIS units, the use of a 6 segment design would result in excessive gaps between the segments while attempting to conform to the surface contour. These figures show that for the practical case of 9 segments, it is necessary to multiply the calculated insulation heat loss by at least a factor of two to determine the actual heat loss.

Losses associated with the tension rod penetrators through the insulation have been estimated to be in the order of one watt for each tension rod, for a total of 3 watts additional loss.

FIGURE 66

EFFECT OF SEGMENTS ON INSULATION HEAT LOSS
FOR NICKEL-COPPER-ALUMINUM SYSTEM
(1360°F - 110°F)

FIGURE 67
EFFECT OF SEGMENTS ON INSULATION HEAT LOSS
FOR COPPER-ALUMINUM SYSTEM
(1360°F - 110°F)

3.2.8.3.6 Calculation of System Heat Loss at Test Temperature Which is Equivalent to 45 watts of Operating Temperature

For the purpose of this section, the test temperature is defined as a spider and upper shield temperature at 1285°F and an outer enclosure at 110°F. Operating temperature as determined from test and specifications is defined as an upper shield temperature of 1285°F, a spider temperature of 1385°F and an outer enclosure temperature of 50°F.

Heat Loss Through Neck Tube: The heat loss through the neck tube at operating temperature was calculated in Section 3.2.8.1 to be 21.7 watts.

Heat Loss Through Tension Rods: The heat loss through the tension rods at a 1285°F to 110°F test temperature was calculated to be 9.3 watts in Section 3.2.8.2.1. The heat loss at operating temperatures (1385°F - 50°F) can be determined by multiplying the 9.3 watts by the ratio of temperature gradients.

$$q = 9.3 \frac{(1385 - 50)}{(1285 - 110)} = 10.6 \text{ watts}$$

Heat Loss Through the Insulation: The allowable heat loss through the insulation at operating temperature (1335°F average hot temperature and 50°F cold temperature) can be obtained by subtracting the neck tube heat loss (21.7 watts) and the tension rod heat loss (10.6 watts) from the specified 45 watts. This yields an allowable 12.7 watts for the insulation. The insulation heat loss allowable at test temperature (1285°F - 110°F) is obtained by multiplying this 12.7 watts by the ratio of the test to operating temperature

$$q = 12.7 \frac{(1285 - 110)}{(1335 - 50)} = 11.6 \text{ watts}$$

Test Temperature Heat Loss: The heat loss of the insulation system at test temperature (1285°F - 110°F) to be equivalent to 45 watts at operating temperature is:

Neck tube	=	21.7 watts
Tension rods	=	9.3 watts
Insulation	=	<u>11.6 watts</u>
Total	=	42.6 watts

3.3 UNIT DEVELOPMENT ACTIVITIES

The activities discussed in this section were conducted using actual unit type hardware as differentiated from the previously discussed bench type development activities of Section 3.1. The work included in this section includes the fabrication of a pre-prototype unit, the development of fabrication techniques and tooling, the development demonstration of thermal and dynamic performance, as well as the static demonstration of the mechanical-thermal aspects of the design.

3.3.1 Prototype Unit

The purpose of the prototype unit was to quickly fabricate an insulation system utilizing existing technology developed under Contract AT(30-1)-3321 to provide a test vehicle for the evaluation of the 3M Company produced thermoelectric generators. As this unit was one of the early activities of the program, it preceded most of the bench development and analysis work which was performed for the subsequent development and delivery units. The design and fabrication techniques are only vaguely related to the subsequent units.

3.3.1.1 Prototype Unit Design

This unit was designed so that the residual enclosure heads (with some modification), radiation shield, and inner liner from contract AT(30-1)-3321 could be utilized. The design essentially is a ^{238}U Moly radiation shield supported from the enclosure head by a thin wall neck tube. The neck tube was attached to the radiation shield using ^{238}U Moly bolts and was attached to the enclosure by welding. The neck tube forms the inner vacuum enclosure while the enclosure head forms the outer enclosure.

The radiation shield was insulated with a metallic foil type multi-layer insulation using previously demonstrated techniques. The insulation space including the radiation shield was evacuated and the vacuum was maintained by a chemical getter installed in a package attached to the upper head. The unit design and fabrication details are presented on Drawing No. E-664004.

3.3.1.2 Prototype Unit Fabrication

The prototype unit fabrication was started by assembling the radiation shield to the inner liner with ^{238}U Moly bolts. The bolts were torqued to 25 inch-pounds and a .0253 inch diameter Molybdenum safety wire was installed per Military Standard MS 33540. This assembly was then installed on a fixture shaft for the insulation of the radiation shield. The assembled inner liner and radiation shield with safety wire installed is shown in Figure 68.

The multi-layer insulation was installed by spirally wrapping the cylindrical portion of the radiation shield with the processed insulation materials leaving an adequate extended length so that the insulation material could be folded in to meet the neck tube at one end and folded to the contour of the shield at the other end. The insulation was installed by rotating the radiation shield while feeding on the insulation from rolls. Table 22 presents the insulation composition, applied layers, and layer density.

FIGURE 68

SNAP 21B PROTOTYPE UNIT PRIOR TO INSULATION APPLICATION
(1865-66)

TABLE 22

INSULATION MATERIALS ON SNAP-21B PROTOTYPE

<u>Materials</u>	<u>No. of Layers</u>	<u>Layer/Inch</u>	<u>Outer Dia. Inch</u>
Nickel Foil and Quartz Paper	46	104	9.46
Copper Foil and Quartz Paper	55 55	89	10.70
Aluminum Foil and 106 Paper	52 52	113	11.62
Nickel Foil and Quartz Paper	5 3	---	11.75

The completed cylindrical insulation is shown in Figure 69. An outer protective nickel foil layer is seen in the center of the unit while the quartz paper extends past the edges of nickel foil.

The insulation was cut and applied to the upper head (neck tube end) of the shield and the lower head of the shield as shown in Figure 70 and Figure 71, respectively. The foils of each layer were welded to gether to hold the insulation on the radiation shield. Figure 72 shows the completed insulation application.

The residual enclosure heads were machined so that the overall unit dimension could be met and a manual heliarc girth closure weld could be performed. To perform the unit closure, the insulated radiation shield was inserted into the bottom enclosure head and cylindrical shell. The top head was then positioned on the neck tube by the adjustable rods as shown in Figure 73 and tack welded. The adjustable rods were removed and neck tube was hand Heliarc welded to the top enclosure head. The cylindrical enclosure shell was then aligned on the top enclosure head and the overall unit length was adjusted by spacers inserted in the weld joint. The upper girth weld was then tack welded and hand Heliarc welded. The weld shrinkage of this girth closure was .049 inch in the unit axial direction as anticipated. Table 23 presents the enclosure welding fabrication data for prototype unit.

Following the assembly and welding, the unit was evacuated and leak checked using a Veeco MS-9 leak detector. A leak (4.2×10^{-7} standard cc air/sec.) was found in the center of the bottom head plug. It is felt that this leak was caused by axial porosity in the rod stock used to fabricate the plug. The leak was repaired by two overlapping stringer beads performed with a Heliarc welder. Subsequent leak checking showed the unit leak rate to be 4.4×10^{-9} standard cc air/sec., which is acceptable.

FIGURE 69

SNAP 21B PROTOTYPE - CYLINDRICAL INSULATION INSTALLED
(308-67)

FIGURE 70

SNAP 21B PROTOTYPE - INSALLATION OF UPPER HEAD INSULATION
(306-67)

FIGURE 71

SNAP 21B PROTOTYPE - INSALLATION OF LOWER HEAD INSULATION
(303-67)

FIGURE 72
SNAP 21B PROTOTYPE - COMPLETED INSULATION APPLICATION
(687-67)

FIGURE 73
SNAP 21B PROTOTYPE - ALIGNMENT FIXTURE FOR NECK TUBE WELD
(686-67)

TABLE 23

FABRICATION DATA SNAP-21B PROTOTYPE

Enclosure Welding and Leak Rate Check
(Manual Heliarc with 25 cfh Argon Shielding Gas)

Weld No.	Parts Welded	Filler Mat'l		Weld Type Preparation	No. Passes	Volts		Amps		Travel Speed IPM	Leak Rate Std. cc/sec. Air-Remarks
		Type	Size			Min.	Max.	Min.	Max.		
1	Plug-(A664019) to bottom head-(C-664018)	308SS	1/16	.093 gap and backup	3 (1)	11.5	12.5	114	126	---	After making welds 1 and 2 Leak rate less than 4.2×10^{-11} cc air/sec.
		"	3/32		(2)	11.5	12.5	118	126	---	
		"	3/32		(3)	11.5	12.5	108	114	---	
2	Bottom head-(C664018) to shell-(C664017)	308SS	1/16	.093 gap and backup	2 (1)	9.5	11.0	125	128	6	
		"	3/32		(2)	10.5	11.5	138	141	6	
										Positioner	
3	Inner liner PD-37-1250 (neck tube) to top head (C-664016)	None	---	Edge	(1)	9.0	10.0	81	90	7-8 Est.	After making welds 3 and 4
											After three helium leak checks, tests confirmed the presence of a leak approx. on dead center of plug-(A-664019), leak rate 4.212×10^{-7} cc air/sec.
4	Top head-(C-664016) to shell-(C-664017)	308SS	1/16	.120 gap and backup	2 (1)	11.5	12.5	123	126	5	
		"	1/16		(2)	12.0	12.5	135	138	5	
										Positioner	
5	Seal leak found in plug-(A-664019)	308SS	1/16	None Overlapping Stringer beads	2	---	---	---	---	---	After making weld 5
											Leak rate of complete enclosure was less than 4.388×10^{-9} cc air/sec.

The top works package which includes the getter package and seal-off valve was preassembled and leak tested. The preassembled getter package and evacuation valve assembly was silver brazed to the 3/8 inch O.D. tube connecting the unit top head after installing a 3M supplied hold down ring on the upper head. Figure 74 shows the installed hold down ring and top works.

The top works assembly contained 9.3 grams of getter packaged in an evacuated glass capsule plus 3.0 grams of a hydrocarbon getter isolated from the glass getter tube by processed 106 paper. The top works leak rate prior to brazing to the unit was checked and found to be less than 4.38×10^{-11} standard cc air/sec. A complete leak check of the unit after assembly of all components was performed, and the leak rate was found to be 6.26×10^{-10} standard cc air/sec. The unit was sealed-off following the conditioning and thermal tests described in Section 3.3.1.3.

3.3.1.3 Prototype Unit Conditioning and Thermal Test

Test No. 1

Following the leak check, the unit was instrumented for conditioning at 1550°F and a thermal performance test at 1285°F (both temperatures measured at the neck tube hot end). Two 3/8 inch O.D. x 4 inch long cartridge heaters were installed in the 3M supplied stainless steel heater block. Heater No. 1 (Watlow - GA4D-25-5, 250 watts, 115 volts) was supplied by 3M Company for this test and was the main heater. Heater No. 2 (Watlow - GA4D-31-5, 250 watts, 115 volts) was a residual heater from the previous contract and was used as a reserve heater.

Two chromel-alumel thermocouples were welded to the edge of the heater block 180° apart, to be opposite the bottom end of the neck tube. It was felt that it was not good practice to attempt to join a thermocouple to the lower portion of the thin wall neck tube because of the potential for a leak. The thermocouples connected to the heater block, which has good thermal contact with the bottom portion of the neck tube, will give an accurate hot end neck tube temperature. A chromel-alumel thermocouple was silver brazed to the bottom of the 3M supplied heater using a high temperature silver braze good for approximately 1600°F. The heater block with heaters was installed in the unit and bolted to the inner liner.

The neck tube volume above the heater block was filled with one inch thick disks of Min-K 2000 insulation with the heater wires and thermocouple wires passing through the insulation. Voids around the wires and the edge of the insulation disk were filled with powdered Min-K 2000 which was tightly packed in place. A stainless steel cover plate was installed over the Min-K insulation to reduce convection. This cover was sealed to the unit with a flat rubber gasket. Following the unit assembly, Heater No. 1 with ceramic beads on the lead wires was wired through a wattmeter, recording ammeter, Variac, and constant voltage power supply. Chromel-alumel thermocouples were installed in the following locations on the outside of the unit: cover plate, upper unit head,

FIGURE 74

SNAP 21B PROTOTYPE - HOLD DOWN RING AND TOP WORKS INSTALLED
(681-67)

upper cylindrical enclosure, lower cylindrical enclosure, enclosure, center of bottom head. All thermocouples were connected to a temperature recorder. Power was supplied to the 3M heater as shown on Figure 75. The unit hot end neck tube temperature versus time is also plotted on Figure 75. After 130 hours of operation, a maximum temperature of 1435°F was achieved. Continued power input did not yield an increase in unit temperature.

After 144 hours under power, the 3M supplied heater resistance, lead to lead, was 60Ω while the lead to case resistance was 10Ω to 70Ω, showing a short to ground. The GA4D-25-5 heater failed after 190 hours of operation. The reserve heater was then powered at 100 watts; however, this heater failed in less than 20 hours. Actually, the GA4D-25-5 heater start of failure was apparent when the maximum hot end neck tube temperature was reached and a further temperature increase could not be achieved.

Following the heater failures, the neck tube insulation and the heater block was removed. During removal it was noted that the heater lead wires were separated from the heaters at the point where the leads enter the heater. The wires were completely burned through, and the ceramic beads were fused. The heaters were very tight in the heater block and had to be pressed out for removal.

In an attempt to determine why the 3/8 inch diameter heaters failed, a test was performed whereby one Watlow GA4D-25-5 and one Watlow GA4D-31-5 were placed in a furnace with the lead wires protruding from the furnace. The furnace was heated to 1550°F and maintained at temperature for 141 hours. During this test, the heaters were not powered. The heat resistances were measured both during and after the test. This test showed that while at temperature, the lead to case resistance is decreased; however, the resistance still remains high in comparison to the lead to lead resistance. The heaters used in the prototype unit test must have been considerably higher in temperature than 1550°F to burn out the lead wires and fuse the ceramic beads. The thermocouple attached to the bottom of the 3M supplied heater, however, never indicated more than 50°F higher than the hot end neck tube temperature.

Test No. 2

For this test, the heater block was machined to accept two 5/8 inch diameter by 4 inch long heaters while still maintaining the 3/8 inch diameter holes for potential future use. Two Watlow LA411 heaters (5/8 inch O.D. x 4 inch long - 250 watts, 115 volts) were placed in the heater block. The heater lead wires were connected in parallel 1 inch above the heater block to reduce the wire heat loss of the unit. The neck tube insulation (Min-K 2000) and the cover plate was installed as in test No. 1. The neck tube insulation was evacuated to approximately 20 torr and backfilled with argon twice.

An isolation transformer was added to the power circuit ahead of the constant voltage transformer. Power was supplied to the parallel connected heaters as shown on Figure 76. The unit hot end neck tube temperature versus time is also plotted on Figure 76. The total operating time of this test was 72 hours. After 65 hours, the power was reduced in an attempt to run

a thermal performance test; however, the parallel heater resistance started to decrease, causing an increase in current and a decrease in voltage to maintain a constant power input. After 72 hours, the current required was 4.88 amps to maintain 34 watts. This high current requirement clearly indicated a heater failure and therefore the test was discontinued. After the heaters were removed after run No. 2, the resistances were measured, and it was found that only one heater had failed; however, due to the internal parallel connection to reduce heat loss, this failure caused a termination of the test.

Test No. 3

Because of the previous heater failures, special heaters good for a 1900°F operating temperature were purchased from the Rama Industrial Heater Company. Four heaters were used in this test, two each - 3/8 inch diameter x 4 inches long - 500 watts - 240 volts, Model No. R-1194, and two each - 5/8 inch diameter x 4 inches long - 1000 watts - 240 volts - Model No. R1070. These four heaters were installed in the heater block utilizing the asbestos lead wire insulation as supplied. All eight heater wires protruded through the Min-K 2000 neck tube insulation and were connected in parallel outside of the unit. The electrical instrumentation used was the same as for Run No. 2. The neck tube insulation was evacuated and argon backfilled prior to power up.

To preclude heater failure, the power input was limited to 70 watts maximum during the entire test; also power increases were made in small increments as shown on Figure 77. In the event of heater failure, it was decided to run the thermal performance test at 1285°F prior to conditioning at 1550°F as the unit has previously been at 1435°F during test No. 1. The hot end neck tube temperature versus time for the entire test to include the thermal test and conditioning is shown on Figure 77.

It required a steady-state power input of 42.88 watts to maintain the unit at 1285°F. To this input power, the following subtractions were made to determine the unit heat loss: neck tube insulation - 4.66 watts; heater wires and insulation - 6.42 watts; and thermocouple wires and insulation - .74 watt. This subtraction yields a total unit heat loss of 31.06 watts (see Appendix H). During the thermal test, the unit was vacuum pumped and the pressure was 1.4 microns. The cold end neck tube temperature was 135°F while the upper head temperature at the girth weld was 115°F. The lower enclosure temperature at the bottom girth weld was 100°F while the temperature at the center of the bottom enclosure head was 95°F.

Following the thermal performance test, the power was increased (see Figure 77) to bring the unit to 1550°F for conditioning of the insulation. The uncorrected power input at 1548°F was 60.5 watts including all subtractable losses. The insulation pressure was maintained at 5.5 microns while vacuum pumping. In addition, the enclosure was heated with a blanket type heater to promote conditioning. At 1548°F hot end neck tube temperature, the following enclosure temperatures were measured: cold end neck tube - 230°F, enclosure at upper girth weld - 240°F, enclosure at lower girth weld - 200°F, center of bottom enclosure head 170°F.

After 24 hours at 1548°F, the power was turned off and the unit was allowed to cool to 1215°F before removing the neck tube insulation for a rapid cooldown. For this temperature range, it was found that the radiation shield cooled at a rate of 11.5°F/hr. The apparent specific heat of the radiation shield and heater block was determined in the following manner.

Consider that the unit heat loss at 1285°F must be equal to the release of stored heat. The heat loss at 1285°F was determined to be 42.88 watts, while the release of stored heat is given by the relationship; stored heat = (mass) (specific heat) (change in temperature). Therefore, with a radiation shield weight of 225 pounds plus a 13.5 pound heater block, the specific heat is:

$$\text{Specific heat} = \frac{42.88 \text{ watts} \times 3.41 \text{ Btu/hr.-watt}}{238.5 \text{ pounds} \times 11.5^\circ\text{F/hr.}}$$

$$C_p = .0532 \frac{\text{Btu}}{\text{lb.-}^\circ\text{F}}$$

It is interesting to note that on all three thermal tests during unit heat-up, Figures 75, 76, and 77 what appears to be a radiation shield phase change occurs in the temperature region 900°F to 1100°F as the rate of temperature rise increases for constant power input. This phenomenon is most dramatically shown on Figure 77.

During test No. 3, the unit was valved off at two constant temperatures to determine the unit pressure rise rate and thus the unit combined offgassing and leak rate. Figure 78 shows the two pressure rise curves. The initial portion of the curve from time zero to approximately 40 minutes is the time required for the unit to reach an equilibrium pressure after the vacuum pump is valved off. Note that the 1285°F pressure rise was performed before conditioning at 1548°F. The pressure rise rate after conditioning would be less. The offgassing plus leak rate can be calculated from the relationship: offgas rate = volume x pressure change/time period. With the prototype unit volume of approximately .55 ft³, the offgassing rate at 1285°F would be: offgassing rate at 1285°F = .55 ft³ x $\frac{28.32 \mu}{\text{ft}^3} \times \frac{.1 \text{ micron}}{\text{hr.}}$ = 1.42 μ-l/hr. while the offgassing rate at 1548°F would be: offgassing rate at 1548°F = .55 ft³ x $\frac{28.32 \mu}{\text{ft}^3} \times .55 \mu/\text{hr.}$ = 8.55 μ-l/hr.

For this prototype unit based on the conductance of the getter retainer, getter pumping speed, and getter capacity, the allowable pressure rise rate for a one year unit life was calculated to be 5.4 microns/hr. The actual pressure rise rate is much lower than the calculated maximum which should allow a unit life longer than one year design life.

Following the thermal test and unit conditioning, after cooling, the unit was connected to a Veeco MS-9 leak detector and evacuation was continued through the leak detector. The unit pressure at this time was

less than 1×10^{-4} torr as read on the Hastings vacuum gauge. All the vacuum piping and the upper works of the unit were leak checked by spraying helium on the components. No indication of leak was noted during this spray type leak check.

To actuate the getter, the metal getter enclosure tube was pinched. The getter actuation was noted by a sharp cracking sound when the glass getter capsule was ruptured. After actuation, helium was immediately sprayed on the metal getter enclosure tube to be certain that a leak was not produced during the pinching operation. No indication of leak was noted on the leak detector.

The unit was then enclosed in a polyethylene bag for a complete system leak check prior to seal-off. The complete unit leak rate was determined to be 5.6×10^{-10} standard cc air/sec. This compares to a previous measured leak rate of the complete unit before thermal tests of 6.26×10^{-10} standard cc air/sec. showing that heating the unit to 1550°F did not produce any leakage.

Following the leak check, the evacuation valve was closed and the unit pressure was monitored for one hour. No pressure rise was observed during this settle-out period. The 3/8 inch diameter copper tube outboard of the evacuation valve was then pinched off and heat was applied to the presoldered tube to provide the final seal. The vacuum in the copper tube outboard to the pinch-off was released and the tube was cut to the desired length. The completed unit is shown on Figure 79.

3.3.1.4 Prototype Unit Shipping Container

A shipping container for transporting the prototype unit was designed (Drawing C-664033), and one container was fabricated. The container directly supports the nuclear radiation shield through a solid neck tube plug which is bolted to the radiation shield and the frame of the shipping container. When installed, the unit, the unit is completely enclosed in the container with plywood sheet bolted to the container framework. Figure 80 shows the prototype unit in the shipping container.

The allowable input 'g' loading which the HTVIS prototype unit can be subjected to during handling and shipping was calculated for the unit being in the horizontal, vertical, and vertical upside-down positions. The allowable input 'g' loading to the HTVIS prototype unit during shipping was also calculated when the shield was supported through a support plug inside the neck tube. In this case, the neck tube supports the enclosure only. The results of the calculations are summarized as follows:

FIGURE 79
COMPLETED SNAP 21B PROTOTYPE UNIT
(778-67)

FIGURE 80

SNAP 21B PROTOTYPE UNIT IN SHIPPING CONTAINER
(782-67)

<u>Position of Unit During Shipping</u>	(Not in Shipping Container) Allowable Input 'g' Loading for 1.5 Safety Factor When Neck Tube Supports <u>Shield</u>	(In Shipping Container) Allowable Input 'g' Loading for 1.5 Safety Factor When Neck Tube Supports <u>Enclosure</u>
Horizontal	2.3	4.4
Vertical	24.6	33.7
Vertical Upside Down	11.6	70.9

3.3.2 Development Units

During the program effort, four development SNAP 21-B insulation systems were fabricated and evaluated prior to the delivery unit production. The development units were designated B10-D1 through B10-D4. The purpose of the development units was to define fabrication methods, determine tooling requirements, establish quality control procedures, qualify vendors, and determine thermal and mechanical performance of the insulation systems. Table 24 summarizes the results of the four development units in the areas of thermal and dynamic performance. The unit heat loss was calculated using subtractibles (heat loss caused by method of test) calculated using both one dimensional and two dimensional heat transfer analysis. The one dimensional analysis was performed similar to that presented in Appendix H while the method of the two dimensional analysis is presented in Appendix I. The following sections present a discussion of each particular unit development, fabrication and testing.

3.3.2.1 Development Unit Design

The design of the development units is based on the analysis work presented in Section 3.2. The metallic foil multi-layer insulated radiation shield is supported by a thin wall neck tube at one end and three tension rods at the other end. To overcome the excessive creep characteristics of the U₈ Moly radiation shield material at operating temperature, the radiation shield was attached to the neck tube and the tension rod connector (spider) by a method called "cold friction--hot interference support concept". Using this concept (with the unit at ambient temperature) U₈ Moly bolts are utilized to support the shield in the axial direction (yield strength of U₈ Moly material at room temperature is 115,000 to 140,000 psi). To support the shield in the radial direction, the U₈ Moly bolts are pretensioned to create a friction force between the inner liner and the shield (top and the hot end connector and the shield (bottom) sufficiently large to support the radial loads with the unit in the horizontal position.

At operating temperature, the U₈ Moly bolts lose the pretension as a result of Molybdenum washers used under the bolt heads. The thermal expansion of the Molybdenum washers is approximately one-third that of the U₈ Moly causing a loss of the pretension as the unit is heated to operating temperature. By allowing the pretension to be relieved with the unit at operating temperature, the bolts will not creep and therefore will be pretensioned when the unit is cooled to ambient temperature.

TABLE 24

SUMMARY OF THERMAL AND DYNAMIC PERFORMANCE
OF DEVELOPMENT HTVIS UNITS

<u>Unit Designation</u>	<u>Heat Loss By Two Dimensional Analysis (Watts)</u>	<u>Heat Loss By One Dimensional Analysis (Watts)</u>	<u>Vibration Test at 3 'g'</u>	<u>Shock Test at 6 'g'</u>	<u>Comments</u>
B10-D1	49.4	46.3	Passed	Passed	Shock tested to 12 'g'. Dynamic test to failure at 4.5 'g'.
B10-D2	47.7	52.8	Passed	Passed	Vibration tested at ambient temperature prior to operating temperature test which were performed after unit B10-D4 tests.
D10-D3	47.0	52.2	Passed	Passed	
D10-D4	42.9	48.7	Failed	Not Conducted	The unit failed during vibration testing. Evidence strongly indicated failure caused by malfunctioning test machine.

While at operating temperature, the radiation shield is supported in the axial direction under 1 'g' loading by pretension in the three tension rods. Under 6 'g' dynamic loading the tension rods and the inner liner share the radiation shield load as the U₈ Moly bolts upon slight vertical movement of the shield will start to support some load. Since the duration of the dynamic loads is short, the creep in the U₈ Moly bolts is negligible.

To support the radiation shield in the radial direction while the unit is at operating temperature, a shoulder is provided between the inner liner (top) and the hot end connection (bottom) and the radiation shield with a size to size or slight interference fit. When the unit is at ambient temperature, there is a slight gap between the mating shoulders. This gap closes during heat-up because of the difference in thermal expansion coefficients of the Hastelloy-X (inner liner and hot end connector) and the U₈ Moly radiation shield. A graph showing the changes in gap dimensions between the mating shoulders of the Hastelloy-X inner liner and hot end connector and the U₈ Moly radiation shield is presented in Figure 81.

The insulated shield is contained within an enclosure shell which provides the cold attachment for the tension rod and neck tube support elements. In addition, the enclosure shell which is formed from an upper and lower enclosure head with a girth weld, provides the outer vacuum barrier. The inner vacuum barrier is provided by the neck tube. The vacuum necessary for optimum insulation performance is maintained with chemical getters which getter the offgassing gas load and the inleakage gas load (except argon). The getter is installed in the bottom enclosure head in the gas porous volume through the unit seal-off apparatus. Installation is after the unit is conditioned and is performed just prior to the final unit seal-off which employs a temporary gold O-ring seal backed up by a welded seal-off.

All the development units were equipped with a thermocouple type vacuum gauge to monitor the performance during thermal and dynamic testing.

3.3.2.2 Development Unit B10-D1

3.3.2.2.1 Unit Fabrication

Upon receipt of the 3M supplied unit, components which included: radiation shield (PD-37-4007), inner liner (PD-37-4017), spider (PD-37-4108), washer-spider support (PD-37-4120), washer-shield mounting bolt (PD-37-4121), bolt-spider support (PD-37-4107), bolt-shield mounting (PD-37-4003), and support rod-male end (C-664039), a quality control inspection of critical dimensions on the above items was performed. The as-inspected dimensions were logged on prints of the individual components for permanent record. The inner liner diametrical fit ranged from .0008 inch interference to .0012 inch clearance and the spider-radiation shield fit was determined to range from .006 inch to .002 inch interference on the mating diameters which is acceptable. The ball on the tension rod was lapped into the socket in the spider to minimize any chance for deflection in this connection. After lapping, approximately 80% of the ball and socket surface area was in contact.

FIGURE 81

The first step in the assembly of the unit components was to install the inner liner in the radiation shield. For this operation, the radiation shield was cleaned with isopropyl alcohol followed by deionized water. Particular care was taken to be sure that the tapped hole threads were cleaned. The inner liner bolts were threaded into the shield before assembly to insure that there would be no seizures. For assembly, the radiation shield was oriented in an upright position with the base resting on a wood platform. Because of the slight interference fit, the inner liner was filled with liquid nitrogen. This temperature reduction provided sufficient shrinkage to allow proper alignment of the flange bolt holes. The liquid nitrogen was removed from the inner liner and the components were allowed to come to ambient temperature before proceeding with the assembly.

The eight molybdenum washers were located in the inner liner flange and the U₈ Moly bolts were installed. The bolts were torqued to the specified 38 in.-lb. and a molybdenum safety wire was installed per MIL-STD 33540 (Double Twist Method) thus completing the installation of the inner liner to the radiation shield.

The unit holding shaft with adaptor was bolted to the inside of the inner liner after the correct alignment was determined by use of an alignment pin in the adaptor which aligns on the hole in the inner liner. The shaft was then assembled into the unit wrapping stand and the radiation shield was placed in a horizontal position. The assembly fixture was then installed on the shaft around the radiation shield. The purpose of this fixture is to set the angular alignment of the spider on the radiation shield with a reference to the pin hole in the emitter plate base of the inner liner. With this known angular relationship the lower enclosure head can also be aligned in the proper location to allow the tension rods to be in plane of the unit axis.

The radiation shield (lower end) and the spider were cleaned with isopropyl alcohol and distilled water just prior to assembly. Again, because of the interference fit between the spider and the radiation shield, it was necessary to cool the spider to accomplish the required shrinkage for a fit. The spider was first slow cooled in saturated nitrogen vapor in a Dewar and then slowly submerged in liquid nitrogen. Fast cooling was avoided because of concern over the sprayed molybdenum coating with a thermal expansion coefficient approximately 1/3 that of the Hastelloy-X spider material. No breaking loose of the molybdenum coating was observed during the cooling of the spider. The spider at liquid nitrogen temperature was removed from the Dewar and installed on the radiation shield. During handling, the spider was purged with helium gas to prevent an accumulation of condensation on the mating surfaces. The angular alignment between the spider and radiation shield was set with the use of two alignment pins projecting from the assembly fixture which mated with the alignment holes in the spider. The spider and radiation shield were allowed to return to ambient temperature before installing the spider holding bolt. The molybdenum spider bolt washer was installed on the spider and the U₈ Moly spider bolt was threaded into the radiation shield. The spider bolt was torqued to the specified 60 ft.-lb. torque and a double molybdenum safety wire anchored the bolt to the spider.

Following the installation of the spider on the radiation shield, the assembly fixture was removed from the shaft and a tension rod positioning fixture was installed. The ball on the tension rod and the socket in the spider was coated with Molykote Type Z dry lubricant powder to prevent cold welding of these components with the unit at temperature in a vacuum. The tension rods were installed in the spider as lapped and held in the proper angular orientation by the tension rod positioning fixture. The tension rod anti-rotation clips were slightly modified and installed in the spider through the drilled hole in the rod ball.

Insulation Application

At the completion of assembly of 3M supplied components, two layers of processed quartz cloth were installed on the unit to completely cover the radiation shield, spider, outside of inner liner, and tension rods. This quartz cloth will prevent the first nickel foil of the multi-layer insulation system from contacting the U₈ Moly shield resulting in an incompatibility.

Following the installation of the cloth layers, wrapping of the nickel, copper, and aluminum layers were accomplished using a Linde proprietary insulation technique. A total of 165 insulation layers was applied to the unit. The layer composition, thickness, and layer density is presented in Table 25.

TABLE 25

Insulation Composition Unit B10-D1

<u>Number of Layers</u>	<u>Layer Composition</u>	<u>Total Thickness (Inch)</u>	<u>Layers Per Inch</u>
2	Quartz Cloth		
45	Nickel Foil		
	Quartz Paper	.422	106
60	Copper Foil		
	Quartz Paper	.625	96
60	Aluminum Foil		
	106 Paper	.406	148

Channels were provided in the outer insulation layers in the area of the tension rod protrusion to provide space for the tension rod receptacles which are welded to the lower enclosure head. Upon completion of the insulation application, two layers of nickel foil were applied over the insulation to provide protection during the unit closure. Figure 82 shows the completely insulated unit looking at the inner liner end of the unit.

FIGURE 82

INSTALLED INSULATION UNIT B10-DL1
(1585-67)

Unit Closure

The unit enclosure heads (top head C-664035, bottom head C-664036) were inspected by the Linde Quality Control inspector upon receipt from Phoenix Products Company. The actual dimensions were recorded on prints of the head drawings for a permanent inspection record. Following the inspection, each of the heads were helium leak checked with a Veeco MS-9 leak detector determining that the leakage was acceptable.

The enclosure support rod receptacles (3) were then aligned and tack welded to the bottom head using the Receptacle Welding Fixture (664063). After the tack welding the receptacles were manually welded to the head. For this unit which did not use a getter, a circular stainless steel disk was edge welded to the bottom head to seal the hole that is provided for the seal-off device used on subsequent units. Following the welding, the bottom head was again leak checked to determine that there was acceptable leakage in the internally welded receptacle weld joints.

One strain gauge (type SR-4) was adhered to the long side of each receptacle to measure the axial strain in the receptacle as described.

The previously leak checked top head was cleaned with isopropanol and installed over the unit shaft to mate with the top edge of the inner liner. The head was aligned on and tack welded to the inner liner using the Tension Rod Alignment Fixture (E-664061). Following the tack welding, the alignment fixture was partially disassembled to provide the required clearance to make the semi-automatic neck tube edge weld. This weld was accomplished by rotating the unit in the assembly fixture while welding with a hand held heliarc torch. The weld parameters recorded for this neck tube edge weld were determined during the work of Section 3.1.5.2 and were as follows: 68-70 amps, 9-11 volts, 10 IPM, 25 cfh argon, no filler wire used.

Following the inner liner edge weld, the assembly fixture was reassembled for installation of the bottom head on the unit. The bottom head was aligned as shown in Figure 83. Pins inserted through the alignment fixture bars into the receptacle provide the angular line up of the receptacle to the spherical tension rod seat of the spider so that the tension rod was located in the plane of the unit axis. The length of the unit is not adjustable as the girth weld joint is designed to have no gap. The correct length of the unit is provided by having the length of the top and bottom head within dimensional tolerance.

After the head was aligned, the female portion of the tension rods (Linde supplied) were threaded on to the male tension rods (3M supplied) in the unit. Once it was determined that the rods could be assembled, the bottom head was tack welded to the top head using nine tacks approximately 3/8 inch long. The unit was oriented to the horizontal position in the assembly fixture and moved to the welding area to perform the automatic girth weld. Prior to welding the unit, several automatic welds were made on 6 inch O.D. stainless steel pipe to check out the automatic welding machine and set the desired weld parameters. The girth weld as determined from the work of Section 3.1.5.1 was made in two passes with the following parameters recorded:

FIGURE 83
ALIGNMENT OF BOTTOM HEAD UNIT B10-D1
(1626-67)

<u>Pass</u>	<u>Amps</u>	<u>Volts</u>	<u>Wire Feed IPM</u>	<u>Travel IPM</u>	<u>Shield Gas cfh</u>
1	288-290	11.5-13.5	80	15	25 argon 75 helium
2	292-296	15.0-15.5	100	15	25 argon 75 helium

The filler wire was .045 inch diameter, 308 ELC. The first pass filled the weld joint to approximately .020 under flush. The second pass provided a slight crown on the weld joint which was smaller than the outside diameter of the unit.

The female tension rods with the spherical washer and a .100 inch thick adjusting washer were threaded on to the respective numbered male rods and sequentially torqued to 40 in.-lb. to insure complete seating of the washers. Measurements were then taken to determine the required washer thickness to provide a 2.939 inch long tension rod assembly. It was determined that the following washer thicknesses were required: Rod No. 1 = .053 inch, Rod No. 2 = .060 inch, Rod No. 3 = .067 inch. These washers were ground and installed in place of the .100 inch thick washers used to determine the required thickness. In addition, upon final assembly, the female rods were insulated with quartz cloth material to prevent rod contact with the insulation foils, and the spherical washer seat and ball were coated with Molykote Type Z powder to prevent any cold welding.

Because of dimensional deviations on the spider (distance from centerline to center of ball socket) and on the overall length of the inner liner -- radiation shield -- spider assembly it was necessary to recalculate the required tension rod angle to ensure rod tightness at operating temperature. Using the assembly fixture the tension rods were located at the following angles: No. 1 = 28°28', No. 2 = 28°17', No. 3 = 28°23' and torqued to 40 in.-lb. to temporarily secure the spherical washer in the receptacle. The adjusting pins were then installed between the spherical washer and the receptacle and tack weld thus securing the components.

Following the tack welding of the spherical washers, the tension rods were loosened and then sequentially torqued in 5 in.-lb. increments to 22.5 in.-lb. The rod anti-rotation devices were then installed in the slots of the female tension rods and tack welded to the spherical washers to prevent loosening of the tension rods. The receptacle seal-off plugs were tack welded to the receptacles and the vacuum seal for this unit was made with an epoxy. These seal-off plugs were sealed with epoxy so they could be removed after the unit dynamic test to failure to examine the tension rods for damage.

The strain gauge wires were fed through the center of the bottom enclosure head using a commercial vacuum feedthrough device sealed with epoxy. A Hastings DV-5M vacuum gauge and a Hooke bellows sealed vacuum valve were installed on the top enclosure head.

The unit was evacuated through the Hooke vacuum valve with a Veeco MS-9 helium leak detector. When the unit pressure was slightly greater than 100 microns, the unit was enclosed in a plastic bag and the bag filled with helium gas to conduct a unit leak check. The unit leak rate was determined to be 9.9×10^{-11} std. cc air/sec.

Measurements of the completed unit showed that the length from the top flange flat to the flat on the bottom head was 14.930 inches. The distance between the imaginary point on the spherical radius and the flat on the bottom head was .180 inch, thus making the overall length of the unit 15.110 inches. The unit diameter at the top head was 12.410 inches and the diameter at the bottom head was 12.402 inches. Dimensions were within tolerance of 3M Drawing PD-37-1349, except the .180 dimension should have been $.125 \pm .005$.

3.3.2.2.2 Thermal Testing

The unit was instrumented for conditioning and a thermal performance test at 1285°F. Four 3M supplied heaters (RAMA-500 watts, 115 volts, R-1833-2) were oriented in the heater block so that the stainless steel heater lead covering would fit into the inner liner. The heaters used in this test were out of specification in that the dimension from the centerline of the heater to the upward bend in the stainless steel lead covering was too long. This extra length required that the heaters be rotated in the heater block and made it impossible to use the heater block emitter plant and, therefore, instrument the unit for the dynamic test as originally planned. The use of the temporary heaters, however, did not affect the conduct of the thermal performance test.

Two chromel-alumel thermocouples were welded to the top of the heater block near the edge to be 180° apart. It was felt that it was not a good practice to attempt to join the thermocouples to the inner liner because of the potential for a leak. The heater block complete with heaters and thermocouples was installed in the inner liner. The heater block was not bolted to the inner liner as no provisions were provided for bolting without the use of the emitter plate.

The neck tube volume above the heater block was filled with one inch thick disks of Min-K 2000 insulation with the ceramic beaded heater wires and ceramic beaded thermocouple wires passing through the insulation. Voids around the wires and the edge of the insulation disks were filled with powdered Min-K 2000 which was tightly packed in place. A stainless steel cover plate was installed over the Min-K insulation to reduce convection. This plate was sealed to the upper head with silicone rubber and the heater wires and thermocouple wires were also sealed where they exited the plate with silicone rubber.

All four heaters were connected in parallel outside the neck tube and wired through a watt meter, recording ammeter, variac, constant voltage power supply, and isolation transformer to the line power. Chromel-alumel thermocouples were installed in the following locations on the unit: cover plate, upper unit head, cylindrical portion of unit near girth weld, near flat on bottom head. All thermocouples were connected to a temperature recorder. The unit was continuously evacuated throughout the unit heat up, conditioning, and thermal test period.

Power was supplied to the heaters initially at 50 watts for 24 hours (365°F) at which time the power was increased to 70 watts. The 70 watt power input was continued until the total accumulated time (TAT) was 95 hours (1060°F) when the power was again increased to 90 watts. Ninety watts power input was continued until 222 hours (TAT) was reached and the unit temperature was 1470°F at which time the power was turned off. Because of scheduled commitments and the fact that this unit was not permanently sealed, it was decided to not fully condition at 1550°F but to condition only enough to achieve acceptable pressures at operating temperature.

When the unit had cooled to 1300°F, the power was switched on at 20 watts to get the heaters operating. As the unit cooled, the power was increased to achieve a steady 1285°F temperature. The maintenance of this temperature required 65 watts as read on the watt meter. The insulation pressure was at 3 microns during the determination of the power input at 1285°F.

To determine the actual heat loss, the subtractible heat losses (meter corrections, heater wire loss, Min-K insulation loss, thermocouple wire loss) were calculated by a one dimensional analysis similar to that presented in Appendix H, and by a two dimensional analysis presented in Appendix I. The unit heat loss by the one dimensional analysis subtractibles was determined to be 46.3 watts and it was 49.4 watts as determined by the two dimensional analysis subtractibles. As this heat loss was somewhat above the specified 45 watt loss, an attempt was made to reduce the heat loss through insulation application modifications on units B10-D3 and B10-D4.

Following the thermal performance test, the power was turned off and the unit allowed to cool to 560°F before removing the Min-K insulation and heater block to replace the temporary heaters for the dynamic performance test.

3.3.2.2.3 Dynamic Testing

Two heaters and Min-K insulation system used during the thermal test were replaced for the dynamic performance test. The Min-K insulation was altered for the dynamic test by the addition of a stainless steel disk mounted on the emitter plate and a stainless steel ring attached to the insulation cover plate (Appendix I). This alteration was necessary to simulate the neck tube temperature profile of an operating unit (including T.E. generator) and thus provide the neck tube thermal expansion to insure support system tightness at operating temperature. In addition, a provision was made to thread a copper rod into the center of the heater block to provide a heat loss which simulates the operating system (203 watts) and thus cause the bottom end of the radiation shield to reach the expected operating temperature of 1430°F.

After installing the Min-K insulation and connecting the heater lead wires to the cover plate terminal box, the unit was installed in a shipping container and transported to the dynamic testing facility (Odgen Technology Laboratories - Deer Park, Long Island, New York).

Upon arrival, the unit was removed from the shipping container and installed in the dynamic test fixture. The electrical wiring was connected and power was supplied to the unit to bring the temperature at the bottom of the neck tube to 1285°F operating temperature. When the operating temperature was reached, the copper rod was installed in the heater block to increase the system heat loss. It was found that with the copper rod, the heat loss at 1285°F was approximately 100 watts instead of the desired 203 watts. Before testing, calculations were performed to determine the effect of less heat input on the tightness of the tension rods; as it was expected that the hot end tension rod temperature would be lower than the 1430°F used in the calculations. These tension rod calculations showed that the rods would be tighter at temperatures lower than 1430°F than at 1430°F allowing the dynamic test of the unit to be performed. The copper heat transfer rod was redesigned for the dynamic test of unit B10-D3 to allow a 200 watt heat input to the unit.

The unit was leak checked at operating temperature prior to the dynamic tests using a Veeco MS-9 helium leak detector. A considerably higher leak rate was measured: 5×10^{-8} std. cc/sec. versus 9.9×10^{-11} std. cc air/sec. when the unit was checked after fabrication at ambient temperature. Following the leak check, helium was sprayed around the vacuum gauge, seal-off valve, receptacles, and strain gauge connectors without any indication of leakage. The cause of this apparent leakage at operating temperatures was not determined.

The dynamic vibration test was conducted per MIL STD. 810-A except that the maximum vibration was limited to 3 'g' (three sweeps at 3 'g' max., 5-50 Hz, for 15 minutes each axis). A helium leak check was performed after each axis of the test with the result that the leak rate was essentially the same as determined prior to testing the unit. Because of the similar leak rates, it is apparent that no failure occurred during the dynamic vibration test.

The dynamic shock test was conducted as per MIL STD. 810-A by the shaker shock method (three shocks each direction each axis - 6 'g' peak sawtooth at 6 ms). A helium leak check was performed after completion of each axis showing that no failure had occurred during the shock tests. The profile achieved during the shock tests was slightly out of specification with MIL STD. 810-A - Figure 516-1 in that the negative 'g' level after the 6 'g' peak was reached exceeded the specified 1.2 'g'.

3.3.2.2.4 Thermal Retest

Following the dynamic vibration and shock tests to specifications a thermal retest was performed to determine if there was any change in insulation system performance. The copper heat transfer rod used during the dynamic tests to increase the unit heat loss was removed and the cavity occupied by the rod was filled with tightly packed powdered Min-K 2000 insulation. During the removal of the copper rod it was necessary to cool the unit to 250°F as the copper rod broke off at the cover plate, requiring the removal of the cover plate and first layer of Min-K insulation to remove the copper rod. During removal, the threaded end of the rod twisted off even with the emitter plate into which it was threaded. The inner liner Min-K insulation was reassembled and the unit was heated to 1285°F for the thermal test.

The thermal performance test was conducted using Ogden Laboratories calibrated watt meter, voltmeter, and ammeter. At a steady hot end inner liner temperature of 1285°F, the unit required 26.3 volts and 2.84 amps. The product of the volts and amps (not considering the power factor) yields an input of 74.69 watts. Following the test, the power lead wiring from the instrumentation to the unit was returned to Linde where it was determined that the power leads exhibited a resistance of .622 ohms. The I^2R loss in the power lead wire is, therefore, 5.02 watts. Subtracting the power lead loss results in a corrected input power of 69.67 watts. Using subtractibles calculated by a one dimensional method the heat loss was 49.9 watts and while using two dimensional calculated (Appendix I) subtractibles the heat loss was 45.7 watts.

3.3.2.2.5 Dynamic Test to Failure

Following the thermal retest the dynamic test to failure was conducted to determine the design factor of the unit. Initially the shock tests were conducted. The shock 'g' level was increased from 6 'g' to 12 'g' in 1-1/2 'g' increments on the unit critical axis. A helium leak test was made at the conclusion of each 'g' level shock test and it was determined that the unit had not failed.

It was decided, with 3M concurrence, that the unit should be vibration tested at higher 'g' levels rather than continue to increase the shock 'g' level to establish a design factor for both vibration and shock. The unit failed during a 4.5 'g' vibration test (50 Hz max.) as evidenced by a loss of vacuum.

The dynamic failure tests were conducted on the unit Y-Y axis only. In this axis one support rod is in the plane of the axis with the other two support rods being 60° from the plane of the axis. This axis was used for the failure test because the support rods exhibit the lowest spring constant in one direction of the axis resulting in maximum deflections of the shield.

Three shocks in each direction of the Y-Y axis were performed at input 'g' levels of 7-1/2 'g', 9 'g', 10-1/2 'g', and 12 'g'. All shocks had a nominal duration of 6 milliseconds. The unit was helium leak checked after each 'g' level shock sequence, except the 10-1/2 'g' level with no evidence of unit failure.

At the conclusion of the above shock tests, a design factor of 2.0 in shock was established. It was decided that if unit modifications were to be made as a result of the failure test, it would be necessary to vibration test the unit to the 6 'g' level to establish a 2.0 design factor in vibration. It was planned to first test the unit at 4.5 'g' in vibration and then 6.0 'g' in vibration.

The unit was vibration tested on the Y-Y axis according to the following schedule: 5-8 Hz - .4 inch double amplitude, 8-21 Hz - ± 1.3 'g', 21-40 Hz - .055 inch double amplitude, 40-50 Hz - ± 4.5 'g', and return to 5 Hz in the reverse of this procedure. Total test time was 15 minutes, 7-1/2 minutes

for 5-50 Hz and 7-1/2 minutes for 50-5 Hz. Following this test, the unit vacuum gauge was turned on and it was noted that the unit had lost vacuum. The unit was removed from the test machine and placed in a helium filled bag to cool. After cooling, the unit was placed in the shipping container and returned to Linde Division, Tonawanda.

The results of the failure test show that the unit failed in vibration at a level predicted during the calculations (3 'g' design x 1.5 design factor = 4.5 'g'). The exact 'g' level causing failure is, however, not known as there was no failure during the 3 'g' vibration tests, but the unit did fail during the 4.5 'g' vibration tests. In addition, there is a possibility that the 12 'g' shock level started a failure which was not of sufficient magnitude to cause leakage and, therefore, allow detection. As a result of the dynamic tests (shock and vibration) to specifications and the dynamic test to failure, the unit structural design was not changed on future development units.

The Min-K insulation system was removed from the inner liner revealing that the failure had occurred in the inner liner neck tube as predicted. The failure was caused by shear buckling as evidenced by 45° wrinkles in the inner liner. The inner liner was cracked open for approximately two-thirds of the circumference. This large failure was no doubt caused by continued testing after initial failure occurred. Figure 84 shows the inner liner failure.

3.3.2.3 Development Unit B10-D2.

3.3.2.3.1 Unit Fabrication

This unit which had a heavier wall neck tube with a higher structural design factor was to be a back-up unit in case of premature failure of unit B10-D1. This unit was fabricated in the same manner as unit B10-D1 (Section 3.3.2.2.1) except that the unit was permanently vacuum sealed and getter was installed in the unit. The additional fabrication effort related to the permanent seal-off is presented in the following paragraphs.

To accommodate the getter and permanent seal-off a getter seal-off device female end, hydrocarbon getter enclosure assembly, and getter retainer assembly were installed in the bottom head during the bottom head sub-assembly operation.

The getter seal-off device, female end, was aligned in the bottom head to be flush with the flat on the head. Four tack welds were made 90° apart. The edge weld was manually performed with the following parameters recorded: 48-50 amps, 8.5-10.0 volts, 25 cfh argon, 6 IPM torch travel, no filler wire added. The hydrocarbon getter enclosure which contained 1.068 grams was centered on the seal-off device, female end, and the attachment lugs were welded to the head using 60-64 amps, 9-10 volts, 25 cfh argon, .045 inch 308L filler wire.

FIGURE 84

FAILED INNER LINER UNIT B10-D1
(99-68)

The getter retainer assembly was aligned in the bottom head and tack welded in eight places around the circumference. The seal weld was manually performed using 72-84 amps, 8.5-10.5 volts, 2-3 IPM, .045 inch 308L filler wire, 25 cfh argon. This weld was not continuous, as approximately two inches of weld was welded at a time, before skipping across the diameter to weld the next two inches. This procedure was employed to keep the shrinkage to a minimum.

After closure, which was performed the same as on unit B10-D1 except that the tension rod seal-off plugs were welded in place, the unit was evacuated and leak checked using a Veeco MS-9 leak detector. With the unit enclosed in a helium filled bag, the leak detector indicated excessive leakage. The bag was removed and the leak was determined to be caused by stringers in No. 1 and No. 2 seal-off plugs. The unit vacuum was released by back filling with dry nitrogen gas and the stringers were repaired by applying a heliarc weld bead over each stringer. A subsequent leak check showed the unit to have a leak rate of 2.9×10^{-10} atm-cc air/sec. which is acceptable.

Measurements of the completed unit showed that the length from the top flange flat to the flat on the bottom head was 14.932 inches. The distance between the imaginary point on the spherical radius and the flat on the bottom head was .116 inch, thus making the overall length of the unit 15.048 inches.

The unit diameter at the top head was 12.413 inches and the diameter at the bottom head was 12.406 inches. The overall length of the unit was .002 inch under minimum length because the distance from the flat to the imaginary point was out of tolerance. The diameters, as measured, are within tolerance.

The getter fill and permanent seal-off was performed after the conditioning and thermal test of Section 3.3.2.3.2 and is discussed in that section.

3.3.2.3.2 Thermal Test

Following the closure, the unit was instrumented for conditioning at 1550°F and a thermal performance test at 1285°F. This unit was instrumented for the thermal test using the inner liner Min-K design as was used for the unit B10-D1 rethermal test. This design was used so that it would not be required to change the Min-K insulation in the event that this unit would assume its backup function and be dynamically tested in the event of premature failure of unit B10-D1. A schematic of the Min-K inner liner insulation system design is shown in Appendix I.

Power was supplied to the heaters initially at 50 watts for 16.75 hours (295°F) at which time the power was increased to 80 watts. The 80 watt power was continued until the total accumulated time (TAT) was 24 hours (425°F) when the power was increased to 100 watts. One hundred watts power input was continued until 43.8 hours (TAT) was reached (790°F) when the power was increased to 150 watts. The 150 watt input was continued until the unit reached 1550°F conditioning temperature at 94 hours (TAT). At this time the power was reduced to approximately 100 watts (adjustments were made when required)

to maintain the 1550°F temperature until 140 hours (TAT) when the power was turned off. At 153 hours the unit had cooled to 1300°F and the power was resumed at 65 watts. As the unit slowly cooled, the power was adjusted to maintain a steady 1285°F. The insulation pressure during the thermal performance test was 1.5 microns and the corrected total power to the unit was 71.82 watts (corrected for meter calibration and I²R loss in power lead wire). The unit heat loss using one dimensional subtractibles was 52.8 watts while the heat loss using two dimensional subtractibles was 47.7 watts. This heat loss is somewhat higher than the heat loss on the B10-D1 rethermal test which used the same neck tube insulation. The difference in heat loss 2-3 watts was attributed to the increased thickness of the neck tube wall.

At the conclusion of the leak check, 13.25 grams of regular getter was installed in the unit through the seal-off device with the unit under vacuum. It was intended to install 15.0 grams, however, 1.75 grams of getter remained in the glass feed tube and did not enter the unit. Offgassing calculations show that the unit only needs 6.4 grams of getter for a five year life, therefore, the 13.25 grams put in this unit is entirely adequate.

The male getter seal-off device with the gold O-ring was threaded into the female seal-off device and torqued to 75 ft.-lb. to make the temporary unit seal-off. Following the temporary seal-off, the final seal-off was made using the following parameters: 50-54 amps, 9.0-10.5 watts, 6 IPM, 25 cfh argon, no filler wire used. Prior to completing the seal-off weld, the volume between the weld and the gold O-ring was purged with dry nitrogen gas to reduce the argon concentration that would remain between the two seals when the weld was completed. The unit vacuum gauge readout indicated a unit pressure of less than .1 micron after seal-off.

The Min-K insulation and heater block was removed from the inner liner and the unit was installed in a shipping container for delivery to 3M Company.

3.3.2.3.3 Dynamic Testing

This unit was not dynamically tested directly following fabrication because of a need for the unit for thermo-electric generator testing and the fact that it was a back-up unit for the successfully tested unit B10-D1. This unit was tested, however, after unit B10-D4 failed during dynamic testing for no apparent reason (subsequent investigation revealed that the B10-D4 failure was caused by test machine malfunction).

Prior to dynamic testing, the history of this unit included a heat up to 1550°F and a thermal test at 1285°F at Linde Tonawanda, followed by a nuclear fueled heat up to operating temperature at Oak Ridge, Tennessee. The unit was subsequently returned to 3M Company, St. Paul, prior to delivery to Ogden Laboratories, Deer Park, Long Island, New York.

Upon arrival at the test facility, the unit was instrumented for an ambient temperature vibration test on the critical axis. The purpose of this test was to determine if the unit was structurally sound (re no loose tension rods). The unit was vibrated at 1/2 'g', 1 'g', 1.3 'g', 2.0 'g', 2.5 'g', and

3 'g' input as indicated on Table 26. For this test, an accelerometer was mounted directly to heavy wall portion of the inner liner inside the unit where the liner is bolted to the radiation shield. Accelerometers were also mounted on the enclosure shell and the fixture adapter plate. The Y-Y direction is parallel to one tension rod with the unit vibrating in the horizontal position, the Z-Z direction is 90° to the Y-Y direction while the X-X direction is the direction of the unit axis.

Unit B10-D2 successfully passed this ambient temperature vibration test. Table 26 was prepared from the accelerometer recording taken during the test and presents the recorded accelerations at the specified accelerometer locations for selected frequencies for each sweep of the test. For test sweeps No. 1 (1/2 'g' peak) through No. 4 (2 'g' peak) there was no amplification noted on the inner liner in the test direction. On sweep No. 5 (2.5 'g' peak) there was a measurable amplification of the inner liner which was observable in the range of 40 to 50 Hz. The maximum 'g' level measured on the inner liner was 3.5 'g' when the measured input was 2.65 'g' at 50 Hz.

On sweep No. 6 there was noticeable amplification of the inner liner from 38 Hz to 50 Hz with the amplification becoming greater as the frequency increased. There was also a considerable 'g' loading on the inner liner in the X-X direction (direction of unit axis) which was no doubt produced by loads induced from the angled tension rods. At 50 Hz where the maximum amplification occurred the sinusoidal 'g' level on the inner liner in the test direction was 5.1 'g' with high frequency spikes noted which were as large as 7.8 'g' peak to peak. This measured 'g' loading occurred with a measured input 'g' loading of 3.75 which included some noise. The unit was successfully tested to specifications at operating temperature following the ambient temperature vibration test by approximately four months. The unit remained at Ogden Laboratories, Deer Park, Long Island, New York between the tests and was not transported.

For the operating temperature test, the inner liner was insulated with Min-K insulation using the same configuration as was used on unit B10-D4 (copper disk and stainless steel ring used). The unit was electrically heated to 1285°F at which time the half inch diameter copper rod was installed to simulate the T/E generator heat loss. The testing was conducted with the unit at a nominal 1285°F while supplying approximately 220 watts of power to the unit.

The dynamic vibration test was conducted as per MIL STD. 810-A (three sweeps at 3 'g' max. for 15 minutes on each axis). The unit pressure remained below .2 microns during and subsequent to the vibration tests.

The dynamic shock test was conducted as per MIL STD 810-A (three shocks each direction each axis, 6 'g' peak sawtooth at 6 ms). The unit pressure was below .2 microns at the conclusion of the testing making it apparent that a failure did not occur during the shock test. At the completion of the dynamic test, the unit was removed from the test fixture, installed in the shipping container, and delivered to 3M Company.

TABLE 26

RECORDED ACCELERATIONS - UNIT B10-D2 (AMBIENT) VIBRATION TEST

	Frequency CPS	Recorded 'g' Levels							No. 8 Adapt. Plate Y-Y
		No. 1 Input Y-Y	No. 2 Neck Tube Y-Y	No. 3 Neck Tube Z-Z	No. 4 Neck Tube X-X	No. 5 Enclosure Y-Y	No. 6 Enclosure Z-Z	No. 7 Enclosure X-X	
SWEEP NO. 1 ($\frac{1}{2}$ 'g' Peak)	5	1.0	.75	.05	.05	1.0	.10	.25	.85
	7	.55	.40	.05	.05	.60	.20	.25	.50
	10	.60	.50	.05	.05	.60	.15	.20	.60
	15	.55	.45	.15	.10	.60	.30	.25	.55
	20	.55	.50	.05	.10	.60	.20	.20	.55
	30	.60	.50	.05	.10	.65	.15	.25	.55
	40	.70	.50	.05	.10	.60	.20	.20	.50
	50	.60	.50	.05	.10	.70	.15	.25	.55
SWEEP NO. 2 (1 g Peak)	5	.50	.40	.05	.05	.55	.10	.20	.45
	7	.90	.80	.10	.15	.90	.25	.30	.85
	10	1.15	.90	.05	.10	1.00	.20	.25	1.05
	15	1.10	.90	.10	.10	1.05	.20	.25	.95
	20	1.10	.95	.10	.10	1.00	.20	.25	1.00
	30	1.05	.90	.10	.20	1.05	.20	.35	.95
	40	1.10	.90	.05	.15	1.05	.20	.25	.95
	50	1.15	.95	.10	.15	1.05	.25	.30	.95
SWEEP NO. 3 (1.3g Peak)	5	.60	.40	.05	.10	.65	.20	.30	.50
	8	1.80	1.15	.05	.10	1.70	.50	.60	1.30
	10	1.70	1.20	.05	.15	1.50	.50	.60	1.30
	15	1.70	1.20	.15	.15	1.45	.30	.35	1.30
	20	1.60	1.15	.20	.20	1.30	.30	.45	1.25
	30	1.50	1.20	.10	.20	1.40	.25	.40	1.30
	40	1.50	1.20	.10	.20	1.45	.25	.30	1.25
	50	1.50	1.40	.30	.40	1.35	.25	.35	1.30
SWEEP NO. 4 (2.0 g Peak)	5	.55	.35	.05	.10	.60	.20	.25	.45
	8	1.90	1.20	.10	.15	1.70	.50	.65	1.35
	10	1.75	1.15	.10	.15	1.50	.45	.50	1.35
	15	1.65	1.20	.20	.15	1.45	.35	.35	1.30
	20	1.65	1.20	.15	.15	1.45	.30	.55	1.30
	30	2.00	1.50	.50	.80	1.70	.40	.50	1.55
	40	2.45	1.90	1.00	1.70	2.15	.50	.60	1.80
	50	2.30	2.15	1.00	1.70	2.05	.45	.60	1.80
SWEEP NO. 5 (2.5 g Peak)	5	.65	.45	.10	.10	.75	.20	.35	.55
	8	1.50	1.25	.10	.15	1.40	.35	.40	1.40
	10	1.50	1.20	.10	.15	1.35	.30	.40	1.40
	15	1.45	1.20	.20	.15	1.35	.25	.35	1.35
	20	1.50	1.25	.15	.15	1.35	.25	.40	1.35
	30	2.20	1.70	.30	.65	2.05	.25	.60	1.90 Some am-
	40	2.85	2.20	.15	.60	2.90	.55	.85	2.35 plificati
	50	2.65	3.5	1.55	1.55	2.45	.40	.80	2.15 on of No.
									4+5 at 28
SWEEP NO. 6 (3.0 g Peak)	5	.75	.45	.10	.10	.75	.25	.40	.55
	8	1.50	1.20	.15	.15	1.40	.30	.40	1.40
	10	1.50	1.25	.15	.15	1.45	.30	.45	1.40
	15	1.50	1.20	.20	.15	1.40	.25	.30	1.40
	20	1.50	1.25	.20	.15	1.40	.25	.40	1.40
	30	2.10	1.60	.25	.30	1.90	.20	.50	1.75
	38	3.00	3.35	.85	2.15	2.90	.35	.80	2.50 @ 38 CPS
			4.40*						Start to
	40	3.30	3.35	1.60	2.00	3.05	.45	.85	2.70 See Noise
			3.65*	2.00*	2.80*				in #2+4
	45	3.50	5.05	2.30	4.00	3.30	1.10	1.55	2.75
			7.70*	3.05*	4.60*			2.15*	
	50	3.75	5.10	3.60*	7.20	3.60	.75	1.20	3.00
			7.85*		12.0 *			2.05*	

*Peak to peak g level including high frequency spikes.

3.3.2.4 Development Unit B10-D3

3.3.2.4.1 Unit Fabrication

This development unit was fabricated in essentially the same manner as unit B10-D2. There was, however, a minor change in the insulation application reducing the number of segment joints from 12 to 9 as discussed in Section 3.2.8.3.5. In addition the bore of the female tension rod was insulated with disks of copper opacified insulation paper.

To simplify the installation of the spherical washers, the use of a separate flat washer was eliminated. The overall tension rods length of 2.939 inches was achieved by starting with a longer spherical washer, and grinding it to the required length.

After closure, the unit was evacuated and leak checked using a Veeco MS-9 leak detector. With the unit enclosed in a helium filled bag, leak check showed the unit to have a leak rate of 5.5×10^{-10} atm cc air/sec., which is acceptable. Measurements of the completed unit showed that the length from the top flange flat to the imaginary point on the spherical radius on the bottom head was 15.052 inches. The unit diameter at the top head was 12.417 inches and the diameter at the bottom head was 12.414 inches. The length and diameters, as measured, are within tolerances.

3.3.2.4.2 Thermal Testing

Following the leak check, the unit was instrumented for conditioning at 1550°F and a thermal performance test at 1285°F. This unit was instrumented for the thermal test using the inner liner Min-K design as shown in Appendix I. This Min-K insulation system design is essentially the same as was used during the testing of unit 10-D2 except that the disk bolted to the emitter plate was fabricated from copper rather than stainless steel. This provided a better thermal path when using the 1/2 inch diameter copper heat transfer rod during the dynamic test providing a 200 watt heat loss to simulate an operating unit.

Power was supplied to the heaters at 50 watts for 24.5 hours (358°F) at which time the power was increased to 100 watts. The 100 watt power was continued until the total accumulated time (TAT) was 43 hours (695°F) when the power was increased to 150 watts. The 150 watt input was continued until the unit reached 1550°F conditioning temperature at 96 hours (TAT). At this time, the power was reduced to approximately 100 watts (adjustments were made when required) to maintain the 1550°F temperature until 117 hours (TAT) when the power was turned off. While cooling, the unit was leak checked with a helium leak detector and the leak rate was found to be 2×10^{-9} std cc air/sec.

At 130 hours (TAT) the unit had cooled to 1303°F and the power was resumed at 72 watts uncorrected. As the unit slowly cooled the power was adjusted to maintain a steady 1285°F. The insulation pressure during the thermal performance test was 1.4 to 2.0 microns and the corrected total power to the unit was 71.3 watts (corrected for meter calibration and I^2R loss in power lead wires).

The heat loss of the unit applying one dimensional subtractibles was 52.2 watts and it was 47.0 watts if the two dimensional subtractibles are applied. This heat loss is approximately one watt lower than the B10-D2 heat loss indicating that the change from the 12 segment joint design to the 9 segment joint design produced some results.

At the conclusion of the thermal test, 15 grams of regular getter was installed in the unit and the male getter seal-off device with the gold O-ring was threaded into the female seal-off device and torqued to 75 ft.-lb. to make the temporary seal off. Following the temporary seal-off, the final seal-off weld was performed. The unit was cooled to ambient temperature, placed in the shipping container, and transported to the dynamic test facility (Ogden Technology Laboratories - Deer Park, Long Island, New York).

3.3.2.4.3 Dynamic Testing

The unit was removed from the shipping container and installed in the dynamic test fixture and power was supplied to the unit to bring the temperature at the bottom of the neck tube to 1285°F operating temperature. When the operating temperature was reached, the 1/2 inch diameter copper rod was installed in the unit to increase the system heat loss. It was found that with this redesigned copper rod system, the unit heat loss could be maintained at 200 watts with 1285°F at the bottom of the neck tube to simulate a unit with a TEG installed.

The dynamic vibration test was conducted as per MIL STD. 810-A (three sweeps at 3 'g' maximum for 15 minutes on each axis). Following each sweep, the unit was bagged in a helium atmosphere for 1/2 hour and the unit pressure was monitored. The unit pressure below .2 microns during the times that the unit was bagged in helium. As a result of this excellent system pressure, it is apparent that no failure occurred during the dynamic vibration test.

The dynamic shock test was conducted as per MIL STD. 810-A (three shocks each direction each axis, 6 'g' peak sawtooth at 6 ms). Following each axis test, the unit was bagged in a helium atmosphere for 1/2 hour and the unit pressure was monitored. The unit pressure remained below .2 micron at all times and, therefore, it is apparent that no failure occurred during the dynamic shock test. The profile achieved during the shock tests was somewhat out of specification with MIL STD. 810-A Figure 516-1 in that the negative 'g' level after the 6 'g' peak was reached exceeded the specified 1.2 'g'. At the completion of the dynamic test, the unit was cooled and the Min-K 2000 neck tube insulation system was removed. The unit was installed in the shipping container and transported by common carrier to 3M Company, St. Paul, Minnesota.

3.3.2.5 Development Unit B10-D4

3.3.2.5.1 Unit Fabrication

This development unit was fabricated in the same manner as discussed for units B10-D2 and B10-D3 except that the nickel foils in the insulation were replaced by copper foils resulting in an installed insulation composition as shown on Table 27.

TABLE 27
INSULATION COMPOSITION UNIT 10-D4

<u>Number of Layers</u>	<u>Layer Composition</u>	<u>Total Thickness (Inch)</u>	<u>Layers per Inch</u>
2	Quartz Cloth	-	-
105	Copper Foil Quartz Paper	.945	111
60	Aluminum Foil 106 Paper	.453	132

This change was made in an attempt to reduce the unit heat loss. Calculations performed in Section 3.2.8.3 showed that the elimination of the nickel foils would result in a lower insulation heat loss.

After closure, the unit was evacuated and leak checked using a Veeco MS-9 leak detector. With the unit enclosed in a helium filled bag, leak check showed the unit to have a leak rate of 9.7×10^{-10} atm cc air/sec. which is acceptable. Measurements of the completed unit showed that the length from the top flange flat to the imaginary point on the spherical radius on the bottom head was 15.061 inches. The unit diameter at the top head was 12.415 inches and the diameter at the bottom head was 12.410 inches. The length and diameters, as measured, are within tolerance.

3.3.2.5.2 Thermal Test

The unit was instrumented for the thermal test in the same manner as for unit 10-D3 discussed in Section 3.3.2.4.2 of this report.

Power was supplied to the heaters at 50 watts for 19 hours (310°F) at which time the power was increased to 100 watts. The 100 watt power was continued until the total accumulated time (TAT) was 43.5 hours (760°F) when the power was increased to 150 watts. The 150 watt input was continued until the unit reached 1550°F conditioning temperature at 88.7 hours (TAT). At this time, the power was reduced to approximately 100 watts to maintain the 1550°F temperature until 121.5 hours (TAT) when the power was turned off. While cooling, the unit was leak checked with a helium leak detector and the leak rate was found to be 4.4×10^{-9} std cc air/sec.

At 137.5 hours (TAT) the unit had cooled to 1289°F and the power was resumed at 50 watts uncorrected. As the unit cooled, the power was adjusted to maintain a steady 1285°F. The insulation pressure during the thermal performance test was 3.8 microns and the corrected total power to the unit was 67.8 watts (corrected for meter calibration and I²R loss in power lead wires). The heat loss of the unit applying one dimensional subtractibles was 48.7 watts and it was 42.9 watts if the two dimensional subtractibles are applied. This is approximately a four watt reduction from the B10-D3 heat loss and also indicates that the specified 45 watt heat loss was achieved.

During this thermal performance test, one of the electric heaters failed while the power supplied was 150 watts as evidenced by a drop in system current and an increase in system voltage. After the unit was conditioned and the power turned off, the heater resistances were checked and it was found that one heater had a lead to lead resistance of 85K ohms while the other three heaters had individual resistances of approximately 27 ohms.

At the conclusion of the thermal test, 15 grams of regular getter was installed and the unit was permanently sealed. The unit was placed in the shipping container and transported to the dynamic test facility (Ogden Technology Laboratories - Deer Park, Long Island, New York) by common carrier shipment.

3.3.2.5.3 Dynamic Testing

The unit was removed from the shipping container and installed in the dynamic test fixture. The electrical wiring was connected and power was supplied to the unit to bring the temperature at the bottom of the neck tube (emitter plate) to 1285°F operating temperature. When the operating temperature was reached, the 1/2 inch diameter copper rod was installed in the unit to increase the system heat loss. The unit heat loss was maintained at approximately 200 watts with 1285°F at the bottom of the neck tube. A second heater failed after the installation of the copper rod. The vibration test was run while powering the unit with two heaters.

The unit in the test fixture was mounted on the vibration machine so that the Y-Y axis (vibration parallel to No. 1 tension rod) would be tested first. A 1 'g' sweep was run on the Y-Y axis from 10 Hz to 50 Hz with the result that the 'g' loading was smooth with no observable noise present. The vacuum level was unchanged following the 1 'g' sweep.

The unit was then vibrated as per MIL STD. 810-A (i.e., 5-8 Hz, .4 inch double amplitude; 8-26 Hz, 1.3 'g'; 26-40.5 Hz, .036 inch double amplitude; 40.5-50 Hz, 3 'g' peak; 50-5 Hz reverse of previous 'g' and double amplitudes). Following the first sweep, the unit vacuum was checked and found to be lost indicating the unit had failed. Examination of the accelerometer printout indicated that the failure most likely occurred at approximately 15 Hz and 1.3 'g'.

After the unit had cooled to approximately 300°F, it was removed from the test fixture, installed in the shipping container, and transported to Linde - Tonawanda. A failure analysis of this unit is presented in Section 3.3.2.5.4 of this report.

3.3.2.5.4 Failure Analysis Unit B10-D4

To determine the reason for failure of unit B10-D4 during the dynamic test, the damaged unit components and design was completely analyzed. This analysis included disassembly with dimensional inspection, chemical analysis to determine material composition, microscopic examination of neck tube material,

design analysis considering different unit temperatures than originally specified, and analysis of performance if a radiation shield phase change occurred. After all the above analysis work was completed and additional development work of determining the tension rod tightness (thermal-force cycles) was performed, no conclusive reason for the unit B10-D4 failure could be absolutely determined.

The reason for unit B10-D4 failure was, however, determined at a later date during the testing of delivery HTVIS units. After it was observed that units B10-DL1 and B10-DL3 were damaged during dynamic vibration testing by a malfunctioning test machine, the oscillograph trace which recorded the accelerations during the vibration test of unit B10-D4 was reviewed. This review revealed that the vibration machine experienced a shut down "dump" at 9 Hz which was the same as experienced by unit B10-DL1 at 7-1/2 Hz. This machine shut down induced loads similar to those which caused the neck tube of unit B10-DL1 to buckle. It is believed that the B10-D4 neck tube was buckled by the machine shut down. Continuation of the test cycle caused the neck tube to completely fail, resulting in the high amplification observed on the oscillograph trace above 15 Hz which occurred approximately 1-1/2 minutes after the machine was restarted. Figure 85 shows that portion of the oscillograph trace where the test machine malfunctioned resulting in a machine shut down. A complete discussion on effects of machine shut down is presented in Section 3.4.2.2.1.

The following sections summarize the failure analysis of unit B10-D4.

3.3.2.5.4.1 Unit Disassembly and Dimensional Inspection

The shipping container was opened and the Min-K insulation in the neck tube was removed. The heater block was removed and the cavity was vacuumed out to remove all the residual Min-K insulation. Figure 86 shows the inside diameter of the neck tube. It can be seen that the neck tube failed by buckling and was broken or separated at approximately the mid-point for approximately 3/4 of the circumference.

Following the observation of the inside of the failed neck tube, the neck tube opening in the upper enclosure head was sealed with a cover plate in order to conduct a leak rate test on all of the unit except the neck tube to determine if there was another source of vacuum leakage. It was determined that the leak rate of the unit not including the neck tube was 9×10^{-10} std cc air/sec. which indicates that the vacuum failure occurred when the neck tube failed.

To remove the female tension rods, a 9/16 inch diameter hole was milled through each tension rod receptacle seal off plug. The anti-rotation pins were broken off from the spherical washer and the female tension rods were threaded out of the unit. Each female rod was intact and not cracked or broken, however, they appeared to be necked down and elongated. The rods were somewhat discolored but the surface of the spherical ball was clean and smooth.

FIGURE 85

OSCILLOGRAPH RECORDING OF ACCELERATIONS DURING
VIBRATION TEST OF UNIT B10-D4 (NOTE MACHINE DUMP)
(1584-68)

FIGURE 86

VIEW INSIDE FAILED NECK TUBE UNIT B10-D4
(417-68)

The removal of the bottom head was accomplished by making a cut approximately 1/4 inch below the girth weld. The following observations were made; the outside nickel insulation layer was discolored adjacent to the tension rod holes, the receptacles appeared to have abraded against the nickel foil in the area of the greatest receptacle penetration into the insulation space, the getter retainer screen had made an impression on the outside nickel layer covering the bottom of the radiation shield, and the insulation had rubbed on the bottom head.

The top head was separated from the inner liner by grinding the edge weld with a seam grinder. With the top head removed it was observed that the insulation had rubbed on the top head. The outer nickel layer of insulation was discolored adjacent to the neck tube. It was also observed that there was some discoloration in the area of the girth weld. The circumference of the insulation on the cylindrical portion of the radiation shield was measured to be 36-7/16 inches top, 36-1/4 inches mid-point, and 36-3/8 inch bottom. These measurements are in close agreement with the final assembled measurement of 36-1/2 inches.

The observations noted above on the condition of the outer layer of insulation are to be expected. The abrasions and evidence of rubbing between the enclosure shells and the insulation indicate that relative motion occurred between these items during the dynamic tests. The extent of this relative motion was, of course, magnified by the structural failure allowing greater than normal deflection of the supported biological shield. The discoloring observed around the tension rod holes and neck tube verify the expected higher localized flux in those areas.

The insulation was then cut circumferentially through to the radiation shield at a point 9 inches from the top edge of the inner liner, separating the insulation into a top and bottom section. Cuts were made in the bottom section adjacent to each of the male rods to allow the section to be removed from the bottom of the radiation shield thus exposing the spider and spider mounting bolt.

Upon removal of the bottom insulation section, it was observed that there was a gap between the spider and the shield in the area of the friction surface. An attempt was made to measure this gap with feeler gauges, however, while handling the spider it was discovered that it was loose and could be easily moved on the shield (Figure 87). The safety wire on the spider holding bolt was intact and in good condition. The spider was removed and it was observed that the spider bolt was broken just below the head of the bolt. Some oxidation was noted on the radiation shield fit diameter. The aluminum oxide coating on the fit diameter and friction surface of the spider appeared to be in good condition. It was also noted that the face of the spider was discolored around the tension rods. The anti-rotation pins in spider securing the male tension rods from rotation were removed and the tension rods were removed from the spider. The anti-rotation pin on Rod No. 1 was sheared off in two places, while the pins on the other two rods were bent by a shear force, however, they were not broken. The male tension rods were discolored but otherwise appeared to be in good condition.

FIGURE 87
SIDE VIEW OF LOOSE SPIDER UNIT B10-D4
(433-68)

The top section of insulation was removed in one piece by sliding it over the shield toward the inner liner end of the unit thus exposing the bolts securing the inner liner to the radiation shield. The safety wiring on the bolts was intact. The safety wiring was removed and penetrating oil was applied to the threads of the eight inner liner bolts. During removal, three of the U_g Moly bolts sheared off just below the bolt head. The other five bolts were removed intact.

The inner liner was lifted out of the shield cavity without any difficulty with a loose fit being apparent. As previously discussed, the thin wall portion of the inner liner was fractured. The aluminum oxide compatibility barrier on the fit diameter and friction surface of the liner appeared to be in good condition. It was observed that there was an accumulation of particles in the shield cavity with a combined volume of approximately 1/4 teaspoon. These particles were analyzed and found to be essentially all Uranium.

With the unit completely disassembled as described above, the next step in the investigation was to determine the dimensional measurements of the components used in the unit. The individual structural components were dimensionally inspected to determine if there was any dimensional change resulting from the unit failure. These measurements were compared to initial inspection measurements made on the components prior to unit assembly.

The structural components that were dimensionally inspected included the radiation shield, inner liner, spider, male tension rods, female tension rods, spider bolt washer, and inner liner bolt washers. The dimensions measured on each of these components both before and after the failure are recorded on Table 28.

Inner Liner

Dimensions compared on the inner liner included the interference fit diameter, friction bolt flange thickness, and neck tube wall thickness. The interference fit diameter was found to be smaller by .0014 to .0026 inches after the failure. It was not determined if this reduction in diameter occurred in the Hastelloy-X material or in the aluminum oxide compatibility barrier. The friction bolt flange thickness was judged to be unchanged even though there were minor deviations in the dimensions possibly due to measurement error. The neck tube wall thickness measured after failure varied from .0114 to .0122 while the before failure measurement was .0115. Again this points out the difficulty in accurately measuring the neck tube wall thickness as obviously the wall did not get thicker. The neck tube wall thickness was, however, below the specified thickness of .012 to .013. The modest dimensional deviation of the neck tube thickness was not the cause of the unit failure because the failure occurred at a significantly lower than design 'g' level.

TABLE 28
 DIMENSIONAL COMPARISON OF UNIT B10-D4
 STRUCTURAL COMPONENTS BEFORE AND AFTER FAILURE

COMPONENT NAME AND LOCATION	BEFORE FAILURE				AFTER FAILURE				CHANGE
<u>INNER LINER COATED</u>									
Interference fit Diam. (Top)	4.0376	4.0370	4.0369	4.0369	4.0355	4.0352	4.0355	4.0350	-.0014 to -.0026
Interference Fit Diam. (Bottom)	4.0370	4.0370	4.0369	4.0369	Above Are Mid-Point				
Friction Bolt Flange Thickness	.140	.141			.1399	to	.1401		+.0001 to -.0011
Neck Tube Wall Thickness	.0115	.0115	.0115	.0115	.0114	to	.0122		
<u>RADIATION SHIELD</u>									
Inner Liner Fit Diam.	4.0384	4.0386	4.0385	4.0385	4.0404	to	4.0417		+.0018 to +.0033
Spider Fit Diam.	4.505				4.5070	to	4.5074		+.0020 to +.0024
Top Friction to Bottom Friction Flat	7.998				7.9970	7.9978			-.0002 to -.0010
<u>SPIDER - SHIELD SUPPORT</u>									
Interference Fit Diam.	4.506				4.5033	to	4.5045		-.0015 to -.0027
Friction Surface to Face	.888	.889			.8871	to	.8882		+.0002 to -.0018
<u>SPIDER BOLT WASHER</u>									
	Not Inspected, Drwg. Spec.								
Thickness	.470	± .005			.4693	to	.4702		
OD	1.090	± .005			1.0192	to	1.0914		
ID	.765	± .005			.7648	to	.7651		
<u>INNER LINER BOLT WASHER</u>									
	Not Inspected, Drwg. Spec.								
Thickness	.112	± .005			.1105	to	.1155		
<u>TENSION ROD - MALE END</u>									
Diameter									
Rod No. 1	.2729	.2734			.2730	.2730	.2734		
Rod No. 2	.2730	.2734			.2728	.2731	.2731		
Rod No. 3	.2730	.2745			.2724	.2732	.2735		
Overall Length									
Rod No. 1	1.9947				1.9943		1.9950		
Rod No. 2	1.9968				1.9924		1.9955		
Rod No. 3	1.9952				1.9940		1.9958		
<u>TENSION ROD - FEMALE END</u>									
Diameter - Thread Section									
Rod No. 1	.3468				.3466		.3468		-.0002
Rod No. 2	.3465				.3469		.3473		+.0004 to +.0008
Rod No. 3	.3465				.3456		.3458		-.0009 to -.0007
Diameter Tube Section					<u>Thread</u>				
Rod No. 1	.2465				.2304	.2383	.2455		-.0161
Rod No. 2	.2465				.2357	.2435	.2446		-.0108
Rod No. 3	.2465				.2367	.2396	.2444		-.0098
Length - Flat to Thread End									
Rod No. 1	1.5045				1.5409		1.5420		+.0364 to .0375
Rod No. 2	1.5071				1.5295		1.5464		+.0224 to .0393
Rod No. 3	1.507				1.5419		1.5497		+.0349 to .0427

Radiation Shield

Dimensions compared on the shield included the inner liner fit diameter, spider fit diameter, and length of shield from top friction flat to bottom friction flat. The inner liner fit diameter was found to be larger by .0018 to .0033 inches after failure. The relative fit between the inner liner and shield after failure, therefore, was a clearance of .0049 to .0067 inches. The allowable clearance at ambient temperature to produce a tight fit at operating temperature is .0015 inches. The fit at assembly was a clearance of .0008 to .0017 inches. The spider fit diameter was also found to be larger after the unit failure. This diameter had increased by .0020 to .0024 inches. The relative fit between the spider and the radiation shield was a clearance of .0025 to .0041 inches. The fit at assembly was an interference of .001 inch. The length of the radiation shield from the inner liner friction flat to the spider friction flat was less by .0002 to .001 inch. Because the original measurement was made in only one location and to only three place accuracy, it is felt that this small difference is due to measurement error.

Spider

Dimensions compared on the spider included the fit diameter and the distance from the friction surface to the face. The fit diameter of the spider was .0015 to .0027 inch less than that measured before failure. This decrease in diameter contributed to the fit clearance as discussed above. As with the inner liner, it was not determined if the decrease in diameter was caused by a movement of the Hastelloy-X material or of the aluminum oxide compatibility barrier. The thickness of the spider from the friction surface to the face varied from an increase of .0002 inch to a decrease of .0018 inch compared to the initial measurement.

Spider Bolt Washer and Inner Liner Bolt Washer

The dimensions of the spider bolt washer and inner liner bolt washers were not inspected by Linde prior to unit assembly. The measurements made after the failure show that these components were within specifications.

Tension Rod - Male End

The diameter and overall length of the male tension rods were checked after the failure and compared to the original dimensions. As seen on Table 28, the diameters and lengths of the male rods were essentially unchanged by the failure. The overall dimension of Rod No. 2 seems to indicate that it was shortened by .0013 inch. However, this is questionable and may be attributable to measurement inaccuracy.

Tension Rod - Female End

The diameter of the tube section, diameter of the thread section, and the length of the female tension rods were determined after the failure and compared to the original measurements. The diameter of the threaded section was essentially unchanged with a dimensional deviation of

of less than .001 inch. It was found, however, that the rods were elongated and necked down on the tube section adjacent to the threaded section (hot end-away from ball). Table 28 shows that the decrease in diameter at the necked section amounted to .0161 inch for Rod No. 1, .0108 inch for rod No. 2, and .0098 inch for Rod No. 3. The increased rod length resulting from the necking down was .0364 to .0375 for Rod No. 1, .0224 to .0393 for Rod No. 2, and .0349 to .0427 for Rod No. 3. It appears that Rods 2 and 3 were also slightly bent as indicated by range of elongation as both the maximum and minimum length were measured.

In summary, the major findings of the component dimensional inspection after the failure showed that the fits between the inner liner-shield and spider-shield have increased in clearance since assembly with the possible conclusion that the fits were not tight at operating temperature. It has also been determined that the female tension rods were elongated. It cannot be absolutely determined if the fit clearances and rod elongation occurred because of the failure or if they occurred prior to the failure

3.3.2.5.4.2 Material Composition of Unit Components

Following the dimensional inspection of the unit components, samples from the components were subjected to emission spectroscopy (semi-quantitative comparison method) to determine that the specified alloys were indeed used during the assembly of Unit B10-D4. The results of this examination showed that the specified materials were used. The unit components tested were as follows:

<u>Component Name</u>	<u>Material</u>
Inner Liner	Hastelloy-X
Spider	Hastelloy-X
Male Rod No. 1	Inconel-625
Male Rod No. 2	Inconel-625
Male Rod No. 3	Inconel-625
Female Rod No. 1	Inconel-718
Female Rod No. 2	Inconel-718
Female Rod No. 3	Inconel-718
Spider Bolt Washer	Molybdenum
Linder Bolt Washer	Molybdenum

3.3.2.5.4.3 Microscopic Examination of Neck Tube

The neck tube portion of the inner liner was cut off from the base portion and was further cut into sections for microscopic examination.

The metallographic examination of the failed unit B10-D4 neck tube revealed that it failed by fatigue. Damage to the fractured surface after initial rupture has eliminated any chance of positive proof that failure was caused by a metallurgical defect. However, certain deficiencies were found that were corrected on the delivery units neck tubes.

The principal metallurgical defect was the presence and poor distribution of carbides. There was considerable grain boundary precipitate but the amount and distribution of the massive carbides was also not desirable. There were stringers of the latter which were found in some cases to be at right angles with the tube wall. The weakness of the paths formed was shown by the propagation of cracks through these paths as well as across the grain in the normal fashion. The grain size of the neck tube is rather coarse but is not considered to be as critical as the carbide problem. The neck tube appeared to be unusually brittle in both cold and hot areas. It is recommended that if tubes are to be made of solid bars, one should start with a bar that is well forged and solution treated. After boring out, the tube should again be cold worked, such as by spinning, and again be solution annealed.

Of course, special attention should be paid to the best tooling for machining and contaminants containing sulfur and lead should be eliminated.

3.3.2.5.4.4 Thermal Expansion of Unit Components

If the axial thermal expansion of the neck tube and the shield is less than the calculated value, the tension rods become loose in the hot condition, and if the axial thermal expansion is more than the calculated value, the tension rods become tighter in the hot condition than in the ambient temperature condition. The amount of looseness or tightness produced in the tension rods as a result of plus or minus axial thermal expansion length variation has been calculated and is shown on Figure 88. It is seen from Figure 88 that looseness or tightness of the tension rods is sensitive to axial thermal expansion variation. For instance, the rod prestress, which corresponds to .00062 inch strain, will be lost if the axial thermal expansion is 0.001 inch less than predicted. If there is excessive tightness in the tension rods, due to plus axial thermal expansion, the tension rods could be yielded. The tension rods can be stressed to the proportional limit without causing permanent deformation. The elongation of the tension rods when stressed to the proportional limit is .0056 inch. This elongation in the tension rods is achieved if the axial thermal expansion of the neck tube and shield is plus .011 inch. The total calculated axial thermal expansion of the neck tube and shield is .113 inch.

The calculated temperature distribution of the neck tube for unit B10-D4 was slightly different from the previous units, because of the elimination of the neckel layers in the insulation. The axial thermal expansion of the neck tube of unit B10-D4 was calculated to be .0005 inch shorter than that of the previous units which had Al-Cu-Ni insulation layers. It is seen from Figure 88 that .0005 inch minus axial thermal expansion produces .00025 inch looseness in the tension rods. This looseness is 40 per cent of the prestress in the tension rods, and, therefore, this change would not cause the tension rods to be loose.

FIGURE 88
EFFECT OF AXIAL THERMAL EXPANSION OF SHIELD, AND NECK TUBE ON
TENSION ROD LOOSENESS, AND TIGHTNESS

3.3.2.5.4.5 Radiation Shield Phase Change

The U_8 Moly radiation shield used in the HTVIS unit should be in the gamma stabilized state before the unit is assembled. The shield in the gamma state when rapidly heated or cooled should not undergo a phase change to the alpha state or alpha plus gamma state. With this performance there would be no discontinuity in the thermal expansion curve as shown below:

The design calculations were made on the basis that the radiation material did not undergo a phase change. Gamma state material which is slowly heated up through the range 800-1050°F can be partially or completely transformed to the alpha state. This transformation is accompanied by a reduction in length or effectively an increase in density. Once the temperature of the material is above 1050°F, the alpha state material will be transformed back to the gamma state with a corresponding increase in length. The thermal expansion curve for a slow heat up may look like the curve presented below:

If transformation occurred during a slow heat up, the shield would be shorter than calculated, resulting in a loose rod condition, however, at temperatures above 1050°F, the alpha would be transformed back to gamma and the rods would again be tight. The transformation from gamma to alpha plus gamma or all alpha during heat up would not cause the tension rods to be loose at operating temperature as long as the alpha plus gamma was transformed to all gamma at operating temperature.

Of a more potentially serious consequence, is the case where the shield may not be initially in the gamma stabilized state and be in the all alpha or alpha plus gamma state at fabrication. For this condition, the thermal expansion curve during heat up would look like the curve presented below.

As seen, the phase change during heat up would cause an expansion of the shield which was not accounted for in the calculations. If the shield went from all alpha to gamma at operating temperature, the additional axial expansion of the shield would be .024 inches. This much axial expansion would amount to a tension rod tightness of .012 inches (Figure 88). Since the tension rods will yield at .0056 inches, there could be a permanent elongation of the rods of .0064 inches. Even if this transformation were to occur, the tension rods should be tight at operating temperature (in fact, they would be preloaded to the proportional limit or yield point). During conditioning of the unit at 1550°F, the rods could be further yielded so that upon return to operating temperature there could be looseness.

3.3.2.5.4.6 Radiation Shield Spider End Temperature Variation

The effect of the variation of the shield temperature at the spider from the specified design temperature of 1430°F with the bottom of the neck tube temperature of 1285°F on the loosening or tightening of tension rods was calculated and is shown on Figure 89. It is seen from Figure 89 that if the shield temperature at the spider end is lower than the temperature of the shield at the neck tube end, the tension rods will be subjected to tensile loads. During insulation conditioning, when the neck tube hot end temperature is 1550°F, the temperature of the shield at the spider end must be 1600°F or more to avoid permanently yielding the tension rods. The results of this analysis show the importance of the knowledge of the temperature of the shield at the spider end to determine if the tension rods are performing as designed.

The effect of temperature drop between the spider and the male tension rods on the tension rod tightness was analyzed. It was found that the tension rod tightness is not extremely sensitive to temperature drop between the spider and the male tension rod. In order to stress the tension rods beyond the proportional limit, the temperature drop between the spider and the male rod would have to be more than 200°F.

FIGURE 89

EFFECT OF TEMPERATURE OF SHIELD AT SPIDER END ON
TENSION ROD LOOSENESS, OR TIGHTNESS

Additional development testing was performed (Section 3.3.3) to determine the temperature of the spider on an operating unit and to determine the tension rod loading history of a unit which was conditioned followed by a simulated thermoelectric generator operation.

3.3.3 Tension Rod Thermal Force Cycles

An HTVIS unit (B10-Q1) was fabricated and instrumented to measure the tension rod loads and spider temperatures. Three thermal/force cycles were conducted with this unit to determine the tension rod loadings, relationship between spider and emitter plate temperature, and susceptibility of the radiation shield to change phase while cooling the unit.

3.3.3.1 Test Unit and Instrumentation

The HTVIS unit used for this test was fabricated to the same design as unit B10-D4. Some features of the unit were modified, however, to allow the installation of the instrumentation required for the test, for example, the bottom head contained a vacuum type feedthrough for the spider thermocouples, the bottom head was only tack welded to the top head and sealed with epoxy, and the enclosure seal-off plugs were replaced with vacuum feedthroughs for the tension rod load measuring instrumentation wires.

The bottom shield temperatures were measured by welding two chromel-alumel thermocouples directly to the spider in the slot provided for the tension rod installation. One chromel-alumel thermocouple was welded to the flat end of male tension rod which is adjacent to the spherical ball. All three thermocouples were calibrated to 1700°F prior to installation. The thermocouple wires were protected with ceramic beads and ceramic tubes where the thermocouples passed through the multi-layer insulation. The installed thermocouples are shown in Figure 90.

The hole through the multi-layer insulation was insulated with disks of the same materials (i.e., copper foil - quartz paper, aluminum foil - 106 paper) as was previously cut out. Processed quartz paper was packed around the ceramic thermocouple insulators to eliminate radiation windows through the insulation system.

Three methods were evaluated to measure the loading in the tension rods during the heat and cool test cycles. These methods included the use of load washers installed between the spherical washer and receptacle, strain gauges mounted on the surface of the spherical washer, and strain gauges mounted directly on the cool end female tension rod.

Load washers are force transducers which operate on the principle of load being proportional to the electrical resistance of a material between the two disks making up the washer. Load washers were procured and evaluated by calibrating on a simulated tension rod assembly in a tensile test machine, and by determining that vacuum has no measurable effect on the calibration. It was found that the load washers had good sensitivity between 0 and 25 pounds but the sensitivity was poor above 25 pounds. It was also determined that moderate temperature changes

FIGURE 90
VIEW OF THERMOCOUPLES INSTALLED ON SPIDER OF THERMAL FORCE CYCLE UNIT
(688-68)

has a negligible effect. In addition, the load washers were extremely fragile and difficult to electrically isolate from the rest of the unit. Load washers were used only on the First Thermal Force Cycle and only as an indication of tension rod tightness or looseness.

To evaluate the concept of measuring the tension rod loading with strain gauges on the spherical washer, six strain gauges were installed on a spherical washer. Three were installed parallel to the axis of the washer and three were installed in the circumferential direction. To determine the force response, the spherical washer was calibrated in a tensile test machine using the same set up as was used on the load washers. It was found that the strain readings of each of the strain gauges depended on the relative orientation of the female rod in the spherical washer and in addition the change in strain was small for the applied load reducing the accuracy. This concept for measuring the tension rod loads was not employed in the Thermal Force Cycles.

By installing strain gauges on the female tension rod, the loads in the rod can be measured directly. This concept of load measurement is attractive from the standpoint that the measured strain is large (about 1800 micro in./in. at 1000 lbs. load) and the strain measurement is independent of the orientation of the female rod in the spherical washer. The maximum temperature of the rod at the strain gauge location was expected to be at 400°F, and at this temperature the strain correction due to temperature is 700 micro in./in.

To measure the load in the tension rods during the thermal force cycles of unit B10-Q1 it was decided to bond strain gauges directly to the female tension rods. Two SR-4 BLH strain gauges (type FAB-12-12 S6S) were mounted on each female rod located approximately 1/32 inch from the spherical ball and 180° opposite to each other. The electrical wires from the strain gauges were fed through two holes (.052 inch diameter) drilled through the spherical ball parallel to the rod axis near the outside diameter of the female rod. Also mounted on each rod between the strain gauges was one chromel-alumel thermocouple. The thermocouple wires also passed through the holes drilled through the rod ball.

Load calibration of the female rod mounted strain gauges was conducted on a Baldwin Tensile Test Machine. The female rod was installed in the lapped spherical washer which was placed in a receptacle on the fixed head of the machine. A tensile load was applied to the female rod through a dummy male rod. The female rods were cycled from 0 to 1000 pounds load to determine the relationship between the indicated strain of the rod mounted strain gauges and the actual load applied. Calibration graphs were prepared for the load-strain calibration for the six strain gauges that were calibrated.

Because the strain gauges (which are temperature sensitive) are mounted on the female rod which changes in temperature as the unit is heated to operating temperature, it was necessary to determine the relationship between indicated strain and strain gauge temperature. To accomplish this,

the female rods with mounted strain gauges were placed in an oven and were heated to 500°F while measuring the indicated strain. Calibration graphs were prepared for the temperature indicated load-strain relationship for the six strain gauges.

To determine if the indicated strain caused by temperature could be subtracted from the indicated strain of a tension rod under load at an elevated temperature to yield a strain which was related to the rod load, the rods were heated while in the tensile test machine and under a known load. Correlating the results of these tests with the load and temperature calibration graphs, it was determined that the temperature induced strain could be directly subtracted from an indicated strain as would be recorded during the test with good accuracy to achieve a strain to determine the load in the tension rod.

3.3.3.2 First Thermal Force Cycle - Unit B10-Q1

The purpose of this test was to determine the tension rod load profile and the temperature of the spider in relation to the temperature of the emitter plate while subjecting the unit to a thermal cycle similar to that used on unit B10-D4. In addition, a secondary purpose of the test was to determine if the radiation shield could be cooled at a rapid enough rate to prevent formation of the alpha phase.

3.3.3.2.1 Unit Closure

Following the calibration of the tension rod strain gauges and the Clark load washers, the following work was performed to close the unit for the test. The female tension rods with the previously ground to length spherical washers were installed in the receptacles with the Clark load washers. The installed rod lengths were measured to verify their overall length at $2.939 \text{ inch} \pm .005$. The Clark washers were isolated electrically from the receptacle and spherical washer with .001 inch thick Mylar washers. A lot of difficulty was encountered in isolating the load washers and as a consequence the no load resistance was considerably lower than was present during the washer calibration. However, it was judged that the resistance was adequately high so that the load washers would operate to determine if the tension rods were at least loose or tight.

Using the tension rod assembly fixture to set the tension rod angle, the rods were sequentially torqued in 5 in.-lb. increments to 23 in.-lb. With the spherical washer properly located in the receptacle as a result of setting the rod angle and torquing the rods, the spherical washer alignment pins (three each washer) were installed and epoxied to the receptacle. The anti-rotation pins were then installed in the female rod slots and epoxied to the spherical washers.

A short extension was epoxied to each of the receptacles for mounting of the vacuum type feedthroughs. The strain gauge wires, thermocouple wires, and load washer wires were then passed through the feedthrough and vacuum sealed. Similarly, the wires from the thermocouples on the

spider were passed through and sealed to a vacuum type feedthrough which was epoxied to the bottom enclosure head. The girth weld joint which was previously tack welded was vacuum sealed with epoxy.

The unit was evacuated through the evacuation and getter fill apparatus as was used on the previous units and leak checked with a helium leak detector resulting in an acceptable leak rate.

3.3.3.2.2 Test Set-Up

The heater block was installed and the inner liner was insulated with Min-K insulation in the same manner as was performed for unit B10-D4 (copper disk and stainless steel ring used). A thermocouple was installed on the bottom of the heater block to determine the temperatures at this location during the unit heat up. Thermocouples were installed on the unit enclosure the same as on unit B10-D4. To complete the preparation of the unit for the thermal force cycle, all the instrumentation was connected to the respective readout equipment.

3.3.3.2.3 Test Cycle Conduct

The test cycle required a total of 280 hours to complete. The cycle, as used on previous development units, consisted of a heat up to 1550°F with a 32 hour hold at this temperature for insulation material conditioning, followed by a cool to and hold at 1285°F for the determination of thermal performance. This unit was then cooled to 900°F during which a phase change occurred so the unit was reheated to 1140°F and held at this temperature for 28 hours to convert the formed alpha phase back to gamma phase. The unit was then cooled at a faster rate to ambient temperature, but some alpha phase transformation was again observed.

Figure 91 presents the temperature and power input versus the cycle time. Plotted on this figure is the average emitter plate temperature, and the temperature at the bottom of the heater block. Figure 92 presents the average load measured in each tension rod versus the cycle time. The average rod load was determined by averaging the loads as determined by each of the strain gauges on a given tension rod. At times during the cycle bending loads were apparent as one strain gauge would indicate a higher load than the other strain gauge on the same tension rod.

During the first two hours of the test, the load in the tension rods increased from an average initial starting point of 300 pounds (preload) to approximately 400 pounds. The tension rod loads then decreased to approximately 350 pounds and remained steady until 40 hours TAT (Total Accumulated Time) when the emitter plate temperature had reached 630°F. From 40 hours TAT to 47 hours TAT, the tension rod loads steadily increased to 470 pounds. At 45 hours, the strain gauges on tension Rods No. 2 and No. 3 became inoperative, however, the strain gauges on tension Rod No. 1 remained fully operational performing throughout the entire test.

FIGURE 91

FIGURE 92
(967-68)

From 47 to 52 hours, the rod load dropped off sharply to 250 pounds. This is a definite indication that the shield was changing phase from gamma to alpha. The emitter plate temperature went from 870°F to 1023°F during this time period. At 52 hours TAT, the tension rod load started to increase sharply until it reached 600 pounds at 59 hours TAT with an emitter plate temperature at this time of 1135°F. This increase in rod load is attributed to the change in the previously produced alpha phase back to the gamma phase with a subsequent increase in shield dimensions. From 59 hours to 74 hours TAT, the rod loads increased at a lower rate resulting in a rod load of 730 pounds. At 68 hours, the emitter plate was approximately 1285°F with the spider only 16°F higher in temperature. The expected rod load at 1285°F under the test conditions measured at 68 hours TAT would be the sum of the following: Preload = 300 pounds, load due to angle tolerance = 200 pounds, load due to emitter plate - spider temperature difference (Figure 89) = 1000 pounds. Total load that should result from test conditions is approximately 1500 pounds. It can be seen that the greatest amount of expected load resulted from the spider temperature being only 16°F higher than the emitter plate temperature, whereas the design considered that the spider would be 145°F higher than the emitter. From the above calculation of the expected load at 68 hours TAT (1285°F emitter), and the actual measured load of approximately 660 pounds, it is apparent that the rods do not experience the loading that should be expected under the test conditions. A discussion is presented in the test conclusion as to why the rod loads deviated from expected.

From 47 hours until 90 hours TAT when the emitter plate reached 1550°F, the load in the rods continued to decrease at a steady rate resulting in a load of approximately 525 pounds at 90 hours TAT. While holding the emitter at 1550°F, the rod load continued to drop until it reached approximately 250 pounds at 110 hours TAT. The rod load held fairly steady at approximately 250 pounds until the power was turned off at 122 hours TAT to allow the emitter plate to cool to 1285°F. At 1550°F, the spider was only 65°F higher in temperature than the emitter plate. For the design it was expected that the temperature of the spider would be 180°F higher than the emitter plate.

While cooling from 1550°F to 1285°F, the load in the rods dropped off to an indicated average of approximately 50 pounds. It is somewhat questionable at this low indicated load as to whether the rods were loose or not due to the accuracy of the strain gauges which is judged not to be better than ± 50 pounds at this temperature.

The emitter plate temperature reached 1285°F at 140 hours TAT and was maintained at this temperature for 27 hours (167 TAT) when the power was turned off to start the cool down. When the unit had cooled to 942°F emitter plate temperature (196.5 TAT), the slope of the cool down curve decreased indicating a phase change was starting to occur. At 203 hours, the emitter plate temperature leveled off at 915°F and remained at this temperature until approximately 208 hours when the temperature began to decrease.

An approximation of the amount of phase change (gamma to alpha) that occurred can be calculated as follows:

Approximate heat loss at 915°F assuming heat loss is linear with temperature.

$$\frac{915^{\circ}\text{F} - 100^{\circ}\text{F}}{1285^{\circ}\text{F} - 100^{\circ}\text{F}} \times 75 \text{ Watts} \times 3.41 \text{ Btu/Hr.-Watt} = 174 \text{ Btu/Hr. at } 1285^{\circ}\text{F}$$

Cool down rate prior to phase change

$$\frac{1000^{\circ}\text{F} - 950^{\circ}\text{F}}{195.8 \text{ Hr.} - 190.8 \text{ Hr.}} = \frac{10^{\circ}\text{F}}{\text{Hr.}}$$

Cool down rate during first portion of phase change

$$\frac{936^{\circ}\text{F} - 915^{\circ}\text{F}}{202.2 \text{ Hr.} - 197.0 \text{ Hr.}} = \frac{4.04^{\circ}\text{F}}{\text{Hr.}}$$

Heat generated during initial phase change

$$\frac{10^{\circ}\text{F/Hr.} - 4.04^{\circ}\text{F/Hr.}}{10^{\circ}\text{F/Hr.}} \times 174 \text{ Btu/Hr.} \times 5.2 \text{ Hr.} = 540 \text{ Btu}$$

Heat generated when temperature remained constant

$$174 \text{ Btu/Hr.} \times (208 \text{ Hr.} - 202 \text{ Hr.}) = 1047 \text{ Btu}$$

$$\text{Total heat generated} = 540 + 1047 = 1587 \text{ Btu}$$

Heat of transformation

$$\frac{1587 \text{ Btu}}{250 \text{ Pounds}} = 6.35 \text{ Btu/lb.}$$

$$\text{Percent transformed} \frac{6.35}{13.8} \times 100 = 46\%$$

From the above approximate calculations, it can be seen that this normal cooling of the radiation shield ($\sim 10^{\circ}\text{F/Hr.}$) resulted in about 46 per cent of the shield being transformed to the alpha phase.

In an attempt to provide an all gamma phase shield after cool down, the unit was heated to 1150°F which is above the transformation temperature and held for approximately 27 hours to assure that the previously produced alpha phase would be transformed back to gamma phase. The unit was then allowed to cool normally to 1050°F when the insulation space (vacuum) was back filled with argon to increase the unit heat loss and subsequently provide a faster cool down rate. Even with an argon back fill, the cool down

rate (40°F/Hr.) was not sufficient to allow the shield to cool without some alpha transformation. The calculated transformed percentage of alpha phase was 55% when calculated by the same approximate method as presented above for the first cooldown.

3.3.3.2.4 Post Test Disassembly

At the conclusion of the test with the unit at ambient temperature, the vacuum feedthrough and each receptacle extension was removed from the unit thus exposing the spherical washers and female tension rods. The anti-rotation pins were removed and it was determined that all three tension rods were loose by using a screwdriver type tool and turning the rods slightly in a clockwise direction. It could not be determined with accuracy how much each rod was loose, however, it was determined that all three rods were loose.

The female rods were threaded off the male rods and removed from the unit. It was observed that some strain gauge wires were slightly damaged in the area where the rod passes through the bottom of the spherical washer.

The spherical washers were loosened by removing only one of the centering pins on each washer. The remaining two pins on each washer were left in place attached to the receptacle wall. For future assembly at the same rod angle, the spherical washers were located using the two remaining pins in each receptacle. The spherical washers and the load washers were removed from the receptacle. The thickness of the load washers was measured and compared to the installed measurements determining that there was no appreciable decrease in thickness.

3.3.3.2.5 Conclusions Drawn From the First Thermal Force Cycle

The conclusions drawn from the first cycle on unit B10-Q1 can be summarized as follows: The temperature of the spider in relation to the emitter plate was considerably less than that assumed in the design, the measured loads in the tension rods did not correlate with the loads expected at the test operating temperatures, and the radiation shield was not cooled fast enough to prevent a partial gamma to alpha transformation.

The smaller than design temperature difference between the spider and emitter plate has the effect of increasing the load in the tension rods as shown in Figure 89. As the temperature of the emitter plate increases it is apparent that the difference between the spider and emitter plate temperature must become greater in order to result in a neutral rod condition. During this test, it was observed that the spider was 65°F hotter than the emitter plate with the emitter plate at 1550°F as well as at 1285°F under steady state conditions.

After the tension rods reached a maximum loading of 740 pounds the indicated loads began to decrease. The events that could possibly account for the load loss are as follows: relaxation of the load washers at high load, creep of the tension rods at high load, and/or creep of the radiation shield.

3.3.3.3 Second Thermal/Force Cycle - Unit B10-Q1

The purpose of this test was to determine the tension rod load profile and temperature of the spider in relation to the temperature of the emitter plate while subjecting the unit to a thermal cycle to simulate a fueled unit with an installed T/E generator. A secondary purpose of this test was to determine if the radiation shield could be cooled at a rapid enough rate to prevent the formation of the alpha phase.

3.3.3.3.1 Unit Closure

The damaged strain gauges on the female tension rods were repaired for the second cycle. A protective epoxy coating was applied over all the strain gauges. To prevent reoccurrence of damage to the strain gauge wires, the spherical washers were rebored to a diameter of .382 inch from the original inside diameter of .358 inch.

Three stainless steel washers were made to replace the load washers. These thicknesses duplicate the thickness of the removed load washers. The washers were adhered to the respective spherical washers with four spot tacks of epoxy on each washer at the edge. There was no epoxy between the mating surfaces of the stainless steel washers and spherical washers.

The spherical washers were installed in their respective receptacles being located by the two remaining pins in each receptacle from the first cycle. The third pin was then installed in each receptacle thereby securing the spherical washer to the receptacle. The female tension rods were threaded onto the male tension rods and sequentially torqued in 5 in.-lb. increments to 23 in.-lbs.

At this point, the overall length of the tension rod assembly was measured assuming that the male tension rod had not changed length. The following overall rod lengths were determined: Rod No. 1 = 2.927; Rod No. 2 = 2.935; Rod No. 3 = 2.923. These lengths were less than that measured when the unit together for the first cycle, i.e.: Rod No. 1 = 2.937; Rod No. 2 = 2.943; Rod No. 3 = 2.938. This difference is caused by either or both of the following: the shield being in part alpha phase will be shorter thereby reducing the installed angle and making the rod length shorter, or creep in the male tension rod which could not be measured prior to the test.

The anti-rotation pins were installed on each tension rod and the unit was vacuum-sealed as described for the first cycle. A copper rod was installed in the neck tube area to simulate the T/E generator and the unit was turned to the vertical upside down position. The heater block and neck tube Min-K insulation was as installed for the first cycle as it had not been removed between cycles.

3.3.3.3.2 Test Cycle Conduct

The test cycle required a total of 217 hours to complete. The cycle consisted of a heat up to 1285°F to simulate the heat up of fueled unit. The unit was then held at operating temperature for 44 hours. Following the hold at operating temperature, the unit was heated to 1550°F and held for 37 hours to determine the effects of this conditioning temperature on the rod loads. After conditioning, the unit was cooled to and held at operating temperature for seven hours and then cooled to ambient temperature.

Figure 93 presents the temperature and power input versus the cycle time. Plotted on this figure is the average emitter plate temperature, average spider temperature and the temperature at the bottom of the heater block.

The unit was powered at 75 watts for the first two hours of the test when the power was increased to 150 watts for two additional hours before setting to the required power level of 215 watts at 4 hours total accumulated time (TAT). The power was continued at 215 watts until 44.5 hours TAT when the power was increased to 250 watts to more quickly bring the unit to operating temperature. At 44.5 hours, the emitter temperature had reached 1041°F. At 69.75 hours, the unit had reached an operating temperature of 1295°F and the power was reduced to 215 watts. The emitter plate was maintained at operating temperature (1285°F - 1295°F) by making required copper rod adjustments until 113.7 hours TAT when the power was increased to 300 watts to bring the emitter plate to an approximate 1550°F conditioning temperature which was reached at 139.45 hours TAT when the power was set to 275 watts. The unit was maintained at the conditioning temperature until 176 hours TAT when the power was turned off allowing the unit to cool to operating temperature (1285°F - 1295°F). Operating temperature was reached at 181.63 hours and the power was resumed at 225 watts maintaining the unit at operating temperature by copper rod adjustment until 187.54 hours TAT when the power was turned off to cool the unit to ambient temperature.

At 192.5 hours, the insulation system vacuum was broken back with argon to atmospheric pressure to increase the cooling rate. A phase change of the radiation shield was not apparent from the cooldown. A phase change would cause a change in cooling rate in the region 1000°F to 900°F. It is felt that the shield at ambient temperature was in the all gamma state and therefore useful for subsequent testing.

Figure 94 presents the temperature difference between the emitter plate and the spider versus the cycle time. The emitter reached a maximum of 50°F higher in temperature than the spider at 4 hours TAT. Between 4 and 10 hours TAT, the difference between the emitter and spider temperature decreased until both were at the same temperature. From 10 hours TAT until approximately 35 hours TAT, the spider temperature steadily increased over the emitter temperature with a 70°F difference being recorded. Between 35 and 45 hours TAT the trend reversed and the temperature difference between the spider and emitter was reduced to 55°F. From Figure 93 it is seen that the period 35 to 45 hours TAT was in the radiation shield phase

FIGURE 94
(1154-68)

change regime and this could account for the reverse in the temperature difference trend. From 45 hours TAT until the emitter reached operating temperature, the spider increased in temperature over the emitter until the temperature was approximately 100°F. This 100°F difference was steady while the unit remained at operating temperature and slowly increased to approximately 100°F temperature difference with the unit at 1550°F conditioning temperature with the copper rod in place.

Figure 95 presents the average load in each tension rod versus the test cycle time. Prior to applying power to the unit, the average rod loads were: Rod No. 1 = 225 pounds; Rod No. 2 = 207 pounds; Rod No. 3 = 250 pounds. During the first six hours of the test the rod loads increased to an average of approximately 380 pounds. This increase in rod load was caused by the emitter plate temperature being higher than the spider temperature. From 6 hours TAT to 18 hours (TAT) rod loads slowly decreased to an approximate average of 340 pounds. At 20 hours (TAT) there was an increase in rod loads followed by a decrease to approximately the same loads as were recorded at 18 hours TAT. At 35 hours TAT with the emitter plate temperature at 950°F the rod loads started to increase sharply reaching a maximum average load of: Rod No. 1 = 990 pounds; Rod No. 2 = 925 pounds; Rod No. 3 = 1040 pounds at 49 hours TAT. This increase in load was caused by transformation of the alpha phase which was in the shield during tension rod assembly resulting from the cooldown after the first cycle. The alpha phase is transformed to gamma phase with a corresponding dimensional increase which would cause rod tightness.

When the emitter plate was stabilized at operating temperature, the average rod loads had decreased to: Rod No. 1 = 915 pounds; Rod No. 2 = 885 pounds; Rod No. 3 = 960 pounds. While at operating temperature the rod loads continued to decrease until they reached an apparent leveling off at 107 hours TAT when the rod loads were: Rod No. 1 = 690 pounds; Rod No. 2 = 750 pounds; Rod No. 3 = 750 pounds. It is expected that some of the tension rod load loss was caused by the spider-emitter temperature difference becoming greater and that some of the load loss was a result of primary creep.

When the power was increased to 300 watts at 113 hours (TAT) to bring the unit to the 1550°F conditioning temperature, the tension rod loads initially increased slightly followed by a steady decline until approximately 165 hours (TAT) when the tension rod loads had apparently leveled off to: Rod No. 1 = 150 pounds; Rod No. 2 = 100 pounds; Rod No. 3 = 225 pounds. It is expected that this decrease in tension rod load was caused by primary creep while at 1550°F.

Upon cooling the unit to the 1285°F operating temperature, the tension rod loads decreased further resulting in what was considered a no load situation within the accuracy of measuring the tension rod loads.

3.3.3.3.3 Post Test Disassembly

After the unit was cooled to ambient temperature, the receptacle extensions were removed to allow access to the tension rods. The anti-rotation pins were removed and the female portion of the tension rod was threaded off

FIGURE 95
(1151-68)

the male portion of the rod. During rod removal, it was discovered that tension Rod No. 1 and No. 2 were forced against the top edge of the spherical washer (unit in vertical upright position). To remove these two rods, it was required to first remove the pins that locate the spherical washer in the receptacle to allow the spherical washer to move and relieve the binding. During removal of the rods, the strain gauges were damaged. With the female rods removed, it was observed that the male Rods No. 1 and No. 2 could not be moved through an arc or in the direction of the rod axis as was possible to do with Rod No. 3.

The insulation covering the spider and male rods was removed to completely expose the rods. The ball joint between the male tension rod and the spider was seized on Rod No. 1 and No. 2. The rods were loosened by taping on the side of the rod with a copper mallet allowing the rods to be removed from the spider. It is felt that the two argon backfills that the unit experienced led to some oxidation of the lubricant between the rod ball and the spider causing the rods to seize to the spider. Although argon was used, it is likely that a trace of oxygen was admitted to the unit during the backfill operation which utilized a plastic bag receiver between the K cylinder and the unit.

The male tension rods were inspected to determine the overall length and degree of bending. It appears that all the bending occurred in one plane which was common to the axis of the lock pin hole which is the axis of rod rotation when the unit is heated. On two of the rods, No. 1 and No. 2, all bending appeared to have occurred in the shaft directly adjacent to the spherical ball. Rod No. 3 also appears to be bent slightly along the entire rod length. The amount of bending recorded was as follows: Rod No. 1 = 2° - 16 minutes to 2° - 22 minutes, Rod No. 2 = 1° - 23 minutes, Rod No. 3 = 1° - 47 minutes to 2° - 18 minutes.

The overall length of the male rods was measured recording both the maximum and minimum lengths (length not equal due to bending). The results of the measurements were as follows:

	<u>Rod No. 1</u>	<u>Rod No. 2</u>	<u>Rod No. 3</u>
Before Test	1.9950	1.9945	1.9950
After Test	2.0038-2.0067	2.0023-2.0106	1.9997-2.0021
Average Elongation	.0102	.0119	.0059

This average elongation shows that primary creep occurred during the test as the rod loads as measured were not great enough to cause stresses greater than the proportional limit of the Inconel-625 rod material.

The Inconel-718 female tension rods were also measured showing that the female rods did not increase in length during the test.

3.3.3.3.4 Conclusions Drawn From the Second Thermal/Force Cycle

The spider - emitter plate temperature relationship measured during the test was not the same as the temperature relationship used in the calculations to determine the tension rod set angle. Calculations show that the spider - emitter temperature relationship measured will cause higher tension rod loads at operating temperature than the temperature relationship used in the unit design. A new tension rod set angle was calculated based on the measured temperature relationship.

The male tension rods experienced creep during the test, however, it was demonstrated that the rods were able to maintain loads of approximately 750 pounds at 1285°F and approximately 150 pounds at 1550°F. To reduce the rod creep to a minimum, the insulation conditioning temperature should be reduced to a temperature less than 1550°F.

The unit was cooled fast enough to prevent alpha transformation during the cooldown by using a copper heat transfer rod in the neck tube area and by back filling the unit with argon.

3.3.3.4 Third Thermal Force Cycle - Unit B10-Q1

The purpose of the two runs performed during this cycle was to determine that the tension rod set angle of 27° 11 minutes would provide adequately tight tension rods with the unit either at operating temperature or at ambient temperature. It was also desired to determine the temperature of the spider in relation to the emitter plate temperature and to determine the effects of conditioning the insulation materials at 1350°F and 1400°F. A secondary purpose was to determine if the radiation shield could be cooled at a rapid enough rate with a water cooled copper chill block to prevent the formation of alpha phase.

3.3.3.4.1 Unit Closure

The elongated male tension rods removed from the unit after the second thermal force cycle were replaced with new male tension rods. The spherical ball on each of the new male rods was lapped to the respective spider seat with the spider still mounted on the radiation shield. Following lapping, Molykote Type Z lubricant was applied to the mating surfaces of the rod and spider and the male rods were installed in the spider and secured with anti-rotation pins.

The multi-layer insulation which was previously removed to allow tension rod access was reinstalled over the spider end of the unit. Two chromel-alumel thermocouples were welded to the spider at Rod No. 2 location with the leads brought out as shown on Figure 90.

Two strain gauges of the type previously used were installed on each of the female tension rods on the straight diameter of the rod, 180 degrees apart to replace the damaged gauges. In addition, a thermocouple was mounted between the strain gauges. This installation of strain gauges and thermocouples was performed in the same manner as was done before the first thermal force cycle. The strain gauges were calibrated for both load and temperature.

The bottom enclosure head was installed and tack welded to the top enclosure head and the joint was vacuum sealed with epoxy. The female tension rods were installed at an angle of 27° 11 minutes to determine the required washer thickness needed to provide an overall rod length of $2.939 \pm .005$. The washer was fabricated and the female tension rod was reinstalled at 27° 11 minutes using the spacer washer. The tension rods were torqued in 5 in.-lb. increments to 23 in.-lb. to provide the required tension rod preload. The spherical washers were anchored to the receptacle by installing the required size pins between the spherical washer and the receptacle. These pins were epoxied to the receptacle to prevent movement. A chromel-alumel thermocouple was installed in the bore of each female rod to measure the temperature at the end of the male rod (rod junction temperature). With the thermocouple installed, the bore of each female rod was filled with quartz paper to reduce the heat loss and to hold the thermocouple in place. The anti-rotation pin was installed in the slot of each female rod and epoxied to the spherical washer. A chromel-alumel thermocouple was attached to the cold end of each female rod to measure this cold end temperature during unit operation. Receptacle extensions were epoxied to the enclosure head and all the instrumentation wiring was brought out of the unit through commercial vacuum feedthroughs. The unit was evacuated and leak checked with a helium detector resulting in an acceptable leak rate.

The heater block was installed in the unit and the emitter plate was bolted to the inner liner using 3M supplied anti-seize compound on the bolt threads. The inner liner was insulated with Min-K insulation in the same manner as was performed for unit B10-D4 (copper disk and stainless steel ring used). A thermocouple was installed on the bottom of the heater block to determine the temperature at this location during the heat up. Thermocouples were installed on the unit enclosure in the same locations as on unit B10-D4 and, in addition, a thermocouple was installed on the outer enclosure as close as possible to each receptacle extension. To complete the preparation of the unit for the third thermal force cycle, all the instrumentation was connected to the respective readout equipment.

3.3.3.4.2 Test Cycle Conduct - Run 3

The test run required a total of 216 hours to complete. The run consisted of a heat up to 1285°F to be equivalent to that conducted on unit B10-D4 and during the first thermal force cycle. The unit was held at operating temperature for 36 hours. Following the hold at operating temperature the unit was heated to 1350°F and held for 24 hours to determine the effects of this conditioning temperature on the tension rod loads. After conditioning, the unit was cooled to and held at operating temperature for 15.5 hours. Following the hold at operating temperature, the copper rod was installed in the neck tube area of the unit to simulate a T/E generator. The power was increased to 215 watts and the unit was held at operating temperature for 25 hours and then quick cooled to ambient temperature using a water cooled copper chill block.

Figure 96 presents the temperature and power input versus the cycle time. Plotted on this figure is the average emitter plate temperature, average spider temperature, and temperature at the bottom of the heater block.

FIGURE 96
(1205-68)

The unit was powered at 50 watts for the first 19 hours of the test when the power was increased to 100 watts and maintained at this level until 43 hours Total Accumulated Time (TAT). The power was increased to 150 watts and maintained at this setting until the emitter plate reached operating temperature at 65 hours TAT. The emitter plate was maintained at operating temperature (1285°F - 1295°F) by adjusting the input power level with a Variac until 103 hours TAT when the power was increased from 65 watts to 150 watts to bring the emitter plate to an approximate 1350°F conditioning temperature which was reached at 107 hours TAT when the power was reduced to 78 watts. The unit was maintained at conditioning temperature until 131 hours TAT when the power was turned off allowing the unit to cool down to operating temperature which was reached at 124.5 hours TAT. The power was then resumed at 73 watts and the unit was maintained at operating temperature. At 150 hours TAT the copper heat transfer rod was installed in the unit to simulate a T/E generator. With the copper rod installed the power was increased to 215 watts and the emitter plate was maintained at operating temperature by making the required copper rod adjustments.

At 175 hours TAT, the power was turned off and the heater block was removed from the inner liner and a 3M supplied copper chill block was installed in the inner liner. No phase change of the radiation shield was apparent. A phase change would have caused a change in cooling rate in the region 1000°F to 900°F. It is felt that the shield at ambient temperature is in the all gamma state, and therefore, useful for subsequent testing.

Figure 97 presents the temperature difference between the emitter plate and the spider versus the cycle time. At four hours TAT, the emitter plate was 32°F higher in temperature than the spider. This temperature difference reduced to 20°F, at 19 hours TAT, when the power was increased the trend reversed and the emitter again increased in temperature over the spider, reaching a 46°F at 22 hours TAT. The emitter plate-spider temperature difference again decreased until 43 hours TAT when the power was again increased causing the temperature difference to increase to 38°F at 45 hours TAT. After this time, the temperature difference decreased until the emitter plate was only a few degrees (0-6°F) higher in temperature than the spider. This temperature difference was maintained while the unit was held at operating temperature, and while the unit was held at the 1350°F conditioning temperature. Some change in the temperature difference was observed when the unit was heated to 1350°F and when the unit was cooled back to 1285°F. Installation of the copper rod to simulate the T/E generator at 150 hours TAT caused the spider to become approximately 45°F higher in temperature than the emitter plate. During Thermal Force Cycle No. 2, the spider was approximately 100°F higher in temperature than the emitter plate, while under the same operating conditions (i.e., copper rod in place).

Figure 98 presents the average load in each tension rod versus the cycle test time. Prior to applying the power to the unit the average rod loads were: Rod No. 1 = 400 pounds, Rod No. 2 = 320 pounds, Rod No. 3 = 255 pounds. During the first four hours of the test, the rod loads increased. This initial increase was caused by the emitter plate being higher in temperature than the spider. From 4 hours TAT until 19 hours TAT, the rod load decreased.

FIGURE 98
(1203-68)

At 19 hours, when the power was increased, the load in the tension rods increased. This increase also being caused by the emitter plate becoming higher in temperature than the spider. At 40 hours TAT, the tension rod average loads were relatively stable and were: Rod No. 1 = 425 pounds, Rod No. 2 = 325 pounds, Rod No. 3 = 225 pounds. At 46 hours (850°F emitter temperature) the loads in the tension rods began to decrease and finally reached a minimum load condition at 53.5 hours TAT (emitter plate temperature 1060°F) when the average loads in the tension rods were: Rod No. 1 = 212 pounds, Rod No. 2 = 137 pounds, Rod No. 3 = 34 pounds. This decrease in rod loading was caused by transformation of some of the initial gamma phase of the radiation shield material to alpha phase with a corresponding dimensional decrease. From 53.5 hours TAT until 66 hours TAT, the average load in the tension rods increased to: Rod No. 1 = 538 pounds, Rod No. 2 = 462 pounds, Rod No. 3 = 368 pounds. At 67 hours, the unit was at operating temperature and the power was reduced. The rod loads slowly decreased while holding the unit at operating temperature until at 99 hours TAT the rod loads were: Rod No. 1 = 436 pounds, Rod No. 2 = 380 pounds, Rod No. 3 = 290 pounds.

When the power was increased to bring the unit to conditioning temperature, the rod load increased, however, while at 1350°F the average load in each tension rod initially was approximately 40 pounds higher than the load at operating temperature. After the unit was cooled from 1350°F, the average loads in the tension rods at operating temperature were: Rod No. 1 = 400 pounds, Rod No. 2 = 360 pounds, Rod No. 3 = 284 pounds. It appears that 24 hours of conditioning at 1350°F caused the following approximate loss of load in each tension rod when comparing the loads at operating temperature before and after conditioning: Rod No. 1 = 36 pounds, Rod No. 2 = 20 pounds, Rod No. 3 = 6 pounds. These low losses in rod loads show that a 1350°F conditioning temperature is acceptable.

After the copper rod was installed in the unit, the tension rod loads remained relatively unchanged from the loads measured without the copper rod although the temperature difference between the emitter plate and the spider changed by approximately 50°F upon installation of the copper rod. Calculations show that if the spider-emitter plate temperature relationship is increased with the emitter temperature held constant, that the tension rod loads should decrease. Apparently, other factors which are not well understood are causing the rod loads to remain relatively stable. These factors could include the influence of the copper rod on the neck tube temperature profile and the influence of the copper rod on the mean temperature of the radiation shield.

Following the fast cooldown, the average rod loads were: Rod No. 1 = 370 pounds, Rod No. 2 = 385 pounds, and Rod No. 3 = 312 pounds. Comparing these loads with the starting rod loads, it appears that only Rod No. 1 lost any load (30 pounds), while Rod No. 2 and Rod No. 3 increased in load by 65 pounds and 43 pounds respectively. This increase in rod loading could be attributed to the fact that the shield may have had a small portion of the alpha phase resulting from the cooldown after the second thermal force cycle. The extremely fast cool down achieved during this run (Run No. 3) no doubt left the shield in the all gamma condition, and, therefore, could result in a small amount of increased rod load.

The following conclusions can be made from the third thermal force cycle - Run No. 3.

1. The tension rods maintained the initial preload while the unit was at operating temperature and when at ambient temperature after the test.
2. The tension rods were under load at all times during the run except during the fast cool period.
3. Conditioning at 1350°F for 24 hours does not cause a significant loss in rod load due to creep.
4. The radiation shield can be cooled rapidly with the copper chill block so to prevent the formation of alpha phase.

3.3.3.4.3 Test Cycle Conduct - Run 4

Run No. 4 of the third thermal force cycle required a total of 310 hours to complete. The run consisted of a heat up to 1285°F to simulate the heat up of a fueled unit. The unit was held at operating temperature for 25 hours before removing the copper rod which simulates the T/E generator. With the copper rod removed, the unit was held at operating temperature for an additional 19.5 hours. Following the hold at operating temperature, the unit was heated to 1400°F emitter plate temperature and held for 65 hours to determine the effects of this conditioning temperature on the tension rod loads. After conditioning, the unit was cooled to and held at operating temperature for 66.5 hours followed by a fast cool to ambient temperature using the water cooled chill block.

Figure 99 presents the temperature and power input versus the cycle time. Plotted on this figure is the average emitter plate temperature, average spider temperature, and the temperature at the bottom of the heater block.

The unit was powered at 75 watts for the first two hours of the test when the power was increased to 150 watts for two additional hours before setting to the required power level of 215 watts at 4 hours TAT. The power was continued at 215 watts until 45 hours TAT when the power was increased to 250 watts to more quickly bring the unit to operating temperature. At 45 hours TAT, the emitter plate temperature had reached 1081°F. At 67 hours TAT, the unit had reached an operating temperature of 1297°F and the power was reduced to 215 watts. The emitter plate was maintained at operating temperature by adjusting the copper rod as required until 92 hours TAT when the copper rod was removed and the power reduced. The emitter plate was maintained at operating temperature until 111.5 hours TAT when the power was increased to 150 watts to bring the emitter plate to a 1400°F conditioning temperature. The conditioning temperature was reached at 119 hours TAT when the power was reduced to a nominal 85 watts. Conditioning was continued until 184 hours TAT when the power was turned off allowing the unit to cool to operating temperature. Operating temperature was reached at 191.5 hours TAT when the power was turned on to a nominal 73 watts.

FIGURE 99
 (1206-68)

The unit was maintained at operating temperature until 257.5 hours TAT when the power was turned off and the heater block removed. A 3M supplied water cooled copper chill block was bolted to the inner liner to provide a fast cool down. No phase change of the radiation shield was apparent. A phase change would cause a change in cooling rate in the region 1000°F to 900°F. It is felt that the radiation shield was in the all gamma state at ambient temperature following the test.

Figure 100 presents the temperature difference between the emitter plate and the spider versus the cycle time. The emitter reached a maximum of 104°F higher than the spider at 6 hours TAT. After the maximum was reached, the temperature difference decreased until both the spider and emitter were at the same temperature at approximately 22 hours TAT. After this time, the spider was higher in temperature than the emitter plate finally achieving a difference of approximately 65°F just before the copper rod was removed at 92 hours TAT. On Thermal Force Cycle No. 2, the temperature was approximately 100°F while exposing the unit to the same heat up cycle. The reason for the difference between the spider-emitter plate relationship on this run and on Thermal Force Cycle No. 2 is not completely understood. Possible explanations include the relative tightness of the heater block in the inner liner for each test and the tightness of the fits between the spider shield and inner liner.

With the copper rod removed, the spider was 8°F to 12°F higher in temperature than the emitter plate for the remainder of the run except when heating to and cooling from the conditioning temperature.

Figure 101 presents the average load in each tension rod versus the test cycle time. Prior to applying power to the unit, the average rod loads were: Rod No. 1 = 370 pounds, Rod No. 2 = 385 pounds, Rod No. 3 = 312 pounds. During the first four hours, the rod loads increased and then they experienced a period of steady decrease until approximately 25 hours TAT when the tension rods became unloaded. The unloading of the rod was caused by the radiation shield being transformed to the alpha condition with the subsequent dimensional decrease and because the spider was continuing to become higher in temperature than the emitter plate which in general causes looseness. At approximately 36 hours TAT, the tension rods started to become loaded again. The emitter plate temperature at this time was 1026°F. The tension rod loads continued to increase until the unit reached operating temperature. The average rod loads at operating temperature with the copper rod in place to simulate the T/E generator were approximately: Rod No. 1 = 350 pounds, Rod No. 2 = 340 pounds, Rod No. 3 = 260 pounds. The average tension rod loads at operating temperature at 110 hours TAT before conditioning were: Rod No. 1 = 360 pounds, Rod No. 2 = 365 pounds, Rod No. 3 = 290 pounds.

After the unit was heated to the 1400°F conditioning temperature, the rod loads were: Rod No. 1 = 450 pounds, Rod No. 2 = 430 pounds, Rod No. 3 = 345 pounds. After 65 hours of conditioning at 1400°F (184 hours TAT) the rod loads were: Rod No. 1 = 387 pounds, Rod No. 2 = 371 pounds, Rod No. 3 = 290 pounds. It appears, therefore, that the rods apparently decreased in loading at the 1400°F conditioning temperature by approximately 60 pounds. Upon

FIGURE 101
(1204-68)

cooling the unit to the operating temperature, the average loads in the tension rods were: Rod No. 1 = 275 pounds, Rod No. 2 = 280 pounds, Rod No. 3 = 192 pounds. Comparison of the average loads in the tension rods before and after the conditioning show that approximately 85 pounds of load was lost during conditioning most likely by primary creep of the male tension rod.

At 257.5 hours, the unit was cooled quickly with the use of a water cooled chill block which was bolted to the inner liner. As soon as the Min-K insulation was removed from the inner liner, the load on the tension rods decreased to essentially zero load and did not return until the unit had cooled to approximately 300°F. This loss of rod load was caused by a sudden change in the inner liner temperature profile resulting in a shorter inner liner and, therefore, loose tension rods. As previously discussed, the cooldown was fast enough to prevent the formation alpha phase in the radiation shield.

After the unit was at ambient temperature, the average loads in the tension rods were: Rod No. 1 = 310 pounds, Rod No. 2 = 325 pounds, Rod No. 3 = 235 pounds. Comparison of these end of run loads with the starting loads in the tension rods reveals that each tension rod lost the following average load: Rod No. 1 = 60 pounds, Rod No. 2 = 60 pounds, Rod No. 3 = 77 pounds.

The following conclusions can be made from the third thermal force cycle - Run No. 4.

1. The tension rods maintained loading while the unit was at operating temperature and at ambient temperature at the conclusion of the run.
2. Conditioning at 1400°F emitter plate temperature for 65 hours resulted in an average tension rod load loss of 85 pounds due to primary creep. There is adequate preload so that the loss of 85 pounds load during conditioning is not critical and will not affect the performance of the unit.
3. The radiation shield can be cooled rapidly with the water cooled copper chill block so to prevent the formation of alpha phase.

3.3.3.5 Recommendation Resulting From Thermal Force Cycles

Based on the results of the thermal force cycles conducted on unit B10-Q1, it was recommended that the tension rods of the delivery units should be set at 27° 30 minutes.

The third thermal force cycle was run with the tension rods set at 27° 11 minutes. On Run No. 3, it was observed that the spider was only 45°F higher in temperature than the emitter plate with the copper rod in place to simulate a T/E generator. The uncertainty in selecting a tension rod set angle of 27° 11 minutes results from the fact that during the second

thermal force cycle while at operating temperature and with the copper rod in place, the spider was 100°F higher in temperature than the emitter plate. If this 100°F temperature difference should occur in the delivery units as it occurred during the second thermal force cycle, it has been calculated that the tension rod load at operating temperature will be reduced by about 350 pounds. This predicted reduction in load makes it somewhat questionable if the tension rods would be tight at operating temperature (1285°) with the 100°F higher in temperature than the emitter plate. To compensate for the calculated reduction in load at operating temperature of 350 pounds, it is recommended that the tension rod angle be set to produce 100 pounds more load at operating temperature so that if the 350 pound load is lost due to spider-emitter plate temperature difference, the tension rods would still have some load at operating temperature. The additional angle to be set to achieve the 100 pounds higher load was calculated to be 19 minutes. Setting the tension rod angle with plus 19 minutes will not change the tension rod loads at ambient temperature if a 100°F temperature difference is achieved between the spider and the emitter plate.

If the spider is only 45°F higher in temperature than the emitter plate on the delivery units, the result of setting the angle to 27° 30 minutes will be to have 100 pounds more rod load at operating temperature than achieved during the third thermal force cycle. If this extra load at operating temperature is lost by primary creep, the only effect would be that the tension rods would have 100 pounds less load when the unit was returned to ambient temperature. With the preload initially greater than 100 pounds, it is obvious that the tension rods would still be loaded at ambient temperature.

It was further recommended that the insulation materials be conditioned using 1400°F emitter plate temperature as the maximum unit temperature. Temperatures higher than 1400°F significantly increase the primary creep rate of the male tension rod material (Inconel-625) and would cause additional loss of load in the tension rods during conditioning.

3.4 HTVIS DELIVERY UNITS

During this contractual effort, a total of eight (8) High Temperature Vacuum Insulation System Delivery Units were fabricated and acceptance tested. The delivery units were identified as the series of B10-DL1 through B10-DL8. Where the B10 denotes an insulation system for the SNAP-21B program 10 watt thermoelectric generator. The DL indicates that the unit is a delivery unit, while the number indicates the individual unit number in the manufacturing sequence. All the delivery units were fabricated as specified in the Manufacturing Flow Plan (D-664079) using Quality Control procedures as presented in the Linde Quality Control Plan which was prepared to meet MIL-Q 9858A. The delivery unit configuration is presented on the unit assembly drawing (D-664034). All units were acceptance tested following fabrication as per the Acceptance Test Plan (Appendix J). Figure 102 shows the side view of a completed Delivery Unit (B10-DL2).

3.4.1 Unit Fabrication

As all the Delivery Units were constructed per the Manufacturing Flow Plan (D-664079), only a listing of the fabrication sequence applicable to the units is presented in this section as follows: 1. Quality Control inspection of 3M and Linde supplied components, 2. Preprocess insulation material and assemble insulation panels (D-664057), lap spider sockets with support rod male end (A-664078), Assemble Shield-Liner-Spider (D-664073), Install insulation on radiation shield (D-664057), fabricate bottom head sub-assembly (D-664071), weld enclosure heads on unit (D-664034), install tension rods - spherical washers and weld on seal-off plugs, perform unit leak rate check, condition insulation system, install getter and perform final unit seal-off.

3.4.2 Unit Acceptance Testing

The acceptance testing performed on a unit following fabrication is presented in the Acceptance Test Plan in Appendix J. The acceptance tests consist of leak rate test, envelope and interface test (dimensional), thermal test, and dynamic test. As all units had acceptable leak rates and the envelope and interface dimensions were within specifications, no further discussion on these tests is warranted. Because of the variation in thermal performance and some problems encountered during the dynamic testing, these tests are discussed in the next section.

3.4.2.1 Unit Thermal Testing

The delivery units were instrumented and the unit thermal performance tests were performed as specified in the Acceptance Test Plan (Appendix J). Table 29 presents a summary of the thermal performance of all the HTVIS units. The delivery unit measured heat loss range from a low of 47.7 watts to a high of 53.9 watts. After testing unit B10-DL6 with its low heat loss tested after an extremely long conditioning cycle in the Thermal Force cycle work, the thought was advanced that additional conditioning of the previous units would have reduced their heat loss. To test this theory,

FIGURE 102
COMPLETED HTVIS DELIVERY UNIT (B10-DL2)
(1467-68)

TABLE 29

SUMMARY OF HTVIS UNIT THERMAL PERFORMANCE

Unit Number	Unit Heat Loss at 1285°F Watts	Insulation Composition	Conditioning Time and Temperature While Evacuating	
B10-D1	50.2	45 layers nickel 60 layers copper 60 layers aluminum	Temperature rise from 1300°F to 1470°F in 88 hours	
B10-D2	47.7	45 layers nickel 60 layers copper 60 layers aluminum	46 Hours at 1550°F	
B10-D3	47.0	45 layers nickel 60 layers copper 60 layers aluminum	21 Hours at 1550°F	
B10-D4	42.9	105 layers copper 60 layers aluminum	33 Hours at 1550°F	
B10-DL1	48.1	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
B10-DL2	49.1	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
B10-DL3	50.6	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
B10-DL4	53.9	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
B10-DL5	50.8	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
B10-DL6	47.7	105 layers copper 60 layers aluminum	Overhaul of B10-Q1 used for thermal force cycles	
B10-DL7	53.1	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
B10-DL8	53.0	105 layers copper 60 layers aluminum	48 Hours at 1400°F	
	50.0	105 layers copper 60 layers aluminum	Additional 106 hours at 1400°F	

unit B10-DL8 was subjected to additional conditioning of 106 hours at 1400°F and it was found that the unit heat loss was reduced by 3.0 watts from the heat loss measured after the initial conditioning. The additional conditioning should, however, not be required as the operating unit in a TEG with a getter will in effect provide self-conditioning thus reducing the initially measured heat loss to a value which would be achieved by complete conditioning.

To ensure that the radiation shield would remain in the all gamma phase, the units were fast cooled following the thermal performance tests by installing a water cooled chill block in the inner liner cavity.

3.4.2.2 Unit Dynamic Testing

The unit dynamic testing (shock and vibration) was conducted as presented in the acceptance test plan (Appendix J), however, due to test machine malfunctions, units B10-DL1 and B10-DL3 were damaged. Only the first three HTVIS units were tested prior to system integration, however, most of the other units were dynamic tested in the 3M pressure vessel. Table 30 presents a summary of the dynamic testing on all the HTVIS units.

3.4.2.2.1 Dynamic Tests - Unit B10-DL1

The unit was shipped to Ogden Laboratories, Deer Park, Long Island, New York by common carrier truck for dynamic testing. The impactograph mounted on the unit was inspected upon unit arrival and it was determined that the unit has been exposed to some shocks in the plane perpendicular to the unit axis in the order of slightly less than 6 'g'. The shipping container is designed to limit the unit 'g' loading to 6 'g'.

The unit was removed from the shipping container and installed in the dynamic test fixture and was instrumented for heat up to operating temperature as per the Acceptance Test Plan (Appendix J).

After the unit was heated to 1285°F operating temperature, the copper rod used to simulate the T/E generator was installed in the unit and the power to the electric heaters was increased to 215 watts. Several adjustments were made with the copper rod until the unit maintained the 1285°F emitter plate temperature.

The unit in the test fixture was put on the vibration machine oriented to test the unit in the horizontal position on the Y-Y axis. The Y-Y axis represents the worst loading condition for the unit. Before the 3 'g' vibration test, the unit was subjected to 1/2 'g' vibration sweep from 5 to 50 Hz in 7-1/2 minutes to determine if the unit was tight in the fixture. It was found that the output acceleration measured on the enclosure shell of the unit in the Y-Y direction was the same as the 1/2 'g' input acceleration measured on the fixture and, therefore, it was concluded that the unit was tight in the fixture.

TABLE 30

SUMMARY OF DYNAMIC TESTS ON MODEL A (10 WATT) HTVIS UNITS

<u>Unit Designation</u>	<u>Preliminary Vibration Test At Ambient Temperature (One Axis)</u>	<u>Vibration Test At Operating Temperature</u>	<u>Shock Test At Operating Temperature</u>	<u>System Dynamic Tests in 3M Pressure Vessel</u>
B10-D1	Not Tested	Ogden 12-(18-21)-67 Passed	Ogden 12-(26-28)-67 Passed	-
B10-D2	Ogden 5-2-68 Passed	Ogden 8-28-68 Passed	Ogden 8-29-68 Passed	Sandia 10-68 Passed
B10-D3	Not Tested	Ogden 2-(21-22)-68 Passed	Ogden 2-23-68 Passed	Sandia 5-68 Passed
B10-D4	Not Tested	Ogden 3-25-68 Unit Failed - Suspected Test Machine Malfunction	-	-
B10-DL1	Not Tested	Ogden 12-6-68 Test Machine Damaged Unit	-	-
B10-DL2	Ogden 11-14-68 Passed	Fairchild 11-(22-23)68 Passed	Not Tested - Ogden Facility Not Operational	Sandia 1-69 Passed
B10-DL3	Fairchild 12-3-68 Test Machine Damaged Unit	-	-	-
B10-DL4	Not Tested	Not Tested	Not Tested	Sandia 1-69 Passed
B10-DL5	Not Tested	Not Tested	Not Tested	Sandia 3-69 Passed
B10-DL6	Not Tested	Not Tested	Not Tested	Not Tested
B10-DL7	Not Tested	Not Tested	Not Tested	Sandia 6-69 Passed
B10-DL8	Not Tested	Not Tested	Not Tested	Not Tested

Following the 1/2 'g' sweep, the unit was subjected to the 3 'g' vibration test as specified by the Acceptance Test Plan. The three 15 minute sweeps were completed on the Y-Y axis without incident. After each 15 minute sweep, the temperatures of the unit were checked to determine if the insulation system was operating. In case of the failure of a structural support (neck tube or tension rods), the loss of vacuum would result in a sudden rise of temperatures on the outside enclosure of the unit and a sudden drop in the emitter plate temperature. It was found after each vibration sweep on the Y-Y axis, that the temperatures of the unit were holding steady. It should be noted that during the three vibration sweeps on the Y-Y axis, the maximum acceleration of the unit measured on the outside enclosure between 40 Hz and 50 Hz did not exceed approximately 4.5 'g's which indicates that the acceleration measured on the outside enclosure was moderate.

Following the test on the Y-Y axis, the unit was oriented on the vibration machine for testing on the second horizontal axis (Z-Z axis). Testing the unit on the Z-Z axis is somewhat less severe on the unit as testing it on the Y-Y axis. The first sweep on the Z-Z axis was completed successfully. The temperatures of the unit were measured before and after the first sweep and were found unchanged.

During the second sweep on the Z-Z axis, the vibration machine dumped (machine malfunction resulting in a sudden stop) on the down sweep at 0.4 inch double amplitude, 7.6 Hz, and approximately 1.25 'g', causing a very severe shock to the unit (Figure 103). After the machine dumped, the temperature on the outside shell of the unit started to rise which indicated the unit had been failed.

Following the accident, the unit was removed from the vibration table, and an immediate investigation was undertaken to determine the cause of the machine malfunction.

First, it was determined that the machine would malfunction (dump) again without the unit. The machine was started up and was run between 5 Hz and 15 Hz at .6 inch double amplitude. The .6 inch double amplitude, with the unit removed from the machine is, equivalent to running the machine with .4 inch double amplitude with the unit on the machine. It was observed that the machine dumped again twice between 6 to 8 Hz frequency. This proved that the machine dumped which caused the unit to fail and that it was not vice versa, that is, that failure of the unit caused the machine to dump.

Secondly, the cause of the malfunction of the machine was investigated. While the machine was made to dump, the electronic controls of the machine were observed. It was found that the rectifying tubes which supply the plate voltage to the amplifier, were arcing and flashing. It was explained by Ogden's vibration test supervisor, Mr. H. Gollinger, that the controls on the machine are set up such that when flashing of the rectifying tubes occur, the machine will dump. It was concluded that the cause of the machine dumping was bad rectifying tubes.

END OF SECOND SWEEP
Z-Z AXIS

UNIT B10-DL1
11-6-68

3g/INCH

FIGURE 103
ACCELEROMETER TRACE DURING VIBRATION MACHINE MALFUNCTION
RESULTING IN FAILURE OF UNIT B10-DL1
(1456-68)

After the unit had been failed by the malfunctioning vibration machine, the unit was cooled down and the neck tube insulation removed for visual inspection of the neck tube. It was found that the loss of vacuum was due to buckling of the neck tube (Figure 104). The wrinkles on the neck tube indicated that buckling occurred due to a shock load.

In order to determine the magnitude of the 'g' loading and the time duration of the shock pulse which failed the unit, the machine was dumped again and the maximum acceleration and time duration of the shock pulse was measured. It was found that the maximum acceleration was 30 to 60 'g' and the time duration was 1.3 milliseconds. Since the unit is designed to fail at 10.8 'g's static loading, it is expected that the shock load obtained from the malfunction of the vibration machine would fail the unit.

3.4.2.2.2 Dynamic Tests - Unit B10-DL2

The unit installed in a HTVIS shipping container and sent by common carrier truck to Ogden Laboratories in Deer Park, Long Island, New York for dynamic testing. An impactograph mounted on the unit during transit revealed that the unit received a few shocks in the plane of the unit axis in the order of 4 'g'. Shocks recorded perpendicular to the unit axis were in the order of only 1 'g'.

Upon arrival at Ogden the unit was removed from the shipping container and installed in the test fixture. The unit was instrumented for an ambient temperature vibration test as presented in the Acceptance Test Plan (Appendix J). Prior to placing the unit on the machine head, the machine was run empty to determine that it was in acceptable operating condition and not subject to a malfunction which could result in a machine "dump".

The unit was placed on the vibration machine in the Y-Y axis (vibration perpendicular to unit axis with one tension rod in the plane of vibration). The unit was then vibrated at 1/2 'g' from 5-50 Hz without incident showing that the tension rods were indeed tight. The unit was then subjected to a specification sweep from 5-50 Hz in 7-1/2 minutes (3 'g' peak). It was noted that from approximately 40 Hz to 50 Hz there was a lot of high frequency accelerations recorded on the oscillograph indicating that the unit was perhaps loose in the test fixture. At the conclusion of the test, the unit neck tube was not damaged showing that the unit could withstand the specified loading without failure.

The test fixture with unit was removed from the vibration machine and the top plate of the test fixture was removed in an attempt to determine why the unit appeared to be loose in the fixture during testing. It was found that the top plate of the test fixture was not contacting the unit at the proper location which could have resulted in apparent looseness. A small amount of metal was removed from the fixture top plate to provide the desired ring contact near the neck tube opening in the unit. The fixture was then reassembled for the conduct of the operating temperature dynamic tests.

FIGURE 104

UNIT B10-DL1 - BUCKLED NECKTUBE CAUSED BY VIBRATION MACHINE MALFUNCTION Z-Z AXIS

To expedite the test schedule, Ogden Laboratories made arrangements with Fairchild Camera, Syosset, New York to perform the dynamic vibration test. The unit was moved to Fairchild while mounted on the test fixture. When at Fairchild, power was applied to the electric heaters at an accelerated rate. When the unit reached operating temperature, the copper rod used to simulate the T/E generator was installed per the Acceptance Test Plan.

While the unit was reaching equilibrium with the copper rod installed, the vibration machine was checked out to determine that it was in satisfactory operating condition. The machine was cycled from 5 Hz - 15 Hz - 5 Hz at .7 inch double amplitude, 5 Hz - 8 Hz - 5 Hz at .8 inch double amplitude, and then a specification sweep from 5 Hz to 50 Hz was run. During these check out runs of the empty machine, no problems were noted that would cause one to suspect that the machine would malfunction.

The unit was mounted on the vibration test machine and the vibration testing to specification was performed on all three axes as described in the Acceptance Test Plan. The unit successfully passed the vibration testing as evidenced by no significant increase in the enclosure temperature at the girth weld on the unit.

Following the successful vibration test, the unit was moved while at operating temperature back to Ogden Laboratories for the performance of the dynamic shock test. While calibrating the vibration machine to perform the shock tests by the "shaker-shock method" it was observed that the machine would malfunction resulting in 'g' levels being produced which were higher than specifications.

Because of the potential for the test machine to malfunction, it was decided (3M - Linde) not to conduct the dynamic shock tests and take the chance of damaging the unit due to excessive 'g' level input.

3.4.2.2.3 Dynamic Tests - Unit B10-DL3

When the unit arrived by common carrier truck at Ogden Laboratories the cover of the shipping container was removed and the unit neck tube was visually inspected and found to be in good condition. Because the Ogden Laboratory test machine has been subject to malfunctioning resulting in "burps" and "dumps" it was arranged by Ogden for the unit vibration test to be performed at Fairchild Camera, Syosset, Long Island, New York.

The unit was transported to Fairchild Camera in the shipping container. Upon arrival, the unit was removed from the shipping container and placed in the dynamic test fixture. The contact between the unit and the fixture was checked and the fixture bolts were tightened to 85 ft.-lbs. torque.

Before the unit was put on the vibration machine, the machine was run empty to calibrate the accelerometers and to determine if the machine was in good working order. Following the calibration of the accelerometers, the machine was run from 5 Hz - 15 Hz - 5 Hz at .7 inch double amplitude, from 5 Hz - 8 Hz - 5 Hz at .8 inch double amplitude, and from 5 Hz - 50 Hz at specification 'g' level (3 'g' maximum). The machine operated perfectly during these test runs. Particularly it was observed that the machine did not "burp" or "dump".

Following the test machine check out, the unit was mounted on the machine for the ambient temperature vibration test as per the Acceptance Test Plan (Appendix J). With the unit oriented for test in the Y-Y direction, the 1/2 'g' sweep was performed from 5 Hz - 50 Hz - 5 Hz. During this sweep, no amplification was recorded by the accelerometer mounted inside the neck tube indicating that the tension rods were indeed tight.

The test to specification was then started, with the cross-overs (changes from constant displacement to constant acceleration or vice versa) made normally by temporarily stopping the machine. At 40.5 Hz, the machine was stopped for a cross-over and the test personnel were looking at the oscillograph trace of recorded accelerations when suddenly the test machine "burped" and "dumped". This machine malfunction caused a shock load which buckled the unit neck tube. The oscillograph was not running when the machine burped, so consequently, the accelerations received during the machine malfunction were not recorded in a manner which could be accurately interpreted. Investigation directly after the unit neck tube was buckled, showed that the machine was on standby, meaning that the amplitude was turned to zero while the amplifier remained turned on. The machine operator was in the control room during the malfunction. The unit was removed from the machine to allow the empty machine to be checked out.

The following morning, the cause of the test machine "dumping" was discussed with Mr. Marvin Rosenberg, Fairchild's Environmental Laboratory Supervisor. It was Mr. Rosenberg's opinion that the machine "dumping" was caused by a surge in the power line, which went through the amplifier causing the machine head to move. The sudden and large movement of the machine head caused the amplitude protection device to trip, shutting down the amplifier and causing the machine to "dump".

Following the discussion with Mr. Rosenberg, the test machine was run to determine its condition. It was found that the machine "dumped" five times at .7 inch double amplitude - twice at 13 Hz and three times at 5 Hz. These dumps occurred while the machine was moving in contrast to the "dump" which caused the unit neck tube to buckle which occurred while the machine was not moving. The cause of the machine dumping while moving was attributed to the overheating of the amplifier and high humidity conditions by Fairchild personnel. A vent to the amplifier was opened to permit better cooling. The machine was started up again and run at .6 inch double amplitude, .65 inch double amplitude, and .7 inch double amplitude between 5 Hz - 15 Hz - 5 Hz without any further machine "dumping".

3.5 SHIPPING CONTAINER

The shipping container for transport of the Model A HTVIS units to the dynamic test location and for delivery to 3M Company was designed based on a suspension system recommended by Lord Manufacturing Company. The suspension system which utilizes four shear type rubber supports, is designed so that the HTVIS unit will not receive an excess of 6 'g' when the shipping container experiences a 4 inch flat drop (free fall) on any side or end of the container. The container, is fabricated with a metal frame covered with plywood, and has provisions for loading with a fork lift truck or a hoist.

Four shipping containers were fabricated per Linde Drawings (664048 - 664054). One of the containers is illustrated in Figure 105. Shipping container No. 1 was drop tested to determine that it would meet the contractual specifications, i.e., 4 inch flat drop on sides or ends shall not transmit greater than 6 'g' to the unit. The results of the drop tests show that the shipping container design is acceptable as the maximum 'g' level recorded for a 4 inch drop was only 4.75 'g'.

To perform the shipping container drop tests, a dummy unit was supplied by 3M Company to simulate an actual unit in terms of weight and configuration. This unit was installed in the shipping container and secured by the container bolted flange. Two accelerometers were used to instrument the unit and a quick release drop device was used to insure uniform non-jerking drops. The data recorded during the test is presented on Table 31.

FIGURE 105
HTVIS MODEL A (10 WATTS) SHIPPING CONTAINER
(94-68)

TABLE 31

SHIPPING CONTAINER DROP TEST DATAContainer No. 1

<u>Drop Direction</u>	<u>Drop Height Inch</u>	<u>Maximum 'g' on Unit</u>		<u>Remarks</u>
		<u>± 6 'g'</u> <u>Accelerometer</u>	<u>± 20 'g'</u> <u>Accelerometer</u>	
Vertical	1	2.0	2.5	Accelerometers mounted on top unit hold down flange. 'g' measured in vertical direction.
Vertical	2	3.0	3.25	
Vertical	3	3.25	4.5	
Vertical	3	4.0	4.0	
Vertical	4	4.25	4.5	
Vertical	4	4.75	4.75	
Vertical	4	4.5	4.5	
Vertical	4	4.75	4.75	
Vertical	4	4.75	4.75	
Vertical	5	5.0	4.75	
Vertical	6	5.5	5.25	
Horizontal	4	3.0	4.0	Accelerometer mounted on cylindrical section of shipping container at unit c.g. 'g' measured in horizontal direction.
Horizontal	4	3.5	4.5	
Horizontal	4	3.25	4.5	
Horizontal	4	4.5	4.5	
Horizontal	4	3.75	4.5	
Horizontal	6	5.5	5.0	
Edge drop on side	2	2.0	3.25	'g' measured in horizontal direction.
Edge drop on side	8	3.0	4.0	
Edge drop on base	8	2.75	2.0	'g' measured in vertical direction.

4.0

CONCLUSIONS AND RECOMMENDATIONS

As a result of the development work and unit fabrication performed on the High Temperature Vacuum Insulation System, there are a number of specific conclusions and recommendations that can be made to summarize the work. The conclusions are in the form of performance parameters or restrictions because of hardware product of the contract, while the recommendations suggest system design changes which would reduce the cost of the system while providing equivalent or superior performance.

Conclusions

- The HTVIS unit will withstand a shock loading of 6 'g' and vibration loading of 3 'g' (5-50 Hz) in any orientation.
- The thermal heat loss of the HTVIS unit is less than 54 watts while at a 1285°F operating temperature.
- The total weight of the HTVIS unit is less than 317 pounds.
- The stable thermal performance of the operating HTVIS unit is assured for a minimum of five years by the use of chemical vacuum getter.
- The operating HTVIS unit must be fast cooled when it is desired to bring to ambient temperature to prevent the biological shield from changing phase causing loose internal system components.
- The HTVIS unit shipping container will assure that the unit does not receive a loading greater than 6 'g' when the container experiences a 4 inch drop.

Recommendations

- The use of adjustable tension rods will eliminate the need for a critical tension rod set angle, will allow the use of tapered fits between the liner, shield, and spider in place of high tolerance fits, will allow assembly with the biological shield in any phase condition rather than the required gamma phase, and will eliminate the requirement for a fast cool down as the tension rods can be tightened at any temperature.
- The development of a method to install the insulation materials by machine will reduce the insulation cost and the calendar time required to fabricate a HTVIS unit.