OCT 17 1967

MASTER

OAK RIDGE NATIONAL LABORATORY

operated by

UNION CARBIDE CORPORATION
NUCLEAR DIVISION

for the

U.S. ATOMIC ENERGY COMMISSION

ORNL - TM - 1874

COPY NO. - 35

DATE - August 22, 1967

DESCRIPTION OF FACILITY RADIATION AND CONTAMINATION ALARM SYSTEMS INSTALLED IN THE BULK SHIELDING FACILITY, BUILDING 3010

J. A. Russell, Jr.

D. J. Knowles

1. ABSTRACT

Facility radiation and contamination alarm systems were installed in the Bulk Shielding Facility, Building 3010, to continuously and automatically monitor gamma radiation (by three gamma monitrons) and air contamination (by three beta-gamma air monitors) in the entire facility.

These instruments and other components in the network provide health physics monitoring information, sound local alarms when abnormal conditions occur, and indicate these conditions on central panel boards in the control room and in the ORR control room.

Operating personnel are first given warning when a caution level is detected by a monitron, constant air monitor, or mobile air monitor. A second warning is given when a high level is detected.

The building evacuation and containment systems operate automatically when two or more monitrons or two or more air monitors detect a high level of radiation or air contamination.

NOTICE This document contains information of a preliminary nature and was prepared primarily for internal use at the Oak Ridge National Laboratory. It is subject to revision or correction and therefore does not represent a final report.

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

fly

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

- A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or
- B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

PAGES 1 to 2
WERE INTENTIONALLY
LEFT BLANK

CONTENTS

	Page
1. ABSTRACT	1
2. INTRODUCTION	4
3. DESCRIPTION	4
3.1 System	4
3.2 Components	5
3.2.1 Panel Board	5
3.2.2 Monitron	6
3.2.3 Air Monitors	9
3.2.4 Indicator Module	12
3.2.5 Coincidence Module	13
3.2.6 Buzzer Module	14
3.2.7 Remote Indication	14
3.2.8 Air Whistle and Beacon Lights	16
3.2.9 Power Supplies	17
3.3 Drawings	18
3.3.1 Prepared by the Instrumentation and Controls Division	18
3.3.2 Prepared by the General Engineering and Construction Division	18
4. CHECKOUT AND OPERATING PROCEDURES	18

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

2. INTRODUCTION

The Bulk Shielding Facility (BSR), Building 3010, is one of 17 facilities at Oak Ridge National Laboratory being equipped with networks of radiation and air monitoring instruments connected to a central control panel in the building and to the Laboratory Emergency Control Center.¹ Facility radiation and contamination alarm systems were installed in Building 3010 to continuously and automatically determine the radiation condition of the entire facility and to report this information to a central control panel within the building. Should the radiation level or the air activity in a large portion of the building exceed preset values, an audible alarm in the building will be actuated, warning lights outside the building will flash, the building will be contained, and an alarm signal will be transmitted to the Emergency Control Center, Building 2500. An alarm is telemetered to the ORR control room by means of the BSR annunciator system. The operator can observe the BSR radiation monitoring panel by means of a closed-circuit TV system.

3. DESCRIPTION

3.1 System

The gamma radiation level is monitored by three monitrons located throughout the building (Table 1). Air is monitored for beta-gamma emitting particles by three constant air monitors located throughout the building.

Most of the required radiation monitoring instrumentation had been installed previously as personnel protection instrumentation with local audible and visible alarms. These instruments were connected to the facility radiation and contamination alarm systems without altering their local health physics functions by using auxiliary contacts within the instrument or by adding auxiliary alarm devices to the equipment. Each instrument is connected to an individual indicator module on the monitoring panel in the operating area. By means of three colored lamps, which normally give a dim light, an indicator module indicates the condition of the instrument to which it is connected; that is, a white lamp burns at full intensity if the instrument becomes inoperative, an amber lamp burns at full intensity if the caution-alarm level is reached, and a red lamp burns at full intensity if the high-alarm level is reached (Table 2). Any change in the intensity of any lamp in the indicator module is accompanied by a buzzer signal.

The high-level alarm outputs of the monitron indicator modules are connected to a coincidence module; the high-level alarm outputs of the three constant air monitors are connected to a coincidence module.

¹D. J. Knowles et al., Instrumentation and Controls Div. Ann. Progr. Rept. Sept. 1, 1963, ORNL-3578, pp. 37-40.

Table 1. Radiation and Contamination Monitors Installed in Building 3010

Location	Monitor Number
1. Facility Radiation Monitors ^{a,b}	
Pool East	1
Pool North	2
Pool West	3
2. Facility Contamination Monitors ^b	
BSR Control Room	1 ^c
Pool North	2 ^d
PCA Control Room	3 ^d

^aAll monitrons are ORNL model Q-1154B-13.

^bCoincidence of any two high-level alarms in the group causes automatic evacuation.

^cORNL model Q-1740B Mobile Air Monitor.

^dORNL model Q-2240B-4 Constant Air Monitor.

If a coincidence module receives a high-level alarm signal from any two or more constant air monitors or monitrons, the building evacuation system is actuated (See Table 1).

3.2 Components

3.2.1 Panel Board

The central panel board (Fig. 1) for the entire system, located in the control room, consists of a 12-module rack, a central control chassis, and a dc power supply. The 12-module rack contains an indicating module for each instrument, coincidence modules for the radiation alarm system and the contamination alarm system, remote alarm modules, a buzzer module, and a manual evacuation module. Indications of radiation, contamination, trouble, and evacuation alarms are transmitted to the ORR control room by means of the BSR annunciator system.

Table 2. Central Control Panel Alarm Indications for Monitrons and Air Monitors

Instrument Condition	Lamp Intensities		
	Red	Amber	White
Normal Operation	Dim	Dim	Dim
Caution Level ^a	Dim	Bright	Dim
High Level ^b	Bright	Bright	Dim
Instrument Inoperative	Dim	Dim	Bright
Instrument Removed ^c	Bright	Bright	Bright

^aCaution level is 1000 counts/min for a model Q-2240 beta-gamma air monitor and 2000 counts/min for a model Q-1740. Caution level is 7.5 mr/hr for a monitron.

^bHigh level is 4000 counts/min for a model Q-2240 air monitor, 10,000 counts/min for a model Q-1740 air monitor, and 23 mr/hr for a monitron.

^cLamp intensities remain until a maintenance connection is made, giving "inoperative" indication.

The racks and modules are made of anodized aluminum. The modules have anodized Metalphoto front panels. A Metalphoto text strip is provided at the top of each rack for instrument identification. The central control chassis contains manual switches, timers, relays, and monitoring equipment which are parts of the system but not built in modular form.

An auxiliary control panel, located on the west wall of the control room, operates the ventilation louvres and shuts down the air conditioners and fans to cause building containment when a high-level radiation signal is received from any one of the following: the facility radiation and contamination alarm systems, the exhaust duct monitor, a 12r/hr gamma monitor, or a pushbutton on the auxiliary panel (this panel and its function is described by drawings listed in Sect. 3.3.2).

3.2.2 Monitron

The Remote Monitron, ORNL model Q-1154B modified with an ORNL model Q-2359-12 high-alarm chassis (Fig. 2), is an ac-powered, null-type radiation detection instrument for monitoring gamma radiation. The monitron, as used in the facility

Fig. 2. Remote Monitron, ORNL Model Q-1154B.

radiation alarm system, consists of three basic units: (1) a control chassis, which contains the power supply, the main amplifier, a radiation-level indicating meter, and the controls; (2) a preamplifier and ion-chamber detector assembly which can be mounted on top of the instrument or mounted remotely up to 50 ft from the control chassis; and (3) an auxiliary contact-making meter relay mounted in the control chassis cabinet. Provisions are made at the rear of the cabinet for external alarms and meters.

The range of the meter is 0 to 25 mr/hr, and the calibrated accuracy of the meter is within 3% for gamma radiation. The zero setting may be checked by means of a pushbutton.

An alarm circuit is incorporated in the instrument which, when the set point is exceeded, rings a bell and lights a red lamp on the instrument. An external alarm contact is used to operate the caution-level radiation alarm in the system. The auxiliary meter relay provides a high-level alarm for the radiation alarm system. To reduce the danger of false alarms due to warm-up transients in the instrument, a 1-min time delay will not permit caution- or high-level alarm signals to be sent to the central alarm panel board until 1 min has elapsed after the monitron power supply has been energized.

The instrument and alarms operate as follows:

1. A power failure or a disconnected power cord will cause the white lamp on the central control panel to burn brightly and a buzzer to sound. After power is

restored and a 1-min delay for warm-up, the white lamp resets itself. During this 1-min delay, the caution-level alarm at the instrument might sound, but the remote caution- and high-level alarms are locked out and signals from them will not be sent to the central panel board.

2. If the caution level of 7.5 mr/hr is exceeded, an electronic alarm circuit causes a yellow lamp on the central panel to burn brightly, a buzzer on the central alarm panel to sound, a red light on the monitron to light, and a bell at the instrument to ring. The alarms are automatically reset at the instrument when the radiation level decreases below 7.5 mr/hr, but they must be reset manually at the central panel.

3. The 0- to 1-ma meter output terminals are connected to the accessory meter-relay, which is set to operate when the 23 mr/hr (high-level alarm) set point is exceeded. At 23 mr/hr, the bell at the instrument will be ringing (since it started at 7.5 mr/hr), the red lamp on the central panel will burn brightly, and the buzzer will sound. When the radiation level decreases to less than 23 mr/hr, the high-level alarm at the instrument will be reset automatically. The central panel alarm must be reset manually.

3.2.3 Air Monitors

Two types of air monitors are used in the system: an older model, the Mobile Air Monitor, ORNL model Q-1740 (Fig. 3); and its successor, the Beta-Gamma Constant Air Monitor, ORNL model Q-2240 (Fig. 4).

Mobile Air Monitor. -- This monitor consists of an aspirating system, a paper filter, a halogen-type Geiger-Mueller tube detector, a logarithmic count-rate meter, and visible and audible alarms. Any background radiation within the range of the instrument can be suppressed, and from one to five decades may be selected for display on a strip-chart recorder. This scale arrangement allows the instrument to accumulate air-contamination data while operating in areas where the background count is high.

A Model H, Leeds & Northrup Speedomax recorder with upscale, downscale, and set-point alarms indicates high radiation, instrument failure, and above-tolerance contamination, respectively. The local alarm circuit is so arranged that, if the air contamination increases to a point above the set point, an amber local annunciator light, indicating tolerance level, is actuated. At very high radiation conditions, an alarm bell and a red annunciator light are actuated simultaneously. The local annunciator lights are mounted on top of the instrument cabinet so that operation of the monitor can be observed from any position in the immediate area. A time-delay relay prevents remote alarms from operating until the instrument has warmed up after being turned on.

Beta-Gamma Constant Air Monitor. -- This monitor consists of an aspirating system, a paper-tape filter, a halogen-type Geiger-Mueller tube detector, a linear count-rate meter, a recorder, and visible and audible alarms. Air is drawn through the filter at 3 cfm (controlled manually) by a Roots blower. A sample of dust particles in the air is collected on the paper-tape filter. The sample tape is advanced automatically every 24 hours. The tape may be advanced manually at any time by the operator.

The detector counts the sample as it is being collected. The count-rate meter is a linear duty-cycle type utilizing a single range and having a high-voltage supply as an integral part. The normal range is 0 to 5000 counts/min, and ranges of 0 to 250, 0 to 1000, 0 to 10,000, and 0 to 25,000 counts/min at full scale may be obtained by relocating two jumper wires under the chassis. The input voltage sensitivity of the rate meter is 200 mv. The over-all accuracy of the rate meter, including the effect of long-term drift, is within 5%. The corona-regulated high-voltage supply is nominally 900 v with ± 150 v adjustment. The maximum load current is 20 μ a.

The rate meter has adjustable high-level and caution alarms and puts out a 1-ma full-scale signal to drive an integrally mounted Rustrak recorder. The caution alarm is adjustable over the range of approximately 2 to 58%, and the high-level alarm is adjustable from the caution-alarm set point to full scale. The caution alarm is an electronic circuit which employs a dual triode and plate relay with potentiometer adjustment. The relay is energized below the trip point and is de-energized by current transfer from one triode to the other by a diode that couples the cathode circuits. Hysteresis is approximately 4% of full scale. The high-level trip is accomplished by the high contact on a contact-making meter. The associated high-level relay is de-energized below the set point. When the set point is reached, the meter contacts and relay are locked in; these are released by depressing the reset pushbutton. A low-level pointer on the panel meter has no contacts and is used only as a visible indicator. The pointer should be set at the level corresponding to the caution-alarm set point.

The instrument has an alarm panel with four lights, a bell, and a buzzer. When the caution set point is reached, an amber lamp is lighted and the buzzer is energized. There is no switch to silence the buzzer, and the operator is expected to advance the tape when this point is reached. When the high-level trip point is reached, a red lamp is lighted and the bell rings. The bell can be silenced by a toggle switch, and when this is done, an amber neon indicator is lighted.

When the filter tape breaks, a red neon indicator is energized and the caution circuit is energized through a flasher. The amber neon bulb burns continuously, and the caution light and the buzzer come on intermittently. If a tape breaks and, at the same time, the caution alarm sounds, the tape-break neon light, the caution light, and the buzzer will be on continuously. A test pushbutton permits checking the alarm panel by simultaneously simulating tape break and high-level alarm signals.

Fig. 3. Mobile Air Monitor, ORNL Model Q-1740.

Fig. 4. Beta-Gamma Constant Air Monitor, ORNL Model Q-2240.

An auxiliary alarm chassis, mounted on the inside rear of the instrument, contains a meter-relay which when it indicates zero (no output) lights the instrument "inoperative" alarm on the central panel module.

The instrument and alarms operate as follows:

1. An accessory meter-relay, ORNL model Q-2311B-4, connected to the constant air monitor count-rate meter will cause the white "inoperative" light on the central panel to burn brightly whenever the meter pointer drops to zero (indicating no signal from the instrument) or when ac power is lost. After power is restored and a 60-sec delay, this alarm clears itself. During the 60-sec delay, local caution- and high-level alarms do not sound since they are locked out.

The mobile air monitor, ORNL model Q-1740, is equipped with an accessory chassis containing three relays. The accessory chassis signals an inoperative condition whenever the mobile air monitor recorder goes to zero or the monitor ac supply has been interrupted. A time delay relay prevents caution- and high-level alarms for 60 sec to reduce the danger of false alarms due to warm-up transients.

2. At the caution-alarm-level set points on a model Q-2240 or Q-1740 instrument, an electronic alarm circuit will cause a yellow lamp in the control room to burn brightly and a buzzer to sound. With an ORNL model Q-2240 air monitor, a buzzer will sound at the instrument and an amber lamp will burn brightly. With an ORNL model Q-1740 air monitor, a bell will ring intermittently at the instrument and an amber light will burn. Caution-level alarms are reset automatically when the filter is changed.

3. At the high-alarm level the panel meter relay on the instrument causes the red lamp in the control room to burn brightly and the buzzer to sound. The bell on the ORNL model Q-2240 instrument sounds and a red light on the instrument burns. The bell on the model Q-1740 instrument changes from an intermittent to a steady ringing and a red light burns. These alarms are reset by advancing or changing the filter and by pressing the manual reset button on the monitor.

3.2.4 Indicator Module

The indicator module, ORNL model Q-2563-1 (Fig. 5), consists of three independent transistorized channels, each operating an indicator lamp and providing a dc-voltage shift signal for alarm or control purposes and a voltage pulse signal for operating the buzzer module. The three lamps and a pushbutton are on the front panel. Each module is 35.8 mm wide, 120 mm high, and 125.8 mm deep. All connections are made at the rear edge of the plug-in module.

When the instrument connected to an indicator module is operating normally, all lamps on that module are dim (Table 2). When the module receives a signal that

Fig. 5. Indicator Module, ORNL Model Q-2563-1.

the instrument is operating abnormally or that the caution-level or the high-level alarm values have been exceeded, the lamps burn at full intensity: white for inoperative instrument, yellow for caution level, and red for high level. A signal is also generated by the module which causes a buzzer to sound. The white lamp indication will remain until the condition causing the alarm is cleared, at which time the lamp will return to the dim condition. The red and amber lights will remain bright until they are manually reset by means of a pushbutton on the indicator module. If the indicator module is reset when the alarm or abnormal condition still exists, the lamps will momentarily become dim when the reset button is depressed, and then will become bright and the buzzer will sound again when the reset button is released.

All ORNL model Q-2563-1 series indicator modules have identical circuits and can be interchanged or replaced without alteration.

3.2.5 Coincidence Module

The coincidence module, ORNL model Q-2563-2 (Fig. 6), consists of one transistorized circuit which accepts a dc-shift signal from as many as six indicator modules. The circuit can be adjusted by internal jumper connections to operate a relay for alarm or control purposes on any combination of one to six input signals. All coincidence modules at Building 3010 are arranged to operate the relay when there is a coincidence of any two alarms. Each module is 35.8 mm wide, 120 mm high, and 125.8 mm deep. All connections are made on printed strip connections at the rear edge of the plug-in module.

All three air-monitor indicator modules are connected to a coincidence module, and the monitron indicator modules are connected to a coincidence module. When two or more of the monitron indicator modules, or two or more air-monitor indicator modules, receive high-level alarm signals, the associated coincidence module will actuate the building warning and evacuation equipment, cause the building to be contained, and will transmit a signal to the Emergency Control Center, Building 2500.

A red lamp on the affected coincidence module will indicate which set of instruments has detected an abnormal condition. When the indicator modules showing an abnormal condition are reset manually, the coincidence module will also be reset.

All coincidence modules are identical and can be interchanged or replaced without alteration, except for an internal jumper connection which determines the number of coincidental input signals required for an output signal.

3.2.6 Buzzer Module

The buzzer module, ORNL model Q-2563-4 (Fig. 7), consists of a transistorized trigger circuit that operates a silicon controlled rectifier to actuate a buzzer when a voltage shift pulse is received from an indicator module. The buzzer module is the same size as all other modules and is interchangeable with other buzzer modules.

The buzzer module gives an audible notice that an indicator module has received any one of three input signals. The buzzer module, which serves all indicator modules, is reset by a pushbutton on its front panel.

After being reset, the buzzer will sound again whenever an input signal is received by one of the indicator modules. For example, a change from a normal condition to a caution-alarm level at some location will start the buzzer. After it is reset, a change to high-alarm level or to inoperative instrument will start the buzzer again.

3.2.7 Remote Indication

Abnormal radiation levels in the BSR are indicated in the ORR control room. A monitron, not a part of the facility radiation and contamination alarm systems, measures the radiation level in the BSR high bay. The radiation level is indicated on a meter on the BSR remote console. Similarly, the radiation level measured by a 12r/hr instrument in the high bay is indicated on a meter on the BSR remote console. High-level alarms from one of these instruments or from an instrument monitoring the radioactivity of the building ventilation outlet will operate the building containment system.

Fig. 6. Coincidence Module, ORNL Model Q-2563-2.

Fig. 7. Buzzer Module, ORNL Model Q-2563-4.

Any alarm on the facility radiation and contamination alarm systems will operate an annunciator in the BSR control room. If the reactor control system is in the "remote" position, a buzzer and light in the ORR control room signals an abnormal condition, and the operator can inspect the BSR control panel by means of closed-circuit TV.

3.2.8 Air Whistle and Beacon Lights

Air Whistle. -- When a coincidence module has been energized by two or more monitrons or air monitors, an air whistle is actuated by a nitrogen gas bottle to notify the building occupants to leave the building. The air whistle, a "Clarion Whistle" by Westinghouse Air Brake Company, will sound about 4 min on one filled gas bottle. A control box for the whistle contains a pressure valve, pressure switches which monitor tank and regulated pressures, and a solenoid valve that is opened by an electrical signal from the coincidence module. A momentary signal will open the solenoid valve, and the valve will remain open until it is closed manually by pressing the mushroom head of the valve stem inward.

Two standard high-pressure gas bottles filled with oil-pumped nitrogen to a pressure of approximately 1800 psi are connected to a manifold through isolating valves to the control box. Normally the valves are set so that one tank supplies the system; the second tank is valved off as a standby supply. The valve arrangement permits replacement of an exhausted tank with a filled tank without disturbing the operational status of the horn alarm assembly.

The normal gas pressures for proper operation of the whistles are not less than 1000 psig tank pressure and 80 to 120 psig line pressure to the solenoid valve. Abnormal pressures are indicated by red lamps (labeled "horn trouble") on the central control panel board, one lamp for each whistle. A dim lamp indicates normal pressures, and a bright lamp indicates abnormal pressures. Inspection of the gages will indicate whether the tank pressure or the line pressure is abnormal.

Beacon Lights. -- Federal Sign and Signal Corp., model 27S-110-v beacons with a magenta colored lens are installed on the corners of the building to warn personnel outside that the building has been evacuated. These beacons are actuated by a signal from a coincidence module, and they are automatically stopped when the coincidence module has returned to a normal condition.

Control Switches. -- A key-operated switch, labeled "normal-disable," on the central control panel board may be used to disconnect the air whistles and beacons during maintenance or abnormal operation periods. Since the Emergency Control Center receives an alarm signal when the switch is moved to the "disable" position, the Control Center should be notified before the switch is set at this position. They may be contacted by telephone by calling extension 3-6646.

A large red pushbutton on the central control panel (Fig. 8), labeled "manual evacuate," actuates the air whistle and beacons, transmits an alarm signal to the Emergency Control Center (if the Center has not already received an alarm), and causes the building to be contained regardless of the position of the "normal-disable" switch. If the manual evacuation pushbutton has been used, it must be reset by pressing the "reset" pushbutton on the module to restore the system to the normal conditions. Remote manual evacuation pushbuttons are provided on the BSR control panel and on the remote BSR control panel in the ORR control room.

The evacuation whistle may be silenced momentarily by pressing a pushbutton on either the BSR control panel or the remote BSR control panel. The whistle will remain silent as long as the pushbutton is pressed, and will continue to sound when the pushbutton is released.

3.2.9 Power Supplies

The main power for the system is 120 v, 60 cycle, and is supplied from the building emergency power bus to the 24-v dc power supply and the monitoring instruments. The system power supply is rack-mounted on the central alarm panel.

The 24-v dc power supply is a regulated saturating core stabilized voltage unit. Green "power on" lamps on the control chassis and on the power supply panel will be brightly lighted to indicate that the power supplies are operating.

Fig. 8. Manual-Evacuate Module, ORNL Model Q-2563-16.

3.3 Drawings

3.3.1 Prepared by the Instrumentation and Controls Division

The Building 3010 Facility Radiation and Contamination Alarm System is described in the following ORNL Instrumentation and Controls Division drawings:

1. Q-2368-1 through -9	Instrumentation location and wiring diagrams.
2. Q-2563-1 through -4 and -16 through -19	Plug-In modules.
348 3. Q-1154B-1 through -14	Monitron.
4. Q-2359-12	Monitron high-level alarm.
CAPE 808 5. Q-2240-1 through -23	Constant air monitor.
6. Q-2311B-4	Constant air monitor instrument trouble box.
19- 7. Q-1740A-1 through -20	Mobile air monitor.
8. Q-2312-7, -8	Mobile air monitor instrument failure box.

3.3.2 Prepared by the General Engineering and Construction Division

1. E-10282-ED-005	Facility contamination and radiation alarm system, sheet 1.
2. E-10282-ED-006	Facility contamination and radiation alarm system, sheet 2.
3. E-20310-ED-007	Electrical schematic containment heating and ventilating, sheet 1.
4. E-20310-ED-008	Electrical schematic containment heating and ventilating, sheet 2.

4. CHECKOUT AND OPERATING PROCEDURES

Although the central alarm panel board serves as an aid in operating the facilities in the building, its primary purpose is to provide automatic radiation and contamination alarms required by radiation safety and control regulations. An "inoperative instrument" alarm and two levels of radiation alarms from each of the fixed-installation monitoring instruments in the facility are indicated on the central alarm panel. High-level alarm signals from these instruments actuate the evacuation alarm when the alarm limit is reached on two or more monitrons or two or more air monitors.

To utilize the indications efficiently, the instruments should be reset, the alarm signals should be cleared, and burned out lamps, horn pressure alarms, and other abnormalities should be corrected promptly. An alarm signal can be cleared by performing the following steps:

1. Press the reset button on the buzzer module. This permits the audible alarm to be sounded again if another alarm is actuated before the first alarm can be cleared.
2. Check conditions at the instrument and reset the instrument if required (air-monitor filter change or air monitor high-level alarm). The air-monitor "caution" and "instrument inoperative" alarms and all monitor alarms are self-resetting when the radiation level or trouble causing the alarm is removed.
3. Reset the module on the central alarm panel by pressing the button at the bottom of the module.

Whenever the local evacuation alarm is sounded in the facility, an alarm signal is indicated and sounded in the Emergency Control Center, Building 2500.

A key-operated "normal-disable" switch located on the central alarm panel can be used to prevent the system from causing unnecessary evacuation of the building or from sending false signals to the Emergency Control Center during maintenance or abnormal operating conditions. Since an alarm indication will show at the Emergency Control Center when the key-operated switch is in the "disable" position, the Emergency Control Center must be notified before the switch is operated (telephone 3-6646).

A procedure for checking the instruments and their indicators for proper operation and a sheet for recording the test results are given on the following pages.

FACILITY RADIATION AND CONTAMINATION SYSTEM CHECK-OUT PROCEDURE
BUILDING 3010

Test	Purpose and Procedure	Correct Operation
1. Preliminary	Prepare to test system.	
a. Disable evacuation portion of system	<ol style="list-style-type: none"> 1. Contact Emergency Control Center (phone 3-6646) and notify dispatcher of coming alarm. 2. Obtain clearance from the operator and have test announced on public address system. 3. Turn key switch to "Disable" and close valves on N_2 tanks for whistles. 	Disconnects evacuation whistles and beacon lights. Gives evacuation alarm signal at Emergency Control Center.
b. Check panel lamps	Examine all panel lamps.	All lamps are dim.
2. Facility Beta-Gamma Contamination System	Test all monitors individually (see checkout sheets for locations).	
a. "Inoperative" alarm	<ol style="list-style-type: none"> 1. Unplug instrument. 2. Plug in instrument. 	<p>Buzzer sounds and white lamp glows brightly. Buzzer can be reset, but lamp cannot be reset.</p> <p>After 1-min delay, white lamp will reset.</p>
b. "Caution" alarm	<ol style="list-style-type: none"> 1. Increase gamma count rate with source to caution-alarm level. 2. Remove source until the count rate is below caution level. 	<p>Buzzer sounds and yellow lamp glows brightly. Buzzer can be reset, but lamp cannot be reset.</p> <p>Yellow lamp can be reset.</p>
c. "High-Level" alarm	<ol style="list-style-type: none"> 1. Increase count rate with source to high-alarm level. 2. Remove source; reset instrument. 	<p>Buzzer sounds and yellow and red lamps glow brightly. Buzzer can be reset, but neither lamp can be reset.</p> <p>Yellow and red lamps can be reset.</p>
3. Facility Radiation System	Test all monitors individually (see checkout sheets for locations).	
a. "Inoperative" alarm	<ol style="list-style-type: none"> 1. Unplug instrument. 2. Plug in instrument. 	<p>Buzzer sounds and white lamp glows brightly. Buzzer can be reset, but lamp cannot be reset.</p> <p>After 1-min delay, white lamp will reset.</p>
b. "Caution" alarm	<ol style="list-style-type: none"> 1. Increase radiation level with source to 7.5 mr/hr. 2. Remove source until radiation level is less than 7.5 mr/hr. 	<p>Buzzer sounds and yellow lamp glows brightly. Buzzer can be reset, but lamp cannot be reset.</p> <p>Yellow lamp can be reset.</p>
c. "High Level" alarm	<ol style="list-style-type: none"> 1. Increase radiation level with source to 23 mr/hr. 2. Remove source until radiation level is less than 7.5 mr/hr. 	<p>Buzzer sounds and red and yellow lamps glow brightly. Buzzer can be reset, but neither lamp can be reset.</p> <p>Red and yellow lamps can be reset.</p>
d. Return system to normal	Turn key switch to "Normal."	Permits beacon lights and Emergency Control Center indicators to operate on alarm condition. Emergency Control Center alarms will reset.
4. Evacuation System	Check all features of evacuation system for correct operation.	A coincidence of two high-level alarms from Facility Contamination System or Facility Radiation System should operate the evacuation horn, magenta lights outside building should flash, and Building 2500 should receive earliest alarm light. Key-switch lockout of horn and lights, and gas tank pressure switch should also be tested.
a. Check for control output from coincidence alarm	<ol style="list-style-type: none"> 1. Turn key switch to "Disable" after contacting Emergency Control Center. 2. Check evacuation modules for radiation and contamination alarm systems. 	<p>Check Emergency Control Center. A radiation and contamination alarm should be noted there.</p> <p>A coincidence of two high-level alarms from Facility Contamination System or Facility Radiation System should operate the appropriate "Evacuation" module. Red lamps on appropriate module should be bright.</p>

FACILITY RADIATION AND CONTAMINATION SYSTEM CHECK-OUT PROCEDURE (Continued)

Test	Purpose and Procedure	Correct Operation
b. Check evacuation alarm equipment	a. Increase radiation at one air monitor to high-alarm level.	Red and yellow lamps on this module become bright and buzzer sounds. Reset buzzer.
	b. Increase radiation at second air monitor in same system to high-alarm level.	Red and yellow lamps become bright on second module and buzzer sounds. Red lamp on evacuation module becomes bright. Reset buzzer.
	c. Remove radiation sources.	Alarm lamps and buzzer may be reset. Evacuation alarm should reset automatically when either alarm is cleared.
	d. Different pairs of instruments should be used each time this test is made.	
	e. Repeat procedure with pairs of monitors in the Facility Radiation System.	Same results as above except Radiation Evacuation module is tested.
	1. Close valve on all horn N ₂ supply tanks (if not previously done in Part I).	
	2. Plug in horn trouble test box at horn control box.	
	3. Move key switch from "Disable" to "Normal."	Alarm lights at Emergency Control Center clear.
	4. Set two coincident "High-Level" alarms on the Facility Contamination System.	Buzzer, channel alarms, and coincidence alarm noted on central panel. Horns sound a short blast, alarm should indicate at Emergency Control Center, and flashing lights outside building should start. Horn trouble lights at central panel become bright. Low-line pressure and low-tank pressure lights show on test box.
	5. Reduce radiation levels to normal and reset alarm modules.	All modules clear, Emergency Control Center alarms clear, and flashing beacons stop.
	6. Reset horn solenoid valves manually; open tank valves until low-pressure alarms on test box clear.	Gas cylinder pressure gauges should show >1000 psi on tank side of regulator and between 80 and 100 psi on horn side. Neither high-pressure nor low-pressure alarms should show on test box. Horn trouble light becomes dim. All alarms in all locations should be clear.
	7. Test high-pressure alarm by raising pressure regulator setting in horn box to more than 110 psi.	Horn trouble light should be on. High-pressure alarm is indicated by test box.
c. Conclude test	8. Close tank valves. Set two coincidence alarms on Facility Radiation System.	Buzzer, channel alarms, and coincidence alarm noted on central panel. Horns sound a short blast, alarm should indicate at Emergency Control Center, and flashing lights outside building should start. Horn trouble lights at central panel become bright. Low pressure alarm lights on test box are lighted.
	9. Repeat step 5.	
	10. Repeat step 6.	
	11. Close valves on tanks and push manual evacuation button.	Same as step 4, except no buzzer, no channel alarms, and only a radiation (red) light appears at the central panel and at the Emergency Control Center.
	12. Reset manual evacuation button and repeat step 6.	End of test
	Return all controls and instruments to normal condition.	<p><u>Check List</u></p> <ol style="list-style-type: none"> 1. Key switch is in "normal" position. 2. No alarm lights on control panel of Emergency Control Center. 3. One gas tank at horn should have valves open, one should have valves closed. Regulator should be adjusted to 100 psi. 4. Notify Emergency Control Center and building personnel of end of test period.

FACILITY RADIATION AND CONTAMINATION ALARM SYSTEM CHECK SHEET

MONTHLY ☐
 QUARTERLY ☐
 ANNUAL ☐

BLDG: 3010
 CHECKED BY: _____
 DATE: _____

CONTAMINATION		INOP.	RADIATION			REMARKS
MONITOR	LOCATION	AC OFF	METER	CAUTION	HIGH	
CAM 1	BSR Control Room					
CAM 2	Pool North					
CAM 3	PCA Control Room					
RADIATION						
M 1	Pool East					
M 2	Pool North					
M 3	Pool West					

EVACUATION SYSTEM

MONITOR	LOCATION	EVAC.	CONTAIN	REMARKS
BETA-GAMMA CONTAMINATION				
CAM 1	BSR Control Room			
CAM 2	Pool North			
CAM 3	PCA Control Room			
Coincidence modules checked using station _____ with all other modules.				
GAMMA RADIATION				
M 1	Pool East			
M 2	Pool North			
M 3	Pool West			
Coincidence modules checked using station _____ with all other modules.				

*Manual evacuation checked: Local ☐
 Remote ☐

BEACON*	LOCATION	ON	ROTATING	HORN	LOCATION	ALARM LIGHTS		CYL.PRESS (PSID)	
						LOW CYL.	LOW HORN	HIGH HORN*	LOW HORN
1	Bldg. Corner SW			1	Bay Area				
2	Bldg. Corner NW								
3	Bldg. Corner NE								
4	Bldg. Corner SE								

ALARMS AT BLDG. 2500—KEY SWITCH DISABLED: Radiation _____ Contamination _____ Buzzer _____.

*Quarterly and annual checks only.

INTERNAL DISTRIBUTION

1. A. E. G. Bates
- 2- 3. J. D. Blanton
4. C. J. Borkowski
5. F. R. Bruce
6. G. C. Cain
7. W. R. Casto
8. J. A. Cox
9. R. A. Dandl
10. D. M. Davis
11. E. P. Epler
12. E. D. Gupton
13. C. C. Hall
14. C. S. Harrill
15. J. H. Holladay
16. T. W. Hungerford
- 17-18. D. J. Knowles
19. F. W. Manning
20. R. W. Peelle
- 21-22. J. A. Russell
23. G. S. Sadowski
24. L. E. Stanford
25. W. H. Tabor
26. K. W. West
- 27-28. Central Research Library
29. Document Reference Section
- 30-32. Laboratory Records Department
33. Laboratory Records, ORNL R.C.
34. ORNL Patent Office
- 35-49. Division of Technical Information Extension
50. Research and Development Division, ORO

EXTERNAL DISTRIBUTION

51. E. H. Cooke--Yarborough, Electronics Division, AERE,
Harwell
52. J. B. H. Kuper, Brookhaven National Laboratory
53. E. Siddall, AECL, Chalk River, Ontario