Emittance Measurement and Modeling for the Fermilab Booster

Xiaobiao Huang^{1,2}, S.Y. Lee^{1,3}, K.Y. Ng², and Y. Su¹

¹ *Department of Physics, Indiana University, Bloomington, IN 47405*

² *Fermi National Accelerator Laboratory, Box 500, Batavia, IL 60510*

³ *GSI, Darmstadt, D64291, Germany*

(Dated: December 12, 2005)

Abstract

Turn-by-turn beam profile data measured at the Fermilab Booster are studied. Lattice models with experimental accelerator ramping parameters are used to obtain the lattice functions for data analysis. We studied the horizontal and vertical emittance growth behavior in different stages of a Booster ramping cycle and its relation to the beam intensity. The transverse and longitudinal components in the horizontal beam width are separated by a fitting model which makes use of the different scaling rules of the beam momentum. We analyze the post-transition horizontal beam size oscillation based on a model where the longitudinal phase space mismatch has resulted from rf voltage mismatch during the transition energy crossing. We carried out systematic multi-particle simulation to show that the source of the vertical emittance growth is a combination of the random errors in skew quadrupole and dipole fields, and the systematic Montague resonance. The effect of random quadrupole field is small for the Fermilab Booster because the betatron envelope-tunes are reasonably far away from the half-integer stopband.

PACS numbers: 52.59.Sa, 29.27.-a, 95.75.-z

I. INTRODUCTION

Emittance evolution for space-charge dominated beams is one of many important topics in high intensity beam accelerators and storage rings (see Refs. [1–5]). Even a small percentage of beam loss in a high intensity accelerator can cause radiation and operation problems. It is imperatively important to minimize beam loss and understand the emittance evolution.

There are many sources that can cause emittance growth. In linacs, the emittance growth can arise from synchro-betatron coupling, halo formation induced by collective envelope-modes or structure resonances, etc. In circular accelerators, two of the most important candidates for the emittance growth are the half-integer stopband that can perturb the beam envelope-function [1, 2] and the Montague resonance [5]. There are many numerical simulation codes that can be used to study the mechanism of emittance growth. However, systematic emittance evolution experiments are few in circular accelerators. Cousineau and collaborators have carried out systematic emittance measurement of high intensity beams at the Proton Storage Ring (PSR) in Los Alamos National Laboratory and made systematic benchmarking of a space charge simulation code [6]. Her conclusion indicated that the half integer stopband played an important role in the emittance growth at the PSR.

There were no systematic emittance measurement for rapid cycling accelerators. The Fermilab Booster is a prototype of high power accelerator. It is a rapid cycling accelerator at 15 Hz. Currently, the Booster regularly delivers about 4×10^{12} protons per pulse, with 10-turn injection from a 400 MeV linac. The overall efficiency is about 83–85%. At higher number of injection-turns, the Booster encounters substantial beam loss as shown in Fig. 1 mainly at the beginning of the acceleration cycle.

The injection efficiency and the efficiency of transition energy crossing derived from the measured total charge is shown in Fig. 2. Note that the efficiency of adiabatic capture is about 92% for injection-turn less than 10, and decreases rapidly as the injection-turn increases. Since the injection efficiency is nearly independent of the injection-turn, the beam loss is most likely in the longitudinal phase space. Similarly, beam loss during the transition-energy crossing becomes more apparent when the injection-turn is larger than 10. In the near future, the Booster is required to deliver even higher proton flux for neutrino physics experiments.

This paper is intended to study the emittance evolution of the Fermilab Booster. The

FIG. 1: Total charge (CHG0, in 10^{12}) for data sets with 3, 5, 7, etc. injection-turns. Note that the notch of beam loss at about revolution-600 is created intentionally by kicking 3 bunches out to facilitate a gap for the extraction kicker. Transition energy loss is visible at the transition energy at about 9550-revolution.

ionization profile monitor (IPM) is used to measure the horizontal and vertical beam size revolution by revolution. The measured rms beam profiles and widths are used to deduce the emittances of the beam. Using the deduced emittances, we will construct a model to fit these data and examine the key ingredient in the Booster for generating these emittance growth.

We organize this paper as follows. Section II presents beam profile measurement and method of emittance deduction. We build a realistic lattice model to analyze measured IPM data and deduce the horizontal and vertical emittances and the rms off-momentum width [7–9]. Section III discusses the algorithm and results of multi-particle tracking simulation. The space-charge force of our model is based on the potential derived from a Gaussian beam-distribution, where the horizontal and vertical rms beam radii are updated in each revolution. We employ this particle tracking model to evaluate the effects of random errors in dipole, quadrupole, skew quadrupole fields on the beam emittances. Section IV presents conclusions and discussions.

FIG. 2: The injection efficiency is defined as the ratio of the total charge at revolution 5000 divided by the total charge at injection excluding the 3-bunches intentionally kicked out. Note that the injection is nearly independent of the injection-turn when the injection-turn is less than 10. The efficiency for transition energy crossing is defined as the ratio of the total charge at revolution 10010 and that at revolution 9010.

II. THE EMITTANCE MEASUREMENTS

IPM data for Booster (under event 17 of the Fermilab Accelerator Control system) were taken with various intensity levels on Feb. 3, 2005. The injected-turn numbers were varied from 2 to 18. The gate of the ionization profile monitor was about $1 \mu\text{s}$, or the measured profile was the average of about 52 bunches. The experimental condition for all data sets was the same as the normal operational condition. The corrector package (e.g. trim quadrupole) settings were recorded to build a realistic lattice model for lattice function calculation.

The profile data at each revolution is fit with a Gaussian plus polynomial model [10],

$$p(y) = a + by + A \exp\left(-\frac{(y - y_0)^2}{2\sigma_y^2}\right), \quad (1)$$

where y is transverse coordinate of a micro-strip and p is the reading of the strip. The separation of adjacent micro-strips is 1.5 mm for the Booster IPM. The parameter σ_y and y_0 are half rms width and central position of the beam, respectively. The calibration routine

with linear parameterization is used to compensate the systematic error of beam width due to the space-charge of the beam [10]. The calibration makes significant corrections for high intensity and small beam width cases. Thus the calibration is much more important for the horizontal beam profile, because $\beta_x \approx 6.5 \text{ m} \ll \beta_z \approx 20.5 \text{ m}$ and the dispersion $D_x = 1.8 \text{ m}$ at the IPM location. Figure 3 shows typical calibrated beam profile for the 6-turn injection at revolutions 500, 4000, 8000, 12000, and 16000 respectively.

FIG. 3: The measured vertical and horizontal beam profiles for 6-turn injection measured at revolutions 500, 4000, 8000, 12000, and 16000 are displayed from top to bottom respectively.

The rms beam width σ_y is related to the “emittance” by

$$\epsilon_{y,\text{rms}} = \frac{\sigma_y^2}{\beta_y}, \quad (2)$$

where $\epsilon_{y,\text{rms}}$ is rms emittance. The 95% emittance $\epsilon_{0.95}$ is $\epsilon_{0.95} = 6\epsilon_{\text{rms}}$. These relations can be directly applied to vertical data ($y \rightarrow z$). For horizontal data, the off-momentum width of the beam also contributes to the beam width. Assuming that the horizontal transverse phase-space distribution is un-correlated to the longitudinal phase-space distribution, we obtain

$$\langle x^2 \rangle = \langle x_\beta^2 \rangle + D^2 \langle \delta^2 \rangle, \quad \text{or} \quad \sigma_x^2 = \beta_x \epsilon_{x,\text{rms}} + D^2 \sigma_\delta^2, \quad (3)$$

where $\langle \cdots \rangle$ denotes ensemble average, $\delta = \Delta p/p$ is the fractional momentum spread, D is the value of the dispersion function at the IPM and x_β is the betatron part of the horizontal orbit, $\epsilon_{x,\text{rms}}$ is the rms horizontal emittance, and σ_δ is rms fractional off-momentum width. The transverse emittances decrease as the beam momentum is ramped up due to adiabatic damping. The normalized emittance defined as $\epsilon_n = \beta\gamma\epsilon$ is supposed to be conserved if non-conservative mechanisms are absent.

The charge signals were taken along with IPM data. Figure 1 shows the total charge for some data sets in the acceleration cycle. Note that loss occurs at the injection, and a small loss also occurs at high injection-turn after transition crossing. Beam-loss becomes very severe at injection turns larger than 12.

The transverse space-charge effect is characterized by the generalized space-charge perveance, defined as

$$K_{sc} = 2Nr_0/(\beta^2\gamma^3),$$

where N is number of protons per unit length and $r_0 = 1.5347 \times 10^{-18}$ m is the classical radius of proton. Taking a Gaussian beam distribution with $N = N_B/(\sqrt{2\pi}\sigma_s)$, where N_B is the number of particles in a bunch and σ_s is the longitudinal rms bunch length, we plot the space-charge perveance for a Booster cycle for the beam intensity with 10-turn injection in Fig. 4.

For emittance calculation in the entire cycle, we build the lattice model at 1 ms interval in the cycle according to the actual beam energy and the accelerator lattice setting. The lattice functions such as beta functions β_x, β_z , dispersion function D and transition gamma γ_t anywhere in the cycle are calculated with interpolation. Fig. 5 shows the change of these lattice functions in the cycle at IPM location.

The revolution-by-revolution beam width signal from the IPM is usually noisy. Since we are interested only in the average behavior, it is useful to filter out the high-frequency noises. We apply a 40-points low-pass digital filter with tune threshold 0.1 to remove such noises. Figure 6 shows the effects of the filter for the vertical mean-square beam size for 10-turn injection.

FIG. 4: The space-charge perveance parameter for an entire Booster ramping cycle for the beam intensity of 10-turn injection (total charge of $4.1\text{E}12$). The bunch length is derived from the total rf voltage (RFSUM) of the Booster cycle while the 95% longitudinal emittance is assumed to be $0.08\text{ eV}\cdot\text{s}$.

A. The Vertical Emittance

Since the transverse emittances are adiabatically damped as the beam-momentum increases, it is more convenient to study the normalized emittance. Figure 7 shows the normalized vertical rms emittance for two data sets with 4-turn or 12-turn injection respectively. We note the emittance starts with the same level ($2\pi\text{-mm-mrad}$) but follows different growth pattern for different intensities.

The normalized emittance grows rapidly in the first 4000 revolutions because of the space-charge effect and the growth rate is nonlinear and highly dependent on beam intensities. For the later part of the cycle (4001-17000 revolutions), except close to extraction, the growth is slow and linear. The cause of the later emittance growth is not likely the space-charge effect because the relativistic gamma is large enough in this region. Possible growth mechanisms are residual gas scattering, intra-beam scattering, or other mechanisms. We will treat the two growth periods separately with the first period (region A) from 70 revolution after injection to 4000-revolution and the second period (region B) from 4001-revolution to

FIG. 5: Lattice functions β_x , β_z , D_x at the IPM location and the transition γ_t normalized by the values at the first 1 ms, where $\beta_{x0} = 6.5$ m, $\beta_{z0} = 20.5$ m, $D_{x0} = 1.8$ m and $\gamma_{t0} = 5.48$. The change of these lattice functions arises from the effect of the DC dogleg-magnets (extraction chicane) and the trim quadrupoles.

FIG. 6: The raw (blue) and filtered σ_z^2 (red) for 10-turn injection are shown for comparison.

FIG. 7: The vertical rms emittance (dashed) and the normalized rms emittance (solid) in the entire cycle for 4-turn and 12-turn injection.

17000-revolution.

1. Linear growth region

The emittance growth in region B can be roughly considered as linear. However some data-sets may lose beam during the transition energy crossing and some have post-transition oscillation. We fit the pre-transition and post-transition regions to linear curves separately. The fitting curves are shown in Fig. 8.

The growth rate of emittance defined by

$$\alpha_z = \frac{\Delta \epsilon_z^n}{\Delta N}, \quad (4)$$

where N is the revolution number, is calculated with the slopes of the linear curves. The growth rates are shown in Fig. 9. The vertical normalized emittance grows about 1π -mm-mrad in 10^4 revolutions for normal working cycles of the Booster. The growth rate seems to be proportional to the injection-turns.

The growth rate due to residual gas scattering is estimated to be $\Delta \epsilon^n / (\epsilon^n \Delta t) = 0.008 \text{ s}^{-1}$ at the vacuum pressure of 100 nTorr, which is about 1.2×10^{-4} in 15 ms (or 10000 rev-

FIG. 8: Left: (Color) The normalized vertical rms emittance from 4001-revolution to 9200-revolution for all data sets with 2-turn injection to 18-turn injection. Right: (Color) The normalized vertical rms emittance from 11001-revolution to 16200-revolution for all data sets with 2-turn injection to 18-turn injection. Note 16-turn data set lost a big fraction of beam at transition and thus has smaller emittance here.

olutions). Thus the emittance growth can not be caused by the residual gas small-angle scattering. The growth rate due to the intrabeam scattering is estimated to be less than $\Delta\epsilon^n/\epsilon^n\Delta t \leq 0.001 \text{ s}^{-1}$ [11]. It is also difficult to see the growth rate of the emittance as large as $1 \pi\text{-mm-mrad}$ in 10^4 revolutions.

2. Space-charge dominated region

Space-charge effects play an important role in the first 4000 revolutions. Figure 10 shows the normalized vertical rms emittance in region A for all data sets. Note that with 12-turn injection or less, the emittance growth is relatively mild. The growth behavior for these data sets follows a similar pattern, which could be modeled. However, for intensity higher than 13-turn injection, the emittances grew and beam loss occurred in the first few hundreds of revolutions as shown in Fig. 1.

Since 1960's, emittance dilution due to space-charge has been a subject of intensive studies, the exact emittance growth mechanism is not clear, and may even be different in each accelerator. A popular believe is that the emittance dilution has resulted from the half-integer stopband of the betatron envelope function [1, 2]. The stopband width depends on the distribution of quadrupole field in an accelerator, while the betatron envelope-tune

FIG. 9: The vertical emittance growth rate before (blue) and after (red) transition for all data sets.

FIG. 10: The normalized vertical rms emittance from 70-revolution to 4000-revolution for all data sets with 2-turn injection to 18-turn injection. Note the RED curve is for 12-turn injection which marks the border of two kinds of emittance growth behavior.

spread is proportional to the space-charge perveance K_{sc} , which depends on the bunching factor and the beam-momentum.

In this Section, we will use phenomenological approach to extract properties of emittance growth by assuming that the instantaneous emittance growth rate is proportional to K_{sc} :

$$\frac{d\epsilon}{dt} = b_1 + b_2 K_{sc}, \quad (5)$$

where t is the revolution number. The normalized emittance can then be expressed as

$$\epsilon = a_0 + b_1 t + b_2 \int_0^t K_{sc} dt', \quad (6)$$

where a_0 denotes initial normalized emittance, b_1 denotes linear growth rate and b_2 denotes space-charge induced growth rate. We fit the measured ϵ_z^n to this model from 2-turn up to 11-turn injections. Beyond 11-turn injection, beam loss at injection becomes substantial. A typical fitting curve is shown in Fig. 11.

FIG. 11: A typical fitting curve of the model using Eq. (6) for the data set with 10-turn injection.

The fitting parameters are shown in Fig. 12. Note that the initial emittance varies from 1.7π -mm-mrad to 2.0π -mm-mrad for all data set. The fitted linear growth rate agrees well with that obtained in the linear growth region, shown in Fig. 9. The space-charge dependent

growth rate b_2 is nearly constant for all data sets because the intensity has been absorbed by the perveance parameter K_{sc} .

FIG. 12: Top left: parameter a_0 , initial vertical normalized emittance. Top right: parameter b_1 , linear growth rate. Bottom left: parameter b_2 , space-charge dependent growth rate. Bottom right: the residual χ^2 , normalized by noise sigma and number of data points.

An alternative model, based on Eq. (6.16) of Ref. [12], leads to

$$(\epsilon_x^n)^2 = \tilde{a}_0 \left(1 + \tilde{b}_1 t + \tilde{b}_2 \int_0^t K_{sc} dt' \right) \quad (7)$$

can also be used to fit the data well. This model describes emittance growth due to an initial non-equilibrium distribution of the beam. Since the parameter $\tilde{b}_2$ is small, the resulting fits are equivalent to the model of Eq. (6).

B. Horizontal Emittance

The horizontal beam width reflects both the horizontal emittance and the longitudinal off-momentum distribution as seen in Eq. (3). Figure 13 shows σ_x^2 for 4-turn and 12-turn

injection for the entire ramping cycle. The off-momentum width becomes more important around transition where the bunch length is shortened. The beam width starts oscillating after transition because of the longitudinal phase space mismatch.

FIG. 13: σ_x^2 for 4-turn and 12-turn injection. The beam widths below and above transition energy shows adiabatic damping, while the beam width is enhanced at the transition energy region due to the increase of the momentum width. It seems that the horizontal emittance does not possess similar initial explosive space-charge emittance growth as that of the vertical plane (see Fig. 10 for comparison).

Since the horizontal beam width is a quadrature of contributions from the betatron motion and the rms off-momentum oscillation, we cannot directly calculate the normalized horizontal emittance unless we can isolate and remove the contributions of the off-momentum contribution. In the following, we will discuss a method by taking the advantage of different scaling property as a function of the beam momentum. We will show that the momentum scaling property can effectively separate the transverse horizontal betatron emittance and the off-momentum width.

1. Below transition energy

One way to obtain the transverse betatron component in σ_x^2 is to subtract the “known” off-momentum width component, i.e. $\sigma_{x,\beta}^2 = \sigma_x^2 - D^2\sigma_\delta^2$. We can do so by assuming the beam fills up the rf bucket during the adiabatic capture at injection. The bunch shape then follows the evolution of rf bucket as a matched beam, which can be determined by the “known” rf voltage V and rf synchronous phase ϕ_s . Figure 14 shows the rf voltage (RFSUM), recorded with console program during the experiment, and the rf synchronous phase, calculated by the energy gain per revolution according to the magnetic field ramp. The top plot of Fig. 15 shows the rf bucket area. The corresponding rms off-momentum width and bunch length (assuming that the 95% bunch phase-space area of 0.08 eV-s) is shown in the bottom plot of Fig. 15. The longitudinal component in σ_x^2 can then be calculated with $D^2\sigma_\delta^2$.

FIG. 14: The rf voltage V (RFSUM) and the synchronous phase ϕ_s recorded with console program during this experiment.

Another way is to make use of the difference of the scaling rules of the transverse and longitudinal components [2]. Both terms of Eq. (3) change in the cycle as the momentum is ramped up. However, they change in different scaling rules:

$$\sigma_x^2 = \beta_x \epsilon_{\text{rms}} + D^2 \sigma_\delta^2 = aA(t) + bB(t) \quad (8)$$

FIG. 15: Top: The bucket area throughout the Booster cycle. The bucket area is about 0.08 eV-s at the beginning of the ramping cycle. Bottom: The rms momentum width σ_δ (blue) and rms bunch length σ_ϕ , assuming phase space area $A = 0.08$ eV-s. The rms value is obtained by dividing the maximum δ and ϕ by $\sqrt{6}$.

with

$$a = \epsilon_{\text{rms}}^n \frac{\beta_{x0}}{\beta_0 \gamma_0}, \quad A(t) = \frac{\beta_x}{\beta_{x0}} \frac{\beta_0 \gamma_0}{\beta \gamma} \quad (9)$$

$$b = D^2 \sigma_{\delta 0}^2, \quad B(t) = \frac{\gamma_0 \sqrt{\gamma_0 |\eta_0| / V_0} |\cos \phi_{s0}|}{\gamma \sqrt{\gamma |\eta| / V} |\cos \phi_s|}, \quad (10)$$

where we have used the scaling rule of $\sigma_\delta \sim V^{1/4} |\eta|^{-1/4} \gamma^{-3/4}$ [2]. The scaling functions $A(t)$ and $B(t)$ are shown in Fig. 16.

FIG. 16: Scaling function $A(t)$ and $B(t)$, obtained with realistic Booster lattice model and rf parameters.

The normalized horizontal emittance can be considered as growing linearly if it has the same behavior as the vertical emittance, so we further assume $a = a_0 + a_1 t$. The invariant longitudinal phase space area is preserved during acceleration, i.e. $b = b_0$. This assumption is reflected in the fact that the bucket area is nearly constant during the first 8000 revolutions in the Booster acceleration cycle. If there is any longitudinal phase space dilution, these particles will be squeezed out of the bucket. We thus try to fit the horizontal width with

$$\sigma_x^2 = (a_0 + a_1 t) A(t) + b_0 B(t). \quad (11)$$

To avoid the nonlinear emittance blow-up in the first several milliseconds of the cycle and the non-adiabatic region near transition, we fit σ_x^2 from 3001-revolution to 9200-revolution

to the model of Eq. (11) to obtain constant parameters a_0 , a_1 and b_0 for each data set. We then convert these parameters to horizontal emittance or rms momentum width according to Eqs. (9) and (10). An example of fitting curves is shown in Fig. 17.

FIG. 17: An example of the fitting curves using Eq. (11) for the horizontal data sets.

This model does not fit the data of high-intensity data very well because the calibrated result of the linear parameterization scheme may deviate from the actual beam size for high intensity beams (See Fig. 2 in Ref. [10]). The horizontal beam size σ_x (see Fig. 13) drops from 3.5 mm (at 3001-revolution) to 2.5 mm at around 7000-revolution. For a beam with $\sigma_x = 3$ mm at a total charge of 4×10^{12} particles (10-turn injection), the calibration error is as large as 5%. As the beam size shrinks due to adiabatic damping, the calibration error of IPM data gets even worse. The scaling property is particularly sensitive to errors in the IPM data calibration. Thus we fit data sets with 10-turn injection or less. The resulting normalized emittance, its growth rate and the rms momentum width are shown in Fig. 18. The standard deviations of the noises in σ_x^2 , along with the covariance matrix of the fitting, are used to estimate the error bars of these parameters.

The results give reasonable values of emittances and rms momentum widths at 3001-revolution. The horizontal normalized emittances are found to be about 2π -mm-mrad. It

FIG. 18: Top left: the fitted normalized horizontal emittance at 3001-revolution $\epsilon_0 = a_0 \frac{\beta_0 \gamma_0}{\beta_{x0}}$. Top right: the horizontal emittance growth rate $\frac{\Delta\epsilon_x^n}{\Delta N}$. Bottom left: the fitted rms momentum width $\sigma_\delta = \sqrt{b_0}/D_0$ at the 3001-revolution. Bottom right: the normalized residual χ^2 for all cases.

seems that the emittance blow-up observed in the vertical plane (see Sec. II A), due to the space-charge effects, is absent in the horizontal data. This horizontal emittance at 3001-revolution number is about the same as that of the initial vertical emittance (see the top-left plot of Fig. 12). The emittance growth rate, defined as

$$\alpha_x = \frac{\Delta\epsilon_x^n}{\Delta N}, \quad (12)$$

is about 0.8π -mm-mrad per 10^4 -revolutions. The horizontal growth rate is about the same as the vertical growth rate shown in Fig. 9. The rms momentum width is about 1.0×10^{-3} , which is smaller than the value 1.4×10^{-3} as predicted in Fig. 15. The momentum width for these data sets are nearly equal, indicating the rf buckets are nearly filled with particles at injection.

We have measured the momentum spread using the resistive wall monitor signal with a high resolution scope for 4-turn and 11-turn injection. The recorded peaks on the beam

current signal are fitted to elliptic model [13] to derive the bunch lengths. The bunch lengths becomes the momentum spread according to the phase space ellipses. The results are shown in Fig. 19. The rms momentum spread at 3001-revolution, deduced from the wall monitor data, is 1.25×10^{-3} .

FIG. 19: The measured rms bunch length σ_ϕ (left) and rms momentum width σ_δ (right) for 4-turn and 11-turn injection are compared to those calculated with phase space area 0.08 eV-s. The measurements were taken on April 29, 2005 under event 14.

From the above analysis, we find that the scaling law can successfully be used to separate the horizontal betatron and off-momentum components in the horizontal beam width. The essential error arises from the fact the IPM is located at a small β_x location, and thus it is intrinsically more prone to errors. The resulting horizontal emittance and rms off-momentum width deduced from the IPM data agree well with other independent measurements.

2. Across the transition energy

The rms momentum width starts to grow rapidly as the beam gets near transition, where the phase slip factor η becomes small. The bunch shape cannot follow the rf bucket when it is very close to transition and the longitudinal motion is non-adiabatic. The adiabatic time and nonlinear time for Booster are estimated to be [2]

$$\tau_{\text{ad}} = \left(\frac{\pi \beta^2 m c^2 \gamma_{\text{T}}^4}{\dot{\gamma} \omega_0^2 h e V |\cos \phi_s|} \right)^{1/3} \approx 0.20 \text{ ms},$$

$$\tau_{\text{nl}} = \gamma_{\text{T}}^3 \frac{\eta_1}{2 \dot{\gamma}} \hat{\delta} = \gamma_{\text{T}} \frac{\frac{3}{2} \beta_0^2 + \gamma_{\text{T}}^2 \alpha_1}{2 \dot{\gamma}} \hat{\delta} \approx 0.07 \text{ ms},$$

where we use $\dot{\gamma} \approx 437 \text{ s}^{-1}$, $\gamma_{\text{T}}^2 \alpha_1 = 1.0$, and $\hat{\delta} = \sqrt{6} \sigma_{\delta}$. The maximum rms momentum width at transition is obtained by using the non-adiabatic formula

$$\sigma_{\delta} \Big|_{\gamma=\gamma_{\text{T}}} = \frac{\gamma_{\text{T}}}{3^{1/6} \beta \tau_{\text{ad}} \Gamma(\frac{2}{3})} \left(\frac{2\mathcal{A}}{3 m c^2 \dot{\gamma}} \right)^{1/2} \approx 0.502 \frac{\gamma_{\text{T}}}{\beta \tau_{\text{ad}}} \left(\frac{\mathcal{A}}{m c^2 \dot{\gamma}} \right)^{1/2}. \quad (13)$$

Here $\mathcal{A}$ is the rms phase space area of the beam in eV-s. We obtain $\tau_{\text{ad}} = 0.187 \text{ ms}$, and $\tau_{\text{nl}} = 0.100 \text{ ms}$, and the total growth due to nonlinear longitudinal motion is $G \approx \exp\{\frac{2}{3}(\tau_{\text{nl}}/\tau_{\text{ad}})^{3/2}\} \approx 1.30$ [2]. Thus the phase space growth due to the nonlinear motion is small. Figure 19 shows clearly that the measured rms bunch length and off-momentum spread agree very well with those derived with a constant phase space area for the 4-turn injection case.

3. Microwave instability

The beam near transition energy can also suffer microwave instability. The emittance growth factor can be estimated as $G = \exp(S)$, where [14, 15]

$$S \approx \frac{n \omega_0 N_{\text{B}}^2 e^4 |Z_{\parallel}/n|^2 \gamma_{\text{T}}^3}{16 \pi \sigma_{\delta 0} \mathcal{A}^2 \dot{\gamma}} F, \quad (14)$$

where $\mathcal{A} = \pi\sigma_E\sigma_t$ is the rms phase space area in (eV-s), $F = 0.207$ is the form factor, N_B is the number of particles in a bunch, and $n = R/b \approx 1500$ is the mode number. Assuming a broadband impedance of $|Z_{||}|/n \approx 20 \text{ } \Omega$, $6\mathcal{A} = 0.08 \text{ eV-s}$, $\sigma_{\delta 0} \approx 0.00232$ is the rms momentum spread at the longitudinal center of the bunch, and $N_B = 6 \times 10^{10}$, we find $G \approx 2.2$, which is small because the microwave instability growth is the growth-factor on the very small Schottky noise.

4. Bunch mismatch oscillations in the synchrotron phase space

The post-transition beam width oscillations may arise from the mis-match across transition due to longitudinal space-charge potential as pointed out by Sorensen [16]. In a linearized approximation, the longitudinal Hamiltonian around the transition energy region is

$$H(\phi, \delta) \approx \frac{h\eta\omega_0}{2}\delta^2 - \frac{\omega_0 e}{4\pi\beta^2 E} \left[V \cos \phi_s - \frac{hec g_0 Z_0 N_B}{2\gamma^2 R \sigma_\phi^3} \right] (\phi - \phi_s)^2, \quad (15)$$

where h is the harmonic number, $g_0 = 1 + 2 \ln \frac{b}{a}$ is the geometric factor, Z_0 is the impedance of vacuum, N_B is the number of particles per bunch, and R is the mean-radius of the synchrotron. Note that the space-charge force has de-focusing effect below transition energy ($\cos \phi_s \geq 0$) and focusing effect above the transition energy ($\cos \phi_s \leq 0$). It causes sudden change of the shape of matched ellipse and thus the mismatch between the beam bunch and the ellipse. Figure 20 shows the rf voltage (RFSUM) and the voltage induced by the space-charge impedance for 12-turn injection. The voltage mismatch due to the space-charge potential can cause post-transition bunch length oscillation.

After passing the non-adiabatic transition energy region, the particles in the beam bunch start to follow the ellipses of the Hamiltonian torus again. Because the space-charge force above the transition energy is focusing, the bunch-ellipse is mismatched to the bucket ellipses. Hence the bunch starts to tumble in the bucket at the rate of synchrotron tune, which causes the rms momentum width of the beam to oscillate at twice the synchrotron tune. Let δ_1, δ_2 be the maximum and minimum rms momentum width, which are connected by the matched ellipses [2]

$$\delta_2 = \frac{\nu_s}{h\eta} \frac{\tilde{\mathcal{A}}}{\delta_1}, \quad (16)$$

where $\tilde{\mathcal{A}} = \pi\delta_1\phi_1$ is the rms phase space area. The extrema of horizontal beam width are related by

$$\sigma_{x,\max}^2 - \sigma_{x,\min}^2 = D^2(\delta_1^2 - \delta_2^2). \quad (17)$$

We can identify $\hat{\delta}$ in Eq. (13) as δ_1 . The phase space area $\mathcal{A}$ (in eV-s) in Eq. (13) is related with the phase space area $\tilde{\mathcal{A}}$ of Eq. (16) by

$$\tilde{\mathcal{A}} = \frac{\omega_0}{\beta^2 E} \mathcal{A}. \quad (18)$$

Combining Eqs. (13), (16) and (17), we can solve for δ_1 , δ_2 and the phase space area $\mathcal{A}$ from the oscillation magnitude of σ_x^2 . This is equivalent to the measurement of the quadrupole mode transfer function [17].

The horizontal beam width oscillation can be seen in Fig. 13. We fit oscillation pattern of σ_x^2 with

$$\sigma_x^2(t) = a + bt + ct^2 + A \exp(-\alpha t) \cos[2\pi(f_1 t + f_2 t^2) + \chi], \quad (19)$$

where t is the revolution-number. We apply this fitting model to data from revolution 10501 to revolution 13500 (transition is at revolution 9500, but we avoid the non-adiabatic motion

FIG. 20: The effective space-charge voltage V_{spchg} (solid) and the V_{rf} in the acceleration cycle.

FIG. 21: Top: Fit σ_x^2 to the model of Eq. (19) for 5-turn injection. Bottom: Fit σ_x^2 to the model of Eq. (19) for 10-turn injection.

of the first 1000 revolutions after the transition). Examples of fitting curves are shown in Fig. 21.

The oscillatory part of σ_x^2 comes essentially from the longitudinal distribution mismatch with the rf bucket. Figure 22 shows the fitted tune parameters f_1 and f_2 as a function of the

injection-turn. The fitted oscillation tune is $f_1 + 2f_2t = 0.0065$ at 10500 revolution (18.6 ms) for 4-turn injection cycle, which is about twice of the synchrotron tune $\nu_s = 0.0034$ measured from turn-by-turn data at 18.4 ms with the same intensity [8].

FIG. 22: The fitted post transition oscillation tune f_1 (1/revolution) and f_2 (1/revolution²). The oscillation tune is given by $f_1 + 2f_2t$.

The oscillation amplitude A and the decoherent coefficient α is shown in Fig. 23. The oscillation amplitude

$$2A = \sigma_{x,\max}^2 - \sigma_{x,\min}^2. \quad (20)$$

can be used to solve the longitudinal phase space area. Employing Eqs. (13), (16) and (17),

we can self-consistently solve the mis-matched motion. The resulting δ_1 and δ_2 are shown in the bottom plot of Fig. 23.

The non-oscillatory part

$$\sigma_{x,\text{static}}^2 = a + bt + ct^2$$

is composed of transverse betatron-motion component and the static off-momentum width component. It can be decomposed into the transverse and longitudinal components. Knowing the maximum (δ_1) and minimum (δ_2) of rms momentum width, the average value $\bar{\delta}$ can be calculated

$$\bar{\delta}_{\text{osci}} = \sqrt{\frac{\delta_1^2 + \delta_2^2}{2}}, \quad (21)$$

where subscript “osci” indicates $\bar{\delta}$ is derived from the oscillation component of σ_x^2 . Figure 24 shows the fitted parameters for the non-oscillatory part, and the corresponding normalized χ^2 normalized to the number of data points for the entire set.

Because the transition energy affects mainly the longitudinal motion, it is reasonable to assume that the transverse emittance will keep growing in the same manner as in the pre-transition region. The vertical emittance growth across transition (Fig. 7) suggests the same picture. Thus we have

$$\sigma_{x,\text{static}}^2 = \frac{\beta_x}{\beta\gamma} \epsilon_{x0}^n (1 + \alpha_x t) + D^2 \bar{\delta}^2, \quad (22)$$

where $\epsilon_{x,\text{rms}}^n$ is normalized rms emittance and α_x is horizontal emittance growth rate. The scaling rule is $\bar{\delta} \sim |\eta|^{-1/4} \gamma^{-3/4}$, neglecting the rf voltage V factor which is constant in the concerned region. The scaling rule does not include the phase space dilution from the smearing of the mismatch bunch. By subtracting the predicted transverse component $\beta_x \epsilon_{x,\text{rms}}$ from $\sigma_{x,\text{static}}^2$, the rms momentum width can also be calculated by

$$\bar{\delta}_{\text{static}} = \frac{\sqrt{\sigma_x^2 - \beta_x \epsilon_{x,\text{rms}}}}{D}, \quad (23)$$

Using the growth rate obtained with the pre-transition fitting to predict $\epsilon_{x,\text{rms}}$ at revolution 10501, we have calculated $\bar{\delta}$ for all data sets, which are compared to the results obtained with Eq. (21) in Fig. 25. It is seen that the two methods produce consistent results.

FIG. 23: The top plot shows the fitted post transition oscillation amplitude $A \text{ (mm}^2\text{)}$, the middle plot shows the decoherent factor $\alpha \text{ (1/revolution)}$, and the bottom plot shows the deduced δ_1 and δ_2 (bottom).

FIG. 24: The fitting parameters of the post-transition horizontal beam size σ_x^2 . Parameter a (mm²) at top left; parameter b (mm²/revolution) at top right; parameter c (mm²/revolution²) at bottom left; and bottom right: the residual χ^2 normalized by noise sigma and number of data points.

III. MODELING AND EMITTANCE DILUTION MECHANISMS

In last section, we have carried out phenomenological fit for the IPM measurement data at the Fermilab Booster under various beam intensity levels. Our findings can be summarized as follows.

1. The normalized vertical emittance starts at about 2π -mm-mrad for all intensity levels, i.e. there is no injection phase-space-painting. For intensity less than 10-turn injection, the space charge is less important, and the injection efficiency is nearly independent of the intensity (see Fig. 2). This implies that beam loss essentially arises in the longitudinal phase space. Longitudinal phase space painting with chopped beam may be needed to minimize the beam loss and satisfy the requirement of fast ramping.

FIG. 25: The average rms momentum width $\bar{\delta}$ obtained with two methods: Eq. (23) (“static”) or Eq. (21) (“osci”).

When the beam intensity is larger than 10-injection turns, the normalized vertical emittance grows rapidly in the first 4000 revolutions. The space-charge force is believed to be the source of the emittance growth.

2. In the later time of the cycle at $\gamma > 2$, the vertical emittance grows linearly with a growth rate of about 1π -mm-mrad in 10^4 revolutions. Both the intra-beam scattering and the beam-gas scattering growth rates are too small to explain this linear emittance growth rate.
3. The horizontal beam width is composed of both the transverse and the longitudinal phase space distribution of the beam. Making use of the fact that the two components have different momentum scaling rules, we can effectively decompose σ_x^2 into betatron and off-momentum beam-widths. Such fitting works well for data sets with less than 10-turn injection when the IPM profile calibration error due to space-charge is mild [10]. The fitting results yield consistent horizontal normalized emittance and the rms momentum width. Note that the horizontal normalized emittance does not exhibit explosive growth at the first 4000 revolutions as that of the vertical normalized emittance. On the other hand, the linear growth rate of the normalized horizontal-emittance was also about 0.8π -mm-mrad in 10^4 revolutions.

4. The horizontal beam width starts to oscillate with frequency twice the synchrotron tune (quadrupole mode) after transition. Such oscillation arises from the mismatch between beam bunch and longitudinal phase space ellipse. The mismatch was believed to be due to the longitudinal space-charge force which is de-focusing before transition and focusing after transition. We extracted the oscillatory and non-oscillatory parts of σ_x^2 by fitting it to a model with second-order polynomial plus damped oscillation with linear phase shift rate. The oscillation amplitude of σ_x^2 can be used to derive the longitudinal phase space area. The non-oscillatory part is again separated into horizontal emittance and static (average) rms off-momentum width by assuming the horizontal normalized emittance grows linearly as in the region before transition. The estimated average rms momentum widths with both the oscillatory or non-oscillatory parts are consistent. The post-transition bunch length (and beam size) oscillation is a possible cause of beam loss at transition. The bunch shape mis-match may be compensated by rf voltage modulation at a frequency slightly larger than twice the synchrotron frequency [19]. A voltage modulation depth of about 3% of the total rf cavity voltage, i.e. about 24 kV, is sufficient to damp the mismatched oscillation. We have learned that Fermilab Booster has recently implemented the quadrupole damper and has since effectively damped the quadrupole mode oscillation [20].

A. Modeling Algorithm

To understand the phenomena of the emittance growth, we construct a multi-particle simulation program to simulate the evolution of beam emittances. As the beam injected into a synchrotron, particles in the synchrotron experience also space-charge force. We track particles including the space-charge force to extract the essential mechanisms of emittance growth for the Fermilab Booster. We will describe our numerical-simulation algorithm in the following subsections.

1. Energy gain in rf cavities

Since rf-cavities at the Fermilab Booster are located in dispersive locations, the beam is constantly and coherently excited by the energy gain at about 400 keV per revolution.

Can this coherent beam excitation combined with beam decoherence produces the observed emittance growth?

Fermilab booster is a fast-ramping accelerator. Semi-adiabatic capture is applied in the H^- injection scheme. The rf voltage is ramped from a small number to about 900 kV to provide fast cycling of 15 Hz. The rf voltage V_{rf} and the synchronous phase ϕ_s were recorded, and employed for this tracking. Energy gain in each revolution is $V_{\text{rf}} \sin \phi_s$, which is equally distributed in all cavities located in each particular long straight section with rf cavities.

We assume that the dipole magnets are ramped linearly, while the beam receives energy at cavities with energy u in each cavity that is located in non-zero dispersive region. The horizontal position of a particle is given by

$$x = x_\beta + D \frac{\Delta E}{\beta^2 E}, \quad x' = x'_\beta + D' \frac{\Delta E}{\beta^2 E}, \quad (24)$$

where (x_β, x'_β) are the betatron coordinates, and (D, D') are the dispersion function. Each particle gains the same amount of energy in rf cavities. As the energy of a particle is gained in a cavity, the changes of the betatron coordinates are

$$\Delta x_\beta = -D \frac{u}{\beta^2 E}, \quad \Delta x'_\beta = -D' \frac{u}{\beta^2 E}, \quad (25)$$

where u is the energy gain at the cavity. The centroid of the beam is constantly and coherently excited by the betatron excitation.

We define the fractional momentum deviation between the beam momentum p_{beam} and the “magnet-momentum” p_{mag} (the momentum associated with the magnetic field) as

$$\frac{\Delta p}{p} \equiv \frac{p_{\text{beam}} - p_{\text{mag}}}{p_{\text{beam}}}.$$

The top plot of Fig. 26 shows that the beam momentum is constantly oscillating against the momentum associated with the magnetic field. The bottom plot shows the betatron motion of the centroid of the beam for 400 revolutions with linear coupling at a coupling strength of 0.005 m^{-1} .

FIG. 26: Top: The fractional momentum deviation of the beam with respect to the momentum associated with the dipole magnetic field. The energy gain is 400 keV per revolution in this example. The actual energy gain in our simulation program per revolution is obtained from the RFSUM data of the Booster operation. Bottom: The coherent betatron motion of the beam excited by the energy gain in each cavity. A linear coupling with a focal length of about 200 m is included in attaining the coherent betatron motion in the vertical plan. The units for (x, z) and (x', z') are mm and m-rad respectively.

2. FODO cells and Random Linear Errors

The Booster is made of 24 combined function FODO cells. Particle transport in each FODO cell is carried out by the transfer matrix from D to F with

$$M_{D \rightarrow F} = \begin{pmatrix} \sqrt{\frac{\beta_{x,F}}{\beta_{x,D}}} \cos \psi_x & \sqrt{\beta_{x,F} \beta_{x,D}} \sin \psi_x & 0 & 0 \\ -\frac{1}{\sqrt{\beta_{x,F} \beta_{x,D}}} \sin \psi_x & \sqrt{\frac{\beta_{x,D}}{\beta_{x,F}}} \cos \psi_x & 0 & 0 \\ 0 & 0 & \sqrt{\frac{\beta_{z,F}}{\beta_{z,D}}} \cos \psi_z & \sqrt{\beta_{z,F} \beta_{z,D}} \sin \psi_z \\ 0 & 0 & -\frac{1}{\sqrt{\beta_{z,F} \beta_{z,D}}} \sin \psi_z & \sqrt{\frac{\beta_{z,D}}{\beta_{z,F}}} \cos \psi_z \end{pmatrix} \quad (26)$$

where $\psi_{x,z} = 2\pi\nu_{x,z}/48$ is the phase advance in a half cell. We have assumed $\alpha_{x,F} = 0$ and $\alpha_{z,F} = 0$.

Similarly, the transfer matrix from the F back to D is

$$M_{F \rightarrow D} = \begin{pmatrix} \sqrt{\frac{\beta_{x,D}}{\beta_{x,F}}} \cos \psi_x & \sqrt{\beta_{x,F} \beta_{x,D}} \sin \psi_x & 0 & 0 \\ -\frac{1}{\sqrt{\beta_{x,F} \beta_{x,D}}} \sin \psi_x & \sqrt{\frac{\beta_{x,F}}{\beta_{x,D}}} \cos \psi_x & 0 & 0 \\ 0 & 0 & \sqrt{\frac{\beta_{z,D}}{\beta_{z,F}}} \cos \psi_z & \sqrt{\beta_{z,F} \beta_{z,D}} \sin \psi_z \\ 0 & 0 & -\frac{1}{\sqrt{\beta_{z,F} \beta_{z,D}}} \sin \psi_z & \sqrt{\frac{\beta_{z,F}}{\beta_{z,D}}} \cos \psi_z \end{pmatrix} \quad (27)$$

The parameters for the betatron amplitude and dispersion functions are $\beta_{x,D} = 6.3$ m, $\beta_{z,D} = 21.4$ m, $\beta_{x,F} = 40.$ m, $\beta_{z,F} = 8.3$ m, $D_{x,D} = 2.54$ m, and $D_{x,F} = 4.5$ m. Figure 27 shows the betatron tunes during the 33 ms ramping cycle.

FIG. 27: The fractional part of the betatron tune during the entire ramping cycle from injection at 400 MeV to the top energy at 8.0 GeV (see Fig. 9 in [8]).

Systematic sextupoles and small random dipole, quadrupole and skew-quadrupole errors are introduced as kicks to each particle:

$$x'' + K_x(s)x = b_0(s) + b_1(s)x + a_1(s)z - \frac{1}{2}b_2(s)(x^2 - z^2), \quad (28)$$

$$z'' + K_z(s)z = -a_0(s) - b_1(s)z + a_1(s)x + b_2(s)xz. \quad (29)$$

The dipole components b_0 and a_0 are applied to each particle with a random seed to simulate the closed orbit mis-injection. The random quadrupole error is intended to create half-integer stopband in order to test the importance of the envelope dynamics. The quadrupole component $b_1(s)$ is generated by a random seed with zero tune shift, i.e. $\oint \beta_x(s)b_1(s)ds = 0$ and $\oint \beta_z(s)b_1(s)ds = 0$. The random skew quadrupoles take into account the quadrupole roll and the vertical closed orbit error in sextupoles. All random numbers are generated by random seeds with uniform distribution from -1 to $+1$. The magnitude of these random linear error field is controlled by an amplitude, i.e.

$$A_{b0}(n) = A_{b0}(0) \exp\left\{-\frac{n}{N_{dipole}}\right\} \quad (30)$$

$$A_{a0}(n) = A_{a0}(0) \exp\left\{-\frac{n}{N_{dipole}}\right\} \quad (31)$$

$$A_{b1}(n) = A_{b1}(0) \exp\left\{-\frac{n}{N_{quad}}\right\} \quad (32)$$

$$A_{a1}(n) = A_{a1}(0) \exp\left\{-\frac{n}{N_{quad}}\right\}. \quad (33)$$

The damping of the dipole kicks is intended to take into account the decoherence effect associated with the initial closed orbit error. The damping of quadrupole kicks takes into account the fact that the particle orbit will eventually evolve into the matched ellipse of the accelerator. The effect of dipole error is most important during the injection, while the effect of quadrupole error requires a longer time to settle into matched beam ellipse. We choose $N_{dipole} = 3000$, and $N_{quad} = 4000$.

The sextupole is inherent to all combined function dipoles. They are introduced as a thin lens kick at the end of each half cell. The sextupole strengths are -0.0173 m^{-2} and -0.263 m^{-2} for focusing and defocusing dipoles respectively for each of the half FODO cell. We also include sextupoles in the short and long straight sections to explore their effects on the emittance growth. However, we find that their effects on emittances are small.

3. Space Charge Effects

We assume a Gaussian charge distribution:

$$\rho(x, z) = \frac{Ne}{2\pi\sigma_x\sigma_z} \exp\left\{-\frac{x^2}{2\sigma_x^2} - \frac{z^2}{2\sigma_z^2}\right\},$$

where N is the charge per unit length and σ_x and σ_z are the horizontal and vertical rms beam radii. The horizontal rms beam radius is composed of both the betatron and off-

momentum width contributions. For a Gaussian charge distribution, the transverse space-charge potential is [21]

$$\begin{aligned}
V(x, z) &= \frac{Nr_0}{\beta^2\gamma^3} \int_0^\infty \frac{-1 + \exp\{-\frac{x^2}{2\sigma_x^2+t} - \frac{z^2}{2\sigma_z^2+t}\}}{\sqrt{(2\sigma_x^2+t)(2\sigma_z^2+t)}} dt \\
&\approx -\frac{Nr_0}{\beta^2\gamma^3} \left\{ \left(\frac{x^2}{\sigma_x(\sigma_x + \sigma_z)} + \frac{z^2}{\sigma_z(\sigma_x + \sigma_z)} \right) \right. \\
&\quad \left. - \frac{Nr_0}{4\beta^2\gamma^3\sigma_x^2(\sigma_x + \sigma_z)^2} \left(\frac{2+R}{3}x^4 + \frac{2}{R}x^2z^2 + \frac{1+2R}{3R^3}z^4 \right) + \dots \right\}, \quad (34)
\end{aligned}$$

where the singularity at $x = z = 0$ is removed by the addition of the -1 term in the numerator of the integrand.

Because of the space-charge potential, each particle experiences a space-charge kick given by

$$\Delta x' = -\frac{\partial V}{\partial x} \ell \approx \frac{2Nr_0\ell}{\beta^2\gamma^3\sigma_x(\sigma_x + \sigma_z)} x \exp\left\{-\frac{x^2 + z^2}{(\sigma_x + \sigma_z)^2}\right\}, \quad (35)$$

$$\Delta z' = -\frac{\partial V}{\partial z} \ell \approx \frac{2Nr_0\ell}{\beta^2\gamma^3\sigma_z(\sigma_x + \sigma_z)} z \exp\left\{-\frac{x^2 + z^2}{(\sigma_x + \sigma_z)^2}\right\}, \quad (36)$$

where ℓ is the length of the half cell. The space charge force is approximated by 48 localized kicks per revolution. The rms beam radii calculated from the multi-particle phase space distribution is used for space-charge kicks in the next revolution. In order to test many conditions, we will carried out non-self-consistent multi-particle simulation based on the potential model, i.e. the space-charge force is modified by the rms radii, but remains in the Gaussian-potential form. Although the distribution function may become non-Gaussian, our space-charge kick remains in the Gaussian beam approximation.

4. Betatron tunes and the rms beam momentum spread

The betatron tunes has been measured during the ramping cycle as shown in Fig. 9 of Ref. [8] (see also Fig. 27). The RF voltage, the synchronous phase, and the bunch length during the ramping cycle have also been measured. In our simulation, we use interpolation between the measured-data in a ramping cycle.

We assume that the (95%) longitudinal bunch area to be 0.08 eV-s. After the transition energy, the rms momentum width begins mis-match oscillation. At revolution $n > n_t =$

9600, the rms off-momentum width $\delta_{\text{rms}}(n)$ is

$$\delta_{\text{rms}}(n) = \delta_{\text{rms},0} B_f(n) (1 + (G_\delta - 1)(1 - \exp(-\alpha_\delta(n - n_t))) \times [1 + A_\delta \exp(-\alpha_\delta(n - n_t)) \sin(2\pi(n - n_t)f)], \quad (37)$$

Here $B_f(n)$ is the bunching factor, $\delta_{\text{rms},0} \approx 3.0 \times 10^{-4}$ is the initial rms off-momentum width, G_δ is the momentum width growth factor, α_δ is the decoherent constant, A_δ is the amplitude of bunch shape oscillation, and f is the oscillation tune. In our simulation, we choose $n_t = 9600$, $G_\delta = 2.0$, $A_\delta = 0.5$, $f = 1/150$ (1/revolution), and $\alpha_\delta = 1/(15 \times 150)$.

The focusing strength of quadrupoles in the Fermilab Booster is about 0.33 m^{-1} . Thus the random quadrupole strength is expected to be about $3.0 \times 10^{-4} \text{ m}^{-1}$. The dipole bending strength for each half FODO cell is about 0.131 rad. The amplitude of dipole errors is estimated to be about 2.0×10^{-5} radian in the horizontal plane and 7.5×10^{-5} in the vertical plane. The horizontal dipole field error corresponds to about 1.5×10^{-4} error in the main dipole field, while the vertical random dipole error field corresponds to about 0.6 mrad of dipole roll. Closed orbit oscillations are evidently visible in the profile data of Fig. 3 for the first 4000 revolutions. The random skew quadrupole strength can be produced by the vertical closed-orbit deviation in sextupole and by the quadrupole roll. We assume an amplitude of $3.5 \times 10^{-3} \text{ m}^{-1}$ for the random skew quadrupole. This is equivalent to an amplitude of vertical closed orbit of the order of 1.0 cm.

To check our program, we first examine the emittance evolution in the presence of linear dipole and quadrupole errors without space-charge force and sextupole non-linearity. Figure 28 shows the rms beam radii and beam emittances at the de-focusing quadrupole location. The vertical beam width is adiabatically damped, and the horizontal beam width shows the characteristic off-momentum dependence. However, The horizontal and vertical emittances are constant in the absence of space-charge force and sextupole nonlinearity.

B. Results of Numerical Simulations

In this section, we will examine the effect of each factor of our algorithm on the emittance growth.

FIG. 28: The emittance is not affected by the linear errors and the coherent beam oscillations due to rf cavities located in dispersive locations.

1. Effect of the half-integer stopband

The half-integer stopband has been considered as one of the main sources on emittance growth since 1960's [1, 2]. When the tunes of the *beam-envelope-function* reach an integer, the emittance may grow and beam loss may occur. In our model, the random quadrupole field is introduced as thin-lens kick in each half cell with a random seeds that produce zero betatron tune-shift.

We first consider only the *linear* space-charge kick. The existence of the random quadrupole error will produce betatron mismatch. The effect is particularly important if the betatron envelope tune is depressed toward the half-integer stopband. Figure 29 shows the initial (black dots) and the final (red dots at $n = 11000$ revolutions) phase space distributions for 12-turn injection with the amplitude of random quadrupole amplitude at $A_{b1}(0) = 4.0 \times 10^{-4} \text{ m}^{-1}$ (top plots) and $A_{b1}(0) = 4.0 \times 10^{-3} \text{ m}^{-1}$ (bottom) of Eq. (32).

In the presence of the linear random quadrupole error, the phase space distribution is altered by the *linear* space-charge force while the phase space areas (or emittances) remain constant in these cases. Emittance dilution occurs only when nonlinear forces such as

FIG. 29: The beam phase-space distribution for the initial (black dots) and the final (red dots at $n = 11000$ revolution or a kinetic energy of 5.0 GeV) distributions for a beam with 12-turn injection. Top: The initial (black dots) and the final (red dots at $n = 11000$ revolution) phase space plots (x, x') and (z, z') for the $A_{b1} = 4.0 \times 10^{-4} \text{ m}^{-1}$. Bottom: The same as that of the top plot except the amplitude of the random quadrupole error is $A_{b1} = 4.0 \times 10^{-3} \text{ m}^{-1}$.

sextupole and higher order multipoles are included. The nonlinearity introduces betatron detuning that gives rise to decoherence in the betatron motion.

We now explore the half integer stopband including nonlinear decoherence. We introduce a random quadrupole distribution such that the stopband widths are about 0 and 0.1 at harmonics 12 and 13 respectively. The corresponding amplitude of random quadrupole field error is $40 \times 10^{-4} \text{ m}^{-1}$, i.e. about 1.3% of the main quadrupole field. We turn off all random

dipole and skew quadrupole field errors so that we examine only the random quadrupole field-error.

We fix the vertical betatron tune at $Q_z = 6.95$ and vary the horizontal betatron tune Q_x from 6 to 7. Since the bare vertical tune is far away from the stopband by choice, the vertical emittance is constant in all cases. Since the horizontal tune is varied across the stopband 13, and approaches a smaller stopband at harmonic 12, we expect to see large horizontal emittance change during this process. The top plot of Fig. 30 shows the final horizontal emittance as a function of the bare horizontal tune for a beam with 12-turn injection. Because of the nonlinear decoherence, the perturbation in the envelope function gives actual emittance dilution shown in Fig. 30. The horizontal emittance is affected by the stopband in the presence of space-charge. When the space-charge force is turned off, the emittance is much less affected by the presence of the half-integer stopband shown as symbols of X's. The bottom plot shows the horizontal Laslett-space-charge tune shift during the ramping process for a small amplitude particle.

The space-charge effect is a self-adjusting process. When the emittance increases or beam loss occurs, the corresponding space-charge tune shift is reduced. Thus in the ramping cycle the linear space-charge tune shifts are different in each machine condition. When the betatron tune is sufficiently near the stopband, the beam distribution is changed by depleting the particle in the center core, and the distribution may become hollow ring in the phase space. However, we also note that the actual random quadrupole error is expected to be 10 times smaller than those used in this calculation. With the expected gradient error of the order of $4 \times 10^{-4} \text{ m}^{-1}$, we find little emittance growth, shown as red points in Fig. 30.

2. *Effects of the Montague Resonance*

Montague resonance has been extensively studied and considered as one of major sources on emittance growth [5]. In order to investigate the effect of Montague resonance at $2\nu_x - 2\nu_z = \text{integer}$ resonance, we turn off all linear random errors while retaining only the systematic sextupole fields in dipoles. To investigate the effect of coupling, we also fix the vertical tune at $\nu_z = 6.85$, and change the horizontal tune from 6.75 to 6.90. Figure 31 shows the effects of Montague resonance as the horizontal tune is varied across the vertical betatron tune.

FIG. 30: Top: The final emittance for a beam with 12-turn injection under the influence of the stopband at harmonics 12 and 13. The stopband width at harmonic 12 is intentionally made small by the choice of a random seed. Bottom: the magnitude of the space-charge tune shift for all cases shown in the top plot. The blue and magenta color correspond to the large emittance growth shown in the top plots. In these two cases, the beam distribution in the horizontal phase space become halo. Note that the space-charge is a self-adjusting process, as the space-charge effect becomes large, the emittance increases, in turn, the space-charge tune shift is reduced to avoid the stopband.

The initial growth of the vertical emittance in Fig. 31 arises from the phase space mismatch. When the horizontal and vertical betatron tunes are equal, two emittances are fully coupled, and the emittances tend to be equal. When the horizontal and vertical betatron tunes are not equal, the emittances are exchanged so that the space-charge tune spread moves away from the Montague resonance line. Although the Montague resonance can

FIG. 31: The emittance evolution for a beam with 12-turn injection when only the space-charge force is included in the calculation. The horizontal betatron tune is varied across the vertical betatron tune to examine the effect of Montague resonance. The right plots zoom in on revolution 500 to 1000 to see the details of the emittance exchange.

cause emittance oscillation and exchange, its effect on the emittance growth is small.

3. Effect of the linear skew quadrupoles

Vertical closed orbit deviation in sextupoles and quadrupole-roll can induce skew-quadrupole field. Random skew-quadrupole kicks are applied at each half cell. The amplitude of the random skew-quadrupole field is estimated to be about $3.50 \times 10^{-3} \text{ m}^{-1}$, or a focal length of about 300 m. This corresponds to an amplitude of vertical closed orbit error of the order of 1.0 cm.

The random skew quadrupole field is much harder to investigate because it may mix-up with the Montague resonance. We explore the effect by varying strengths of the random skew quadrupoles with an identical random number seed. Figure 32 shows the emittances vs the horizontal tune Q_x , while the vertical tune is fixed at $Q_z = 6.85$. The random skew-quadrupoles are applied to every half FODO-cell with amplitudes 0 , $3.5 \times 10^{-4} \text{ m}^{-1}$, $14 \times 10^{-4} \text{ m}^{-1}$, $35 \times 10^{-4} \text{ m}^{-1}$ respectively.

FIG. 32: The emittance evolution for a beam with 12-turn injection when the space-charge force and random skew quadrupole kicks are included. The importance of the linear coupling (sum and difference) resonances are clearly visible when the amplitude of skew quadrupole is large. Note that the random skew quadrupole error also introduces stopband width to integer resonances.

The blue lines (square symbols) are emittances for the calculation without random skew quadrupole field. Note that the Montague resonance is most important when the horizontal and vertical tunes are equal. The emittances are shown to be nearly equal in Fig. 32 when this condition is met. On the other hand, when the horizontal betatron tune approaches any integer, particle encounters coherent kicks and the horizontal emittance becomes very large. The phase space distribution becomes halo in the horizontal phase space.

When random skew-quadrupole kicks are introduced in the accelerator, it introduces

linear coupling resonances $\nu_x \pm \nu_z = \text{integer}$ resonances. When the skew-quadrupole strength is small, e.g. $g_{sq} = 3.5 \times 10^{-4} \text{ m}^{-1}$ as shown as X-symbol (green lines) in Fig. 32, the effect does not differ much from that of no skew quadrupole. When the amplitude of skew quadrupole strength is increased to $14 \times 10^{-4} \text{ m}^{-1}$, shown as black lines in Fig. 32, both the linear coupling difference and sum resonances becomes important. When the amplitude of skew quadrupoles is 35×10^{-4} , as shown in the red lines in Fig. 32, the linear coupling resonances becomes extremely strong. Substantial beam loss will occur when Q_x falls in the width of the stopband, i.e. $6.15 < Q_x < 6.35$. In particular, the sum resonance $\nu_x + \nu_z = \text{integer}$ produces a very large vertical emittance growth even when the resonance is still far away. Figure 33 shows the initial (black) and final (red) phase space plot for the case with betatron tunes at $Q_x = 6.30$ and $Q_z = 6.85$. We note that the distribution function becomes hollow rings in both the horizontal and vertical phase spaces.

FIG. 33: The horizontal (left plot) and vertical (right plot) phase space distributions for a beam with 12-turn injection for skew quadrupole amplitude 0.0014 m^{-1} . The initial phase space points, shown in blue dots, have normalized emittances of about $1.7 \pi \text{ mm-mrad}$ on both planes. The final phase space distributions, shown in red at 6000-revolution, have normalized emittances 2.6 and $3.8 \pi\text{-mm-mrad}$ in the horizontal and vertical planes respectively. Note that the phase space distribution becomes halo in both the horizontal and vertical planes.

To examine the stopband width of the sum resonance in the presence of space-charge tune spread, we examine the emittance growth vs the beam intensity. Figure 34 shows the horizontal (solid line) and vertical (dashed line) emittances as a function of the horizontal

betatron tune Q_x for a fixed vertical betatron tune at $Q_z = 6.85$. The intensity is varied from 1-turn injection to 11-turn injection. We note that the stopband width increases with the beam intensity. Substantial beam loss occurs when the bare tunes fall within the stopband.

FIG. 34: The horizontal (dashed line) and vertical (solid line) emittances are plotted as a function of the horizontal tune for different beam intensities (from 1-turn to 11-turn injections).

The skew quadrupole generates a surprising emittance growth mechanism for the difference coupling resonance at $\nu_x - \nu_z = \text{integer}$. Figures 32 and 34 show that the emittances grow together when the horizontal and vertical tunes are equal. This is counter-intuitive. We expect that the sum of the horizontal and vertical emittances should be constant at a linear difference resonance. The reason for the emittance growth for the linear coupling resonance is the phase space mis-match. The beam is constantly excited by the phase space mis-match when the tunes are equal. The phase space mis-match induces emittance dilution in both the horizontal and vertical planes.

4. Effect of dipole field errors

The effect of dipole field error produces coherent beam oscillation. Nonlinearities in the accelerator converts the coherent beam oscillation into emittance dilution. Figure 35 shows the effect of emittance evolution in the presence of space-charge force with and without dipole field errors. Since the horizontal dipole field error can be produced by dipole roll, we expected to have a larger a_0 term than the corresponding b_0 term. We estimated that the amplitudes of dipole error are about 2.0×10^{-5} rad for horizontal motion and 7.5×10^{-5} rad for vertical motion respectively. A large a_0 term produces a larger vertical beam emittance increase as shown in Fig. 35. Had we have a large b_0 term, we would have produced a large horizontal emittance increase.

FIG. 35: The emittance evolution for a beam with 12-turn injection for the case with random dipole field error (red), and without the dipole field error (blue). The random dipole field error has an amplitude of 2.0×10^{-5} rad and 7.5×10^{-5} rad for the horizontal and vertical planes respectively.

5. *Effect of rf cavities in the dispersive region*

It is known that the quantum fluctuation induced by synchrotron radiation loss in dipole is the main source of excitation for electron beams in storage rings. The acceleration of localized rf cavities in the Fermilab Booster causes coherent beam betatron oscillation about the closed orbit as shown in Fig. 26. However, the effective kick angles of these cavities is less than 1×10^{-5} rad, its effect is small. Had we have all cavities located in a single straight section, the resulting increase of emittance would be about 0.5π -mm-mrad during the acceleration. Since these cavities are distributed in 10 straight sections, its effect on emittance is small!

C. **Putting it all together**

When the space-charge force is included during the injection process, the phase space ellipse of the particle motion becomes mis-matched. The magnitude of mismatch is proportional to the space-charge perveance K_{sc} . The phase space mismatch of each particle will decohere and the resulting beam distribution will reach a larger emittance. Thus the emittance growth rate is proportional to the space-charge perveance, i.e. $d\epsilon/dt \sim K_{sc}$, where t is the revolution number. This may explain the reason that we were able to fit the vertical beam emittance data with the model. Figure 36 shows the rms beam radii at a focusing quadrupole location and the emittance evolution for the beam intensity at 12-turn injection. The parameters used in the numerical simulations are 2.0×10^{-5} rad and 7.5×10^{-5} rad dipole error for the horizontal and vertical motion respectively, $4.0 \times 10^{-4} \text{ m}^{-1}$ quadrupole field error, and $35 \times 10^{-4} \text{ m}^{-1}$ for the skew quadrupole field error. The characteristic of the the vertical emittance growth clearly resembles that of the experimental data shown in Fig. 10.

The emittance dilution occurs mainly in the vertical plane. This has resulted from the combination of the random skew quadrupoles, Montague resonance and a larger dipole error for the vertical motion (than that for the horizontal motion). The situation can be different if the machine operation condition is changed. The Fermilab Booster has been optimized by many years of operational experiences. The current mode is certainly an acceptable one. The contribution of emittance growth for the 12-turn injection is 50% due to the

FIG. 36: The emittance evolution for a beam with 12-turn injection when the space-charge force is introduced.

skew quadrupole, 25% dipole field error, and 25% from the intrinsic space-charge effects (Montague resonance). The effect of large skew quadrupole contribution is due to a large space-charge tune shift, and a large linear sum resonance at $\nu_x + \nu_z = \text{integer}$ resonance as shown in Fig. 32.

We now compare the emittance evolution for various beam intensities. Figure 37 compares the evolution of the vertical emittances for 6, 12, and 16-turn injections. Note that the emittance growth resembles that shown in Fig. 10.

D. Other observations

We have found that the horizontal rms bunch-width oscillates with twice the synchrotron frequency due to mis-match in the rf potential well after the transition energy crossing. We found that this mis-matched horizontal bunch-width oscillation could actually occur before the transition energy if the beam intensity is high.

The vertical beam width showed also post-transition oscillation (see Fig. 6). The post-transition vertical beam width oscillation is out of phase with that of the horizontal plane.

FIG. 37: The evolution of the vertical emittance evolution for beams with 6, 12, and 16-turn injections. The emittance evolution can be compared with those of Fig. 10.

This may have resulted from the Montague resonance. However, using the betatron tunes measured from independent component analysis (ICA) method, we do not observe the vertical emittance oscillation in our numerical simulation, unless the betatron tunes are nearer to each other at the transition energy crossing.

IV. CONCLUSION

We have carried out systematic IPM measurements at the Fermilab Booster for the first time to understand the emittance evolution for a space-charge dominated beams. The vertical emittance has a very strong dependence on the beam intensity with $d\epsilon_z/dt \sim K_{sc}$. Using the scaling laws of the betatron emittance and off-momentum spread, we have also succeeded in separating the horizontal emittance and the rms off-momentum spread from the horizontal beam width. We found that the horizontal emittance is less dependent on the space charge!

We use the rms space-charge potential model to carry out systematic numerical simulation to understand the observed phenomena. We find that the vertical emittance growth is

induced mainly by random skew quadrupoles in the presence of a large space-charge tune spread. The sum and difference linear-coupling resonances play a very important role in the emittance growth for a fast ramping accelerator. The Montague resonance plays a minor roll in the vertical emittance growth. The random dipole field error for the vertical plane, due mainly to the dipole roll, has contributed a role in the vertical emittance growth. The random quadrupole error is not important at the Fermilab Booster because the betatron tunes are far away from the stopbands.

Although we can use our numerical simulation model to understand the main source of emittance growth at the Fermilab Booster, we do not have the explanation of the slow growth of the emittance at about 1π -mm-mrad in 10^4 revolutions. One can introduce an rf-noise model in dipole or quadrupole fields to produce this emittance growth. Since we do not know the source, we decide not to put it in our model.

We find that the sum and difference linear coupling resonances induced by the skew quadrupoles are the major source of emittance growth at the Fermilab Booster, it would be very important to carry out additional emittance measurements with skew quadrupole correction scheme that minimizes the sum and difference stopbands. We think that the beam loss at the Fermilab Booster arises essentially in the longitudinal phase space, the skew-quadrupole correction scheme may be able to reduce the vertical emittance growth, but may not be able to minimize the beam loss. To minimize beam loss, one needs to chop the linac beam-pulse as the source and employ longitudinal phase space painting in the longitudinal phase space at injection. Work on experiment with skew quadrupole correction schemes will be carried out in the near future.

Acknowledgments

This work is supported in part by grants from the US Department of Energy, under contract DE-AC02-76CH03000, and DE-FG0292ER40747 and the National Science Foundation NSF PHY-0244793. One of the author (SYL) thanks supports from the Humboldt Foundation in Germany and the Indiana University, USA. He also thanks Prof. I. Hofmann for

helpful discussions and GSI for kind hospitality during this research leave.

-
- [1] F.J. Sacherer, *Transverse Space-charge effects in circular accelerators*, Ph.D. Thesis, UCRL-18454 (UC berkeley, 1968).
 - [2] S. Y. Lee, *Accelerator Physics*, 2nd edition (World Scientific, Singapore, 2004).
 - [3] *High Intensity and High Brightness Hadron Beams*, AIP proceedings No. **773**, edited by I. Hofmann, J.M. Lagniel, and R.W. Hasse (AIP, New York 2004).
 - [4] *Space-charge dominated beams and applications of high brightness beams*, AIP Conference Proceedings **377**, edited by S.Y. Lee (AIP, New York, 1996).
 - [5] B.W. Montague, CERN-Report No. 68-38, (CERN, 1968); I. Hofmann, *et al.*, p. 169 in Ref. [3]; I. Hofmann *et al.*, Proc. of 2005 Particle Accelerator Conference, p. 330 (IEEE. N.Y., 2005).
 - [6] S. Cousineau, Ph.D. Thesis, Indiana University, (2002); S. Cousineau, *et al*, Physical Review Special Topics in Accelerators and Beams, **6**, 034205 (2003).
 - [7] X. Huang, S.Y. Lee, Eric Prebys, Chuck Ankenbrandt, Proceedings of PAC05 (2005).
 - [8] X. Huang, S.Y. Lee, E. Prebys, and R. Tomlin, Phys. Rev. Special Topics, Accelerators and Beams, **8**, 064001 (2005).
 - [9] X. Huang and S.Y. Lee, Fermilab Tech-memo FERMILAB-TM-2326-AD (2005).
 - [10] J. Amundsen *et al*, Phys. Rev. Special Topics, Accelerators and Beams **6**, 102801 (2003). The computer code from James Amundson was used to fit the profile data and calibrate the beam width.
 - [11] See e.g. A. Piwinski, *Intrabeam Scattering*, CERN-92-01, p. 226 (1992).
 - [12] M. Reiser, *Theory and design of charged particle beams*, See Eq. (6.186) (Wiley, New York, 1994).
 - [13] S. Ohnuma, Fermilab Technical Memo TM-1381-A, 1986
 - [14] S.Y. Lee and J.M. Wang, Proc. of the Particle Accelerator Conference 1985, p. 2323 (1985).
 - [15] D. Huang, S.Y. Lee and K.Y. Ng, Fermilab-FN-0774-AD (2005).
 - [16] A. Sorrensen, Particle Accelerators **6**, 141 (1975).
 - [17] W. Guo and S.Y. Lee, Phys. Rev. E **65**, 066505 (2002); M.H. Wang, Y. Sato, and S.Y. Lee, Proceedings of the 2003 Particle Accelerator Conference, p. 3240 (PAC, 2003).
 - [18] X. Huang and S.Y. Lee, Fermilab Tech-memo, FERMILAB-TM-2327-AD (2005)

- [19] M.H. Wang, and S.Y. Lee, Journal of Applied Physics, **92**, 555 (2002).
- [20] Bill Pellico, private communication (2005).
- [21] S. Kheifit, PETRA Note 119 (1976).