B9

162

PACIFIC GAS AND ELECTRIC COMPANY
THE GEYSERS POWER PLANT
UNIT NO. 3
PLANT DATA

Donated By:
Herbert Rogers Jr.
Rogers Engineering Co.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

TABLE 3—COMBUSTION CONSTANTS

No.	Substance	Formula	Molecular Weight ^a	Lbs. per Cu.Ft. ^b	Cu.Ft. per Lb. ^b	Sp. Gr. Air = 1.000 ^b	Heat of Combustion ^a				Cu.Ft. per Cu.Ft. of Combustible						Lbs. per Lb. of Combustible						Experimental Error in Heat of Combustion Percent + or -		
							B.t.u. per Cu.Ft.		B.t.u. per Lb.		Required for Combustion			Flue Products			Required for Combustion			Flue Products					
							Gross	Net ^d	Gross	Net ^d	O ₂	N ₂	Air	CO ₂	H ₂ O	N ₂	O ₂	N ₂	Air	CO ₂	H ₂ O	N ₂			
1	Carbon	C	12.01	...	...	...	...	...	14,093 ^e	14,093 ^e	...	...	...	...	...	...	2.554	8.853	11.527	3.654	...	5.263	0.012		
2	Hydrogen	H ₂	2.016	0.005327	187.723	0.06959	324.9 ^a	274.9 ^a	60,991	61,605 ^f	0.8	1.882	2.382	...	1.0	1.882	7.937	26.406	34.344	...	3.937	28.407	0.015		
3	Oxygen	O ₂	32.000	0.08451	11.819	1.1053	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...		
4	Nitrogen (atoms.)	N ₂	28.016	0.07439 ^a	13.443 ^a	0.9718 ^a	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...		
5	Carbon monoxide	CO	28.01	0.07404	13.506	0.9872	321.6 ^a	321.6 ^a	4,323	4,323 ^a	0.8	1.882	2.382	1.0	...	1.882	0.571	1.600	2.471	1.571	...	1.900	0.048		
6	Carbon dioxide	CO ₂	44.01	0.1170	8.548	1.5282	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...		
Paraffin series C _n H _{2n+2}																									
7	Methane	CH ₄	16.042 ^a	0.04246 ^a	23.552 ^a	0.5543	1014.0 ^a	914.5 ^a	23,896	21,537 ^a	2.0	7.528	9.528	1.0	2.0	7.528	3.990	13.275	17.265	2.744	2.248	13.275	...	0.033	
8	Ethane	C ₂ H ₆	30.068 ^a	0.08029 ^a	12.455 ^a	1.04882 ^a	1739 ^a	1639 ^a	22,282	20,394 ^a	3.5	13.175	16.575	2.0	3.0	13.175	3.725	12.394	16.110	2.927	1.793	12.394	...	0.030	
9	Propane	C ₃ H ₈	44.094 ^a	0.1196 ^a	8.365 ^a	1.5617 ^a	2573 ^a	2373 ^a	21,523	19,807 ^a	5.0	18.821	23.821	3.0	4.0	18.821	3.629	12.074	15.703	2.994	1.634	12.074	...	0.023	
10	n-Butane	C ₄ H ₁₀	58.120 ^a	0.1582 ^a	6.321 ^a	2.06654 ^a	3392 ^a	3142 ^a	21,441	19,313 ^a	6.5	24.467	30.967	4.0	5.0	24.467	3.579	11.908	15.487	3.029	1.550	11.908	...	0.022	
11	Isobutane	C ₄ H ₁₀	58.120 ^a	0.1582 ^a	6.321 ^a	2.06654 ^a	3363 ^a	3105 ^a	21,257	19,629	6.5	24.467	30.967	4.0	5.0	24.467	3.579	11.908	15.487	3.029	1.550	11.908	...	0.019	
12	n-Pentane	C ₅ H ₁₂	72.146 ^a	0.1904 ^a	5.252 ^a	2.4872 ^a	4200 ^a	3900 ^a	22,058	20,185 ^a	8.0	30.114	38.114	5.0	6.0	30.114	3.548	11.805	15.353	3.050	1.498	11.805	...	0.025	
13	Isopentane	C ₅ H ₁₂	72.146 ^a	0.1904 ^a	5.252 ^a	2.4872 ^a	4008 ^a	3716 ^a	21,052	19,478	8.0	30.114	38.114	5.0	6.0	30.114	3.548	11.805	15.353	3.050	1.498	11.805	...	0.071	
14	Neopentane	C ₅ H ₁₂	72.146 ^a	0.1904 ^a	5.252 ^a	2.4872 ^a	3693 ^a	3593 ^a	20,970	19,396	8.0	30.114	38.114	5.0	6.0	30.114	3.548	11.805	15.353	3.050	1.498	11.805	...	0.11	
15	n-Hexane	C ₆ H ₁₄	86.169	0.2274 ^a	4.398 ^a	2.9704 ^a	4762	4412	20,940	19,403	9.5	35.760	45.260	6.0	7.0	35.760	3.528	11.738	15.268	3.054	1.464	11.738	...	0.05	
Olefin series C _n H _{2n}																									
16	Ethylene	C ₂ H ₄	28.052 ^a	0.07421 ^a	13.475 ^a	0.9740	1614 ^a	1514 ^a	21,647	20,298 ^a	3.0	11.293	14.293	2.0	2.0	11.293	3.422	11.385	14.807	3.138	1.285	11.385	...	0.021	
17	Propylene	C ₃ H ₆	42.078 ^a	0.1110 ^a	9.007 ^a	1.4504 ^a	2385 ^a	2233 ^a	21,464	20,115 ^a	4.5	16.939	21.439	3.0	3.0	16.939	3.422	11.385	14.807	3.138	1.285	11.385	...	0.031	
18	n-Butene (Butylene)	C ₄ H ₈	56.104 ^a	0.1480 ^a	6.756 ^a	1.9336 ^a	3180 ^a	2990 ^a	21,552	20,203 ^a	6.0	22.585	28.585	4.0	4.0	22.585	3.422	11.385	14.807	3.138	1.285	11.385	...	0.031	
19	Isobutene	C ₄ H ₈	56.104 ^a	0.1480 ^a	6.756 ^a	1.9336 ^a	3180 ^a	2980 ^a	21,484	20,135 ^a	6.0	22.585	28.585	4.0	4.0	22.585	3.422	11.385	14.807	3.138	1.285	11.385	...	0.031	
20	n-Pentene	C ₅ H ₁₀	70.130 ^a	0.1852 ^a	5.400 ^a	2.4180 ^a	4000 ^a	3750 ^a	21,600	20,211 ^a	7.5	28.232	35.732	5.0	5.0	28.232	3.422	11.385	14.807	3.138	1.285	11.385	...	0.037	
Aromatic series C _n H _{2n-6}																									
21	Benzene	C ₆ H ₆	78.180 ^a	0.2060 ^a	4.852 ^a	2.6020 ^a	3630 ^a	3780 ^a	19,068	18,341 ^a	7.5	28.232	35.732	6.0	3.0	28.232	3.073	10.224	13.297	3.381	0.892	10.224	...	0.12	
22	Toluene	C ₇ H ₈	92.134 ^a	0.2431 ^a	4.113 ^a	3.1760 ^a	4750 ^a	4550 ^a	19,537	18,716 ^a	9.0	33.878	42.878	7.0	4.0	33.878	3.126	10.401	13.627	3.364	0.782	10.401	...	0.21	
23	Xylene	C ₈ H ₁₀	106.158	0.2803 ^a	3.567 ^a	3.6618 ^a	5230	4980	18,650	17,760	10.5	39.524	50.024	8.0	5.0	39.524	3.165	10.530	13.695	3.317	0.849	10.530	...	0.36	
Miscellaneous gases																									
24	Acetylene	C ₂ H ₂	26.036	0.06971	14.344	0.9107	1488 ^a	1438 ^a	21,344	20,617 ^a	2.5	9.411	11.911	2.0	1.0	9.411	3.073	10.224	13.297	3.381	0.892	10.224	...	0.16	
25	Naphthalene	C ₁₀ H ₈	128.162	0.3394 ^a	2.955 ^a	4.4208 ^a	5854 ^a	5654 ^a	17,298 ^a	16,708 ^a	12.0	45.170	57.170	10.0	4.0	45.170	2.993	9.995	12.994	3.434	0.562	9.995	...	...	
26	Methyl alcohol	CH ₃ OH	32.041	0.0848 ^a	11.820 ^a	1.1052 ^a	867.9	768.0	10,259	9076	1.5	5.646	7.146	1.0	2.0	5.646	1.408	4.984	6.482	1.374	1.125	4.984	...	0.027	
27	Ethyl alcohol	C ₂ H ₅ OH	46.067	0.1216 ^a	8.221 ^a	1.6890 ^a	1600.3	1450.5	13,161	11,929	3.0	11.293	14.293	2.0	3.0	11.293	2.084	6.934	9.018	1.622	1.170	6.934	...	0.030	
28	Ammonia	NH ₃	17.031	0.0455 ^a	21.914 ^a	0.6961 ^a	441.1	355.1	9663	8001	0.75	2.523	3.673	...	1.5	3.323	1.400	4.688	6.097	...	1.527	5.511	...	0.038	
Sulfur																									
29	Sulfur	S	32.06	...	...	...	...	...	3983	3983	...	...	...	...	...	...	0.903	3.287	4.235	1.698	...	3.287	...	0.071	
30	Hydrogen sulfide	H ₂ S	34.076	0.09109 ^a	10.979 ^a	1.1898 ^a	647	565	7100	6345	1.5	5.646	7.146	1.0	1.0	5.646	1.409	4.638	6.097	1.880	0.529	4.585	...	0.30	
31	Sulfur dioxide	SO ₂	64.05	0.1733	5.770	2.264	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	
32	Water vapor	H ₂ O	18.016	0.04758 ^a	21.017 ^a	0.6215 ^a	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	
33	Air		28.9	0.07658	13.063	1.0000	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	...	

All gas volumes corrected to 60°F and 30 in. Hg dry. For gases saturated with water at 60°F, 1.74% of the B.t.u. value must be deducted.

^a Calculated from atomic weights given in *Journal of the American Chemical Society*, February 1937.

^b Densities calculated from values given in grams per liter at 0°C and 760 mm. in the International Critical Tables allowing for the known deviations from the gas laws. Where the coefficient of expansion was not available, the assumed value was taken as 0.0037 per °C. Compare this with 0.003982 which is the coefficient for a perfect gas. Where no densities were available the volume of the mole was taken as 22.4115 liters.

^c Converted to mean B.t.u. per lb. (1/10 of the heat per lb. of water from 32 to 212°F) from data by Frederick D. Rossini, National Bureau of Standards, letter of April 10, 1937, except as noted.

^d Deduction from gross to net heating value determined by deducting 18,910 B.t.u. per lb. mole of water

in the products of combustion. Osborne, Stimson, and Ginnings, *Mechanical Engineering*, p. 163, March 1935, and Osborne, Stimson, and Fieck, National Bureau of Standards Research Paper 209.

^e Denotes that either the density or the coefficient of expansion has been assumed. Some of the materials cannot exist as gases at 60°F and 30 in. Hg pressure, in which case the values are theoretical ones given for ease of calculation of gas problems. Under the actual concentrations in which these materials are present their partial pressure is low enough to keep them as gases.

^f From Third Edition of "Combustion."

^g National Bureau of Standards, RP 1141.

^h Linden, H. R. "Encyclopedia of Chemical Technology," Vol. 6, The Interscience Encyclopedia, Inc., N. Y. (1951).

ⁱ Calculated from data in Table 13, page 23.

Fig. 2 Mean molal specific heat of gases between final temperature (t_2) and 80F at standard atmospheric pressure.

Fig. 3 Water content of air for various wet- and dry-bulb temperatures.

Table 7 Molal Quantities—converted to lb units See Combustion Calculations—Molal Basis for line references							L I N E
a ¹	Air (dry) supplied per unit of fuel = moles air, line 17 × 29, (mol. wt air)					1166.4 lb	a ¹
b ¹	H ₂ O in air supplied per unit of fuel = moles H ₂ O, line 18 × 18, (mol. wt H ₂ O)					15.3 lb	b ¹
c ¹	Wet air supplied per unit of fuel = lines a ¹ + b ¹					1181.7 lb	c ¹
d ¹	Wet air supplied per lb of fuel { Line c ¹ ÷ 100 for solid or liquid fuels Line c ¹ ÷ line f for gaseous fuels					11.82 lb	d ¹
e ¹	Flue gas constituent and mol. wt	CO ₂ + SO ₂ 44 64	O ₂ 32	N ₂ 28	H ₂ O 18	CO 28	e ¹
f ¹	Wet F.G., % by vol = 100 × line 20 ÷ line s (wet)*	14.14	3.30	74.40	8.16		f ¹
g ¹	Dry F.G., % by vol = 100 × line 20 ÷ line s (dry)*	15.40	3.59	81.01			g ¹
h ¹	Wt of each constit = line 20 × mol. wt of each, lb	264.0 3.2	45.1	891.0	62.8		h ¹
i ¹	Total wt flue gas = Σ (line h ¹ wet) and Σ (line h ¹ dry)	Wet wt	1266.1 lb	Dry wt	1203.3 lb		i ¹
j ¹	Wet flue gas per lb fuel { Wet wt, line i ¹ ÷ 100, solid and liquid fuels Wet wt, line i ¹ ÷ line f, gaseous fuels				12.66 lb		j ¹
k ¹	Dry flue gas per lb fuel { Dry wt, line i ¹ ÷ 100, solid and liquid fuels Dry wt, line i ¹ ÷ line f, gaseous fuels				12.03 lb		k ¹
l ¹	Molecular wt of wet flue gas = wet wt, line i ¹ ÷ wet moles, line s				29.60		l ¹
m ¹	Molecular wt of dry flue gas = dry wt, line i ¹ ÷ dry moles, line s				30.63		m ¹
n ¹	Density of wet flue gas = line l ¹ ÷ 394† (at 80 F and 30 in. Hg)				0.0751 lb/cu ft		n ¹
o ¹	Density of dry flue gas = line m ¹ ÷ 394† (at 80 F and 30 in. Hg)				0.0778 lb/cu ft		o ¹

*Flue gas analysis as calculated, based on total air, line d, assigned or observed.
The calculated values, line g¹, should agree substantially with ORSAT analysis when flue gas is analyzed.
†Volume of 1 mole of any gas at 80 F and 30 in. Hg = 394 cu ft.

CONTENTS

GENERAL DESCRIPTION

E 44412

PERFORMANCE

THROTTLE FLOW 509,600 S/HR
 GENERATOR ELEC. OUTPUT 27,500 KW
 AUX. POWER, ELECTRICAL:
 CIRC. WATER PUMPS 590 KW
 COOLING TOWER FANS 200 KW
 OTHER 10 KW
 TOTAL 800 KW

NET UNIT OUTPUT 26,700 KW
 HEAT INPUT 633×10^6 BTU/HR
 NET HEAT RATE 23,200 BTU/KWH
 REFERRED TO 60°F

CONDITIONS

GENERATOR POWER FACTOR 0.98
 TURBINE EXHAUST BACK PRESS. 4.0 Hg
 DRY BULB AIR TEMP 78°F
 WET BULB AIR TEMP 65°F
 ALL STEAM FLOWS INCLUDE 1.0 %
 NON-CONDENSIBLE GASES

LEGEND

--- MAIN STEAM LINE
 --- WATER LINE
 --- STEAM LINE
 --- GAS LINE
 S POUNDS PER HOUR OF STEAM
 W POUNDS PER HOUR OF WATER
 B POUNDS PER HOUR OF GASES
 F DEGREES FAHRENHEIT
 H ENTHALPY OF STEAM BTU/LB
 A ABSOLUTE PRESSURE-PSIA
 G GAUGE PRESSURE-PSIG

NO.	DATE	DESCRIPTION	GM	BY	CH.	APPD.	NO.	DATE	DESCRIPTION	GM	BY	CH.	APPD.

TABLE OF CHANGES

APPROVED FOR CONSTRUCTION

TABLE OF CHANGES

APPROVED BY	GM 159324
SUPV. BY	R. Ordian
DESIGN	R. Subroth
DR.	J. Kelere
CH.	
O.K.	R. Ordian
DATE	11-22-65
SCALES	None

HEAT BALANCE DIAGRAM
 MAXIMUM GUARANTEED LOAD
 UNIT NO. 3
 THE GEYSERS POWER PLANT
 DEPARTMENT OF ENGINEERING
 PACIFIC GAS AND ELECTRIC COMPANY
 SAN FRANCISCO, CALIFORNIA

BILL OF MATERIAL	
DRAWING LIST	
SUPERSEDED	
SUPERSEDED BY	
SHEET NO.	214443
DRAWING NUMBER	
CHANGES

KEY MAP
SCALE IN MILES

NO.	DATE	DESCRIPTION	BY	CHK.	APPROVED	NO.	DATE	DESCRIPTION	BY	CHK.	APPROVED
1	1-28-64	APPROVED FOR CONSTRUCTION	JES	AKB	AKB	2	1-28-64	APPROVED FOR CONSTRUCTION	JES	AKB	AKB
TABLE OF CHANGES						TABLE OF CHANGES					

APPROVED BY: *[Signature]*
DATE: 1-28-64
SCALE: 1"=80' HY

GENERAL LAYOUT PLAN
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

REVISIONS
NO. DATE DESCRIPTION
1 1-28-64 APPROVED FOR CONSTRUCTION
2 1-28-64 APPROVED FOR CONSTRUCTION

432591

TURBINE-GENERATOR

TURBINE

Manufacturer	Elliott Division of Carrier Corp.
Purchase Order Number	4R 34093
Serial Number	B-4908
Size	NB-7
Type	Horizontal shaft, 7-stage, condensing
Kilowatt Rating	27,500
Rated Speed	3,600 rpm
Critical Speed	2,366 rpm
Steam Pressure	78.9 psia
Steam Temperature	341.8 F
Exhaust-Vacuum	4 in. Hg abs
Approximate Weight-Turbine	120,000 lb
Approximate Weight-Rotor	11,500 lb

GENERATOR

KVA	32,000
KW	28,000
P.F.	0.90
Hydrogen	30 psig
Volts	13,800
Amp.	1,340
Freq.	60 cps
Fld. Volts	250
Fld. Amp.	450
Stator Wt.	115,000 lb
Rotor Wt.	30,000 lb

REF. NO.

TITLE PACIFIC GAS AND ELECTRIC COMPANY

CURVE

No. B4908-A

27,500 KW TURBINE GENERATOR UNIT
78.9° PSIA (1200 BTU) 341.8°F.T.T. - 1"Hg.abs.

Approximate First Stage Pressure

KW OUTPUT X 1000

60

50

40

30

20

10

15

20

25

30

35

REF. NO.

TITLE

PACIFIC GAS AND ELECTRIC COMPANY

CURVE

NO. B-4908-A-1

27,500 KW TURBINE GENERATOR UNIT
78.97 PSIA (1200 BTU) 841.8°F T.T. - 4" Hg. Abs.

WATER VAPOR PRESSURE

Throttle Flow $\frac{lb}{hr} \times 1000$

ELLIOTT COMPANY ENGINEERING DEPT. JEANNETTE, PA.

BY JFC

DATE 4/7/65

REF. NO.

TITLE

Pacific Gas and Electric Company

27,500 Turbine-Generator Unit

78.97 PSIA (1200 Btu) 341.8°F TT - 4" Hg. Abs.

Pressure Corrs. Factor (Approx.)

Throttle Pr. Absolute

CURVE
NO.

ELLIOTT COMPANY

A DIVISION OF CARRIER CORPORATION

BY HAL

9/15/64
DATE 7/24/64

NO. 218 - 30 DIVISIONS PER INCH BOTH AXES - 120 BY 300 DIVISIONS

COOPER BOOK COMPANY, INC. NEW YORK, N.Y.

REF. NO. TITLE PACIFIC GAS AND ELECTRIC COMPANY

CURVE No. B-4908-2

TEMP. & VAC. CORR. CURVE
27,500 Turbine Generator Unit
78.9# PSIA (1200 Btu) 341.8°FIT - 4" Hg. Abs.

Temp. Corr. Factors (Approx.)

Expected Vacuum Correction (Approximate)

Temperature

REF. NO.

TITLE PACIFIC GAS AND ELECTRIC COMPANY

CURVE NO. B-4908-3

27,500 Turbine Generator Unit
78.5% FEA (1200 BTU) 341.8°F - 4" Hg. Abs.

EXTRACTED RED POINT H₂O

1080
1060
1040
1020
1000

T/HR - THROTTLE FLOW
X 1000

CURVE NO.

ELLIOTT COMPANY
A DIVISION OF CARRIER CORPORATION

BY JFC

DATE 2/15/65

REF. NO. _____ TITLE PACIFIC GAS AND ELECTRIC COMPANYCURVE
NO. B-4908-4

27,500 Turbine Generator Unit
 78.9# PSIA (1200 Btu) 341.8° FTT - 4" Hg. Abs.

Leakage Enthalpy

Steam Leakage #/Hr.

1200

1160

600

400

200

0

0

5000

10000

15000

20000

25000

30000

KW OUTPUT

Sealing Steam Required

Leakage Steam to Water Eductor (Exhaust End) 160#/Hr. 25-30 cfm air
 " " " " " (Steam End) 110#/Hr. 20-25 cfm air

NO. 318. 30 DIVISIONS PER INCH BOTH WAYS. 100 BY 400 DIVISIONS.

NO. 318. 30 DIVISIONS PER INCH BOTH WAYS. 100 BY 400 DIVISIONS.

SCHUTTE & KOERTING CO.
CORNWELLS HEIGHTS PA.

PERFORMANCE OF
2½" GLAND CONDENSER
P.O. 52-8-091

NO TAIL PIPE

AVERAGE WATER TEMP 93°F

WATER CONSUMPTION

10 PSI-G	22.0 GPM
20 PSI	30.5 GPM
30 PSI	37.5 GPM
40 PSI	43.0 GPM
50 PSI	48.5 GPM
60 PSI	53.0 GPM
70 PSI	57.5 GPM
80 PSI	61.5 GPM
90 PSI	65.0 GPM
100 PSI	69.0 GPM

52-K-145-J

ROUGH DRAFT
(2/4/66)

TURBINE EXHAUST DUCT AND DRIP PUMPS

1. GENERAL DESCRIPTION

The turbine exhaust duct carries exhaust steam from the turbine to the barometric condensers. Design and construction of the duct is in accordance with the ASME Boiler and Pressure Vessel Code, Section VIII, 1962. The materials of the duct are stainless steel.

Steam leaves the turbine exhaust hood travelling vertically downward. A duct elbow and a transition section turn the flow to horizontal and conduct the steam to a duct tee section. The tee section is of vertical cylindrical form; it conducts steam upward to a wye. The steam flow is divided at the wye, half the steam is conducted to each of two barometric condensers via two elbows. The steam enters the condensers through their sides, near the bottoms.

The tee section of the duct has two expansion joints near its top, and one expansion joint near the bottom, above the dished head bottom. It is restrained from excessive vibration by a system of vibration snubbers which have flexible ball type stub joints at each end.

The dished head on the bottom of the duct tee section will collect any liquid condensed from the steam travelling through the duct. Two exhaust duct drip pumps are provided to remove excess water from the duct. As accumulation of an excessive amount of water in the duct could cause damage to the turbine, a high liquid level trip (HLT-1) and a backup high liquid level trip (HLT-2) are provided, either of which will actuate the turbine lockout relay. In addition, the turbine lockout relay is actuated if either of the duct drip pump circuit breakers is open. Piping and valving is provided whereby a part of the drip pumps' discharge is recirculated through the duct tee section to permit operation of the drip pumps during start-up and shutdown of the Unit.

2. TURBINE EXHAUST DUCT

Manufacturer	Saracco Tank and Mfg. Co.
Purchase	4-R 42549
Shell	
Material	Type 304L stainless steel
Rectangular Section	
and Transition Section	3/8 inch plate
Tee section and	
11 ft. dia. section	5/16 inch plate
Wye Branch	3/8 inch plate
8 ft. Dia. Sections	5/16 inch plate
Exterior Stiffeners, Supports	ASTM A-36 steel
Expansion joints:	
Manufacturer	TempFlex Co.
Material	T304 El C stainless steel
Supports:	
Transition Section	2 - Bergen V.S.1 F19
Tee Section	4 - Bergen DSV-4 Type D
Vibration Snubbers	2 - Barco Vibrasnub No.10-50513 4 inch 4 - Barco Vibrasnub No.10-50512 2-1/2 inch

Weights (estimated) :

Elbow Section

31,507 lb $\frac{1}{2}$

Wye Branch and Elbows

44,167 lb $\frac{1}{2}$

Tee Section

36,280 lb $\frac{1}{2}$

3. EXHAUST DUCT DRIP PUMP

Number of units

2

Manufacturer

Peerless Pump Division, FMC

Purchase Order

4R-45269

Type of Pump

Centrifugal, horizontal shaft

Pump Size

2 x 3 x 8-1/2

Fluid Pumped:

Water

Temperature

125°F

Capacity

60 gpm

Head

50 ft $\frac{1}{2}$

Speed

1750 rpm

Flanges

150 lb $\frac{1}{2}$ ASA, 1/16 inch
raised face

Pump Serial Numbers

208597, 208598

4. EXHAUST DUCT DRIP PUMP MOTOR

Number of Units

2

Manufacturer

General Electric Company

Horsepower

2

Volts

440

Phase

3

Cycle

60

Frame

184

RPM

1800

LUBRICATING OIL SYSTEM

A. General Description

Oil systems are provided to lubricate the turbine-generator bearings, to supply the ~~hydrostatic~~ turbine controls, and to seal the generator shaft openings against hydrogen gas leakage. The hydrogen seal-oil system is separately described in the section describing the generator.

An oil reservoir is provided by the turbine manufacturer. It is vented to atmosphere through an a-c motor driven vapor exhaust blower or through a d-c motor driven stand-by exhauster. The main oil pump, the auxiliary oil pump, the d-c stand-by oil pump, and the turning gear lubricating oil pump all take oil from the reservoir. The reservoir receives oil drains from the bearings and the turbine control systems. It also can receive oil either from delivery truck or from the lubricating oil filter pump.

The turbine oil reservoir sits on top of a lubricating oil storage tank, which is divided into two compartments for the storage of clean and dirty oil. Any overflow from the dirty oil storage compartment discharges to a sump well. A three compartment filter system^{manufactured} by Bowser Company is provided for oil purification.

Two full capacity oil coolers are provided to receive lubricating oil and cool it to ____°F before it is delivered to the bearing oil header. The ~~cooler~~ valve arrangement permits servicing one cooler at a time without shutting down the Unit.

B. MAIN LUBRICATING OIL PUMP

The main lubricating oil pump is a centrifugal unit mounted on the governor end of the turbine shaft. The pump discharges at approximately 150 psig when operated at rated speed with a 20 psig suction head. The pump is not self priming, about one half of its discharge flow is used to operate an ejector located in the lubricating oil reservoir which in turn supplies the

suction pressure for the ~~main~~ pump. Initial priming during the start-up is provided by the auxiliary lubricating oil pump.

C. AUXILIARY LUBRICATING OIL PUMP

The auxiliary lubricating oil pump is a vertical shaft centrifugal unit mounted on the lubricating oil reservoir. It is driven by a 30 hp, 480 volt, 3 phase motor. It supplies both the control oil and lubricating oil requirements of the Unit during start-up and shutdown.

If automatic operation of the pump is selected the pump will start on a drop of the main oil pump discharge pressure to 60 psig (APS-3).

D. D-C STAND-BY LUBRICATING OIL PUMP

The d-c stand-by lubricating oil pump is provided to supply lubrication for the turbine-generator bearings during roll-down after an overall Unit trip.

If automatic starting of the pump is selected the pump will start on a drop of bearing oil header pressure to 4 psig (APS-1). The pump will shut down on a rise in oil pressure to 6 psig, which would occur on starting of the a-c motor driven auxiliary oil pump, or it can be shut down manually. In addition a timer is provided that can be set to trip the pump motor after a period of time sufficient ^{for the turbine-generator} to roll to a stop. The purpose of this timed trip is to save station battery capacity for operation of the d-c operated seal oil stand-by pump.

D. LUBRICATING OIL DISTRIBUTION AND USE

The 150 lb_x oil system is used directly to operate the main pump ejector and to provide hydraulic operating power to the turbine steam admission valves. A combination of a reducing orifice (RO-2) and a relief valve (RV-3) provide oil from the 150 lb_x system to a 75 lb_x system which serves the turbine governor with control oil and serves the turbine trip valve system.

A hydrogen seal oil back-up supply is derived from the 75 lb_x oil system via pressure control valve VPC-2.

Unit bearing lubricating oil is provided at approximately 15 psig from the 75 lb_x system through a combination of reducing orifice RO-1 and relief valve RV-2.

Oil discharged at approximately 15 psig from the turning gear lubricating oil pump will supply Unit bearing lubrication when the unit is on turning gear. The turning gear lubricating oil pump discharge also serves as an additional stand-by supply for the hydrogen seal oil system.

TURNING GEAR

A motor-driven turning gear is provided to rotate the turbine-generator rotor during shutdown to minimize rotor distortion during the cooling-off period. It can also be used to rotate the turbine for start-up or to jog the rotor into a desired position for maintenance. Turbine rotation when driven by the turning gear is approximately 10 rpm.

The turning gear motor is locked out of operation if pressure in the turbine-generator bearing lubrication header is less than 4 psig.

B. GENERATOR

1. Generator General Description

The Unit 3 generator is a 3,600 rpm, hydrogen cooled, 13,800 volt, two pole, three phase, sixty cycle synchronous generator.

It is wye-connected, ^{self excited through static} ~~with excitation power taken from current-excitation equipment, and equipped with static voltage transformers inserted between generator winding terminals and the regulation equipment.~~ wye connection point.

Auxiliary equipment required for and supplied with the generator are a hydrogen gas supply and control system, a carbon dioxide gas supply and control system, a seal oil system, a gas dryer system, gas purity indication equipment, water detection equipment, and ^{the} an excitation and voltage control system.

2. Generator Ratings

- a) The generator is rated, at 30 psig hydrogen gas pressure, with both hydrogen gas coolers in operation, continuous capability:

Kva	32,000
Pf	0.90 (lagging)
Kw	28,800
Volts	13,800
Amperes	1,340
Short Circuit Ratio	0.65

- b) Continuous capability, when operated at 0.95 pf leading and at 95% of rated voltage, is 28,000 kw.
- c) Continuous capability at 0.90 pf leading and at 95% of rated voltage is 26,000 kw.

- d) Continuous capability when operated at rated conditions except with one hydrogen cooler out of service is 19,500 kw.
- e) Maximum temperature rises with gas cooling supply not exceeding 46 C, and with gas pressure of 30 psig:

Stator Winding (by detector)	45 C
Field Winding (by resistance)	79 C
Collector (by thermometer)	85 C
Core and Mechanical Parts (by thermometer)	64 C

f) Insulation Dielectric Tests:

Stator	28,600 volts
Rotor	2,500 volts

g) Excitation Requirements at Rated Conditions:

Kw	120
Volts	250

h) Volume to be Gas Filled: 720 cu ft.

i) Cooling Water

Temperature	95 F
Quantity	500 gpm
Pressure Drop	8 ft.

3. Generator Construction

a) Stator

The frame consists of annular steel plates with spacing bars between them, enclosed by a steel wrapper plate, all electrically welded together. Bolting flanges are welded to the ends of the

frame for attachment of similar flanges on the end domes. The bolted joint is made gas-tight by forcing a non-hardening sealing compound into a groove in one of the mating members under high pressure.

Studs extending lengthwise of the frame at its inner periphery project through clamping plates at each end of the core and apply clamping pressure to the core. The studs are welded to intermediate annular frame plates. The studs and clamping plates are made heavy to eliminate any necessity for insulated clamping bolts extending through and surrounded by the core.

The core consists of silicon steel laminations, individually insulated with baked-on enamel. The laminations partly surrounded the axial studs at the inner periphery of the frame. The studs locate and key the laminations in place. Non-magnetic steel fingers maintain longitudinal clamping pressure on the teeth at both ends of the core.

Double frequency vibrations are present in two pole generators and consideration is given in the machine design to reduce and isolate these 120 cycle vibrations. The core is supported by slotted frame plates laid out in a manner to provide an elastic mounting of the core structure inside the frame, which isolates the vibration. The core stacking studs welded to the inner periphery of the slotted frame plates maintain a rigid core support within the elastic mounting.

Radial ventilation ducts are provided at intervals along the core. Cooling gas, impelled by blowers located on the rotor, is forced into the generator air gap and out through radial vent ducts in the core. Laminations at each end of the core are stepped back to a larger diameter to facilitate entry of gas into the air gap. Some of the cooling gas is forced through ducts in the frame outside the core into chambers near the middle of the core. From these the gas is forced inward radially through core vent ducts to the air gap where it travels axially along the air gap, mingles with gas forced in from the ends of the air gap and is discharged radially outward through other ducts in the core. Hot spots in the middle of the core are eliminated by this ventilation system.

The generator coils are constructed with Class B insulation, vacuum pressure impregnated, and finished with a layer of glass tape and painted with black insulating varnish. To reduce corona, a semi-conducting paint is applied to the straight sections of the coil and extended beyond the core. A laminated phenolic spacer, impregnated with semi-conducting material, is used between coil sides in the stator slots. Non-shrinking phenolic slot wedges are used.

The stator windings are braced to withstand forces imposed by fault currents. Rows of phenolic spacing blocks are fitted between adjacent coils and lashed in place with glass twine, arch-bracing the end winding. Insulating plates are supported from the frame clamping plates, to which the coils are lashed with glass twine. Upper and lower layers of the end winding are also blocked apart at each of these supporting plates.

b) Rotor

The rotor body and shaft ends are machined from a single piece heat treated carbon steel forging. Axial slots are milled in the outer periphery to carry the field coils. The outside surface of the rotor is grooved to reduce surface losses and to increase the surface available for dissipation of heat.

The rotor windings are of copper strap bent on edge. Insulation between turns consists of mica tape. Ground insulation consists of moulded mica slot cells for the embedded portions of the coils and additional mica tape on several of the top turns of each coil, finished with glass protective tape over end turns. The turns are varnished as they are placed in the slots and the rotor is baked. Slot wedges are of high strength aluminum alloy.

The end turns of the rotor are held in place against centrifugal force by alloy steel cylindrical retaining bands shrunk on the ends of the rotor body. The bands are lined on the inside with asbestos phenolic insulation moulded in place. The outboard ends of the retaining bands are shrunk over end plate rings which extend toward the shaft a sufficient distance to cover and protect the coil ends. The end plates provide the means to mount axial-flow, blower impellers, ^{and ?} are also drilled and ^{tapped} to receive balance weights. x ?

End turns of the rotor coils are braced apart in axial and transverse directions with asbestos phenolic blocks. Radial slots in the sides of these blocks form vent ducts for cooling. Additional ventilation is drawn through slots beneath the rotor field coils and discharged through radial holes to the periphery of the rotor.

4. Lubrication

The two generator shaft bearings are lubricated from an oil header served by the turbine lube oil system. Oil discharged from bearing No. 3 is used to lubricate the coupling between the turbine and the generator. High temperature alarm and high temperature tripping is provided on the discharge oil from each bearing.

5. Generator Cooling

a) Generator Cooling - General Description

The Unit 3 generator is cooled by circulating hydrogen gas. Hydrogen is used instead of air because of its lower density and superior heat conducting properties. The hydrogen operates in a closed system in an allowable gas static pressure range between 0.5 and 30 psig. Axial-flow blowers mounted at each end of the generator rotor circulate the hydrogen gas. Four vertical-tube heat exchangers, located one at each corner of the generator frame, cool the hydrogen. 2

Precautions must be taken to avoid hydrogen leaking from or air leaking into the generator, both to conserve hydrogen and to eliminate the possibility of creating an explosive air-hydrogen mixture. Some hydrogen gas is lost from the system continually, and replacement is made from the hydrogen supply system.

The generator shell and end domes are constructed and fitted to eliminate gas leakage, and a special seal oil system is provided to eliminate gas leakage ^{where} when the generator shaft extends through the end domes. In addition the shell and dome structure is designed to withstand forces resulting from an internal explosion.

A carbon dioxide (CO₂) gas supply is provided to be used to avoid creating any hydrogen-air mixtures when the generator is shut down to be opened for inspection or maintenance work. When the generator is to be opened, all hydrogen gas in the generator is ^{must} ~~is~~ to be displaced with carbon dioxide gas before any air is admitted.

When the generator is closed to go back into service the air in the generator ^{must} ~~is~~ to be completely displaced with CO₂ gas before any hydrogen gas is admitted.

b) Gas Supplies and Generator Purge

A hydrogen gas manifold and a carbon dioxide gas manifold connect gas supply cylinders to the generator gas systems and provide control of the gases.

The hydrogen gas manifold has connections for four gas cylinders each containing, when full, approximately 220 scf of H₂ at 2,200 psig. Manual shut-off valves are provided plus a solenoid operated shut-off valve (SSV-3). Pressure control valves (VPC-4 and VPC-5) provide hydrogen pressure adjustment within the range between 0.5 psig and 30 psig.

A self contained three-way pressure relief valve installed in the manifold assembly upstream of a check valve (H-16) is provided to prevent overpressuring the generator on ^{in position} failure open of the

pressure control valve VPC-5. The relief valve vents to the gas vent line. Backup generator overpressure relief is provided by a rupture diaphragm which will discharge gas to the vent line. A manually operated generator vent valve is provided, as is the solenoid operated vent valve SSV-4. Pressure gages, sampling connections, and low hydrogen supply pressure alarm LPA-9 are also a part of the hydrogen manifold assembly.

The carbon dioxide gas manifold connects eight cylinders to the system in one group of six and one group of two. One full cylinder of carbon dioxide at 800 psig contains approximately 174 scf of gas.

Manual shut-off valves are provided, as is a solenoid operated shut-off valve SSV-5. Pressure regulation equipment for the carbon dioxide is not required, but a relief valve (RV-5) is provided. A check valve, pressure gage, low pressure alarms and test connections are incorporated in the manifold assembly. A tap is taken from the CO₂ manifold to supply purge gas to the hydrogen gas drier and to the hydrogen purity indicator.

c) Generator Purge

Automatic purging of the generator hydrogen gas is provided in case of Unit trip due to low generator seal-oil-gas differential pressure. For the automatic purge to be initiated it is necessary for the turbine steam trip valve to be closed (POS-2B), the generator air circuit breaker to be opened (contact M7-M8 on auxiliary switch of ACB 252-3) and the seal-oil-gas differential

trip contact (PS-6) to be closed.

When these conditions are met solenoid valve SSV-4 is energized, opening the valve and venting the generator to the vent line, solenoid valve SSV-3 is de-energized, closing that valve and securing the supply of hydrogen to the generator, and SSV-5 is energized, opening the valve and admitting purge CO₂ gas to the generator.

Manually operated valves are also provided on the manifolds to perform the purging operation and to perform the reverse purging operation to put the generator back into service.

d) Gas Drier and Water Detector

A hydrogen gas drier and a generator water detector are provided mounted on one assembly.

The water detector consists of a chamber with a float switch. Any water that may accumulate in the bottom of the generator is drained to the water detector float chamber providing first a high level alarm (HLA-2) and, if the water level in the detector chamber rises to a higher level, a Unit trip (HLT-3).

The gas drier removes water from hydrogen by passing it through an activated alumina dessicant. The intake of the drier is connected to a high pressure region of the generator and the drier discharge is connected to a low pressure region, thus a generator gas impeller provides energy to circulate the gas through the drier. .

A glass port is provided on the side of the drier to give visible indication of the condition of the dessicant. A ^bblue-purple color indicates that the dessicant can absorb additional water from the gas; a white or pale pink color indicates a need for regeneration.

Regeneration is accomplished by securing the flow of hydrogen, purging the drier with CO₂, and then passing air, by means of the blower provided, through the electrically heated drying chamber, venting to the vent stack.

e) Generator Seal Oil System

(1) Shaft Seals

A shaft seal is provided at each end of the generator, where the shaft penetrates the generator housing. The construction of the seal is similar to a thrust bearing with a spring loaded non-rotating sealing surface rubbing against a collar which is fixed to the shaft. Oil is introduced into a circular groove in the non-rotating member at a pressure above that of the gas in the generator. Part of the oil flows toward the air side of the seal, lubricating and cooling the seal, and the rest flows inward toward the hydrogen side of the seal, preventing leakage of the gas. Labyrinth seals and a shaft slinger groove prevent creepage of seal oil further along the shaft into the generator.

(2) Seal Oil Supply

The seal oil supply unit uses oil from the turbine-generator lubricating oil tank. The oil is cooled and then pumped through a filter to the shaft seals.

The main seal oil pump is driven by a 3 horsepower, 480 volt, 3 phase motor with a manual start and stop control. X

The first backup supply for the seal oil system is the turbine shaft mounted lubricating oil pump. This pump, when the turbine is in operation, maintains approximately 75 psig oil pressure to an emergency seal oil pressure regulator (VCP-2) which in turn maintains a pressure providing any required backup supply.

A second seal oil backup supply is provided by a d-c motor driven pump. The motor is a 5 horsepower, 125 volt motor supplied from the station battery. The motor control switch provides selection of "OFF", manual or "AUTOMATIC" start. If automatic starting is selected, starting will be initiated by APS-4 on a drop of seal oil pressure to _____psig.

A check valve isolates APS-4 from the pressure rise caused by the pump it started and prevents start-stop hunting. If seal oil supply pressure is restored by the main seal oil pump or by the 75 lb oil system APS-4 will stop the d-c pump motor, otherwise once started the motor will continue to run until it either trips on overload or is stopped manually.

A third seal oil backup source is the turning gear oil pump. This pump is driven by a 480 volt a-c, 5 horsepower motor and will provide enough oil for operation at reduced hydrogen pressure. The motor control switch provides selection of manual or automatic starting. If automatic starting is selected, starting will be initiated by a drop in turbine lubricating oil header pressure to 8 psig. X

The motor will stop on a rise in pressure to 9 psig. An alarm is given when the turning gear pump is started.

The "Hydrogen System Trouble" alarm is given for a drop in pressure at LPA-4 (located on the main seal oil pump discharge) to _____ psig.

Unit trip is initiated on high seal oil temperature (HTT-9 and HTT-10) and by low seal oil-gas differential pressure PS-6.

(3) Detraining Tank

Oil traveling through the generator seals entrains a small amount of hydrogen gas which is removed in a detraining tank before the oil is returned to the lubricating oil reservoir. In the detraining tank the oil flows over a system of plates and baffles; the gas evolves as the oil flows through. As the pipes from the generator seals to the detraining tank are only partly full of oil the evolved gas returns to the generator through these pipes. Flow of oil through the detraining tank is slow; in the order of a few ounces per minute.

The oil level in the detraining tank is maintained by an external float control (LC-1). On release from the detraining tank the oil passes through a gas trap and is returned to the lubricating oil reservoir. High or low oil level in the detraining tank will initiate a "Hydrogen System Trouble" alarm (HLA-3 and LLA-3).

A detraining tank solenoid operated vent valve (SSV-2) is provided to vent out contaminated hydrogen gas. The solenoid valve is actuated by a pushbutton.

6. Excitation and Voltage Regulation

a) Excitation and Voltage Regulation - General Description.

The ^{maximum} excitation power requirement of the ^{U?} unit generator field is ~~120 kw~~ ^{120 kw} at 250 volts d-c. The power is supplied during operation by the Unit generator via a current-voltage transformer (CVT) static exciter. A field flashing circuit is provided to supply generator field current ^{from the station battery} during start-up until self-excitation is established.

A static voltage regulator is provided to control the generator voltage output. Control is effected through the controlled d-c output of the voltage regulator which energizes control windings of the exciter's CVT transformers.

No field current circuit breaker is provided; a field shorting system removes excitation from the generator field without creating the high ^{voltage} ~~voltage~~ associated with opening field current circuits.

Voltage regulation is available through either a manual or an automatic regulator system. A transfer switch located on the ^{U?} unit master control board provides selection of these systems, plus a "test" condition. On "test" the automatic voltage regulator is energized for testing, but generator excitation is under control of the manual voltage regulator. In automatic operation, the generator base voltage is established by a voltage adjusting rheostat. In manual operation the voltage is controlled by the "Manual" rheostat. Both rheostats are motor driven and are operated through control switches (VAR and MR) located on the ^{U?} unit master control board.

b) Exciter

The exciter consists of a three phase step ^{U?} down transformer, three single phase reactors, three d-c controlled single phase current-voltage

transformers (CVT's) and a three phase full wave power rectifier.

The CVT's have four windings each. One primary winding takes single phase power from the 200 ^{kva} ~~kv~~ step-down transformer via a series reactor. The stepdown transformer is energized from the output of the unit generator and provides power and ^{a measure of voltage} ~~voltage sensitivity~~ to the exciter. A second winding on each CVT is connected in series between a unit generator phase winding and the generator wye point. The CVT winding carries generator current and provides current sensitivity to the exciter. A third winding on each CVT is energized by the d-c output of the voltage regulator. Current in this winding tends to saturate the CVT, providing control of its output. The output windings of the CVT's supply ^a ~~the~~ three phase full wave diode rectifier. The rectified output supplies the ^U ~~unit~~ generator field.

Dual rectifier units are provided, each capable of carrying continuously full generated field current. Gang operated five pole switches will isolate the rectifiers so that one rectifier unit at a time can be isolated without shutting the unit down.

c) Voltage Regulator

The voltage regulator has two sections, providing manual or automatic regulation.

The manual control section has a single phase bridge rectifier composed of two solid state diodes and two silicon controlled rectifier (SCR) elements. The d-c output of the section is controlled by varying the firing time of the SCR elements during each cycle of the regulator's a-c supply voltage. Control of the firing time is effected through the "manual" control rheostat which varies the charging time of an R-C circuit. The R-C circuit, ~~the~~ ⁱⁿ ~~connection~~ with a unijunction transistor constitutes a relaxation oscillator which provides gate signal pulses to the SCR's of the rectifier. The controlled

d-c output of the rectifier is applied, when the excitation system is under manual control, to the control windings of the exciter CVT's.

The automatic section of the voltage regulator equipment is similar to the manual section, but has additional features. Cross-current compensation is provided to control the ^Y unit generator's response to system demands for reactive kva. A drooping response characteristic is required to prevent the generator from assuming more than its proportional share of reactive load. The control is effected by biasing the voltage regulator's input signal with a voltage proportional to the reactive current being carried by the generator. The bias voltage is derived from a 3000/5 ampere current transformer (CCCT) in the B phase of the generator's winding-to-neutral leads. A manually set rheostat in the voltage regulator cabinet provides adjustment of the cross-current compensation effect of the regulator.

An underexcitation discriminator circuit is provided in the automatic voltage regulation section. The purpose of the underexcitation discrimination is to prevent lowering of generator excitation to the point of machine instability under conditions of leading ^{generator} ~~system~~ power factor. The discriminator circuit is sensitive to generator kilowatt load and ^{to} ~~at~~ leading power factor current. The output of the discriminator biases the voltage regulator's input signal providing a minimum excitation level.

d. Field Flashing

A field flashing system is provided to excite the main generator field on startup until sustained self-excitation is effected. Field flashing is applied when the generator reaches rated speed, and is maintained until generator buildup occurs, generally about ten seconds. Power for field flashing is taken from the station battery; switching is accomplished through

a relay. A "Field Flashing" pushbutton, located on the main control board actuates the relay provided the field shorting relay is open.

e) Field Shorting

A field shorting system is provided to remove field excitation from the main generator. The system consists of an electrically operated relay which shorts out the output of the current-voltage transformers which supply the exciter rectifier. The characteristics of the generator-exciter system are such that self-excitation cannot be maintained with the shorting switch closed as long as there is no external supply to the generator armature. It is essential that the main generator air circuit breaker (ACB 252-3) be open for the field shorting system to perform its purpose. Therefore a "b" contact on ACB 252-3 is connected as a permissive for operation of field shorting. The field shorting ^{Manual switch} control is located on the ^{Unit} main control board. Field shorting is also initiated by operation of the Generator ACB control sw, the Generator Lockout relay, and the Unit Lockout relay.

? Unit

2

X

CIRCULATING WATER

SECTION INDEX

- A. Cooling Water
 - 1. General Description
- B. Cooling Tower
- C. Cooling Tower Supply Pump
- D. Turbine Exhaust Condenser System
 - 1. General Description
 - 2. Condenser Supply Pump
 - 3. Turbine Exhaust Condensers
 - 4. Steam Set Ejectors
 - 5. Inter Condenser
 - 6. After Condenser

REFERENCES

<u>Drawing</u>	<u>Title</u>
432594	Piping and Instrumentation Diagram, Steam and Condensate
432595	Piping and Instrumentation Diagram, Cooling Water
433117	Schematic Diagram, Condenser Supply, Cooling Tower Supply, and Fan Motors

CIRCULATING WATER

A. Cooling Water

(1) General Description

Cooling water is provided for the condensers, the generator hydrogen coolers, the lubricating oil coolers, the hydrogen seal oil coolers, and the gland steam eductors.

The cooling water system is a circulating system in which the water is cooled by evaporation in a cooling tower. Water is lost from the system by evaporation and by rejection to drainage. Water is added to the system by condensation of exhaust steam. The water added is expected to exceed the losses under all operating conditions so additional makeup should not be necessary. The initial start-up charge of water is obtained from the water system provided for fire protection.

The water from the condensers including the condensate, is discharged into a seal well which insures a water seal on the discharge pipe outlets. The seal well discharges to a hotwell. The cooling tower supply pump takes water from the hotwell and pumps it to the cooling tower through a 36-inch ID concrete pipe, a 24-inch header and three 24-inch riser pipes. A butterfly valve is provided in each riser to permit adjustment of the water flow to each section of the cooling tower.

The cooling tower basin drains to the cold well. The cold well overflow is connected to the hotwell to equalize the water levels and balance the flows in the circulating system. This connection, bypassing the cooling tower supply pump and the cooling tower, will prevent the condenser supply pump from losing suction should the cooling tower pump fail or during start-up when the condenser supply pump is used without the cooling tower supply pump.

The condenser supply pump picks up water from the cold well and pumps to the cooling water distribution system.

The cooling tower supply pump and the condenser supply pump are each driven by a 400 horsepower, 480 volt motor. Each motor is manually started and stopped. The cooling tower supply pump motor will be tripped if the condenser supply motor circuit breaker is not closed, therefor the condenser supply pump must be started first.

A trip of either the condenser supply pump motor or the cooling tower supply pump motor will, if the main generator circuit breaker is closed, trip the Unit.

B. Cooling Tower

Manufacturer	Fluor Products Co.
Type	Three cell counterflow induced draft
Manufacturer's model number	3F60 B2184V-3666B4P
Design flow	29,000 gpm
Design water inlet temperature	119F
Design water outlet temperature	80F
Design wet bulb temperature	65F
Design wind velocity	0-10 mph
Number of fans	6
Number of blades per fan	4
Fan Diameter	18 ft - 0 in.
Fan blade material	AISI T-302/304 stainless steel
Fan Speed	193 rpm
Tip speed	10,900 ft per min
Fan motor hp	75
Fan speed reducer	Fluor-Western Model FWD-75, Double reduction spiral bevel gear
Fan stack	14 ft - 0 in. parabolic venturi
Static pumping head above basin curb	41 ft
Dimensions:	
length	109 ft
width	66 ft plus 6 ft louver extension
height	43 ft plus 14 ft fan stack

B. Cooling Tower (cont'd)

Materials:

structural framework	Clear heart redwood
joint connectors	Type 356T6 aluminum
bolts	Type 6061T6 aluminum
nuts	Type 606 IT6, or 6062T9 aluminum
fill	High impact polystyrene
sheathing	Flat 1/4 in. cement asbestos board
Water distribution system	Redwood stave pipe
Nozzles	Polypropylene

COOLING TOWER PERFORMANCE CURVE

COOLING TOWER PERFORMANCE CURVE

COOLING TOWER PERFORMANCE CURVE

COOLING TOWER PERFORMANCE CURVE

DESIGN CONDITIONS:

GPM 29,000 T_1 119 °F
 T_{wb} 85 °F T_2 80 °F

MOTOR DATA SHEET

Application : Cooling Tower Fan

Quantity 6

Manufacturer ~~General Electric~~ WESTINGHOUSE

Rated H.P. 75

Frame 444 U

Poles 4

Type K

Volts 440

Cycle 60

Phase 3

Speed rpm

Synch. 1800

Rated Load 1775

NEMA Design B

Enclosure TEFC

Service Factor 1.00

Vertical or Horizontal Shaft Horizontal

Cooling Self-air

Connection to Equipment Coupling

Bearings Ball

Lubrication Grease

Weight in lbs. Stator 650

Rotor 390

Winding Connection WYE

No. of Leads Brought Out 3

Insulation Class A-1007

Dielectric Test 1880 volts a-c 1 min.

Temperature Rise 55 C

Amps: Rated Load 95.0

No Load 30

Locked Rotor 542.5

Torques: Rated Load 222

Locked Rotor 338

Breakdown 444

Power Factor: Rated Load 86.5

3/4 Load 85.5

1/2 Load 80

Efficiencies: Rated Load 90.5

3/4 Load 90.5

1/2 Load 83

Rotation: Clockwise

Remarks:

in error

C. Cooling Tower Supply Pump

Number of Units	1
Manufacturer	Peerless Pump Division, FMC
Manufacturer's Type	36HH, single stage industrial turbine
Shaft	vertical
Pump Serial Number	207576
Purchase Order Number	4R - 37524
Quantity Pumped (Design)	29,000 gpm
Field Head	45 ft
Rpm	705
Drive Motor	400 hp
Suction	38 in. dia
Bowl	36-3/16 in. dia
Bowl Material	316 stainless steel
Bushings	carbon
Bowl Wear Rings	316 stainless steel
Shaft, Couplings, Column	316 stainless steel
Discharge	horizontal, 36 in. O.D.
Discharge Flange	3 ft - 10 in. O.D.
Weights	
Motor	5,300 lb
Elbow	4,800 lb
Bowl Unit	<u>3,740 lb</u>
TOTAL	13,840 lb

D. Turbine Exhaust Condenser System

1. General Description

Steam exhausted from the turbine is condensed and noncondensable exhaust gases are removed by a barometric condenser system equipped with two stages of steam ejection. An intercondenser, an aftercondenser and a vapor exhaust separator are provided in conjunction with the ejectors.

The system is designed to handle 509,000 lb per hr of turbine exhaust, providing a back pressure of 3.75 in. of Hg abs. The exhaust consists of 503,400 lb per hr of steam of molecular weight 18, and 5,600 lb per hr of noncondensable gases of an average molecular weight 31.4.

Total cooling water requirement for the condenser-ejector system is 24,752 gallons per minute at 80F.; the total motive steam requirement for the ejectors is 22,800 lb per hr. Normal barometric pressure at the installation is taken as 27.9 in. Hg.

1. Condenser Supply Pump

Number of Units	1
Manufacturer	Peerless Pump Division, FMC
Manufacturer's Type	36HH, single stage industrial turbine
Shaft	vertical
Pump Serial Number	207575
Purchase Order Number	4R - 37524
Quantity Pumped (Design)	27,900 gpm
Field Head	43 ft
Rpm	705
Drive Motor	400 hp
Suction	38 in. dia
Bowl	36-3/16 in. dia
Bowl Material	316 stainless steel
Bushing Material	carbon
Bowl Wear Rings	316 stainless steel
Shaft, Couplings, Column	316 stainless steel
Discharge	horizontal, 36 in. O.D.
Discharge Flange	3 ft - 10 in. O.D.
Weights	
Motor	5,300 lb
Elbow	4,800 lb
Bowl Unit	<u>3,740 lb</u>
TOTAL	13,840 lb

2. Turbine Exhaust Condensers

Number of units	2 (connected in parallel)
Type	Barometric
Manufacturer	Elliott Company
Size	132 in. (diameter)
Design Duty:	Condense 509,000 lb per hr exhaust steam
Cooling Water Flow	11,625 gpm each
Cooling Water Temperature	80F
Water Temperature Rise	39.8F
Back pressure	3.75 in. Hg abs
Material:	
Shell	Carbon steel Clad with 316L stainless steel
Tray	316L stainless steel
Water nozzle	316L stainless steel
Weight:	
Empty	37,000 lb
Operating	42,000 lb
Full of water	163,000 lb

3. Steam Jet Ejectors

Manufacturer	Elliott Company
Number of stages	2
Design Conditions	
Minimum steam pressure	50 psig
Minimum ^{Min} steam temperature	298F
Maximum back-pressure on final stage	1 psig
First Stage Ejector	
Size (nominal)	16 in. x 16 in.
Steam requirement	9,920 lb per hr
Second Stage Ejector	
Size (nominal)	10 in. x 10 in.
Steam requirement	12,900 lb per hr
Material (both ejectors)	
Steam chests	316L stainless steel
Steam nozzles	316L stainless steel
Suction chambers	316L stainless steel
Diffusers	316L stainless steel

4. Intercondenser

Manufacturer	Elliott Company
Number of Units	1
Size (nominal)	60 in. (diameter)
Design Conditions	
Cooling Water Flow	835 gpm
Cooling Water Temperature	80F
Water Temperature Rise	29F
Material	
Shell	316L stainless steel
Water Nozzle	316L stainless steel

5. Aftercondenser

Manufacturer	Elliott Company
Number of Units	1
Size (nominal)	48 in. (diameter)
Design Conditions	
Cooling Water Flow	672 gpm
Cooling Water Temperature	80F
Water Temperature Rise	40F
Material	
Shell	316L stainless steel
Water Nozzle	316L stainless steel

CONDENSER VACUUM VERSUS CONDENSER LOADING

SUCTION PRESSURE VERSUS CAPACITY FOR
THE TWO STAGE EJECTOR SERVING THE
MAIN CONDENSERS

PROTECTIVE RELAYS

SECTION INDEX

- A. Protective Relay System - General
- B. Lockout and Tripping Schemes
- C. Turbine Overspeed Trip
- D. Relay Data

REFERENCES

<u>Drawing No.</u>	<u>Title</u>
433105	Functional Diagram, Turbine Generator Protection
433102	Single Line Meter and Relay Diagram
433107	Schematic Meter and Relay Diagram, Generator, Exciter, Regulator and Air Circuit Breaker

A. PROTECTIVE RELAY SYSTEM - GENERAL

The design of the protective relay system of Unit 3, like that of Units 1 and 2, is based on the consideration that the Unit, while requiring manual control for start-up, will operate unattended. This requires that many operating conditions that would initiate only an alarm in an attended plant must trip this Unit.

A sequential tripping scheme is used to trip the Unit in response to all mechanical and some electrical troubles that call for trip. The purpose of the sequential tripping is to protect against a turbine runaway should the generator air circuit breaker trip open and the turbine trip valve and the trip check valve fail to close. The sequential tripping is accomplished by using a Turbine-Generator Lockout Relay (286-3) to energize a solenoid dump valve (SV-1). The dump valve releases the auto-stop oil which causes closing of the turbine trip valve and the turbine check valve. Position switches on the valves initiate trip of the generator air circuit breaker when either the trip valve or the check valve closes.

The sequential tripping scheme is not used to trip the Unit in response to certain electrical faults. These are faults that require rapid tripping to minimize electrical damage, and in these cases tripping of the auto-stop oil and of the generator air circuit breaker are initiated simultaneously.

The generator low frequency relay (281-L3) trips the Unit (through a lockout relay) only if the generator air circuit breaker is closed. This low frequency relay serves as a protection against power overload that might be imposed on the Unit by system switching.

B. LOCKOUT AND TRIP SCHEMES

Protective relays and functions (except for turbine overspeed trip) initiate operation of one of five devices:

1. Solenoid Valve SV-1 - Solenoid Dump Valve
2. Device No. 286-3 - Turbine-Generator Trouble Lockout
3. Device No. 286F-3 - Generator Trouble Lockout
4. Device No. 386-3 - Unit Overall Lockout
5. Device No. 86M-3 - 480 Volt Switchgear Lockout Relay

1. Solenoid Valve SV-1 - Solenoid Dump Valve:

The Solenoid Dump Valve, SV-1, opens when energized, releasing pressure of the auto-stop oil, which trips the turbine. After the turbine trip, the generator air circuit breaker is tripped as explained above. All three lockout relays, (286-3), (286F-3), and (386-3) will energize SV-1. In addition, it is energized by a Bearing Oil Low Pressure Switch (PS-5), and by a manual Emergency Trip Control Switch (205-3).

2. Device No. 286-3 - Turbine-Generator Trouble Lockout Relay:

The Turbine-Generator Trouble Lockout Relay (286-3), when picked up, energizes the Solenoid Dump Valve (SV-1) and the 480 volt Switchgear Lockout Relay (86M-3). The 480 volt Switchgear Lockout Relay, in turn, trips and locks out 480 volt auxiliary motors no longer required after a unit trip.

The Turbine-Generator Trouble Lockout Relay (286-3) is energized directly for twenty-six trouble inputs, through a time delay for one, (Low Hydrogen Purity), and through a "generator air circuit breaker closed" contact for four others.

The functions and devices which will directly cause the 286-3 relay to operate are:

<u>FUNCTION</u>	<u>DEVICE</u>
(1) H ₂ Gas High Temperature	HTT-5, HTT-6
(2) Low Gas-Oil Differential Pressure	PS-6
(3) High Seal Temperature (Turbine End)	HTT-9
(4) High Seal Temperature (Collector End)	HTT-10
(5) H ₂ Gas Low Pressure	PS-11
(6) Liquid Drain High Level	HLT-3
(7) Low H ₂ Purity (time delayed)	74-X-10-3
(8) H ₂ Gas High Pressure	PS-7
(9) Generator Overcurrent Backup	251-V-3
(10) Generator Negative Sequence Current Relay	246-3
(11) Generator High Frequency	281-H-3
(12) Generator Loss of Field Relay	240-3
(13) Generator Overvoltage	259-3
(14) Generator Field Ground	264-3
(15) Generator Stator High Temperature	226-3
(16) Turbine-Generator Vibration Detector	V 1B
(17) Turbine-Generator Bearing High Temperature	HTT-1 through HTT-8
(18) Turbine Exhaust High Temperature	HTT-11
(19) Turbine Oil High Temperature	HTT-7
(20) Rotor Movement	POT-7, POT-8
(21) Bearing Oil, Low Pressure	PS-13
(22) Exhaust Duct, Drip Pumps Off	42-20, 42-21
(23) Water in Turbine Exhaust Duct	HLT-1, HLT-2

(24) 480 Volt Bus Undervoltage	27-3
(25) Main Transformer, High Temperature	26-Q
(26) Main Transformer, Sudden Pressure	63-FP
(27) Turbine Oil Low Pressure	PS-5

The functions which will cause operation of the 286-3 relay only if the generator air circuit breaker is closed are:

<u>FUNCTION</u>	<u>DEVICE</u>
(1) Generator Low Frequency	281 L-3
(2) Condenser Low Vacuum	PS-1
(3) Cooling Tower Supply Pump Breaker Open	52-8
(4) Condenser Supply Pump Breaker Open	52-7

3. Device No. 286F-3 - Generator Trouble Lockout

Operation of the Generator Trouble Lockout Relay (286F-3) does not initiate the sequential tripping action as it is desirable to disconnect the generator quickly to minimize electrical damage. Therefore the 286F-3 energizes the Solenoid Dump Valve, the generator air circuit breaker trip circuit, and the 480 volt switchgear lockout relay simultaneously.

The 286F-3 is operated by three functions:

<u>FUNCTION</u>	<u>DEVICE</u>
(1) Generator Neutral Overvoltage	259N-3
(2) Generator Neutral Instantaneous Overvoltage	259I-3
(3) Generator Differential Current	287-3

4. Device No. 286-3 - Unit Overall Lockout Relay

The Unit Overall Lockout Relay (286-3) trips the same devices as the Generator Trouble Lockout Relay (286F-3), as listed above. In addition it initiates tripping of the 60 kv air circuit breaker (OCB No. 42).

Device No. 286-3 is energized by operation of the following:

<u>FUNCTION</u>	<u>DEVICE</u>
(1) Unit Overall Differential Relay	387-3
(2) Auxiliary Transformer Overcurrent	251-3
(3) Station Battery Undervoltage	80-3
(4) 60 kv Line Overcurrent	351-1
(5) 60 kv Line Ground Overcurrent	351N-1

5. Device 86M-3 - 480 Volt Switchgear Lockout

The 480 Volt Switchgear Lockout Relay trips circuit breakers in the motor control center that feed the condenser supply pump, the cooling tower supply pump, and the cooling tower fans.

The 86M-3 device is tripped through operation of the Turbine-Generator Trouble Relay (286-3), the Generator Trouble Relay (286F-3), or the Unit Overall Lockout Relay (386-3).

LIST OF RELAYS

<u>Device</u>	<u>Description</u>	<u>Mfgr. Type-Style</u>
27-3	480 Volt Bus Undervoltage	W.E. CV-2 1875508
27-BC	Battery Charger Undervoltage	(Part of battery charger)
74-3	Battery System Ground	Exide GDR GDR503
74-TG	Turning Gear Trouble Alarm	Struthers-Dunn A5BXX
80-3	Battery Undervoltage	Mole Richardson A500868-60B
86M-3	480 Volt Switchgear Lockout	W.E. Co. WL 300P758G01
226-3	Generator Stator High Temperature	
240-3	Generator Loss of Field	W.E. Co. KLF 290B481A09
246-3	Generator Negative Sequence	W.E. Co. COQ 1956207
251-3	Auxiliary Transformer Overcurrent	W.E. Co. CO-9 1875283
251V-3	Generator Overcurrent Backup	G.E. IJCV 1211JCV51A1A
259-3	Generator Overvoltage	W.E. Co. CV-25 290B569A21
259-N-3	Generator Neutral Overvoltage	W.E. Co. CV-8 1875526
2591-3	Gen. Neut. Overvoltage, Instantaneous	W.E. Co. SV 1876094
264-3	Generator Field Ground	W.E. Co. DGF 1878175
281H-3	Generator Overfrequency	W.E. Co. CF-1 291B995A09
281L-3	Generator Underfrequency	W.E. Co. CF-1 291B995A10
286-3	Turbine-Generator Trouble Lockout	W.E. Co. WL 300P758G01
286F-3	Generator Trouble Lockout	W.E. Co. WL 300P758G01
287-3	Generator Differential	W.E. Co. HA 1876163
290-3	Turbine Load Controller	I&N 69627A1
351-1	Line Overcurrent	W.E. Co. CO-9 1875289
351N-1	Ground Relay	W.E. Co. CO-9 1875283
386-3	Unit Overall Lockout	W.E. Co. WL 300P758G01
387-3	Unit Overall Differential	W.E. Co. CO-8 1875273

MAKE-UP WATER AND FIRE PROTECTION

SECTION INDEX

- A. General Description
- B. Intake and Pump Sump
- C. Make-up water Pump
- D. Pump Controls
- E. Water Storage
- F. Water Distribution

REFERENCES

Drawing Number

432597

433119

433163

433164

433173

212538

Title

Piping and Instrumentation, Miscellaneous Service Systems

Schematic Diagrams, Miscellaneous Service Systems

Water Supply and Fire Protection System

Water Supply Intake

Requirements for Water Supply Tank

Assembly of Material for Standard Wood Shelter for Fire Hose

Record Number

657498

Title

Manufacturer's Setting Plan, Make-up Water Pump

TURBINE & GENERATOR TRIPS											
NUMBER	FUNCTION	DEVICE NO.	TRIPPING ELEMENTS								REMARKS
			TURBINE I	TURBINE II	TURBINE III	GEN. ACB	GEN. FIELD	GEN. DCB	AUX. TRIP	GEN. FIELD OVERVOLTAGE	
1T	MANUAL EMERGENCY TRIP	299-3	X	X	X	X					LOCATED BY TURBINE-GENERATOR PANEL 1A-3
2T	OVERSPEED		X	X	X	X					TRIPS WHEN UNIT REACHES A SPEED OF 110%
3T	LOW BEARING OIL PRESSURE		X	X	X	X					TRIPS WHEN BEARING OIL PRESSURE DROPS TO 7 PSIG (1.72)
16	UNIT OVERALL DIFFERENTIAL	387-3	X	X	X	X	X		X		CURRENT DIFFERENTIAL BETWEEN NEUTRAL THRU 1 80 V LINE
26	AUXILIARY TRANSFORMER OVERCURRENT	251-3	X	X	X	X	X		X		
36	BATTERY UNDERVOLTAGE	80-3	X	X	X	X	X		X		
46	60KV LINE PHASE OVERCURRENT	357-1	X	X	X	X	X	X			
56	60KV LINE GROUND OVERCURRENT	358-1	X	X	X	X	X	X			
66	GEN. NEUTRAL OVERVOLTAGE	259-3	X	X	X	X	X		X		
76	GEN. NEUTRAL INSIMULTANEOUS OVERVOLTAGE	259-3	X	X	X	X	X		X		
86	GEN. DIFFERENTIAL	287-3	X	X	X	X	X		X		CURRENT DIFFERENTIAL BETWEEN NEUTRAL THRU 1 GEN. BREAKER
96	GEN. BACK-UP OVERCURRENT	251-3	X	X	X	X	X		X		
106	GEN. NEGATIVE SEQUENCE	260-3	X	X	X	X	X		X		TRIPS BY UNBALANCED PHASES
116	GEN. HIGH FREQUENCY	281-3	X	X	X	X	X		X		
126	GEN. LOSS OF FIELD	260-3	X	X	X	X	X		X		
136	GEN. OVERVOLTAGE	259-3	X	X	X	X	X		X		
146	GEN. FIELD GROUND	260-3	X	X	X	X	X		X		
156	GEN. STARTER HIGH TEMPERATURE	226-3	X	X	X	X	X		X		
166	TURBINE-GEN. VIBRATION DETECTOR	VIB	X	X	X	X	X		X		
176	TURBINE-GEN. BEARING HIGH TEMPERATURE	HTW-1 HTB-1	X	X	X	X	X		X		TRIPS WHEN TEMPERATURE REACHES - - - - -
186	TURBINE EXHAUST HIGH TEMPERATURE	HTW-4	X	X	X	X	X		X		TRIPS WHEN TEMPERATURE REACHES - - - - -
196	TURBINE OIL HIGH TEMPERATURE	HTF-1	X	X	X	X	X		X		TRIPS WHEN TEMPERATURE REACHES - - - - -
206	AXON MOVEMENT	PORT PORT	X	X	X	X	X		X		TRIPS WHEN POTENTIAL MOVEMENT IS IN EXCESS OF 60 IN.
216	BEARING OIL LOW PRESSURE	PS-13	X	X	X	X	X		X		
226	EXHAUST DRIP PUMP OFF	12-30 12-31	X	X	X	X	X		X		TRIPS WHEN BOTH EXHAUST DRIP PUMPS ARE TRIPPED
236	WATER IN TURBINE EXHAUST DUCT	WET-1 WET-2	X	X	X	X	X		X		
246	MOV BUS UNDERVOLTAGE	27-3	X	X	X	X	X		X		
256	MAIN TRANSFORMER HIGH TEMPERATURE	26-3	X	X	X	X	X		X		
266	MAIN TRANSFORMER JUNCTION PRESSURE	43-30	X	X	X	X	X		X		
276	GEN. LOW FREQUENCY	281-3	X	X	X	X	X		X		TRIPS WHEN GEN. ACB IS CLOSED
286	CONDENSER LOW VACUUM	FD-1	X	X	X	X	X		X		TRIPS WHEN GEN. ACB IS CLOSED
296	COOLING TOWER FAN PUMP BREAKER OPEN	52-8	X	X	X	X	X		X		TRIPS WHEN GEN. ACB IS CLOSED
306	CONDENSER SUPPLY PUMP BREAKER OPEN	52-7	X	X	X	X	X		X		TRIPS WHEN GEN. ACB IS CLOSED
316	CONDENSER SUPPLY PUMP LOW DISCHARGE	PS-3	X	X	X	X	X	X	X		TRIPS WHEN GEN. ACB IS CLOSED
326	TURBINE TRIP VALVE CLOSED	PS-26	X	X	X	X	X		X		
336	TURBINE CHECK VALVE CLOSED	PS-38	X	X	X	X	X		X		
346	GEN. AIR CIRCUIT BREAKER TRIPPED	232-3	X	X	X	X	X		X		GENERATOR ACB CLOSING INITIATED BY 'O' CONTACTS.
356	TURBINE LOW OIL PRESSURE	PS-9	X	X	X	X	X		X		
1H	H ₂ GAS HIGH TEMPERATURE	HTS-5 HTS-6	X	X	X	X	X		X		
2H	GEN. OIL DIFFERENTIAL LOW PRESSURE	PS-6	X	X	X	X	X		X		
3H	H ₂ GAS HIGH TEMPERATURE TURBINE END	HTS-5	X	X	X	X	X		X		
4H	H ₂ GAS HIGH TEMPERATURE COLLECTOR END	HTW-9	X	X	X	X	X		X		
5H	H ₂ GAS LOW PRESSURE	PS-11	X	X	X	X	X		X		
6H	GROUND DRAIN HIGH LEVEL	MLT-1	X	X	X	X	X		X		
7H	LOW PURITY	RT-05	X	X	X	X	X		X		TRIPS AFTER PURITY HAS REMAINED LOW FOR APPROXIMATELY
8H	H ₂ GAS HIGH PRESSURE	PS-1	X	X	X	X	X		X		

LEGEND

— ELECTRICAL CONTROL
-H- MECHANICAL CONTROL

FUNCTIONAL DIAGRAM
TURBINE GENERATOR PROTECTION
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

BILL OF MATERIAL	
DRAWING LIST	
SUPERSEDES	
SUPERSEDED BY	
SHEET NO.	ONE
DRAWING NUMBER	CHK
433105	

[illegible]

MAKE-UP AND FIRE PROTECTION WATER

A. General Description

Water for general service, fire protection and cooling water make-up is gathered from a spring fed stream and pumped to storage in a 50,000 gallon redwood tank. The water is not treated and is considered non-drinkable. The dependable flow of the supply stream is estimated to be 5 to 6 gpm, but is expected to be more than that during most of the year. The elevation of the storage tank provides a static pressure on the water distribution system at the Unit of approximately 100 psig. As the operation of the turbine-generator Unit will provide more condensate than the loss due to evaporation at the cooling tower, it is expected that water will be drawn from storage ~~only~~ for initial fill of the cooling water system ^{but not} ~~rather~~ than for make-up. The elevation of the intake is 1,922 ft~~x~~, the elevation of the pump sump is 1,886 ft~~x~~, and the elevation of the control point water surface in the storage tank is 2,138 ft.

B. Intake and Pump Sump

An intake structure located approximately 950 ft~~x~~ north of the Unit diverts water into a 6 in. asbestos concrete intake pipe.

The intake pipe conducts the water down to the make-up water pump sump which is located near the northwest corner of the cooling tower. A channel is provided to permit draining water from the cooling tower basin to the pump sump if this becomes necessary. The pump sump is provided with an overflow which discharges into a stream downhill from the Unit. A 2 in. line terminating at the intake works with a hydrant, is provided for cleaning and flushing ^{the intake.} ~~service.~~ This line is served from ^a the line between the pumps and the storage tank.

C. Make-up Water Pumps

Number of pumps	2
Manufacturer	Westco (Fairbanks-Morse)
Model	SR6H6
Material	all iron
Fluid Pumped	water
TDH (Design)	250 ft.
Flow (Design)	22.5 gpm
Motor	
Manufacturer	Westinghouse
Frame	254 U
Horsepower	7-1/2
Phase	3
Frequency	60 cycle
Volts	440
RPM (synchronous)	1,800
Type	horizontal, totally enclosed fan cooled

D. Make-up Pump Motor Controls

Selection is provided of "start", "stop", and "automatic" for each motor by a control switch located near the motor. No spring return is provided. If automatic operation is selected for either or both pumps starting and stopping will be initiated by the storage tank level float control switch, ILS-1. Note that ILS-1 and its auxiliary relay ILSX-1 are energized from the control circuit of the 480 volt circuit breaker (52-14) for the make-up pump 3-1. If this control circuit is de-energized water can be pumped ^{only} by manual starting of pump 3-2.

E. Water Storage Tank

The water storage tank is of 50,000 gallon capacity. It is constructed of redwood, and fitted with aluminum screen and screen fasteners. The 6 in. outlet pipe is of type 316 stainless steel. An aluminum float, filled with styrofoam, is provided to operate the make-up pump control switch (LLS-1) and the water tank low level alarm (LLA-1).

F. Water Distribution

The water pumps discharge through check valves into a ~~6 in.~~ distribution system. A tap line from the distribution loop conveys water to and from the storage tank. A sectionalizing valve is provided near the storage tank.

The distribution system is basically a 6 in. concrete asbestos pipeline that loops around the Unit and the area provided for Units 4 and 5. Six sectionalizing valves are provided in the loop.

Five fire hose stations are located on short taps from the loop, and two additional fire hose stations are provided on a tap that extends along the northwest side of the switchyard.

Service water for a toilet, a washbasin and a service sink is taken from the distribution system.

BUILDING AND CRANE

ELECTRICAL CONTROL SYSTEM

SECTION INDEX

1. General Description
2. Control Switchboard
3. Annunciator

REFERENCES

Drawing Number

Title

433131

Arrangement of Electric Control
and Relay Board

045783

Bill of Material for Drawing
433131

ELECTRICAL CONTROL SYSTEM

(1) General Description

The main control board is located on the south side of the building near the turbine end standard. With some exceptions the Unit is controlled from this board including Unit synchronization, 13.8 kv generator air circuit breaker control, 60 kv oil circuit breaker control, generator field control, and plant auxiliary control. Most of the Unit instrumentation is displayed on this board, including generator instruments, steam flow recorders, and the plant annunciator. Almost all of the plant protective relays are mounted on this board. The board is composed of five panels, a Turbine-Generator section, two Generator panels, a Station Service panel and a 60 kv control panel. The board is fully enclosed, with an access door at each end. Copper wire, cable and bus conductors are tinned, and wherever practicable other copper parts are tinned or coated to protect against corrosion due to hydrogen sulfide gas.

(2) Control Switchboard

Manufacturer	Western Switchboard Co.
Purchase Order No.	4R-42454
Specification No.	6887

(3) Annunciator

Manufacturer	Rochester Instrument Systems
Purchase Order No.	4R-42245
Manufacturer's Type	AN 100

The main plant annunciator is mounted on a generator control panel of the main control switchboard. It is a forty-eight window system, eight rows high by six columns wide. Twenty-four indicators in the upper four rows are set up to provide "first alarm" indication by showing red illumination of the first of that group to receive an alarm. The "first out" display will remain until reset through a separate "first out acknowledgement" push button, even if the alarm condition returns to normal. This feature is provided as an aid to diagnosis of trouble, as the first condition that causes a Unit trip is followed by a large number of subsequent alarms.

GENERATOR SWITCHGEAR

Specification Number	6889
Purchase Order Number	4R-37523
Manufacturer	Westinghouse
Manufacturers Type	150DHP 500

General Description:

The generator switchgear is a two compartment, indoor metal-clad unit. One compartment contains the 13.8 kv drawout type generator air circuit breaker and 3 current transformers. The other compartment contains three potential transformers and their fuses.

Bus	Aluminum 1/2-in. x 4-in., 2 per phase
Bus current rating	2,000 amperes
Air circuit Breaker	
Rated Voltage	13.8 kv
Interrupting rating	500 mva at rated voltage
Continuous rating	2,000 amperes
Momentary rating	40,000 amperes
4 second rating	25,000 amperes
Interrupting rating	21,000 amperes at rated voltage
Control	125 volts d-c
Current Transformers	2,000/5 amperes
Potential Transformers	14,400/120 volts

AUXILIARY POWER

Section Index

- A. Auxiliary Power System - General
- B. Auxiliary Power Transformer
- C. 480 Volt Switchgear
- D. Motor Control Center

References

Drawing Number

Title

433102

Single Line Meter and Relay Diagram

433122

Schematic Diagram, 120-208 Volt
Station Service

Record Number

657780

Manufacturer's Drawings 480 Volt Switchgear

658220

Manufacturer's Drawings 480 Volt Motor
Control Center

AUXILIARY POWER

A. Auxiliary Power System-General

Electric power is used for the operation of Unit 3 at the following voltages:

- (1) 480 volt, a-c, 3 phase, delta
- (2) 120-208 volt, a-c, 3 phase, grounded Y
- (3) 125 volt, d-c. (The d-c supply and use is described in a separate section).

The auxiliary power is supplied through a 3 phase 1,350 kva, 13.8/480 volt auxiliary power transformer. The high voltage connection to the transformer is tapped directly to the 13.8 kv bus between the generator air circuit breaker and the main power transformer. Thus the source of auxiliary power, when the Unit is on the line, is the generator. However with the generator air circuit breaker (252-3) open, power is available from the 60 kv line by way of the main power transformer.

A metal enclosed bus connects the auxiliary transformer to the 480 volt switchgear assembly. No incoming circuit breaker is provided; an auxiliary power transformer primary overcurrent relay (251-3), when picked up, will initiate trip of the Unit and the 60 kv circuit breaker, completely deenergizing the primary winding of the auxiliary power transformer. The 480 volt switchgear serves cooling tower motors, the cooling tower supply pump motor, the condenser supply pump motor and the 480 volt motor control center. A 480 volt bus ground relay (64-3) provides an alarm only for 480 volt system ground.

The 480 volt motor control center serves motors up to 30 horsepower, power receptacles and the lighting transformer.

The lighting transformer is a 3 phase, 45 kva, 480/120-208 volt transformer supplying a 3 phase, 4 wire, grounded neutral lighting panel No. 1. The lighting panel supplies small auxiliary functions such as sump pumps, water heater, roof exhaust fans and instruments as well as lighting. It also supplies power to the station battery charger.

B. AUXILIARY POWER TRANSFORMER

Number of Units	1
Specification Number	6886
Purchase Order	4R-42223
Manufacturer	Kuhlman Electric Company
Rating	1,200/1,350 kva, 55/65C rise
Phase	3 phase
High Voltage	13,800 volts
High Voltage Taps	14,500-14,150-13,450-13,100
Low Voltage	480 volts
Tertiary	None
Connection	Delta-Delta
Exciting Current:	
@ 100% voltage:	0.6%
@ 110% voltage:	1.1%
No Load Losses	2,000 watts
Total Losses	16,000 watts
Efficiency	98.68%
Regulation	
@ 100% pf	1.5%
@ 80% pf	6.09%
Oil	350 gallons
Weights	
Core and coils	6,000 lbs.
Tank and fittings	2,200 lbs.
Oil	2,630 lbs.
Total	10,830 lbs.
Bushings	Lapp 73531-B
HV	Lapp 60026
LV	8.25%
Impedance	

C. 480 VOLT SWITCHGEAR

Number of Units	1
Manufacturer	General Electric Company
Manufacturer's Type	AKD-5 Powermaster Switchgear
Specification Number	6888
Purchase Order	4R-37581
Bus Rating:	
Momentary	50,000 amp
Continuous	1,600 amp, 40C ambient
Circuit Breaker cells:	
600 amp frame	7
1,600 amp frame	1
Circuit Breakers	
AK2A25	6
AK2A50	1
Potential Transformers	5, GE type JVP, 300 va 65C ambient 480/120 volt

NOTE: Metal enclosed bus to connect the 480 volt switchgear to the auxiliary power transformer is supplied on the same purchase as the switchgear.

D 480 VOLT MOTOR CONTROL CENTER

Number of Units	1
Manufacturer	Cutler Hammer
Specification Number	6890
Purchase Order	4R-42225
Bus Rating	
Momentary	50,000 amps
Continuous	600 amp (minimum)
Motor Starter Units	
NEMA Size 1	10
NEMA Size 2	3
NEMA Size 3	1
Circuit Breakers (100 ampere)	6

125 VOLT D-C SYSTEM

Section Index

- A. 125 Volt D-C System - General
- B. 125 Volt D-C Supply
- C. Alarms and Control
- D. Emergency Lighting Supply

References

Drawing

Title

433122

Schematic Diagram, 120/208 Volt Station Service
and 125 Volt D-C System

Record Number

Title

657254

Instructions, Battery Charger

125 VOLT D-C SYSTEM

A. 125 Volt D-C System - General

The station 125 volt d-c system serves the following equipment and functions:

1. Control power for relays, solenoids, exciter regulation, circuit breaker and switchgear.
2. Annunciator supplies.
3. Main generator field flashing.
4. Emergency lighting.
5. Standby pump motor supply
 - (a) Standby lubricating oil pump
 - (b) Standby seal oil pump
 - (c) Standby lube oil vapor exhaust pump

B. 125 Volt D-C Supply

The direct current supply consists of a 60 cell lead-acid battery. Each cell is in a plastic jar with sealed cover.

The battery is an Exide, Type 1-6 FMP-11. A battery charger is provided, Model 1-US-130-1-25. Power supply to the battery charger is 208 volts a-c, taken from the 120/208 volt distribution panel.

C. Alarms and Control

A low voltage relay (27 BC), which is a part of the battery charger, provides an alarm only for low charger voltage.

However low battery voltage is potentially hazardous to the Unit as many vital control circuits are d-c. As the Unit operates unattended, Unit trip and lockout are initiated by the operation of a battery low voltage relay (80-3).

A battery system ground detector is provided, and a battery system ground relay provides an alarm. The battery ground detector system is open circuited by operation of the generator field flashing pushbutton. The purpose is to prevent interaction between the generator field ground detector system and the battery ground detector system.

D. Emergency Lighting Supply

A d-c circuit is provided for emergency lighting service. The double throw two pole transfer switch is manually operated. Care should be taken that the emergency lights are not left drawing power from the battery when not necessary.

SPECIFICATION LIST

<u>Spec. No.</u>	<u>Description</u>	<u>Contract Number</u>	<u>Manufacturer or Contractor</u>
6871	F&D Turbine Generator Unit	4R-34093	Elliott Co.
6872	F&D Barometric Condenser	4R-34192	Elliott Co.
6874	Construction of Cooling Tower	22-414-64	Fluor Products
6875	F&D Circulating Water Pumps	4R-37524	Peerless Pumps
6876			
6877			
6878	F&D Turbine Steam Exhaust Duct and Expansion Joints	4R-42549	Saracco Tank & Mfg. Co.
6879	F&D Steam Power Plant Piping	4R-42601	Pacific Pipe
6880	F&D Lubricating Oil Tank	4R-51031	Conlin & Roberts
6881	F&D Butterfly Valves	4R-42252	Keystone Valve Corp.
6882	F&D Air Compressor	4R-37462	Davey Compressor Co.
6883			
6884			
6885	F&D Main Transformer Bank	4R-83903	General Electric
6886	F&D Station Service Transformer Bank	4R-42223	Kuhlman Electric Co.
6887	F&D Control and Relay Board	4R-42454	Western Switchboard Co,
6888	F&D 480 Volt Switchgear	4R-37581	General Electric
6889	F&D Generator Switchgear	4R-37523	Westinghouse
6890	F&D Motor Control Center	4R-42225	Cutler-Hammer
6891	Grading & Paving		

<u>Spec. No.</u>	<u>Description</u>	<u>Contract Number</u>	<u>Manufacturer or Contractor</u>
6892	Installation of E&M Equipment, Thermal Insulation, and Erection of T-G	22-371-65	Owl Constructors
6893	Preliminary Foundation Excavation (G-C Spec)		A.B. Siri, Inc.
6894			
6895	Fencing		
6896	F, D, & E Crane	22-228-65	Crane Hoist Eng. & Mfg. Co.
6897	Construction of Power Building, Foundations and Structural Steel	22-255-65	Christensen & Foster
6898			
7319	Station Battery and Charger		Exide

DRAWING LIST

<u>Description of Drawing</u>	<u>Drawing Number</u>
<u>Civil Drawings</u>	
Rough Grading Plan	433161
Grading and General Layout	433162
Water Supply and Fire Protection System	433163
Water Supply Intake	433164
Storm and Sanitary Sewers	433165
General Utilities	433166
Circulating Water System Concrete Outline	433167
Circulating Water System, Reinforcing & Details	433168
Foundations for Transformers, Switchyard, and Miscellaneous Structures	433169
Waste Water Disposal System, Sedimentation Basin	433170
Waste Water Disposal System, Piping and Details	433171
Fencing and Paving, Plan and Details	433172
Water Supply Tank Requirements	433173
Circulating Water System, Piping Layout and Details	433174
Circulating Water System, Anchor Liners	433175
Hydrogen Bottle Racks, Manifold Cabinet & Misc. Details	433176
<u>Structural Drawings</u>	
Concrete Outline, Plan at Elev. 1896 ft-0 in.	433178
Concrete Outline, Plan at Elev. 1881 ft-0 in. and Sections	433179
Concrete Outline Sections N1, N2, N4, N5	433180
Concrete Outline Sections W2, W3, N3, N6	433181
Reinforcing Plan at Elev. 1896 ft-0 in. and Details	433182
Reinforcing Plan at Elev. 1881 ft-0 in. and Sections	433183
Reinforcing Sections	433184
Cooling Tower, Foundation and Details	433186
Power Building Superstructure - Steel Framing	433187
Power Building Superstructure - Steel Framing Details	433188
Plans and Elevation Tower for Barometric Condensers	433189
Details of Tower for Barometric Condensers	433190
20 Ton Crane Requirements	04 6007
<u>Architectural Drawings</u>	
First Floor Plan	433701
Basement Floor Plan	433702
Elevations and Sections	433703
Exterior Wall Sections	433704
Roof Plan and Details	433705
Miscellaneous Steel	433706
Miscellaneous Steel in Building	433707
Ladder Schedule and Details	433708
Storage and Toilet Rooms	433709
Ventilation and Electrical	433710
Plumbing	433711
Perspective	433712

DRAWING LIST

<u>Description of Drawing</u>	<u>Drawing Number</u>
<u>General Layout</u>	432591
<u>Equipment Location</u>	
Plan at: Basement, Operating Floor,	
Condenser Platform	57431
Section A-A and B-B	57432
Section C-C and D-D	57433
<u>Piping and Mechanical</u>	
<u>Area A</u>	
Plan Below Elev. 1895 ft-0 in.	57435
Plan Below Elev. 1920 ft-0 in.	57436
Section A-1, A-2	57437
Section A-3, A-4, A-5	57438
Miscellaneous Sections	57439
<u>Area B</u>	
Plan Below Elev. 1882, 1895,	
1920, 1958, and Sect. B-3 & B-4	57441
Section B-1, B-2	57442
Miscellaneous Sections	57443
Cooling Tower - Plan and Sect.	57445
Piping Layout - Main Steam	57446
P&M General Notes, References	045599
<u>Miscellaneous Piping</u>	
Drain Funnels	100871
Lube Oil Storage Tank	SK-2676-33
Sleeves and Spools	328738
Insulating Flange Schedule	214441
<u>Piping and Instrumentation Diagrams</u>	
P.&I.D. Legend	100872
P.&I.D. Steam and Condensate	432594
P.&I.D. Cooling Water	432595
P.&I.D. Lubricating Oil	432596
P.&I.D. Miscellaneous Service Systems	432597
Heat Balance Diagram	214443
Line Designation Table	100881
<u>Instrument Specifications</u>	
Pressure	100873
Temperature	100874
Flow and Level	100875
Control Valves	100876
Electrical	100877
Steam Traps	100878
Relief Valves	100879
Miscellaneous Instruments	100880

Drawing List (cont'd)

<u>Description of Drawing</u>	<u>Drawing Number</u>
<u>Instrument Piping Standards</u>	
Index of Instrument Symbols	045581
Instrument Pipe Line Take-off Conn.	045582
Main Steam Sample Nozzle	045584
Steam Trap Installation	045585
Pressure (P&PX) Installation	045586
Pressure Gage and Sample Conn. at Pump Discharge	045587
Steam Flow and Press. Recording Inst.	045588
Feed Lines Flow Test (Pitot Tube) Inst.	045589
Vacuum Duct Level Control	045590
Water Storage Tank Level Switch Inst.	045591
Hydrogen Coolers Outlet Temperature	045592
Exhaust Pressure Instrument Inst.	045593
Main Steam Pressure and Temp. Recorder	045594
Sump Pump Control and Alarm	045595
Requirements for CO ₂ Bottle Rack	045598
<hr/>	
General Notes and References for Pipe Hangers & Supports.	045601
Details of Pipe Hanger No. 101.	045602
Details of Pipe Hanger No. 102	045603
Details of Pipe Hanger No. 103	045604
Details of Pipe Hanger No. 104	045605
Details of Pipe Hanger No. 105	045606
Details of Pipe Hanger No. 106	045607
Details of Pipe Hanger No. 107	045608
Details of Pipe Hanger No. 108	045609
Details of Pipe Hanger No. 109	045610
Details of Pipe Hanger No. 110	045611
Details of Main Steam Pipe Hanger No. 301	045612
Support Shoe & Load Flange for Main Steam Hanger No. 301	045613
Details of Main Steam Pipe Hanger No. 302	045614
Details of Main Steam Pipe Hanger No. 303	045615
Details of Main Steam Pipe Hanger No. 304	045616
Details of Main Steam Pipe Hanger No. 305	045617
Support Shoe & Base Plate Details of Hangers No. 303, 304, 305	045618
Details of Main Steam Pipe Hanger No. 306	045619
Details of Pipe Hanger Steel Attachment No. 1	045621
Details of Pipe Hanger No. 111	045623
Details of Pipe Hanger No. 112	045624
Details of Pipe Hanger No. 113	045625
Details of Pipe Hanger No. 114	045626
Details of Pipe Hanger No. 115	045627
Details of Pipe Hanger No. 116	045628
Details of Pipe Hanger No. 117	045629
Details of Pipe Hanger No. 118	045630
Details of Pipe Hanger No. 119	046271
Details of Pipe Hanger No. 120	046272
Details of Pipe Hanger No. 121	046273
Details of Pipe Hanger No. 122	046274
Details of Pipe Hanger No. 123	046275

Drawing List (cond't)

<u>Description of Drawing</u>	<u>Drawing Number</u>
Details of Pipe Hanger No. 124	046276
Details of Pipe Hanger No. 125	046277
Details of Pipe Hanger No. 126	046278
Details of Pipe Hanger No. 127	046279
Details of Pipe Hanger No. 128	046280
Details of Pipe Hanger No. 129	046281
Details of Pipe Hanger No. 130	046282
Details of Pipe Hanger No. 1	046283
Details of Pipe Hanger No. 2	046284
Details of Pipe Hanger No. 3	046285
Details of Pipe Hanger No. 4	046286
Details of Pipe Hanger No. 5	046287
Details of Pipe Hanger No. 6	046288
Details of Pipe Hanger No. 7	046289
Details of Pipe Hanger No. 8	046290
Details of Pipe Hanger No. 9	046291
Details of Pipe Hanger No. 10	046292
Details of Pipe Hanger No. 11	046293
Details of Pipe Hanger No. 12	046294

DRAWING LIST

<u>Description of Drawing</u>	<u>Drawing Number</u>
<u>Electrical Drawings</u>	
<u>Single Line Diagrams</u>	
S.L. Diag. Unit 3	433101
S.L. M.&R. Diag. Unit 3	433102
Function Diagram Turbine-Generator Protection	433105
System Phasing and Syn. Pot. Diagram	433106
<u>Main Unit Schematic Diagrams</u>	
Schematic M.&R. Gen. Transformer, OCB	433107
Schematic Diagram Turbine Control	433110
Schematic Diagram Gen. Control (Sh. 1)	433111
Schematic Diagram Gen. Control (Sh. 2)	433112
Schematic Diagram Seal Oil PPs & H ₂ Control	433114
Schematic Diagram Excitation - Regulation	433115
Schematic Diagram Turning Gear Motors	433116
Schematic Diagram Cooling Water Pumps	433117
Schematic Diagram Lube Oil Pumps	433118
Schematic Diagram Miscellaneous Motors	433119
Schematic Diagram 60 kv OCB	433120
<u>Station Electrical Schematic Diagrams</u>	
Schematic Diagram Main & Aux. Transformers	433121
Schematic Diagram 120/208 V. Sta. Serv. & 125 vdc	433122
Schematic Diagram Annunciator System	433126
Schematic Diagram Instrumentation	433128
Wiring Diagrams, Terminal Boxes	433129
Arrangement of Control and Relay Board	433131
Arrangement of Main and Auxiliary Transformers	433133
Air Switch Requirements for 60 kv Switch and Bus	433135
Arrangement 60 kv Switch and Bus Structure	433136
Electrical Arrangement of Cooling Tower	433137
Steel Requirements 60 kv Switch and Bus	214837
<u>Cable Trays and Conduit Layouts</u>	
Arrangement of Conduits, Outdoors	433139
Arrangement of Embedded Conduits and Grounds-Power Building	433140
Cable Tray and Conduit Layout.. Power Building Basement	433141
Cable Tray and Conduit Layout Plan Above Main Floor	433142
Cable Tray and Conduit Layout Sections	433143
Conduit Section and Details	433144
<u>Conduit and Tray Schedules</u>	
Tray Schedule	045771
Conduit Schedule - Power Building	045772
Conduit Schedule - Switchyard	045773

Electrical Drawing List (cont'd)

<u>Description of Drawing</u>	<u>Drawing Number</u>
<u>Circuit Schedules</u>	
Circuit Schedule - Turbine Generator Excitation and Regulation	045776
Circuit Schedule - 480 Volt	045777
Circuit Schedule - 125 Volt DC	045778
Circuit Schedule - Annunciator	045779
Circuit Schedule - Lighting & Miscellaneous	045780
<u>Grounding Layouts</u>	
General Arrangement of Sta. & Fence Gnd.	433146
<u>Lighting Layouts</u>	
Lighting Layout Power Building	433149
<u>Bill of Material</u>	
Control and Relay Boards	045783
Arrangement of Main and Auxiliary Transformers	045784
Power Control Wire and Cable	045785
Tel. Thermo. and Miscellaneous Wire	045786
Grounding Materials	045787
Miscellaneous Equipment	045788
Arrangement 60 kv Switch and Bus Str.	045789
Cable Tray and Conduit Layout, Power Building Basement	045795
<u>Miscellaneous</u>	
Typical Details - Conduit, Trays, Miscellaneous	045790
General Notes and Symbols, Trays and Conduits	045791
Ground Symbols - Notes - Details	045792
Typical Mounting Details - Miscellaneous Lighting Fixtures	045794

P&I DRAWINGS

MEASURED VARIABLE	MEASURING			ALARM		SWITCH		TEST POINT
	RECORDING	REMOTE INDICATING	LOCAL INDICATING	LOW	HIGH	LOW	HIGH	
P-PRESSURE	PR	PI	P	LPA	HPA	PS		PX
T-TEMPERATURE								
F-FLOW	FR							FX
L-LEVEL			L	LLA	HLA	LLS	HLS	
S-SAMPLE CONN.								SC
PO-POSITION						POS		

APS - AUTOMATIC PUMP START
BS - BASKET STRAINER
DT - DRAIN TRAP
HLT - HIGH LEVEL TRIP
HTA - HIGH TEMPERATURE ALARM
HTT - HIGH TEMPERATURE TRIP
LC - LEVEL CONTROLLER
M - MANOMETER
POT - POSITION TRIP
PUI - PURITY INDICATOR
RO - RESTRICTING ORIFICE
RV - RELIEF VALVE
SSV - SOLENOID STOP VALVE
ST - STEAM TRAP
T - THERMOMETER (LOCAL)
TCV - TRIP CHECK VALVE
TTV - TRIP THROTTLE VALVE
VFC - FLOW CONTROL VALVE
VPC - PRESSURE CONTROL VALVE
YS - WYE STRAINER

MISCELLANEOUS

FLOW ORIFICE	STEAM TRAP	Y-STRAINER	STM. JET EJECTOR
REDUCER INCREASER	FURNISHED WITH ASSOC. EQUIP.	RESTRICT. ORIFICE	EXPANSION JT.
PIPE COUPLING	REFERENCE TO DWG. NO. SHOWN	BASKET STRAINER	

VALVE SYMBOLS

CONTROL VALVE	LOCK VALVES	
	OPEN	CLOSED
	L.O.	L.C.
	NORMAL POSITION	
	OPEN	CLOSED
		FLOW
	GATE	GLOBE
		CHECK
	BUTTERFLY	ANGLE
		NEEDLE
	PLUG OR BALL	SOLENOID SINGLE COIL
		DOUBLE COIL
		3 WAY VALVE

LINE SYMBOLS

VALVE SYMBOLS

TYPICAL INSTRUMENT SYMBOLS

M-INDICATES P.G. & E. MASTER CONTROL BOARD
E-INDICATES PANEL FURNISHED BY ELLIOTT CO.
H-INDICATES HYDROGEN BOND
TG-INDICATES TURNING GEAR BOARD.

PRIMARY LINES
SECONDARY LINES
INSTRUMENT ELECTRIC LEAD
INSTRUMENT CAPILLARY TUBING

REFERENCE DRAWINGS

NUMBER	TITLE
432594	STEAM & CONDENSATE
432595	COOLING WATER
432596	LUBRICATING OIL
432597	MISC. SERVICE SYSTEMS

NORTH BAY DIVISION

NO.	DATE	DESCRIPTION	GM	BY	CH.	APRD.
3	1-15-65	DELETED & ADDED INSTRUMENT SYMBOLS	159324	JAV	PS	
2	8-9-65	ADDED VALVE SYMBOL & ISSUED FOR BID SPEC. 6892	159324	WP	PS	
1	7-22-65	APPROVED FOR CONSTRUCTION	159324	WP	PS	
01	5-12-65	ISSUED FOR INFORMATION	159324	WP	PS	

TABLE OF CHANGES

APPROVED BY	GM 159324
SUPRV. BY	W. Dodson
DSGN. BY	M.C.
DR.	W. Cordrey
CH.	P. Schroth
O.K.	Law
DATE	4-27-65
SCALE	None

PIPING AND INSTRUMENT DIAGRAM
LEGEND
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

BILL OF MATERIAL	
DRAWING LIST	
SUPERSEDES	
SUPERSEDED BY	
SHEET NO.	SHEETS
DRAWING NUMBER	CHANGE
100872	3

PIPING AND INSTRUMENT DIAGRAM
 STEAM AND CONDENSATE
 UNIT NO. 3
 THE GEYSERS POWER PLANT
 DEPARTMENT OF ENGINEERING
 PACIFIC GAS AND ELECTRIC COMPANY
 SAN FRANCISCO, CALIFORNIA

432594

502224

TABLE OF CHANGES				TABLE OF CHANGES			
NO.	DATE	DESCRIPTION	BY	NO.	DATE	DESCRIPTION	BY
1	12-15-62	REVISIONS FOR INSTRUMENTATION	CH	1	12-15-62	REVISIONS FOR INSTRUMENTATION	CH
2	1-15-63	REVISIONS FOR INSTRUMENTATION	CH	2	1-15-63	REVISIONS FOR INSTRUMENTATION	CH
3	2-15-63	REVISIONS FOR INSTRUMENTATION	CH	3	2-15-63	REVISIONS FOR INSTRUMENTATION	CH
4	3-15-63	REVISIONS FOR INSTRUMENTATION	CH	4	3-15-63	REVISIONS FOR INSTRUMENTATION	CH
5	4-15-63	REVISIONS FOR INSTRUMENTATION	CH	5	4-15-63	REVISIONS FOR INSTRUMENTATION	CH
6	5-15-63	REVISIONS FOR INSTRUMENTATION	CH	6	5-15-63	REVISIONS FOR INSTRUMENTATION	CH
7	6-15-63	REVISIONS FOR INSTRUMENTATION	CH	7	6-15-63	REVISIONS FOR INSTRUMENTATION	CH
8	7-15-63	REVISIONS FOR INSTRUMENTATION	CH	8	7-15-63	REVISIONS FOR INSTRUMENTATION	CH
9	8-15-63	REVISIONS FOR INSTRUMENTATION	CH	9	8-15-63	REVISIONS FOR INSTRUMENTATION	CH
10	9-15-63	REVISIONS FOR INSTRUMENTATION	CH	10	9-15-63	REVISIONS FOR INSTRUMENTATION	CH

APPROVED BY: D. V. KELLY
No. 9209
DATE: 1-15-63

GM 159324
SHEET NO. 3
DATE: 1-15-63
SCALE: 1/8" = 1'-0"

PIPING AND INSTRUMENT DIAGRAM
COOLING WATER
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

RECEIVED PROFESSIONAL ENGINEER
D. V. KELLY
No. 9209
SAN FRANCISCO, CALIFORNIA
NORTH BAY DIVISION

BILL OF MATERIAL
DRAWING LIST
SUPERSEDED BY
SUPERSEDED BY
SHEET NO. 3
432595

LEGEND
 L.O. SUPPLY
 L.O. RETURN
 SEAL OIL SUPPLY
 SEAL OIL RETURN

MANUAL OVERSPEED
 ROTOR POSITION (UPSTREAM & DOWN STREAM)
 VIBRATION
 LOW VACUUM TRIP - PS-1
 MAIN LOBE OIL COOLER OUTLET TEMP - HIGH - HTT-7
 TURBINE & GENERATOR BEARING TEMP - HTT-1, 3, 4, 6
 LOW BEARING OIL PRESSURE (TURNING GEAR)
 LOW BEARING OIL PRESSURE - PS-8
 LIQUID DETECTOR - MLT-3
 GENERATOR GAS HIGH TEMP - HTT-5 & 6
 HIGH SEAL TEMP - HTT-9 & 10
 LOW NO GAS PRESSURE - PS-7
 LOW PURITY (AFTER TIME DELAY)
 433105

REFERENCE DWGS.
 4R-34093-7, 8, 14, 39,
 4R-34063-55, 66.

TABLE OF CHANGES				TABLE OF CHANGES			
NO.	DATE	DESCRIPTION	BY	NO.	DATE	DESCRIPTION	BY
1	12-20-41	DELETED BY-1		1	12-20-41	DELETED BY-1	
2	10-10-41	MINOR REVISIONS		2	10-10-41	MINOR REVISIONS	
3	11-14-41	APPROVED FOR CONSTRUCTION		3	11-14-41	APPROVED FOR CONSTRUCTION	
4	12-20-41	ISSUED FOR INFORMATION		4	12-20-41	ISSUED FOR INFORMATION	

PIPING AND INSTRUMENT DIAGRAM
 LUBRICATING OIL
 UNIT NO. 3
 THE GEYSERS POWER PLANT
 DEPARTMENT OF ENGINEERING
 PACIFIC GAS AND ELECTRIC COMPANY
 SAN FRANCISCO, CALIFORNIA

432596

TABLE OF CHANGES					TABLE OF CHANGES				
NO.	DATE	DESCRIPTION	BY	CHK.	NO.	DATE	DESCRIPTION	BY	CHK.
1	10-23-61	ADDED SEPARATE VENT	WJW	RS	1	10-23-61	ADDED SEPARATE VENT	WJW	RS
2	11-22-61	ADDED SERVICE AIR SYSTEM	WJW	RS	2	11-22-61	ADDED SERVICE AIR SYSTEM	WJW	RS
3	1-13-62	ISSUED FOR INFORMATION	WJW	RS	3	1-13-62	ISSUED FOR INFORMATION	WJW	RS

APPROVED BY
D. V. KELLY
DATE 2-21-62

GM15992.4
BY W. W. DODD
CHECKED BY
DATE 2-21-62

PIPING AND INSTRUMENT DIAGRAM
MISCELLANEOUS SERVICE SYSTEMS
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

SHEET NO.
4325973

DATE
2-21-62

**LINE DESIGNATION
TABLE**

LINE NO.	SERVICE	MAXIMUM FLOW CONDITIONS				DESIGN RATING		LINE INFORMATION				REMARKS
		FLOW		PRESS. PSIG	TEMP. °F	PRESS. PSIG	TEMP. °F	SIZE IN	VEL. FPS	ΔP PSI	INSUL SPEC.	
		QUAN.	UNITS									
1	VENT FROM AFTER CONDENSER	5,326	LB/Hr.					8			-	
2	YS-1 BLOWDOWN	322	GPM					2			IV P	
3	EXHAUST DUCT DRIP PUMPS DISCH. HDR.	15,000		25	125			3			-	
4	EXHAUST DUCT DRIP HEADER	15,000		24" Hg				4			-	
5	EXHAUST DUCT DRIP PUMP 3-1 SUCTION	7,500						3			-	
6	EXHAUST DUCT DRIP PUMP 3-2 SUCTION										-	
7	EXHAUST DUCT DRIP PUMP 3-1 DISCHARGE			25							-	
8	EXHAUST DUCT DRIP PUMP 3-2 DISCHARGE			25							-	
9	MAIN STEAM THROTTLE VALVE BELOW SEAT DRAIN							1			IV P	
10	TURBINE SHELL DRAIN HEADER							2			-	
11	SECOND STAGE EJECTOR OUTLET	12,771	LB/Hr		300			10			-	
12	MAIN STEAM THROTTLE VALVE ABOVE SEAT DRAIN							3/4			IV P	
13	FUNNEL NO. 1 DRAIN.							2				
14	TCV-1 DRAIN							1				
15	MISCELLANEOUS DRAIN HEADER.							2				
16	INTER CONDENSER GAS DISCHARGE	5,197	LB/Hr					10			-	
17	EXHAUST DUCT DRIP PUMP 3-1 RECIRCULATION							3/4			-	
18	EXHAUST DUCT DRIP PUMP 3-2 RECIRCULATION										-	
19	EXHAUST DUCT DRIP PUMPS RECIRCULATION HEADER										-	
20	GAS FROM BAROMETRIC CONDENSER 3-1	2,549	LB/Hr					16			-	
21	GAS FROM BAROMETRIC CONDENSER 3-2	2,549						16			-	
22	FIRST STAGE EJECTOR OUTLET.	9,821						16			-	
23	ST-5 DRAIN & YS-3 BLOWDOWN HEADER.							1			-	
24	SUMP PUMP NO. 3-1 DISCHARGE							2			-	
25	" " NO. 3-2 "										-	
26	" " DISCHARGE HEADER										-	
27	WETTING PUMP NO. 3-1 SUCTION	100	GPM	10	80			4"			-	
28	" " NO. 3-2 "	100	GPM	10	80			4"			-	
29	COOLING TOWER SUPPLY PUMP DISCHARGE	14,500,000	LB/Hr	24	119			36			-	
30	CONDENSER SUPPLY PUMP DISCHARGE	13,900,000	LB/Hr	24	80			36

				APPROVED BY	GM 159324
				DRAWING LIST	
				BY W. Dodson	
				DR. J. A. VALERO	
				COL. P. Behrath	
				DATE 5-25-65	
				SCALE NONE	
NO.	DATE	DESCRIPTION	APPROVED		
1	3-8-66	APPROVED FOR CONSTRUCTION			
01	8-9-65	ISSUED FOR BID SPEC. 6892			
TABLE OF CHANGES				DVK	

LINE DESIGNATION TABLE
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

PIPE SPEC. B	
SUPERSEDED BY	
SHEET NO. 2	7 SHEETS
DRAWING NUMBER	CHANGE
100881	1

LINE NO.	SERVICE	MAXIMUM FLOW CONDITIONS				DESIGN RATING		LINE INFORMATION				REMARKS
		FLOW		PRESS. PSIG	TEMP. °F	PRESS. PSIG	TEMP. °F	SIZE IN.	VEL. FPS	ΔP PSI	INSUL. SPEC.	
		QUAN.	UNITS									
1	CONDENSER SUPPLY PUMP DISCHARGE.	13,900,000	LB/HR	50	80			36				
2	COOLING WATER TO H ₂ & OIL COOLERS & TO INTER & AFTER COND.	1,071,000						14				
3	HYDROGEN COOLING WATER SUPPLY HEADER.	250,000						6				
4	COOLING WATER FROM LUBE OIL COOLER.	67,500			86			4				
5	COOLING WATER TO LUBE OIL COOLERS.	67,500			80			4				
6	COOLING WATER FROM HYDROGEN COOLER.	250,000			87			6				
7	CIRC. WATER SUPPLY TO BAROMETRIC CONDENSERS.	12,816,500			80			36				
8	↓ INTERCONDENSER.	417,500						8				
9	↓ AFTERCONDENSER.	336,000						8				
10	↓ ↓ HYDROGEN SEAL OIL COOLERS.	12,500						1 1/2				
11	↓ FEED TO COOLING TOWER CELL NO. 1.	4,833,333			119			24				
12	↓ ↓ ↓ NO. 2.	↓						24				
13	↓ ↓ ↓ NO. 3.	↓						24				
14	↓ SUPPLY TO BAROMETRIC CONDENSER NO. 3-1.	6,408,250			80			24				
15	↓ ↓ NO. 3-2.	6,408,250			80			24				
16	DRIPS FROM BAROMETRIC CONDENSER 3-1.	6,653,371		3.75" Hg	119.8			36				
17	DRIPS FROM BAROMETRIC CONDENSER 3-2.	6,653,371		3.75" Hg	119.8			36				
18	DRIPS FROM INTERCONDENSER 3-1.	426,821		3.5-28.5"	109			20				
19	DRIPS FROM AFTER CONDENSER 3-1.	398,771		Hg ABS	120			16				
20	GLAND STEAM EDUCTOR NO. 3-1 EXHAUST.	25,133.5			85			4				
21	↓ NO. 3-2 ↓	25,133.5			85			4				
22 *	GLAND SEAL EDUCTOR & WETTING SUPPLY PUMP NO. 3-1 DISCH.	100	GPM.		80			3				
23 *	↓ NO. 3-2	↓						3				
24 *	↓ DISCH. HEADER.	↓						3				
25	COOLING TOWER WETTING LINE.							3				
26	GLAND STEAM EDUCTOR EXHAUST HEADER.	50,267	LB/HR		85			6				
27	COOLING WATER TO HYDROGEN COOLER 3-1.	62,500			80			3				
28	COOLING WATER TO HYDROGEN COOLER 3-2.							3				
29	COOLING WATER TO HYDROGEN COOLER 3-3.							3				
30	COOLING WATER TO HYDROGEN COOLER 3-4.							3

UNIT NO.
PIPE SPEC.
LINE NO.
LINE SIZE
INSUL. SPEC.

NO.	DATE	DESCRIPTION	APPROVED
1	3-8-66	APPROVED FOR CONSTRUCTION	
01	8-9-65	ISSUED FOR BID SPEC. 6892	
TABLE OF CHANGES			

APPROVED BY	ON 159324
DRAWING LIST	
BY W. Dodson	
DR. J. A. VALERO	
CH. P. Schroth	
G.E. Plan	
DATE 5-25-65	
SCALE	NONE

LINE DESIGNATION TABLE
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

PIPE SPEC.	C
SUPERSEDES	
REPLACES	
DRAWING NO. 3	7
DRAWING NUMBER	100881
CHANGES	1

LINE NO.	SERVICE	MAXIMUM FLOW CONDITIONS				DESIGN RATING		LINE INFORMATION				REMARKS
		FLOW		PRESS. PSIG	TEMP. °F	PRESS. PSIG	TEMP. °F	SIZE IN.	VEL. FPS	ΔP PSI	INSUL SPEC.	
		QUAN.	UNITS									
1	DIRTY OIL TANK DISCHARGE							1 1/2				
2	CLEAN OIL TANK DISCHARGE											
3	LUBE OIL FILTER TANK DISCHARGE											
4	LUBE OIL FILTER PUMP SUCTION											
5	LUBE OIL FILTER PUMP DISCHARGE											
6	LUBE OIL FILTER TANK INLET											
7	LUBE OIL RESERVOIR DRAIN											
9	H ₂ DETRAINING TANK & GAS TRAPS - VENT HEADER							2				
10	LUBE OIL EXHAUSTER - EXHAUT							4				
11	↓ ↓ ↓ ↓											
12	↓ ↓ ↓ ↓ - HEADER

UNIT NO.
PIPE SPEC.
LINE NO.
LINE SIZE
INSUL. SPEC.

NO.	DATE	DESCRIPTION	APPROVED
1	3-8-66	APPROVED FOR CONSTRUCTION	
01	8-9-65	ISSUED FOR BID SPEC. 6892	
TABLE OF CHANGES			

APPROVED BY	DN 159324
DRAWING LIST	
BY W. Dodson	
DR. J.A. VALERO	
CH. P. Schroth	
O.E. <i>[Signature]</i>	
DATE 5-25-65	
SCALES	NONE

LINE DESIGNATION TABLE
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

PIPE SPEC.	F
SUPERSEDES	
SUPERSEDED BY	
SHEET NO. 7	7 SHEETS
DRAWING NUMBER	100881
CHANGES	1

EQUIPMENT LOCATION
DRAWINGS

TABLE OF CHANGES				TABLE OF CHANGES			
NO.	DATE	DESCRIPTION	BY	NO.	DATE	DESCRIPTION	BY
1	10/1/54	Approved for Const.	1/1	1	10/1/54	Approved for Const.	1/1
2	10/1/54	Issued for Const.	1/1	2	10/1/54	Issued for Const.	1/1

EQUIPMENT LOCATION
PLANS AT EL. 1978'-6", 1920'-0" AND 1954'-0"
UNIT NO. 3
THE GEYSERS POWER PLANT
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA
57431

APPROVED BY: <i>[Signature]</i> DATE: 1-18-54		CHECKED BY: <i>[Signature]</i> DATE: 1-18-54		DESIGNED BY: <i>[Signature]</i> DATE: 1-18-54	
DRAWING NO. 57434		SHEET NO. 1		TOTAL SHEETS 1	
BILL OF MATERIAL DRAWING LIST SUPERSEDED BY REVISIONS BY SHEET NO.		57434			

ELECTRICAL

[illegible]

LEGEND

- FSS FIELD STARTING SWITCH
SS SYNCHRONIZING SWITCH
V VOLTMETER SWITCH
@A1 AMMETER SWITCH
@ WHITE INDICATING LIGHT
R RESISTOR
② MOTOR WITH INDICATED H.P.
□ CONTROL STATION AT LOCATION AS SHOWN
□ CONTROL STATION IN/AUTO STARTING DEVICE AT LOCATION AS SHOWN
L.A. LIGHTNING ARRESTER

EQUIPMENT LOCATIONS

- EQUIPMENT LOCATION
- 1A-3 MASTER CONTROL BOARD, PANEL A, UNIT No. 3
25 LOCAL CONTROL STATION AT MOTOR
35-3 480V. MOTOR CONTROL CENTER, UNIT No. 3
52-3 480V. SWITCHGEAR, UNIT No. 3
57-3C REGULATOR CONTROL CABINET
57-3T REGULATOR POWER TRANSFORMER
60-3 EXCITER CABINET, UNIT No. 3
55-1 12KV SWITCHGEAR, CELL 1
09-3 TURNING GEAR, CONTROL CABINET, UNIT No. 3
26-3 HYDROGEN CONTROL BOARD GENERATOR No. 3

SINGLE LINE DIAGRAM UNIT 3

DWG. 433101

[illegible]

APPROVED BY	GM 159324
	SPY. W.M. Hoffman
	DOON.
	DR. A.R. Schaefer
	CH.
	O.K. <i>[Signature]</i>
DATE	2-28-64
SCALE	<i>[Signature]</i>

**SINGLE LINE METER AND RELAY DIAGRAM
UNIT NO.3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA**

BILL OF MATERIAL	
DRAWING LIST	
SUPERSEDED	
SUPERSEDED BY	
SHEET NO.	OF
DRAWING NUMBER	
433102

GOVERNOR MOTOR CONTROL CIRCUIT

13.8KV GENERATOR AIR CIRCUIT BREAKER CIRCUIT NO 3G

DEVICE	FUNCTION	RATING	MFR.	TYPE	CAT. NO. REV. ENG. NO.	REMARKS
80/205-3	UNIT LOCKOUT RELAY D.C. UNDERVOLTAGE RELAY	125V D.C.	M.E.G.	5G	1161 590	1ST SPARE CONTACT
80/252-3	GENERATOR BREAKER CONTROL D.C. UNDERVOLTAGE RELAY	125V D.C.	M.E.G.	5G	1161 590	
80X-3	BATTERY UNDERVOLTAGE AUXILIARY RELAY	—	—	—	(5)	
86M-3	100X SWITCHBAR LOCKOUT RELAY	125V D.C.	M.E.G.	WL	300P30501	MANUAL RESET
231-3	AUXILIARY TRANSFORMER OVERCURRENT RELAYS	—	—	—	(1)	
232-3	GENERATOR AIR CIRCUIT BREAKER	—	—	—		
206-3	TURBINE LOCKOUT RELAY	—	—	—	(3)	
206F-3	GENERATOR LOCKOUT RELAY	—	—	—	(3)	
351-1	LINE PHASE OVERCURRENT RELAYS	—	—	—	(1)	
35W-1	LINE GROUND OVERCURRENT RELAY	—	—	—	(1)	
306-3	UNIT LOCKOUT RELAY	125V D.C.	M.E.G.	WL	300P30601	MANUAL RESET
507-3	UNIT OVERALL DIFFERENTIAL RELAYS	—	—	—	(1)	
POS-2A	TURBINE MAIN STEAM TRIP VALVE	—	—	—	INSTL. SPEC. PART. NO. 1020800	
POS-3A	TURBINE MAIN STEAM CHECK VALVE	—	—	—	INSTL. SPEC. DRAW. NO. 1020800	

LEGEND

FSS - FIELD SHORTING SWITCH
HR - HAND RESET
ICS - INDICATING CONTACTOR SWITCH
RCO - RELAY CUT-OUT
TCO - TRIP CUT-OUT

EQUIPMENT LOCATION

1A-3 MASTER CONTROL BOARD, PANEL A, UNIT #3
35-1 13.8KV SWITCHGEAR, CUBICLE #1
57-36 REGULATOR CONTROL CABINET
86A TURBINE TERMINAL BOX A

REFERENCES

REFERENCES	
1.	SINGLE LINE METER & RELAY DIAGRAM DWS. # 433102
2.	SCHEMATIC DIAGRAM BURNING CONTROL 433110
3.	GENERATOR CONTROL SKI 433111
4.	EXCITATION REGULATION 433115
5.	10/200BY. SKI. SKM & 125KDC SYSTEM 433122
6.	AMMUNICATOR SYSTEM 433126
7.	SKL OIL PUMPS & H ₂ CONTROL SYSTEM 433114
8.	60 KV OCB 433180

CONTACTS	POSITIONS		REMARKS
	OFF	ON	
— —	A	X	REG. DIAL. NO.
— —	B	X	SPACE
— —	C	X	REG. DIAL. NO.
— —	D	X	THIS DIAL.
— —	E	X	SPACE
— —	F	X	SPACE

SYNCHRONIZING SWITCH ²⁵²⁻³
SS
NO SPRING RETURN LOC 1B-3

CONTACTS	POSITIONS			REMARKS
	TRIP	OFF AFTER TRIP	CLOSE	
A1 ——— B1	A	X		THIS DIED
A1 ——— B1	B	X	X	See Rev. Dura
A1 ——— B1	C			THIS DIED
A1 ——— B1	D	X	X	SPARE
A1 ——— B1	E		X	See Rev. Dura
B1 ——— B1	F	X	X	SPARE
B1 ——— B1	G		X	SPARE

CONTROL SWITCH 252-3
CS
SPRING RETURN TO NEUTRAL LOC 1B-3

										APPROVED					GM 159324				
															SPERN. Herlin				
															DOWNS. Berlin				
															Ph. L. Coleman				
															GR.				
															D.L. HER				
															DATE 4-22-68				
															7.13				
															None				

**SCHEMATIC DIAGRAM
GENERATOR CONTROL
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA**

NORTH BAY DIVISION

BILL OF MATERIAL
DRAWING LIST
SUPERSEDES
SUPERSEDED BY
SHEET NO. 2 2
DRAWING NUMBER
433112

HYDROGEN SYSTEM
TRIP
SEE REF. DWG. NO. 3

25.3 80H.3 25.3
PK PK

DC CONTROL UNDERV
SEE REF. DWG. NO. 3

GAS DRYER CIRCUIT NO 41-18

LINE START INDUCTION MOTOR
THREE LINE DIAGRAM

120V AC CONTROL SCHEMATIC
TURNING GEAR DRIVE CKT. No. 3-16 P

LINE START INDUCTION MOTOR
THREE LINE DIAGRAM

120V AC CONTROL SCHEMATIC
TURNING GEAR OIL PUMP CKT. No. 3-17 P

CONTACT	POSITION	REMARKS
42-17	MANUAL	
42-17	AUTO	
42-17	INDICATION	
42-17	ALARM	

CONTROL SWITCH 42-17
USED AT LOC. 82-3
NO SPRING RETURN

DEVICE	FUNCTION	RATING	WTR	TYPE	REMARKS
42-17	480V Motor Starter (Size 1)			(2)	
42-18	480V Motor Starter Overload Relay			(2)	
52-15-17	480V Motor Starter Circuit Breaker			(2)	
74-76	Turning Gear Trouble Alarm Relay			ASBX	Latch Relay, Electr. Reset
74-77	Turning Gear Bearing Low Oil Press.				
74-78	Turning Gear Bearing Low Oil Press.				
74-79	Turning Gear Bearing Low Oil Press.				
74-80	Turning Gear Bearing Low Oil Press.				
74-81	Turning Gear Bearing Low Oil Press.				
74-82	Turning Gear Bearing Low Oil Press.				
74-83	Turning Gear Bearing Low Oil Press.				
74-84	Turning Gear Bearing Low Oil Press.				
74-85	Turning Gear Bearing Low Oil Press.				
74-86	Turning Gear Bearing Low Oil Press.				
74-87	Turning Gear Bearing Low Oil Press.				
74-88	Turning Gear Bearing Low Oil Press.				
74-89	Turning Gear Bearing Low Oil Press.				
74-90	Turning Gear Bearing Low Oil Press.				
74-91	Turning Gear Bearing Low Oil Press.				
74-92	Turning Gear Bearing Low Oil Press.				
74-93	Turning Gear Bearing Low Oil Press.				
74-94	Turning Gear Bearing Low Oil Press.				
74-95	Turning Gear Bearing Low Oil Press.				
74-96	Turning Gear Bearing Low Oil Press.				
74-97	Turning Gear Bearing Low Oil Press.				
74-98	Turning Gear Bearing Low Oil Press.				
74-99	Turning Gear Bearing Low Oil Press.				
74-100	Turning Gear Bearing Low Oil Press.				

- EQUIPMENT LOCATION
- 24 Locally Mounted Device
 - 35-3 480V Motor Control Center
 - 86-8 Turbine Terminal Box "B"
 - 82-3 Turning Gear Drive Cabinet, Generator No. 3

- REFERENCE DRAWINGS
- 1. P.E.I. Diagram Lubricating Oil ———— DAMEL 432196
 - 2. Single Line Meter & Relay Diagram, Unit No. 3 ———— DAMEL 433102
 - 3. Schematic Diagram Annunciator System, Unit No. 3 ———— DAMEL 433126
 - 4. ————
 - 5. ————
 - 6. ————

NO.	DATE	DESCRIPTION	BY	CH.	APPROVED	DATE	DESCRIPTION	BY	CH.	APPROVED	DATE
1	10-1-65	Add Alarm 42-17									

SCHEMATIC DIAGRAM
TURNING GEAR MOTORS
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

433116

MOTOR	H.P.	CKT. BKR.	CKT. No.	CONTROL SWITCH & IND. LIGHTS AT	42- AUX. CONTACTS		ALARM	HYDR. STARTER AUX. RELAY
					AI- A2	AI- AL2		
VAPOR EXHAUSTER	1/2	52-19	3-19P	LOC. 10-3	SPARE	ALARM THIS OWB.	—	42X-19
LUBE OIL FILTER PUMP	1/3	52-18	3-18P	LOC. 25	SPARE	ALARM THIS OWB.	HL-5 AS SHOWN	—

TABLE OF DEVICES						
DEVICE	FUNCTION	RATING	NFR TYPE	CAT. NO.		REMARKS
42-11	480V. MOTOR STARTER (SIZE 2)	—	—	(2)		
49-11	480V. MTR. STR. OVERLOAD RELAY	—	—	(2)		
52-11	480V. MTR. STR. CIRCUIT BREAKER	—	—	(2)		
42-1B, 19	480V. MOTOR STARTER (SIZE 1)	—	—	(2)		
49-1B, 19	480V. MTR. STR. OVERLOAD RELAY	—	—	(2)		
52-1B, 19B	480V. V. MTR. STR. CIRCUIT BREAKER	—	—	(2)		
62-21	STAND-BY LUBE OIL TIMING RELAY	125K.DC	W.E.Omp	TK	H76018	WITH INVERTER STYLE 1005561
42A-11, -19	480V. MOTOR STARTER AUX. RELAY	115 V.A.C.	W.E.Otp	S6	1205 GMS	
72-6	125K.DC DISTR. PHL. CIRCUIT BREAKER	—	—	(3)		
72C-6	125K.DC MOTOR STARTER	—	—	(3)		
76-6	125K.DC MTR. STR. OVERLOAD RELAY	125K.DC	G.E.Co.	CR-106	S12G DEA	HEATER CNT.NR. C 6.30 A
72-21	125K.DC DISTR. PHL. CIRCUIT BREAKER	—	—	(3)		
72C-21	25K.V DC 480V. MOLT. MOTOR STARTER	125K.DC	G.E.Co.	101052-AIP		
76-21	125K.DC MOTOR STR. OVERLOAD RELAY	125K.DC	W.E.Omp	36		MTR.CNT.NR. CR193C 25.00 SIZE P RELAY
72CK-21	125 K DC MTR. STR. AUX. RELAY	125K.DC	W.E.Omp	36		
APS-1	LUBE OIL STAND-BY PUMP START PRESS. SW.	—	—	—	WITH BEAC. HUB 17	DATA IN 4-837 Q-201 AT 6 PSI CASH AT 40 PSI P-241 AT 35 PSI
APS-3	LUBE OIL AUX. PUMP START PRESS. SW.	—	—	—	"	"
NLS-1	LUBE OIL FILTER TANK HIGH LEVEL SW.	—	—	—	"	"
NLA-5	" " " " " " ALARM	—	—	—	"	"
NLA-6	LUBE OIL RESERVOIR HIGH LEVEL ALARM	—	—	—	"	"
NLA-2	" " " " " " ALARM	—	—	—	"	"

EQUIPMENT LOCATION

10-3 Master Control Board, Panel D, Unit No. 3
24 Locally Mounted Device
35-3 480 V. Motor Control Center, Unit No. 3
63-3 125 V. DC Distribution Panel, Unit No. 3
96-B Turbine Terminal Box B
99-3 Turning Gear Control Cabinet, Generator No. 3
25 Local Control Station at Motor

REFERENCE DRAWINGS

1.	P&I Diagram Lubricating Oil	Dwg. No. 432596
2.	Single Line Meter & Relay Diagram, Unit No. 3	Dwg. No. 433102
3.	Schematic Diagram 120/208V Sta. Serv. & 125V DC System Unit No. 3	Dwg. No. 433122
4.	Schematic Diagram Annunciator System, Unit No. 3	Dwg. No. 433126

[illegible]

APPROVED BY	GM 159324
	SUPERV. WITH HARTIN
	DR. S. KAN
	DR. D. DODSON
	GN.
	O.K. <i>Flair</i>
	DATE 8-9-65
	SCALE None

**SCHEMATIC DIAGRAM
LUBE OIL AND EXHAUST PUMPS
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY**

BILL OF MATERIALS
DRAWING LIST
SUPERSEDES
SUPERSEDED BY
SHEET NO.
DRAWING NUMBER

BILL OF MATERIAL	
DRAWING LIST	
SUPERSEDES	
SUPERSEDED BY	
SHEET NO.	
DRAWING NUMBER	
433119	

021887

CONTINUED ON DWG. NO. 433121

DC CONTROL SCHEMATIC FOR 60 KV O.C.B. CIRCUIT NO. 35

COMPRESSOR MOTOR CIRCUIT NO. 3-9D

CONTROL MECHANISM HEATER CIRCUIT NO. LI-34

CONTROL SWITCH CS
Used at Loc. 1E3
Spring return to Neutral

SYNCHRONIZING SWITCH 352-1
Used at Loc. 1E3
No Spring return

TABLE OF DEVICES						
DEVICE	FUNCTION	RATING	MFR.	TYPE	CAT. NO. REF. DWG.	REMARKS
AM	60 KV Line - Current	—	—	—	(1)	
WM	60 KV Line - Megawatts	—	—	—	(1)	
VAR	60 KV Line - Megavars	—	—	—	(1)	
WH	Unit Power Output	—	—	—	(1)	
VM	Station Voltage (Running)	—	—	—	(1)	
VM	Line Voltage (Incoming)	—	—	—	(1)	
SYN	Unit Synchronizing	—	—	—	(1)	
80/352-1	60 KV O.C.B. - DC Under-voltage Relay	125V DC	WE Co.	SG	1161 340	
351-A	Line Overcurrent Relays	—	—	—	(1)	
351N-1	Line Ground Overcurrent Relay	—	—	—	(1)	
352-1	60 KV Oil Circuit Breaker	—	—	—	(1)	
363A-1	60 KV O.C.B. Low Air Pressure Alarm	—	—	—	Part of 80/352-1	
386-1	Unit Lockout Relay	—	—	—	(2)	Hand Reset

EQUIPMENT LOCATION

- 1A-3 Master Control Board, Panel A, Unit No. 3
- 1E3 High Voltage Potential Transformer (60KV)
- 1E2 60 KV Oil Circuit Breaker Control Cabinet
- 1E4 Metering Set (60KV)

REFERENCES

- 1. Single Line Meter & Relay Diagram
 - 2. Schematic Diagram Generator Control Sh. 2
 - 3. Schematic Diagram 120/208V Sta. Serv. 125V DC. Sys.
 - 4. Schematic Meter & Relay Diag. Gen. Exc., Reg., & Air Ckt. Blk.
 - 5. Schematic Diagram Annunciator
- Dwg. No. 433102
Dwg. No. 433112
Dwg. No. 433122
Dwg. No. 433107
Dwg. No. 433126

APPROVED BY: GM159324		DATE: 12-1-65	
CHECKED BY: [Signature]		DATE: 12-1-65	
DRAWN BY: [Signature]		DATE: 12-1-65	
SUPERSEDED BY: [Signature]		DATE: 12-1-65	
SHEET NO. 433120		SHEET NO. 433120	

SCHEMATIC DIAGRAM
60KV OCB NO. 42
UNIT NO. 3
THE GEYSERS POWER PLANT
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

CONTINUED ON DWG. No. 433107
13.8 KV

MAIN TRANSFORMER COOLING EQUIPMENT, CKT.# LI-40

125 V DC. SCHEMATIC DIAGRAM
MAIN TRANSFORMER ANNUNCIATOR

CONTACT		POSITION								REMARK
		SWP	INT	A	INT	B	INT	C		
	A	x		x	x	x	x	x	x	
	B		x	x	x		x	x	x	
	C		x	x	x		x	x	x	
	D	x	x	x	x		x	x	x	
	E					x	x			
	F					x	x	x		
	G	x	x	x	x	x	x		x	
	H							x	x	
	K							x	x	
		x	x	x	x	x	x		x	SPARE
		x	x	x	x	x	x		x	SPARE
		x	x	x	x	x	x		x	SPARE

AMMETER SWITCH $\frac{AM}{SW}$
USED AT LOC 1D-3

CONTACT	POSITION				REMARK
	OFF	A-B	B-C	C-A
A	X
B		X
C			X
D	X
E		X
F			X	

VOLTMETER SWITCH
USED AT LOC. 10-3

125 V D.C. SCHEMATIC DIAGRAM
480V M.C.C. TIE BREAKER, CKT. # 3-1P

CONTACT	POSITION			REMARKS
	TRIP RESET	NEUT.	CLOSE
A			X	THIS DWG
B	X			THIS DWG

CONTROL SWITCH 52-1
USED AT LOC. 1D-3
SPRING RETURN TO NEUTRAL

EQUIPMENT LOCATION

- 1D-3 MASTER CONTROL BOARD, PANEL D, UNIT No.3
35-3 480 V MOTOR CONTROL CENTER, UNIT No.3
41-3 MAIN TRANSFORMER, ELECTRO COOLER CAB., GEN. No.3
52-3 480 V SWITCHGEAR, UNIT No.3
55-1 13.8 KV SWITCHGEAR, CUB. No.1
58-3 120/208 V AC DISTRIBUTION PANEL, UNIT No.3
70-3 AUXILIARY TRANSFORMER, UNIT No.3

REFERENCE DRAWINGS

1. SINGLE LINE DIAGRAM, UNIT NO.3
2. SINGLE LINE METER & RELAY DIAGRAM, UNIT NO.3
3. SCHEMATIC DIAGRAM GENERATOR CONTROL, SK-1, UNIT NO.3
4. 120/208 V AC STATION SERVICE AND IEEE DC SYSTEMS, UNIT NO.3
5. SCHEMATIC DIAGRAM ANNUNCIATOR SYSTEM, UNIT NO.3
6. SCHEMATIC DIAGRAM METER & RELAY GENERATOR
7. SCHEMATIC DIAGRAM 600Y OL OIL CIRCUIT BREAKER
8. ELEMENTARY DIAGRAM MAIN TRANSFORMER

DWG. No. 433 101
433 102
433 111
433 122
433 126
433 107
433 120
↓
REC. No. 656818

**SCHEMATIC DIAGRAM
MAIN AND AUXILIARY TRANSFORMERS
AND 480VOLT TIE BREAKER
UNIT NO3 THE GEYSERS POWER PLANT**
DEPARTMENT OF ENGINEERING
PACIFIC GAS AND ELECTRIC COMPANY
SAN FRANCISCO, CALIFORNIA

ALL OF MATERIAL	
DRAWING LIST	
SUPERSEDES	
SUPERSEDED BY	
SHEET NO.	SHEETS
DRAWING NUMBER	CHANGE
4.33121	1