NOV 14 1966

SNPO-C
MASTER

Westinghouse Electric Corporation Astronuclear Laboratory

TNR-189

RELEASED FOR ANNOUNCEMENT
IN NUCLEAR SCIENCE ABSTRACTS

RECEIVED
WESTINGHOUSE ASTRONUCLEAR CORP.
OCT 13 1966
ASTONUCLEAR LAB
PITTSBURGH, PA

UNCLASSIFIED NERVA RESEARCH
AND DEVELOPMENT REPORT.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

Astronuclear
WANL-TNR-189
DECEMBER 1964

SUBMITTED BY:

Westinghouse Electric Corporation
Astronuclear Laboratory
Pittsburgh, Pennsylvania 15236

REC-300-118-70

INFORMATION CATEGORY

UNCLASSIFIED

DW Drawbaugh 12/10/64
Authorized Classifier - Date

RELEASED FOR ANNOUNCEMENT

IN NUCLEAR SCIENCE ABSTRACTS

PREPARED BY:

G. Collier
and
J. W. Riese

APPROVED BY:

DW Drawbaugh
D. W. Drawbaugh, Mgr.
Reactor Physics & Math.

VARI-QUIR III:
A TWO-DIMENSIONAL STEADY STATE
MULTI-GROUP DIFFUSION CODE

UNCLASSIFIED NERVA RESEARCH
AND DEVELOPMENT REPORT.

TABLE OF CONTENTS

ABSTRACT	<u>Page</u> i
CHAPTER I - PROBLEM, EQUATION DERIVATION, APPLICATION	
A. The Problem	1
B. Variational Principle	3
C. The "Quadratic-in-Region" Form (VARI-QUIR)	6
D. The Two-Dimensional Equations	8
E. Typical Problem	26
F. Further Plans	31
CHAPTER II - DESCRIPTION OF CODE	
A. Present Limitations	32
B. Input Preparation	33
References	38
Appendix A - Derivation of the ϕg^* Euler Equation	39
Appendix B - A Practical Problem Using the Variational Principle	43
Appendix C - FORTRAN Listing	52

ABSTRACT

A variational approximation is developed for the steady state neutron diffusion equations. The method is incorporated into a computer code, which allows up to 18 energy groups and 23 different-material regions. The code can handle problems with X-Y and R-Z geometries. An R- θ version of the code is being written and the equations for R- θ geometry are also given in this report.

I. PROBLEM, EQUATION DERIVATION, APPLICATION

A. The Problem¹

We wish to solve the steady state equations arising from neutron diffusion theory. These equations can be written as:

$g = 1 \text{ to } G$

$$\nabla \cdot D_g \nabla \phi_g - \sum_g^R \phi_g + \sum_{g' \neq g}^G \sum_{g' \rightarrow g}^{TR} \phi_{g'} + k \chi_g \sum_{g'=1}^G \nu_{g'} \sum_{g'}^F \phi_{g'} = 0$$

where D_g is the diffusion coefficient, ϕ_g is the flux, $\sum_g^R$ is the macroscopic removal cross section, $\sum_{g' \rightarrow g}^{TR}$ is the macroscopic transfer cross section, k is the eigenvalue, χ_g is the fraction of the fission spectrum in the g th group, $\nu_{g'}$ is the average number of neutrons per fission in the g' th group, and $\sum_{g'}^F$ is the macroscopic fission cross section.

These steady state equations may be written:

$g = 1 \text{ to } G$

$$\nabla \cdot D_g \nabla \phi_g - \sum_{g'=1}^G \left[A_{gg'} \phi_{g'} - k B_{gg'} \phi_{g'} \right] = 0 \quad (1)$$

where the coefficients $\sum, \chi, \nu$ have been condensed into two matrices A and B . A is the removal part and B is the fission part.

Mathematically, we wish to find the lowest eigenvalue k of equation (1). If one knew the exact solution ϕ_g of equation (1), k could be found by solving for it in any one of the G equations, at any point in space. If one has only an approximate solution for the ϕ_g 's, the best estimate of k would be attained by averaging equation (1) over all space and all G equations, and then solving for k . This averaging is demonstrated, in part B, with the use of a variational principle.

B. Variational Principle

If we solve for k in equation (1), we get

$$k = \frac{\sum_{g=1}^G - \left[\nabla \cdot D_g \nabla \phi_g - \sum_{g'=1}^G A_{gg'} \phi_{g'} \right]}{\sum_{g=1}^G \sum_{g'=1}^G B_{gg'} \phi_{g'}} \quad (2)$$

Now we may integrate the numerator and the denominator over volume and at the same time multiply each by an arbitrary weighting function, say ϕ_g^* . With a little manipulation of the numerator and the removal of zero surface terms, the result will appear as[‡]:

$$k = \frac{\sum_{g=1}^G \int_V d^3\vec{r} \left\{ D_g (\nabla \phi_g^*) \cdot (\nabla \phi_g) + \sum_{g'=1}^G \phi_g^* A_{gg'} \phi_{g'} \right\}}{\sum_{g=1}^G \sum_{g'=1}^G \int_V d^3\vec{r} \phi_g^* B_{gg'} \phi_{g'}} \quad (3)$$

A good value of the eigenvalue k will be calculable from equation (3) as soon as we can get some estimate of the solution ϕ_g and the proper weighting function ϕ_g^* .

[‡] D_g is independent of position.

The correct weighting function will, by definition, be one that gives very small errors δk in k when our estimate of ϕ errs by $\delta\phi$; $\frac{\delta k}{\delta\phi} = 0$ gives us a criterion for ϕ^* . On the other hand, we already know by the way we set up equation (2) that any weighting function would work if we knew ϕ exactly, i.e., k is independent of ϕ^* when ϕ is correct, or $\frac{\delta k}{\delta\phi^*} = 0$ can be used to define ϕ . Combining these two results we see that simultaneous first-order variations in ϕ and ϕ^* will lead to only second-order variations in k , through the product $\delta\phi \cdot \delta\phi^*$. Therefore k is stationary for small variations in ϕ and ϕ^* , i.e.,

$$\delta k = 0 \tag{4}$$

Equation (4), along with the definition (3), is the required variational principle. It is easily shown[†] to lead to two Euler equations, one being just equation (2), the other a similar equation with all operators replaced by their adjoints and ϕ by ϕ^* .

The fact that these two Euler equations are of the same form gives a hint that whatever function is used to approximate ϕ_g , the same type should be used for ϕ_g^* .

[†]See Appendix A.

The variational principle, equation (4), is exact and completely equivalent to equation (1). It is, in addition, a convenient starting point for approximate solutions. Instead of considering the class of all possible functions with the correct boundary condition, suppose we consider some sub-class in detail, to find one which best approximates equation (4). This selection is covered in section C.

C. The "Quadratic-in-Region" Form (VARI-QUIR)

In studying plots of steady-state flux solutions, one observes that they are usually very smooth and simple curves within each material region. Sharp corners occur only in going from one material region to another, and sharp dips or peaks only as a result of such transitions. It would therefore seem possible to express the flux accurately within each different region as a different low-order polynomial in the spatial variables. Because of this reason we chose the simplest polynomial that allows smooth curves in a region, with possibly continuous slopes between region, namely the quadratic.

The only decision to be made now is the question of continuity of fluxes between regions. We know that the exact solutions for the fluxes will be continuous in value across an interface because of the ∇^2 operator in equation (2). Hence we could require our approximate solutions to also be continuous at interfaces. This is necessary, for otherwise non-integrable infinities will arise in the evaluation of equation (3), due to the product of $\nabla \phi_g \cdot \nabla \phi_g^*$. The problem was eliminated by the following trick, which we demonstrate for the one-dimensional case[†]. Instead of specifying the quadratic in a given region by its three coefficients,

[†]See Appendix B.

we can specify it uniquely by its values at three points. If the right-edge point of region n is called by the same name as the left-edge point of region $n+1$, the two curves are automatically continuous. One can readily verify by counting that there are just $2N+1$ such points in an N -region problem. With the two outside points determined by boundary conditions, this leaves just $2N-1$ points free to vary. With the foregoing designation on the quadratics, the variation principle reduces to a set of difference equations for the point values ϕ_n .

D. The Two-Dimensional Equations

The two-dimensional equations are presented here without derivation. These equations (5, 6, 7, and 8) are for the X-Y slab case without symmetry. Sketch 5 shows the four types of points to be calculated for each flux group.

Sketch 5

<u>Point No.</u>	<u>Type of Point</u>	<u>Material Regions Affecting Point (n)</u>	<u>Number of Points Affecting Point (n)</u>
(1)	Middle	I only	8 points surrounding point (1)
(2)	Left edge	XIII and XIV	14 points surrounding point (2)
(3)	Top edge	IX and XIII	14 points surrounding point (3)
(4)	Corner	VI, VIII, X, & XI	24 points surrounding point (4)

Each type of point has its own set of equations which are:

1. Middle Point Equations

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX$$

$$j = 1 \text{ to } NY$$

$$\sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g,i,j) \left[\frac{DX(i)}{DY(j)} P(i_1,2)Q(j_1,2) + \frac{DY(j)}{DX(i)} Q(i_1,2)P(j_1,2) \right] \right. \\
 \left. \phi(g,2i-2+i_1,2j-2+j_1) + DX(i)DY(j) \sum_{g'} \left[A(g,g',i,j) \right. \right. \\
 \left. \left. - kB(g,g',i,j) \right] P(i_1,2)P(j_1,2)\phi(g',2i-2+i_1,2j-2+j_1) \right\} = 0 \quad (5)$$

where D is the diffusion coefficient, ϕ is the flux, A is the removal matrix, B is the fission matrix, k is the eigenvalue, DX and DY are the region lengths in the X and Y direction respectively, and the P 's and Q 's are defined in Appendix B.

2. Left-Edge Point Equations

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX-1$$

$$j = 1 \text{ to } NY$$

$$\begin{aligned}
 & \sum_{s=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i-1+s, j) \left[\frac{DX(i-1+s)}{DY(j)} P(i_1, 5-2s) Q(j_1, 2) \right. \right. \\
 & \quad \left. \left. + \frac{DY(j)}{DX(i-1+s)} Q(i_1, 5-2s) P(j_1, 2) \right] \phi(g, 2i-4+2s+i_1, 2j-2+j_1) \right. \\
 & \quad \left. + DX(i-1+s) DY(j) \sum_{g'} \left[A(g, g', i-1+s, j) - kB(g, g', i-1+s, j) \right] \cdot \right. \\
 & \quad \left. P(i_1, 5-2s) P(j_1, 2) \phi(g', 2i-4+2s+i_1, 2j-2+j_1) \right\} = 0 \quad (6)
 \end{aligned}$$

3. Top-Edge Point Equations

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX$$

$$j = 1 \text{ to } NY-1$$

$$\begin{aligned}
 & \sum_{t=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i, j-1+t) \left[\frac{DX(i)}{DY(j-1+t)} P(i_1, 2) Q(j_1, 5-2t) \right. \right. \\
 & \quad \left. \left. + \frac{DY(j-1+t)}{DX(i)} Q(i_1, 2) P(j_1, 5-2t) \right] \phi(g, 2i-2+i_1, 2j-4+2t+j_1) \right. \\
 & \quad \left. + DX(i) DY(j-1+t) \sum_{g'} \left[A(g, g', i, j-1+t) - kB(g, g', i, j-1+t) \right] \right. \\
 & \quad \left. P(i_1, 2) P(j_1, 5-2t) \phi(g', 2i-2+i_1, 2j-4+2t+j_1) \right\} = 0 \quad (7)
 \end{aligned}$$

4. Corner Point Equations

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX-1$$

$$j = 1 \text{ to } NY-1$$

$$\sum_{s=1}^2 \sum_{t=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i-1+s, j-1+t) \left[\frac{DX(i-1+s)}{DY(j-1+t)} P(i_1, 5-2s) Q(j_1, 5-2t) \right. \right.$$

$$\left. + \frac{DY(j-1+t)}{DX(i-1+s)} Q(i_1, 5-2s) P(j_1, 5-2t) \right] \cdot$$

$$\phi(g, 2i-4+2s+i_1, 2j-4+2t+j_1) + DX(i-1+s)DY(j-1+t) \cdot$$

$$\sum_{g'} \left[A(g, g', i-1+s, j-1+t) - kB(g, g', i-1+s, j-1+t) \right] \cdot$$

$$\left. P(i_1, 5-2s) P(j_1, 5-2t) \phi(g', 2i-4+2s+i_1, 2j-4+2t+j_1) \right\} = 0 \quad (8)$$

As stated before, these equations are for the non-symmetrical slab case. To modify these basic equations for R-Z geometry, one must define five other sets of matrices similar to the P's and Q's of the above equations.

Let PR, QR, RAV, PRR, and QRR be defined as:

$$PR(i_1, i_2) = \begin{pmatrix} -\frac{3}{2} & -1 & 0 \\ -1 & 0 & 1 \\ 0 & 1 & \frac{3}{2} \end{pmatrix}, \quad QR(i_1, i_2) = 10 \begin{pmatrix} -2 & 2 & 0 \\ 2 & 0 & -2 \\ 0 & -2 & 2 \end{pmatrix}$$

$$RAV(1) = DY(1)/2 \quad \text{for } j = 1$$

$$j = 2 \text{ to } NY$$

$$RAV(j) = RAV(j-1) + \left[\frac{DY(j) + DY(j-1)}{2} \right]$$

Now with the above definitions PRR and QRR are defined as

$$PRR(i_1, i_2, j) = RAV(j)P(i_1, i_2) + DY(j)PR(i_1, i_2)$$

$$QRR(i_1, i_2, j) = RAV(j)Q(i_1, i_2) + DY(j)QR(i_1, i_2)$$

These PR's and QR's are a simple convenience and are derived in a similar manner as the P's and Q's.[†]

[†]See Appendix B.

The PRR's and the QRR's are required because of the r factor in the dV in equation (A5) of Appendix A.

In X-Y geometry the dV is just $dx dy$, but in R-Z geometry the dV is $r dr dz$. Now if we let X equal Z and Y equal R in equations (5, 6, 7, and 8) with the proper coefficient changes, we get four sets of equations for R-Z geometry. They are:

1. Middle Point Equations for R-Z Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX$$

$$j = 1 \text{ to } NY$$

$$\sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i, j) \left[\frac{DX(i)}{DY(j)} P(i_1, 2) QRR(j_1, 2, j) + \frac{DY(j)}{DX(i)} Q(i_1, 2) PRR(j_1, 2, j) \right] \cdot \right. \\
 \left. \phi(g, 2i-2+i_1, 2j-2+j_1) + DX(i) DY(j) \sum_{g'} \left[A(g, g', i, j) \right. \right. \\
 \left. \left. - kB(g, g', i, j) \right] P(i_1, 2) PRR(j_1, 2, j) \phi(g', 2i-2+i_1, 2j-2+j_1) \right\} = 0 \quad (9)$$

2. Left-Edge Point Equations for R-Z Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX-1$$

$$j = 1 \text{ to } NY$$

$$\begin{aligned}
 & \sum_{s=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i-1+s, j) \left[\frac{DX(i-1+s)}{DY(j)} P(i_1, 5-2s) QRR(j_1, 2, j) \right. \right. \\
 & \quad \left. \left. + \frac{DY(j)}{DX(i-1+s)} Q(i_1, 5-2s) PRR(j_1, 2, j) \right] \cdot \phi(g, 2i-4+2s+i_1, 2j-2+j_1) \right. \\
 & \quad \left. + DX(i-1+s) DY(j) \sum_{g'} \left[A(g, g', i-1+s, j) - kB(g, g', i-1+s, j) \right] \right. \\
 & \quad \left. P(i_1, 5-2s) PRR(j_1, 2, j) \phi(g', 2i-4+2s+i_1, 2j-2+j_1) \right\} = 0 \quad (10)
 \end{aligned}$$

3. Top-Edge Point Equations for R-Z Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX$$

$$j = 1 \text{ to } NY-1$$

$$\begin{aligned}
 & \sum_{t=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i, j-1+t) \left[\frac{DX(i)}{DY(j-1+t)} P(i_1, 2) QRR(j_1, 5-2t, j-1+t) \right. \right. \\
 & \quad \left. \left. + \frac{DY(j-1+t)}{DX(i)} Q(i_1, 2) PRR(j_1, 5-2t, j-1+t) \right] \cdot \phi(g, 2i-2+i_1, 2j-4+2t+j_1) \right. \\
 & \quad \left. + DX(i)DY(j-1+t) \sum_{g'} \left[A(g, g', i, j-1+t) - kB(g, g', i, j-1+t) \right] \right. \\
 & \quad \left. P(i_1, 2) PRR(j_1, 5-2t, j-1+t) \phi(g', 2i-2+i_1, 2j-4+2t+j_1) \right\} = 0 \quad (11)
 \end{aligned}$$

4. Corner Point Equations for R-Z Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX-1$$

$$j = 1 \text{ to } NY-1$$

$$\sum_{s=1}^2 \sum_{t=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i-1+s, j-1+t) \left[\frac{DX(i-1+s)}{DY(j-1+t)} P(i_1, 5-2s) \right. \right.$$

$$\left. \left. QRR(j_1, 5-2t, j-1+t) + \frac{DY(j-1+t)}{DX(i-1+s)} Q(i_1, 5-2s) \right. \right.$$

$$\left. \left. PRR(j_1, 5-2t, j-1+t) \right] \cdot \phi(g, 2i-4+2s+i_1, 2j-4+2t+j_1) \right.$$

$$+ DX(i-1+s)DY(j-1+t) \sum_{g'} \left[A(g, g', i-1+s, j-1+t) \right.$$

$$\left. \left. - kB(g, g', i-1+s, j-1+t) \right] P(i_1, 5-2s) PRR(j_1, 5-2t, j-1+t) \right.$$

$$\left. \left. \cdot \phi(g', 2i-4+2s+i_1, 2j-4+2t+j_1) \right\} = 0 \quad (12)$$

These equations have symmetry, about the Z axis, built into the PRR and QRR coefficients. Just as the X-Y equations were modified to get the R-Z equations, we can modify these new equations (R-Z) to get equations for the R- Θ geometries.

Now if we let X equal Θ and Y equal R in equations (9, 10, 11 and 12) and define some new coefficients, we will have the difference equations for the R- Θ geometry.

Let α and PRT(i_1, i_2, j) be defined as:

$$\alpha = \frac{RAV(j)}{\Delta R} = \frac{RAV(j)}{DY(j)}$$

$$PRT(i_1, i_2, 1) = \frac{5}{DY(1)} F(i_1, i_2) \quad \text{for } j = 1$$

and for $j > 1$

$$\begin{aligned}
 PRT(i_1, i_2, j) = \frac{10}{DY(j)} & \left\{ \left[12A(i_1, i_2)\alpha^3 + 12B(i_1, i_2)\alpha^2 + 2C(i_1, i_2)\alpha + D(i_1, i_2) \right] \right. \\
 & \left[\alpha \ln\left(\frac{2\alpha+1}{2\alpha-1}\right) - 1 \right] + \left[E(i_1, i_2) - B(i_1, i_2)\alpha - A(i_1, i_2)\alpha^2 \right] \\
 & \left. \ln\left(\frac{2\alpha+1}{2\alpha-1}\right) \right\}
 \end{aligned}$$

where $A(i_1, i_2)$ through $F(i_1, i_2)$ have the following definitions.

$$A(i_1, i_2) = \begin{pmatrix} 1 & -2 & 1 \\ -2 & 4 & -2 \\ 1 & -2 & 1 \end{pmatrix} \quad B(i_1, i_2) = \begin{pmatrix} 1 & -1 & 0 \\ -1 & 0 & 1 \\ 0 & 1 & -1 \end{pmatrix} \quad C(i_1, i_2) = \begin{pmatrix} 2 & 2 & -1 \\ 2 & -10 & 2 \\ -1 & 2 & 2 \end{pmatrix}$$

$$D(i_1, i_2) = \begin{pmatrix} 1 & 2 & 0 \\ 2 & 0 & -2 \\ 0 & -2 & -1 \end{pmatrix} \quad E(i_1, i_2) = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 3 & 0 \\ 0 & 0 & 0 \end{pmatrix} \quad F(i_1, i_2) = \begin{pmatrix} 0 & 0 & 0 \\ 0 & 8 & 0 \\ 0 & 0 & 1 \end{pmatrix}$$

The R- θ Geometry Equations are:

1. Middle Point Equations for R- θ Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX$$

$$j = 1 \text{ to } NY$$

$$\begin{aligned}
 & \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i, j) \left[\frac{DX(i)}{DY(j)} P(i_1, 2) QRR(j_1, 2, j) + \frac{DY(j)}{DX(i)} Q(i_1, 2) PRT(j_1, 2, j) \right] \cdot \right. \\
 & \quad \phi(g, 2i-2+i_1, 2j-2+j_1) + DX(i)DY(j) \sum_{g'} \left[A(g, g', i, j) - kB(g, g', i, j) \right] \cdot \\
 & \quad \left. P(i_1, 2) PRR(j_1, 2, j) \phi(g', 2i-2+i_1, 2j-2+j_1) \right\} = 0 \quad (13)
 \end{aligned}$$

2. Left-Edge Point Equations of R- θ Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX-1$$

$$j = 1 \text{ to } NY$$

$$\begin{aligned}
 & \sum_{s=1}^2 \sum_{i_1=1}^3 \sum_{j=1} \left\{ D(g, i-1+s, j) \left[\frac{DX(i-1+s)}{DY(j)} P(i_1, 5-2s) QRR(j_1, 2, j) \right. \right. \\
 & \quad \left. \left. + \frac{DY(j)}{DX(i-1+s)} Q(i_1, 5-2s) PRT(j_1, 2, j) \right] \phi(g, 2i-4+2s+i_1, 2j-2+j_1) \right. \\
 & \quad \left. + DX(i-1+s) DY(j) \sum_{g'} \left[A(g, g', i-1+s, j) - kB(g, g', i-1+s, j) \right] \right. \\
 & \quad \left. P(i_1, 5-2s) PRR(j_1, 2, j) \phi(g', 2i-4+2s+i_1, 2j-2+j_1) \right\} = 0 \quad (14)
 \end{aligned}$$

3. Top-Edge Point Equations for R- θ Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX$$

$$j = 1 \text{ to } NY-1$$

$$\begin{aligned}
 & \sum_{t=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i, j-1+t) \left[\frac{DX(i)}{DY(j-1+t)} P(i_1, 2) QRR(j_1, 5-2t, j-1+t) \right. \right. \\
 & \quad \left. \left. + \frac{DY(j-1+t)}{DX(i)} Q(i_1, 2) PRT(j_1, 5-2t, j-1+t) \right] \phi(g, 2i-2+i_1, 2j-4+2t+j_1) \right. \\
 & \quad \left. + DX(i)DY(j-1+t) \sum_{g'} \left[A(g, g', i, j-1+t) - kB(g, g', i, j-1+t) \right] \right. \\
 & \quad \left. P(i_1, 2) PRR(j_1, 5-2t, j-1+t) \phi(g', 2i-2+i_1, 2j-4+2t+j_1) \right\} = 0 \quad (15)
 \end{aligned}$$

4. Corner Point Equations for R- θ Geometry

$$g = 1 \text{ to } G$$

$$i = 1 \text{ to } NX-1$$

$$j = 1 \text{ to } NY-1$$

$$\begin{aligned}
 & \sum_{s=1}^2 \sum_{t=1}^2 \sum_{i_1=1}^3 \sum_{j_1=1}^3 \left\{ D(g, i-1+s, j-1+t) \left[\frac{DX(i-1+s)}{DY(j-1+t)} P(i_1, 5-2s) \right. \right. \\
 & \quad \left. \left. QRR(j_1, 5-2t, j-1+t) + \frac{DY(j-1+t)}{DX(i-1+s)} Q(i_1, 5-2s) \right. \right. \\
 & \quad \left. \left. PRT(j_1, 5-2t, j-1+t) \right] \cdot \phi(g, 2i-4+2s+i_1, 2j-4+2t+j_1) \right. \\
 & \quad \left. + DX(i-1+s)DY(j-1+t) \sum_{g'} \left[A(g, g', i-1+s, j-1+t) \right. \right. \\
 & \quad \left. \left. - kB(g, g', i-1+s, j-1+t) \right] P(i_1, 5-2s) PRR(j_1, 5-2t, j-1+t) \cdot \right. \\
 & \quad \left. \phi(g', 2i-4+2s+i_1, 2j-4+2t+j_1) \right\} = 0 \quad (16)
 \end{aligned}$$

5. Center Point Equation (r=0) for R- θ Geometry

$g = 1 \text{ to } G$

$$\begin{aligned}
 \sum_{i=1}^{NX} \left\{ D(g,i,1) \frac{DX(i)}{DY(1)} \right. & \left[30QRR(1,1,1)\phi(g,1,1) + QRR(1,2,1) \left\{ 5\phi(g,1,2) \right. \right. \\
 & + 20\phi(g,2,2) + 5\phi(g,3,2) \left. \right\} + QRR(1,3,1) \left\{ 5\phi(g,1,2) \right. \\
 & + 20\phi(g,2,3) + 5\phi(g,3,3) \left. \right\} \left. \right] + DX(i)DY(1) \sum_{g'} \left[A(g,g',i,1) \right. \\
 & - k_B(g,g',i,1) \left. \right] \left[30PRR(1,1,1)\phi(g',1,1) + PRR(1,2,1) \cdot \right. \\
 & \left. \left\{ 5\phi(g',1,2) + 20\phi(g',2,2) + 5\phi(g',3,2) \right\} + PRR(1,3,1) \cdot \right. \\
 & \left. \left\{ 5\phi(g',1,3) + 20\phi(g',2,3) + 5\phi(g',3,3) \right\} \right] \left. \right\} = 0 \quad (17)
 \end{aligned}$$

The computer code (VARI-QUIR III) solves these difference equations for X-Y and R-Z geometries. Work will be started in the near future to incorporate the R- Θ geometry into VARI-QUIR III.

E. Typical Problem¹

The difference equations presented in Section D are solved in the computer code by a combination of "inner" and "outer" iterations. The inner iterations, keeping the fission "source" constant, use Seidel's method and converge quite rapidly because of the diagonal dominance of the space matrix*. At each outer iteration, the eigenvalue is re-computed from its stationary form (equation 4).

For our problem we chose a cylindrical reflected reactor, homogeneous in the Z-direction, and with five radial regions: core, reflector, reflector, absorbing ring, and more reflector. We used four energy groups.

Because the core was rather large to the other regions, we broke it into two regions. Two problems were run, the ring present and absent. Results with the ring in are shown in Figures 1-4. The accuracy of our method is demonstrated here against the CURE² code. The CURE output is plotted as a full line and the VARI-QUIR solution at crucial points marked on with crosses. The fit is quite good, except for being low in the center of the core in Group 4. Suspecting this might be due to core size, we added still another core region and got the excellent results marked as circles. Each of our sets of results were obtained in slightly over two minutes, as compared to about 16 to 20 for CURE.

*See equations B1 and B2 of Appendix B.

FIVE-RADIAL-REGION FOUR-GROUP STEADY-STATE PROBLEM
(Figures 1-4)

FIGURE 1 GROUP 1 FLUX

FIVE-RADIAL-REGION FOUR-GROUP STEADY-STATE PROBLEM
(Figures 1-4)

FIGURE 2 GROUP 2 FLUX

FIVE-RADIAL-REGION FOUR-GROUP STEADY-STATE PROBLEM
(Figures 1-4)

FIGURE 3 GROUP 3 FLUX

FIVE-RADIAL-REGION FOUR-GROUP STEADY-STATE PROBLEM
(Figures 1-4)

FIGURE 4 GROUP 4 FLUX

F. Further Plans

1. Incorporate the R- Θ equations into the VARI-QUIR III Code to handle R- Θ geometries.
2. Replace the diffusion-coefficient, column matrix by a square matrix, i.e.,
$$\text{Change } D(g,X,Y) \longrightarrow D(g,g^i,X,Y)$$
3. Change VARI-QUIR III from the FORTRAN II to the FORTRAN IV language to allow greater exchange of X-region, Y-region, materials, etc. This would permit the exchange of any one parameter (in number) for any other.

II. DESCRIPTION OF CODE

A. Present Limitations

Geometry - XY or RZ

Boundary conditions - $\phi = 0$ or $\nabla_n \phi = 0$

Energy groups - 18 or less

Regions - 36 or less

Regions in either direction - 10 or less

Different material regions - 23 or less

Starting options - (1) Fluxes and adjoints computed from scratch.

(2) Flux guess is read into the program, but
the adjoint guess is computed from scratch.

(3) Flux and adjoint guesses are both read
into the program.

(4) The fluxes and adjoints from the previous
problem are used as guesses.

Successive problems - any number may be stacked.

B. Input Preparation

Card No. 1:

This card may contain any alphanumerical information that will adequately describe the problem. It is printed at the beginning of the output, following the problem number.

Card No. 2:

This card provides information which defines the problem in terms of overall structure.

Punch in cols. 1-4	NPROB	Problem number
7-8	NG	Number of groups
11-12	NM	Number of materials
15-16	NX	Number of X or Z regions
19-20	NY	Number of Y or R regions
23-24	NGEOM	Geometry specifications
		NGEOM = -2 XY double symmetry
		= -1 XY single symmetry
		= 0 XY no symmetry
		= 1 RZ single symmetry
		= 2 RZ double symmetry
27-28	NGES	Initial flux option
		NGES = -1 fluxes and adjoints are computed from scratch
		= 0 flux guess is read into the program, but the adjoint guess is computed from scratch
		= 1 flux and adjoint guesses are both read into the program
		= 2 the fluxes and adjoints from the previous problem are used as guesses.
32	INTPX	This is the number of interpolated points given in the printout in addition to the three points per region in the X or Z direction, e.g. if INTPX is 1 the program will print out five points per region in the X or Z direction. One interpolated point between each regular point. No. of points per region = 2*INTPX+3

36	INTPY	The same as above only in the Y or R direction
39-40	NPCH	Flux and adjoint punch option NPCH < 0 The program will not punch the fluxes and adjoints out at the end of the problem. ≥ 0 The program will punch the fluxes and adjoints out at the end of the problem. This option is available so that one may restart a problem that is only partially converged.
42-44	ITOUT	Number of outer iterations on the flux computations
46-48	ITINN	Number of inner iterations on the flux computation
52-52	ITPRNT	Number of outer iterations between flux and adjoint printouts
56	ISSW	Sense switch option ISSW = 0 Since switches 1,2, and 3 are not available for action during the problem run. The program will run until the number of outer iteration is equal to ITOUT. = 1 Sense switches 1,2, and 3 are available and the eigenvalue will be printed out on-line after each outer iteration. Sense switch (1) permits one to terminate a problem at any time during a run. Sense switch (2) permits one to increase the relaxation constant by DRELAX during a run. Sense switch (3) permits one to decrease the relaxation constant by DRELAX. In the use of the three sense switches the above action will take place if the respective sense switch is put down. If sense (1) is activated, to take a problem off, one must, after tape A4 moves, put sense switch (1) up again or it will take the 2nd, 3rd, stacked problem off the computer, too.

Card No. 3:

Punch in cols. 1-10 RELAX is the successive overrelaxation constant. If RELAX is read in as 1, the method of solution reduces to successive iteration method or Seidel's method.

11-20 DRELAX is the amount one may increase or decrease RELAX with sense switches (2) and (3) respectively. Experience has shown that for large problems a value of 1.10 for RELAX and a value of 0.05 for DRELAX works well. As convergence came about, it has proved advisable to decrease RELAX to 1.0.

Card Group No. 4:

The X or Z length of each region using successive 10-column fields. Starting from the left (where $X = 0$).

Card Group No. 5:

The Y or R length of each region using successive 10-column fields. Starting from the bottom (where $Y = 0$).

Card Group No. 6:

These cards list the material number for each region, using one Y-row per card and as many cards as there are Y regions. On each card, the material numbers for the X regions, starting from the left, are listed in successive 4-column fields.

Sample Problem

X regions 3 NX = 3

Y regions 2 NY = 2 The two Y regions require 2 cards.

↑ Y	Material 1	Material 2	Material 4
	Material 2	Material 3	Material 1
	X →		

Card Input for Sample Problem

Card 6.1 M(1,1) = 2

 M(2,1) = 3

 M(3,1) = 1

Column	1	45	89	12
		2	3	1

Card 6.2 M(1,2) = 1

 M(2,2) = 2

 M(3,2) = 4

Column	1	45	89	12
		1	2	4

Card Group No. 7:

These cards contain the nuclear constants for each material.

SABS1(IG) is $\sum_a$ for group IG of material IM.
 SFIL(IG,IM) is $\sum_f$ for group IG of material IM.
 XNUL(IG) is γ for group IG of material IM.
 CHIL(IG,IM) is χ for group IG of material IM.
 DI(IG,IM) is D for group IG of material IM.
 STRI(IG,IGP) is $\sum^{TR}$ into group IG from group IGP of material IM.

These nuclear constants may be generated with a computer code, called GAM-TNS³, which punches them on cards with the proper format for VARI-QUIR III. If one chooses to have these nuclear constants punched by hand, they should see cards 141 to 161, of the first chain, of the FORTRAN listing (Appendix C).

Card Group No. 8: (omitted if NGES = -1 or 2)

The type and the amount of cards used here are dependent upon the value of NGES.

NGES = -1 omit this card group

- = 0 These cards should contain the flux guess that is to be read into the program, but not the adjoint guess.
- = 1 These cards should contain the flux and adjoint guesses. The flux cards first and the adjoint cards second. In all of the cards that are read in here (NGES=0 or 1) the FORMAT is (5E15.8). Every flux group and every adjoint group will start a new card.
- = 2 omit this card group.

References

1. Riese, J. W. and Collier, G., VARI-QUIR: A Two-Dimensional Time-Dependent Multi-Group Diffusion Code, WANL-TNR-133, September 1963.
2. Trantham, F. M. Jr., CURE: A Two-Space-Dimension, Multi-Group Code for the IBM-704, APEX-452, August 1958.
3. Joanou, G. D. and Dudik, J. S., GAM-I: A Consistent P_1 Multigroup Code for the Calculation of Fast Neutrons Spectra and Multigroup Constants, GA-1850.

Stevens, C. A. and Young, S., TNS, An IBM 7090 Program for Computing Thermal Neutron Spectra and Multithermal Group Cross Sections, WANL-TME-263, September 1962.

Appendix A. - Derivation of the ϕ_g^* Euler Equation

Equation (2) is our ϕ_g Euler equation. Restated this equation is

$$k = \frac{\sum_{g=1}^G \left[\nabla \cdot D_g \nabla \phi_g - \sum_{g'=1}^G A_{gg'} \phi_{g'} \right]}{\sum_{g=1}^G \sum_{g'=1}^G B_{gg'} \phi_{g'}} \quad (A2)$$

Now if we remove the g summation signs in the numerator and the denominator, and multiply each by ϕ_g^* we get:

$$k = \frac{-\phi_g^* \left[\nabla \cdot D_g \nabla \phi_g - \sum_{g'=1}^G A_{gg'} \phi_{g'} \right]}{\phi_g^* \sum_{g'=1}^G B_{gg'} \phi_{g'}} \quad (A3)$$

For simplicity, in equation (A3), it is convenient at this point to call the numerator U and the denominator V . Rewriting equation (A3) and taking a small variation in k , we get

$$\begin{aligned} k &= \frac{U}{V} \\ \delta k &= \delta \left(\frac{U}{V} \right) \\ &= \frac{1}{V} \left[\delta U - k \delta V \right] = 0 \end{aligned} \quad (A4)$$

We want to pick ϕ^* so that $\frac{\delta k}{\delta \phi_g} = 0$; because of this we will use the second factor in equation (A4) to define ϕ . Therefore

$$\delta U - k \delta V = 0$$

or

$$\delta \left\{ -\phi_g^* \left[\nabla \cdot D_g \nabla \phi_g - \sum_{g'=1}^G A_{gg'} \phi_{g'} \right] \right\} - k \delta \left\{ \phi_g^* \sum_{g'=1}^G B_{gg'} \phi_{g'} \right\} = 0$$

Remembering that we are taking a small variation with respect to ϕ_g ,

we get

$$-\phi_g^* \left\{ D_g \delta \nabla^2 \phi_g - \sum_{g'=1}^G A_{gg'} \delta \phi_{g'} \right\} - k \phi_g^* \sum_{g'=1}^G B_{gg'} \delta \phi_{g'} = 0$$

Now, if we replace the first term of the above equation by

$$-D_g \left\{ \nabla \cdot (\phi_g^* \delta \nabla \phi_g) - (\nabla \phi_g^*) \cdot (\delta \nabla \phi_g) \right\} \text{ and integrate over volume}$$

we get

$$\begin{aligned}
 & -D_g \left\{ \int_V \nabla \cdot (\phi_g^* \delta \nabla \phi_g) dV - \int_V (\nabla \phi_g^*) \cdot (\delta \nabla \phi_g) dV \right\} + \sum_{g'=1}^G A_{gg'} \cdot \\
 & \int_V \phi_{g'}^* \delta \phi_{g'} dV - k \sum_{g'=1}^G B_{gg'} \int_V \phi_g^* \delta \phi_{g'} dV = 0
 \end{aligned}$$

$$-Dg \left\{ \left[\phi_{g^*} \delta \nabla \phi_g \right]_0^V - \int^V \delta \nabla \phi_g \cdot \nabla \phi_{g^*} dV \right\} + \sum_{g'=1}^G A g g'.$$

$$\int^V \phi_{g^*} \delta \phi_g dV - k \sum_{g'=1}^G B g g' \int^V \phi_{g^*} \delta \phi_g dV = 0$$

$$\left[\phi_{g^*} \delta \nabla \phi_g \right]_0^V \text{ is zero because } \phi_{g^*} \text{ is zero at all boundaries.}$$

Here we make the assumption that

$\nabla \cdot \delta \phi_g = \delta \nabla \phi_g$ which is good for small variations in ϕ_g . Therefore if we factor out $\delta \phi_g$, we have

$$\delta \phi_g \left[\int^V \nabla \cdot Dg \nabla \phi_{g^*} dV + \sum_{g'=1}^G A g g' \int^V \phi_{g^*} dV - k \sum_{g'=1}^G B g g' \int^V \phi_{g^*} dV \right] = 0 \quad (A5)$$

Finally if we divide out $\delta\phi_g$ and rearrange this equation, we have

$$k = \frac{\sum_{g=1}^G - \left[\nabla \cdot Dg \nabla \phi_g^* - \sum_{g'=1}^G Ag'g \phi_{g'}^* \right]}{\sum_{g=1}^G \sum_{g'=1}^G Bg'g \phi_{g'}^*}$$

This is exactly the same form as equation (A2) except all the ϕ_g are replaced by ϕ_g^* , and all matrix elements are transposed.

Appendix B - A Practical Problem Using the Variational Principle

ϕ could be approximated in each region by a quadratic equation.

$$\phi = \begin{cases} \text{region 1} & \phi = a_1 + b_1x + c_1x^2 \\ \text{region 2} & \phi = a_2 + b_2x + c_2x^2 \\ \vdots & \vdots \\ \text{region N} & \phi = a_N + b_Nx + c_Nx^2 \end{cases}$$

But this would cause discontinuities at the edges of adjacent regions.

This problem can be eliminated by using three points to define the quadratic equation rather than using its coefficients. With this idea and a point structure as shown in sketch 1 the continuity problem is solved.

Sketch 1

For N region we will have $2N-1$ degrees of freedom ($2n-1$ equations).

The quadratic equation can be written as the sum of three other quadratic equations. e.g.

Sketch 2

$$\phi_1 = a_1 + b_1x + c_1x^2 \quad \phi_2 = a_2 + b_2x + c_2x^2 \quad \phi_3 = a_3 + b_3x + c_3x^3$$

$$\phi = \phi_1 + \phi_2 + \phi_3 = (a_1 + a_2 + a_3) + (b_1 + b_2 + b_3)x + (c_1 + c_2 + c_3)x^2$$

$$\phi = a + bx + cx^2$$

These quadratics are non-zero at only one of the three points that defines them. This makes the integrals in equation (3) easier to calculate.

In the integration of the integrals in the numerator (U) and the denominator (V) of equation (3) there are four types of overlap between the flux and the adjoint. They are shown in Sketch 3.

Sketch 3

If we break the numerator of equation (3) into two parts, say

$$U = U_1 + U_2 = (\nabla \phi_g^*) \cdot (\nabla \phi_g) + \phi_g^* \phi_g ,$$

and let the denominator be

$$V = \phi_g^* \phi_g \quad \text{we see that the integral of } U_2 \text{ will equal the integral of } V \text{ with proper coefficient adjustments.}$$

Now we have to evaluate all possible forms of overlap, between the fluxes and adjoints, in the numerator and the denominator. Since the second term in the numerator is the same as the denominator, we will only evaluate the integrals in the denominator.

The appropriate integrals that appear in equation (3) are:

$$V_{MM} = \int_0^L dx \left[4 \frac{X}{L} \left(1 - \frac{X}{L} \right) \right]^2 = \frac{16}{30} L$$

$$U_{MM} = \int_0^L dx \left[\frac{4}{L} \left(1 - \frac{2X}{L} \right) \right]^2 = \frac{16}{3L}$$

$$V_{ME} = \int_0^L dx \left[\frac{4X}{L} \left(1 - \frac{X}{L} \right) \right] \left[\frac{X}{L} \frac{2X}{L} - 1 \right] = \frac{2L}{30}$$

$$U_{ME} = \int_0^L dx \left[\frac{4}{L} \left(1 - \frac{2X}{L} \right) \right] \left[\frac{1}{L} \left(\frac{4X}{L} - 1 \right) \right] = - \frac{8}{3L}$$

$$V_{E_1 E_1} = \int_0^{L_1} dx \left[\frac{X}{L_1} \left(\frac{2X}{L_1} - 1 \right) \right]^2 + \int_0^{L_2} dx \left[\frac{X}{L_2} \left(\frac{2X}{L_2} - 1 \right) \right]^2 = \frac{4}{30} (L_1 + L_2)$$

$$U_{E_1 E_1} = \int_0^{L_1} dx \left[\frac{1}{L_1} \left(\frac{4X}{L_1} - 1 \right) \right]^2 + \int_0^{L_2} dx \left[\frac{1}{L_2} \left(\frac{4X}{L_2} - 1 \right) \right]^2 = \frac{7}{3} \left(\frac{1}{L_1} + \frac{1}{L_2} \right)$$

$$V_{E_1 E_2} = \int_0^L dx \left[\left(1 - \frac{X}{L}\right) \left(1 - \frac{2X}{L}\right) \right] \left[\frac{X}{L} \left(\frac{2X}{L} - 1\right) \right] = -\frac{L}{30}$$

$$U_{E_1 E_2} = \int_0^L dx \left[\frac{1}{L} \left(-3 + \frac{4X}{L}\right) \right] \left[\frac{1}{L} \left(\frac{4X}{L} - 1\right) \right] = \frac{1}{3L}$$

Using these results we may setup the following transformation scheme to obtain the flux and adjoint difference equations.

1. At a center point, say j

$$A \phi_j \longrightarrow \frac{A_{j/2}}{10} \cdot \left[\phi_{j-1} + 8 \phi_j + \phi_{j+1} \right] \quad (B1)$$

$$\nabla \cdot D \nabla \phi_j \longrightarrow \frac{4D_{j/2}}{L_{j/2}^2} \cdot \left[\phi_{j-1} - 2 \phi_j + \phi_{j+1} \right] \quad (B2)$$

2. At an edge point, say $j+1$

$$\begin{aligned}
 A \phi_{j+1} \longrightarrow & \frac{1}{5(L_{j/2} + L_{j/2+1})} \cdot \left[A_{j/2} L_{j/2} (-\phi_{j-1+2} \phi_{j+4} \phi_{j+1}) \right. \\
 & \left. + A_{j/2+1} L_{j/2+1} (4 \phi_{j+1+2} \phi_{j+2} - \phi_{j+3}) \right] \quad (B3)
 \end{aligned}$$

$$\begin{aligned}
 \nabla \cdot D \nabla \phi_{j+1} \longrightarrow & \frac{2}{(L_{j/2} + L_{j/2+1})} \cdot \left[\frac{D_{j/2}}{L_{j/2}} (-\phi_{j-1} + 8\phi_j - 7\phi_{j+1}) \right. \\
 & \left. + \frac{D_{j/2+1}}{L_{j/2+1}} (-7\phi_{j+1} + 8\phi_{j+2} - \phi_{j+3}) \right]
 \end{aligned} \tag{B4}$$

These transformations are made on both Euler equations referred to in Section B of Chapter I.

The use of these transformations will be demonstrated on equation (1) for the calculation of a middle point, e.g., point j of region i (see sketch below).

Sketch 4

The relationship between j and i is that $2i = j$.

$$\nabla \cdot D_g \nabla \phi_g - \sum_{g'=1}^G \left[A_{gg'} \phi_{g'} - k_{Bgg'} \phi_{g'} \right] = 0 \tag{1}$$

$$\frac{4D(g,i)}{L^2(i)} \left[\phi(g,j-1) - 2\phi(g,j) + \phi(g,j+1) \right] - \sum_{g'=1}^G \left[\frac{A(g,g',i)}{10} - \frac{kB(g,g',i)}{10} \right] \cdot$$

$$\left[\phi(g',j-1) + 8\phi(g',j) + \phi(g',j+1) \right] = 0$$

Changing all j's to 2i and multiplying both sides by the factor 10.L(i), we get:

$$\frac{40D(g,i)}{L(i)} \left[\phi(g,2i-1) - 2\phi(g,2i) + \phi(g,2i+1) \right] - L(i) \sum_{g'=1}^G \left[A(g,g',i) - kB(g,g',i) \right] \cdot$$

$$\left[\phi(g',2i-1) + 8\phi(g',2i) + \phi(g',2i+1) \right] = 0$$

Multiply both sides by -2 to get

$$\frac{D(g,i)}{L(i)} \left[-8\phi(g,2i-1) + 16\phi(g,2i) - 2\phi(g,2i+1) \right] + L(i) \sum_{g'=1}^G \left[A(g,g',i) - kB(g,g',i) \right] \cdot$$

$$\left[2\phi(g',2i-1) + 16\phi(g',2i) + 2\phi(g',2i+1) \right] = 0$$

This equation and the other difference equation (e.g. edge point $j+1$) can be put in a more compact form by the use of the following definitions.

$$P(i_1, i_2) = \begin{pmatrix} 4 & 2 & -1 \\ 2 & 16 & 2 \\ -1 & 2 & 4 \end{pmatrix} \quad Q(i_1, i_2) = 10 \cdot \begin{pmatrix} 7 & -8 & 1 \\ -8 & 16 & -8 \\ 1 & -8 & 7 \end{pmatrix}$$

Finally the difference equations for all regions from 1 to N become

$g = 1 \text{ to } G$

$i = 1 \text{ to } N$

$$\sum_{i_1=1}^3 \left\{ \frac{D(g, i)}{L(i)} Q(i_1, 2) \cdot \phi(g, 2i-2+i_1) + L(i) \sum_{g'=1}^G \left[A(g, g', i) - kB(g, g', i) \right] \right. \\ \left. \left[P(i_1, 2) \cdot \phi(g', 2i-2+i_1) \right] \right\} = 0$$

The adjoint equations for middle points are exactly the same except all the ϕ 's are replaced by ϕ^* 's and the A and B matrices have transposed elements.

The edge point equations are recorded here without derivation, and again the adjoint equations are the same except for the above exceptions.

$g = 1 \text{ to } G$

$i = 1 \text{ to } N-1$

$$\sum_{s=1}^2 \sum_{i_1=1}^3 \left\{ \frac{D(g, i-1+s)}{L(i-1+s)} Q(i_1, 5-2s) \cdot \phi(g, 2i-4+2s+i_1) + L(i-1+s) \sum_{g'=1}^G \cdot \right.$$

$$\left. \left[A(g, g', i-1+s) - kB(g, g', i-1+s) \right] \left[P(i_1, 5-2s) \phi(g', 2i-4+2s+i_1) \right] \right\} = 0$$

These four groups of equations (flux and adjoint equations) are of the type that a one-dimensional VARI-QUIR code would have to solve.

Appendix C - FORTRAN Listing

```

      CHAI (1,4)
      LIST
      TWO-DIM. VARI-QUIR STEADY STATE CHAIN ONE
      DIMENSION P(3,3),C(3,3),PR(3,3),QR(3,3),M(10,10),DX(10),DY(10)
      1,PR(3,3,10),QR(3,3,10),STR1(18,23),SAPS1(18),SFI1(18,23)
      2,CHI1(18,23),XNL1(18),D1(18,23),A1(18,18,23),Y(3042),YD(3042)
      3,R(18,23),W1(5000),W2(426)

      EQUIVALENCE (A1,W1),(W2(13),B)

      COMMON A1,W2,NG,NV,NX,NY,NX2,NY2,NPX,NPY,NP,NPCH,INTPX,INTPY,ISSW
      1,NGEOM,I1,ITINN,ITOUT,ITPRNT,LINK,NCOL,NROW,IL,NPXJ,NPYJ,NPJ,N
      2,P,Q,PR,QR,PRR,QRR,M,DX,DY,SFI1,CHI1,D1,Y,YD,RELAX,DRELAX

      IF(LINK-139)G1,26,31
      31 TIME = CLOCKF(CAPE,CHGE)
      DO 1 I = 1,3
      DO 1 J=1,3
      S=32.28*(I-2)**2*(J-2)**2/5*(I-2)*(J-2)+27*(I-2)**2*(J-2)**2
      P(I,J)=S/2.0
      Q(I,J)=(1-24*(I-2)**2*(J-2)**2+(I-2)*(J-2)*(3+36*(I-2)*(J-2)))*
      110
      SR=(4.71-21*(J-2)*(I+J-4))
      PR(1,J)=SR/4.0
      1 QR(I,J)=(3*(I-2)*(J-2)-2)*(I+J-4)*10
      239 READ INPUT TAPE 5,193,(W2(I),I=1,14)
      133 FORMAT(1346,A2)
      READ INPUT TAPE 5,100,NPROB,NG NM,NX,NY,NGEOM,NGES,INTPX,INTPY
      1,NPCH,ITOUT,ITINN,ITPRNT,ISSW
      100 FORMAT(20I4)
      READ INPUT TAPE 5,107,DRELAX,DRELAX
      NX2 = 2*NX
      NPX = NX2 +1
      NY2 = 2*NY
      NPY = NY2 +1
      NGP1= NG +1
      NPXJ = 3*NX
      NPYJ = 3*NY
      NPJ = NPXJ*NPYJ
      NP = NPX*NPY
      NNN=NG*NP+1
      NROW = 2*INTPY +3
      NCOL = 2*INTPX +3
      IL = NCOL*NX
      NCARD = CARD
      NREM = CHGE
      WRITE OUTPUT TAPE 6,101,NPROB,TIME,NCARD,NREM

```

```

      CH1 1
      CH1 2
      CH1 3
      CH1 4
      CH1 5
      CH1 6
      CH1 7
      CH1 8
      CH1 9
      CH1 10
      CH1 11
      CH1 12
      CH1 13
      CH1 14
      CH1 15
      CH1 16
      CH1 17
      CH1 18
      CH1 19
      CH1 20
      CH1 21
      CH1 22
      CH1 23
      CH1 24
      CH1 25
      CH1 26
      CH1 27
      CH1 28
      CH1 29
      CH1 30
      CH1 31
      CH1 32
      CH1 33
      CH1 34
      CH1 35
      CH1 36
      CH1 37
      CH1 38
      CH1 39
      CH1 40
      CH1 41
      CH1 42
      CH1 43
      CH1 44
      CH1 45
      CH1 46
      CH1 47

```

101	FORMAT(12H1PROBLEM NO I4,45X15HCOMPUTER TIME = -3PF6.3,5XI2,1H/I2,CH1	48
	13H,64)	CH1 49
	WRITE OUTPUT TAPE 5 192,(W2*I,I=1,14)	CH1 50
192	FORMAT(1H 13A,12//)	CH1 51
	WRITE OUTPUT TAPE 6 192,NG, NX,NY NM	CH1 52
102	FORMAT(6X74,RIUPS-I , 6X10HX REGIONS=I2,6X16HY,CH1	53
	1R RI REGIONS=I2,6X10H MATERIALS=I2//)	CH1 54
87	IF NCEOM 3,3,2	CH1 55
	2 WRITE OUTPUT TAPE 6,103	CH1 56
103	FORMAT(6X60HTHIS PROBLEM HAS CYLINDRICAL COORDINATES X,R GEOMETRYCH1	57
	1. /6X40HTHE SYMBOL Y REPRESENTS R THROUGHOUT.)	CH1 58
	6 IF NCE5 19,4,52	CH1 59
52	IF NCE5 1,4,5,53	CH1 60
53	WRITE OUTPUT TAPE 6,54	CH1 61
54	FORMAT(6X52HPRECEDING PROBLEM SUPPLIES FLUX AND ADJOINT GUESS.)CH1	62
	GO TO 7	CH1 63
199	WRITE OUTPUT TAPE 5 117	CH1 64
117	FORMAT(6X 45HFLUX AND ADJOINTS ARE COMPUTED FROM SCRATCH. , CH1	65
	GO TO 7	CH1 66
	4 WRITE OUTPUT TAPE 5 104	CH1 67
104	FORMAT(6X50HINPUT FLUX GUESS, ADJOINTS COMPUTED FROM SCRATCH.)CH1	68
	GO TO 7	CH1 69
	3 WRITE OUTPUT TAPE 6 105	CH1 70
105	FORMAT(6X60HTHIS PROBLEM HAS RECTANGULAR COORDINATES X,Y GEOMETRYCH1	71
	1. ,	CH1 72
	GO TO 6	CH1 73
	5 WRITE OUTPUT TAPE 6 106	CH1 74
106	FORMAT(6X 65HFLUX AND ADJOINT GUESSES ARE READ IN TO PROGRAM IN THCH1	75
	115 PROBLEM)	CH1 76
	7 READ INPUT TAPE 5 107, DX,IX, IX 1 NX	CH1 77
107	FORMAT(6E10 4/	CH1 78
	WRITE OUTPUT TAPE 5 123	CH1 79
123	FORMAT(1H ,	CH1 80
	WRITE OUTPUT TAPE 6,108,(IX DX,IX , IX-1,NX)	CH1 81
108	FORMAT(6X11HDELTA X NO.13,2H =1PE14 7	CH1 82
	READ INPUT TAPE 5 107,(DY,LY , LY-1 NY)	CH1 83
	IF NCEOM 8,3,9	CH1 84
	8 WRITE OUTPUT TAPE 6,123	CH1 85
	WRITE OUTPUT TAPE 6 109,(LY,DY,LY , LY-1,NY)	CH1 86
109	FORMAT(6X11HDELTA Y NO.13 2H =1PE14 7	CH1 87
	DO 88 IY=1,NY	CH1 88
	DO 88 I1=1,3	CH1 89
	DO 88 I2=1,3	CH1 90
	PRR(I1 I2 IY)=P(I1,I2)*DY(IY)	CH1 91
98	QRR(I1 I2 IY)=Q(I1,I2)/DY(IY)	CH1 92
	GO TO 101	CH1 93
	9 WRITE OUTPUT TAPE 6 123	CH1 94

WRITE OUTPUT TAPE 6,110,((IY,DY(IY)),IY=1,NY)	CH1 95
110 FORMAT(6X11HDELTA R NO.I3,2H =1PE14.7)	CH1 96
RAV= DY(1)/2.C	CH1 97
DO 11 I1=1,3	CH1 98
DO 11 I2=1,3	CH1 99
PRR(I1,I2,1)=RAV*DY(1)*P(I1,I2)+PR(I1,I2)*DY(1)**2	CH1 100
11 QRR(I1,I2,1)=RAV*Q(I1,I2)/DY(1)+QR(I1,I2)	CH1 101
IF(NY-1)1001,1001,12	CH1 102
12 DO 98 IY=2,NY	CH1 103
RAV= RAV + 0.5*(DY(IY)+DY(IY-1))	CH1 104
DO 98 I1=1,3	CH1 105
DO 98 I2=1,3	CH1 106
PRR(I1,I2,IY)=RAV*DY(IY)*P(I1,I2)+PR(I1,I2)*DY(IY)**2	CH1 107
98 QRR(I1,I2,IY)=RAV*Q(I1,I2)/DY(IY)+QR(I1,I2)	CH1 108
1001 DO 1002 I = 1,3	CH1 109
PR(I) = 0.0	CH1 110
1002 QR(I) = 0.0	CH1 111
IF(NGEOM)1003,10,1003	CH1 112
1003 DO 1004 I = 1,3	CH1 113
S = 44 - 50*I + 12*I**2	CH1 114
PR(I) = S*PRR(1,I,1)/3.0	CH1 115
1004 QR(I) = S*QRR(1,I,1)/3.0	CH1 116
PRR(2,2,1) = PRR(2,2,1) + 8.0*PRR(1,2,1)/3.0	CH1 117
PRR(2,3,1) = PRR(2,3,1) + (4.0*PRR(1,3,1) - PRR(1,2,1))/3.0	CH1 118
PRR(3,2,1) = PRR(2,3,1)	CH1 119
PRR(3,3,1) = PRR(3,3,1) - 2.0*PRR(1,3,1)/3.0	CH1 120
PRR(1,3,1) = -PRR(1,1,1)/3.0	CH1 121
PRR(1,2,1) = 4.0*PRR(1,1,1)/3.0	CH1 122
PRR(2,1,1) = PRR(1,2,1)	CH1 123
PRR(3,1,1) = PRR(1,3,1)	CH1 124
PRR(1,1,1) = -PRR(1,1,1)	CH1 125
QRR(2,2,1) = QRR(2,2,1) + 8.0*QRR(1,2,1)/3.0	CH1 126
QRR(2,3,1) = QRR(2,3,1) + (4.0*QRR(1,3,1) - QRR(1,2,1))/3.0	CH1 127
QRR(3,2,1) = QRR(2,3,1)	CH1 128
QRR(3,3,1) = QRR(3,3,1) - 2.0*QRR(1,3,1)/3.0	CH1 129
QRR(1,3,1) = -QRR(1,1,1)/3.0	CH1 130
QRR(1,2,1) = 4.0*QRR(1,1,1)/3.0	CH1 131
QRR(2,1,1) = QRR(1,2,1)	CH1 132
QRR(3,1,1) = QRR(1,3,1)	CH1 133
QRR(1,1,1) = -QRR(1,1,1)	CH1 134
10 WRITE OUTPUT TAPE 6, 123	CH1 135
DO 13 IY = 1, NY	CH1 136
READ INPUT TAPE 5,100,(M(IX,IY),IX=1,NX)	CH1 137
DO 13 IX=1,NX	CH1 138
13 WRITE OUTPUT TAPE 6,112,IX,IY,M(IX,IY)	CH1 139
112 FORMAT(6X15HMATERIAL NO. M(I2,1H,I2,3H) =I3)	CH1 140
DO 14 IM =1,NM	CH1 141

WRITE OUTPUT TAPE 6,2000,IM	CH1 142
2000 FORMAT(16H0 MATERIAL NO. I2 //)	CH1 143
DO 97 IG = 1,NG	CH1 144
97 READ INPUT TAPE 5,801,SABS1(IG),SF11(IG,IM),XNU1(IG),CHI1(IG,IM)	CH1 145
1,D1(IG,IM),(STR1(IG,IGP),IGP = 1,NG)	CH1 146
801 FORMAT(5E15.8)	CH1 147
DO 96 IG=1,NG	CH1 148
DO 64 IGP=1,NG	CH1 149
64 A1(IG,IGP,IM) = -STR1(IG,IGP)	CH1 150
A1(IG,IG,IM) = A1(IG,IG,IM) + SABS1(IG)	CH1 151
B(IG,IM) = XNU1(IG)*SF11(IG,IM)	CH1 152
WRITE OUTPUT TAPE 6,2001,IG,SABS1(IG),SF11(IG,IM),XNU1(IG)	CH1 153
1,CHI1(IG,IM),D1(IG,IM),IG,NG,(STR1(IG,IGP),IGP = 1,NG)	CH1 154
2001 FORMAT(16H0 GROUP NO. I2, // 14X 5HSIGA= 1PE14.7 ,	CH1 155
1 4X 5HSIGF= 1PE14.7 , 4X3HNU= 1PE14.7 , 4X4HCHI= 1PE14.7 ,	CH1 156
2 4X 2HD= 1PE14.7 , // 14X15HTRANSFERS INTO I2,	CH1 157
3 2X17HFROM 1, 2, ... , I2, 4H -- //(21X1PE14.7,1P3E20.7))	CH1 158
DO 96 IGP = 1,NG	CH1 159
96 A1(IG,IG,IM) = A1(IG,IG,IM) +STR1(IGP,IG)	CH1 160
14 CONTINUE	CH1 161
IF(NGES)17,15,55	CH1 162
55 IF(NGES-1)15,15,25	CH1 163
15 DO 16 IG=1,NG	CH1 164
K1= (IG-1)*NP +1	CH1 165
K2= IG*NP	CH1 166
16 READ INPUT TAPE 5,801,(Y(I),I=K1,K2)	CH1 167
IF(NGES)17,20,86	CH1 168
86 DO 85 IG = 1,NG	CH1 169
K1 = (IG-1)*NP +1	CH1 170
K2 = IG*NP	CH1 171
85 READ INPUT TAPE 5,801,(YD(I),I=K1,K2)	CH1 172
GO TO 25	CH1 173
17 DO 18 IX = 1,NX	CH1 174
DO 18 IY = 1,NY	CH1 175
IM = M(IX,IY)	CH1 176
DO 18 IG = 1,NG	CH1 177
I = (IG-1)*NP + (2*IY-1)*NPX +2*IX	CH1 178
DO 63 I1 = 1,3	CH1 179
DO 63 J1 = 1,3	CH1 180
INDX = I + (J1-2)*NPX +I1-2	CH1 181
63 Y(INDX) = CHI1(IG,IM)*SF11(NG,IM)	CH1 182
18 CONTINUE	CH1 183
20 DO 1005 IX =1,NX	CH1 184
DO 1005 IY =1,NY	CH1 185
IM = M(IX,IY)	CH1 186
DO 1005 IG = 1,NG	CH1 187
I = (IG-1)*NP + (2*IY-1)*NPX +2*IX	CH1 188

```

DO 50 I1 = 1,3
DO 50 J1 = 1,3
INDX = I + (J1-2)*NPX + I1-2
50 YD(INDX) = SF11(IG,IM)
1005 CONTINUE
25 DO 21 IG=1,NG
DO 22 IY=1,NPY
J = (IG-1)*NP + (IY-1)*NPX + 1
K = J + NPX-1
YD(J) = 0.0
YD(K) = 0.0
Y(J) = 0.0
22 Y(K) = 0.0
DO 21 IX=1,NPX
J = (IG-1)*NP + IX
K = IG*NP+1-IX
YD(J) = 0.0
YD(K) = 0.0
Y(J) = 0.0
21 Y(K) = 0.0
70 J = NGEOM**2
IF(J-1)56,72,24
24 DO 71 IG=1,NG
DO 71 IY=1,NPY
K = (IG-1)*NP + (IY-1)*NPX + 1
YD(K) = ( 4.0* YD(K+1) - YD(K+2) ) /3.0
71 Y(K)= (4.*Y(K+1)-Y(K+2))/3.0
72 DO 73 IG=1,NG
DO 73 IX=1,NPX
K=(IG-1)*NP + IX
K1=K+NPX
K2=K1+NPX
YD(K) = ( 4.0* YD(K1) - YD(K2) ) /3.0
73 Y(K)= (4.*Y(K1)-Y(K2))/3.0
56 WRITE OUTPUT TAPE 6,2002,ITOUT,ITINN,ITPRNT,ISSW,RELAX
2002 FORMAT( /// 7H0ITOUT=I3, 5X6HITINN=I3, 5X7HITPRNT=I2,
1 5X5HISSW=I2, 10X6HRELAX= 1PE14.7 ///)
200 TIME = CLOCKF(CARD,CHGE)
WRITE OUTPUT TAPE 6,804,TIME
804 FORMAT(77HOENTRY TO THE STEADY STATE CHAIN.
1 COMPUTER TIME = -3PF6.3 )
CALL CHAIN(2,4)
26 SUM=0.0
SUMD=0.0
DO 122 I=1,NX
DO 122 J=1,NY
IM=M(I,J)

```

```

CH1 189
CH1 190
CH1 191
CH1 192
CH1 193
CH1 194
CH1 195
CH1 196
CH1 197
CH1 198
CH1 199
CH1 200
CH1 201
CH1 202
CH1 203
CH1 204
CH1 205
CH1 206
CH1 207
CH1 208
CH1 209
CH1 210
CH1 211
CH1 212
CH1 213
CH1 214
CH1 215
CH1 216
CH1 217
CH1 218
CH1 219
CH1 220
CH1 221
CH1 222
CH1 223
CH1 224
CH1 225
CH1 226
CH1 227
CH1 228
CH1 229
CH1 230
CH1 231
CH1 232
CH1 233
CH1 234
CH1 235

```


DO 122 I1=1,3	CH1 236
DO 122 J1=1,3	CH1 237
SUM1=0.0	CH1 238
INDX=(3*J+J1-4)*NPXJ+3*I+I1-3	CH1 239
DO 129 IG=1,NG	CH1 240
INDX1=(IG-1)*NP+(2*J+J1-3)*NPX+2*I+I1-2	CH1 241
129 SUM1=SUM1+ SF11(IG,IM) * Y(INDX1)	CH1 242
B(INDX)=SUM1	CH1 243
IF(NGEOM)4997,4997,4998	CH1 244
4997 S = 0.0	CH1 245
GO TO 4999	CH1 246
4998 S = J1-2	CH1 247
4999 IF(J-1) 1101,1101,1100	CH1 248
1100 T = 0.0	CH1 249
GO TO 1102	CH1 250
1101 T = 1.0	CH1 251
1102 SR = P(I1,I1)*DX(I)*(PRR(J1,J1,J) + 0.5*S*DY(J)**2 + T*PR(J1))	CH1 252
SUM=SUM+SUM1*SR	CH1 253
122 SUMD=SUMD+SR	CH1 254
S=SUM/SUMD	CH1 255
WRITE OUTPUT TAPE 6,124,S	CH1 256
124 FORMAT(5X70HPOWER DENSITY,FLUX TIMES SIGMA FISSION (AVERAGE	CH1 257
1 POWER DENSITY = 1PE14.7,1H))	CH1 258
IG = 0	CH1 259
KRET = 1	CH1 260
SUM = INTPY + 1	CH1 261
SUM1 = INTPX + 1	CH1 262
5000 DO 5003 IY = 1,NY	CH1 263
INDX = 3*NPXJ*(IY-1)	CH1 264
DO 5003 I1 = 1,NROW	CH1 265
SUM2 = I1-INTPY-2	CH1 266
SUM2 = SUM2/SUM	CH1 267
DO 5002 IX = 1,NX	CH1 268
INDX4 = NCOL*(IX-1)	CH1 269
I = INDX4 - INTPX	CH1 270
DO 5001 I2 = 1,3	CH1 271
INDX1 = INDX + 3*(IX-1) + I2	CH1 272
INDX2 = INDX1 + NPXJ	CH1 273
INDX3 = INDX2 + NPXJ	CH1 274
J = I + I2*(INTPX+1)	CH1 275
5001 A1(J) = SUM2*(SUM2-1.)* B(INDX1)/2. + (1.-SUM2**2)* B(INDX2)	CH1 276
1 + SUM2*(SUM2+1.)* B(INDX3)/2.	CH1 277
INDX1 = INDX4 + 1	CH1 278
INDX2 = INDX1 + INTPX + 1	CH1 279
INDX3 = INDX2 + INTPX + 1	CH1 280
DO 5002 I2 = 2,NCOL	CH1 281
J = INDX4 + I2	CH1 282

SUM3 = 12 -INTPX -2	CH1 283
SUM3 = SUM3/SUM1	CH1 284
5002 A1(J) = SUM3*(SUM3-1.)*A1(INDX1)/2. + (1.0-SUM3**2)*A1(INDX2)	CH1 285
1 + SUM3*(SUM3+1.)*A1(INDX3)/2.	CH1 286
5003 WRITE OUTPUT TAPE 6,113,(A1(I2),I2=1,IL)	CH1 287
GO TO (5004,5008),KRET	CH1 288
5004 IG = IG + 1	CH1 289
IF(IG-NG)5005,5005,5007	CH1 290
5005 WRITE OUTPUT TAPE 6,120	CH1 291
120 FORMAT(1H)	CH1 292
WRITE OUTPUT TAPE 6,119,IG	CH1 293
119 FORMAT(5X14HFLUX GROUP NO.13)	CH1 294
113 FORMAT(1P5E20.7)	CH1 295
DO 5006 IX = 1,NX	CH1 296
DO 5006 IY = 1,NY	CH1 297
INDX = (IG-1)*NP + (2*IY-3)*NPX + 2*IX-2	CH1 298
INDX1 = (3*IY-4)*NPXJ + 3*IX-3	CH1 299
DO 5006 I1 = 1,3	CH1 300
DO 5006 I2 = 1,3	CH1 301
INDX2 = INDX + I2*NPX +I1	CH1 302
INDX3 = INDX1 + I2*NPXJ +I1	CH1 303
5006 B(INDX3) = Y(INDX2)	CH1 304
GO TO 5000	CH1 305
5007 IG = 0	CH1 306
KRET = 2	CH1 307
5008 IG = IG + 1	CH1 308
IF(IG-NG)5009,5009,91	CH1 309
5009 WRITE OUTPUT TAPE 6,120	CH1 310
WRITE OUTPUT TAPE 6,130,IG	CH1 311
130 FORMAT(5X17HADJOINT GROUP NO.13)	CH1 312
DO 51 IX = 1,NX	CH1 313
DO 51 IY = 1,NY	CH1 314
INDX = (IG-1)*NP + (2*IY-3)*NPX + 2*IX-2	CH1 315
INDX1 = (3*IY-4)*NPXJ + 3*IX-3	CH1 316
DO 51 I1 = 1,3	CH1 317
DO 51 I2 = 1,3	CH1 318
INDX2 = INDX + I2*NPX +I1	CH1 319
INDX3 = INDX1 + I2*NPXJ +I1	CH1 320
51 B(INDX3) = YD(INDX2)	CH1 321
GO TO 5000	CH1 322
END	CH1 323

* CHAIN(2,4)	CH2	1
* LIST	CH2	2
C TWO-DIM. VARI-QUIR STEADY STATE CHAIN TWO	CH2	3
DIMENS(DN P(3,3),Q(3,3),PR(3,3),QR(3,3),M(10,10),DX(10),DY(10)	CH2	4
1,PRR(3,3,10),QRR(3,3,10),SF11(18,23),CHI1(18,23),D1(18,23)	CH2	5
2,A1(18,18,23),Y(3042),YD(3042),YDS(3042),YS(3042),DEN(3042)	CH2	6
3,B(18,23),W1(5000),W2(426)	CH2	7
	CH2	8
EQUIVALENCE (A1,W1),(W2(13),B)	CH2	9
	CH2	10
COMMON A1,W2,NG,NM,NX,NY,NX2,NY2,NPX,NPY,NP,NPCH,INTPX,INTPY,ISSW	CH2	11
1,NGECM,E1,ITIAN,ITOUT,ITPRNT,LINK,NCOL,NROW,IL,NPXJ,NPYJ,NPJ,N	CH2	12
2,P,Q,PR,QR,PRR,QRR,M,DX,DY,SF11,CHI1,D1,Y,YC,RELAX,DRELAX	CH2	13
	CH2	14
LINK = 139	CH2	15
KNORM = 1	CH2	16
113 FORMAT(1P5E20,7)	CH2	17
119 FORMAT(5X14HFLUX GROUP NO.13)	CH2	18
120 FORMAT(1H)	CH2	19
200 NN= NG*NP	CH2	20
KTOLT = 0	CH2	21
KTPRNT = 0	CH2	22
GO TO 350	CH2	23
	CH2	24
EIGENVALUE CALCULATION	CH2	25
300 XUM1 = 0.0	CH2	26
XUM2 = 0.0	CH2	27
DEN1 = 0.0	CH2	28
DO 312 I = 1,NX	CH2	29
DO 311 J = 1,NY	CH2	30
IM = M(I,J)	CH2	31
DO 310 IG = 1,NG	CH2	32
INDX = (IG-1)*NP + (2*J-1)*NPX + 2*I	CH2	33
SUM = 0.0	CH2	34
DO 304 I1 = 1,3	CH2	35
DO 303 I2 = 1,3	CH2	36
DO 302 J1 = 1,3	CH2	37
DO 301 J2 = 1,3	CH2	38
INDX1 = INDX + (J1-2)*NPX + I1-2	CH2	39
INDX2 = INDX + (J2-2)*NPX + I2-2	CH2	40
301 SUM = SUM + YC(INDX1)*Y(INDX2)*(PRR(J1,J2,J)*Q(I1,I2)/DX(I)**2 +	CH2	41
1 P(I1,I2)*QRR(J1,J2,J))	CH2	42
302 CONTINUE	CH2	43
303 CONTINUE	CH2	44
304 CONTINUE	CH2	45
XUM2 = XUM2 + SUM*DX(I)*D1(IG,IM)	CH2	46
DO 309 NGP = 1,NG	CH2	47

INDX3 = INDX + (IGP-IG)*NP	CH2	48
SUM = 0.0	CH2	49
DO 308 I1 = 1,3	CH2	50
DO 307 I2 = 1,3	CH2	51
DO 306 J1 = 1,3	CH2	52
DO 305 J2 = 1,3	CH2	53
INDX1 = INDX + (J1-2)*NPX + I1-2	CH2	54
INDX2 = INDX3 + (J2-2)*NPX + I2-2	CH2	55
305 SUM = SUM + YD(INDX1)*Y(INDX2)*P(I1,I2)*PRR(J1,J2,J)	CH2	56
306 CONTINUE	CH2	57
307 CONTINUE	CH2	58
308 CONTINUE	CH2	59
XUM1 = XUM1 + SUM*DX(I)*A1(IG,IGP,IM)	CH2	60
309 DEN1 = DEN1 + SUM* CHI1(IG,IM)*B(IGP,IM)* DX(I)	CH2	61
310 CONTINUE	CH2	62
311 CONTINUE	CH2	63
312 CONTINUE	CH2	64
AMB = (XUM1 + XUM2)/DEN1	CH2	65
RAMB = 1.0/AMB	CH2	66
KTPRNT = KTPRNT +1	CH2	67
WRITE OUTPUT TAPE 6,601, RAMB	CH2	68
601 FORMAT(1H0 // 13HOEIGENVALUE = 1PE14.7)	CH2	69
IF(ITPRNT-KTPRNT)313,313,650	CH2	70
313 KTPRNT = 0	CH2	71
GO TO 202	CH2	72
C	CH2	73
C DENOMINATOR CALCULATION	CH2	74
350 DO 356 IG = 1,NG	CH2	75
DO 356 I = 1,NX	CH2	76
DO 356 J = 1,NY	CH2	77
INDX = (IG-1)*NP + (2*J-1)*NPX + 2*I	CH2	78
IM = M(I,J)	CH2	79
DEN(INDX) = 16.0*PRR(2,2,J)*A1(IG,IG,IM) + D1(IG,IM)*(16.0*QRR(2,2,J) + PRR(2,2,J)*Q(2,2)/DX(I)**2)	CH2	80
IF(NX-I)352,352,351	CH2	81
351 IM1 = M(I+1,J)	CH2	82
DEN(INDX+1) = PRR(2,2,J)*4.0*(A1(IG,IG,IM)*DX(I) + DX(I+1)*A1(IG,IG,IM1)) + QRR(2,2,J)*4.0*(D1(IG,IM)*DX(I)+DX(I+1)*D1(IG,IM1))+ 2*PRR(2,2,J)*(Q(3,3)*D1(IG,IM)/DX(I) + Q(1,1)*D1(IG,IM1)/DX(I+1))	CH2	83
352 IF(NY-J)355,355,353	CH2	84
353 IM2 = M(I,J+1)	CH2	85
INDX1 = INDX + NPX	CH2	86
DEN(INDX1) = 16.0*(PRR(3,3,J)*A1(IG,IG,IM)+PRR(1,1,J+1)*A1(IG,IG,IM2)) + 16.0*(QRR(3,3,J)*D1(IG,IM)+QRR(1,1,J+1)*D1(IG,IM2))+Q(2,2)*(PRR(3,3,J)*D1(IG,IM)+PRR(1,1,J+1)*D1(IG,IM2))/DX(I)**2	CH2	87
IF(NX-I)355,355,354	CH2	88
354 IM3 = M(I+1,J+1)	CH2	89
	CH2	90
	CH2	91
	CH2	92
	CH2	93
	CH2	94

```

DEN(INDX1+1)=PRR(3,3,J)*(A1(IG,IG,IM)*P(3,3)*DX(I)+A1(IG,IG,IM1)* CH2 95
1P(1,1)*DX(I+1))+4.0*PRR(1,1,J+1)*(A1(IG,IG,IM2)*DX(I) +A1(IG,IG,IMCH2 96
23)*CX(I+1))+4.0*QRR(3,3,J)*(D1(IG,IM)*DX(I)+D1(IG,IM1)*DX(I+1)) CH2 97
3+4.0*QRR(1,1,J+1)*(D1(IG,IM2)*DX(I)+D1(IG,IM3)*DX(I+1))+PRR(3,3,J)CH2 98
4*(Q(3,3)*D1(IG,IM)/DX(I)+Q(1,1)*D1(IG,IM1)/DX(I+1))+PRR(1,1,J+1)* CH2 99
5(Q(3,3)*D1(IG,IM2)/DX(I)+Q(1,1)*D1(IG,IM3)/DX(I+1)) CH2 100
355 CONTINUE CH2 101
356 CONTINUE CH2 102
GO TO 300 CH2 103
C SOURCE CALCULATION CH2 104
C CH2 105
400 SIZE =0.0 CH2 106
SIZED = 0.0 CH2 107
DO 415 IG = 1,NG CH2 108
DO 415 I = 1,NX CH2 109
DO 415 J = 1,NY CH2 110
INDX=(IG-1)*NP+(2*J-1)*NPX+2*I CH2 111
IM=M(I,J) CH2 112
SUM = 0.0 CH2 113
SUMD = 0.0 CH2 114
T1 = 0.0 CH2 115
T2 = 1.0 CH2 116
DO 402 IGP = 1,NG CH2 117
INDX1 = INDX + (IGP-IG)*NP CH2 118
IF(IG-IGP)416,417,418 CH2 119
417 T2 = 0.0 CH2 120
GO TO 418 CH2 121
416 T1 = 1.0 CH2 122
418 SUM1 = 0.0 CH2 123
SUM2 = 0.0 CH2 124
DO 401 I1 = 1,3 CH2 125
DO 401 J1 = 1,3 CH2 126
INDX2 = INDX1 + (J1-2)*NPX +I1-2 CH2 127
SUM1 = SUM1 +P(I1,2)*PRR(J1,2,J)*YD(INDX2) CH2 128
401 SUM2 = SUM2 +P(I1,2)*PRR(J1,2,J)*Y(INDX2) CH2 129
SUMD = SUMD +SUM1* ( CHI1(IGP,IM)*B(IG,IM) *AMB-A1(IGP,IG,IM)*T2) CH2 130
402 SUM = SUM +SUM2* ( CHI1(IG,IM)*B(IGP,IM) *AMB-A1(IG,IGP,IM)*T1) CH2 131
YDS(INDX) = SUMD CH2 132
YS(INDX) = SUM CH2 133
SIZE = SIZE + SUM*DX(I) CH2 134
SIZED = SIZED + SUMD*DX(I) CH2 135
IF(NX-I)406,406,403 CH2 136
403 INDX = INDX +I CH2 137
SUM = 0.0 CH2 138
SUMD = 0.0 CH2 139
DO 405 IS = 1,2 CH2 140
I2=5-2 CH2 141

```

```

II=I+IS-1
IM=M(II,J)
T1 = 0.0
T2 = 1.0
DO 405 IGP = 1,NG
INDX1 = INDX + (IGP-IG)*NP + 2*IS-3
IF(IG-IGP)419,420,421
420 T2 = 0.0
GO TO 421
419 T1 = 1.0
421 SUM1 = 0.0
SUM2 = 0.0
DO 404 I1 = 1,3
DO 404 J1 = 1,3
INDX2 = INDX1 + (J1-2)*NPX + I1-2
SUM1 = SUM1 + YD(INDX2)*PRR(J1,2,J)*P(I1,I2)
404 SUM2 = SUM2 + Y(INDX2)*PRR(J1,2,J)*P(I1,I2)
SUMD = SUMD + SUM1*DX(II)*(AMB
1 -T2*A1(IGP,IG,IM))
405 SUM = SUM + SUM2*DX(II)*(AMB
1 -T1*A1(IG,IGP,IM))
YDS(INDX) = SUMD
YS(INDX) = SUM
SIZE = SIZE + SUM
SIZED = SIZED + SUMD
406 IF(NY-J)414,414,407
407 INDX = (IG-1)*NP + 2*J*NPX + 2*I
SUM = 0.0
SUMD = 0.0
DO 409 JS = 1,2
J2=5-2*JS
JJ=J+JS-1
IM=M(I,JJ)
T1 = 0.0
T2 = 1.0
DO 409 IGP = 1,NG
INDX1 = INDX + (IGP-IG)*NP + (2*JS-3)*NPX
IF(IG-IGP)422,423,424
423 T2 = 0.0
GO TO 424
422 T1 = 1.0
424 SUM1 = 0.0
SUM2 = 0.0
DO 408 I1 = 1,3
DO 408 J1 = 1,3
INDX2 = INDX1 + (J1-2)*NPX + I1-2
SUM1 = SUM1 + YD(INDX2)*PRR(J1,J2,JJ)*P(I1,2)

```

```

CH2 142
CH2 143
CH2 144
CH2 145
CH2 146
CH2 147
CH2 148
CH2 149
CH2 150
CH2 151
CH2 152
CH2 153
CH2 154
CH2 155
CH2 156
CH2 157
CH2 158
CH2 159
CH2 160
CH2 161
CH2 162
CH2 163
CH2 164
CH2 165
CH2 166
CH2 167
CH2 168
CH2 169
CH2 170
CH2 171
CH2 172
CH2 173
CH2 174
CH2 175
CH2 176
CH2 177
CH2 178
CH2 179
CH2 180
CH2 181
CH2 182
CH2 183
CH2 184
CH2 185
CH2 186
CH2 187
CH2 188

```

408	SUM2 = SUM2 + Y(INDX2)*PRR(J1,J2,JJ)*P(I1,2)	CH2 189
	SUMD = SUMD + SUM1*(CHI1(IGP,IM) * B(IG,IM)*AMB-T2*A1(IGP,IG,IM))	CH2 190
409	SUM = SUM + SUM2*(CHI1(IG,IM) * B(IGP,IM) *AMB-T1*A1(IG,IGP,IM))	CH2 191
	YDS(INDX) = SUMD	CH2 192
	YS(INDX) = SUM	CH2 193
	SIZE = SIZE + SUM *DX(I)	CH2 194
	SIZED = SIZED + SUMD *DX(I)	CH2 195
	IF(NX-I)414,414,410	CH2 196
410	INDX = INDX +1	CH2 197
	SUM = 0.0	CH2 198
	SUMD = 0.0	CH2 199
	DO 413 IS = 1,2	CH2 200
	I2=5-2*IS	CH2 201
	II=I+IS-1	CH2 202
	DO 413 JS = 1,2	CH2 203
	J2=5-2*JS	CH2 204
	JJ= J+JS-1	CH2 205
	IM = M(II,JJ)	CH2 206
	T1 = 0.0	CH2 207
	T2 = 1.0	CH2 208
	DO 412 IGP = 1,NG	CH2 209
	INDX1 = INDX + (IGP-IG)*NP + (2*JS-3)*NPX + 2*IS-3	CH2 210
	IF(IG-IGP)425,426,427	CH2 211
426	T2 = 0.0	CH2 212
	GO TO 427	CH2 213
425	T1 = 1.0	CH2 214
427	SUM1 = 0.0	CH2 215
	SUM2 = 0.0	CH2 216
	DO 411 I1 = 1,3	CH2 217
	DO 411 J1 = 1,3	CH2 218
	INDX2 = INDX1 + (J1-2)*NPX + I1-2	CH2 219
	SUM1 = SUM1 + YD(INDX2)*PRR(J1,J2,JJ)*P(I1,I2)	CH2 220
411	SUM2 = SUM2 + Y(INDX2)*PRR(J1,J2,JJ)*P(I1,I2)	CH2 221
	SUMD = SUMD + SUM1*DX(II)*(AMB *CHI1(IGP,IM)*B(IG,IM)	CH2 222
	1 -T2*A1(IGP,IG,IM))	CH2 223
412	SUM = SUM + SUM2*DX(II)*(AMB *CHI1(IG,IM)*B(IGP,IM)	CH2 224
	1 -T1*A1(IG,IGP,IM))	CH2 225
413	CONTINUE	CH2 226
	YDS(INDX) = SUMD	CH2 227
	YS(INDX) = SUM	CH2 228
	SIZE = SIZE + SUM	CH2 229
	SIZED = SIZED + SUMD	CH2 230
414	CONTINUE	CH2 231
415	CONTINUE	CH2 232
	INNER ITERATION (THROUGH 522)	CH2 233
500	SUM = 0.0	CH2 234
	SUMS = 0.0	CH2 235

```

DO 1417 I = 1, NX
S = DX(I)
IF(I-1) 1401, 1401, 1402
1401 I21 = 2
GO TO 1403
1402 I21 = 1
1403 IF(I-NX) 1405, 1404, 1404
1404 I22 = 2
GO TO 1406
1405 I22 = 3
1406 DO 1419 J=1, NY
IM = M(I, J)
IF(J-1) 1407, 1407, 1408
1407 J21 = 2
GO TO 1409
1408 J21 = 1
1409 IF(J-NY) 1411, 1410, 1410
1410 J22 = 2
GO TO 1412
1411 J22 = 3
1412 DO 1415 I1=1, 3
SUM1 = 0.0
SUM2 = 0.0
DO 1413 J2 = I21, I22
SUM1 = SUM1 + P(I1, I2)
1413 SUM2 = SUM2 + Q(I1, I2)
W2(I1) = SUM1 * S
W2(I1+3) = SUM2 / S
SUM1 = 0.0
SUM2 = 0.0
DO 1414 J2 = J21, J22
SUM1 = SUM1 + PRR(I1, J2, J)
1414 SUM2 = SUM2 + CRR(I1, J2, J)
W2(I1+6) = SUM1
1415 W2(I1+9) = SUM2
DO 1418 IG = 1, NG
INDX = (IG-1)*NP + (2*J-1)*NPX + 2*I
JG = NG - IG + 1
SUMC = 0.0
XUMC = 0.0
DO 1416 IGP = IG, NG
JGP = NG - IGP + 1
XUMD = XUMD + A1(JG, JGP, IM)
1416 SUMC = SUMC + A1(IGP, IG, IM)
SUM1 = 0.0
SUM2 = 0.0
SUM3 = 0.0

```

```

CH2 236
CH2 237
CH2 238
CH2 239
CH2 240
CH2 241
CH2 242
CH2 243
CH2 244
CH2 245
CH2 246
CH2 247
CH2 248
CH2 249
CH2 250
CH2 251
CH2 252
CH2 253
CH2 254
CH2 255
CH2 256
CH2 257
CH2 258
CH2 259
CH2 260
CH2 261
CH2 262
CH2 263
CH2 264
CH2 265
CH2 266
CH2 267
CH2 268
CH2 269
CH2 270
CH2 271
CH2 272
CH2 273
CH2 274
CH2 275
CH2 276
CH2 277
CH2 278
CH2 279
CH2 280
CH2 281
CH2 282

```


SUM4 = 0.0	CH2 283
DO 1417 I1=1,3	CH2 284
DO 1417 J1=1,3	CH2 285
INDX1 = INDX + I1-2 + (J1-2)*NPX	CH2 286
INAX1 = INDX1 + (JG-IG)*NP	CH2 287
SUM3 = SUM3 + YD(INAX1)*W2(I1)*W2(J1+6)	CH2 288
SUM4 = SUM4 + YD(INAX1)*(W2(I1)*W2(J1+9)+W2(I1+3)*W2(J1+6))	CH2 289
SUM1 = SUM1 + Y(INDX1)*W2(I1)*W2(J1+6)	CH2 290
1417 SUM2 = SUM2 + Y(INDX1)*(W2(I1)*W2(J1+9) + W2(I1+3)*W2(J1+6))	CH2 291
SUM5 = SUM5 + SUM3*XUMD + D1(JG,IM)*SUM4	CH2 292
1418 SUM = SUM + SUM1*SUMD + D1(IG,IM)*SUM2	CH2 293
1419 CONTINUE	CH2 294
SUM1 = SIZE/SUM	CH2 295
SUM2 = SIZED/SUM5	CH2 296
J = NP*NG	CH2 297
DO 1420 I =1,J	CH2 298
Y(I) = Y(I)*SUM1	CH2 299
1420 YD(I) = YD(I)*SUM2	CH2 300
DO 525 IG=1,NG	CH2 301
JG = NG - IG +1	CH2 302
KTIAN = 0	CH2 303
524 DO 519 I=1,NX	CH2 304
DO 517 J=1,NY	CH2 305
INDX = (IG-1)*NP+(2*J-1)*NPX+2*I	CH2 306
INAX = INDX + (JG-IG)*NP	CH2 307
INAX = INAX + (JG-IG)*NP	CH2 308
SUMD=0.0	CH2 309
SUM = 0.0	CH2 310
DO 502 I1=1,3	CH2 311
DO 502 J1=1,3	CH2 312
INAX1=INDX+(J1-2)*NPX+I1-2	CH2 313
INAX1 = INDX1 + (JG-IG)*NP	CH2 314
SUM1 = (Q(I1,2)*PRR(J1,2,J)/DX(I)**2+P(I1,2)*QRR(J1,2,J))	CH2 315
SUMD=SUMD+SUM1*YD(INAX1) *D1(JG,IM)	CH2 316
SUM =SUM+SUM1*Y(INDX1) *D1(IG,IM)	CH2 317
SUMD=0.0	CH2 318
SUM = 0.0	CH2 319
DO 501 IGP=1,IG	CH2 320
JG = NG -IGP +1	CH2 321
INAX2=INDX1+(IGP-IG)*NP	CH2 322
INAX2 = INDX2 + (JGP-IGP)*NP	CH2 323
SUM1=SUM1+A1(JGP,JG,IM)*YD(INAX2)	CH2 324
501 SUMD=SUMD+A1(IG,IGP,IM)*Y(INDX2)	CH2 325
SUMD=SUMD+SUM1*P(I1,2)*PRR(J1,2,J)	CH2 326
502 SUM =SUM +SUM2*P(I1,2)*PRR(J1,2,J)	CH2 327
YD(INAX) = YD(INAX) + (YDS(INAX)-SUMD)*RELAX/DEN(INAX)	CH2 328
Y(INDX) = Y(INDX) + (YS(INDX)-SUM)*RELAX/DEN(INDX)	CH2 329

	IF(NX-1) 507,507,503	CH2 330
503	INDX=INDX+1	CH2 331
	INAX = INAX +1	CH2 332
	SUMD=0.0	CH2 333
	SUM =0.0	CH2 334
	DO 506 IS=1,2	CH2 335
	II=I+IS-1	CH2 336
	IM=M(II,J)	CH2 337
	I2=5-2*IS	CH2 338
	DO 505 I1=1,3	CH2 339
	DO 505 J1=1,3	CH2 340
	INDX1=INDX+(J1-2)*NPX+I1-I2	CH2 341
	INAX1 = INDX1 +(JG-IG)*NP	CH2 342
	SUM1= (Q(I1,I2)*PRR(J1,2,J)/DX(II)+P(I1,I2)*QRR(J1,2,J)*	CH2 343
	1 DX(II))	CH2 344
	SUMD=SUMD+SUM1*YD(INAX1) *D1(JG,IM)	CH2 345
	SUM =SUM +SUM1*Y (INDX1) *D1(IG,IM)	CH2 346
	SUM1=0.0	CH2 347
	SUM2=0.0	CH2 348
	DO 504 IGP=1,IG	CH2 349
	JGP = NG -IGP +1	CH2 350
	INDX2=INDX1+(IGP-IG)*NP	CH2 351
	INAX2 = INDX2 +(JGP-IGP)*NP	CH2 352
	SUM1=SUM1+A1(JGP,JG,IM)*YD(INAX2)	CH2 353
504	SUM2=SUM2+A1(IG,IGP,IM)*Y (INDX2)	CH2 354
	SUMD=SUMD+SUM1*P(I1,I2)*PRR(J1,2,J)*DX(II)	CH2 355
505	SUM =SUM +SUM2*P(I1,I2)*PRR(J1,2,J)*DX(II)	CH2 356
506	CONTINUE	CH2 357
	YD(INAX) = YD(INAX) + (YDS(INAX)-SUMD)*RELAX/DEN(INAX)	CH2 358
	Y(INDX) = Y(INDX) + (YS(INDX)-SUM)*RELAX/DEN(INDX)	CH2 359
507	IF(NY-J) 516,516,508	CH2 360
508	INDX=(IG-1)*NP+2*J*NPX+2*I	CH2 361
	INAX = INDX + (JG-IG)*NP	CH2 362
	SUMD=0.0	CH2 363
	SUM =0.0	CH2 364
	DO 511 JS=1,2	CH2 365
	JJ=J+JS-1	CH2 366
	IM=M(I,JJ)	CH2 367
	J2=5-2*JS	CH2 368
	DO 510 I1=1,3	CH2 369
	DO 510 J1=1,3	CH2 370
	INDX1=INDX+(J1-J2)*NPX+I1-2	CH2 371
	INAX1 = INDX1 +(JG-IG)*NP	CH2 372
	SUM1= (Q(I1,2)*PRR(J1,J2,JJ)/DX(I)**2+P(I1,2)*QRR(J1,J2,	CH2 373
	1 JJ))	CH2 374
	SUMD=SUMD+SUM1*YD(INAX1) *D1(JG,IM)	CH2 375
	SUM SUM +SUM1*Y (INDX1) *D1(IG,IM)	CH2 376

SUM1=0.0	CH2 377
SUM2=0.0	CH2 378
DO 509 IGP=1,IG	CH2 379
JGP = NG -IGP +1	CH2 380
INDX2=INDX1+(IGP-IG)*NP	CH2 381
INAX2 = INDX2 + (JGP-IGP)*NP	CH2 382
SUM1=SUM1+A1(JGP,JG,IM)*YD(INAX2)	CH2 383
509 SUM2=SUM2+A1(IG,IGP,IM)*Y (INDX2)	CH2 384
SUMD=SUMD+SUM1*P(I1,2)*PRR(J1,J2,JJ)	CH2 385
510 SUM =SUM +SUM2*P(I1,2)*PRR(J1,J2,JJ)	CH2 386
511 CONTINUE	CH2 387
YD(INAX) = YD(INAX) + (YDS(INAX)-SUMD)*RELAX/DEN(INAX)	CH2 388
Y(INDX) = Y(INDX) + (YS(INDX)-SUM)*RELAX/DEN(INDX)	CH2 389
IF(IX-1) 516,516,512	CH2 390
512 INDX=INDX+1	CH2 391
INAX = INAX +1	CH2 392
SUMD=0.0	CH2 393
SUM =0.0	CH2 394
DO 515 IS=1,2	CH2 395
I1=I+IS-1	CH2 396
I2=5-2*IS	CH2 397
DO 515 JS=1,2	CH2 398
JJ=J+JS-1	CH2 399
J2=5-2*JS	CH2 400
IM=M(I1,JJ)	CH2 401
DO 514 I1=1,3	CH2 402
DO 514 J1=1,3	CH2 403
INDX1=INDX+(J1-J2)*NPX+(I1-I2)	CH2 404
INAX1 = INDX1 + (JG-IG)*NP	CH2 405
SUM1= (Q(I1,I2)*PRR(J1,J2,JJ)/DX(I1)+P(I1,I2)*QRR(J1,J2,	CH2 406
1 JJ)*DX(I1))	CH2 407
SUMD=SUMD+SUM1*YD(INAX1) *D1(JG,IM)	CH2 408
SUM =SUM +SUM1*Y (INDX1) *D1(IG,IM)	CH2 409
SUM1=0.0	CH2 410
SUM2=0.0	CH2 411
DO 513 IGP=1,IG	CH2 412
JGP = NG +1 - IGP	CH2 413
INDX2=INDX1+(IGP-IG)*NP	CH2 414
INAX2 = INDX2 + (JGP-IGP)*NP	CH2 415
SUM1=SUM1+A1(JGP,JG,IM)*YD(INAX2)	CH2 416
513 SUM2=SUM2+A1(IG,IGP,IM)*Y (INDX2)	CH2 417
SUMD=SUMD+SUM1*P(I1,I2)*PRR(J1,J2,JJ)*DX(I1)	CH2 418
514 SUM =SUM +SUM2*P(I1,I2)*PRR(J1,J2,JJ)*DX(I1)	CH2 419
515 CONTINUE	CH2 420
YD(INAX) = YD(INAX) + (YDS(INAX)-SUMD)*RELAX/DEN(INAX)	CH2 421
Y(INDX) = Y(INDX) + (YS(INDX)-SUM)*RELAX/DEN(INDX)	CH2 422
516 CONTINUE	CH2 423

517 CONTINUE	CH2 424
IF(NGEOM**2)519,519,518	CH2 425
518 INDX=(IG-1)*NP+2*I	CH2 426
INDX1=INDX+NPX	CH2 427
INDX2=INDX1+NPX	CH2 428
INAX = INDX + (JG-IG)*NP	CH2 429
INAX1 = INAX +NPX	CH2 430
INAX2 = INAX1 +NPX	CH2 431
YD(INAX)=(4.0*YD(INAX1)-YD(INAX2))/3.0	CH2 432
YD(INAX-1)=(4.0*YD(INAX1-1)-YD(INAX2-1))/3.0	CH2 433
Y(INDX)=(4.0*Y(INDX1)-Y(INDX2))/3.0	CH2 434
Y(INDX-1)=(4.0*Y(INDX1-1)-Y(INDX2-1))/3.0	CH2 435
519 CONTINUE	CH2 436
IF(NGEOM**2-1)522,522,520	CH2 437
520 INDX=(IG-1)*NP+1-NPX	CH2 438
INAX = INDX + (JG-IG)*NP	CH2 439
DO 521 J=1,NY2	CH2 440
INDX=INDX+NPX	CH2 441
INAX = INAX + NPX	CH2 442
YD(INAX)=(4.0*YD(INAX+1)-YD(INAX+2))/3.0	CH2 443
521 Y(INDX)=(4.0*Y(INDX+1)-Y(INDX+2))/3.0	CH2 444
522 CONTINUE	CH2 445
KTINN=KTINN+1	CH2 446
IF(KTINN-ITINN)524,525,525	CH2 447
525 CONTINUE	CH2 448
GO TO 300	CH2 449
	CH2 450
NORMALIZATION	CH2 451
709 KNORM = 2	CH2 452
202 YMAX= Y(1)	CH2 453
SUM = YMAX**2	CH2 454
DO 204 I = 2,NN	CH2 455
CHGE = Y(I)**2	CH2 456
IF(CHGE-SUM)204,204,203	CH2 457
203 YMAX = Y(I)	CH2 458
SUM = YMAX**2	CH2 459
204 CONTINUE	CH2 460
YDMAX = YD(1)	CH2 461
SUM = YDMAX**2	CH2 462
DO 206 I = 2,NN	CH2 463
CHGE = YD(I)**2	CH2 464
IF(CHGE-SUM)206,206,205	CH2 465
205 YDMAX = YD(I)	CH2 466
SUM = YDMAX**2	CH2 467
206 CONTINUE	CH2 468
YMAX = YMAX*1.0E-6	CH2 469
YDMAX = YDMAX*1.0E-6	CH2 470

```

DO 207 I = 1,NN
Y(I) = Y(I)/YMAX
207 YD(I) = YD(I)/YDMAX
GO TC (600,700),KNORM
600 DO 646 IG = 1,NG
WRITE OUTPUT TAPE 6,120
WRITE OUTPUT TAPE 6,119,IG
DO 646 IPY = 1,NPY
I1=(IG-1)*NP+(IPY-1)*NPX+1
I2=I1+NPX-1
646 WRITE OUTPUT TAPE 6,113,(Y(I),I=I1,I2)
DO 647 IG = 1,NG
WRITE OUTPUT TAPE 6,120
WRITE OUTPUT TAPE 6,602,IG
602 FORMAT(5X17HACJCINT GROUP NO.I3 )
DO 647 IPY = 1,NPY
I1=(IG-1)*NP+(IPY-1)*NPX+1
I2=I1+NPX-1
647 WRITE OUTPUT TAPE 6,113,(YD(I),I=I1,I2)
650 KTOUT = KROUT +1
IF(ISSW)811,811,812
812 PRINT 809,RAMB
809 FORMAT(13H0EIGENVALUE = 1PE14.7 )
IF(SENSE SWITCH 2)680,681
680 RELAX = RELAX + DRELAX
682 WRITE OUTPUT TAPE 6,683,RELAX
683 FORMAT(1H0//6X8HRELAX = 1PE14.7)
PRINT 683,RELAX
GO TC 684
681 IF(SENSE SWITCH 3)685,684
685 RELAX = RELAX - DRELAX
GO TC 682
684 IF(SENSE SWITCH 1)810,811
810 KTOUT = 10000
811 IF(KTOUT-ITOUT)400,709,709
700 IF(NPCH)706,707,707
707 DO 800 IG=1,NG
K1=(IG-1)*NP +1
K2= IG*NP
800 WRITE OUTPUT TAPE 7,801,(Y(I),I=K1,K2)
801 FORMAT(5E15.8)
DO 701 IG = 1,NG
K1 = (IG-1)*NP +1
K2 = IG*NP
701 WRITE OUTPUT TAPE 7,801,(YD(I),I = K1,K2)
706 CONTINUE
TIM = DTIME(CARD,CHGE)

```

```

CF2 471
CF2 472
CF2 473
CF2 474
CF2 475
CF2 476
CF2 477
CF2 478
CF2 479
CF2 480
CF2 481
CF2 482
CF2 483
CF2 484
CF2 485
CF2 486
CF2 487
CF2 488
CF2 489
CF2 490
CF2 491
CF2 492
CF2 493
CF2 494
CF2 495
CF2 496
CF2 497
CF2 498
CF2 499
CF2 500
CF2 501
CF2 502
CF2 503
CF2 504
CF2 505
CF2 506
CF2 507
CF2 508
CF2 509
CF2 510
CF2 511
CF2 512
CF2 513
CF2 514
CF2 515
CF2 516
CF2 517

```

WRITE OUTPUT TAPE 6,803,TIME
803 FORMAT(/// 61X16HCOMPUTER TIME = -3PF6.3)
CALL CHAIN(1,4)
END

CH2 518
CH2 519
CH2 520
CH2 521