Dwr. - 1

GEAP-13825-3

AEC RESEARCH AND DEVELOPMENT REPORT
OCTOBER 1972

LMFBR IN-CORE INSTRUMENTATION AND IN-VESSEL SURVEILLANCE SYSTEMS

THIRD QUARTERLY REPORT
JULY-SEPTEMBER 1972

U.S. ATOMIC ENERGY COMMISSION
CONTRACT AT(04-3)-189 PROJECT AGREEMENT 65

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

GENERAL ELECTRIC

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

**LMFBR IN-CORE INSTRUMENTATION AND IN-VESSEL
SURVEILLANCE SYSTEMS
THIRD QUARTERLY REPORT
JULY—SEPTEMBER 1972**

NOTICE

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

Approved:

G. I. Samstad
Technical Project Engineer

Approved:

C. L. Larson
Program Manager

Prepared for the
United States Atomic Energy Commission
Under Contract AT(04-3)-189
Project Agreement No. 65

BREEDER REACTOR DEPARTMENT • GENERAL ELECTRIC COMPANY
SUNNYVALE, CALIFORNIA 94086

NOTICE

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

TABLE OF CONTENTS

ABSTRACT.....	vii
1. INTRODUCTION	1-1
2. SUMMARY	2-1
2.1 Task A—Neutron Monitoring.....	2-1
2.2 Task B—Acoustic Monitoring.....	2-1
2.3 Task C—Core Exit Instrumentation.....	2-1
2.4 Task D—Failed Fuel Detection and Location.....	2-2
2.5 Task E—On-Line Reactivity Computer (ORC)	2-2
2.6 Task F—Plant Protection System.....	2-2
3. TECHNICAL ACCOMPLISHMENTS.....	3-1
3.1 Task A—Neutron Monitoring.....	3-1
3.2 Task B—Acoustic Monitoring.....	3-13
3.3 Task C—Core Exit Instrumentation.....	3-24
3.4 Task E—On-Line Reactivity Computer (ORC)	3-24
4. ADMINISTRATIVE.....	4-1
4.1 Trips.....	4-1
4.2 Visits	4-1
4.3 List of Contributors.....	4-1
DISTRIBUTION	- 1-

LIST OF ILLUSTRATIONS

Figure	Title	Page
1	Source Range Monitor Neutron Pulse Width Versus Applied Voltage.....	3-2
2	Cable Breakdown Pulse Noise (BPN).....	3-3
3	Cable Breakdown Pulse Noise (BPN).....	3-4
4	Cable Breakdown Pulse Noise (BPN).....	3-5
5	Cable Internal Resistance (Conductor to Sheath) Versus Temperature at 100 Volts.....	3-6
6	Cable Leakage Current Versus Voltage and Temperature.....	3-7
7	Cable Leakage Current Versus Voltage and Temperature.....	3-8
8	Cable Leakage Current Versus Voltage and Temperature.....	3-9
9	High Temperature Seal for LMFBR Source Range Monitor	3-10
10	ZPPR Assembly 3, Phase 1B, Reference Core.....	3-11
11	Thermal Protective Structures	3-16
12	Reactor Vessel Shielding.....	3-17
13	Sodium Supply System.....	3-18
14	Sodium Supply System.....	3-19
15	Lower Plenum Assembly	3-20
16	Low Pressure Supply Pipe Normal Mode Vibration Characteristics	3-21
17	Low Pressure Supply Pipe Normal Mode Vibration Characteristics	3-22

ABSTRACT

This report summarizes the work performed on the research and development program for LMFBR In-Core Instrumentation and In-Vessel Surveillance Systems during the period from July 1, 1972 through September 30, 1972. The work was performed under Contract AT(04-3)-189, Project Agreement 65.

GENERAL ELECTRIC

ATOMIC POWER EQUIPMENT DEPARTMENT
SAN JOSE, CALIFORNIA

APPLICABLE TO

PUBLICATION NO. GEAP-13825-3

TITLE LMFBR In-Core Instrumenta-
tion & In-Vessel Surveillance
Systems, 3rd Quaterly Report

ISSUE DATE October 1972

ERRATA And ADDENDA SHEET

NO. 1
DATE Dec 28, 1972

*NOTE Correct all copies of the applicable
publication as specified below.*

ITEM	REFERENCES (SECTION, PAGE, PARAGRAPH, LINE)	INSTRUCTIONS (CORRECTIONS AND ADDITIONS)
1	Figure 16, page 3-21 Top Curve Bottom Curve	Change 32. 4 cps to 324 cps. Change 89. 5 cps to 895 cps.
2	Figure 17, page 3-22 Top Curve Bottom Curve	Change 5. 1 cps to 51 cps. Change 31. 9 cps to 319 cps.

1. INTRODUCTION

This program was initiated in January 1972 with the objective of developing in-core and in-vessel instrumentation for application to LMFBR's. The program is presently divided into six major tasks:

Task A — In-vessel high temperature neutron detectors and cable assemblies.

Task B — Acoustic monitoring systems for application to the reactor core and vessel.

Task C — Reactor core exit instrumentation.

Task D — Failed fuel detection and location systems.

Task E — On-line reactivity computer system.

Task F — Plant protection system

Primary emphasis is on overall system development, making maximum use of base technology information available from the National Laboratories.

In addition to regular quarterly progress reports, the following reports have been written in partial fulfillment of USAEC Contract AT(04-3)-189, Project Agreement 65:

1. Wimpee, L. C., State-of-the-Art Review for LMFBR Source Range Fission Counter, July 1972 (GEAP-10611).
2. Wimpee, L. C., "Conceptual Design Report for Source Range Detector for LMFBR," NEDG-13883, July 1972.
3. Swartz, P. W., "Factors Concerning Source Range Neutron Detector Location in an LMFBR," NEDG-13884, June 1972.
4. Berg, F. H., et al., "State-of-the-Art Report on Acoustic Monitoring Nuclear Reactors," NEDG-13896, May 1972.
5. Boyd, L. R., et al., "Selection of Functional Objectives for Task B, PA-65, Acoustic Monitoring," NEDG-13891, August 1972.

2. SUMMARY

2.1 TASK A—NEUTRON MONITORING

The objective of this task is to develop in-vessel neutron detector and cable assemblies that do not require auxiliary cooling or special shielding. Both startup (source range) and intermediate or wide range detectors are planned with first priority given to startup detectors.

The following significant progress was made during the quarter:

- The conceptual design of the source range fission counter was evaluated for three in-vessel positions using the computer programs developed during the detector physics study.
- The neutron pulse characteristics of the first development model detector were evaluated with two different gas mixtures.
- The first phase of cable evaluation (breakdown pulse noise, electrical characteristics) was completed and the purchase specification for cable was drafted.
- An order was placed for assembly of high temperature seals.
- A plan was prepared for the experimental evaluation (in ZPPR, Assembly III) of the source range detector neutron sensitivity required for various in-vessel shield configurations.

2.2 TASK B—ACOUSTIC MONITORING

The objective of this task is to develop acoustic systems for in-service surveillance of LMFBR core and in-vessel components.

During this reporting period, effort was primarily applied to the following activities:

1. Preparation of the development plan which defines the interdependence of the various task activities and their sequential arrangement required to accomplish task objectives.
2. Characterization of both the normal and failure mode vibration characteristics of in-vessel components, which were selected on the basis of susceptibility to vibration.
3. Identification of the test facilities in which tests might be performed to experimentally characterize acoustic signals.

Several other activities received lesser applied effort than those listed above. The report identifying the functional objectives of the task was issued. Preliminary definition was made of technical support required from ANL in the areas of acoustic transducers and waveguides. Finally, the analyses to characterize acoustic signals at transducer sites were initiated.

2.3 TASK C—CORE EXIT INSTRUMENTATION

The objectives of this task are to identify system functional objectives and to define and conduct the necessary programs to produce a representative Core Exit Instrumentation (CEI) probe design and system specification.

This task was initiated this quarter, and the activity was concentrated in two areas: (a) definition of functional requirements; and (b) survey of current and planned LMFBR core exit instrumentation.

Functional requirements were solicited from the reactor core and vessel designers and safety engineers personnel within GE-BRD. The LMFBR core exit instrument survey was reviewed and comments received. The survey is planned to be updated periodically.

2.4 TASK D—FAILED FUEL DETECTION AND LOCATION

No significant effort was performed on the task during the quarter.

2.5 TASK E—ON-LINE REACTIVITY COMPUTER (ORC)

Work for the year was planned and a review of existing reactor development programs was made to determine possible sources of supporting information for the ORC development effort.

2.6 TASK F—PLANT PROTECTION SYSTEM

No significant effort was performed on this task during the quarter.

3. TECHNICAL ACCOMPLISHMENTS

3.1 TASK A—NEUTRON MONITORING

3.1.1 Source Range Detector Location

The computer programs developed during the detector physics study were used to evaluate the conceptual design for three locations: (1) vessel shield, (2) core shield, (3) vessel shield with a sodium window (cavity). See Figure 10 for relative location of shields.

The effective neutron count rate shown in Table 1 is not significantly better in position (2) than in position (3) because even though the fission rate is higher in (2), the gamma field is also higher. The neutron count rate for position (3) is somewhat higher than the goal of 10 cps. The detector is gamma limited for the three locations considered. Even though the alpha count rate is quite high at discriminator settings up to 0.23 volt, which corresponds to the maximum single-alpha pulse height, it drops to a negligible value for higher settings because there is virtually no alpha pile-up.

Table 1
COMPARISON OF DETECTOR LOCATIONS

Location	Gamma Field (R/h)	U235 Fission Rate at Shutdown (f/s/gm)	Detector Fission Rate (f/s)	Discriminator Setting (volts)	Probability Factor ^(a)	Neutron Count Rate ^(a) (c/s)
1. Vessel Shield	0.535×10^6	8.25	7.66	0.24	0.61	4.66
2. Radial Shield	8.590×10^6	140	131	0.94	0.11	14.4
3. Vessel Shield with Na Window	0.535×10^6	24.75	23	0.24	0.61	14

(a) Uncertainty is $\pm 20\%$ in Probability Factor and $+0/-66\%$ in Fission Rate Calculations.

3.1.2 First Development Model

Pulse-width measurements for the first development model, with a 0.050-inch electrode gap spacing, showed it to be filled with two atmospheres of 90% argon and 10% nitrogen. The neutron pulse width was measured. The model later was refilled with two atmospheres of 89.5% argon, 10% nitrogen, 0.5% oxygen and the neutron pulse width was again measured. The electron collection time of the two gas mixtures was essentially the same, approximately 40 nanoseconds at 400 volts applied. This suggests that the required fast collection time can be obtained with a gas mixture containing oxygen. The oxygen is needed to provide an oxide film on internal surfaces to inhibit nitrogen take-up by metallic components. Further tests are planned to determine if this amount of oxygen is sufficient to maintain the oxide film for the required detector life. Figure 1 shows a comparison of predicted and experimental relation between neutron pulse widths and applied voltage for the two mixtures.

3.1.3 Cable Investigation

The first phase of the cable investigation was completed and an interim report started. It was determined that three cable manufacturers can supply cable which will be free of breakdown pulse noise (BPN) in the voltage range of interest, which is up to 400 volts at a temperature of 650°C. Figures 2, 3 and 4 show typical BPN data for Control Products cable, ERI cable, and Kaman cable respectively. Figure 5 shows typical internal resistance (conductor-to-sheath) of the same three manufacturers' cables from 100°C to 650°C. Figures 6, 7, and 8 show typical leakage currents (conductor-to-sheath) for the same three manufacturers, respectively, for temperatures up to 650°C and applied potentials up to 1000 volts. The figures show data for only one cable from each manufacturer but are typical for the type of cable tested.

Figure 1. Source Range Monitor Neutron Pulse Width Versus Applied Voltage

Figure 2. Cable Breakdown Pulse Noise (BPN)

Figure 3. Cable Breakdown Pulse Noise (BPN)

Figure 4. Cable Breakdown Pulse Noise (BPN)

Figure 5. Cable Internal Resistance (Conductor to Sheath) Versus Temperature at 100 Volts

Figure 6. Cable Leakage Current Versus Voltage and Temperature

Figure 7. Cable Leakage Current Versus Voltage and Temperature

Figure 8. Cable Leakage Current Versus Voltage and Temperature

3.1.4 Seals

An order has been placed to Basic Ceramics Incorporated (BCI) to provide 20 high-temperature seals. The metal parts were made by GE-APED and delivered to BCI for the seal assembly. Figure 9 shows the configuration of the seal. These seals will be used for development model No. 3, and for seal testing and evaluation.

Figure 9. High Temperature Seal for LMFBR Source Range Monitor

3.1.5 ZPPR-Assembly III Measurement of Expected U-235 Fission Rate for Various Shielding Configurations

A plan was developed for experimentally evaluating the variation of the U-235 fission rate under various shielding configurations. This plan calls for comparison of four shielding configurations.

- With no shielding in the core region (see Figure 10)
- With steel shielding for the core shield
- With B₄C shielding for the core shield
- With a neutron window (cavity) in the B₄C shielding for the core shield.

This work is being done in cooperation with PA-59 "Critical Experiments and Cooperative Evaluation Program." The experimental work is scheduled for the second quarter of FY 1973, and is described below.

Figure 10. ZPPR Assembly 3, Phase 1B, Reference Core

EXPERIMENTAL PLAN—MEASUREMENT OF EXPECTED U-235 FISSION RATE FOR VARIOUS SHIELDING CONFIGURATIONS

These measurements will determine the U-235 fission rate, relative to the core center, at a location in shielding material adjacent to the core assembly. The effects of various core shielding designs will be studied by having four configurations between the detector and reactor boundary. The intent is to provide experimental support to the feasibility study for neutron source range monitoring in the vessel shield of an LMFBR Demonstration Plant.

Additional drawer loadings are required in one quadrant of the empty matrix positions surrounding the present ZPPR-3 Phase IB assembly. A recommended loading arrangement is shown in the lower left hand corner of Figure 10 with a general description of the regions summarized in Table 2. The axial dimension of this zone should be at least core length. This size would provide detector response primarily from core leakage neutrons attenuated by the shield. The four shield configurations used in this measurement are summarized below.

A Empty Matrix Positions

All regions will be loaded except the core shield. The detector response with the empty matrix as the only shield would be measured.

B Bulk Steel Shielding

Shielding material with approximately 4:1 steel-to-sodium ratio is loaded into the empty matrix positions.

C Bulk B₄C Shielding

Available B₄C inventory is presently used in loaded drawers simulating the core control rods. These drawers will be used to construct the B₄C bulk shielding without any reloading. The outer ring of simulated control contains the greater amount of poison. These will comprise the main portion of the shield, centered in front of the detector location. This, however, is not sufficient to complete the shield. Inner control ring drawers, with less poison inventory, will be used for the shield at the edge. Remaining peripheral matrix positions will have the bulk steel shielding.

D Central Cavity

A central cavity in front of the detector location is placed in the bulk B₄C shielding. The drawers forming the central shield area will be displaced axially one foot to leave the vacancy. The result should leave an unshielded region through the shield approximately 10 to 12 inches wide.

Measurements with a U-235 fission detector will be made in a single location in the corner of the assembly matrix. These should be normalized to the detector response in the core center. To reduce the influence of room return neutron flux at the detector, absorber material will be placed along the edges of the corner area. Drawers from the inner ring of simulated core control would serve this purpose.

The various measurements of the detector response with each shielding configuration are to determine relative changes as well as absolute values. Using the shield materials as the single experimental variable, systematic uncertainties in interpretation of the data will be reduced. The uncertainty from both statistical and any systematic error in this fission rate measurement should be limited to $\pm 10\%$ standard error. This will allow adequate interpretation of the measured data.

Table 2
GENERAL DESCRIPTION OF SHIELDING REGIONS

	Region	Composition (Volume %)	Matrix Positions (Number)
I	Sodium	100% Na	41
II	Core Shield		
	A. Empty Matrix	8% Steel, 92% Void	92
	B. Bulk Steel	80% Steel, 20% Na	92
	C. Bulk B ₄ C	Outer Ring Control	48
		with Inner Ring Control	10
		with Remaining Bulk Steel	34
	D. Central Cavity	Cavity (12 inches axially)	18
III	Steel	100% Steel	23
IV	Vessel Shield	67% Steel, 33% Na	26
	Detector Location	Row 60, Column 3	1
	Room Return Absorber	Inner Ring Control	17

3.2 TASK B—ACOUSTIC MONITORING

3.2.1 Overall Task Planning and Integration

Task planning and integration proceeded in several areas. The report (NEDG-13891) describing selected functional objectives was issued. The preliminary data sheets for the several functions were reported in the last quarter. The development plan for execution of the task is being finalized. The technical support of this task required from Argonne National Laboratory (ANL) is being defined. Agreement on the scope of this support will be negotiated in the next quarter. The planning for the acoustic signal characterization test is in progress. Potential testing facilities are being contacted, and meetings are planned to establish agreements on testing.

3.2.2 Acoustic Source Characterization

The characterization of the vibrations of in-vessel components (selected on the basis of susceptibility to vibration) was started. The components identified to date are as follows:

- **Thermal Protective Structure**—The thermal protective structure protects critical vessel regions (such as nozzles) from thermal transients. Loss of this structure is not easily detected and could subject the vessel to temperature conditions beyond its design limits.
- **Reactor Vessel Shielding**—The vessel shielding will be analyzed as a potential background noise source. Since the shielding surrounds the core region, its acoustic signals from vibration could overpower the core acoustic transmissions.
- **Internal Piping**—Internal piping may be included in the design for sodium overflow lines, neutron monitor guide tubes, level probes, and (possibly) piping to the alternate shutdown drives. Acoustic techniques may be able to detect loss of a support point or other conditions which may precede a pipe failure.
- **Internal Arresting Cylinder**—The internal arresting cylinder is a large stainless steel cylinder located just inside the reactor vessel. The internal arresting cylinder protects the vessel in the event of a hypothetical core disassembly accident. Although this item is not expected to fail, its vibration could influence the vibration characteristics of other reactor components. The large structure is well coupled to the reactor vessel which may result in strong acoustic signals.

- **Reactor Closure**—The reactor closure contains several items that contribute to the background noise and generate useful acoustic signals. The core exit instrumentation, level probes and heaters are all slender probes fitting loosely in guide tubes. These arrangements are likely to be acoustically noisy.

The drywell guide tubes are important items since a failure would allow fission gas and sodium vapor to escape into the closure's upper housing. The drywells will be analyzed to identify the acoustic signals preceding a possible failure and those signals associated with a failure.

- **Lateral Core Support**—The lateral core support keeps the core restrained and in the proper configuration. Failures resulting in partial core loosening will be accompanied by reactivity and power fluctuations. The lateral core restraint will be analyzed for characteristic acoustic signals preceding and following the various failure modes. Background noise sources will also be identified.

Analysis was initiated on the thermal protective structure, shield rods, internal piping and several reactor closure items.

The analysis is directed at calculating the vibration characteristics preceding a component failure and those following a component failure. The failure modes analyzed are those considered to be most likely, based on engineering judgements.

The natural frequencies and mode shapes are being calculated for the components of interest. The vibration amplitudes and impact energies are being estimated where possible and the location of impact is being identified. Stress and fatigue evaluations are being made for components whose failure is preceded by characteristic acoustic signals.

The various analytical techniques and formulae used in the acoustic source analyses are being catalogued. This catalogue will make it possible to obtain frequencies and amplitudes of the specific structural members in other reactors which have similar configurations.

Calculating natural frequencies and mode shapes require a reactor to be defined in some detail, and the dimensions and features used in these analyses are intended to be representative of a typical LMFBR.

The analysis work completed to date is summarized below:

3.2.2.1 Thermal Protective Structure

The thermal protective structure is shown on Figure 11. The thermal sleeves are held in the vessel by collars weighted with special shield rods. The special shield rods are suspended from the collars and are supported laterally by bushings attached to the vessel wall. This arrangement allows the collar to be raised, freeing the thermal sleeve for removal and replacement. Since the bushings are well coupled to the reactor vessel, any noise due to impacting or rubbing against the bushing should be detectable at the vessel wall. Although excessive amplitudes could fatigue the thermal sleeves, the problem can be controlled by the design. Two types of vibration were considered for each thermal sleeve design. The thermal sleeves were considered as springs supporting the shield rods. The shield rods vertical oscillations result in rubbing against the bushings. The shield rods are also free to swing as pendulums resulting in impacts against the bushings. The vibration frequencies are tabulated in Table 3.

3.2.2.2 Shield Rods

The shield rods are shown in Figure 12. The rods are simply supported at both ends and are cooled with the bypass leakage flow (~ 5% of the total flow). The calculated shield rod natural frequencies are shown in Table 4. With 5% bypass leakage the sodium velocity is about 0.34 ft/sec in the shield region resulting in negligible vibration amplitudes. With a 35% bypass leakage flow, the sodium velocity increases to 2.4 ft/sec and the calculated vibration amplitude is to be less than 3×10^{-6} inches. Noise generation from the shield region is therefore not expected to be a problem.

Table 3

Thermal Liner Designation*	Pendulum Oscillation Frequency (cps)	Equivalent Spring - Mass Frequency (cps)	Amplitude for 10,000 psi stress (in.)
N4, N5, N6	0.25	372	0.029
N7, N8, N9	0.30	70.6	0.062
N14	0.24	26	0.068
N13	0.26	17	0.140

* See Figure 11

Table 4
SHIELD ROD VIBRATIONS

Rod Diameter (in.)	Rod Length (in.)	Natural Frequency (cps)
3.5	166	8.73
3.5	130	14.1
4	166	9.9
4	130	16.2
4.25	300	3.22
4.25	130	17.1
4.5	200	7.7
4.5	130	18.1

3.2.2.3 Internal Piping

Figures 13 and 14 show the internal piping for a possible alternate shutdown control supply system. Normally the pipe is bolted to a flange at one end and is constrained in a slip joint at the other. A short length of pipe connects the flange to the reactor vessel providing a continuous sound path to the reactor vessel. The first natural mode frequency under normal conditions is 10 cps. Should thermal transients or some other phenomenon cause the flange to loosen, the first mode vibration frequency is reduced to 6 cps. The flow-induced vibration effects and possible impact locations have not been evaluated at this time.

3.2.2.4 Low Pressure Supply Pipe

Figure 15 shows the pipe supplying low pressure sodium to the lateral core restraint region. The pipe passes through the high pressure plenum and is directly exposed to the flowing inlet sodium. A pipe failure would result in a direct leakage path between the high and low plenum regions.

Figure 16 shows the pipe's frequencies, mode shape and moment curves for the first two normal vibration modes. Figure 17 shows the same information for an assumed failure at one end of the pipe.

A 10,000 psi peak alternating stress is assumed a safe limit. A 0.012 inch clearance between the pipe and the filter screen will keep the stresses less than 10,000 psi for both the first and second vibration modes, but impacting may occur at this location.

Should some occurrence break the pipe loose from its socket joint at either end, the pipe will vibrate as shown in Figure 17. Both first and second mode vibrations will impact at the socket joint rather than at the filter screen.

Figure 11. Thermal Protective Structures

TYPICAL ROD SHIELDING

ALL DIMENSIONS AND
FEATURES ARE GENERALLY
REPRESENTATIVE OF AN
LMFBR

SHIELD ROD SIZE BETWEEN SUPPORT PLATES

LOCATION	DIAMETER	LENGTH
INNER ROWS	3-1/2	166
		130
	4	166
		130
OUTER ROWS	4-1/4	300
		130
	4-1/2	200
		130

Figure 12. Reactor Vessel Shielding

Figure 13. Sodium Supply System Plan View

Figure 14. Sodium Supply System Elevation Section

Figure 15. Lower Plenum Assembly

$$y_n(x) = A Y_n(x)$$

$$M_n(x) = E I K_n^2 A M_n(x)$$

$y_n(x)$ = PIPE DEFLECTION AT x

$M_n(x)$ = MOMENT AT x

A = CONSTANT (DETERMINED FROM KNOWN DEFLECTION POINT)

E = MODULUS OF ELASTICITY

I = MOMENT OF INERTIA

Figure 16. Low Pressure Supply Pipe Normal Mode Vibration Characteristics

$$y_n(x) = A Y_n(x)$$

$$M_n(x) = E I K_n^2 A M_n(x)$$

$y_n(x)$ = PIPE DEFLECTION AT x
 $M_n(x)$ = MOMENT IN PIPE AT x
 A = CONSTANT (DETERMINED FROM KNOWN DEFLECTION POINT)
 E = MODULUS OF ELASTICITY
 I = MOMENT OF INERTIA

Figure 17. Low Pressure Supply Pipe Failure Mode Vibration Characteristics

3.2.3 Signal Characterization Tests

Planning is underway for the signal characterization testing required to confirm the analysis performed on individual component failures. It has been determined that tests will be necessary to acquire data for the establishment of baseline acoustic signatures, failure mode signatures, and verification of signal processing techniques. These tests will utilize a number of test facilities available for LMFBR testing in order to adequately cover all acoustic monitoring functions. It will also include tests to evaluate transducers and mounting locations relative to components and signal sources monitored.

Four major functions have been selected for acoustic monitoring development. These are

- 1 Impact Monitoring
- 2 Vibration Monitoring
- 3 Control Rod Drive Monitoring
- 4 Core Monitoring

The most serious obstacle to accomplishing the task functional objectives is the high background noise level. Potential cavitation and flow noise is expected to produce a high amplitude white noise which will make the white boiling signal very difficult to detect. The many in-vessel components in the flow stream are expected to produce a variety of roughly periodic signals over a wide band of frequencies which will make impact monitoring difficult. An investigation of the need to reduce background noise and thereby increase the signal-to-noise ratios of the several measurements is being initiated.

Final selection will result from meetings scheduled with responsible personnel from each facility and associated programs. Tests must be compatible with present programs and meetings are being planned at LMEC-AI and ANL to discuss existing programs. Following is a brief description of the facilities under consideration for signal and background characterization.

- 1 Pump Bearing Test Facility
LMEC, Santa Susana, California

Data acquired at this facility would provide information on sodium pump and flow contributions to the noise environment of the reactor. The facility is capable of testing prototype LMFBR bearings at 1200°F, 235 psig and 2,000 gpm.

- 2 SCTI—Sodium Components Test Installation
LMEC, Santa Susana, California

This facility for testing of steam generators and IHX includes provisions for mounting accelerometers or other sensors and monitoring internal component vibrations. Sodium is circulated at up to 3,000 gpm at 1300°F. It might be used for impact monitoring tests in large vessels.

- 3 Failed Components Loop
ORNL

This loop may be operable to provide information on sodium boiling and transducer performance.

Additional facilities will be scheduled to monitor controlled impact experiments, control rod drive tests and signal correlation tests. A testing program is also scheduled with ANL at EBR-II.

3.2.4 Acoustic Analysis

Work on signal parameter analysis is also presently underway. These investigations will select the acoustic parameters to be monitored for each measurement function and evaluate the effects of signal propagation through the vessel structures. Component failure predictions supplied by GE-BRD are being reviewed by the Corporate Research and Development Center, and the expected signal available at the sensor will be identified. Factors being considered include frequency and amplitude of component vibrations, attenuation of signals within the reactor vessel, and interference from background and other local noise generators.

3.3 TASK C—CORE EXIT INSTRUMENTATION

3.3.1 Overall Task Planning

The task plan for the Core Exit Instrumentation (CEI) was revised to reflect current funding and program direction. A development plan is being prepared which will define the responsibility for the various technical activities required to develop a CEI system to meet the functional requirements.

3.3.2 Functional Requirements

The definition of the functional requirements activity was initiated by soliciting from the reactor design and safety engineering groups proposed uses and justification for the CEI. The evaluation of these submitted functional requirements is continuing. The functional requirements are slated to be reported on next quarter.

3.3.3 Core Exit Instrumentation

The survey of Core Exit Instrumentation was completed and the results are summarized in Table 5. It is planned to extend this survey to include information on coolant flow and temperature responses to various changes occurring within the core (e.g., effects on flow and temperature distribution of partial core blockages).

3.4 TASK E—ON-LINE REACTIVITY COMPUTER (ORC)

Tentative plans for work on this task have been established. Work this year is planned to generate a study report, which will build on the work performed last year. Effort is planned to: (1) identify the requirements for an ORC in a LMFBR plant; (2) establish the relationship of ORC to other surveillance systems; and (3) further establish uncertainties with respect to the reactivity parameters. A task force approach to this study is being taken with nuclear engineering, core design, safety, and instrumentation personnel participating. Task plans were written to define work scopes of the various contributing disciplines.

Work on ORC is supported by information obtained from other reactor development programs. A review to identify supporting programs within GE-BRD was completed. Representative programs include:

- Alternate shutdown system development (PA-64)
- Core restraint study (PA-10)
- Defective fuel testing (PA-10)
- Study of reactor operation with defective fuel (PA-10)
- Critical experiment measurements (PA-59)
- Nuclear methods development (PA-59)

Contact is also being maintained with FFTF (i.e., Reactivity Monitor and Anomaly System, and Digital Data Handling and Display System), and with the staffs of FERMI and EBR II to take advantage of knowledge they have gained from similar tasks, plus operating experience with ORC's.

Table 5
SUMMARY OF CORE EXIT INSTRUMENTATION SURVEY

Facility	Instrumentation
PFR (Dounreay, Scotland)	<p data-bbox="678 436 1158 552">Temperature: 1 chromel-alumel thermocouple (TC) per probe (dry or wet) . . . probes located at fuel assembly exits . . . used for surveillance (dry probes) and safety (wet probes).</p> <p data-bbox="678 594 1158 709">Flow: 1 eddy current flowmeter (FM) per probe . . . 3 (total) probes located at select fuel assembly exits . . . monitor core flow (part of plant protection system).</p> <p data-bbox="678 751 1158 804">Comment: Some consideration being given to 3 TC's plus 3 FM for each assembly.</p>
PHENIX (Marcoule, France)	<p data-bbox="678 909 1158 1087">Temperature: 2 chromel-alumel TC's per probe (dry . . . probes located at each fuel assembly exit and at 18 blanket assembly exits . . . signals tied to operator selected scram . . . multiplexer system (scans every 1.5 sec).</p>
SNR (Kalkar/Rheim, Germany)	<p data-bbox="678 1192 1158 1350">Temperature: 2 chromel-alumel TC's per probe (dry) . . . probes located at fuel and blanket assembly exits . . . detect gross assembly flow blockage by detection of mixed mean assembly temperature.</p> <p data-bbox="678 1392 1158 1476">Comment: Development is planned to provide special dry probes (unspecified number) with 4 chromel-alumel TC's and 1 eddy current FM.</p>
SEFOR (Fayetteville, Arkansas)	<p data-bbox="678 1581 1158 1633">Probe (quantity, 6) configuration was a modified (instrumented) fuel assembly (IFA).</p> <p data-bbox="678 1675 1158 1822">Temperature: 2 W5Re/W26Re TC's (2 each in 2 fuel rods) . . . measured fuel center temperature; 3 chromel-alumel TC's (1 at IFA inlet and 2 at IFA outlet) . . . measured coolant temperature of IFA.</p> <p data-bbox="678 1864 1158 1917">Flow: 1 permanent magnet FM at IFA inlet . . . measured coolant flow for IFA.</p>

Table 5 (Continued)

Facility	Instrumentation
SEFOR (continued)	<p data-bbox="773 386 1255 443">Probe (quantity, 1) configuration was a modified (instrumented) fuel rod (IFR).</p> <p data-bbox="773 480 1255 569">Temperature: 1 W5Re/W26Re TC in fuel rod . . . measured fuel center temperature near top of core.</p> <p data-bbox="773 606 1255 695">Comment: IFA and IFR were special systems developed for test program; in addition to normal plant process instrumentation.</p>
EBR-II (NRTS, Idaho)	<p data-bbox="773 795 1255 1077">Temperature: chromel-alumel TC's (22-gage wires twisted and welded or butt welded at hot junction) in thermowells . . . located at select fuel assembly exits (26) . . . blanket assembly exit temperatures (select number) measured by TC's located on assembly holddown rods (in path of outlet stream) . . . 4 fuel assembly exit TC's assigned reactor scram and alarm function.</p> <p data-bbox="773 1115 1255 1203">Pressure: NaK filled volumetric pressure units (10) located on reactor vessel to provide data on core ΔP.</p>
EFFBR (Lagoona Beach, Michigan)	<p data-bbox="773 1304 1255 1392">Temperature: Iron-Constantan TC's (4) located on core holddown figures to measure core outlet temperature.</p> <p data-bbox="773 1430 1255 1556">Flow: Electromagnetic flowmeters to measure primary sodium flow through high pressure plenum (core and inner radial blanket) and low pressure plenum (outer radial blanket).</p>
FFTF (Richland, Washington)	<p data-bbox="773 1656 1255 1808">Temperature and Flow: 3 chromel-alumel TC's and 1 eddy current FM per probe (dry) . . . probes located at fuel assembly exits . . . guide tube configuration leaves sensing tip ~ 2 feet above outlet.</p> <p data-bbox="773 1845 1255 1898">Comment: FM may be adequate for bubble detection.</p>

4. ADMINISTRATIVE

4.1 TRIPS

None

4.2 VISITS

July 10-14, 1972—K. Smith of GE-B&D Center visited Sunnyvale to participate in planning and technical effort on the acoustic monitoring program.

September 18, 1972—R. D. Lumley of LMEC visited Sunnyvale to discuss the RDT Standards program in the instrumentation and electrical area.

4.3 LIST OF CONTRIBUTORS

Breeder Reactor Department

C. W. Albert	L. McCarty
D. C. Allen	W. G. Meinhardt
H. S. Bailey	E. E. Olich
L. R. Boyd	G. E. Orr
G. Billuris	G. R. Pflasterer
S. L. Derby	J. J. Regimbal
T. E. Gleason	C. E. Russell
D. Glover	G. I. Samstad
P. Greebler	B. F. Shoopak
P. J. Hendriksz	P. W. Swartz
C. L. Larson	P. C. Vaughan
A. J. Lipps	M. L. Weiss
C. R. McMillan	M. B. Wittry

Atomic Power Equipment Department (Nuclear Instrumentation Group)

Y. Dayal
G. W. Titus
L. C. Wimpee

Corporate R&D Center

J. Wallach
K. Smith

DISTRIBUTION

U.S. Atomic Energy Commission Division of Technical Information Extension P.O. Box 62 Oak Ridge, Tennessee	203	U.S. Atomic Energy Commission Office of RDT Site Representative 310 De Guigne Drive Sunnyvale, California 94086	1
Division of Reactor Development and Technology U.S. Atomic Energy Commission Washington, D. C. 20545 Attn: Director	2	U.S. Atomic Energy Commission San Francisco Operations Office 2111 Bancroft Way Berkeley, California 94704 Attn: Director, PMIC	2