6/7/68

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission
A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights, or
B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report
As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

GEMS 400

AEC RESEARCH AND DEVELOPMENT REPORT

C-92A

M-3679 EDITION 55

SNAP-27

QUARTERLY REPORT NO. 10

CONTRACT NO. AT(30-1) 3535

JANUARY 1, 1968 TO MARCH 31, 1968

PREPARED FOR

U. S. ATOMIC ENERGY COMMISSION
ALBUQUERQUE OPERATIONS OFFICE
ALBUQUERQUE, NEW MEXICO

UNCL /21 MAR 68/ Paul E. Brown
CLASS. DATE AUTHORIZED CLASSIFIER

APPROVED BY:

A. Pitrolo

A. PITROLO - MANAGER SNAP-27 PROGRAM

ISOTOPE POWER SYSTEMS OPERATION

GENERAL ELECTRIC
MISSILE AND SPACE DIVISION
KING OF PRUSSIA PARK
PO BOX 8661 PHILADELPHIA PENNA 19101

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

fel

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

- A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information apparatus, method or process disclosed in this report may not infringe privately owned rights; or
- B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

TABLE OF CONTENTS

Section		Page
1	SUMMARY OF ACCOMPLISHMENTS.....	1-1
1.1	ALSEP Interface-IPU System.....	1-1
1.2	Generator Assembly.....	1-1
1.3	Fuel Capsule Assembly (FCA).....	1-2
1.4	Graphite LM Fuel Cask (GLFC).....	1-3
1.5	Support.....	1-4
1.6	Safety.....	1-5
2	SCHEDULES.....	2-1
3	LIAISON AND INTEGRATION.....	3-1
3.1	Interface Requirements.....	3-1
3.1.1	IPU System.....	3-1
3.1.2	GLFC.....	3-1
3.2	Hardware and Testing.....	3-3
3.2.1	ALSEP Qualification Program.....	3-3
3.2.2	Prototype and Development Testing of GLFC.....	3-3
3.2.3	Power Conditioning Unit.....	3-4
3.3	Kennedy Space Center Prelaunch Support.....	3-8
3.3.1	Procedures.....	3-8
3.3.2	LM/SLA/IU Mock-Up.....	3-9
3.3.3	IPU Test Console Trouble Shooting Procedure/Schematics.....	3-10
3.3.4	Operational Manual.....	3-10
3.3.5	Walk-Throughs.....	3-10
4	IPU SYSTEM.....	4-1
4.1	Generator Assembly	
4.1.1	Thermal Analysis of Generator/FCA Fixture.....	4-1
4.1.2	Generator Hardware Status.....	4-4

TABLE OF CONTENTS (CONT)

Section		Page
	4.1.3 Generator Testing.....	4-4
4.2	Fuel Capsule.....	4-27
	4.2.1 Design and Analysis.....	4-27
	4.2.2 Mound Laboratory and GE-Vallecitos Liaison.....	4-34
	4.2.3 Testing.....	4-39
	4.2.4 FCA Component Status.....	4-46
4.3	Support Equipment Status	
	4.3.1 Flight Handling Tool.....	4-47
	4.3.2 Ground Handling Tool (GHT).....	4-47
	4.3.3 Electric Fuel Capsule Simulators (EFCS).....	4-47
	4.3.4 SLA Transfer Cask.....	4-47
	4.3.5 SLA Handling Tools (SHT).....	4-48
	4.3.6 Port Entry Trough (PET).....	4-48
	4.3.7 SLA Inspection Tools (SIT).....	4-48
	4.3.8 Shipping Containers.....	4-48
	4.3.9 M8 & M9 Final Training Mockups.....	4-48
	4.3.10 Ground Shipping Casks (GSC).....	4-48
5	GRAPHITE LM FUEL CASK	
5.1	Design Status.....	5-1
	5.1.1 Drawing Status.....	5-1
	5.1.2 Secondary Heat Shield.....	5-11
	5.1.3 Weight Summary.....	5-11
5.2	Thermal Analysis.....	5-13
	5.2.1 GLFC with a Beryllium Heat Shield...	5-15
	5.2.2 GLFC with a Beryllium Oxide Secondary Heat Shield.....	5-26
5.3	Structural Analysis	
	5.3.1 Graphite Shell During Re-entry.....	5-31
	5.3.2 Secondary Heat Shield Assembly.....	5-34

TABLE OF CONTENTS (CONT)

Section		Page
5.4	Materials Program	
5.4.1	Graphite Primary Heat Shield.....	5-37
5.4.2	Secondary Heat Shield SiO ₂ /Cb Design.....	5-37
5.4.3	Secondary Heat Shield Beryllium Design.....	5-41
5.4.4	Coatings and Compatibility.....	5-41
5.5	GLFC Hardware.....	5-48
5.5.1	Bendix System Test Article (BSTA)...	5-49
5.5.2	Secondary Thermal Shields.....	5-49
5.5.3	Graphite Parts.....	5-49
5.5.4	Forward Capsule Supports.....	5-50
5.5.5	Latch Fittings.....	5-50
5.5.6	Litton Astronaut Test Hardware.....	5-50
5.6	GLFC Testing.....	5-50
5.6.1	Engineering Development Testing.....	5-50
5.7	References.....	5-59
6	SAFETY.....	6-1
6.1	Safety Test Program.....	6-1
6.1.1	Test Series 6 - Capsule Burial.....	6-1
6.1.2	Test Series 7 - Fuel-Clad-Soil Reaction.....	6-1
6.1.3	Test Series No. 12 - Capsule Melt Down-Radiant Heat.....	6-1
6.1.4	Test Series No. 16 - Radiation Measurements.....	6-2
6.2	Safety Thermal Analysis.....	6-5
6.3	Safety Reports.....	6-8

LIST OF ILLUSTRATIONS

Figure	Title	Page
3-1	Useful Life of Heated GLFC in Ambient Dry Air.....	3-2
3-2	Typical Telemetry Outputs for Thermal Instrumentation.....	3-5
3-3	Actual PCU Input Variations Over ALSEP Load Range....	3-6
3-4	Telemetry Signals Representing PCU Input Parameters..	3-7
4-1	Axial Temperature Distribution of the Generator Outer Case During Air Operation with Convection Baffles in Place.....	4-2
4-2	Axial Temperature Distribution of the Mod 8 Generator Outer Case during Vacuum Operation with and Without Convection Baffles in Place.....	4-3
4-3	Vacuum Chamber Pressure vs Time for Mod 8 Generator Venting Sequence.....	4-5
4-4	Mod 8 Fin Base Temperature History during Vacuum Chamber Venting Operation (Circumferential Averages).	4-6
4-5	Mod 23 GA Power Output vs EFCS Input (Lunar Day Conditions).....	4-9
4-6	Mod 23 GA Power Output vs EFCS Input (Lunar Night Conditions).....	4-9
4-7	Mod 5 Generator Normalized Power Output.....	4-10
4-8	Mod 5 Generator Normalized Open Circuit Voltage.....	4-11
4-9	Mod 5 Generator Resistance Ratio	
4-10	Mod 5 Generator Internal Pressure.....	4-13
4-11	Leak Rate vs Time, Mod 5.....	4-14
4-12	I-V Maps Before and After Life Test (Lunar Day Cycle).....	4-16
4-13	I-V Maps Before and After Life Test (Lunar Night Cycle).....	4-16
4-14	Mod 10 Generator Normalized Power Output.....	4-18
4-15	Mod 10 Generator Normalized Open Circuit Voltage.....	4-19
4-16	Mod 10 Generator Resistance Ratio.....	4-20
4-17	Magnetic Evaluation Data of Mod 10 GA and Mod 10 IPU.	4-21
4-18	Mod 8B Generator Normalized Power Output.....	4-22
4-19	Mod 8B Generator Normalized Open Circuit Voltage.....	4-23
4-20	Mod 8B Generator Normalized Resistance Ratio.....	4-24
4-21	Margin of Safety at Capsule Center Section.....	4-32
4-22	Coated Haynes-25 Emissivity Test Strip after Air and Vacuum Cycling (1200 to 1400°F).....	4-34

LIST OF ILLUSTRATION (CONT)

Figure	Title	Page
4-23	Tubular Weld Test Components.....	4-41
4-24	Tubular Weld Test Specimen Assembly.....	4-41
4-25	Test Rig Tubular Weld Specimen Test, Front Elevation.	4-42
4-26	Test Rig Tubular Weld Specimen Test, Side Elevation..	4-43
4-27	Fatigued and Side Grooved V-notched Modified Charpy Test Specimen (Unwelded).....	4-45
4-28	Fatigued and Side Grooved V-notched Modified Charpy Test Specimens (Unwelded).....	4-45
5-1	GLFC Secondary Thermal Shield, Beryllium.....	5-3
5-2	Support Rings Thermal Shield, Fwd.....	5-5
5-3	Support Rings Thermal Shield, Aft.....	5-7
5-4	GLFC Assembly.....	5-9
5-5	Relationship of Capsule Temperature to Secondary Heat Shield Silicon Dioxide Thickness.....	5-14
5-6	Maximum Capsule Temperature during Re-Entry vs Thickness of a Beryllium Secondary Heat Shield.....	5-16
5-7	Maximum Temperature Gradient Across a Be Secondary Heat Shield during Re-entry vs Shield Thickness.....	5-17
5-8	Weight of Be Secondary Heat Shield vs Thickness of Shield.....	5-17
5-9	Capsule/Cask Temperatures (Lateral Spin).....	5-18
5-10	Capsule/Cask Temperatures (Super-orbital $\gamma = 38.05^\circ$)..	5-19
5-11	Capsule/Cask Temperatures (Super-orbital $\gamma = 6.25^\circ$)...	5-19
5-12	GLFC 2D THT-D Model Nodal Numbering System.....	5-22
5-13	GLFC 2-D THT-D Model Capsule/Cask Temperatures ($^\circ\text{F}$) at 6210 Seconds.....	5-23
5-14	GLFC 2-D THT-D Model Capsule/Cask Temperatures ($^\circ\text{F}$) at 6260 Seconds.....	5-24
5-15	GLFC 2-D THT-D Model Capsule/Cask Temperatures ($^\circ\text{F}$) at 6350 Seconds.....	5-25
5-16	Capsule/Cask Temperatures - Stagnation Line Nodes - 2-D Model.....	5-27
5-17	Maximum Capsule Temperature during Re-entry vs Thickness of a BeO Secondary Heat Shield.....	5-28
5-18	Maximum Temperature Gradient Across a BeO Secondary Heat Shield during Re-entry vs Shield Thickness.....	5-29
5-19	Weight of BeO Secondary Heat Shield vs Thickness of Shield.....	5-30
5-20	Radial Temperature Gradients for Planar Tumble.....	5-31
5-21	"B" Direction Elastic Modulus.....	5-32

LIST OF ILLUSTRATIONS (CONT)

Figure	Title	Page
5-22	"B" Direction Plastic Modulus.....	5-32
5-23	"B" Direction Intersection Strength (E/Ep).....	5-33
5-24	Pyrocarb "406" Circumferential Direction Ultimate Tensile Strength.....	5-33
5-25	"B" Direction vs. Length Elastic.....	5-34
5-26	Configuration for Re-entry Analysis of Secondary Heat Shield.....	5-35
5-27	High "B" Fill Crimp in Section Taken from Tag End of Cylinder S/N 24630B.....	5-40
5-28	Test for Compatibility of Rhodium/Radifrax Coated Beryllium in Contact with Fuel.....	5-42
5-29	Engineering Development Test Setup.....	5-52
5-30	Rotation of Dome and Cylinder After Test.....	5-54
5-31	Broken Spline Following Test.....	5-54
5-32	Forward Capsule Support Following Test.....	5-55
5-33	Secondary Thermal Shield - Cracked SiO ₂ Rings.....	5-57
5-34	Secondary Thermal Shield - Bad Braze.....	5-57
6-1	Ottawa Sand Thermal Conductivity.....	6-2
6-2	Neutron Energy Spectrum for SNAP-27.....	6-4
6-3	Neutron Energy Spectrum for SNAP-27 in Generator.....	6-4
6-4	Transient Burial Analysis - Configuration I.....	6-6
6-5	Transient Burial Analysis - Configuration II.....	6-7
6-6	Transient Burial Analysis - Configuration III (Intact GLFC).....	6-7

LIST OF TABLES

Table	Title	Page
2-1	SNAP-27 Generator Schedule.....	2-2
2-2	SNAP-27 Support Equipment Schedule.....	2-3
2-3	SNAP-27 Fuel Capsule Schedule.....	2-4
2-4	SNAP-27 Graphite LM Fuel Cask Schedule.....	2-5
4-1	Test Summary for the SNAP-27 Flight Generator Assemblies.....	4-7
4-2	RTD Temperature (°F) Summary for the Flight Generator Assemblies.....	4-8
4-3	104-Couple Module Performance Summary.....	4-26

LIST OF TABLES (CONT)

Table	Title	Page
4-4	10-Couple Module Performance Summary.....	4-28
4-5	Mound Laboratory Helium Release Rate.....	4-38
5-1	GLFC Nominal Weight Summary.....	5-12
5-2	Peak Temperatures for the GLFC with a 0.565" Thick, Cylindrical Beryllium Secondary Heat Shield having a 3.0 Inch ID.....	5-20
5-3	Comparison of Tag-End Values with Cylinder Values....	5-38
5-4	Tensile Properties Showing Affects of Re-Impregnation	5-39
5-5	Beryllium Heat Shield Compatibility Test.....	5-43
6-1	SNAP-27 Fuel Capsule Assembly Dose Rate Measurements.	6-3

BLANK

1. SUMMARY OF ACCOMPLISHMENTS

The following is a summary of accomplishments during the January 1 through March 31, 1968 reporting period. Detailed discussion is contained in the applicable sections of this report.

1.1 ALSEP INTERFACE-IPU SYSTEM

- Completed SNAP-27 end item storage life capability assessment. Four years is acceptable under certain conditions on all components except the Fuel Capsule Assembly (FCA).
- Participated in Bendix Qual Readiness review for Mod 15 system, reviewed available test plans and supplied Bendix with supporting SNAP-27 data.
- Completed Power Conditioning Unit (PCU) evaluation and submitted report and recommendations to AEC. PCU design was deemed acceptable based on implementation of certain fixes now in progress.
- Updated all Integrated Power Unit (IPU) System Interface Control Drawings, including: IPU, FCA, Flight Handling Tool (FHT), Ground Handling Tool (GHT), Electric Fuel Capsule Simulator (EFCS) and Test Console.

1.2 GENERATOR ASSEMBLY

- Thermal vacuum acceptance of last flight generator Mod 23 was completed and presented to AEC for component buy-off.
- Operated two generators with fuel capsule assembly. Performance was two watts higher than with EFCS at same thermal setting.
- Mod 8B generator was operated in the "free convection baffle" under both room and thermal vacuum conditions using an EFCS to prove the fixture design prior to using it for testing with a fuel capsule.
- Completed magnetic test of Mod 10 with Fuel Capsule No. 1 at NASA Goddard. Results indicate a magnetic field of 0.013 gamma at 50 feet which meets the requirements of 0.10 gamma.

- The Mod 5 generator completed one year of thermal vacuum testing under simulated lunar environments on March 17, 1968.
- Operating summary for generator testing as of March 28:
 - Mod 5 - 9641 total hours; 9032 hours thermal vacuum
 - Mod 8B - 5869 total hours; 5621 hours thermal vacuum
 - Mod 10 - 5219 total hours; 4975 hours thermal vacuum
- Nominal power summary for flight generators (1455 watts input with output controlled at 16 volts) is as follows:

	<u>Lunar Day</u>	<u>Lunar Night</u>
Mod 13	67.1	68.8
Mod 19	67.5	68.8
Mod 21	66.0	66.7
Mod 22	66.2	67.3
Mod 23	67.9	68.9

- Generator weights were all less than the specified maximum of 28.0 pounds.

1.3 FUEL CAPSULE ASSEMBLY (FCA)

- NDT symposium was held at GE/VNC to gain insight into the indications being detected in dome closure welds.
- Detailed analytical and experimental program established to evaluate structural capability of Capsule No. 2 and to determine maximum permissible deviations.
- Received FCA No. 1 at GE Valley Forge. Completed component acceptance testing February 16-17.
- Initial studies were completed on Capsule No. 1 permitting its release for component acceptance and use in the magnetic measurement of Mod 10 generator.
- Completed non-dynamic component acceptance of Fuel Capsule No. 1.
- FCA No. 1 completed Magnetic Testing at NASA Goddard with Generator Mod 10.
- Fuel Capsule No. 2 was received by GE.

- Capsule No. 2 was released for non-dynamic testing. Final acceptance of units 1 and 2 pending completion of GE Haynes behavior material evaluation program.
- Capsule No. 2 has been released for acceptance testing by GE. Based on a Mound evaluation (concurrent by GE) the teflon contamination of the fuel is considered to present no significant problem.
- Capsule No. 3 fueled at Mound.
- Initiated fatigue testing of tubular specimens in weld test program.

1.4 GRAPHITE LM FUEL CASK (GLFC)

- Graphite cask, BSTA, was delivered to Bendix January 9, 1968.
- Engineering T/V test on the GLFC was abbreviated due to high thermal resistance of radiation barrier.
- Final GLFC specification complete.
- Completed fabrication and testing of GLFC vibration test fixture.
- BSTA assembled, tested and shipped to Bendix on January 9, 1968.
- The second Fansteel thermal barrier was tested and performance was improved over the engineering unit but still not satisfactory. The Vac Hyd engineering unit indicated melting of the silver rings and poor adherence of nickel plating. The second Fansteel unit indicated a good braze was achieved but silver rings were cracked and nickel plating showed poor adherence. A new vendor (Solar) was started.
- Received Request for Proposal from Bendix relating to the GLFC/ALSEP qual and flight acceptance test program. Proposal submitted March 12, 1968.
- Participated in meeting with NASA/Bendix to finalize generator ICS, up-date GLFC ICS, and define test requirement for SNAP-27 ALSEP qual and acceptance test program.
- Selected Litton as contractor to perform operational test of GLFC in vacuum.

- Completed GLFC graphite material characterization program.
- Developed non-destructive test technique for inspecting GLFC radiation barriers.
- The graphite heat shield material characterization program was completed and a detailed acceptance specification was issued.
- Meeting was held with Bendix, February 26-27, 1968, to establish GLFC/ALSEP vibration program to evaluate interface loads.
- Completed scoping study of internal redesign of GLFC to resist blast and fireball.
- Introduced beryllium structure for GLFC radiation barrier.
- Completed design beryllium radiation barrier.
- Compatibility of beryllium plated with rhodium with $^{239}\text{PuO}_2$ fuel was demonstrated.
- Received first qual graphite hardware.
- Successfully completed cold vibration testing of GLFC to the specified interface load levels.
- Completed preparations for Litton manned test of operational performance of GLFC in thermal vacuum environment. Test to start April 16, 1968.
- Completed critique of Bendix spline extraction lanyard.

1.5 SUPPORT

- Issued report of Mod 15 EFCS used in Bendix pre-acceptance test (PIA)
- Specifications for M8/M9 mock-ups were completed and issued.
- Rough draft of SNAP-27 Technical Manual completed and now being reviewed and revised.
- Prepared preliminary flow chart of fuel capsule/GLFC pre-launch installation activities.

- Redesigned wrist tether.
- Verified inspection tool design by checkout with EFCS and GLFC.
- Completed acceptance testing of SLA handling tools.
- All SLA equipment with exception of transfer casks and port entry troughs have been accepted by Sandia and are in storage.
- M5 GLFC and FCA specifications and designs completed.
- Supported checkout at Bendix and KSC of integrated KSC loading procedures for ALSEP packages/GLFC/support structure/fuel capsule.
- Participated at Bendix and at KSC in checkout of integrated loading procedures for ALSEP packages/GLFC/ALSEP Support Structure/Fuel Capsule using engineering/mock-up tools and hardware and the LM mock-ups.
- Shipped first prime IPU test console to Bendix.
- Submitted new IPU test console schematics as required by NASA.
- LM mock-up at GE nearing completion.

1.6 SAFETY

- Received and reviewed preliminary safety documentation inputs from NASA.
- Submitted working copies of the Draft Final Safety Analysis Report (SAR) to AEC.
- Formulated basic analytical and test programs to assess re-entry reaction on GLFC during abort considering ALSEP hardware attached.
- Submitted formal request to NASA for input revision to final Reference Design Document (RDD) and SAR.
- Meetings held with NASA-AMES and AEC have resulted in major reorientation of the re-entry safety analysis and verification program.

- Reviewed SAR draft comments with Sandia/AEC.
- Initiated safety evaluation of Beryllium Secondary Heat Shield.
- Received preliminary abort probability numbers from AEC.
- Requested AEC to investigate the possibility of NASA's instrumenting LM vehicles to provide information on breakup altitude and temperature as well as LM fuel tank conditions during re-entry to aid in determining whether LM fuel tanks explode.
- Submitted to NASA, interaction data of GLFC/titanium and possible solutions to reduce reactions at the interface.
- Re-entry evaluation of GLFC/LM/ALSEP has been initiated. Program reviewed with AMES.
- Reviewed re-entry data from AS-204 Apollo (launched 1/27/68) as supplied by NASA. Propellant weight in Descent Stage and interpretation of data by NORAD are required to make this information meaningful.

2. SCHEDULES

Current schedules for the SNAP-27 Program are shown in Tables 2-1 through 2-4. These schedules include:

- Generator Assemblies
- Support Equipment
- Fuel Capsule Assemblies
- Graphite LM Fuel Casks

TABLE 2-1. SNAP-27 GENERATOR SCHEDULE

▲ - MILESTONE
 ▲ - COMPLETED MILESTONE
 ▲ - RESCHEDULED MILESTONE
 ▲ - COMPLETED RESCHEDULED MILESTONE
 SF - SHRINK FIT AT 3M
 P&T - PROCESSING & TESTING AT 3M
 AT - ACCEPTANCE TESTING AT GE
 OS - OUTER SHELL FROM SOLAR

TABLE 2-2. SNAP-27 SUPPORT EQUIPMENT SCHEDULE

LEGEND: ▲ -MILESTONE
 ▲ -COMPLETED MILESTONE
 ▲ -RESCHEDULED MILESTONE
 ▲ -COMPLETED RESCHEDULED MILESTONE

TABLE 2-3. SNAP-27 FUEL CAPSULE SCHEDULE

LEGEND: 1-HARDWARE AVAILABLE AT MOUND

2-START FUELING AT MOUND

3-SHIP TO VALLECITOS

4-SHIP TO GE

5-COMPLETE FUEL CAPSULE ACCEPTANCE TESTING

6-COMPLETE FUEL CAPSULE/GENERATOR TESTING

7-COMPLETE FUEL CAPSULE/GRAPHITE LEM FUEL CASK ACCEPTANCE TESTING

8-COMPLTE IPU SYSTEM COMPATIBILITY TESTS

3A-SHIP TO MOUND FOR RADIATION MEASUREMENT

3B-SHIP TO MOUND FOR RADIOGRAPHY

5A-MAGNETIC TEST W/ MOD 10 AT NASA GODDARD

△ -MILESTONE

▲ -COMPLETED MILESTONE

△ ◇ -RESCHEDULED MILESTONE

▲ ◇ -COMPLETED RESCHEDULED MILESTONE

TABLE 2-4. SNAP-27 GRAPHITE LM FUEL CASK SCHEDULE

BLANK

3. LIAISON AND INTEGRATION

The following are the highlights of the SNAP-27/ALSEP activities associated with the integration and liaison of the power subsystem into the total ALSEP/Apollo program.

3.1 INTERFACE REQUIREMENTS

Meetings were held during the reporting period to resolve outstanding items for the Integrated Power Unit (IPU) and the Graphite LM Fuel Cask (GLFC) Systems.

3.1.1 IPU SYSTEM

A complete set of IPU System Interface Control Drawings was updated and issued including:

- 47C300644 Interface - Flight Handling Tool
- 47D301190 Interface - Ground Handling Tool
- 47D300201 Interface - Electric Fuel Capsule Simulator
- 47D300186 Capsule Assembly Envelope Interface
- 47E300112 IPU Interface
- 47E300292 IPU Test Console Interface

A set of reproducibles was forwarded to Bendix for review and signature.

3.1.2 GLFC

The GLFC ICD 2334552 has been completely revised and is currently being issued by Bendix for GE approval. Several of the notes and non-dimensional aspects of this drawing were transferred to the ICS. These items include:

- a. Force to remove locking spline not to exceed 20 pounds.
- b. Torque required to remove end cap not to exceed 80 pound-inches.
- c. Orientation of FCA inside GLFC is such that one latch points down during FCA removal operations.

A revised ICS, 314121, is being prepared by NASA/Bendix at this time and will include results of thermal and dynamic testing at Bendix.

In order to enhance the re-entry safety aspects of the GLFC Support Structure, Bendix has completed a study of low melting temperature alloys to replace the stainless steel rivets and dome pins now being used. The best material found, displaying adequate strength at operational temperatures, was Al Bronze D which melts at 1910°F.

A thermocouple will be used to monitor the GLFC temperature prior to launch and possibly during flight.

Requested updated writeups from NASA in support of the SNAP-27 Safety Documentation.

Reviewed ALSEP spline removal lanyard concept. There is a possibility that this will be a weak link in the system insofar as operational and re-entry reliabilities are concerned. Analysis or test data are required to show that the system will operate as expected.

Issued a curve, Figure 3-1, defining the useful life in dry air of a heated GLFC. The cumulative damage formula is shown in the figure.

Figure 3-1. Useful Life of Heated GLFC in Ambient Dry Air

3.2 HARDWARE AND TESTING

3.2.1 ALSEP QUALIFICATION PROGRAM

3.2.1.1 IPU System Qual

Participated in ALSEP Qual Readiness Review. Mod 15 System was found to be in good condition for System Qualification.

Mod 15 and the Qual Model of ALSEP Pallet No. 2 have completed thermal vacuum portion of Acceptance Testing prior to qualification. Low level vibration will begin shortly. The generator is currently operating about 2.5 watts below the output level of earlier tests. A portion of this difference is believed attributed to additional cabling, re-calibrated test console, aging of EFCS and other undeterminable factors. Nevertheless, the generator appears to be degrading slightly.

3.2.1.2 GLFC Qual

A proposal has been submitted by GE in response to the Bendix RFP to perform the joint qualification of the GLFC/FCA/Support Structure as a system. Details are being worked out between the two organizations and will be reported on at a later date.

3.2.2 PROTOTYPE AND DEVELOPMENT TESTING OF GLFC

3.2.2.1 Bendix Test Program

A scrap GLFC designated the Bendix System Test Article (BSTA) was shipped to Bendix in support of their prototype test of the GLFC/Support Structure as a system. This hardware had the early Super-temp seamed graphite and a scrap secondary thermal shield. The latter was believed to have non-representative thermal resistance but would not affect external heating characteristics insofar as the ALSEP structure is concerned. The GE thermal shroud and test canister were also sent to Bendix, along with thermal instrumentation and connectors.

Recent results of this Bendix test showed that the launch and flight temperatures are as predicted by analysis and are in line with existing interface agreements.

Dynamic testing of this system at Bendix will be performed during the next quarter.

3.2.2.2 GE Testing of GLFC Integrated Structure

In order to assess various human factors performance requirements of the GLFC, a thermal vacuum test is planned to be run at Litton using a Litton "astronaut". Of particular interest are the spline removal force, the dome removal torque and the affects of the hot capsule on an astronaut. ALSEP support structure, thermal shield and tilt mechanism hardware, tools and personnel were requested from NASA to support this test effort which is scheduled to begin in mid - April.

3.2.3 POWER CONDITIONING UNIT

During this quarter a test was conducted to determine the performance of the ALSEP temperature telemetry circuits powered by the Bendix Power Conditioning Unit (PCU). This test supplements the PCU-IPU Integration tests discussed in the last Quarterly Report.

The temperature telemetry circuits involved in this test are designed to translate resistance changes in the six Resistance Temperature Detectors (RTD's), mounted on the IPU, into corresponding 0 - 5 volt telemetry (TM) signals to permit monitoring of IPU temperatures during lunar operations. Although these circuits are not part of the PCU in the ALSEP application, they are energized by power from the PCU. The particular circuits tested were furnished by Bendix as a printed circuit card attached to the PCU Test Chassis.

For purposes of this test the RTD's were simulated by means of adjustable and fixed resistors, adjusted to cause the TM circuits to operate at about the midpoints of their ranges. PCU input power, derived from an external power supply in series with an external resistor, was adjusted to simulate a 68 watt IPU. The PCU was then loaded and unloaded over its prescribed operating range with external variable resistors to simulate ALSEP experiment load variations.

Results of the test are plotted in Figures 3-2, 3-3 and 3-4. Figure 3-2 shows the variation of the temperature telemetry signals with PCU load. Since the levels of these temperature telemetry signals were unrelated to PCU load current except by the effect of this current on PCU output voltages, it is clear that the telemetry signals are sensitive to variations in the output voltages.

Variations in input quantities are shown in Figure 3-3 and variations in the telemetry signals representing these input quantities are shown on Figure 3-4. Note the variation in the telemetry signal

Figure 3-2. Typical Telemetry Outputs for Thermal Instrumentation

Figure 3-3. Actual PCU Input Variations Over ALSEP Load Range

Figure 3-4. Telemetry Signals Representing PCU Input Parameters

representing input current. It is apparent that the correspondence between the two curves is poor at high input currents. This result confirms previous observations during the Integration Tests performed last Quarter.

The general conclusion from this study is that PCU telemetry information generally cannot be depended on when the PCU is operating beyond its regulating range.

A final summary report entitled "Summary Report of Compatibility and Performance Testing of the ALSEP Power Conditioning Unit (PCU) with the SNAP-27 Integrated Power Unit (IPU)" ANSO Document 6300-307, was released January 15, 1968. This report along with Addendum I describes details of the overall PCU and RTD telemetry circuit test program. Conclusions are that the PCU design is acceptable provided that certain changes now under consideration to improve the regulating range are implemented.

A shorting plug has been recently incorporated between the PCU and the IPU to enable the astronaut to mate the cable with the Central Station in an electrically inert state. This unit contains a 900 ohm ground resistor, an ammeter, a switch and two connector assemblies. Since a failure in this item could appear as a SNAP-27 IPU failure, an AEC review and buyoff procedure similar to the PCU, should be provided.

3.3 KENNEDY SPACE CENTER PRELAUNCH SUPPORT

3.3.1 PROCEDURES

Initial drafts of the following SNAP-27 KSC procedures were prepared and submitted to AEC/ALO for review:

FCA Prelaunch Loading on the Lunar Module

FCA Unloading from the Lunar Module

GLFC Receiving and Inspection

Receiving and Inspection of FCA at KSC

Storage of FCA at KSC

Removal of FCA from Ground Shipping Cask

Installation of FCA into the Ground Shipping Cask

FCA GSE Receiving and Inspection

FCA Fit Checks at KSC

GA Receiving Inspection

RTG Leak Rate Test

EFCS Receiving and Inspection.

Copies of the FCA/GLFC Prelaunch Installation Flow Chart were also submitted.

3.3.2 LM/SLA/IU MOCK-UP

Work was started at GE on a wooden mock-up of the section of the Apollo Space Vehicle directly involved with the on-board FCA loading procedure. The section of the space vehicle to be simulated is that encompassing the IU where the hatch is situated, the IU work platforms, the ladder leading to the SLA work platforms, the SLA work platforms adjacent to the GLFC required for loading the capsule, the SLA section with a 10 inch diameter port, the section of the LM for mounting the GLFC, and the LM plume deflector. The mock-up will be used to:

- a. Evaluate the completeness and accuracy of the capsule loading and unloading procedures which have been prepared, and to analyze the different problems associated with the two alternate methods of transporting the capsule to and from the GLFC location. The two concepts under study utilize the SLA 10 inch port and the IU hatch, respectively.
- b. Generate a time and motion study to assess the radiation exposure times which will be accrued by capsule handling personnel during the loading activities. This will determine the maximum likely exposure rates for different parts of the body, accumulated dosage and frequency of replacement of handling personnel in order to stay within safe limits.
- c. Assess the number of personnel required to perform this launch pad fueling/defueling operation.

The mock-up is expected to be completed by April 5, 1968.

3.3.3 IPU TEST CONSOLE TROUBLE SHOOTING PROCEDURE/SCHEMATICS

In response to a NASA request, the IPU Test Console schematics were redrawn on one sheet to provide greater clarity for trouble shooting purposes. In addition, a trouble shooting procedure was prepared.

3.3.4 OPERATIONAL MANUAL

A SNAP-27 Operational Manual for use at KSC is in process which will include descriptions of the SNAP-27 System hardware, methods of operation, shipping and receiving procedures, test procedures, storage, maintenance/trouble shooting procedures and operational procedures.

3.3.5 WALK-THROUGHS

A walk-through was held at Bendix on January 10, 1968, using a simplified mock-up of the SLA/LM/IU section affecting GLFC and capsule loading. Dimensionally, the mock-up was sufficiently representative to obtain a feel for obvious loading problems.

The walk-through was an integrated effort, in that both Bendix and GE exercised their respective procedures for loading the GLFC, the support structure/thermal shield and the simulated capsule. Highlights of the walk-through were:

- a. Considerable difficulty was experienced in mounting the support structure/thermal shield to the Grumman struts
- b. The GLFC/band assembly carrying method and its installation technique on the ALSEP support structure appeared acceptable
- c. The access through the SLA 10 inch port was verified as the best approach to capsule loading
- d. The alternate method for loading, where the SLA Transfer Cask with capsule are brought in through the IU and then lifted up onto the 525 platform proved unsatisfactory. Due to a redesign of the LM SEQ Bay door, there is now insufficient room for the SLA Transfer Cask on the 525 platform.

A second walk-through was held on February 5-8, 1968, at KSC using the KSC LM-3 mockup. Installation problems encountered with the ALSEP Support Structure/Thermal Shield were similar in nature to what had been experienced during the previous walk-through mentioned above.

The method for attaching this hardware to the Grumman support struts (using nuts and bolts) was apparently intended to be used before the SLA is installed over the LM, when the problem of lack of working space does not exist. A quick method such as pip pins, or some other quick-latching means, for securing the ALSEP Support Structure to the Grumman struts is apparently required.

No significant problem areas were observed as far as installation of the GLFC/Band Assembly to the support structure is concerned.

The capsule loading exercise produced no new problems not encountered previously during the walk-through at Bendix. The primary method of bringing the capsule into the SLA, i.e., through the 10 inch diameter SLA port using the Port Entry Trough, was again demonstrated to be preferable. The alternate method, i.e., lifting the SLA Transfer Cask up and placing it on the 525 platform was again verified as no longer practical due to interference from the new SEQ bay door.

Further study uncovered two other possibilities for bringing up the capsule via the IU. Both of these are closely allied to the alternate scheme previously found impractical. In both methods the SLA Transfer Cask is lifted aloft by two men standing on the 441 level platform to a point close to either the front or rear of the 525 level platform. The man standing on the 525 platform then removes the capsule from the SLA transfer Cask using the SLA Handling Tool and carries it over to the location of LM-mounted GLFC for insertion. These alternate methods were tried out and found to work quite satisfactorily. The GE procedure for capsule loading and unloading will be revised to reflect these alternate methods.

BLANK

4. IPU SYSTEM

4.1 GENERATOR ASSEMBLY

4.1.1 THERMAL ANALYSIS OF GENERATOR/FCA FIXTURE

Vacuum testing of a generator with a fueled capsule presents two problems due to the constant heat input and the ambient to vacuum and vacuum to ambient transitions; 1) the generator must be modified such that it can operate satisfactorily in both air and vacuum and 2) the generator's cooling transient during the vacuum to air transition (500°F to 300°F respective outer case temperatures) must be slow and controlled in order to preclude cracking of the outer case.

A fixture consisting of reflective baffles was designed and tested with an electric fuel capsule simulator. The baffles consist of three annular discs that were slotted to enable them to fit around the generator, 2, 4 and 8 inches from the bottom of the generator. They were designed to inhibit free convection cooling over the lower portion of the RTG. In a vacuum environment, the top of the generator normally runs cooler than the bottom, but during air operation this gradient reverses and the bottom runs cooler than the top. The baffles decrease the slope of these gradients and, consequently, reduce thermal stresses in the outer case. The axial temperature distribution in the outer case is shown in Figure 4-1 for Mod 8 and previous Mod 6 air tests. It may be seen in this figure that for the uncracked Mod 8 outer case, the baffles kept the gradient from the midplane to the bottom, below 90°F, compared with an estimated 150 - 180°F without the baffle. In addition to preventing large gradients during air operation, the baffles were designed such that they would not adversely affect the operation of the generator in a vacuum environment. To this end, the baffles were made of aluminum with low emissivity surfaces to reflect as much of the heat from the generator as possible. Also, they were positioned with a spacing that would not restrict the view between generator and sink more than was necessary. The axial temperature distribution in the outer case, with and without baffles, is shown in Figure 4-2 for vacuum operation. The average temperature of the generator is raised slightly by the presence of the baffles; however, the slightly lower electrical output of the generator was acceptable for test purposes.

Outer case thermal stresses would become excessive in an abrupt transition from vacuum operation to air operation as would occur in the usual mode of vacuum chamber venting. The sharp rise to

Figure 4-1. Axial Temperature Distribution of the Generator Outer Case during Air Operation with Convection Baffles in Place

Figure 4-2. Axial Temperature Distribution of the Mod 8 Generator Outer Case during Vacuum Operation with and without Convection Baffles in Place

atmospheric pressure in the chamber immediately adds the full value of free convection cooling to the radiation heat rejection of the generator. Even with the convection baffles in place, the sudden chilling of the fins could impose thermal shock on the outer case.

Since there could be considerable error in predicting the precise pressure at which convection would become significant, a conservative, controlled venting rate of one pressure decade per hour was chosen. To be further conservative, no significant convection effects were expected below a pressure of 0.01 torr and the controlled vent was started at that point. The chamber pressure rise transient is shown in Figure 4-3 and the effect that this slow increase in pressure had on the generator outer case temperatures is shown in Figure 4-4. The maximum outer case axial gradient may be seen by comparing the "Generator Mid-plane" curve with that for the top of the generator. Also, from an examination of Figures 4-3 and 4-4 it is seen that convection did not become significant until the chamber pressure reached 10MM of mercury.

The test confirmed the satisfactory performance of the baffle fixture in both ambient and vacuum conditions and the acceptability of the vacuum chamber controlled venting procedure.

4.1.2 GENERATOR HARDWARE STATUS

All flight generator assemblies successfully passed acceptance tests and were placed in storage during the first quarter of 1968. All generator assemblies were accepted by Sandia Corp. via Certificate of Inspection, then packaged in their shipping containers and again accepted by C.O.I. and DD 250. Generators are being stored pending FCA fit checks and receipt of shipping instructions from the AEC.

4.1.3 GENERATOR TESTING

4.1.3.1 Flight Generator Acceptance Testing

The fifth and final SNAP-27 Flight Generator, MOD 23, successfully passed acceptance testing.

Figures 4-5 and 4-6 illustrate the MOD 23 GA output power as a function of power input from the Electric Fuel Capsule Simulator (EFCS) for five different load conditions.

A summary comparison of the Flight Generator's performance is illustrated in Tables 4-1 and 4-2.

Figure 4-3. Vacuum Chamber Pressure vs Time
for Mod 8 Generator Venting Sequence

Figure 4-4. Mod 8 Fin Base Temperature History during Vacuum Chamber Venting Operation (Circumferential Averages)

TABLE 4-1. TEST SUMMARY FOR THE SNAP-27 FLIGHT GENERATOR ASSEMBLIES

OPERATING CONDITIONS			MOD 13	MOD 19	MOD 21	MOD 22	MOD 23
POWER INPUT	EQV. LOAD	SINK TEMP. (°F)	GA S/N 6320006	GA S/N 6320009	GA S/N 6320011	GA S/N 6320012	GA S/N 6320013
1505W	16 V	+170°F	69.8W	69.1W	68.2W	68.3W	70.7W
1455W	16 V	+170°F	67.1W	67.5W	66.0W	66.2W	67.9W
1415W	16 V	+170°F	64.3W	64.7W	63.2W	63.2W	65.0W
1505W	16 V	-280°F	72.5W	72.9W	71.3W	71.3W	72.9W
1455W	16 V	-280°F	68.8W	68.8W	66.7W	67.3W	68.9W
1415W	16 V	-280°F	65.3W	65.3W	64.0W	64.1W	65.1W
1450W	4.7 OHMS	AMBIENT	69.6W	69.7W	67.9W	69.1W	70.2W
TOTAL ACCUMULATED OPERATIONAL TIME (AIR & VACUUM) (HOURS)			550	593	581	640	571
OPERATIONAL TIME IN A VACUUM			240	264	256	303	233
FINAL GA LEAK RATE IN STD CC/SEC OF ARGON WHILE OPERATING IN A +170°F SINK AT 4.7 OHMS LOAD			2.50×10^{-6}	4.36×10^{-7}	1.09×10^{-6}	3.7×10^{-7}	LESS THAN 3.92×10^{-7}
STORAGE CONTAINER SERIAL NO.			6287007	6287004	6287006	6287005	6287003
TOTAL WEIGHT ~ POUNDS, (LESS PROTECTIVE CABLE SLEEVING).			27.83	27.77	27.96	27.86	27.80

TABLE 4-2. RTD TEMPERATURE (°F) SUMMARY FOR THE FLIGHT GENERATOR ASSEMBLIES

OPERATING CONDITIONS - 1505 WATTS PWR. INPUT, 16 V OUTPUT, LUNAR DAY (+170°F)								
FLIGHT GENERATOR ASSEMBLY	RTD IDENTIFICATION							
	R1-1	R1-2	R1-3	AVG.	R3-1	R3-2	R3-3	AVG.
MOD 13	1136	1122	1138	1132	486	468	477	477
MOD 19	1131	1152	1155	1146	486	462	466	471
MOD 21	1147	1170	1175	1164	475	465	464	468
MOD 22	OPEN*	1150	1152	1151	482	460	469	470
MOD 23	1149	1126	1141	1139	492	469	480	480

OPERATING CONDITIONS - 1505 W PWR. INPUT, 16 V OUTPUT, LUNAR NIGHT (-280°F)								
FLIGHT GENERATOR ASSEMBLY	RTD IDENTIFICATION							
	R1-1	R1-2	R1-3	AVG.	R3-1	R3-2	R3-3	AVG.
MOD 13	1077	1064	1077	1073	425	408	417	417
MOD 19	1071	1092	1095	1086	428	399	405	411
MOD 21	1080	1109	1114	1101	411	406	404	407
MOD 22	OPEN*	1091	1085	1088	420	400	408	409
MOD 23	1090	1066	1088	1081	432	407	421	420

OPERATING CONDITIONS - 1455 WATTS PWR. INPUT, 16 V OUTPUT, LUNAR DAY (+170°F)								
FLIGHT GENERATOR ASSEMBLY	RTD IDENTIFICATION							
	R1-1	R1-2	R1-3	AVG.	R3-1	R3-2	R3-3	AVG.
MOD 13	1114	1096	1118	1109	481	464	472	472
MOD 19	1104	1127	1128	1120	480	455	460	465
MOD 21	1116	1141	1143	1133	469	462	460	464
MOD 22	OPEN*	1123	1120	1122	476	456	464	465
MOD 23	1125	1103	1119	1116	486	465	475	475

OPERATING CONDITIONS - 1455 W PWR. INPUT, 16 V OUTPUT, LUNAR NIGHT (-280°F)								
FLIGHT GENERATOR ASSEMBLY	RTD IDENTIFICATION							
	R1-1	R1-2	R1-3	AVG.	R3-1	R3-2	R3-3	AVG.
MOD 13	1056	1043	1061	1053	418	402	410	410
MOD 19	1050	1070	1075	1065	419	391	396	402
MOD 21	1060	1085	1091	1079	404	400	397	400
MOD 22	OPEN*	1069	1065	1067	412	392	402	402
MOD 23	1066	1042	1061	1056	424	400	413	412

OPERATING CONDITIONS - 1415 WATTS PWR. INPUT, 16 V OUTPUT, LUNAR DAY (+170°F)								
FLIGHT GENERATOR ASSEMBLY	RTD IDENTIFICATION							
	R1-1	R1-2	R1-3	AVG.	R3-1	R3-2	R3-3	AVG.
MOD 13	1097	1086	1101	1095	476	460	468	468
MOD 19	1085	1107	1109	1100	475	451	456	461
MOD 21	1100	1124	1128	1117	464	456	455	458
MOD 22	OPEN*	1107	1105	1106	470	452	460	461
MOD 23	1107	1085	1101	1098	480	459	470	470

OPERATING CONDITIONS - 1415 W PWR. INPUT, 16 V OUTPUT, LUNAR NIGHT (-280°F)								
FLIGHT GENERATOR ASSEMBLY	RTD IDENTIFICATION							
	R1-1	R1-2	R1-3	AVG.	R3-1	R3-2	R3-3	AVG.
MOD 13	1035	1018	1035	1029	410	395	403	403
MOD 19	1030	1051	1053	1045	412	384	390	395
MOD 21	1040	1067	1073	1060	397	394	390	394
MOD 22	OPEN*	1047	1044	1046	407	386	395	396
MOD 23	1048	1023	1043	1038	418	394	408	407

RTD Location: R1-1 Hot Frame, A-28,C-1 R3-1 Outer Shell, A-11,C-1
 R1-2 Hot Frame, A-28,C-9 R3-2 Top of Fin #2
 R1-3 Hot Frame, A-28,C-17 R3-3 Outer Shell, A-25,C-17

* Replaced upon completion of testing.

Figure 4-5. Mod 23 GA Power Output vs EFCS Input (Lunar Day Conditions)

Figure 4-6. Mod 23 GA Power Output vs EFCS Input (Lunar Night Conditions)

The final test reports for each SNAP-27 Flight Generator Assembly have been issued. Their ANSO Document Numbers are as follows:

MOD 13	No. 6300-289
MOD 19	No. 6300-282
MOD 21	No. 6300-296
MOD 22	No. 6300-313
MOD 23	No. 6300-310

4.1.3.2 MOD 5 Generator

Figures 4-7 through 4-11 display the latest normalized test data for the Mod 5 generator. Test data from 0 to 5000 hrs were presented in Quarterly Report No. 9. During this most recent period two I-V mappings were completed - one after 7500 hours of vacuum testing (approximately 8100 hours of totaled elapsed test time), and one at one year of vacuum operation (total elapsed test time 9400 hours). In order to equalize the lunar day-lunar night operating time at end of one year simulated mission, the lunar day cycle was increased to three weeks and the lunar night cycle decreased to

Figure 4-7. Mod 5 Generator Normalized Power Output

Figure 4-8. Mod 5 Generator Normalized Open Circuit Voltage

Figure 4-9. Mod 5 Generator Resistance Ratio

Figure 4-10. Mod 5 Generator Internal Pressure

Figure 4-11. Leak Rate vs Time, Mod 5

one week. Presently, at 9900-hour total elapsed time, the test will be conducted for an additional 34 days at lunar day conditions to complete this day-night balancing.

As was predicted in Quarterly Report No. 9, an increased degradation rate was experienced due to the prolonged test time at lunar day conditions. Lowest power output was reported with 67.8w at 9400 hours for lunar day environment while after I-V mapping the power output is slightly up at 68.5w with a total elapsed time of 9900 hours.

This slight recovery stems most likely from the installation of a newly calibrated wattmeter at about 9600 hours with the deviation well within the expected test accuracy. The results of almost 10,000 hrs of operation on Mod 5 can be summarized as follows:

- a. For a 10,000 hour mission the optimum hot junction temperature is about 1100°F, as selected for SNAP-27 at maximum fuel loading.
- b. Considering the lowest output of 67.8w @ 9400 hours, the total degradation so far is about 4%, which was almost exactly the 67.4 watts predicted in Quarterly Report No. 7, July 1967. The I-V maps for the beginning of vacuum testing and after 9400 hr total test time are shown in Figure 4-12 and 4-13.
- c. The increase in thermopile resistance (about 10%) is partially compensated by an increase in hot junction temperature, yielding a small net degradation rate. This temperature increase is caused by reduction in Peltier heat absorption at the hot junction as the current flow decreases. The cold junction temperature is essentially unchanged. This mechanism explains the increasing open circuit voltage after 5500 hours and the constant power output between 5500 hours and 8000 hours.
- d. This increase in temperature - even though desirable for this short term mission, since it yields smaller effective degradation rates at the highest possible efficiencies, will ultimately lead to a self-aggravating situation, with the increased temperature increasing the sublimation rate of the N-material at the hot junction and vice versa. We can therefore expect an accelerated power degradation in the future, even though the power input will be slightly decreased from 1500w to 1485w after 10,000 hours to reflect the decay of the isotope fuel.

Figure 4-12. I-V Maps Before and After Life Test (Lunar Day Cycle)

Figure 4-13. I-V Maps Before and After Life Test (Lunar Night Cycle)

- e. Early test data indicated a leak with the pressure decreasing from about 22 psia at beginning of testing to about 15 psia after 5000 hours, see Figure 4-11. Since the pressure has not apparently stabilized even though the leak rate showed no significant changes, it is possible that the pressure transducer is defective. Only a post test analysis with a recalibration of this pressure transducer can clarify this point. It is interesting to note that two of the 104-couple modules, B6 and B12, showed similar behavior, and were traced to a drift in transducer calibration.

4.1.3.3 MOD 10 Generator

The power fluctuation which occurred between 2000 and 3000 hours of test time and which was attributed to troubles with the EFCS (See Quarterly Report No. 9) has disappeared completely after the installation of a new EFCS. The performance is very stable with no apparent degradation up to 5000 hours (Figures 4-14 through 4-16). From the experience gained on Mod 5 and the 10-couple modules, some degradation is to be expected in the near future beginning with a slight increase in internal resistance after 4500 hours.

The Mod 10 Qualification Life Test was interrupted to perform a magnetic evaluation of the IPU. This testing of the SNAP-27 IPU was performed at NASA-Goddard's Attitude Control Laboratory in Greenbelt, Maryland. The laboratory provided a magnetic environment which cancelled the earth's field and allowed measurements of the magnetic properties of the unit.

Figure 4-17 illustrates the magnetic evaluation data of the Mod 10 GA and the Mod 10 IPU along the +X axis. In the worst case, after a 15-oersted perm, the Mod 10 GA and Mod 10 IPU magnetic characteristics were approximately a factor of 10 lower than its maximum allowable level of 0.1 gamma at a distance of 50 feet.

4.1.3.4 Generator Mod 8B

Since the start of testing Mod 8B shows a somewhat erratic and unexpected behavior. It should be noted however that the Mod 8B thermopile was salvaged from the ill-fated generator Mod 8 which experienced a case failure during processing. Furthermore, a replacement aft hermetic seal with instrumentation feed-throughs and provision for a pressure transducer was not available during assembly and a qual-generator seal was used. This required that the instrumentation wires be cut off and the pressure transducer omitted. In short, Mod 8B is not an optimal unit and its performance can not be expected to be typical.

During the first 4500 hours of testing the generator showed a power degradation of about 3 percent (Figures 4-18 through 4-20). This was totally unexpected since the generator operated at a heat input of 1415w with an estimated hot junction temperature of only about 1045°F. The power decrease resulted from a decrease in open circuit voltage (See Figures 4-18 through 4-20). In addition, the thermopile resistance decreased, a very incongruous phenomenon. Since this could not be traced to a decrease in heat input it was deduced that internal shorts between the cut instrumentation wires must have caused this most unusual behavior. After 4500 hours the generator

Figure 4-14. Mod 10 Generator Normalized Power Output

Figure 4-15. Mod 10 Generator Normalized Open Circuit Voltage

Figure 4-16. Mod 10 Generator Resistance Ratio

Figure 4-17. Magnetic Evaluation Data of Mod 10 GA and Mod 10 IPU

showed a remarkable change in degradation pattern with the resistance increasing at a rate of approximately 4 percent per 1000 hours. Such degradation was experienced with generator Mod 5 at 1500w input and then only after about 9000 hours of operation. It should further be noted that the leak rate of the generator is perfectly normal (between 2×10^{-7} to 2×10^{-6} std cc/sec of argon)

4.1.3.4.1 Magnetic Test Fixture Evaluation with an FCA and MOD 8B GA - After the generator successfully completed the required 5000-hour I-V mappings, the life test was interrupted for utilization of the Generator Assembly in the following tests:

TR #6314-062 - Magnetic Test Fixture Evaluation with an FCA.

TR #6314-065 - Free Convection Baffle Test Utilizing an EFCS.

The first operational IPU test, with a mated, live FCA, was when the IPU operated successfully for four hours in air while mounted in the magnetic thermal shroud test fixture. Results of this test are explained in Paragraph 4.1.1.

The MOD 8B GA power output with an EFCS was 68.0 watts as compared to the IPU output of 70.0 watts for similar operating conditions. This was attributed to a difference in temperature profiles between the EFCS and the FCA.

Figure 4-18. Mod 8B Generator Normalized Power Output

Figure 4-19. Mod 8B Generator Normalized Open Circuit Voltage

Figure 4-20. Mod 8B Generator Normalized Resistance Ratio

4.1.3.4.2 Free Convection Baffle Test - The MOD 8B GA was next utilized to check out the convection baffles and venting procedure to be used when testing generators in vacuum with an FCA. Both the baffles and a slow vacuum chamber venting sequence are required to preclude excessive thermal stresses in the outer case of the generator during the initial insertion of an FCA into the GA, and in the transition from vacuum to air operation.

Utilizing an EFCS, the test verified that the baffles worked satisfactorily both in air and in vacuum, and that the chamber can be vented at the desired rate without over stressing an operating IPU outer case. Paragraph 4.1.1, "Thermal Analysis," shows the results of this test.

Also concluded from this test was the fact that the baffles have little effect on the operation of the GA as compared to tests without baffles for a vacuum environment.

4.1.3.5 104-Couple Module Testing

Table 4-3 shows the performance up to April 8, 1968. Since the data reduction on 21 August 1967, the output power listed are raw data and subject to correction for hot and cold junction temperature deviations.

Module 7 is still out of operation awaiting repairs to the test console.

Module 8 has apparently developed shorts, since both the power output and the internal resistance have dropped (similar to Mod 8B). The shorts may be either internal to the module or in the test equipment, and an investigation is in process.

Module 9, at 1100°F/525°F with xenon as the fill gas has continued to show extremely stable performance. All other modules have argon gas. Additional tests would be required, however, to establish if there is a significant effect of type of inert gas fill on stability of performance.

Module 10 is apparently showing a very high degradation rate. This will be investigated as time and funding allow.

Module 12 had been fairly stable up until the 2 April data scan when a power drop of 1.6 watts from the previous week appeared. This effect is also being investigated.

TABLE 4-3. 104-COUPLE MODULE PERFORMANCE SUMMARY

MODULE	TEST DESCRIPTION	300 HR. ACCEPT. TEST COMPLETION AT 3M	TEST START AT GE	INITIAL POWER*	MAX POWER	POWER @ 4/8/68++	ELAPSED TIME t (HOURS) 4/8/68
104B-6	Shock & Vibration 1100/525°F	11/14/66	12/7/66	15.7	16.5		2413 terminated
104B-7	Cycle Performance (on-off) 1100/525°F 17 cycles completed	11/30/66	12/19/66	16.2	17.3	16.3	5598 cycling terminated
104B-8	Lunar Cycle 1100/525-1045/470°F 20 cycles completed	1/25/67	2/15/67	13.7	15.9	12.2	8709 cycling terminated
104B-9	Long Term Stability 1100/525°F	1/11/67	2/8/67	15.1	17.2	16.9	9547
104B-10	Efficiency 1100/525°F	1/27/67	3/1/67	15.3	17.5	14.5	9872
104B-11	Off Des. Hot Junction 1130/525°F	2/1/67	3/24/67	17.5 ⁺	19.5	16.0	8571
104B-12	Long Term Stability	2/8/67	3/24/67	16.2	17.5	14.1	9155
104B-13	Cycle Performance (on-off) 1050/525°F 10 cycles completed	2/24/67	4/7/67	16.2	16.9 ⁺	13.6	8600 cycle terminated T _H red. to 1050
104B-14	Off Des. Hot Junction 1050/525°F	2/16/67	4/14/67	16.0 ⁺	13.5	13.0	8961
104B-15	High Spring Pressure	3/3/67	7/26/67	17.1 ⁺	17.1 ⁺	14.6	6492
104B-1	Off Des. Hot Junction 1030/525°F	3/10/67		15.7			314
104B-2	Efficiency with 4-Zone Heater 1070/525°F	3/3/67	3/31/67	16.5 ⁺	17.0 ⁺	15.6	6897
104B-3	Off Des. Hot Junction	3/17/67	**	16.7			316
104B-4	Off Des. Hot Junction	3/31/67	**	14.9			303
104B-5	Off Design Pressure	4/7/67	**	15.1			335

* Acceptance Test at 3M

+ At 1100/525

** Dependent upon test equipment availability

++ Since data reduction was terminated on 8/21/67,
these are raw power data, subject to slight
temperature variation

Modules 2, 13, 14 and 15 have shown stable performance over the last 2100 hours of operation.

4.1.3.6 10-Couple Module Testing

The 10-couple module data are summarized in Table 4-4. Since the detailed data reduction was terminated in August, 1967, the data presented are only spot checks where certain scatter cannot be eliminated.

Module C16 with 5 psia internal gas pressure has continued to show a high degradation rate exemplifying the importance of gas pressure on performance. The rate of degradation at 5 psia and 1100°F/525°F is even greater than the rate at 1200°F/525°F and 25 psia.

The other modules appear to be showing stable performance or normal degradation rates.

4.2 FUEL CAPSULE

4.2.1 DESIGN AND ANALYSIS

4.2.1.1 Structural Analysis of Closure Welds

During this quarter, General Electric performed a structural analysis of the capsule dome end closure weld under launch environments. This study evaluated a 0.012 inch lack of penetration (at the inner corner of the male step) for a 35 degree arc simulating the most severe interpretation of the ultrasonic indications seen on FCA No. 2. Key assumptions used in the analysis were:

- a. The Graphite LM Fuel Cask (GLFC) will be subjected to a maximum ± 8 g sinusoidal level to 100Hz per the existing specification. There is a possibility that the amplification through the Bendix structure may significantly exceed these levels.
- b. The capsule internal pressure at launch will be that corresponding to a two-year storage period.
- c. Corrections for notch sensitivity are applicable.
- d. The adjacent liner wall produces a beneficial situation.

TABLE 4-4. 10-COUPLE MODULE PERFORMANCE SUMMARY

MODULE	STRING	TEST DESCRIPTION	TEST START	INITIAL POWER	MAX POWER*	ELAPSED TIME @P _{MAX}	POWER P/P _{TH} 2/28/68	ELAPSED TIME t (HOURS) 2/28/68
B1	odd even	1100/525	5/27	.965 .955	.97 .975	3500	terminated	2206
B2	odd even	Short Term Stability 1100/525	5/22	.93 .98	1.035 1.033	3500	.88*** .88	15,412***
C3	odd even	1100/525	6/9	.975 .945	.98 .945		terminated	
C4	odd even	Short Term Stability 1100/525	6/10	.99	1.030	3500	.83 .81	14,976
C5	odd even	Off Des. Hot Junction Temp. 1130/525	8/29	1.025 .945	1.095 1.093	400	.71 .74	13,054
C6	odd even	Off Des. Hot Junction 1030/525	8/29	.95 .95	1.05 1.055	500	.81 .81	13,122
C7	odd even	Off Des. Hot Junction Temp. 1050/525	9/22	.925 .81	1.035 .900	2000	.97 .83	12,477
C8	odd even	Off Des. Hot Junction Temp 1050/525	9/22	.98 .96	1.07 1.055	2000	1.01 1.02	12,477
C9	odd even	Off Des. Hot Junction Temp. 1200/525	10/11	1.035 1.05	1.05 1.05	0	.75 .69	12,012
C10	odd even	Off Des. Hot Junction Temp. 1200/525	10/21	1.03 1.03	1.09 1.055	300	.80 .75	11,698
C11	odd even	Lower Gas Pressure 16 psi 1100/525	10/13	.9 .95	1.03 1.025	750 1500	.80 .80	11,973
C12	odd even	Lower Gas Pressure .5 psi 1100/525	11/3	.77 .91	.80 .915	500 200	terminated	
C13	odd even	Lunar Cycle	1/4	.80 .82	.91 .90	1600 1800	.81 .80	10,006
C14	odd even	Spring Pressure 250 psi 1100/525	2/15	1.06 1.02	1.12 1.12	900 900	1.02 1.02	9,062
C15	odd even	Spring Pressure 250 psi	1/31	.94 .72	1.12 .8	1250 2000	.85 .86	9,738
C16	odd even	Lower Gas Pressure 5 psi 1100/525					.710** .794**	4,150**
C17	odd even	Lunar Cycle	1/4	.99 .94	1.08 1.06	2000 2000	.93 .91	9,922
C18	odd even	1100/575	1/6	.92 .95	1.12 1.12	2200 2200	.94 .92	9,939
C19	odd even	1100/625	2/15	.93 .91	1.10 1.09	1000 800	1.00 .92	9,517

* Normalized to Theoretical Value Based on 3M Published Data for TPM 10 and TPM 15.

** Data of 2-14-68

*** Data of 3-15-68

However, since the launch loads may be increased in the near future dependent upon results of current Bendix test programs, and the dynamic analysis of the FCA in the GLFC has not yet been substantiated by test, the interpretation of the results is questionable. It should be noted that the prefueling helium retention was not considered in the analysis. Also, there is a limited amount of data related to notched specimens of Haynes-25 alloy subjected to stress-strain cycles at elevated temperatures. Since, in addition, the effect of aging on crack propagation and the true effect of the liner and fuel are unknown, no firm conclusions can be drawn.

Although the actual effects of launch loads on the fuel capsule will not be known until integrated vibration testing is completed utilizing the Bendix structure, some credence of the analytical model was established by the FCA vibration testing described in Paragraph 4.2.3.1.1. A simple vibration test of the FCA without the GLFC is being planned to further validate the analytical model.

Although the results of this structural analysis showed a positive margin, the uncertainties of the analysis and system behavior indicated the need for a weld substantiation program as described in Paragraph 4.2.3.1. Analysis of the fuel capsule capability to meet mission requirements, as discussed in Paragraph 4.2.1.2 is based on the launch loads resulting from the analytical model.

4.2.1.2 Capsule Capabilities in Various Abort Situations

The fuel capsule cladding integrity during the following abort situations was analyzed:

- a. Pad abort-Saturn V fireball/afterfire
- b. Earth orbital decay reentry
- c. Superorbital reentry (down angles of 6.25, 20, and 38.05 degrees).

These analyses were based on the GLFC with the prior silicon dioxide secondary heat shield. All cases were analyzed for different initial boundary conditions corresponding to varying durations of storage in the ground shipping cask prior to launch. The investigation centered around the stress rupture life and ultimate strength of the cladding for the abort conditions. Fuel capsule failure in this analysis is defined as the rupture of the half-capsule cladding.

The analyses presented the following conclusions:

- a. If there is a capsule failure, the midsection ruptures prior to the half-capsule cladding rupture.
- b. The limiting re-entry case is earth-orbital re-entry, with clad rupture due to internal pressure and decreasing clad strength. For the one and two-year storage cases, the FCA ruptured when the clad reached 2190°F and 2080°F, respectively.
- c. The FCA would not survive a launch pad fireball and after-fire. For the one-year storage case, the FCA would rupture in about 36 minutes of afterfire, at a temperature of 2120°F. For the two-year storage case, the FCA would only survive about 16 minutes of afterfire to a clad temperature of 2060°F.
- d. In all re-entry cases, the deceleration stresses on the fuel capsule are not critical. The peak of 210 g's for super-orbital re-entry of 38.05 degrees down angle, occurs well before peak heating.

The fuel capsule clad integrity was re-analyzed in a similar manner for the following special conditions:

- a. A beryllium secondary heat shield replacing the silicon dioxide heat shield in the GLFC.
- b. Oriented side-on re-entry (no spinning or tumbling).
- c. Helium retention for 225 days prior to encapsulation.
- d. For earth-orbital decay, as the worst case with 2 years ground storage.

These analyses presented the following conclusions:

- a. The FCA is capable of withstanding an earth-orbital re-entry peak clad temperature of 2050°F.
- b. This maximum allowable peak clad temperature is independent of whether the GLFC re-enters in oriented or non-oriented side-on attitudes.
- c. The maximum clad temperature in a launch pad fireball is 1900°F dome end with a maximum during the afterfire of 2027°F at the midsection.

4.2.1.3 Effect of Helium Retention

The allowable ground storage time for a FCA is governed to some extent by retention of helium in the fuel prior to encapsulation, since pressure-induced stresses are affected. For purposes of determining a storage time limit the following worst case assumptions are considered necessary, since detailed understanding of this retention phenomena and ramifications are incomplete at this time:

- a. 225 days elapse between fuel spheroidization and final encapsulation.
- b. All helium generated subsequent to spheroidization is retained in the microspheres until after the time of encapsulation.
- c. All retained helium is released after encapsulation and contributes to increase internal pressure on the clad at launch.
- d. Reduction of resultant margin-of-safety for the FCA center section to zero is the limiting criteria for determining FCA storage time limit.

The conclusion of this analysis (See Figure 4-21) is that the FCA has a ground storage time limit of 31 months from time of fueling.

This conclusion is necessarily based on extremely limited data on SNAP-27 fuel helium retention and launch loads as derived from the analytical model described in Paragraph 4.2.1.1. As better loads definition and further knowledge of helium retention and release rates are obtained, the storage time limit for the SNAP-27 can be reviewed.

4.2.1.4 Evaluation of Welds

As a result of the nondestructive and destructive testing performed, it is concluded that both ultrasonic testing and tangential radiography techniques should be utilized to determine fuel capsule closure weld acceptability.

Some of the limitations of the existing ultrasonic testing techniques appear to be:

- a. Defects cannot be classified as to type or configuration, and layered or multiple linear type defects may appear as a single indication.

Figure 4-21. Margin of Safety at Capsule Center Section

- b. The limiting detectable size of defects has not been clearly established.
- c. Defects are not being accurately located.
- d. Ultrasonic standards are not completely representative of all types of defects encountered in welds.

The following, normally occurring, structures in welded Haynes-25 alloy do not appear to register as defects when tested ultrasonically:

- a. The weld interface between weld overlays.
- b. Coherent material in grain boundaries.
- c. Columnar structure in the solidified weld puddle.
- d. Odd-shaped weld underbeads.
- e. Combinations of different size grains.

Voids, cracks, layered microfissures and mechanically closed but unfused joint interfaces appear to be detectable by ultrasonic testing.

Defects detected by radiography (x-rays normal to the test piece) appear to be detectable by ultrasonic testing. However, ultrasonic testing locates defects that are not resolvable by "straight through" radiography. "Tangential radiography" (the method used to radiograph SNAP-27 fueled capsules) does not define defects as clearly as "straight through" radiography. "Straight through" radiography identifies defects as small as 0.005 inch regardless of orientation within the thickness of the weld while defects as small as 0.010 to 0.020 inch can be located by "tangential radiography", if the defect is positioned in the top half of the weldment. The latter method, however, may be instrumental in identifying some defects in fueled capsule welds that are detected, but not classified, by ultrasonic testing.

4.2.1.5 Capsule Coating Test

During this quarter the long life capsule coating test was completed. Six Haynes-25 emissivity test strips were plasma arc sprayed with Radifrax 356 to an emissivity of 0.89 at GE-Vallecitos and shipped to GE/MSD for testing. These specimens were then subjected to seventy-two hour room temperature to 1200°F cycles for a total of 35 cycles. All specimens survived this test. A check showed the emissivity to have increased to about 0.91.

One of the six specimens was then subjected to 4986 additional hours in 10^{-7} torr vacuum and cycled between 1200°F and 1400°F. Of the 4986 hours, 3500 were at 1400°F. The emissivity after completion of test measured 0.91; a microphotograph of the test specimen after the entire 7488 hours is shown in Figure 4-22. The surface of the Haynes-25 had been affected for a depth of approximately 0.002 inches. However, this condition appears no worse than uncoated Haynes-25 subjected to similar vacuum conditions at 1400°F to 1600°F. The 0.002 inch attack after approximately 7500 hours should not present a problem, considering the total clad thickness of 0.060 inch.

Coating adherence was excellent. The affected zone on the coated Haynes-25 specimen is much like that exhibited by uncoated Haynes-25 in hard vacuum at high temperatures ($>1400^{\circ}\text{F}$), and therefore, this affected zone could not be a diffusion zone caused by any reaction between the coating and substrate. The coating appears unaffected and unchanged in both thickness and appearance.

Figure 4-22. Coated Haynes-25 Emissivity Test Strip after Air and Vacuum Cycling (1200 to 1400°F)

4.2.2 MOUND LABORATORY AND GE-VALLECITOS LIAISON

4.2.2.1 Mound Laboratory Liaison

4.2.2.1.1 Capsule Status

- a. Capsule No. 1 - Since additional radiography in the suspected area of the forward closure weld failed to confirm the indication determined by ultrasonics, the capsule was reshipped to GE-Vallecitos for final processing prior to shipment to GE/Valley Forge for limited acceptance testing.

- b. Capsule No. 2 - Gamma and neutron dose rate and spectra measurements of Capsule No. 2 installed in a generator assembly were performed this quarter.

Simultaneously, Mound Laboratory conducted a Teflon/fuel compatibility study which indicated that Capsule No. 2 could be utilized without any detrimental effects being created by the Teflon. The results of Mound's metallographic and spectrographic analysis showed that the Teflon would be tied up with the fuel form without endangering the capsule clad integrity. The capsule was therefore released for shipment to GE/Valley Forge for limited acceptance testing, excluding any dynamic environmental testing. The brass nuts installed at GE-Vallecitos to temporarily secure the capsule backplate to the capsule were replaced with the prime stainless steel lock nuts at Mound.

- c. Capsule No. 3 - The first pre-example weld wandered and missed the joint for a distance of approximately .625 inches. This condition occurred approximately 140° from the start; the weld in the area of the start and stop appeared acceptable. After cleaning of the weld head and electrode replacement, Mound successfully welded an unofficial sample weld and proceeded into the normal welding sequence of pre-example welds. Both official pre-example welds were acceptable and the flange-to-center section closure weld was performed. Weld bead wander was experienced on the following weld, the dome-to-center section closure weld. The joint was missed resulting in weld leakage. Even though it is a Mound Laboratory policy not to perform rewelding, a joint decision was made to perform a re-weld since the hardware was already committed and Mound stated they had previous experience with double welds on SNAP-27 type joints which would be available for General Electric review. In addition, this decision was made on the availability of ultrasonics and tangential radiography to uncover detrimental areas. The resulting double weld decreased the leakage to within specification requirements. Weld wander was again seen on the weld immediately following the first dome-to-center section weld.

The example welds for the third capsule, including two with double weld beads, were sent to GE-Vallecitos for ultrasonics inspection where numerous indications were noted. Straight through radiography and extensive metallography in the ultrasonic signal areas was then performed by Mound,

reporting on February 28 little or no correlation between actual defects verified by metallography and ultrasonic indications. This was generally in disagreement with GE's findings on the test piece reported in Paragraph 4.2.1.4. The reason for the lack of correlation between ultrasonic indications and actual defects as reported by Mound is still unknown. GE is using ultrasonics to determine weld defects in the Weld Substantiation Program reported in Paragraph 4.2.3.1 and will have additional correlation data, supplemented by radiography, by the end of the next quarter. Mound has been performing additional work in an attempt to establish the limitations and capabilities of tangential radiography.

After repeated rejection of Series IV liner heads by Mound, it was agreed that Mound would rework the heads thereby removing the defects which Mound felt were detrimental to welding.

Mound also attempted to perform Radiant Heat Capsule welding and missed the flange to center section weld joint on the first Radiant Heat Capsule. The liner could not be removed from the center section assembly but the flange section could be easily removed. Since it appeared that the liner was completely welded to the cladding and would not be suitable for test, the welding was terminated. Welding will be resumed following certain improvements in welding techniques.

4.2.2.1.2 Fuel Liaison - During the period January through March 1968, the fuel liaison effort was directed to investigation of helium retention in fuel.

When the alpha-particles produced in the radioactive decay of ^{238}Pu acquire two electrons, they become neutral helium atoms. The significance of a substantial helium inventory retained in the fuel prior to encapsulation is discussed in Paragraph 4.2.1.3. It can be noted here that for fuel life in excess of about 180 days (225 days for Capsules 1, 2 and 3), prior to encapsulation, a quantitative accumulation of helium retained in the fuel would limit the storage time available.

The SNAP-27 capsule was designed on the basis of Mound Laboratory data (MLM1270, pp. 77-79) indicating that helium was quantitatively released as it was formed and was not retained in the material. It was assumed, on the basis of the Mound data, that there would be effectively no inventory of helium in the material at the time of encapsulation. Based on experience with retention of fission gases in ceramic fuels and with retention of helium in irradiated BeO, even at temperatures up to 1200°C, there was some question as to the correctness of this opinion. It was postulated, however, that over long periods various mechanisms would permit quantitative release of helium.

The release of helium formed in the fuel crystal structure is a multi-variant phenomenon depending at least on temperature, pressure, effective particle radius, diffusion coefficient, composition and age.

During the past six months, the possibility of helium retention has been investigated by Mound Lab., Los Alamos Scientific Lab., Oak Ridge National Lab and Sandia Corporation. Initial results of these investigations were presented in January at a meeting at Sandia. The test results are derived from small, incompletely characterized samples and conclusions from these data must be regarded as preliminary. The analysis presented by Sandia based on classical diffusion theory is in agreement with similar analyses by GE-VNC and others. The practical application of these analyses for prediction of helium inventory in a specific batch of fuel are unfortunately dependent on empirical data currently unavailable, e.g., the effective radii of the fuel. Despite these limitations on both analyses and experimental data, Sandia has verified the existence of a temperature threshold, and this represents the only currently available approach to the problem. Table 4-5 summarizes the helium release rates measured at various temperatures as defined on a single 1 gram batch of $^{238}\text{PuO}_2$ microspheres.

Because of the new information on helium retention, GE-MSD in negotiating the contract in February, stipulated that fuel would not be acceptable if it were more than 180 days old (225 days for Capsules 1, 2 and 3) after processing or after suitable treatment to remove retained helium. This limitation was based on the contractual obligation to design for the two year storage life prior to launch.

4.2.2.2 GE-Vallecitos Liaison

Following the decision to use FCA No. 1 for non-dynamic acceptance testing, the capsule was shipped from Mound, arriving at GE-Vallecitos on January 22, 1968. The capsule processing was completed successfully and the capsule was shipped to GE/Valley Forge on February 2, 1968.

TABLE 4-5. MOUND LABORATORY HELIUM RELEASE RATE DATA

(Generation Rate: $1.8 \times 10^{-8} \text{cm}^3\text{-sec}^{-1}\text{-g}^{-1}$) Sample Size: 1 Gram 3 Months Old		
Exposure Time Hours	Temperature °C	Averaged Release Rate $\text{cm}^3\text{-sec}^{-1}\text{-g}^{-1}$
96	25	5.8×10^{-10}
96	260	2.04×10^{-9}
72	540	9×10^{-9}
216	810	1.4×10^{-8}
768	810	5×10^{-9}
Recycled to Ambient Then Re-exposed		
2	260	3.9×10^{-11}
2	540	4.2×10^{-10}
2	810	4.8×10^{-9}

In addition to the ultrasonics indication seen earlier, two other deviations occurred. Hot dimensional inspection of the coated capsule was not performed and eight emissive coating passes rather than five were required to establish the required coating thickness. The coating emissivity met requirements. The coated capsule was accepted dimensionally, based on the results of the dimensional inspection performed in the uncoated condition.

The majority of work performed during this quarter involved ultrasonics testing and its relationship to the SNAP-27 capsule. A meeting was held at GE-Vallecitos on January 11, 1968 to discuss the ultrasonic abnormalities found in the first two fuel capsules. On January 29, another meeting was held at GE-Vallecitos to review the ultrasonics data from the six example welds for FCA No. 3.

GE-Vallecitos also performed ultrasonic inspection of four electron-beam weld center section assemblies, twelve closure weld ring samples for fatigue testing (see Paragraph 4.2.3.1), Mound mockup hardware,

and two verification capsules which they also coated and delivered to GE/Valley Forge.

4.2.3 TESTING

4.2.3.1 Weld Substantiation Program

The objective here is to obtain basic materials data for clad weld behavior under typical capsule environmental conditions. This information will be used to substantiate analytical study assumptions and will help to evaluate the acceptability of fuel capsules No. 1, No. 2 and No. 3 which have indications of anomalous conditions in the closure welds. The program as originally proposed consisted of three phases:

- a. Part I - Vibration of a series II dummy fuel capsule inside a GLFC and dynamic testing of welded tubular samples to obtain fatigue data.
- b. Part II - Modal vibration testing of a capsule with simulated fuel independent of a GLFC.
- c. Part III - Plane strain testing of welded test specimens to augment data obtained by Sandia testing of welded and unwelded material.

Approval has been received to proceed with Part I of the program and Parts II and III are being negotiated.

4.2.3.1.1 GLFC/FCA Vibration Test - A sinusoidal and random vibration test of an instrumented, series II dummy fuel capsule inside a graphite LM fuel cask (GLFC) under room ambient conditions was performed to evaluate dynamic loads experienced during launch environments and to verify dynamic analysis. The test was performed with the GLFC and capsule supported and shimmed to simulate actual flight conditions. Preliminary results indicate that the accelerations and stresses are most severe along the "z" axis (lateral movement in the horizontal plane). Results of the tests agree favorably with the analytical predictions.

The fundamental capsule resonance, where the capsule vibrates on the GLFC support structure, varies with the input acceleration due to free play between the support structure and the capsule. High transient accelerations were evident as the capsule impacted with the support structure. These indications were evident on all accelerometers. The high frequency impact transient appears to be on the order of 2000 cps.

The interpretation of the capsule strain gage data is difficult due to the impact phenomena and resulting noise in the instrumentation system. Vibration testing of a capsule (Part II of the program), that is unrestrained by the GLFC and supports, is required before a meaningful interpretation of the FCA/GLFC data can be made.

4.2.3.1.2 Fatigue Testing of Tubular Weld Specimens - Defect indications have been ultrasonically detected in the closure-welds of SNAP-27 fuel capsules. The nondestructive test could not determine the nature of the defects but unfused joints, porosity or cracks are suspect. The effect of the defects on capsule performance has been calculated but assumptions used must be verified by test before the data can be considered meaningful.

Twenty-four tubular weld test specimens (Figures 4-23 and 4-24) have been fabricated, aged, radiographed, ultrasonically tested and welded into mandrels for fatigue testing by flexural mode on a hydraulically operated Materials Technology Incorporated machine. This machine is capable of high or low cycle oscillating stress operation and has a capacity of 10,000 pounds (Figures 4-25 and 4-26). The frequency is a function of the amplitude and operation is controlled by servo-loop mechanism.

The 1350°F testing temperature is provided by a "clam-shell", nichrome wire-wound heater enclosed in a ceramic holder. Control of the furnace is provided by an iron-constantan thermocouple attached to the specimen at the neutral axis. An atmosphere of 400 psi helium gas is maintained in the cavity of the tubular specimen during testing. A weld failure is considered to occur when a helium pressure drop or a sudden load decrease is indicated, whereupon the system is automatically shut down.

Weld defects, detected radiographically or ultrasonically, are positioned on the maximum stressed axis of the test specimen. Strain gages, attached to the area of interest, indicate the amount of stress applied.

Testing is in process and will be reported again in the next quarterly report.

4.2.3.1.3 Plane Strain Testing - Sandia is currently determining the fracture toughness of unwelded and welded solution annealed SNAP-27 Haynes-25 alloy that is aged:

- a. 100 hours @ 1230°F and 32 additional hours @ 1350°F (simulate flight and capsule conditions).

Figure 4-23. Tubular Weld Test Components

Figure 4-24. Tubular Weld Test Specimen Assembly

Figure 4-25. Test Rig Tubular Weld Specimen Test, Front Elevation

Figure 4-26. Test Rig Tubular Weld Specimen Test, Side Elevation

- b. 128 hours @ 1230°F and 80 additional hours @ 1350°F (simulate qualification capsule condition).

Testing of the aged, but unwelded material is completed. Results for an infinite flat plate show that the fracture toughness (Figure 4-27) is affected more by testing temperature than by aging treatment; the toughness is lowest at room temperature, increases progressively as the testing temperature is raised to 850°F and regresses moderately as the temperature is increased to 1350°F. The Sandia test data further indicates that critical crack length of four to five inches can be sustained at room temperature before the rupture strength of the unwelded clad material is affected (Figure 4-28). Applicability to SNAP-27 FCA is to be determined.

4.2.3.2 FCA Acceptance Tests

Fuel Capsule Assemblies 1 and 2 have completed processing at Vallecitos and have been conditionally accepted by Sandia Corporation. Both FCA's have successfully passed emissivity requirements as verified by testing of coating samples at GE-Valley Forge. Receiving Inspection, Thermal Mapping, and Leak Tests have also been completed and witnessed by QC at GE-Valley Forge. FCA No. 3 is at Mound Lab and is scheduled to be at GE-Vallecitos for coating application and NDT early in the second quarter.

On February 9, 1968, FCA No. 1 was removed from its GSC in accordance with SI 249178, "Acceptance Test Plan for Thermal Mapping, Helium Leak Check and Flange Weld Inspection of the SNAP-27 Fuel Capsule Assembly," to complete these acceptance tests described therein. The FCA was placed into the thermal mapping vacuum test chamber and pump down of the chamber continued for eight hours in an attempt to reach a test pressure of 1×10^{-5} torr or less. The specified test pressure was not reached and the test was aborted after eight hours. The problem was traced to the outgassing of the Min-K insulation block. Subsequent Min-K blocks will be outgassed on a component basis prior to installation in the FCA.

On February 16, 1968, FCA No. 1 was once again removed from its GSC in accordance with SI 249178, and the acceptance tests described there were performed with the following results:

- a. The helium leak rate was 1.96×10^{-8} std cc helium/second

Figure 4-27. Fatigued and Side Grooved V-notched Modified Charpy Test Specimen (Unwelded)

Figure 4-28. Fatigued and Side Grooved V-notched Modified Charpy Test Specimens (Unwelded)

- b. The thermal map of FCA No. 1 is as listed below:

Distance from FCA Dome in Inches	Circumferential Average 3 Points 120° Apart (°F)
.3	766
1.0	874
4.5	996
8.0	960
11.5	987
15.2	785

The above data are in the raw form. Correction factors are presently being formulated, and corrected data will be presented in the next quarterly report.

- c. The visual flange weld inspection of FCA No. 1, utilizing the Questar telescope, indicated no visual discrepancies in the weld joint.

4.2.4 FCA Component Status

a. Hardware shipped during 1st quarter

1. Miscellaneous Liner Tubing for F-line setup at Mound.
2. Tubing Assemblies for Radiant Heat Capsules at Mound.
3. Three capsules for F-line walk thru at Mound.
4. Replacement unit for SN 19 center section at Mound.
5. Four Weld Test Specimens for Ultrasonic Testing at GE-Valecitos.
6. All liner components for 5th and 6th Capsules to Mound.
7. One walk-thru capsule to GE-Vallecitos.

b. Hardware Status

1. Center Sections designated for FCA No. 4 were recalled from Mound because of a possible discrepancy. GE QC will request cancellation of Sandia acceptance on these units and will initiate MRB action. Backup units remaining from FCA Nos. 1, 2 and 3 will be used for FCA No. 4 fueling.
2. Cladding sets for FCA Nos. 5 and 6 will be presented for Sandia acceptance during the first week in April.

3. Undersize Cladding components were reworked and are now at GE-Vallecitos for NDT. Acceptance would provide center sections for four more capsules.
4. A replacement radiant heat center section is at GE-Vallecitos for NDT. The first unit was scrapped at Mound Laboratories during welding.
5. All cladding and liner material is being inventoried pending Program Office direction as to dispositioning of remaining FCA hardware.
6. Verification Capsules have been received and are awaiting test definition from engineering.

4.3 SUPPORT EQUIPMENT STATUS

4.3.1 FLIGHT HANDLING TOOL

All Flight Handling Tools have completed acceptance tests, have been accepted by Sandia and are in storage awaiting shipping instructions from the AEC.

4.3.2 GROUND HANDLING TOOL (GHT)

Acceptance tests were completed on last two Ground Handling Tools. All GHT's have been accepted by Sandia and are now in storage, awaiting shipping instructions from the AEC.

4.3.3 ELECTRIC FUEL CAPSULE SIMULATORS (EFCS)

All deliverable EFCS have been previously accepted and are in storage awaiting shipping instructions.

4.3.4 SLA TRANSFER CASK

The qualification unit was subjected to acceptance tests. Prior to starting the qualification tests, a requirement arose for the use of this cask during the magnetic tests at NASA-Goddard on the qual IPU.

The cask was therefore used to move the capsule from the AEC van to the inside of the building where the tests were to be run. At the completion of the tests, it was noticed that some of the Pyromark high temperature paint from the inside surface of the SLA Transfer Cask cavity had come off on the fuel capsule. The capsule had apparently been lifted up at a slight inclination which resulted in

contact between the surfaces of the capsule and cask I.D. As a result, a search for a new coating was made. Tests on samples indicated that a ceramic paint, Lithoid, possessed good thermal and abrasion resisting properties. The cavities of all prime casks will be finished with this coating.

In addition, all stainless steel parts on the cask were passivated and aluminum parts alodined to provide corrosion resistance.

4.3.5 SLA HANDLING TOOLS (SHT)

All five SHT's completed acceptance tests, were accepted by Sandia and are in storage awaiting shipping instructions from the AEC.

4.3.6 PORT ENTRY TROUGH (PET)

Both PET's were received and inspected during the first quarter of 1968. However, they were returned to the vendor for modifications to incorporate the latest design configuration. GE Vendor Surveillance will visit the vendor during the 1st week in April to accept delivery.

4.3.7 SLA INSPECTION TOOLS (SIT)

All SIT's have been accepted by Sandia Corporation and are in storage.

4.3.8 SHIPPING CONTAINERS

One GLFC Shipping Container has completed Qualification Tests. Containers for flight units are in process at the vendor.

Shipping Containers for all remaining items have been accepted and are in storage with the items they are designed to contain.

4.3.9 M8 & M9 FINAL TRAINING MOCKUPS

All hardware for the M8 and M9 Mockup systems are in process and scheduled to be presented for Sandia Acceptance during the first week in April.

4.3.10 GROUND SHIPPING CASKS (GSC)

All Ground Shipping Casks have been previously accepted by Sandia/AEC. However, all units, with the exception of GSC No. 5, need rework to update them to Revision S, AN 15 which is the latest configuration.

The status of each cask is as follows:

GSC No.	Present Configuration	Location	Use
2	Rev. J, AN 9	GE	FCA No. 2
3	Rev. R, AN 14	GE	FCA (Backup)
4	Rev. L, AN 11	Mound	FCA No. 3
5	Rev. S, AN 15	GE	FCA No. 1
6	Rev. R, AN 14	GE	Being reworked
7	Rev. R, AN 14	GE	Being reworked

The design modifications made to the GSC for improved operability were:

- a. A shot reservoir was added to the shot fill line. The shot reservoir holds an additional 150 grams of the nickel particle coolant which compensates for particle packing during handling and transportation vibration by settling.
- b. The six copper guide rollers were removed from the GSC cavity and replaced by stainless steel plugs. Operational experience indicated that the rollers tended to leave traces of copper on the capsule surface. Since the need for these rollers was not pressing, no affect will be seen in FCA insertion and removal operations.
- c. Washers were added to the ten GSC top plate studs for the cover assembly. These washers prevent the chipping of the nickel plate in the proximity of the cover stud holes while applying torque to the nuts.

BLANK

5. GRAPHITE LM FUEL CASK

The major effort during this quarter consisted of redesign and analysis of the secondary heat shield because of fabrication problems and minimal margins under dynamic load, engineering tests of the GLFC assembly, hardware procurement, and systems engineering (See Section 3).

5.1 DESIGN STATUS

The critical design activities during this quarter were devoted to:

- a. Establishing a back-up Silicon Dioxide Secondary Thermal Shield design. Solar Division of International Harvester Company was contracted to fabricate a 6" demonstration assembly for evaluation. Their efforts produced a system assembly that facilitated an "inspect-as-you-go" brazing procedure for each silver conduction ring. The demonstration cylinder was received at the time the decision was made to utilize beryllium for the shield.
- b. Substitution of a beryllium secondary heat shield for the SiO_2 secondary heat shield formerly specified
- c. Redesign of secondary heat shield support structure and fasteners
- d. Minor modification of other existing GLFC internal parts to accommodate the beryllium secondary heat shield and to maintain the GLFC weight at 40 pounds or less
- e. Analysis of the graphite shell and of GLFC internal parts to assess their ability to protect the fuel capsule in all prescribed environments.

5.1.1 DRAWING STATUS

The following new drawings have been issued:

- a. Drawing 47D301251 Secondary Thermal Shield, Beryllium, GLFC - As shown in Figure 5-1, the GLFC secondary heat shield is a hollow beryllium cylinder which is rhodium plated to prevent any possible reaction between the

beryllium and the plutonium fuel, should the two come in contact. A Radifrax coating is then applied over the rhodium for high emissivity.

- b. Drawings 47D301252 and 47D301253, Forward and Aft Thermal Shield Support Rings, respectively - The support rings (see Figures 5-2 and 5-3) are fabricated of Inconel-X and are of segmented construction. The aft support ring is designed to transmit both lateral and axial loads. The support rings accommodate differential thermal expansion (existing between the beryllium secondary heat shield and the graphite shell) by incorporating radial slots in both the forward and aft assemblies (see layout, Figure 5-4). The support rings are fabricated of Inconel-X, flame-sprayed with an aluminum oxide coating for low emissivity and for compatibility with titanium parts.
- c. Drawing 47D301254, Cover, Thermal-Forward Capsule Support - The thermal cover material has been changed from 321 stainless to titanium and the thickness increased from 0.060 inches to 0.125 inches. This modification eliminates differential thermal expansion between the thermal cover and the forward capsule support.

The following drawings have been modified as indicated:

- a. Drawing 47E300973, Latch Fitting, GLFC - Bolt holes have been added to accommodate the re-designed aft support ring.
- b. Drawing 47E301110, Forward Capsule Support, GLFC - Bolt holes have been added to accommodate the new forward support ring. To increase the lateral stiffness the web dimensions were changed and the number of webs was increased from 12 to 16.
- c. Drawing 47D300977 P1 and P4, Dome Insulation - To effect a weight reduction, material has been removed from both the forward and aft dome insulation pieces.

BLANK

Figure 5-2. Support Rings Thermal Shield, Fwd

BLANK

BLANK

Figure 5-4. GLFC Assembly

BLANK

- d. Drawing 47D301129, Spline Assembly - Graphite locking cylinder was replaced by tantalum to increase its capability to withstand load during launch vibration.

5.1.2 SECONDARY HEAT SHIELD

The new secondary heat shield consists of a hollow beryllium cylinder with a 4.13 inch outer diameter and a 0.565 inch wall, rhodium plated and radifrax coated for compatibility and emissivity requirements. The secondary heat shield supporting structure supports the beryllium cylinder inside the graphite outer shell. The major consideration here is the difference in thermal expansion between the beryllium and the graphite. A rigid structure would develop high thermal stresses; consequently, a design has been adopted that permits a degree of radial motion between the primary and secondary heat shields yet constrains the two shields laterally. This is accomplished by radial slots, Figure 5-4, in the aft support ring engaged by bolts secured in the latch fitting, and by radial webs in the forward support ring that engage radial slots machined in the end of the beryllium cylinder. This arrangement results in adequate axial and lateral constraint under all expected load conditions, however, with negligible stresses introduced in the graphite or beryllium due to differential thermal expansion. The aft support ring provides both axial and lateral constraint, the forward support ring provides lateral constraint only. Both aft and forward rings are segmented to minimize circumferential thermal expansion effects between the support ring, the beryllium cylinder and the titanium rings. The forward support ring consists of two interlocking parts, each containing three segments, so arranged that they cannot normally provide any axial constraint, but will in the event of a blast, provide sufficient axial constraint to hold the thermal cover in place on the secondary heat shield for additional abort fireball protection.

5.1.3 WEIGHT SUMMARY

Table 5-1 presents the comparison of nominal weight summaries for the new and old designs. The introduction of the beryllium secondary shield adds 2.28 pounds, however, through various savings in other areas, the net increase is 1.42 pounds on the overall GLFC/FCA system. This coupled with weight savings on the old design overall gives a new GLFC total weight of 39.92 pounds.

TABLE 5-1. GLFC NOMINAL WEIGHT SUMMARY

Description	SiO ₂ Design	Mat'l	Be Design	Mat'l
<u>GRAPHITE PRIMARY SHIELD</u>				
Cylinder	7.68	Pyrocarb	7.68	Pyrocarb
End Caps (2)	5.88	Pyrocarb	5.88	Pyrocarb
Retainer	.39	Pyrocarb	.39	Pyrocarb
Total Graphite	13.95		13.95	
<u>SECONDARY SHIELD</u>				
Cylinder	1.62	CB	5.75	Be
Coatings	.66	CBSiO ₂	.40	Rh, Ag
Rings	.85	Ag, Cb	-	-
Insulation	1.99	SiO ₂	-	-
Attachments	-	-	1.25	Incox Ti, L-605
Total Shield	5.12		7.40	
<u>INSULATION</u>				
Inside End Caps	2.14	Fiber-frax	1.00	Fiber-frax
<u>OTHER</u>				
Latch Fitting	1.18	Ti	1.18	Ti
Fwd	1.16	Ti, L-605	1.16	Ti, L-605
Dome Cover	.15	300SS	.43	Ti
<u>SUB TOTAL</u>	23.70		25.12	
<u>CAPSULE/BACK PLATE</u>	14.80	L-605	14.80	L-605
<u>SYSTEM TOTAL</u>	38.50		39.92	

5.2 THERMAL ANALYSIS

In order to redesign the secondary shield, thermal analyses were performed to define and optimize a design. Thermal characteristics of the existing silicon dioxide design concept were investigated and are shown in Figure 5-5 for the fireball after-fire and the earth orbital spinning re-entry; the two most severe cases in terms of capsule temperature for the existing design. This figure shows that the peak capsule temperature decreases with increasing thickness for the earth orbital re-entry case and increases with thickness for the after-fire case. Also, it shows that there is no way to reduce peak capsule temperatures below 2200°F for both cases using the silicon dioxide design concept.

Examination and extrapolation of Figure 5-5 shows that a re-designed secondary thermal shield should have a thermal time constant equal to or greater than a 0.6 inch thick SiO₂ shield in order to satisfy the earth orbital case. Also, it should have a radial conductance equal to or greater than a 0.05 inch thick SiO₂ shield (with silver fins melted) in order to satisfy the steady state residual fire case. Since the thermal time constant for this design can be reasonably approximated as the shield's inertia term (WC_p) divided by the shield's radial conductance (K), this provides a good starting point as to what the WC_p value should be for the re-designed shield.

A survey was undertaken to find materials with suitable thermal properties, but which were also readily available, had known properties in the proper temperature range, and were as compatible as possible with all other cask materials. The three resulting candidate materials were beryllium, beryllium oxide, and ATJ graphite. Beryllium appeared to be the best of the three because it had the largest specific heat (most thermal inertia per unit weight), and the best structural characteristics. It was also readily available. Some preliminary comparisons were made using the material properties and are summarized below:

- Beryllium will result in the lightest weight secondary shield; approximately 5.7 lb, 7.3 lb and 9 lb for beryllium, beryllium oxide and graphite respectively.
- Approximately 0.5 inch thickness of beryllium or beryllium oxide would be required but graphite would require approximately 0.8 inch.

Figure 5-5. Relationship of Capsule Temperature to Secondary Heat Shield Silicon Dioxide Thickness

- Radial thermal gradients during re-entry will result in critical stresses in beryllium oxide.
- Compatibility with other cask and capsule materials would be less of a problem with beryllium oxide than with either beryllium or graphite.
- Graphite has a potential oxidation problem for operation at 1000°F in air.

Graphite probably could not keep the peak capsule temperatures below 2100°F for all cases because the thickness required for re-entry protection would combine with a low conductivity to result in excessive capsule temperatures during the fireball afterfire.

5.2.1 GLFC WITH A BERYLLIUM HEAT SHIELD

5.2.1.1 Design Analysis

An analysis was begun for GLFC configurations using cylindrical beryllium secondary heat shields, replacing the present cylindrical columbium/silver/silicon dioxide brazed assembly. On the aft end the cylinder would be supported from the latch ring by intermediate metallic brackets. On the forward end the cylinder would be tied into the forward capsule support to both support the beryllium and provide a complete enclosure for the capsule should the graphite shatter. This results in additional heat and blast protection for the fireball and those super-orbital re-entry cases which previously failed the graphite and exposed the capsule to the fireball.

In order to determine the required beryllium thickness, a parametric study was performed to determine the capsule temperatures with the GLFC being exposed to various thermal environments. This sizing study used super-orbital graphite ID temperatures previously calculated for the SiO₂ design to avoid having to make a large number of REKAP runs. Figure 5-6 shows maximum capsule temperature as a function of shield thickness for earth-orbital re-entry heating, 6.25° for horizontal (DFH) super-orbital re-entry heating, and for an 1870°F residual fireball environment. It may be seen that the capsule temperature is relatively insensitive to shield thickness in the residual fire. Since there is only a small radial temperature drop through the beryllium shield in a steady-state condition, such as residual fire, the capsule temperature may only be lowered by moving the shield out to a larger diameter. The shield temperature, and consequently the capsule temperature, goes down as

Figure 5-6. Maximum Capsule Temperature during Re-Entry vs Thickness of a Beryllium Secondary Heat Shield

the radiating area of the shield increases with diameter. For a given thickness, however, the shield will weigh more at a larger ID. Therefore, for the lowest weight beryllium shield, the capsule temperature cannot be kept below 2060°F in the fireball environment. On the other hand, small increases in shield thickness have a large effect on capsule temperature for the two most severe re-entry conditions as shown in Figure 5-6. It appears that a shield thickness between 0.5 and 0.6 inches is needed for the additional capsule protection. The radial thermal gradient through the shield during re-entry, and the weight of a beryllium shield with a 3.0 inch ID are shown as a function of shield thickness in Figure 5-7 and Figure 5-8, respectively.

An annular cylinder with a length of 13.75 inches, a thickness of 0.565 inches, and an ID of 3.0 inches was chosen for the preliminary beryllium shield design. Temperature response curves for the GLFC with the 0.565 inch thick beryllium shield are given in Figures 5-9, 5-10 and 5-11, using a one-dimensional, pie-slice model. The

Figure 5-7. Maximum Temperature Gradient Across a Be Secondary Heat Shield during Re-entry vs Shield Thickness

Figure 5-8. Weight of Be Secondary Heat Shield vs Thickness of Shield

Figure 5-9. Capsule/Cask Temperatures (Lateral Spin)

Figure 5-10. Capsule/Cask Temperatures (Super-orbital $\gamma = 38.05^\circ$)

Figure 5-11. Capsule/Cask Temperatures (Super-orbital $\gamma = 6.25^\circ$)

conditions under which these temperatures were calculated are listed below:

Figure 5-9 - Earth-orbital decay, spinning cask

Figure 5-10 - Super-orbital re-entry 38.05° DFH, Planar
Tumbling Cask

Figure 5-11 - Super-orbital Re-entry 6.25° DFH, Planar
Tumbling Cask

A summary of peak component temperatures and the times that they occur are given in Table 5-2.

TABLE 5-2. PEAK TEMPERATURES FOR THE GLFC WITH A 0.565" THICK, CYLINDRICAL BERYLLIUM SECONDARY HEAT SHIELD HAVING A 3.0 INCH ID

	EARTH ORBITAL LATERAL SPIN	6.25° S.O PL. TUMBLE SIDE HEAT	38° S.O PL. TUMBLE SIDE HEAT
GRAPHITE O.D.	2543°F @ 6260 sec.	3700°F @ 82 sec.	4750°F @ 12 sec.
GRAPHITE I.D.	2451°F @ 6260 sec.	3004°F @ 90 sec.	2794°F @ 18 sec.
Be O.D.	2027°F @ 6300 sec.	1822°F @ 160 sec.	1349°F @ 185 sec.
Be I.D.	2021°F @ 6310 sec.	1816°F @ 170 sec.	1351°F @ 185 sec.
CAPSULE O.D.	2008°F @ 6370 sec.	1784°F @ 284 sec.	1498°F @ 201 sec.
LINER I.D.	2158°F @ 6560 sec.	1937°F @ 404 sec.	1680°F @ 201 sec.
MAX. Δ T from Be O.D. to I.D.	28°F @ 6270 sec.	52°F @ 100 sec.	30°F @ 20 sec.

5.2.1.2 Oriented Re-entry Analyses

The thermal design of the GLFC has been based on the assumption that the GLFC would re-enter spinning or tumbling. Consequently, the cask was designed to provide sufficient protection to the capsule both for lateral spinning earth-orbital and planar tumbling super-orbital re-entry conditions. An assessment has been made of the survival capabilities of the capsule/cask assembly oriented in a side-on re-entry. This section presents the results obtained from the first portion of these analyses - oriented earth orbital re-entry.

With a spinning or tumbling cask, the re-entry heat flux is distributed uniformly over the cylindrical cask barrel. Since all areas of the barrel are heated evenly, a one-dimensional model was sufficient for the determination of the temperature response of a spinning or tumbling cask. However, with an oriented cask, the re-entry heating around the circumference is non-uniform, decreasing from the stagnation line in approximately a cosine distribution. To analyze this situation, a cask model was developed that included a 180° segment of the capsule/cask assembly. This model is a one inch thick slice taken at the cask mid-plane, see Figure 5-12. Since the cask is attached to the LM down to 300 k ft in an earth-orbital decay design trajectory, the effects of the LM thermal shield had to be included in the model. A line from the center of the LM to the center of the cask bisects the cask but cuts the LM shield unevenly. Therefore, the 180° section of the cask which is covered by the greater portion of the LM shield was used for the analysis, leading to slightly conservative results.

The temperature history of the capsule/cask assembly was calculated for earth orbital decay in two parts. In the first part of the trajectory, the LM thermal shield was part of the model, and appropriate multipliers were used on the cask stagnation flux (nose radius = 4.0 inches) to account for a spinning LM. A heat flux was applied to the LM shield based on the projected area of the shield. The first part of the analysis covered the descent from 400 kft ($t=0$) to 300 kft ($t=5900$ sec).

For the second part of the analysis, the LM shield was removed from the model, and a cosine flux distribution was applied to the outer cask nodes with the stagnation line of node 1. Figures 5-13, 5-14 and 5-15 show the capsule/cask temperature distribution at three

Figure 5-12. GLFC 2D THT-D Model Nodal Numbering System

EARTH ORBIT DECAY
ORIENTED CASK
LM SHIELD REMOVED
AT 300K FT. (5900 SEC.)

5-23

Figure 5-14. GLFC 2-D THT-D Model Capsule/Cask
Temperatures (°F) at 6260 Seconds

Figure 5-15. GLFC 2-D THT-D Model Capsule/Cask
Temperature (°F) at 6350 Seconds

different times in the trajectory. The time-in-trajectory, and the significance of that time are as follows:

Figure 5-13 - $t = 6210$ sec.

Maximum radial gradient in the cask wall

Figure 5-14 - $t = 6260$ sec.

Maximum cask wall temperature and maximum
cask wall circumferential gradient

Figure 5-15 - $t = 6350$ sec.

Maximum capsule clad temperature

The temperature versus time history of the cask and capsule nodes on the stagnation line is shown in Figure 5-16. It may be seen from these figures that the maximum cask wall and capsule temperatures are 3477°F and 2115°F , respectively. Since the calculations were done with THT-D computer code, which does not account for reaction kinetics in an ablating material, both of these temperatures are too high. Reaction kinetic effects would reduce both the peak temperatures and gradients in both radial and circumferential directions.

5.2.2 GLFC WITH A BERYLLIUM OXIDE SECONDARY HEAT SHIELD

A parallel design analysis effort was done on a beryllium oxide (BeO) secondary heat shield in order to have a backup design in the event that the beryllium compatibility problems had proved insurmountable. BeO was selected as the alternate because of its similarity to beryllium in thermal properties and inherent inert nature.

As with the beryllium design, a parametric sizing study was done. The temperature responses of the capsule/cask assembly with various thicknesses of BeO heat shield were calculated for fire-ball heating and for three different re-entry trajectories. The maximum capsule temperature is shown in Figure 5-17 as a function of BeO thickness. Given an upper limit of capsule temperature, a shield thickness can be found to satisfy both re-entry and fireball heating conditions. However, if this upper limit is set below 2071°F it may be seen in this figure that there is no BeO thickness that will satisfy the fireball requirements. Since thermal stresses in a BeO heat shield are also a major problem, the maximum temperature differences from the OD to the ID of the BeO shield during re-entry are shown in Figure 5-18 as a function of shield thickness. The weight of a BeO

Figure 5-16. Capsule/Cask Temperatures - Stagnation Line Nodes - 2-D Model

Figure 5-17. Maximum Capsule Temperature during Re-entry vs Thickness of a BeO Secondary Heat Shield

Figure 5-18. Maximum Temperature Gradient Across a BeO Secondary Heat Shield during Re-entry vs Shield Thickness

secondary heat shield of length 13.75 inches and an ID of 3.0 inches is shown in Figure 5-19, also as a function of thickness.

As expected from the preliminary estimates, BeO results in a heavier secondary heat shield design with critical thermal stresses producing similar peak capsule temperatures when compared to the beryllium design.

Figure 5-19. Weight of BeO Secondary Heat Shield vs Thickness of Shield

5.3 STRUCTURAL ANALYSIS

5.3.1 GRAPHITE SHELL DURING RE-ENTRY

Thermal structural analyses to date have considered planar tumble super-orbital re-entry with uniform circumferential temperatures. For the cases analyzed, the radial temperature gradients shown in Figure 5-20 and material properties and density gradients from tag end data from cylinders produced by HITCO were used. The material properties were correlated with density and temperature as described in PIR 8155-1957. The resulting material properties curves are shown in Figures 5-21, 5-22, 5-23 and 5-24.

In addition to the normally calculated thermal stresses in the circumferential direction, an effort was made to evaluate the effect of the unrestrained ends of the cylinder. To determine the magnitude of these effects a test case was made using the ARBAS computer code. Material properties were taken from PIR-8155-1957, and the density gradient from the Pyrocarb 406 specification NS-0060-02-32. The upper specification density was chosen. The temperature gradient used in the analysis was for 38° planar tumble with a graphite primary and Be secondary heat shield combination. The axial variations of compressive and tensile circumferential stresses are shown in Figure 5-25, indicating an increase in circumferential stress of up to 20 percent. The maximum thermal stress is therefore obtained by multiplying the calculated inner fiber tensile stress by 1.2. No plastic effects were considered in this analysis.

Figure 5-20. Radial Temperature Gradients for Planar Tumble

Figure 5-21. "B" Direction Elastic Modulus

Figure 5-22. "B" Direction Plastic Modulus

Figure 5-23. "B" Direction Intersection Strength (E/E_P)

Figure 5-24. Pyrocarb "406" Circumferential Direction Ultimate Tensile Strength

Figure 5-25. "B" Direction vs. Length Elastic

5.3.2 SECONDARY HEAT SHIELD ASSEMBLY

The structural analysis of the beryllium secondary heat shield assembly, Figure 5-26, was performed to assess its capability to survive the following critical environments:

Load Cond.	Load Description	Temp. of Cylinder	Temp. of Supports	Load Factor Gx	Load Factor Gn	Press. psi
A	Lateral Vibration	1000	1000	-	60	
B	Super-Orbital $6\frac{1}{4}^\circ$ Re-entry Planar tumbling	2160	1960 to 1995	-	6.1	
C	Super-Orbital 38° Re-entry Planar tumbling	1100	1395	-	210.	
D	Axial Blast at 20% TNT yield (static over pressure)	1000	1000	(equiv) 2590	-	1152
E	Lateral Blast at 20% TNT yield (static over pressure)	1000	1000	-		1152

x - direction is longitudinal
n - direction is lateral

Figure 5-26. Configuration for Re-entry Analysis
of Secondary Heat Shield

5.3.2.1 Beryllium Cylinder

Preliminary calculations show that the Be cylinder will probably not survive the specified blast impulse environment (loads D and E) since an impulse capability of only 2.5 percent TNT yield can be demonstrated. A more sophisticated analysis will be conducted to determine the blast capability.

The following points were apparent from the analysis

- a. The allowable blast overpressure is 2550 psi based on yield strength criteria for the thick-walled cylinder. For 20 percent TNT yield, the environment is 1152 psi, showing an ample margin of safety for this yield (Reference 1).

- b. The allowable impulse is 39,400 taps based on the equation 5.2 of Reference 2. The TNT yield for this impulse is 2.5 percent as presented for the S-IC static impulse in a Saturn V explosion (Reference 1). In both re-entry and normal operation (load conditions A, B or c), a high margin of safety is evident.
- c. During re-entry, the cylinder is critical for the $6\frac{1}{4}^{\circ}$ angle super-orbital, planar tumble, side heating case. A peak temperature of 2160°F at 152 seconds of re-entry time, combined with a 6.1 g level, is realized. The resultant elongation is 13 micro-inches/inch compared to the allowable of 28,000 microinches/inch, and therefore, a high margin of safety exists.
- d. Re-entry at the highest re-entry angle considered, $\gamma = 38^{\circ}$, is not nearly as critical as the low angle. For the maximum loads time of 14.5 seconds, a level of 210 g's is experienced in planar tumble, which produces only 417.5 psi stress in the cylinder. At the 1110°F temperature for this re-entry time, beryllium tensile strengths are 17,600 psi yield and 23,700 psi ultimate resulting a high margin of safety.

5.3.2.2 Forward Support Ring

The forward support is critical for re-entry load condition B, and has a very small positive margin of safety. The tabs on the ring were found to be critical in bending at a re-entry time of 102 seconds, which corresponds with a g level at the support of 12.6 at 1960°F .

For blast load condition D, the 12 tabs are directly in compression and have a high margin of safety.

5.3.2.3 Aft Support Ring

The aft support is critical for blast, Load Condition D, where bending of the ring cross-section from a static blast overpressure of 1152 psi produces a margin of safety of + 0.04, based upon a ring temperature of 1000°F .

The critical re-entry, load condition B, gives a high margin in the aft support when the most severe condition occurs at time 125 seconds, ring temperature of 1995°F and a g level of 10.45.

5.4 MATERIALS PROGRAM

Materials activity for the first quarter of 1968 included property and process analysis of the Pyrocarb 406 production units for the primary heat shields, support of the fabrication of the SiO_2 secondary heat shield, development of coatings for the new beryllium secondary heat shield and support in selection of materials for associated components.

5.4.1 GRAPHITE PRIMARY HEAT SHIELD

Two lots of graphite cylinders and associated hardware were produced during the reporting period.

One of the cylinders (SN 24630B) was cut up and used to correlate tag end material property values with center section values. Cylinder S/N 24630B showed tag end data indicating low "B" direction (circumferential) tensile properties and a non-conforming density gradient. Due to pre-infiltration machining differences, the top tag end did not exactly represent the center section material. A bottom tag end that was more representative was tested and these corresponding tensile values were higher than the top tag end.

As can be seen from the data in Table 5-3, the center values were higher than the top tag end value by as much as 23.3 percent. Previous observations on a sectioned engineering cylinder showed that hoop tensile strength at the center was 10.5 percent higher than at the ends.

The low "B" values may be related to high "crimp" in the "B" fill fibers as shown in Figure 5-27. The data for each tag end and batch sample are being analyzed and compared to published design data. Of particular interest is the strength/modulus vs density relationships.

Table 5-4 shows the results of a reimpregnation program carried out at HITCO to increase strength values. Reimpregnation of parts with subsequent heat treatment seems to accomplish the desired effects of increasing strength while decreasing voids, but reduction of the density gradient through the cask wall may offset any capability gain made by virtue of higher material strength. There are no plans to implement such a reimpregnation process step at this time.

5.4.2 SECONDARY HEAT SHIELD SiO_2 /Cb DESIGN

Vac-Hyd and Fansteel have each delivered one apparently acceptable SiO_2 heat shield. These shields have been inspected but not tested.

TABLE 5-3. COMPARISON OF TAG-END VALUES WITH CYLINDER VALUES

• <u>AXIAL "A" DIRECTION:</u>					
<u>TOP TAG-END</u>		<u>CENTER SECTION</u>		<u>BOTTOM TAG-END</u>	
<u>STRESS</u> (PSI)	<u>TANGENT MODULUS</u> (PSI X 10 ⁶)	<u>STRESS</u> (PSI)	<u>TANGENT MODULUS</u> (PSI X 10 ⁶)	Small size of the bottom tag-end prohibited "A" tests.	
15,365	2.4	13,922	2.6		
13,837	2.4	18,489	2.7		
<u>15,357</u>	<u>2.6</u>	<u>15,860</u>	<u>2.7</u>		
AVG 14,853	AVG 2.5	AVG 16,090	AVG 2.7		
• <u>CIRCUMFERENTIAL "B" DIRECTION:</u>					
<u>TOP TAG-END</u>		<u>CENTER SECTION</u>		<u>BOTTOM TAG-END</u>	
<u>STRESS</u> (PSI)	<u>TANGENT MODULUS</u> (PSI X 10 ⁶)	<u>STRESS</u> (PSI)	<u>TANGENT MODULUS</u> (PSI X 10 ⁶)	<u>STRESS</u> (PSI)	<u>TANGENT MODULUS</u> (PSI X 10 ⁶)
3,003	1.4	3,664	1.8	2,804	1.5
2,584	-	3,837	1.8	4,191	1.8
2,657	1.7	3,484	1.6	4,054	1.9
3,091	1.6	3,580	1.7	4,368	1.9
2,660	1.4	4,223	1.7	3,758	1.8
<u>3,079</u>	<u>1.4</u>	<u>3,525</u>	<u>1.7</u>	<u>4,274</u>	<u>1.7</u>
AVG 3,012	AVG 1.5	AVG 3,715	AVG 1.7	AVG 3,909	AVG 1.8
• <u>THROUGH THICKNESS "C" DIRECTION</u>					
<u>TOP TAG-END</u>		<u>CENTER SECTION</u>		<u>BOTTOM TAG-END</u>	
<u>STRESS (PSI)</u>		<u>STRESS (PSI)</u>		Material not available for "C" tests	
672		806			
620		856			
688		788			
<u>690</u>		<u>851</u>			
AVG 688		AVG 825			
• <u>DENSITY</u>					
Average density to a depth of 0.150" from I.D. (ρ = 86.8 lb/ft ³		ρ = 90.1 lb/ft ³		ρ = 88.0 lb/ft ³	

TABLE 5-4. TENSILE PROPERTIES SHOWING AFFECTS OF RE-IMPREGNATION

Test Specimens	Prior to Reimpregnation		After First Reimpregnation	Tensile Modulus psi x 10 ⁶	After Second Reimpregnation	Tensile Modulus psi x 10 ⁶
	Tensile Strength, psi	Tensile Modulus psi x 10 ⁶	Tensile Strength, psi		Tensile Strength, psi	
HITCO Furfuryl, Cyliner Thin Wall section	3880	1.83	3900	1.2	6240	1.7
	4290	1.60	3850	1.2	5870	1.7
	4940	1.81	5990	1.4	-	-
	<u>4710</u>	<u>1.60</u>	<u>6090</u>	<u>1.4</u>	-	-
Avg.	4460	1.71	4960	1.3	6050	1.7
Thick wall section	3150	1.26	4860	1.6	5360	1.6
	<u>2920</u>	<u>1.41</u>				
Avg.	3040	1.34				
HITCO Furfuryl, Shingle Angle test panels	**	**	6040	1.6	6220	1.5
			5710	1.8	5650	1.5
			<u>6400</u>	<u>1.8</u>	<u>5080</u>	<u>1.5</u>
Avg.			6050	1.7	5980	1.5
*NARMCO Furfuryl, Cylinder Thin wall section	**	**	6440	1.7		
			<u>6310</u>	<u>1.8</u>		
Avg.			6370	1.8		
Thick wall section						
Avg.	**	**	5240	1.7		
U.S.POLYMERIC 39 Filled Cylinder, Thin wall section	**	**	5370	1.4		
			<u>5020</u>	<u>1.5</u>		
Avg.			5190	1.5		
Thick wall section						
Avg.	**	**	4680	1.4		

NOTE: * One longitudinal tensile specimen was pulled yielding at 10,829 psi with a modulus of 2.1×10^6 psi.

** Tests not run on 7° shingle panel prior to reimpregnation.

Figure 5-27. High "B" Fill Crimp in Section Taken from
Tag End of Cylinder S/N 24630B

All further SiO_2 design components were placed on a hold status, and attention is now focused on the new beryllium secondary heat shield design. The following progress was made on the SiO_2 secondary heat shield prior to the hold action:

- a. Oxidation Protection Coating of Columbium - Controls were developed to assure uniform aluminide coating application and a compatible electroless nickel surface coating was established for the Fansteel unit. Vac-Hyd improved their aluminide surface for brazing by applying a thin coat of titanium hydride on top of the aluminide coating.
- b. Brazing Cycle - Satisfactory temperature mappings of both Vac-Hyd and Fansteel furnace runs were achieved. Process specifications were written and abort criteria established. Studies were initiated on thermographic techniques to ascertain braze joint quality.
- c. SiO_2 Insulation Rings - Cleaning and bakeout procedures were established to eliminate contaminants from the rings.

The following problems remained to be solved at the time of the hold; 1) platinum coating on the silver rings adhered poorly, 2) phosphorous from the previous nickel coating tended to embrittle the silver rings and 3) no satisfactory technique for non-destructive inspecting of the braze has been developed.

5.4.3 SECONDARY HEAT SHIELD BERYLLIUM DESIGN

Beryllium and BeO were the final candidates for the new secondary heat shield design based on high heat absorbing capacity and good thermal conductivity. BeO had advantages of high melting point and chemical inertness, but is heavier and is less resistant to thermal shock. Beryllium was selected for prime effort based upon thermal calculations showing that melting would not be a problem during normal operation or abort cases. A hot pressed block material was then recommended because of its isotropic properties.

5.4.4 COATINGS AND COMPATIBILITY

A coating for the beryllium was needed to ensure safehandling, high emittance, oxidation/sublimation protection and compatibility with fuel and adjacent materials.

Several variations of coatings on beryllium were considered: nickel plate over silver, chrome plate over silver, Iridite 14-9, Iridite 14-2, Alodine 1200-S, Rhodium plate over Ni/Ag, Platinum over Ni/Ag, Rhodium paint slurry, platinum paint slurry, Thompson Frit No. 54, Rhodium by autoclaving over silver and platinum by autoclaving over silver.

The most promising coating which meets the requirements consists of plating with silver, vacuum annealing, plating with rhodium and then emissive coating with Radifrax.

Figure 5-28 shows a compatibility test made on the rhodium coated beryllium with Radifrax. In the test, a small amount of $^{239}\text{PuO}_2$ was placed on top of the sample to determine if a reaction occurs. Although the coating wrinkled after five minutes at 2100°F in air, there was no reaction with the fuel. Table 5-5 shows other beryllium compatibility tests in progress along with results to date.

Beginning of Test

After five minutes at 2100°F in air

Figure 5-28. Test for Compatibility of Rhodium/Radifrax Coated Beryllium in Contact with Fuel

TABLE 5-5. BERYLLIUM HEAT SHIELD COMPATIBILITY TESTS

Series No.	Set No.	Specimen Description	Test Conditions	Location of Test	Results	Weight Change
1B0	1	Plain Be	1200F/Air/2 hrs.	NMPO	Specimen Discolored	Gain 0.01%
1B0	2	RC356/Be	1200/Air/2 hrs.	NMPO	RC356 Spalled	Unknown
1B0	3	RC356/Rh/Be	1200F/Air/2 hrs.	NMPO	No effect	Gain 0.01%
2B0	1	Plain Be	1400/10 ⁻⁵ Torr/2.5 hrs.	NMPO	Slightly Discolored	Loss 0.01%
2B0	2	RC356/Be	1400F/10 ⁻⁵ Torr/2.5 hrs.	NMPO	Slight Spalling of RC356	Loss 0.01%
2B0	3	RC356/Rh/Be	1400F/10 ⁻⁵ Torr/2.5 hrs.	NMPO	No effect	Loss 0.01%
5B4	V-1	RC356/Be	2100F/Air/5 minutes	Val.	RC356 Spalled	
5B4	V-2	Rh/Be	2100F/Air/5 minutes	Val.	No effect	
5B4	V-3	RC356/Rh/Be	2100/Air/5 minutes	Val.	No effect	
5B4F	V-1	Fuel/Rh/Be	2100/Air/5 minutes	Val.	Slight Sticking	
5B4F	V-2	Fuel/RC356/Rh/Be	2100F/Air/5 minutes	Val.	No reaction	
5B4F	V-3	Fuel/Be	2100F/Air/5 minutes	Val.	Fuel reacted with beryllium. PuO ₂ dissolved in Be surface. Slight penetration.	

TABLE 5-5. BERYLLIUM HEAT SHIELD COMPATIBILITY TESTS (CONT)

Series No.	Set No.	Specimen Description	Test Conditions	Location of Test	Results	Weight Change
1B1	1	Plain Be	1200F/Air/100 hrs.	NMPO		
1B1	2	Rh/Be	1200F/Air/100 hrs.	NMPO		
1B1	3	ϵ -Ctg/Be	1200F/Air/100 hrs.	NMPO		
1B1	4	ϵ -Ctg./Rh/Be	1200F/Air/100 hrs.	NMPO		
1B1	5	ϵ -Ctg./Rh/Be/ HS25	1200F/Air/100 hrs.	NMPO		
1B1	6	ϵ -Ctg./Rh/Be/ Ti alloy	1200F/Air/100 hrs.	NMPO		

TABLE 5-5. BERYLLIUM HEAT SHIELD COMPATIBILITY TESTS (CONT)

Series No.	Set No.	Specimen Description	Test Conditions	Location of Test	Results	Weight Change
2B1	1	Plain Be	1400F/10 ⁻⁵ Torr/1000 hrs.	NMPO		
2B1	2	Rh/Be	1400F/10 ⁻⁵ Torr/1000 hrs.	NMPO		
2B1	3	ε Ctg./Be	1400F/10 ⁻⁵ Torr/1000 hrs.	NMPO		
2B1	4	ε Ctg./Rh/Be	1400F/10 ⁻⁵ Torr/1000 hrs.	NMPO		
2B1	5	ε Ctg./Rh/Be/ HS25	1400F/10 ⁻⁵ Torr/1000 hrs.	NMPO		

TABLE 5-5. BERYLLIUM HEAT SHIELD COMPATIBILITY TESTS (CONT)

Series No.	Set No.	Specimen Description	Test Conditions	Location of Test	Results	Weight Change
5B4		R356/Be-vs.-P406	2100F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		R356/Rh/Be-vs.-P406	2100F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		R166/Rh/Be-vs.-P406	2100F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		€ Ctg/Rh/Be-vs.-HS25	2100F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		€ Ctg./Rh/Be-vs.-A286	2100F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		€ Ctg./Rh/Be-vs. Ti alloy	2100F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		€ Ctg./Rh/Be-vs. P406	2300F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		€ Ctg./Rh/Be-vs. Ti Alloy	2300F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4		€ Ctg./Rh/Be-vs. HS25	2300F/10 ⁻⁵ Torr/5 minutes	NMPO		
5B4F	V-4	R166/Rh/Be	2100F/10 ⁻⁵ Torr/5 minutes	Val	No reaction with fuel. R166 melted and shriveled	

TABLE 5-5. BERYLLIUM HEAT SHIELD COMPATIBILITY TESTS (CONT)

Series No.	Set No.	Specimen Description	Test Conditions	Location of Test	Results	Weight Change
5B4F	V-5	Fuel/R166/Rh/Be- vs. -P406	2100F/10 ⁻⁵ Torr/5 minutes	Val.		
5B4F	V-6	Fuel/R166/Rh/Be- vs. -HS25	2100F/10 ⁻⁵ Torr/5 minutes	Val.		

The following additional compatibility tests have been proposed for the purpose of further evaluating beryllium for the secondary heat shield application:

Series 1B0	- Air	- 1200°F	- Proof Tests
Series 2B0	- Vacuum	- 1400°F	- Proof Tests
Series 1B1	- Air	- 20/100 hrs.	- 1200°F
Series 2B1	- Vacuum	- 100/1000 hrs.	- 1400°F
Series 5B4	- Vacuum	- 5 minutes	- 2100-2300°F
Series 5B4F	- Vacuum	- 5 minutes	- 2100-2300°F

These tests will accomplish the following goals:

- a. Determine air oxidation characteristics of beryllium
- b. Determine effects of thermal-vacuum on beryllium
- c. Demonstrate oxidation/sublimation resistance of coatings
- d. Establish compatibility characteristics of various coatings with substrates and adjoining materials and environments.

A high temperature, high-emittance coating is required on the ID and OD of the beryllium heat shield to satisfy thermal requirements. The flame-sprayed, RC356, Radifrax coating was applied to representative rhodium-plated samples and successfully tested for compatibility in both air and vacuum to 2100°F. Due to the inaccessibility of the ID for plasma arc spraying, the emissive coating was applied by a spray paint technique. Several formulations and firing schedules were investigated with RC-156 coating showing the most promise, containing 60 percent iron titanate in a 40 percent lead borosilicate (glass) base. Compatibility tests were run with the RC-168, RC-166, RC-156 coatings, and, as anticipated, the glasses softened and tended to wrinkle on the rhodium surface when cooled. This softening and wrinkling, however, had no noticeable effect on the compatibility with the fuel or the environment. Further avenues are being pursued to improve this glass softening situation.

5.5 GLFC HARDWARE

The status of the GLFC hardware is discussed in the following paragraphs.

5.5.1 BENDIX SYSTEM TEST ARTICLE (BSTA)

The BSTA was successfully tested, accepted by Sandia and shipped to Bendix on January 9, 1968.

5.5.2 SECONDARY THERMAL SHIELDS

Secondary Thermal Shields (SN 11 & 104) were received and accepted from Vac-Hyd and Fansteel. Due to redesign however, these units are now obsolete and all fabrication effort is on "hold". The newly designed beryllium shields are now in process. Material has been procured from Berylco and is now being machined at Speedring. Discussions and preliminary plans for coating of the shields have been made with GE-NMPO. A visit by engineering procurement and Q.C. personnel will be made to GE-NMPO during the first week in April to discuss process & Q.C. Requirements.

5.5.3 GRAPHITE PARTS

Two sets of graphite parts have been accepted from HITCO for the M8 and M9 Mockup GLFC's.

Two lots of graphite cylinders and associated hardware were produced during the reporting period. The specific components included were:

<u>Lot #1</u>	<u>Test Specimens</u>
Cylinders:	24629B
	24630B ----- (Cut up for correlation of tag-end material property values with center section values.)
End Caps:	27357B ----- (Cut up for verification of the batch properties.)
	26226B
	26228B
	26229B
	26982B
	27357B

<u>Lot #2</u>	<u>Test Specimens</u>
Cylinders:	29245B 27120B 28106B ----- (Diameter out of specification)
End Caps:	28098B ----- Cut up for verification of batch properties. 27870B 27376B 28100B 29506B 29502B

5.5.4 FORWARD CAPSULE SUPPORTS

All available forward capsule supports are being reworked by the vendor to incorporate the latest design changes.

5.5.5 LATCH FITTINGS

The raw material procured for the latch fittings was found to be unusable in that it did not meet the requirements of MIL-T-9046. New material has been re-ordered and receipt is expected in early April.

5.5.6 LITTON ASTRONAUT TEST HARDWARE

GLFC hardware to be used in the Litton Astronaut Tests is being accumulated and will be shipped to Litton during the first week in April.

5.6 GLFC TESTING

5.6.1 ENGINEERING DEVELOPMENT TESTING

5.6.1.1 Shaker Fixture Resonance Search

In accordance with SI 249177, a resonance search was performed on the shock and vibration fixture, utilizing a simulated GLFC. This

fixture simulates the ALSEP GLFC Support Structure, particularly with regards to the bands, see Figure 5-29.

Analysis of the data provided the following information:

a. Z Axis Cask Response

RESONANT FREQUENCIES - 210, 270, 920, 1150

b. X Axis Response

RESONANT FREQUENCIES - 210, 470, 1100

c. Y Axis Response

RESONANT FREQUENCIES 310, 360, 920, 1050

Figure 5-29. Engineering Development Test Setup

The fixture post amplifications were approximately 4:1 with cask amplifications at approximately 12:1 at resonant frequencies. Since no resonances were observed under 100 Hz, no fixture difficulties were expected during GLFC sine vibration. But, due to the inherent fixture resonances above 100 Hz, the random vibration spectrum were notched at the critical frequencies for uniform input to the GLFC.

5.6.1.2 Cold Vibration Testing of GLFC

Engineering hardware and a simulated fuel capsule were tested in the support fixture with the following instrumentation:

a. Accelerometers - per Drawing 47E301131.

Cask	9
Capsule	9
Secondary Thermal Shield	3
Latch Fitting	2
Latch Plate	3
Forward Capsule Support	2
Fixture	1

- b. Strain gages - A total of 16 located on the simulated fuel capsule per Drawing MSC 239.

The verification fuel capsule simulated the actual hardware and fuel conditions of flight hardware and with clearances at the latch fitting and forward capsule support shimmed to simulate hot conditions.

Assembled hardware was mounted horizontally in the vibration fixture, see Figure 5-29, constrained by 0.010 inch thick titanium bands. The band preload was set at 35 psi for simulated launch conditions, using strain gage instrumentation.

A summary of the vibration tests completed to date is as follows:

- a. The first series of vibration tests were in the Z axis, with the following control levels:

Sine - 1g, 3g, 5g and 7g

Random - 3.15 grms for 1 minute

The hardware was examined at the completion of the runs and an accelerometer on the capsule was found jammed against a gusset on the forward end of the secondary thermal shield. The tests were aborted, the discrepancy corrected and the hardware reassembled.

- b. The Z axis vibration tests performed above were rerun except that the random level was increased to 5.2 grms at the control accelerometer.

During the sine runs, the forward cap rotated approximately 1/8 inch, see Figure 5-30, due to the excessive clearance that existed between the spline lock and groove. Continuation of the random vibration caused the cap to move an additional 1/4 inch causing the graphite segments of the spline lock to break, see Figure 5-31.

A complete teardown and inspection of all hardware was then made with the following conditions noted:

- 1. Three silver thermal bridges on the forward capsule support webs broke loose due to poor resistance welds on these parts, see Figure 5-32.

Figure 5-30. Rotation of Dome and Cylinder After Test

Figure 5-31. Broken Spline Following Test

Figure 5-32. Forward Capsule Support Following Test

2. The forward capsule support webs yielded at the expansion slots reducing the outer diameter from 5.993 inches to 5.979 inches, causing the shim between the forward capsule support and graphite end cap to come loose.
3. The forward capsule support impact ring moved approximately .020 inch due to inadequate shimming, see Figure 5-32.
4. A considerable amount of dust and dirt was found inside the GLFC caused by the chafing of the Fiberfrax insulation at instrumentation leads in aft cap and under the forward capsule support in the forward cap.
5. Examination of the capsule, secondary thermal shield, latch fitting and graphite showed no damage.

The hardware was reshimmed, cleaned and reassembled for further vibration tests.

- c. The hardware was set up in the X axis and runs were made at the following control levels:

Sine - 1g, 3g, 5g and 7g

Random - 6.7 grms for 43 seconds

- d. The hardware was set up in the Y axis and runs were made at the following control levels:

Sine - 1g, 3g, 5g and 7g

Random - 12 grms for 37 seconds

This effort completed the cold-instrumented vibration tests of the GLFC.

A complete tear down and inspection of all hardware was made at this time and the following conditions were noted:

- a. The aft spline lock graphite segments were broken in the same manner as the forward spline lock in the previous test, however, no movement of the aft cap was observed.
- b. Fiberfrax dust and dirt noted during the Z axis inspection was evident again.
- c. The forward capsule support web yielding, OD shim loss, thermal bridge loss and impact ring movement were similar to that found during the Z axis inspection.
- d. Examination of the secondary thermal shield disclosed the following failures which were due to the marginal hardware used (cracked SiO₂ rings and bad braze), see Figures 5-33 and 5-34.
 - 1. Bottom columbium ring on STS was loose (braze).
 - 2. Two bottom silicon dioxide rings had fallen off the secondary shield (cracked rings).
 - 3. Bottom silver ring on secondary shield had fallen off (braze).
- e. All other hardware showed no adverse effects.

Figure 5-33. Secondary Thermal Shield - Cracked SiO₂ Rings

Figure 5-34. Secondary Thermal Shield - Bad Braze

General observations concerning these tests are as follows:

- a. The test program as conducted and completed was realistic in that input qualification levels controlled at the cask-band interface agreed with prescribed interface levels for sine and random.
- b. Hardware responses verified previous dynamic analyses. A complete analysis of the accelerometer and strain gage data from the Z axis has been prepared and is covered in detail in ANSO Document, PIR 1K75-3 (X and Y axis analyses will be published when the analysis is completed.
- c. Spline lock problems in the form of graphite locking cylinder breakage were caused by the large clearances in the spline grooves. This problem has since been corrected by changing the graphite portion of the spline lock which cracked to tantalum.
- d. Weaknesses in the forward capsule support which were demonstrated during testing were suspected some time ago. The design has been changed to increase the number of webs from 12 to 16.
- e. Secondary thermal shield problems were caused by marginal hardware. The design has been changed to a solid beryllium configuration.
- f. The forward capsule support impact ring which was shimmed to simulate hot conditions did not have sufficient bearing area to resist the impact of the capsule. The capsule was, therefore, not fixed as rigidly as it should have been throughout the test.
- g. The titanium bands used to constrain the graphite cask worked very well in that they 1) held the cask firmly, 2) did not cause undue loads or wear on the graphite and 3) did not lose more than 10 to 15 percent of their load during vibration.
- h. The vibration inputs to the cask generated significant responses in the hardware. Recent changes to this design described above appear to provide adequate margin for the levels imposed.

- i. The final analysis and evaluation of the GLFC is dependent upon the results of the ALSEP-GLFC combined vibration test. These combined tests to be performed by Bendix in early April will provide firm conclusions as to the adequacy of the integrated GLFC/FCA/Support Structure System.

5.7 REFERENCES

1. Rough Draft of Document #6300-300, "Volume II - Accident Model Document", dated 1/10/68, ANSO, GE.
2. Lindberg, H. E., et al, "Hardening Technology Studies, Response of Re-entry Vehicle Type Shells to Blast Loads", LMSC-B130200 Vol IV-C, Stanford Research Institute, 30 September 1965.

BLANK

6. SAFETY

6.1 SAFETY TEST PROGRAM

The following paragraphs describe the current status of the SNAP-27 Safety Test Program.

6.1.1 TEST SERIES 6 - CAPSULE BURIAL

In the preceding quarter it was reported that the Ottawa sand thermal conductivity data from GE laboratory tests were not in agreement with thermal conductivity values derived from analysis of the Capsule Burial Test No. 2 performed at Sandia. These test data have since been re-evaluated and have been found to compare well with the thermal conductivities that were calculated from the Capsule Burial Test. The re-evaluated data, shown in Figure 6-1, will be used in a final analysis of the burial cases described in the Accident Model Document.

6.1.2 TEST SERIES 7 - FUEL-CLAD-SOIL REACTION

The fuel-clad soil reaction tests have been completed and the results are reported in the Mound Monthly Report for February 1968. An investigation was conducted to determine whether any changes occurred in the physical or chemical properties of the fuel when in contact with soil and cladding material under earth burial conditions at elevated temperatures. Ten different soils were exposed to 1000°C for eight hours with samples of cladding and production grade Pu²³⁸ oxide microspheres. The soils tested were attapulgite, bentonite, chernozem soil, diatomaceous earth, feldspar, hematite, kaolin, montmorillonite, Ottawa sand, and Yellowstone limestone.

Mound concluded that no observable affect on the tested fuel was created by heating the fuel with the designated soil samples up to 1000°C in air for eight hours. This conclusion was based on microscopic examination, apparent density and crush strength measurements, and X-ray diffraction analysis of the tested fuel.

6.1.3 TEST SERIES NO. 12 - CAPSULE MELT DOWN-RADIANT HEAT

Radiant heat test hardware was spoiled during capsule welding at Mound thus delaying the completion of these capsules. A replacement center section assembly is being fabricated at GE and Mound is working to solve the welding problem. It now appears that radiant heat capsules will be available at Sandia for testing about mid May 1968.

Due to the recent change in the Graphite LM Fuel Cask (GLFC) to a beryllium thermal barrier, the temperature transients for the radiant heat test are being re-evaluated.

6.1.4 TEST SERIES NO. 16 - RADIATION MEASUREMENTS

Gamma and neutron dose rate measurements have been performed at Mound Laboratory on the first three SNAP-27 FCA's. The results are summarized in Table 6-1. The neutron spectrum from Capsule No. 2 bare and installed in the generator assembly are shown in Figures 6-2 and 6-3 respectively.

Figure 6-1. Ottawa Sand Thermal Conductivity

TABLE 6-1. SNAP-27 FUEL CAPSULE ASSEMBLY DOSE RATE MEASUREMENTS

(SNAP-27 Fuel Capsule Assembly Dose Rates - mrem/hr)									
Distance from Center of Fuel Capsule to Center of Detector-cm	Fuel Capsule No. 1			Fuel Capsule No. 2			Fuel Capsule No. 3		
	neutron	gamma	total	neutron	gamma	total	neutron	gamma	total
<u>Side of Fuel Capsule Assembly</u>									
20	1,604	150	1,754	1,688	165	1,853	1,800	160	1,960
25	1,089	115	1,204	1,132	120	1,252	1,237	120	1,357
40	476	48	524	490	52	542	536	36	572
50	306	29	335	319	33	352	358	23	381
100	86	6	92	93	8	101	101	5.3	106
200	27	2	29	29	2	31	31	1.5	33
<u>Domed End of Fuel Capsule Assembly</u>									
40	249	9	258	346	15	361	480	15.0	495
50	132	4.5	136.5	189	7.1	196.1	250	8.0	258
60	125	4	129	120	4.1	124.1	157	4.1	161
100	45	1	46	42	1.4	43.4	52	1.3	53
120	32	0.8	32.8	31	1.2	32.2	37	0.9	38
200	12	0.4	12.4	15	0.5	15.5	17	0.4	17
<u>Flanged End of Fuel Capsule Assembly</u>									
40	364	20	384	334	15	349	305	8.0	313
50	194	8.5	202.5	172	6.6	178.6	164	3.5	168
60	123	4	127	109	4.4	113.4	105	2.3	107
100	43	1.1	44.1	38	1.6	39.6	37	0.8	38
120	31	0.8	31.8	29	1	30	28	0.5	29
200	13	0.4	13.4	14	0.6	14.6	14	0.3	14

Figure 6-2. Neutron Energy Spectrum for SNAP-27

Figure 6-3. Neutron Energy Spectrum for SNAP-27 in Generator

6.2 SAFETY THERMAL ANALYSIS

Knowledge of the transient temperature response of a buried GLFC from the time of earth impact to capsule clad melt is necessary in determining possible graphite/capsule clad/fuel interaction rates. This analysis predicted the transient responses of three, one-dimensional burial configurations. The three configurations analyzed are as follows:

- a. Configuration I - The annulus between the columbium shield and the graphite barrel was completely filled with 1/3 dense Furilica-10 (SiO_2).
- b. Configuration II - The annulus between the Cb shield and the graphite was void of SiO_2 , thereby permitting a direct radiation path to exist between the columbium and the graphite. The outer surface of the columbium had an emissivity of 0.4.
- c. Configuration III - This configuration was a completely intact GLFC. The silver in the secondary shield was assumed to have melted due to re-entry heating.

Initial temperatures were based on an earth orbital decay re-entry for the GLFC in a lateral, spinning mode at time of earth impact (the design case with the hottest capsule temperatures at impact) and were as follows:

Cask Outer Surface	1180°F
Insulation Barrier O.D.	1640°F
Cb Shield	1920°F
Capsule Clad	2110°F
Capsule Inner Liner	2380°F

The times to complete capsule clad melt and the corresponding graphite temperatures for the three configurations investigated are shown below:

Configuration	Time to Complete Capsule Clad Melt	Corresponding Graphite Temperature
I	500 seconds	485°F
II	72 hours	2330°F
III	17.85 hours	1769°F

The transient temperature responses are shown in Figures 6-4, 6-5, and 6-6 for Configurations I, II and III respectively with Configuration I showing the least time to capsule clad melt. The 1/3 dense Furilica-10 restricted the flow of heat radially outward from the columbium shield, thereby making the outer columbium surface nearly adiabatic. Most of the energy generated by the fuel went into increasing capsule temperatures since the columbium shield had negligible mass. The thermal response of Configuration II shows the maximum time to capsule clad melt which could have been decreased if a soil with a higher thermal conductivity were used or if the emissivity of the outer columbium surface had been higher.

The initial temperatures used in the analysis are somewhat pessimistic, since convective cooling below 100,000 feet was not included in the re-entry analysis. The capsule temperature should not have been greatly affected by this convective cooling, since the time duration from 100,000 feet to impact was only 300 seconds. The graphite temperatures, however, would have been slightly lower.

Figure 6-4. Transient Burial Analysis - Configuration I

Figure 6-5. Transient Burial Analysis - Configuration II

Figure 6-6. Transient Burial Analysis - Configuration III (Intact GLFC)

6.3 SAFETY REPORTS

Drafts of Final SNAP-27 Safety Reports were reviewed by Sandia and the AEC. These drafts were incomplete in the re-entry evaluation area, since authorization has not been received to start analysis of GLFC re-entry when attached to the LM and in the area of accident probabilities and GLFC support structure descriptions, where information has not yet been supplied by NASA.

Comments were received from the reviewers and revision of the drafts was started. A late quarter design change on the GLFC secondary heat shield to beryllium has necessitated re-evaluation of a number of the accidents. Due to the extra analyses required by this design change, the Draft Final Document will not be published during the second quarter, but will be revised and issued during the third quarter. The delay in AEC/Sandia approval to start the re-entry analysis of the GLFC will require a Safety Report Addendum which will be issued during the last quarter of 1968.