DOE/MC/21338--T3

DE92 017661

PERFORMANCE EVALUATION OF A CERAMIC CROSS-FLOW FILTER
ON A BENCH-SCALE COAL GASIFIER

Westinghouse Principal Investigators
D. F. Ciliberti and T. E. Lippert

Third Quarterly Report
April 1 - June 30, 1985
Contract Number DE-AC21-84MC21338

DOE Project Officer: Randall J. Dellefield
Department of Energy
Morgantown Energy Technology Center
P.O. Box 880
Collins Ferry Road
Morgantown, WV 26505

DISCLAIMER

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Department of Energy, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, mark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

PATENT STATUS

This technical report is being transmitted in advance of DOE patent clearance and no further dissemination or publication shall be made of the report without prior approval of the DOE Patent Counsel.

TECHNICAL STATUS

This technical report is being transmitted in advance of DOE review and no further dissemination or publication shall be made of the report without prior approval of the DOE Project/Program Manager.

OVERALL PROGRAM OBJECTIVES

The Department of Energy is currently supporting a program that will aid in the development of cross flow filtration technology as applied to combined cycle power generation with coal gasification. The stated overall goal is to gain information on both the operational and economic feasibility of the implementation of cross flow filtration in various gasifier options. Westinghouse has prepared a comprehensive program that will lead directly to these program goals in an efficient manner.

The proposed program is composed of three major technical tasks. Task 1 is directed at the design and actual test of a cross flow filter at a DOE bench scale gasifier. Task 2 is composed of several smaller theoretical and experimental efforts that are intended to firm up areas where engineering and design principles are lacking or considered inadequate. The third task is intended to integrate the results of the first two tasks in a conceptual design and cost analysis such that proper economic perspective for the filter concept can be gained. A brief summary of the approach taken in the technical tasks is presented in the following discussion.

In the conduct of Task 1, we will design, fabricate, install, and operate a cross flow test system at the AGC. The actual test article will incorporate provisions for a scaled down cross flow element that will accommodate all of the gasifier flow. From this element, we will gain information on filtration parameters such as efficiency, pressure drop, and cleanability. The element will be instrumented with high speed differential pressure transducers that will allow us to quantify the pulse jet parameters that are required for successful blow back cleaning. These will subsequently serve as inputs to scaling models for full size module calculations.

In Task 2 we propose to conduct a series of independent tests. The efforts center on the following areas: 1) a task to develop a filter element with improved mounting and delamination properties, 2) a task to refine our model that describes the dynamics of pulse jet cleaning, 3) a task to quantify the dust cake properties of char and sulfur sorbent fines, and 4) a chemical stability test of the cross flow filter in a simulated gasifier environment.

The third technical task will involve the integration of new test data and model refinements into a sound conceptual design for at least three gasifier systems. Westinghouse personnel that have had past and current responsibility for commercial gasification systems design and cost analysis will assume the primary responsibility for this task. We are confident that the approach of coupling a sound scientific data base and scaling methodology with a broad systems understanding and capability will result in a sound conceptual design and costing basis.

Summary of Third Quarterly Report

Filter System Design and Supply:

Filter Vessel: The housing pressure pressure vessel for the filter was received from the local shop this quarter. It was inspected and found to be in excellent condition. The refractory system consisting of 316 SS liners and fiber frax insulating material, was installed along with other vessel internals. The internal heating system consisting of three sets of three tubular heaters were attached to the liner system, were wired and were tested over a period of several days. At 212 V each set of three heaters draws 8 amps and maintains a 1500°F internal temperature. Surface temperatures were monitored and found to be 110 °F at this internal temperature.

A new concept for mounting the cross flow filter was conceived during this report period. A design for this new arrangement was completed and the new filter mount was fabricated by in-house shops. The mount was designed so that it could be installed in the either the existing Westinghouse test vessel or the vessel being delivered to METC under the current program. The new mount has, in fact, been tested at HTHP at Westinghouse and has been adopted as the method to be used in the METC gasifier test program.

By late June, work on the vessel and internals had been completed and the equipment was prepared to be shipped to METC along with the instrument cabinet which had also been checked out earlier.

As part of the preparation for the actual testing at METC, a first version of the METC operating procedure was reviewed by Westinghouse in an effort to efficiently integrate the operation of the cross flow filter system in to the procedure. This effort was completed and a second revision of the Westinghouse cross flow filter operating procedure document was submitted to DOE project personnel for review.

Design Principles Testing:

A final test plan document for the design principles testing was completed and submitted to DOE for review during this quarter. Because of the rather tight scheduler constraints, we have proceeded with preliminary efforts in several areas of this area of the project based on conversation with cognizant DOE personnel.

Pulse Jet Cleaning Studies:

Modeling Efforts: Efforts have continued on the task of moving the pulse pressure rise and eductor portions of the existing cleaning model from the main frame R&D computer to our local IBM-XT. In this process we have undertaken to update portions of the eductor subroutines in light of more recent experience. This effort has taken more effort than expected, however, we anticipate that this work will be of value in correlation of the experimental results being obtained on the full scale pulse jet test assembly.

Experimental Efforts: During this quarter the design, fabrication and installation of the full scale cross flow filter plenum assembly was completed. Pulse rise instrumentation was installed and a microcomputer based data acquisition was installed. This system was programed to control and monitor pulse rises generated in the plenum as a function of pulse parameters such as reservoir pressure, nozzle size, nozzle position, axial position and whether or not induced flow was permitted. A preliminary set of 60 test runs was carried out in the system, and while detailed analysis of the data has not been possible yet a few general conclusions have been reached.

There does not appear to be any significant axial gradient of pulse pressure rise in the plenum.

Preventing the induction of air by capping the module top, decreases the magnitude of the pulse pressure rise.

Positioning of the nozzle with respect to the entrance of the module is important for the cleaning of the uppermost filters. If the pulse jet has not expanded to the plenum walls by the time it reaches the first set of filters, the filters will experience a negative pressure pulse and will never be cleaned.

Dust Adhesion Testing:

In this quarter the design of the test system for the dust cake adhesion tests was completed and modifications to an existing pressurizable flow reactor were completed. A four cell assembly of filter holders was designed and fabricated for installation in the modified flow reactor system, and a preliminary series of tests were carried out on PFBC ash and on gasifier char fines obtained from the KRW gasifier. These tests were first carried out at ambient conditions in order to gain experience in interpreting the pressure drop characteristics in view of the dust cake removal process. Subsequently, tests were carried out at 1500°F with the four cell assembly in the flow reactor.

Analysis of these results has not been completed yet but initial comments are as follows:

At ambient conditions the pressure drop characteristics observed can be correlated with the lifting and removal of the dust cake from the surface of the filter media.

The pressure (or velocity) required to remove the char dust deposits is very small relative to the PFBC ash. The implication is that it should be relatively to dislodge the char dust cake in the METC tests.

At elevated temperatures it is much more difficult to detect the dust cake lifting process by examination of the pressure drop curves. Char deposits do not appear to possess much of the traditional cake like behavior at elevated temperatures, and with a clean nitrogen atmosphere.

We are currently trying to assess the value of continuing this series of tests, in view of the char behavior.

Filter Supply and Testing at HTHP:

Coors: We received our first pair of flanged ceramic cross flow filter elements from Coors and their general appearance was very good. We subsequently have been able to test one of the filters in our HTHP test facility, using the newly developed mounting technique. The initial filtration properties of the filter were excellent, with an unused filter pressure drop of only 1.0 in wg at a filter velocity of 10 ft/min. During an initial period of operation we inadvertently exposed the filter to excessive forward flow pressure drop and plugged the element with soot. Some minor repairs to the element were required and residual soot had to be burned out by heating the filter element in an oven. The element was remounted and tested at 1000°F, 150 psig with a filter face velocity of approximately 6 ft/min. With a dust concentration of 7500 ppm the typical cycle time was quite constant at about 30 minutes for a base DP of 3 in wg to rise to 12 in wg. Pulse jet cleaning from a 250 psig reservoir was effective in maintaining a level baseline pressure drop. During the first day of test the efficiency was 99.99+%, however, during the second and third day of testing the efficiency was observed to decline to roughly 99%. When the filter was removed for examination it was discovered that the

element had delaminated and allowed a small amount of leakage. We are currently conferring with Coors personnel on ways to avoid this problem. Avenues being investigated include 1) the use of more glassy bonding material, 2) higher temperature firing of the elements and 3) the inclusion of a mechanical locking design.

GTE: We have received two shipments of filters from GTE during this reporting period. The first consisted of a full scale 12x12x4 cross flow filter. This element did not have the desired pore size and porosity but was very encouraging in that it demonstrated GTE's ability to fabricate the full scale version of the filter. While the bonding between layers appeared to be excellent, the back face seal was poor. To remedy this problem GTE made a novel design change in their extrusion die shape that more positively sealed the back face. The dies were machined and the first set of 12x12x4 units were shipped to Westinghouse late in June. The new back seals were effective, however, a minor problem with uneven shrinkage was caused and the two new units to have a significant slope from the back to front face. This problem can be simply solved and GTE is currently fabricating a new set of filters for test.

PROJECT STATUS FOR THIRD QUARTER

TASK 1 - Vessel and Internals Design and Testing

Vessel Supply:

In early April we took receipt of the pressure vessel to be used in the DOE/Westinghouse testing of the cross flow filter at METC. Figure 1 presents a photograph of the vessel as it was being unloaded from the delivery truck. A preliminary examination of the unit was made and the vessel appears to be in fin shape as expected.

Essentially all of the vessel internals were completed in the Westinghouse shops and were delivered to us for installation.

In May most of the vessel internals were checked for fit, and some minor modifications to liner parts were found to be necessary. These modifications were made by our shops and virtually all of the internal parts were readied. The vessel head and nozzles were insulated and lined.

We encountered some initial difficulties with supply of the tubular heaters because of vendor misinformation on stock status. We found the appropriate heaters at an alternate site and took delivery of the heaters. Even then, we encountered some additional difficulty with the fit of the tubular heaters on the vessel liner. When mounted in the heat dissipating mounts, we found we could not bend the rods to fit properly because they were too long. Fortunately an appropriate length was found to be in stock locally and we were able to obtain these heaters in a week. These have been mounted and found to fit well. We completed the installation of the lower internals, heaters, liners and insulation early in June.

Figure 1 - Pressure Vessel For Cross Flow Filter Unit Being Delivered

In the month of June, we completed installation of the power wiring to the vessel heaters. This consisted of three sets of 3 rod heaters wired in a WYE configuration. Leads in proper conduit were routed to the contactor box mounted on a support leg. Tempering 3 phase, 208V power was provided by plant electricians and the heaters and control system were checked out over a three day test period. The vessel was heated to 1500°F in 50°F increments several times in order to check the response time of the system. The heater system would raise the temperature 50° in roughly 10 min over the entire range of temperature. After the vessel was brought to temperature, thermocouples were attached to the outer surface to check metal temperature. In static ambient air the metal temperature rose to only 110°F with the internal temperature at 1500°F. This is a direct indication of the high degree of insulation provided in the system design. Additional testing consisted of a check of current flow in each of the 3 legs of the heater system. Each set was found to be drawing 8 amps at 208 volts.

Final vessel preparation consisted of insulating the spool piece that connects the filter vessel to the dust collection vessel, and in the application of temperatures sensitive paint to the vessel. This paint is blue at ambient temperatures and turns olive green at 400°F and finally to a brown color at 650°. Having completed checkout of the vessel we made preparations to ship the unit to Morgantown, in anticipation of an early July ship date.

New Filter Mounting System:

A newly developed concept for mounting the cross flow filter elements has evolved. In this concept the filter element is mounted with the clean sealed face pointed downward as shown schematically in Figure 2. In this configuration the flanged element is resting on the

Use or disclosure of data contained on this sheet is subject to the restriction on the title page of this proposal or quotation.

Figure 2 - Westinghouse Design for Cross Flow Filter Mount

horizontal sealing surface with gravity and pressure drop aiding in the seal. This design was thought to have enough merit to warrant fabrication of a mounting assembly. Therefore, we designed an assembly (shown in Figures 3 to 6) and started fabrication of the assembly in our shops. The mounting assembly was configured so that it could be used in the existing HTHP test facility at Westinghouse and also used in the DOE/Westinghouse test vessel to be delivered to METC. In May we received the new horizontal cross flow mounting assembly from our shops. The new horizontal assembly is shown in Figure 7 along with the previous vertical mount design. Figure 8 shows an exploded view of the mounting assembly and the Interam gasketing material.

Instrumentation and Control:

The control panel assembly has been completed and all the instruments have been tested (Figure 9). As mentioned above, the vessel heater control system was operated and proof tested when the vessel internals were installed and heater tests conducted.

Operating Procedure:

DOE has provided Westinghouse with their preliminary system operating procedure. We have reviewed this document and provided feedback to DOE, which has been factored into subsequent revisions. This first revision has allowed Westinghouse to update our own preliminary operating procedure and better integrate the cross flow filter system into the overall test system. A recently developed P&ID for the filter system is presented in Figure 10, and it demonstrates the evolution and integration process that is underway. We have completed preparation of our second revision and it has been delivered to DOE.

TITLE				CROSS FLOW FILTER VESSEL				REV 1.2			
DWG 7201C23				FILTER MTG BOX DET							
ITEM	NOTE	PART NAME	DEF	(SIZE) REFERENCE INFORMATION	MATERIAL	SIZE	LINK	PART NUMBER	OR REF DWG	PROCESS OR	GROUP
01		CLAMP		4.38 x .25 OF .062 THK SST TYP 316	9306-0101						
02		LOCKING PLATE		7.75 x 3.88 OF .38 THK SST TYP 316	8604-0101

CHANGE		2	316 SST WMS	304	JAN 3-28-85	1.125 R	V.R. NABUDA
2		316 SST WMS	304	JAN 3-28-85	1.125 R	V.R. NABUDA	
1		316 SST WMS	304	JAN 3-28-85	1.125 R	V.R. NABUDA	

TOLERANCES		UNLESS OTHERWISE SPECIFIED	
DEC	IN	DEC	IN
1	1	1	1
2	2	2	2
3	3	3	3
4	4	4	4
5	5	5	5
6	6	6	6
7	7	7	7
8	8	8	8
9	9	9	9
10	10	10	10

GEOMETRIC CHARACTERISTIC SYMBOLS	
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10	10

2027241	
Westinghouse Electric Corporation	
TITLE CROSS FLOW FILTER VESSEL	
FILTER MTG BOX DET	
REV 1.2	
7201C23	

Figure 5 - Cross Flow Filter Vessel Filter Mounting Box Details

DWG	TITLE

NOTE :

A - RYERSON - PGH. PA

Figure 7 - Photograph of Horizontal and Vertical Flanged Mounting System for CWXF1 Cross Flow Filter

Figure 8 - Exploded View of Coors Cross Flow Filter CWXF1
and New Horizontal Flanged Mounting Assembly

Figure 9 - Westinghouse Cross Flow Filter Control Panel

Figure 10 - METC P&ID For Westinghouse Configuration

TASK 2 - Design Principles Testing

Test Plan:

The development of a detailed test plan for all of the design principles testing was completed and delivered to DOE. However, since some of the testing is important to the upcoming testing at METC, and since that schedule is tight, we have proceeded to initiate several aspects of the test program at this point in time without having the entire design principle detailed test plan reviewed.

Blow Back System Studies

Modeling:

The existing code for the overall blow back model was transferred to local IBM-XT format in order to make complete system calculations easier. This rather large numerical model has been found to be somewhat inconvenient for the task of correlating the data currently being generated by the full scale (ambient) cross flow pulse test assembly. We have attempted to extract the pulse rise and eductor components from the large model and tailor them for use in the analysis of the pulse data being generated. This task has proved a bit more time consuming than had been anticipated, but we still feel it is appropriate and will be useful in the long run. In the later portion of this quarter we have continued our efforts to extract the eduction portion of the cross flow filter performance numerical computer model, and modify this segment so that it will be in a more convenient form for use with the experimental input from the pulse test in the large scale ambient filter module simulator. Progress has been made, and what we believe are improvements to the model have been incorporated, but have not as yet gotten the current modified version working in a fashion suitable for data reduction.

Experimental:

Assembly of the ambient full scale cross flow filter module was completed as shown schematically in Figure 11. The unit was instrumented with several differential pulse transducers which were in turn multiplexed into an A/D converter for a small microcomputer data acquisition system. A short program was prepared to scan the transducers at a rate of 1 per millisecond during the pulse and subsequently store the transducer output on disk for later analysis. The first actual test sequence was completed at the end of April with 60 different conditions being examined. The parameters examined included the following:

Pulse Pressure	200-600 psig
Nozzle Size	1/2-3/4 inch
Nozzle Position Relative to Module Inlet	0-6 inches
Induced Flow	allowed and not
Plenum Length	8-12 ft
Simulated Filter Resistance with and without Dust	clean - 4 in wg

The data gathered will be used to calibrate adjustable parameters in the pulse rise/eductor portion of the model when we get that part of the code working independently. General observations have been about as we expected, however, with measured pulse rises ranging from about 0.2 to 1.5 psi and with no discernible gradient of pulse intensity along the axis of the clean air plenum.

Figure 11- Cleaning Pulse Test System for Full Scale Cross Flow Filter Module

We have done a preliminary sorting through the data from the first test sequence which was described in last month's report. Table 1 presents the various combinations of parameters comprising this first test sequence and an indication of the approximate maximum pulse pressure rise observed.

Dust Adhesion Testing:

An essential input to the pulse jet cleaning model is the force/pressure that is required to dislodge the filter cake from the filter surface. We have planned a series of simple experiments where we will deposit gasifier fines on a filter flat and then determine the pressure required to lift that particular dust cake from a specific filter material surface under variable conditions of temperature, pressure and gaseous environment. This is accomplished by flowing gas from the clean face of the filter, and measuring the series pressure drop of the filter media and the dust cake combined. By increasing the flow, we can eventually generate enough pressure drop across the cake so that it separates from the filter surface. This point is determined by a break in the pressure drop vs flow curve where the slope decreases from the combined series resistance to a value close to that obtained by the filter media above.

We have designed a system to accomplish this type of testing and show a schematic of the apparatus in Figure 12. To carry out high temperature and pressure tests we have arranged to place up to four separate filter/dust cake adhesion units in a pressurizable furnace. Each dust adhesion test jig is provided with a controlled flow of gas that passes through the filter from the clean side. A means of continuously measuring the pressure drop across the filter flat and dust cake is provided in order to determine the separation pressure.

Table 1

PULSE JET CLEANING TEST MATRIX

Pulse Tank Pressure (Psig)	Nozzle Size (in)	Nozzle Position From Plenum (in)	Induced Flow (Y/N)	Added Flow Resistance	Plenum Length (ft)	Max Pulse Rise (psi)
200	.75	0	Y	N	12	.4
400	.75	0	Y	N	12	1.3
600	.75	0	Y	N	12	1.4
200	.75	3	Y	N	12	.4
400	.75	3	Y	N	12	1.3
600	.75	3	Y	N	12	.7
200	.75	6	Y	N	12	.4
400	.75	6	Y	N	12	1.2
600	.75	6	Y	N	12	1.1
200	.75	0	N	N	12	1.5
400	.75	0	N	N	12	.3
600	.75	0	N	N	12	.4
200	.50	0	Y	N	12	.38
400	.50	0	Y	N	12	.60
600	.50	0	Y	N	12	.75
200	.50	0	N	N	12	.10
400	.50	0	N	N	12	.35
600	.50	0	N	N	12	.38
200	.75	0	N	N	8	.20
400	.75	0	N	N	8	.60
600	.75	0	N	N	8	.75
200	.75	0	Y	N	8	.40
400	.75	0	Y	N	8	.90
600	.75	0	Y	N	8	1.5
200	.75	0	Y	Y	8	.65
400	.75	0	Y	Y	8	.75
600	.75	0	Y	Y	8	.85
200	.75	0	N	Y	9	.30
400	.75	0	N	Y	8	.75
600	.75	0	N	Y	8	.75
200	.75	0	N	Y	12	.30
400	.75	0	N	Y	12	.60
600	.75	0	N	Y	12	.60
200	.75	0	Y	Y	12	.50
400	.75	0	Y	Y	12	1.2
600	.75	0	Y	Y	12	1.6

Figure 12 -Dust Cake Adhesion Test Apparatus

Design of the dust cake adhesion test jig was fairly challenging since we were constrained by the small available space in the pressurized furnace, and the desire to be able to incorporate as many independent test cells as possible, in order to make testing as efficient as possible. The detailed design of the test cells and provisions for gas preheating coils are shown in Figures 13 through 16. This design was submitted to in-house machine shops for fabrication. Filter disks were received from Coors, and provisions were made to obtain char fines from the KRW gasifier's second cyclone.

In this report period the dust cake adhesion test assemblies were received back from the shops. Figure 17 shows a single test jig and demonstrates the path for flow in the unit. A carefully measured gas flow enters the jig through the fitting shown on the right and flow downward through the heating coil which is enclosed in the tubular furnace below the actual filter media holder. This preheated gas is then be routed to the bottom chamber of the filter flat/dust cake jig where it will then flow upward through the dust cake. The differential pressure between the clean and dusty side of the assembly is be monitored as a function of flow. Figure 18 presents a closeup of the filter flat/dust cake test jig and shows how the gasketed flat of filter media is held in place.

Figure 19 shows how the assembly of all four test jigs appears. Notice how the four heating coils occupy the bottom portion of the assembly with the four independent filter flat/dust cake assemblies are spaced above. The entire compact assembly can be lowered into a pressurized tubular heater roughly 5 inches in diameter and 15 inches long.

DUST CAKE ADHESION TEST FIXTURE ASSY									
Rev. 2D27315									
Rev.	Part Name	Mat.	QTY	Notes	Part Name	Mat.	QTY	Notes	Part Name
01	HOUSING	Steel	1		2D27315-01	Steel	1		
02	HOUSING	Steel	1		2D27315-02	Steel	1		
03	HOUSING	Steel	1		2D27315-03	Steel	1		
04	HOUSING	Steel	1		2D27315-04	Steel	1		
05	COIL TUBE	Steel	1		2D27315-05	Steel	1		
06	COIL TUBE	Steel	1		2D27315-06	Steel	1		
07	COIL TUBE	Steel	1		2D27315-07	Steel	1		
08	COIL TUBE	Steel	1		2D27315-08	Steel	1		
09	CLAMP	Steel	4		2D27315-09	Steel	4		
10	SCREW	Steel	12		2D27315-10	Steel	12		
11	WASHER	Steel	4		2D27315-11	Steel	4		
12	NUT	Steel	4		2D27315-12	Steel	4		
13	NUT	Steel	16		2D27315-13	Steel	16		

NOTE:
A - SUPPLIED BY ENGINEER

Westinghouse Electric Corporation	
DUST CAKE ADHESION TEST FIXTURE ASSY	
Rev. 2D27315	Rev. 2D27315
DATE: 10-10-54	
BY: [Signature]	
CHECKED: [Signature]	
APPROVED: [Signature]	

Figure 13 - Dust Cake Adhesion Test Fixture Assembly

11114 DUST CAKE ADHESION TEST FIXTURE

DWG 7202C49 REV

ITEM	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100	101	102	103	104	105	106	107	108	109	110	111	112	113	114	115	116	117	118	119	120	121	122	123	124	125	126	127	128	129	130	131	132	133	134	135	136	137	138	139	140	141	142	143	144	145	146	147	148	149	150	151	152	153	154	155	156	157	158	159	160	161	162	163	164	165	166	167	168	169	170	171	172	173	174	175	176	177	178	179	180	181	182	183	184	185	186	187	188	189	190	191	192	193	194	195	196	197	198	199	200	201	202	203	204	205	206	207	208	209	210	211	212	213	214	215	216	217	218	219	220	221	222	223	224	225	226	227	228	229	230	231	232	233	234	235	236	237	238	239	240	241	242	243	244	245	246	247	248	249	250	251	252	253	254	255	256	257	258	259	260	261	262	263	264	265	266	267	268	269	270	271	272	273	274	275	276	277	278	279	280	281	282	283	284	285	286	287	288	289	290	291	292	293	294	295	296	297	298	299	300	301	302	303	304	305	306	307	308	309	310	311	312	313	314	315	316	317	318	319	320	321	322	323	324	325	326	327	328	329	330	331	332	333	334	335	336	337	338	339	340	341	342	343	344	345	346	347	348	349	350	351	352	353	354	355	356	357	358	359	360	361	362	363	364	365	366	367	368	369	370	371	372	373	374	375	376	377	378	379	380	381	382	383	384	385	386	387	388	389	390	391	392	393	394	395	396	397	398	399	400	401	402	403	404	405	406	407	408	409	410	411	412	413	414	415	416	417	418	419	420	421	422	423	424	425	426	427	428	429	430	431	432	433	434	435	436	437	438	439	440	441	442	443	444	445	446	447	448	449	450	451	452	453	454	455	456	457	458	459	460	461	462	463	464	465	466	467	468	469	470	471	472	473	474	475	476	477	478	479	480	481	482	483	484	485	486	487	488	489	490	491	492	493	494	495	496	497	498	499	500	501	502	503	504	505	506	507	508	509	510	511	512	513	514	515	516	517	518	519	520	521	522	523	524	525	526	527	528	529	530	531	532	533	534	535	536	537	538	539	540	541	542	543	544	545	546	547	548	549	550	551	552	553	554	555	556	557	558	559	560	561	562	563	564	565	566	567	568	569	570	571	572	573	574	575	576	577	578	579	580	581	582	583	584	585	586	587	588	589	590	591	592	593	594	595	596	597	598	599	600	601	602	603	604	605	606	607	608	609	610	611	612	613	614	615	616	617	618	619	620	621	622	623	624	625	626	627	628	629	630	631	632	633	634	635	636	637	638	639	640	641	642	643	644	645	646	647	648	649	650	651	652	653	654	655	656	657	658	659	660	661	662	663	664	665	666	667	668	669	670	671	672	673	674	675	676	677	678	679	680	681	682	683	684	685	686	687	688	689	690	691	692	693	694	695	696	697	698	699	700	701	702	703	704	705	706	707	708	709	710	711	712	713	714	715	716	717	718	719	720	721	722	723	724	725	726	727	728	729	730	731	732	733	734	735	736	737	738	739	740	741	742	743	744	745	746	747	748	749	750	751	752	753	754	755	756	757	758	759	760	761	762	763	764	765	766	767	768	769	770	771	772	773	774	775	776	777	778	779	780	781	782	783	784	785	786	787	788	789	790	791	792	793	794	795	796	797	798	799	800	801	802	803	804	805	806	807	808	809	810	811	812	813	814	815	816	817	818	819	820	821	822	823	824	825	826	827	828	829	830	831	832	833	834	835	836	837	838	839	840	841	842	843	844	845	846	847	848	849	850	851	852	853	854	855	856	857	858	859	860	861	862	863	864	865	866	867	868	869	870	871	872	873	874	875	876	877	878	879	880	881	882	883	884	885	886	887	888	889	890	891	892	893	894	895	896	897	898	899	900	901	902	903	904	905	906	907	908	909	910	911	912	913	914	915	916	917	918	919	920	921	922	923	924	925	926	927	928	929	930	931	932	933	934	935	936	937	938	939	940	941	942	943	944	945	946	947	948	949	950	951	952	953	954	955	956	957	958	959	960	961	962	963	964	965	966	967	968	969	970	971	972	973	974	975	976	977	978	979	980	981	982	983	984	985	986	987	988	989	990	991	992	993	994	995	996	997	998	999	1000	1001	1002	1003	1004	1005	1006	1007	1008	1009	1010	1011	1012	1013	1014	1015	1016	1017	1018	1019	1020	1021	1022	1023	1024	1025	1026	1027	1028	1029	1030	1031	1032	1033	1034	1035	1036	1037	1038	1039	1040	1041	1042	1043	1044	1045	1046	1047	1048	1049	1050	1051	1052	1053	1054	1055	1056	1057	1058	1059	1060	1061	1062	1063	1064	1065	1066	1067	1068	1069	1070	1071	1072	1073	1074	1075	1076	1077	1078	1079	1080	1081	1082	1083	1084	1085	1086	1087	1088	1089	1090	1091	1092	1093	1094	1095	1096	1097	1098	1099	1100	1101	1102	1103	1104	1105	1106	1107	1108	1109	1110	1111	1112	1113	1114	1115	1116	1117	1118	1119	1120	1121	1122	1123	1124	1125	1126	1127	1128	1129	1130	1131	1132	1133	1134	1135	1136	1137	1138	1139	1140	1141	1142	1143	1144	1145	1146	1147	1148	1149	1150	1151	1152	1153	1154	1155	1156	1157	1158	1159	1160	1161	1162	1163	1164	1165	1166	1167	1168	1169	1170	1171	1172	1173	1174	1175	1176	1177	1178	1179	1180	1181	1182	1183	1184	1185	1186	1187	1188	1189	1190	1191	1192	1193	1194	1195	1196	1197	1198	1199	1200	1201	1202	1203	1204	1205	1206	1207	1208	1209	1210	1211	1212	1213	1214	1215	1216	1217	1218	1219	1220	1221	1222	1223	1224	1225	1226	1227	1228	1229	1230	1231	1232	1233	1234	1235	1236	1237	1238	1239	1240	1241	1242	1243	1244	1245	1246	1247	1248	1249	1250	1251	1252	1253	1254	1255	1256	1257	1258	1259	1260	1261	1262	1263	1264	1265	1266	1267	1268	1269	1270	1271	1272	1273	1274	1275	1276	1277	1278	1279	1280	1281	1282	1283	1284	1285	1286	1287	1288	1289	1290	1291	1292	1293	1294	1295	1296	1297	1298	1299	1300	1301	1302	1303	1304	1305	1306	1307	1308	1309	1310	1311	1312	1313	1314	1315	1316	1317	1318	1319	1320	1321	1322	1323	1324	1325	1326	1327	1328	1329	1330	1331	1332	1333	1334	1335	1336	1337	1338	1339	1340	1341	1342	1343	1344	1345	1346	1347	1348	1349	1350	1351	1352	1353	1354	1355	1356	1357	1358	1359	1360	1361	1362	1363	1364	1365	1366	1367	1368	1369	1370	1371	1372	1373	1374	1375	1376	1377	1378	1379	1380	1381	1382	1383	1384	1385	1386	1387	1388	1389	1390	1391	1392	1393	1394	1395	1396	1397	1398	1399	1400	1401	1402	1403	1404	1405	1406	1407	1408	1409	1410	1411	1412	1413	1414	1415	1416	1417	1418	1419	1420	1421	1422	1423	1424	1425	1426	1427	1428	1429	1430	1431	1432	1433	1434	1435	1436	1437	1438	1439	1440	1441	1442	1443	1444	1445	1446	1447	1448	1449	1450	1451	1452	1453	1454	1455	1456	1457	1458	1459	1460	1461	1462	1463	1464	1465	1466	1467	1468	1469	1470	1471	1472	1473	1474	1475	1476	1477	1478	1479	1480	1481	1482	1483
------	---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------

DUST CAKE ADHESION TEST FIXTURE									
COIL & TUBE WELDMENT									
TEST NO.	TEST NAME	TEST TYPE	TEST MATERIAL	TEST METHOD	TEST RESULT	TEST DATE	TEST TIME	TEST LOCATION	TEST COMMENTS
01	COIL	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
02	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
03	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
04	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
05	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
06	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
07	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
08	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06
09	TUBE	WELD	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06	122C58 H06

Hestings Electric Corporation		DUST CAKE ADHESION TEST FIXTURE	
COIL & TUBE WELDMENT		2027314	
2027314		2027314	

Figure 16 - Dust Cake Adhesion Test Fixture Coil and Tube Weldment

Figure 17 - Layout View of Dust Cake Adhesion Test Unit

Figure 18 - Close Up View of Single Dust Cake Adhesion
Test Jig

Figure 19 - Dust Cake Adhesion Test Assembly.

Preliminary Experimental Results From The Dust Adhesion Tests

During June a series of dust adhesion tests were carried out in which PFBC ash and gasifier char were examined both at ambient and at high temperature. The initial set of runs was carried out in single cells on the bench, so the characteristics of the dust cake removal could be observed visually, and so we could gain experience in recognizing the pressure drop behavior during removal of the dust cake. The final series of four tests were carried out with the four cell assembly placed in the pressurizable furnace.

The test procedure was as follows

- o The test cell was attached to a vacuum pump and a 1 gram sample of dust was dispersed in the gas stream being drawn through the filter. This dust was deposited on the surface of the ceramic filter disk which was held in the test cell.
- o Clean gas flow was then directed downward through the dust deposit and then through the filter media and the pressure drop of the series resistance of the dust and filter were measured as a function of flow.
- o The direction of the flow was then reversed so that clean gas flowed first through the filter and then through the dust deposit in an up flow orientation. As before, the pressure drop was monitored as a function of flow. During this period, discontinuities in pressure drop were visually observed and correlated with physical lifting and breaking of the dust deposit.

In early runs it became apparent that the pressure drop at which the dust separated from the filter surface was lower than the Δp transducer we had for that service, so we used an inclined manometer for the remainder of the testing.

The first test series has been completed and a summary of preliminary results is presented in Table 2. A complete set of these results and analysis will be reported in future reports, however, we offer the following general comments regarding these tests:

- o Char dust deposited on the filter surface at ambient conditions usually tends to lift up as a cake when pressure forces are exerted on it from the filter side.
- o The pressure at which this occurs for char is fairly reproducible albeit very small (.04 in wg)
- o In single cell tests pressure drop behavior could be correlated with char cake lifting.
- o At high temperature the cake like behavior is much less apparent if it exists at all. This is also true for samples removed from the furnace and then tested immediately.
- o Pressure drop at which PFBC ash is lifted from the filter surface is very much higher than the ash being typically on the order of 0.5-1.0 in wg.
- o As with the char, high temperature testing of PFBC ash did not reveal the sharp breaks in the Δp curves that had been observed in ambient tests.

Prior to a careful analysis of the data gained to date, we are developing some reservations about the probability of success in this series of tests. Before we commit to further testing we want to assess the situation, and come to a reasonable decision.

Table 2
DUST ADHESION TESTS SUMMARY

<u>Test Date</u>	<u>Dust Type</u>	<u>Comments</u>
6/12-1	Char Fines	Dust cake starts to lift and crack at
-2	"	pressure drop of .04 in wg at velocity
-3	"	of about 2 cm/min
-4	"	
6/13-1	Char Fines	Cake compressed with high downflow at
-2	"	415 cm/min and 9-10 in wg. Did not
-3	"	change velocity or pressure drop at
-4	"	which cake lifts and cracks
6/14-1	PFBC Ash	PFBC ash cake compressed at 725 cm/s
-2	"	and 32 in wg. Pressure and velocity at
-3	"	which cake lifts much higher than char.
-4	"	$\Delta p = .7 - 1.0$ in wg and velocity = 25 - 30 cm/min.
6/21-1	Char Fines	Test carried out in 4 cell assembly in
-2	"	furnace but at ambient temp. Cell 1 was
-3	"	disturbed during installation. The
-4	"	pressure drop and velocity break about 3-4 cm/min and .04 - .05 in wg.
6/25-1	PFBC Ash	Test carried out in 4 cell assembly in
-2	"	furnace at ambient temperature. Cell 1
-3	"	was the only unit that displayed a
-4	"	break in Δp curve at expected velocity/ pressure drop. Installation may have disturbed dust cake layer.
6/26-1	Char Fines	Test carried out in 4 cell assembly in
-2	"	furnace at 815°C. Were unable to
-3	"	discern any breaks in pressure drop
-4	"	curve
6/28-1	PFBC Ash	Tests carried out in 4 cell assembly in
-2	"	furnace at 815°C. Only Cell 3 showed
-3	"	a break in pressure drop behavior. The
-4	"	others did not exhibit clear change in Δp curves.

Filter Element Supply:

A summary of the filter elements received by us to date is presented in Table 3.

Coors:

Late in April we received our first two flanged cross flow filter elements from Coors. One of the elements received is shown in Figure 20. Visual inspection of the filters indicated that both filters appeared to be of excellent quality. These filter elements were prepared for testing by filing the flange edges slightly so that the element fit the mounting jig. The first of these elements was tested in late June and early July as discussed in the section on High Temperature and Pressure Testing.

GTE:

Early efforts by GTE to supply a usable cross flow filter were not successful during this quarter as they continued to experience difficulty in achieving a back face seal. GTE shipped a full scale (4" x 12" x 12") element (WGTE2) and even though the back seal was not adequate it demonstrated their ability to fabricate the large full scale units. This element is shown in Figure 21. To deal with the back face seal problem GTE went to an alternative design wherein the seal is effected by a double high end on alternate layers of the body as shown in Figure 22. New extrusion dies were fabricated, and bodies incorporating the new design were fabricated.

The first set of elements that were fabricated with the new back face seal design were fired but shrank more on the unsealed front face than the back. This gave rise to a slanted body that GTE did not feel was of use as a filter (Figure 23). GTE reports that the remedy to this situation is at hand and they are in the process of fabricating a new set of elements.

Table 3
CROSS FLOW FILTER ELEMENTS RECEIVED TO DATE

<u>Supplier</u>	<u>ID</u>	<u>Size</u>	<u>Comments</u>
Coors	WCXF1	6x6x2	Identical filter elements with flanged front fact
	WCXF2	6x6x2	
GTE	WGTE1	6x6x2	Non porous prototype. Confirms ability to make elements. Back face seal poor
GTE	WGTE2	6x6x2	Porosity lower than desired. Glued back seal poor.
GTE	WGTE3	12x12x4	Full scale elements, low porosity poor back face seal.
GTE	WGTE4	12x12x4	New back sealing method looks good. Slumped during firing caused downward slope back to front.
	WGTE5	12x12x4

Figure 20 - Coors Flanged Cross Flow Filter (WCXF-1)

Figure 21 - GTE Sylvania Full Scale Cross Flow Filter Element
(12" x 12" x 6") (WGTE3)

Dwg. 9375A13

Figure 22 - GTE Design Concept for Sealing Back Face of Cross Flow Filter

Figure 23 - Coors Filter WGTE4 Has New Design for Back Face Seal. Front (left) Face Has Shrunk More Than Back (right) Face. Result in Slanted Filter.

Corning:

During this month we have been contacted by Corning Glass Works who claim to have an interest in the area of gas cleaning using ceramic filters. We have agreed to exchange information and to pursue some method of cooperation provided some mutual interest exists.

High Temperature and Pressure Testing:

On 5/21 the first Coors filter (WCXF1) element was mounted and installed in the HTHP test facility. The first test performed consisted of flowing air through the new media and recording the pressure drop vs flow or velocity characteristics for the element at ambient conditions. Figure 24 presents a plot of these data. As Figure 24 indicates, the new never been exposed to dust, material has a very low resistance to flow with a pressure drop of only about 1 in wg at 10 ft/min.

After this brief baseline test we attempted to bring the system to temperature and pressure. Some difficulty in getting the combustor lit was experienced, and when a flame had been established it was noted that the combustion was sooty and poor. Attempts were made to "trim" the combustion by increasing the air premix to the gas feed, however, the flame remained very orange and sooty. The system was brought to a flow of 100 lbm/hr air with a system pressure of 36 psig. The temperature eventually rose to about 1250°F and the filter pressure drop was measured at 5.1 in wg. Because the technician was still having trouble controlling the temperature and system pressure, the test was stopped.

The following day the back pressure valve was cleaned and a new stem and seat were installed. The system was restarted and brought to a flow of 100 lbm/hr air, at 100 psig and a filter temperature of 1440°F. Again temperature control was poor, and the flame was very orange, indicating incomplete combustion. After some time had been spent adjusting the air premix in an attempt to achieve a clean flame, it was noticed that the filter pressure drop had gone off scale at 10 psig. The system was quickly shut down and allowed to cool for inspection.

Figure 24 - Cross Flow Filter (WCXF1) Pressure Drop vs Filter Velocity T = 70°F, P = 0 psig

The next day the system was opened and it was observed that very fine soot had covered everything in the filter housing and had plugged the filter element absolutely solid. Figure 25 shows the filter as it was lifted from the pressure vessel. Figure 26 shows how the thick (1/8") layer of hard soot could be chipped from the filter surface. When the back side of the element was examined it was observed that two large holes in the soot coating existed as seen in Figure 27. We presumed that the filter had failed in these two channels. This fact was confirmed later after the element was cleaned. Figure 28 shows the manner in which two holes had formed in the "floors" of the indicated channels. Evidently the overpressure had been so great that the filter flat had caved in at these two spots in the central outlet channel.

The mounting flange was removed and the filter was removed from the new mounting assembly. It was gratifying to note (Figure 29) that no dust/soot had penetrated the sealed and gasketed surface in spite of a very large overpressure.

While the exact level of overpressure could not be determined Figure 30 presents evidence that it was truly substantial. Notice how the thermal expansion skirt was crushed inwardly by the pressure forces across the tubesheet.

The filter was washed and brushed to remove as much soot as possible and then placed in an oven at 700°C for about a day. This procedure did a very good job of removing the soot. The unit was then repaired by filling the two damaged channels with fiber frax and glazing the outer surface with a ceramic cement. The repaired unit is shown in Figure 31. The repaired unit was remounted and installed in the test passage.

Figure 25 - CWXF1 As Removed From HTHP Test System After
Inadvertantly Filling and Coating With Soot

Figure 26 - Photo of CWXF1 Showing Thickness of Soot Accumulation

Figure 27- CWXF1 Covered with Soot Showing Area Where Holes
Formed Due to High Pressure Drop

Figure 28 - Holes Caused By High Pressure Drop Operation of
CWXF1

Figure 29 - CWXF1 Sealed Face Showing No Leaks After Being
Exposed to Very High Pressure Drop

Figure 30 - Thermal Expansion Skirt Damaged by
Over Pressure

Figure 31 - Cross Flow Filter (CWXF1) Repaired and Prepared for Further Testing

After some detective work we determined that the cause of the poor combustion control was that the trim in the natural gas fuel control valve had not been changed during the conversion from methanol operation to the natural gas firing. The C_v required for the methanol combustor was several hundred times that required for our tests with gas. The trim was replaced yielding an appropriate C_v and another test was started.

On 5/31/85 the system was brought to a flow 120 lbm/hr air at a pressure of 150 psig and a filter outlet temperature of about 1000°F. These conditions gave a filter face velocity of about 6 ft/min. We were unsuccessful in our attempts to achieve higher filter outlet temperature due to heat losses in the system. The combustor was actually running at about 2100°F but at the relatively low passage mass flow of air we could not push higher in temperature.

Dust feed was initiated and established at approximately 7500 ppm of fluid bed combustion ash. The subsequent pressure drop vs time traces are shown in Figure 32. It can be seen that the pressure drop rose steadily from a base level of 1.5 in wg to a pulse trigger pressure drop value of 11 in wg over about a 1 hour time period. The filter was then cleaned by a single pulse from a 250 psig reservoir with a 3/8" nozzle at the filter plenum outlet. The baseline pressure drop returned to a level of about 2 in wg. Six subsequent cycles were achieved that day with the baseline increasing at a slow rate to a final value of about 3.3" by the days end. For a new filter, the cycle times remained quite constant only decreasing from 38 min in the second cycle to 31 min in the seventh. The efficiency measured throughout the day was constant and essentially absolute with values exceeding 99.99%. Testing was continued during the days of 6/3 and 6/4. Test conditions were held at constant conditions over these two days and cleaning/pressure

Curve 750078-B

Figure 32 - Cross Flow Filter (WCXF1) Pressure Drop vs Time Test 5/31/85.

T = 950-1100°F, P = 150 psig, C = 7500 ppm, η = 99.99+%

V = 6 ft/min. Pulse Jet (3/8" noz., 250 psig, 0.1 sec)

drop behavior was constant, however, a perceptible decline in filter efficiency was observed, as can be seen in Figure 33. On 6/3 the average overall efficiency dropped from 99.99+% to 99.83%, and on 6/4 the efficiency declined even further to 99.147%. A decision was made to halt testing and examine the filter element. When the filter was removed from the pressure vessel it appeared to be in excellent condition but on close examination it was observed that a delamination of the filter had occurred as seen in Figure 34. When the element was removed from the mount, it was obvious that new method of mounting had been successful as there were no signs of dust leaks., except at the point of delamination.

TASK 4 - Project Management

During the month of April a paper was prepared for presentation at the Fifth Annual DOE Contractor's Meeting.

Figure 33 - Cross Flow Filter (WCXF1) Pressure Drop vs Time Test 6/3/-4/85.
 T = 1000-1100°F, P = 150 psig, C = 7500 ppm, V = 6 ft/min.
 Pulse Jet (3/8" noz., 250 psig, 0.1 sec)

Figure 34 - CWXF1 As Removed From Test Rig and Showing Dust Leak at Clean Face at Point of Delamination

END

**DATE
FILMED**

9 / 1 / 92