5/3/80

HA. 1252

DSE-3408-T1

POWER SYSTEM DEVELOPMENT (PSD) II

Ocean Thermal Energy Conversion (OTEC)

Preliminary Design Report

MASTER

August 10, 1979

Work Performed Under Contract No. ET-78-C-01-3408

TRW Defense and Space Systems Group
Redondo Beach, California

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

U.S. Department of Energy

Solar Energy

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

DISCLAIMER

"This book was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof."

This report has been reproduced directly from the best available copy.

Available from the National Technical Information Service, U. S. Department of Commerce, Springfield, Virginia 22161.

Price: Paper Copy \$22.00
Microfiche \$3.50

PRELIMINARY DESIGN REPORT

Ocean Thermal Energy Conversion (OTEC) POWER SYSTEM DEVELOPMENT (PSD) II

10 AUGUST 1979

CONTRACT NO. ET-78-C-01-3408

Prepared for
UNITED STATES DEPARTMENT OF ENERGY
WASHINGTON, D.C. 20545

TRW
DEFENSE AND SPACE SYSTEMS GROUP

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED
XAC

**THIS PAGE
WAS INTENTIONALLY
LEFT BLANK**

CONTENTS

	Page
1. INTRODUCTION	1-1
1.1 PROJECT DESCRIPTION	1-1
1.2 CONCLUSIONS	1-1
1.3 PROJECT SCOPE	1-4
1.4 TECHNICAL APPROACH	1-6
1.4.1 0.2 MWe Heat Exchangers Design	1-6
1.4.2 10 MWe Power System Module Design	1-6
1.4.3 Performance Capabilities	1-7
1.4.4 Performance/Cost	1-8
1.4.5 Safety and Maintenance	1-8
1.4.6 Power Usage	1-8
1.4.7 Environmental Impact	1-8
1.5 TECHNICAL MODIFICATIONS	1-8
2. SUMMARY	
2.1 HEAT EXCHANGERS (TEST ARTICLE AND 10 MWe POWER SYSTEM)	2-1
2.2 ROTATING MACHINERY	2-6
2.3 POWER SYSTEM CONFIGURATION AND PERFORMANCE	2-6
2.4 POWER SYSTEM COST AND NET ENERGY ANALYSES	2-8
2.5 STAINLESS STEEL FEASIBILITY STUDY	2-8
3. HEAT EXCHANGERS	3-1
3.1 10 MWe HEAT EXCHANGERS MECHANICAL DESIGN	3-2
3.1.1 Design Requirements	3-5
3.1.2 Design Approach	3-7
3.1.3 Code Considerations	3-7
3.1.4 Module Details	3-9
3.1.5 Structural Design	3-10
3.2 THERMAL/HYDRAULIC DESIGN AND PERFORMANCE	3-28
3.2.1 Configuration	3-28
3.2.2 Passage/Panel Dimensions	3-13
3.2.3 Heat Transfer Enhancement	3-33
3.2.4 Thermal/Hydraulic Design Program	3-37
3.2.5 Heat Exchanger Performance	3-39

CONTENTS (Continued)

	Page
3.2.6 Off-Design Conditions	3-45
3.2.7 Effect of Non-Evaporables on Evaporator Performance	3-46
3.2.8 Effect of Noncondensibles on Condenser Performance	3-49
3.2.9 Entrainment and Recirculation	3-53
3.2.10 Thermal/Hydraulic Design and Performance of 0.2 MWe Test Articles	3-54
 3.3 0.2 MWe TEST ARTICLES, INTEGRATION AND TEST	 3-59
3.3.1 Test Objectives	3-59
3.3.2 System Description	3-60
3.3.3 OTEC-1 Integration	3-78
3.3.4 Test Planning	3-90
 3.4 BIOFOULING CONTROL	 3-104
3.4.1 Requirements	3-104
3.4.2 Approach	3-104
3.4.3 Fouling Processes and Data	3-106
3.4.4 Biofouling Effects	3-107
3.4.5 Design Factors Influencing Biofouling Control	3-111
3.4.6 10 MWe Exchanger Tube Cleaner	3-112
3.4.7 Chlorination Subsystem	3-123
3.4.8 Heat Exchanger Intermodule Fouling Control	3-128
3.4.9 0.2 MWe Test Articles Tube Cleaner	3-128
3.4.10 Phase II Testing	3-130
 3.5 MATERIALS SELECTION	 3-134
3.5.1 Approach	3-134
3.5.2 Corrosion	3-134
3.5.3 Other Considerations	3-136
3.5.4 Sealants and Adhesives	3-136
3.5.5 Alternate Materials	3-137
3.5.6 0.2 MWe Aluminum Test Articles	3-140
 3.6 MANUFACTURABILITY	 3-142
 3.7 HEAT EXCHANGER LIFE CYCLE COSTS	 3-147
3.7.1 Objectives and Requirements	3-147
3.7.2 Approach and Assumptions	3-147
3.7.3 10 MWe Heat Exchanger Initial Capital Costs	3-148
3.7.4 Present Value Cost Analysis for Aluminum Heat Exchangers	3-149

CONTENTS (Continued)

	Page
3.7.5 Present Value Analysis for Stainless Heat Exchangers	3-152
3.7.6 Results and Summary	3-152
4. ROTATING MACHINERY	4-1
4.1 TURBINE	4-1
4.1.1 Preliminary Turbine Design	4-2
4.1.2 Optimizing the Turbine Design	4-3
4.1.3 Turbine Arrangement	4-5
4.1.4 Mechanical Design	4-7
4.2 GENERATOR	4-10
4.3 AMMONIA FEED PUMP	4-13
4.3.1 Feed Pump Selection Approach	4-15
4.3.2 Pump Seals	4-19
4.4 SEAWATER PUMPS	4-19
4.4.1 Fixed Speed Versus Variable Speed	4-20
4.4.2 Seals and Lubrication	4-23
4.4.3 Interface with Evaporator and Condenser	4-23
4.4.4 Input Power Characteristics	4-23
5. POWER SYSTEM CONFIGURATION AND PERFORMANCE	5-1
5.1 SYSTEM DESIGN	5-1
5.1.1 Design and Performance Summary	5-1
5.1.2 Process Flow Diagram	5-4
5.1.3 Piping and Instrumentation Diagram (P&ID)	5-7
5.1.4 General Arrangement	5-8
5.1.5 Mechanical Design	5-15
5.1.6 Structural Design	5-25
5.1.7 Electrical Design	5-36
5.1.8 Critical Interfaces	5-47
5.1.9 Stacked Heat Exchanger Option	5-54
5.2 SYSTEM OPTIMIZATION AND ANALYSIS	5-57
5.2.1 System Optimization	5-57
5.2.2 Design Sensitivities	5-63
5.2.3 Seawater System Dynamics	5-72

CONTENTS (Continued)

	Page
5.3 SYSTEM OPERATION AND PERFORMANCE	5-81
5.3.1 Steady-State Performance	5-81
5.3.2 Transient Performance	5-91
5.3.3 Operational Requirements	5-95
5.3.4 Startup and Shutdown	5-104
5.4 INSTRUMENTATION AND CONTROLS	5-110
5.4.1 Requirements	5-110
5.4.2 Implementation	5-110
5.4.3 Sensors	5-112
5.4.4 Control Room	5-114
5.4.5 Control System	5-119
5.4.6 Diagnostics	5-121
5.4.7 Plant Computer	5-122
5.4.8 Trips and Alarms	5-125
5.4.9 Instrumentation Wiring	5-127
5.5 RELIABILITY, AVAILABILITY AND MAINTAINABILITY	5-128
5.5.1 Introduction and Conclusions	5-128
5.5.2 Reliability, Availability, Maintainability (RAM) Requirements	5-129
5.5.3 Approach and Assumptions	5-129
5.5.4 Availability and Reliability	5-130
5.5.5 Operability/Maintainability Plan	5-142
5.5.6 Ammonia Leak Detection	5-147
5.5.7 Heat Exchanger Tube Plugging	5-150
5.5.8 Failure Modes and Effects Analysis	5-155
5.6 MATERIALS COMPATIBILITY	5-155
5.6.1 Requirements and Objectives	5-158
5.6.2 Design Approach	5-158
5.6.3 Design Materials	5-159
5.6.4 Compatibility Issues	5-159
5.7 SYSTEM SAFETY, REGULATORY REQUIREMENTS & ENVIRONMENTAL IMPACT	5-163
5.7.1 System Safety	5-163
5.7.2 Regulatory Requirements	5-165
5.7.3 Environmental Impact and Awareness	5-166
5.8 AUXILIARY EQUIPMENT	5-168
5.8.1 Ammonia Support Subsystem	5-168
5.8.2 Nitrogen Support Subsystem	5-177

CONTENTS (Continued)

	Page
5.8.3 Special Support Equipment	5-184
5.8.4 Producibility	5-186
5.8.5 Transportation	5-186
5.8.6 Installation	5-189
5.8.7 Long-Lead Items	5-195
6. POWER SYSTEM COST AND NET ENERGY ANALYSIS	6-1
6.1 POWER MODULE LIFE-CYCLE COSTS	6-1
6.1.1 Power System Initial Cost Estimates	6-3
6.1.2 Power Module Cost Analysis	6-3
6.1.3 Power Generation Cost	6-5
6.1.4 Cost Impact of NH ₃ Leaks in Aluminum Heat Exchangers	6-10
6.2 NET ENERGY AND RESOURCE ANALYSIS	6-16
7. STAINLESS STEEL FEASIBILITY STUDY	7-1
7.1 STAINLESS STEEL HEAT EXCHANGERS	7-1
7.1.1 10 MWe Heat Exchangers Material Selection	7-1
7.1.2 0.2 MWe Stainless Steel Test Articles Material Selection	7-3
7.1.3 Performance of Stainless Steel Exchangers	7-5
7.1.4 Cost of Stainless Steel Exchangers	7-6
7.2 POWER SYSTEM DESIGN	7-6
7.2.1 Changes to the Computer Model	7-6
7.2.2 Results	7-7
7.2.3 Conclusions	7-8

1. INTRODUCTION

1.1 PROJECT DESCRIPTION

This project is one of two Department of Energy (DOE) Power System Development (PSD) programs which have the general objective of improving Ocean Thermal Energy Conversion (OTEC) heat exchanger designs so that OTEC systems will provide cost-competitive electric power to the southeastern utility grid. Improvement in performance (heat transfer) and reduction of cost of heat exchangers, compared to conventional heat exchanger design and fabrication techniques, is essential for the success of the program.

The development projects are PSD-I, restricted to shell-and-tube type heat exchangers of either state-of-the-art or advanced heat transfer techniques; and PSD II, restricted to "shell-less" heat exchangers. The PSD-I analyses indicated that using relatively standard fabrication techniques result in heat exchangers with costs approaching \$1,000 per kilowatt. To be cost competitive with conventional power plants, therefore, the goal of PSD II is to design heat exchangers with a lower life cycle cost (not to exceed \$700 per kilowatt) through application of mass production fabrication technology.

This report describes the TRW/Linde PSD II project results, Contract ET-78-C-01-3408. The power system design is for a 10 MWe net power output configuration based on enhanced plate type heat exchangers by Union Carbide Corporation's Linde Division, Tonawanda, New York (Linde) (see Figure 1-1). The system engineering and power system design are by TRW's Defense and Space Systems Division, Redondo Beach, California (TRW). The power system (see Figure 1-2) is designed for a specified DOE plant ship.

1.2 CONCLUSIONS

The commercialization of OTEC is contingent on reducing the capital cost of the power plant since there is no fuel cost. That is, once deployed and operating, the energy (fuel) for producing OTEC power is derived from the sun via warm surface waters working in a thermodynamic cycle which rejects heat to the arctic cooled ocean depths. TRW PSD II power system design, based on enhanced plate type heat exchangers,

Figure 1-1. TRW/Linde PSD II Heat Exchange

minimizes the capital cost by coupling relatively efficient power conversion with existing mass production techniques. It thus offers a competitively attractive power generation system, either on a plant ship or connected to a utility grid.

Aluminum, due to the low initial cost, ease of fabrication and general availability was the proposed heat exchanger material. Phase I design has been specifically oriented toward a power system capable of being operated, maintained and repaired using aluminum heat exchangers. The heat exchangers made from Alclad aluminum alloys (e.g., aluminum 3004) will last ten years or longer in a seawater environment if appropriate anti-corrosion protection is incorporated in the design. The complexities of accomplishing adequate protection and the associated risk stimulated an investigation of alternate materials. This investigation (feasibility study) conducted by TRW and Linde has concluded that an equally viable enhanced plate type heat exchanger can be fabricated from super stainless steel (e.g., Allegheny 6X). A comparison of the costs of the two approaches indicates that (Figure 1-3) aluminum heat exchangers

Figure 1-2. 10 MWe Power Module System

(at an initial cost of \$320/kWe) lasting 14 years will have equal present value to that of 30-year life stainless steel heat exchangers (at an initial cost of \$561/kWe). Either of these materials can be readily applied to the final design and will result in attractive power system costs.

Figure 1-3. TRW/LINDE PSD-II 10 MWe Heat Exchangers Present Value Vs. Life

Since the generating cost of power is a better determinant of the commercial potential of OTEC, the additional system capital and operation cost have also been evaluated. These costs coupled with the present value cost of heat exchangers, using various fixed charge rates result in power generation cost as illustrated by Figure 1-4.

1.3 PROJECT SCOPE

This project is separated into two phases. Each phase is per project definitions outlined by DOE.

Figure 1-4. PSD II 10 MWe Power Generation Costs

Phase I - October 1978 through June 1979

- Conceptual and preliminary design of a 10 MWe power module using shell-less heat exchangers (aluminum)
- Conceptual and preliminary design of a 0.2 MWe test evaporator and a condenser representative of the full size exchangers
- Preparation of Phase II plan (proposal) for detail design, development, fabrication and checkout of the test heat exchangers and installation and operational support on an ocean-based government furnished test facility (OTEC 1).

Phase II (redefined by instructions/guidance of 3 April 1979)

- Conceptual and preliminary design of a 10 MWe closed cycle ammonia power system module with super stainless steel heat exchangers (optional)
- Design, fabrication, and delivery of test article heat exchangers representative of power system design

- Design, fabrication, and delivery of any special ancillary equipment required for handling, delivery, field fabrication/ installation, and operation of the test hardware on OTEC-1
- Participation and support of the OTEC-1 Systems Interface Control Working Group and Test Planning and Instrumentation Working Group
- Provision for manufacturer's representative support during three years of OTEC-1 operations.

This report describes the design conclusions of Phase I and provides the technical rationale for proceeding on to Phase II.

1.4 TECHNICAL APPROACH

The technical approach is illustrated by Figure 1-5. (As noted thereon, several tasks for this project and those of TRW's PSD-I project using vertical tube falling film heat transfer techniques were similar and resulted in project cost savings.) The following sections summarize the principal issues and the consideration given to them during the conduct of the project. (These were originally defined in the PSD II request for proposal.)

1.4.1 0.2 MWe Heat Exchangers Designs

The 0.2 MWe heat exchangers are representative models of the full scale units. Our design approach has been to first develop the full scale concepts, then assess the critical parameters affecting performance (for example, scaling considerations), and finally formulate a design. The production of this unit is planned using prototype tooling and fixturing; the resulting hardware will confirm the fabricability and performance of the 10 MWe module.

1.4.2 10 MWe Power System Module Design

The power module design task primarily required matching the performance of the main power unit elements to the unique characteristics of the heat exchangers considering the need to package the power module efficiently into the candidate hull. As our design is based on aluminum of a 10 to 15 year life, emphasis has been put on designing methods to repair and/or replace heat exchangers (the design requirement is for a 30-year power system.) Modularization of the heat exchangers which achieve maximum production cost benefits also allows flexibility for startup/ shutdown and maintenance activities.

Figure 1-5. Summary Technical Approach

1.4.3 Performance Capabilities

The 0.2 MWe and the 10 MWe systems have been designed and analyzed with the aid of computer programs. These programs provide capabilities for both design and off-design performance evaluations (for example, seawater temperature differences, seawater and ammonia flow and pressure drop variations, fouling and overall heat transfer, and availability).

1.4.4 Performance/Cost

TRW has evaluated the relationship of power system capital cost to cost of generated power considering system and component design and performance factors. The objective has been to design a power system which has low capital (\$/KWe) and a low power generation cost (mills/KW-hr) (see Conclusions, Section 1.2).

1.4.5 Safety and Maintenance

TRW has identified the potential safety hazards of testing 0.2 MWe heat exchangers and 10 MWe power module operations. This information will be used with ship systems contractors to establish safety requirements for the PSD II test hardware. Preventive maintenance and scheduled downtimes are built into the design to assure system availability. Startup considerations are part of the system design to assure starting reliability.

1.4.6 Power Usage

Gross power of 13.87 MWe is generated by the 10 MWe (net) power system module. TRW has optimized the system performance parameters to minimize power loads of the support systems and equipment. Computer programs developed for PSD-I and other OTEC programs have been used for system design, performance evaluations, and sensitivity analyses.

1.4.7 Environmental Impact

During the conceptual and preliminary design phase, we have remained aware of the environmental impact of the mechanical cleaning of fouled heat exchanger tubes, chlorination, metallic elements, and release of working fluid and have incorporated these factors in our design.

1.4.8 0.2 MWe Test Operation

The test heat exchangers have been designed for integration and test on board DOE's OTEC-1. Conceptual test plans, with instrumentation, to provide design verification of the full scale heat exchangers have been completed.

1.5 TECHNICAL MODIFICATIONS

Two significant design assumptions affected the progress of the preliminary design and resulting conclusions. These assumptions were:

- 1) The space allocation on the specified hull for the power module was assumed to be the full aft half of the APL plant ship (see Figure 1-6). The result is a power system consisting of four evaporator and four condenser module subassemblies on a single elevation. This configuration is addressed in detail in the report.

A request to package the module into "one-half of the after half" of the APL plant ship has been responded to at a conceptual level. This evaluation, which has two evaporator and two condenser module subassemblies on different elevations, has verified the physical capability to install a power module with a plan area less than required by the basic design.

- 2) At the beginning of this project, little data existed to confirm or deny the capability to design economically viable heat exchangers of aluminum for a 30-year design life power system. Research and study conclusions are now that alclad aluminum may be made to last for ten years or longer and, coupled with maintenance/repair/replacement procedures, a system can be developed to assure acceptable availability. Some risk remains, however, for the near term application of OTEC power system using this material.

Due to this risk and since the heat exchanger design is not materials dependent, alternate materials (i.e., longer life) have been evaluated for feasibility of application. One such material, a super stainless steel alloy, has been found to offer a competitive cost to aluminum. As a result of this study, further work with this material has been offered as an option for Phase II.

Figure 1-6. PSD II Power Module in OTEC Pilot Plant Ship Hull
1-10

2. SUMMARY

This report documents the results and conclusions of the PSD II, Phase I, preliminary design of a 10 MWe OTEC power system, using enhanced plate type heat exchangers, and of representative 0.2 MWe test articles. It further provides the documentation (specifications, drawings, trade studies, etc.) resulting from the design activities. A summary of the requirements and capabilities is in Figure 2-1.

The data and discussions of the technical concepts are organized to respond to the PSD II, Phase II proposal evaluation criteria. This volume, which specifically addresses the three evaluation categories (heat exchangers, rotating machinery, and power system configuration and performance) is an integral part of the Phase II plans (proposal) which describe the technical approach to delivering test articles to OTEC-1. In addition, there is a section which addresses power system cost and net energy analysis and another which discusses the results of stainless steel feasibility studies. Supporting documentation is contained in two appendix volumes. Appendix I contains the specifications and drawings prepared during the course of the contract. Appendix II contains trade studies, calculations and reports which provide the rationale for design conclusions. These appendices are organized to satisfy the deliverable documentation requirements of the Phase I Statement of Work.

2.1 HEAT EXCHANGERS (TEST ARTICLE AND 10 MWe POWER SYSTEM)

The major effort of the TRW/Linde PSD II preliminary design has been to evaluate options and select heat exchanger designs which are both thermally and hydraulically efficient and capable of mass production; thereby satisfying the cost objective of \$700/kWe. Detailed discussions of the design and the supporting rationale are contained in Section 3. Sub-sections therein are organized to enable the technical conclusions to be evaluated relative to the indicated DOE criteria (Phase II proposal instructions.)

10 MWe Heat Exchangers (Section 3.1)

A physical description of the heat exchangers, including the structural details, is contained in this section. A basic conclusion is that

the design is mechanically sound, considering all the static and dynamic loads of a shipboard installation, and capable of being code approved. Further, it is compact, readily maintained and cleaned, operates with ammonia and is producible with current manufacturing techniques.

Thermal/Hydraulic Performance (Section 3.2)

A close coupling of the mechanical design and thermal/hydraulic performance is required to assure optimum, cost effective design. The basic structural design results in configurations which are thermally efficient and capable of analysis using vertical thermo-siphon reboiler technology. Further, data from UCC/Linde experience and recent Argonne tests of enhanced ammonia surfaces have been used to provide assurance of operational performance. The analysis indicates that the overall heat transfer coefficient for the evaporator will be 820 and for the condenser will be 623 Btu/hr-ft²-F°.

Test Articles and Integration (Section 3.3)

The Phase II activities are to deliver scaled (0.2 MWe), representative heat exchangers fully integrated with test support equipment (phase separator and tube cleaner) for installation and performance verification tests at sea on board the DOE OTEC-1. This section discusses the test articles, integration concepts and recommended data collection consistent with defined test objectives. The test heat exchangers are mechanically identical to a full size heat exchanger and thermal/hydraulic performance will be fully verified. The fabrication of these exchangers will prove the manufacturing techniques, cost and code acceptability of the design.

Biofouling Control (Section 3.4)

The specified requirement for biofouling control is to maintain the average fouling resistance below 0.0005 (°F-hr-ft²/Btu). The solution to this requirement is to mechanically brush each water passage at a frequency of once a week which, along with a low dosage rate of chlorination (0.05 ppm), is projected to maintain the fouling at 0.0003 (average). The heat exchanger seawater passages are smooth and circular and fully accessible for in-situ cleaning. The details of the design configuration and basis for the assumptions are contained in this section.

Figure 2-1. PSD-II Requirements Versus Capabilities

DESIGN AND FUNCTIONAL REQUIREMENTS	SOLUTION AND/OR APPROACH	REPORT REFERENCE SECTION NO.
THE DESIGN SHALL BE BASED ON AN OCEAN ENERGY RESOURCE OF 82°F FOR THE SURFACE SEAWATER AND 40°F FOR THE DEEP SEAWATER, UTILIZING A ΔT OF 42 F DEGREES. PERFORMANCE SHALL ALSO BE SHOWN PROVIDING A ΔT RANGE FROM 32 F DEGREES TO 45 F DEGREES.	<ul style="list-style-type: none">• THE DESIGN (OR NOMINAL) ΔT IS 42°F WITH WARM WATER TEMPERATURE OF 82°F AND COLD WATER TEMPERATURE OF 40°F.• PERFORMANCE HAS BEEN ANALYZED OVER FULL RANGE OF ΔT.	5.1, 5.2, I-2, II-1 5.3, II-2, I-2
THE DESIGN SELECTED SHALL GIVE CONSIDERATION TO MANUFACTURABILITY, AND BIOFOULING AND CLEANING.	<ul style="list-style-type: none">• MANUFACTURABILITY IS A MAJOR DESIGN CONSIDERATION IN PARTICULAR WITH REGARDS TO HEAT EXCHANGERS: MANUFACTURING PLANS, AND RATIONALE FULLY DESCRIBED FOR FULL SCALE PROTOTYPE, PRODUCTION ARTICLES, AND TEST ARTICLES.• HEAT EXCHANGERS ARE CLEANABLE BY REASON OF ACCESSIBLE ROUND WATER FLOW PASSAGES WHICH WILL BE MAINTAINED CLEAN BY MECHANICAL BRUSHING AND CHLORINATION.	3.3, 3.6, II-10, 4.1 3.4, I-10, I-3, II-7
THE WORKING FLUID TO BE USED SHALL BE CHOSEN ON THE BASIS OF THERMOPHYSICAL AND OTHER APPROPRIATE PROPERTIES.	AMMONIA SELECTED BECAUSE OF SUPERIOR THERMODYNAMIC AND HEAT TRANSFER PROPERTIES. DATA BASED ON NBS-142.	5.1, 5.2, II-1, II-2
THE HEAT EXCHANGER MATERIAL SHALL BE CHOSEN TO BE COMPATIBLE WITH SEAWATER AND THE CHOSEN WORKING FLUID AS WELL AS WITH MATERIALS IN THE POWER MODULE. THE MATERIAL CHOSEN SHOULD ALSO EXHIBIT GOOD JOINABILITY, STRENGTH, THERMAL PROPERTIES, ETC.	EXTENSIVE MATERIAL INVESTIGATIONS HAVE RESULTED IN SELECTION OF TWO CANDIDATE HEAT EXCHANGER MATERIALS: 1) ALCLAD ALUMINUM 2) "SUPER" STAINLESS STEEL ALCLAD ALUMINUM IS COMPATIBLE WITH SEAWATER UNDER CONDITIONS WHERE VELOCITY OF WATER IS CONTROLLED AND GALVANIC ACTION RESTRICTED. STAINLESS STEEL ALTERNATE HAS SUPERIOR LIFE CAPABILITY IN SEAWATER USE.	3.5, 5.6, II-14
THE CONTROL SYSTEM FOR THE 10 MWe POWER MODULE SHALL BE DESIGNED TO OPTIMIZE THE POWER OUTPUT FOR BOTH DESIGN AND EXPECTED OFF-DESIGN OPERATION.	CONTROL SYSTEM INCLUDES ADAPTIVE CONTROL FEATURES (AMMONIA LIQUID LEVEL AND TURBINE INLET GUIDE VANES) TO OPTIMIZE POWER AT ALL OPERATING CONDITIONS.	5.3, 5.4
THE DESIGN OF THE 10 MWe POWER MODULE SHALL BE BASED ON A 30-YEAR DESIGN LIFE AT 8000 HOURS PER YEAR OPERATION WITH AT LEAST 1000 START/STOP CYCLES.	<ul style="list-style-type: none">• MATERIALS SELECTED TO MEET DESIGN LIFE GOAL; EXPECT ONE REPLACEMENT OF ALUMINUM HEAT EXCHANGERS.• AVAILABILITY ANALYSIS INDICATE THAT OPERATIONAL GOAL WILL BE MET BY A COMPREHENSIVE MAINTENANCE PROGRAM.	3.5, 5.6, II-14, 5.5
ALL ITEMS SHALL BE DESIGNED TO APPROPRIATE GOVERNMENT AND INDUSTRIAL CODES TO COVER ALL PHASES OF SAFETY.	SAFETY HAS BEEN CONSIDERED IN THE DESIGN. APPROPRIATE ASME AND USCG CODES GOVERN SAFETY AND ARE REFERENCED IN THE SYSTEM AND COMPONENT SPECIFICATIONS. UCC/LINDE WILL WORK WITH THE ASME CODE AUTHORITY TO QUALIFY THE DESIGN FOR ASME STAMP.	5.7, I-1 THRU 10
REDUNDANCY OF DESIGN TO ENSURE CONTINUITY OF KEY FUNCTIONS, AS WELL AS FAIL-SAFE OPERATIONS ARE REQUIRED.	REDUNDANCY OF CRITICAL COMPONENT PROVIDED IN THE DESIGN (AMMONIA PUMPS, HEAT EXCHANGER MODULARITY) AS WELL AS THROUGH INSTRUMENTATION (ALARMS, INTERLOCKS).	5.4, 5.5
A SURFACE PLATFORM/SHIP (ATTACHMENT 1) SHALL BE USED AS THE BASIC REFERENCE HULL FOR CONCEPTUAL DESIGN. SPACE AND ACCELERATION REQUIREMENTS OF THIS CANDIDATE OTEC-10 PLATFORM ARE AS NOTED IN ATTACHMENT 1.	<ul style="list-style-type: none">• THE JHU/APL PLANT SHIP IS THE REFERENCE HULL. TWO ARRANGEMENTS HAVE BEEN DEVELOPED WHICH SATISFY SPACE CONSTRAINTS: 1) BASELINE, AFT SECTION OF SHIP (PREL. DESIGN) 2) ALTERNATE, HALF OF AFT HALF OF SHIP (CONCEPTUAL DESIGN ONLY)• ACCELERATIONS AND AMPLITUDES ARE INPUT TO STRUCTURAL AND FUNCTIONAL DESIGN, MINIMAL IMPACT ON HEAT EXCHANGER DESIGN.	5.1, 5.2, I-2 3.2, 5.1, 5.2, 5.3, II-3, II-6
THE APPROXIMATE TOTAL PRESSURE DROPS FOR THE WARM AND COLD WATER SYSTEMS SHALL NOT EXCEED 10 FEET AND 15 FEET OF WATER, RESPECTIVELY.	TOTAL SYSTEM PRESSURE DROPS ARE: – WARM WATER SYSTEM: 7 FEET OF SEAWATER – COLD WATER SYSTEM: 12 FEET OF SEAWATER THESE VALUES RESULT FROM SYSTEM OPTIMIZATION STUDIES, SENSITIVITY AND ANALYSES	5.1, 5.2
THE AMMONIA (OR OTHER WORKING FLUID) VAPOR PRESSURE DROP WITHIN EACH HEAT EXCHANGER POWER MODULE (INCLUDING OF MANIFOLDING) SHALL NOT EXCEED 2 PERCENT THE VAPOR PRESSURE DIFFERENCE AT 82°F IN THE EVAPORATOR AND AT 40°F IN THE CONDENSER.	OPTIMIZED PRESSURE DROP WITHIN VAPORSIDE INCLUDING MANIFOLDING LOSSES, PHASE SEPARATOR LOSSES, PIPING AND VALVING LOSSES AND EXCHANGER NOZZLE LOSSES TOTAL 0.8 PSI, WELL WITHIN THE SPECIFICATION.	5.1, 5.2, II-1
THE 10 MWe POWER MODULE RATING REFERS TO THE NET BUS BAR POWER AVAILABLE AFTER ALL PARASITIC LOSSES, AUXILIARY EQUIPMENT AND HOTEL REQUIREMENTS (APPROXIMATELY 450 KW FOR HOTEL) ARE SATISFIED.	NET POWER IS 10 MWe AT NOMINAL CONDITIONS. GROSS POWER IS 13.9 MWe. PARASITIC POWER INCLUDES IN ADDITION TO AMMONIA AND WATER PUMPING LOSSES, 112.5 KWe FOR HOTEL (PER 10 MWe, 450 MWe PER 40 MWe) AND 350 KWe FOR AUXILIARY EQUIPMENT.	5.1, 5.2, 5.8
FOULING (BIOLOGICAL AND CHEMICAL) OF HEAT EXCHANGERS MUST BE CONTROLLED NOT TO EXCEED A FOULING FACTOR OF $\frac{0.0005 \text{ HR-FT}^2\text{-}^\circ\text{F}}{\text{BTU}}$. IMPROVEMENT OF THIS VALUE SHOULD BE A DESIGN GOAL.	DESIGN FOULING FACTOR IS .0003 HR-FT ² -°F/BTU FOR BOTH EVAPORATOR AND CONDENSER. MECHANICAL BRUSHING APPROXIMATELY ONCE A WEEK COMBINED WITH CONTINUOUS LOW DOSES OF CHLORINATION. INTERMITTENT LARGE DOSES CAN BE SUPPLIED, IF REQUIRED.	3.4, II-7
THE AUXILIARY STARTING POWER AND OPERATIONAL AUXILIARY POWER SHALL BE QUANTIFIED. SEQUENTIAL LOGIC AND PROCEDURES FOR PHASED TEST EQUIPMENT AND PROTOTYPE MODULE STARTUP/SHUT DOWN MUST BE ADDRESSED.	INCLUDED IN INSTRUMENTATION AND CONTROL DESIGN.	5.3, 5.4
THE STAGED APPLICATION OF TORQUE ON PUMP MOTORS SHALL BE CONSIDERED IN THE DESIGN.	DISCUSSED IN DESIGN REPORT. SELECTED DESIGN EMPLOYS NON-STAGED PUMP MOTORS.	4.4, 5.3
THE USE OF VARIABLE VERSUS FIXED WATER FLOW THROUGH THE HEAT EXCHANGERS SHALL BE ASSESSED IN CONJUNCTION WITH NET OUTPUT MAXIMIZATION DURING OFF-DESIGN OPERATION.	TRADEOFF STUDY SHOWS THAT FOR SPECIFIED ΔT VARIATION OF -4°F TO +3°F VARIABLE SPEED PUMPS CANNOT BE JUSTIFIED ON THE BASIS OF NET POWER OPTIMIZATION.	4.4, 5.3
PROVISIONS SHALL BE MADE FOR EFFICIENT MAINTENANCE DURING DOWNTIME.	CONSIDERED IN DESIGN-MODULARITY OF HEAT EXCHANGERS SIMPLIFY MAINTENANCE AND IMPROVES INTEGRATED POWER OUTPUT.	5.1, 5.3, 5.5, II-11
OPERABILITY ASSURANCE WHICH SHALL BE MET AFTER AN INITIAL CHECKOUT PERIOD ARE: 90 PERCENT AT A 60 PERCENT CONFIDENCE LEVEL.	MONTE-CARLO SIMULATION USING MTBF AND MTTR DATA SUPPLIED BY INDUSTRY VERIFIES THAT THE REQUIREMENT WILL BE MET WITH A SMALL MARGIN. DUAL NH ₃ PUMPS REQUIRED.	5.5
SYSTEM STARTING RELIABILITY (SUCCESSFUL STARTS DIVIDED BY ATTEMPTED STARTS) SHALL BE 95 PERCENT AT A 60 PERCENT CONFIDENCE LEVEL.	MONTE-CARLO SIMULATION INDICATES THAT REQUIREMENT WILL BE MET WITH AMPLE MARGIN.	5.5
THE FOLLOWING POWER USAGE CRITERIA SHALL BE ADDRESSED: PARTIAL LOAD AND TURNDOWN, LOAD SHEDDING, AND STARTUP LOAD CARRYING CAPABILITY, AND POWER CONDITIONING (TRANSFORMATION AND RECTIFICATION).	THESE CRITERIA WERE INPUT TO THE ELECTRICAL SYSTEM, AND INSTRUMENTATION AND CONTROL SYSTEM DESIGN.	5.1, 5.4, I-6, II-5
ENVIRONMENTAL IMPACT INFORMATION RELEVANT TO THE CHOICE OF WORKING FLUID SHALL BE PROVIDED.	CONSIDERED IN DESIGN. AMMONIA LEAK DETECTION, COLLECTION AND MAINTENANCE PROCEDURES WILL MINIMIZE ENVIRONMENTAL IMPACT.	5.5, 5.7, 5.8, I-5

**THIS PAGE
WAS INTENTIONALLY
LEFT BLANK**

Materials Selection and Corrosion (Section 3.5)

Considerable effort has been expended in assessing material options for the heat exchangers. The baseline material (originally proposed) has been aluminum. Evaluations of alloys and their susceptibility to corrosion in an ocean environment resulted in a conclusion that for 3004 Alclad the operating life of the heat exchangers will be 10 years or longer. Concern, however, with the risks associated with using aluminum of indeterminate life and possible failures, resulted in assessments of alternative materials. The conclusion is that an alloy similar to AL-6X is a preferred material for near-term 10 MWe power system heat exchangers, with test articles of either material depending on criticality of DOE schedules. These alloys do not have the environmental concerns of coppernickel nor the high cost of titanium and are fully compatible with the ammonia working fluid.

Manufacturability (Section 3.6)

A key concern to the OTEC program is ability to manufacture the heat exchangers in a cost effective manner. The analysis of the facility requirements reveals that the test articles can be produced at the existing UCC/Linde facilities in New York with little impact. A detailed evaluation of the type of facilities required for production of 0.625 MWe heat exchanger modules at a rate of 100 MWe per year is also included. The techniques required to produce these articles are outlined using proven technology and offer low cost options to standard shell and tube designs.

Cost Analysis (Section 3.7)

Detail cost analyses for mass produced aluminum or super stainless steel heat exchanger modules have been prepared and are reported in this section. The analysis indicates that either aluminum heat exchangers with an initial capital cost of \$367 per kilowatt (life cycle cost depends on life of the heat exchangers) or stainless steel with an initial capital cost of \$642 per kilowatt will meet the DOE objective of production heat exchangers at a cost below \$700 per kilowatt. These cost projections are based on standard production cost procedures and include transportation and installation charges of 14.4 percent.

2.2 ROTATING MACHINERY

Since the primary objective of this PSD II project has been to design cost effective heat exchangers and, since the performance parameters of the power system are very similar to the TRW PSD-I power system design, little new work has been done in the area of rotating machinery. A review of the PSD-I selected equipment, however, was made and revised specification sheets have been prepared. The equipment includes a four stage, double flow, axial turbine (designed by Elliott); an air cooled 4160 volt, 18 MWe capacity generator, (Brown Boveri); horizontal, centrifugal, variable speed ammonia pumps (Ingersoll-Rand); and vertical, axial, propeller type seawater pumps; all reconfigured to match the unique installation requirements of PSD II. These equipment definitions are satisfactory for a preliminary design. These items are discussed in Sections 4.1 through 4.4.

2.3 POWER SYSTEM CONFIGURATION AND PERFORMANCE

A second major activity (to that of heat exchanger design) of PSD II has been the integration of the heat exchangers into a power system capable of being packaged within the DOE specified plant ship and providing a net power output of 10 MWe under operating conditions defined by DOE. Section 5 provides the detailed conclusions for specific areas.

System Design and Description (Section 5.1)

The 10 MWe power system consists of a basic power loop (heat exchangers, turbine-generator and pumps) and support subsystems. The detailed descriptions of the major system elements are contained in this section. The principal conclusion is that a gross power output of 13.87 MWe yields the 10 MWe net required by DOE. The power budget includes 240 kWe for ammonia feed pumps, 112.5 kWe hotel load as specified by DOE, and 350 kWe for miscellaneous loads. The major system parasitic power use is for seawater pumps, allocated at 3.17 MWe.

An optional packaging configuration for the power system has also been evaluated to allow greater flexibility of power system-to-ship integration design. This option, although not optimum, indicates that the power system can, conceptually, be packaged in a space taking approximately 50 percent of the plan area currently used for the design (i.e., using only one-half of the aft half of the APL plant ship).

System Optimization and Analysis (Section 5.2)

The 10 MWe design has been developed by matching the heat exchanger performance characteristics and cost, the options for installation (i.e., number of modules in series) and the gross/net power outputs. Conclusions as to optimum water flow rate and modular configurations are contained in this section. Also included are results of design sensitivity analyses and seawater system analyses.

System Operation and Performance (Section 5.3)

The capability of the power system to be set in operation, operated, and shut down at sea on an OTEC platform has been evaluated. The results of these evaluations, with respect to effects on power generation, are contained in this section.

Instrumentation and Controls (Section 5.4)

An assessment of the approach to control of a 10MWe power system, based on the operation and performance characteristics described in section 5.3, and the required instrumentation is discussed.

Reliability, Availability, Maintainability (Section 5.5)

The critical need to have power generation which is reliable and meets the availability requirements with cost effective maintenance/repair techniques has been given careful consideration. Analyses have shown that the proposed design will meet the specified availability requirement of 0.9 and satisfy the design life requirements using either aluminum or stainless steel heat exchangers. These analyses, however, have been key to decisions to offer stainless steel as the best option for near term OTEC power systems. Design solutions for leak detection and repair or replacement of heat exchangers are equally applicable to either material, however, the frequency of application is less for stainless steel than aluminum and thus the probability of a successful demonstration of OTEC power system capabilities is greater with stainless steel. The data and conclusions are in this section.

Materials Compatibility (Section 5.6)

The need for careful material control, if using aluminum heat exchangers, has been included as a part of the design considerations. The requirements and constraints for material compatibility are contained in this section.

System Safety, Regulatory Requirements and Environmental Impact (Section 5.7)

Discussions of each of these constraining issues are contained in Section 5.7. Safety issues, as identified through hazard analysis techniques; specification of applicable regulations; and assesment of possible environmental impacts, relying heavily on IRW's UTEC 1 activities, have been defined and considered in the design of the power system.

Auxiliary Equipment (Section 5.8)

Assumptions and specifications of required support equipment are discussed in this section.

2.4 POWER SYSTEM COST AND NET ENERGY ANALYSIS

Assessments of the power system generation cost, based on different heat exchanger options and life cycle cost, are contained in section 6.1. The rationale for the projection of heat exchanger costs below DOE's specified requirement of \$700 per kilowatt and anticipated power generation cost of about 35 mills per kilowatt-hour are included. Further, the power module net energy and resource analysis indicates a ratio of 22 to 1 for delivered energy to energy input.

2.5 STAINLESS STEEL FEASIBILITY STUDY

Due to the concerns with the expected life of aluminum in seawater, stainless steel was selected as the alternative heat exchanger fabrication material. The results of the study for both the heat exchangers and the resulting effect on the power system are presented in Section 7.

3. HEAT EXCHANGERS

This section of the report documents the analysis and design of heat exchanger configurations. The primary requirement has been to design "shell-less" heat exchangers with consideration for manufacturing, biofouling and cleaning for use in an OTEC power system. The study has demonstrated that compact, surface-enhanced heat exchangers will result in a lower initial capital investment than shell-and-tube exchangers. A secondary requirement has been to design representative test heat exchangers for installation and test on board DOE's OTEC-1.

The general design considerations for the 10 MWe power module heat exchangers are discussed in Section 3.1. The associated thermal-hydraulic analyses of the heat exchangers are presented in Section 3.2. The analyses show that the choice of materials (aluminum or stainless steel) for the heat exchangers has little effect on the overall physical size of the exchanger although the active heat transfer area and water flow requirements for the stainless steel option are greater by approximately 10 percent. The 0.2 MWe heat exchanger test articles, of the same basic design as the module developed for the 10 MWe power system, are discussed in Section 3.3. The test article size will demonstrate the structural integrity and thermal/hydraulic performance for full size modules and for 10 MWe and larger OTEC power plants. The test plans, integration concept and the support equipment requirements for the 0.2 MWe heat exchangers are also presented in Section 3.3.

The critical maintenance concern of biofouling control is discussed in Section 3.4. A significant feature of the TRW/Linde power module heat exchangers is the accessibility of the water flow passages (tubes) formed by the panels. These tubes are planned to be mechanically brushed weekly, although it is feasible to do so twice a week. This cleaning, in conjunction with chlorination and periodic manual cleaning, should maintain the fouling resistance well below the required $0.0005 \text{ hr-ft}^2\text{-}^\circ\text{F/Btu}$ (the design base is an average of 0.0003) based on the evaluation of available DOE studies. Verification tests of the concept are planned as part of the 0.2 MWe test article program.

The selection of materials and corrosion control methods for the heat

exchangers are discussed in Section 3.5. The important technical considerations such as effects of biofouling and deterioration are included. The relative merits of aluminum and stainless steel, a critical consideration for near term and longer term potentials of OTEC, are covered in this section. The associated manufacturing conclusions are discussed in Section 3.6. The general plans required to produce OTEC power modules at a rate of 100 MWe per year are included therein. The detail plans for 0.2 MWe heat exchangers are a part of the Phase II plans.

A key factor in promotion and success of future OTEC power plants is reliable cost estimates for the heat exchangers. Since the heat exchangers represent a substantial portion of the cost of the power system, the cost estimates have been carefully prepared with specific emphasis placed on quantity production costs. The results of this study are discussed in Section 3.7. Costs for aluminum and super stainless steel 10 MWe heat exchangers are presented. The 10 MWe aluminum heat exchanger costs are estimated at \$320/KWe, whereas the alternative design stainless steel heat exchanger costs are estimated at \$561/kWe (before shipping and installation).

Aluminum, the proposed baseline material, has been evaluated in depth. As an alternative, stainless steel heat exchangers have also been evaluated. The structural design for stainless steel is conceptually similar to the aluminum heat exchangers with structural members constructed from a combination of stainless steel panels and carbon steel structural support members (strongbacks, headers, etc.). This is feasible since the two types of alloys can be welded to each other easily. Stress calculations for this concept have been made to assure feasibility of the material. (These are documented in Appendix II, Section 8.) The sizes of the heat exchangers are similar to the aluminum heat exchangers. Based on this limited design effort, stainless steel is as viable as aluminum for the design. The initial cost is higher, but lower maintenance costs, longer life expectancy and other factors make the life cycle cost of stainless steel competitive with aluminum.

3.1 10 MWe HEAT EXCHANGERS MECHANICAL DESIGN

The concept for the 10 MWe power system heat exchangers is based upon the development work performed at UCC/Linde during the past decade for automotive radiator application. These shell-less heat exchangers with enhanced surfaces provide an attractive performance to cost ratio when compared to

conventional commercial designs. The basic material considered has been an Alclad aluminum alloy used successfully in automotive work and with demonstrated durability in hostile environments.

During the preliminary design phase the module concept has been refined through close study of the structural and thermal/hydraulic requirements. A total of 32 modules are required for a 10 MWe power plant - 16 evaporator and 16 condenser modules of 0.625 MWe rating each. The condenser and evaporator are the same size and have been designed with common components to minimize costs. Each module is approximately 14 feet high, 20 feet long and 4 1/2 feet deep (in the seawater flow direction), and contains 204 active heat transfer panels. A typical heat exchanger module is shown in Figure 3.1-1. The modules are arranged in groups of four in series in the water flow direction (see Figure 3.1-2) to utilize more fully the thermal capacity of the seawater. The panels have a corrugated shape so that water flow passages are formed by abutting two panels together (see Figure 3.1-3). Internal to each panel is the ammonia flow passage, which has an enhanced heat transfer surface.

Figure 3.1-1. Module Showing Strongbacks

Figure 3.1-2. Heat Exchanger Subassembly

Figure 3.1-3. Basic Panel Concept

The module panels are grouped and manifolded on the ammonia side to an upper and lower semi-cylindrical header. The pressure within the panels - 167 psig design pressure - is restrained by two end plates or strongbacks which are tied together by the use of side rails and the semi-cylindrical header (see Figure 3.1-4). Aside from the task of forming and welding the relatively large assemblies, no new technologies are required to fabricate, test or transport the exchangers. The details of the stress calculations and design details are commensurate with a preliminary design level.

Figure 3.1-4 Semi Cylindrical Header Construction Concept

3.1.1 Design Requirements

The basic design requirement of the OTEC PSD II Heat Exchangers is to blend thermal-hydraulic performance with mechanical practicality. These factors have proved to be mutually compatible with no significant compromises. Further, the exchangers are required to operate in a 10 MWe power system under the constraints discussed in section 5.1. A summary of the requirements and solutions for the heat exchangers is contained in Figure 3.1-5. Detail discussions of these items are contained below and in the appendices.

DESIGN AND FUNCTIONAL REQUIREMENTS	SOLUTION AND/OR APPROACH
<p>(A) ENERGY RESOURCE</p> <p>THE DESIGN SHALL BE BASED ON AN OCEAN ENERGY RESOURCE OF 82°F FOR THE SURFACE SEAWATER, AND 40°F FOR THE DEEP SEAWATER, UTILIZING A ΔT OF 42°F DEGREES. PERFORMANCE SHALL ALSO BE SHOWN PROVIDING A ΔT RANGE FROM 32°F DEGREES TO 45°F DEGREES.</p>	<p>TRW OPTIMIZATION STUDY DETERMINED NOMINAL OPERATING CONDITIONS FOR BOTH EVAPORATOR AND CONDENSER BASED ON OCEAN TEMPERATURE RANGE AND HAS SET PERFORMANCE REQUIREMENTS ON THE HEAT EXCHANGERS.</p>
<p>(B) CONSTRUCTION</p> <p>ALL HEAT EXCHANGERS SHALL BE OF THE "SHELL-LESS" CONSTRUCTION. THE DESIGN SELECTED SHALL GIVE CONSIDERATION TO MANUFACTURABILITY, AND BIOFOULING AND CLEANING.</p>	<p>UCC ENHANCED PLATE TYPE EXCHANGERS ARE SHELL-LESS AND HAVE EASE (LOW COST) OF MANUFACTURE. THE ABILITY TO CLEAN IS ENHANCED BY ACCESSIBLE, ROUND WATER FLOW PASSAGES.</p>
<p>(C) WORKING FLUID</p> <p>THE WORKING FLUID TO BE USED SHALL BE CHOSEN ON THE BASIS OF THERMOPHYSICAL AND OTHER APPROPRIATE PROPERTIES. AMONG THE WORKING FLUIDS WHICH HAVE BEEN CONSIDERED ARE: AMMONIA, PROPANE, OTHER HYDROCARBONS, AND FLUOROCARBONS. THE CONTRACTOR IS NOT LIMITED TO THESE WORKING FLUIDS.</p>	<p>AMMONIA WAS PROPOSED FOR THIS DESIGN AS THE WORKING FLUID FOR REASON OF ITS EXCELLENT PROPERTIES IN A THERMODYNAMIC CYCLE. NO ADDITIONAL TRADE STUDIES HAVE BEEN CONDUCTED.</p>
<p>(D) MATERIAL COMPATIBILITY</p> <p>THE HEAT EXCHANGER MATERIAL SHALL BE CHOSEN TO BE COMPATIBLE WITH SEAWATER AND THE CHOSEN WORKING FLUID AS WELL AS WITH MATERIALS IN THE POWER MODULE. THE MATERIAL CHOSEN SHOULD ALSO EXHIBIT GOOD JOINABILITY, STRENGTH, THERMAL PROPERTIES, ETC.</p>	<p>ALCLAD ALUMINUM IS COMPATIBLE WITH SEAWATER UNDER CONDITIONS WHERE VELOCITY OF SEAWATER IS CONTROLLED AND GALVANIC ACTION IS RESTRICTED. STAINLESS STEEL AS AN ALTERNATE, HAS SUPERIOR LIFE CAPABILITY IN SEAWATER USE. THE DESIGN WORK HAS BEEN DONE BASED ON ALUMINUM WITH A FEASIBILITY ASSESSMENT OF OTHER MATERIALS.</p>
<p>(E) DESIGN LIFE</p> <p>THE DESIGN OF THE 10 MW_e POWER MODULE SHALL BE BASED ON A 30 YEAR DESIGN LIFE AT 8000 HOURS PER YEAR OPERATION WITH AT LEAST 1000 START/STOP CYCLES.</p>	<p>THE DESIGN LIFE OF 30 YEARS IS AT THE POWER MODULE LEVEL. THE HEAT EXCHANGERS, BASED ON ALUMINUM ARE PROJECTED TO HAVE AN OPERATING LIFE OF 10 TO 20 YEARS AND ARE REPLACEABLE. THE STAINLESS STEEL IS PROJECTED TO HAVE A 30 YEAR LIFE.</p>
<p>(F) INSTALLATION</p> <p>THE TRANSPORTATION, HANDLING, AND INSTALLATION APPROACHES OF THE 0.2 MW_e HEAT EXCHANGERS AND THE 10 MW_e POWER MODULE SHALL BE EXPLAINED. ANY SPECIAL EQUIPMENT NEEDED SHALL BE CLEARLY SPECIFIED.</p>	<p>THE INSTALLATION, HANDLING APPROACH FOR THE FULL SCALE MODULES (0.625 MW_e) AND THE 0.2 MW_e TEST ARTICLES ARE ESSENTIALLY THE SAME. THESE MODULES ARE TRANSPORTABLE BY TRUCK.</p>
<p>(G) CODES</p> <p>ALL OF THE ITEMS SHALL BE DESIGNED TO APPROPRIATE GOVERNMENT AND INDUSTRIAL CODES TO COVER ALL PHASES OF SAFETY.</p>	<p>THE HEAT EXCHANGERS ARE PLANNED TO BE QUALIFIED TO ASME CODES. THE PRELIMINARY DESIGN HAS USED CODE CRITERIA AS A GUIDE. PHASE II WILL REQUIRE WORKING WITH CODE AUTHORITY.</p>
<p>(H) A SURFACE PLATFORM/SHIP (ATTACHMENT 2) SHALL BE USED AS THE BASIC REFERENCE HULL DURING CONCEPTUAL DESIGN.</p>	<p>THE HEAT EXCHANGERS ARE DESIGNED TO ENABLE THE POWER MODULE TO BE INSTALLED IN THE DOE CONCEPTUAL SHIP.</p>
<p>(I) THE APPROXIMATE TOTAL PRESSURE DROPS FOR THE WARM AND COLD WATER SYSTEMS SHALL NOT EXCEED 10 FEET AND 15 FEET OF WATER, RESPECTIVELY.</p>	<p>THE HEAT EXCHANGER BUDGETED PRESSURE LOSS ALLOWS VELOCITIES OF 6 FT./SEC. WHICH ARE ADEQUATE TO OBTAIN THE REQUIRED HEAT TRANSFER PERFORMANCE AND FOULING CONTROL.</p>
<p>(J) THE AMMONIA (OR OTHER WORKING FLUID) VAPOR PRESSURE DROP WITHIN EACH HEAT EXCHANGER POWER MODULE (INCLUSIVE OF MANIFOLDING) SHALL NOT EXCEED 2 PERCENT THE VAPOR PRESSURE DIFFERENCE AT 82°F IN THE EVAPORATOR AND AT 40°F IN THE CONDENSER.</p>	<p>PRESSURE LOSS ON AMMONIA SIDE OF HEAT EXCHANGERS IS WITHIN THIS RESTRICTION.</p>
<p>(K) FOULING (BIOLOGICAL AND CHEMICAL) OF HEAT EXCHANGERS MUST BE CONTROLLED NOT TO EXCEED A FOULING FACTOR OF $0.0005 \frac{\text{HR-FT}^2\text{-}^\circ\text{F}}{\text{BTU}}$.</p>	<p>DESIGN CALCULATIONS ARE BASED ON AN AVERAGE OF 0.0003 FOULING FACTOR WHICH CAN BE OBTAINED BY BRUSHING TECHNIQUES.</p>
<p>(L) PROVISIONS SHALL BE MADE FOR EFFICIENT MAINTENANCE DURING DOWNTIME.</p>	<p>THE MODULAR APPROACH PROVIDES FOR REMOVAL OF DEFECTIVE HEAT EXCHANGER ASSEMBLIES. CRITICAL AREAS ARE ACCESSIBLE FOR MAINTENANCE.</p>
<p>(M) THE DESIGN OF THE 0.2 MW_e HEAT EXCHANGER SHALL BE GOVERNED BY THE SPACE AVAILABLE ON OTEC-1. THE HEAT EXCHANGERS SHALL ALSO BE DESIGNED TO MEET THE ACCELERATIONS EXPECTED ON THE TEST PLATFORM OF OTEC-1 IN STORM CONDITIONS.</p>	<p>THE TEST HEAT EXCHANGERS WILL FIT IN THE ALLOCATED SPACE AND THE DESIGN WILL MEET THE SPECIFIED ACCELERATIONS. ADDED SPACE IS REQUIRED FOR THE INSTALLATION AND SUPPORT EQUIPMENT.</p>
<p>(N) SIMILARLY, THE 10 MW_e POWER MODULE SHALL BE DESIGNED TO MEET THE SPACE AND ACCELERATION REQUIREMENTS OF THE OTEC-10 PLATFORM TO BE SELECTED BY THE GOVERNMENT.</p>	<p>THE EXCHANGERS ARE STURDILY DESIGNED TO MEET LOADINGS DUE TO SHIP ACCELERATIONS.</p>

Figure 3.1-5. Heat Exchanger Requirements/Approach Matrix

3.1.2 Design Approach

The structural design for the core has been approached by use of the patented Linde Isostress heat transfer surface exchanger core geometry. This approach, coupled with Linde's patented surface enhancement techniques for evaporation and condensation performance, provides core geometry with the following advantages:

- Shell-less construction
- Highly formable in most materials
- High compatibility with thermal/hydraulic requirements
- Replaceable mass-produced modules
- Condenser and evaporator similarity
- Accessible seawater flow passages for maximum cleanability
- Compact, mechanically efficient construction.

Strongbacks, header beams, and upper and lower heads provide horizontal constraints for the heat exchanger core. The core consists of heat transfer panels and downcomer assemblies (see Figure 3.1-4). The strongbacks, together with the downcomers, carry vertical tensile forces and serve to tie the upper and lower heads together.

3.1.3 Code Considerations

The structural design of the heat exchangers was based on the following regulations and specifications:

- 1) "Rules and Regulations for Cargo and Miscellaneous Vessels", CG-257, September 1, 1977
- 2) "Rules and Regulations for Tank Vessels", CG-123, August 1, 1977
- 3) "A Manual for the Safe Handling of Flammable and Combustible Liquids and Other Hazardous Products", CG-174, September 1, 1976
- 4) "Marine Engineering Regulations", CG-115, August 1, 1977

- 5) "ASME Boiler and Pressure Vessel Code", Section VIII, Division 1
- 6) OSHA Standard 1910.11 - Storage and Handling of Anhydrous Ammonia.

The first two regulations are of background interest to the preliminary heat exchanger mechanical design. They concern the outfitting and equipment of vessels and deal with lifeboat specifications, fire fighting equipment, etc. These regulations are of primary concern to the naval architect.

The third regulation is a manual for tankermen and provides a general view of safety equipment and procedures found on board ships and practiced by USCG regulated vessels. This manual, too, serves as a source of background information for the preliminary mechanical design.

The fourth manual, the Marine Engineering Regulations, contains regulations dealing with engineering components and is the publication that most affects the design. Review of the regulations has shown that USCG certification will be required for the heat exchangers. Fortunately, the USCG regulations have adapted the ASME Boiler and Pressure Vessel Code, subject to certain specified modifications which tighten the code. The regulations also give procedures for requesting exemptions and for requesting certification of designs not covered by the regulations.

The ASME code was consulted for allowable stress values and acceptable methods for joint construction and welding for all applicable sections of the power modules. Code certification is planned to be obtained in pressure tests during detail design of the test articles and design documentation. The actual certification will take one of two forms. The first, the simplest and least costly approach, is to have the heat exchangers treated as a multi-chambered vessels. In this case, the upper and lower headers are considered separate, independent vessels joined by piping (the panels). It will be necessary to apply the standard hydrostatic test (150% of maximum allowable working pressure) to each header separately. This approach, analogous to plate heat exchanger practice, has the benefit that each header can be shown to be in compliance with the code calculations per the provisions of Section VIII, Division 1, and the panels can be treated as piping (their

enclosed volume is small and hence are not required to meet the code). The following procedures will have to be used if heat exchanger certification is obtained by this method:

- Demonstrate by calculation that those components covered by the code are in conformance
- Qualify welds by testing per provisions of the code
- Test the complete heat exchanger assembly to 150 percent of maximum allowable working pressure.

The second approach is more complex but more certain. This is to treat the heat exchangers analogously to brazed aluminum heat exchangers. In this case, the headers would be shown to be in compliance by calculation and it would be necessary to demonstrate compliance of the panels by proof test. The proof test probably would require that at least a cubic foot of representative core be pressurized to failure. This test would establish maximum allowable working pressure for the core and the results would be generalized to all identically fabricated cores. Finally, the entire heat exchanger would be subjected to the standard hydrostatic test. The following procedures will have to be used if heat exchanger certification is obtained by this method:

- Demonstrate by calculation that those components covered by the code are in compliance
- Qualify welds by testing per the provisions of the code
- Fabricate test equipment and samples to proof test representative samples of the core
- Test the complete heat exchanger assembly to 150 percent of maximum allowable working pressure.

The actual process applied will be determined during the detail design phase.

3.1.4 Module Details

Each heat exchanger module is composed of a number of panels. Sheets are corrugated to form both water and ammonia flow passages and are assembled in pairs to form a panel. The corrugations of the plates act as self-supporting structural members for the internal pressure. Internal

separators are provided at regular intervals allowing the panel to withstand external pressures.

The panels are stacked beside each other and supported at each end by the cylindrical shell structure. This provides the required distribution of ammonia flow through each panel.

The condenser and evaporator panels are identical in size and shape with different enhancement surfaces on the ammonia side only. Flow passages within the panels are identical. Stiffeners are equally positioned along the panel width to carry external loading. Downcomers, located at equal intervals and stacked in series with the panels, provide structural integrity to the semi-cylindrical headers by resisting internal hydraulic pressures and allow liquid recirculation in the evaporator. These internal downcomers are equally spaced across the face of the heat exchanger to give the same number of flow passages per section. This greatly eases the cleaning process. The condenser downcomers, which function only to strengthen the core, are orificed at their upper end to minimize flow through them. A corrugated stiffener is used inside each downcomer.

The semi-cylindrical headers are fixed at each end by structural components called strongbacks. These carry not only the majority of the tensile load developed by the internal pressures in the headers, but also the pressure loading from the panels. This box-like structure resists the high bending moments in each corner and minimizes panel deflection along each side.

The weight of each module is 30,500 pounds. This weight includes the strongbacks, upper shell weldment, lower shell weldment, downcomers, tube envelopes, and header beams. A detail breakdown of the component weight and internal module volume is presented in Appendix II, Section 8.

3.1.5 Structural Design

The pressure at operating condition, determined from the system requirements and analysis, is 135 psia for the evaporator and 92 psia for the condenser. The corresponding design pressure has been set at 167 psig based on a saturation pressure at 85°F plus ten percent. The structural members are designed, as discussed herein, to provide vessels meeting the ASME Code. The heat exchanger structural system has also been evaluated

considering the dynamic loads resulting from platform motions. The platform induced dynamic loads, specified as equivalent static loads and expressed as multiples of the gravitational acceleration, are well within acceptable limits of design. Details of the analysis are contained in Appendix II, Section 8.

3.1.5.1 Panels

The panels are based on a geometry derived from Linde's experience with automotive radiators. They are mass producible and structurally efficient. The panels are corrugated so that when assembled, they form essentially circular 0.75 inch diameter water passages accessible from the face of the exchanger. The panel tips are in full contact with no movement under internal pressure loading. Stress analyses performed on the panel shape with thickness variations from 0.018 to 0.032 inches showed that the panel structure had relatively low stress levels and that failures would result from a yield or buckling condition. Assuming a margin of safety of five times the design pressure, a material thickness of 0.025 inches is required. This is shown graphically in Figure 3.1-6.

Figure 3.1-6. Aluminum Panel Thickness Requirements

The aluminum alloy materials considered for the design are presented in Figure 3.1-7. Additional analysis of the originally proposed panel material, 3004-H32, has shown that the H32 temper could not be formed satisfactorily. Since cladding has been determined to be essential for corrosion protection, the 3004-0 Alclad material was chosen. The total design sheet thickness (inches) is 0.050, including 0.010 cladding on the water side.

CORE ALLOY	TEMPER	ALLOWABLE STRESS (PSI)	CORE THICKNESS W/O CLAD (INCH)	CALCULATED CORE STRESS (PSI)
3004	H-32	6,300	0.025	5,300
3004	0	4,900	0.032	4,800
3003	H-14	4,500	0.036	4,500
5052	H-32	7,700	0.025	5,300
5052	0	6,200	0.025	5,300
5086	H-32	10,000	0.025	5,300
5086	0	8,700	0.025	5,300

Figure 3.1-7. Minimum Core Thickness (Structural)

The ASME code allowable stress for 3004-0 is 5500 psi. Therefore, the panel wall thickness has been calculated to be 0.013 inches.

An additional 0.012 inch thickness has been added to satisfy code requirements. For this thickness the maximum allowable working pressure is 313 psig, which provides a 1.84 margin of safety over the internal design pressure.

To withstand an external differential pressure of 15 psi, a number of panel stiffeners have been included. An allowable stress of 90% of minimum yield stress, or 7650 psi, has been used as the design basis. This was chosen since the external pressure of 15 psig is not a working load, but a periodic condition. Considering the panel between the stiffeners as a simply supported beam, the maximum bending stress is equal to 7050 psi which gives a margin of safety from external collapse of 1.08.

The flat panel ends at the header section are adhesively sealed tight and are not exposed to the 15 psig external pressure. Therefore, a corrugated-type stiffener design is not included for this particular section.

Panel Test Program. A test program has been conducted to demonstrate that the heat exchanger modules can withstand code-required hydrostatic pressures. Since the panel structure is buckling-failure critical, as opposed to stress-failure critical, it needs to withstand five times the design pressures, or approximately 850 psi. This represents an as-corroded condition.

The test apparatus, which consists of a top and bottom plate 2 inches thick and approximately 16 inches square, is shown in Figure 3.1-8. An additional 1/2 inch thick plate is available for high pressure testing (500 psi). Equally spaced along the perimeter of the fixture are four 1/2 inch nut and bolt fastener assemblies. Spacers between each plate perform two functions: they (1) determine the required test panel thickness and (2) act as a fixture stop to resist any panel movement.

Figure 3.1-8. Test Fixture

Test specimens are panel sections with approximately 1 foot square material thickness of 0.050 inches. The panels are welded along the total perimeter and liquid pressure tap plus an air bleed tap are welded on one side of the panel (see Figure 3.1-9).

Figure 3.1-9. Photograph of First Test Panel Before Pressure Test

Test Results. The test results of 5052-H32 annealed to -O condition indicate that the proposed panel configurations and wall thicknesses will withstand the code required hydrostatic pressures. The first panel tested failed at a buckling pressure of approximately 300 psig. This low failure number was attributed to poor end restraint; therefore, the test results were considered non-representative of actual design conditions.

The second test panel showed good end restraint. This was accomplished by adhesively potting both panel ends. This panel failed at 850 psig by weld failure (panels were TIG welded). Upon removal for rewelding, the panel showed no signs of buckling failure.

After reweld, panel buckling failure occurred at approximately 950 psig. As shown in Figure 3.1-10, a total of four ridges buckled. Visual check of the other ridge surface showed slight to significant deformation.

Figure 3.1-10. Photograph of Second Test Panel After Pressure Test

Sample sections of a typical panel were also checked for material thickness. Plate thickness before forming was 0.050 inches. Plate thickness after forming showed a 0.0025 inch reduction in the arc (valley) region (0.0475 inches thick) and approximately 0.009 inch reduction in the ridge corner region (0.041 inches thick). The dimensions of these formed sections are shown in Figure 3.1-11.

Figure 3.1-11. Formed Panel Thickness

Therefore, for a material thickness of 0.041 inches, the theoretical buckling pressure can be estimated as:

$$P_{CR} = \frac{Et^3 \left(\frac{\pi^2}{\alpha^2} - 1 \right)}{12r^3 (1-\nu^2)} = 3650 \text{ psi}$$

where: $E = 10 \times 10^6$
 $t = .041$ inches
 $\alpha = 1.358$ radians
 $r = .425$ inches
 $\nu = .33$

The margin of safety against buckling, estimated from the calculated buckling pressure for a safety factor of 5 and an allowable pressure of 730 psi, the margin of safety is:

$$M.S. = \frac{950}{730} = 1.3$$

This value is within acceptable limits for design.

3.1.5.2 Downcomers

The use of internal downcomers provides two important functions.

- 1) It eliminates the need for separate recirculation circuit plumbing, and
- 2) It contributes to the structural integrity of the upper and lower semi-cylindrical headers.

The latter is due to approximately 1/3 of the total tensile load induced by internal pressure on the shells being carried by the downcomers.

The downcomer structure consists of two 1/4 inch thick side plates similar in width and length to the panels as shown by Figure 3.1-12. End bars provide 1) the downcomer opening (1" width), and 2) a sealed rectangular box-like structure. These bars, in turn, are welded to the header plate to form the shell-to-downcomer structure. In between, and throughout the total length of the side plates, is a corrugated structure which provides the stiffness necessary to withstand internal hydraulic pressures from the

Figure 3.1-12. Evaporator Downcomer

panels. The panels butt to each downcomer and are welded at both the top and bottom edges. The semi-circular seawater passage between the side of the downcomer and the first panel is plugged with adhesive to eliminate ammonia vaporization in the downcomer.

The combination of the relative spacing, stiffness, and number of downcomers necessitated using the elastic foundation analysis for the cylindrical shell-downcomer design. The limiting factor for the actual size and number is the maximum allowable bending stress in the shell-to-strongback attachment. The analysis, therefore, is one of trial and error.

The starting point in the analysis is the minimum downcomer opening (width). When the opening is fixed at 1 inch plus and a workable side plate thickness is selected, the cross sectional stiffness can be calculated. This leads to the final optimization of the number of downcomers and permits analysis of the shell bending stress. Having met the required allowable shell stress, the downcomer is stress analyzed.

The downcomer is subjected to three types of loading under normal operating conditions:

- 1) Vertical tensile load produced by the shell deflection (upwards)
- 2) Lateral tensile load produced by the shell deflection (sideways)
- 3) Internal pressure difference between the ammonia and seawater sides.

The total maximum stress in the downcomer has to meet allowable stress requirements before the design is acceptable. Appendix II, Section 8 reports this analysis in detail. The results indicate that 11 downcomers of the dimensions mentioned above are required.

3.1.5.3 Manifolds

Several different means of enclosing the area at the ends of the tube envelopes have been investigated. Rectangular aluminum extrusions, spherical segments, and cylindrical manifolds were among methods considered. These design options (illustrated in Figures 3.1-13 to 3.1-17) were evaluated by assessing the ability of each to satisfy the following criteria:

- Perform safely at the design pressure while maintaining material stress levels below those allowed by the applicable codes, keeping material and fabrication costs to a minimum

Figure 3.1-13. Rectangular Aluminum Extrusion Module Assembly

- Provide the necessary disengagement height to allow entrained liquid ammonia to separate out of the evaporator discharge before the vapor enters the outlet nozzle
- Permit periodic inspection of the tube-to-tube weld joints and determine the effects of internal corrosion, if any.

The selected cylindrical shell design clearly displays advantages in all three areas. Although a thicker wall is required than for the spherical segment approach, the additional material cost is offset by the savings in fabrication cost. In addition to providing ample disengagement height, the cylindrical shell approach offers the most flexibility with regard to cleaning and inspection requirements. (See Appendix II, Section 8 for detailed design calculations.)

Figure 3.1-14. Rectangular Aluminum Extrusion Module Assembly

3.1.5.4 Header Beam

The header beam is a separate piece and functions primarily as a part of the shell weldment assembly to significantly increase the section modulus, thus reducing gross deflections and maintaining fiber stresses within the limits allowed by the ASME Code. The large cross-sectional area (14 in² each) keeps tensile stresses within limits and constrains longitudinal elongation caused by the action of hydraulic forces acting against the strongbacks. The cylindrical shells also act as tensile members; thus these two components are considered together. The header beam also serves as a convenient method of sealing the transition area from the thick-walled cylindrical shell to the thin-walled tube envelopes. A weld adaptor is used which matches the cross-sectional areas and minimizes the effect of unbalanced thermal conduction and uneven melting. The upper portion of this adaptor is welded to the header beam while the

Figure 3.1-15. Spherical Segment Module Assembly

lower portion is welded to the tube ends so that a hermetic seal is provided along the entire length. The header beam and weld adaptors are illustrated in Figure 3.1-18.

3.1.5.5 Strongbacks

The structural attachments between the upper and lower cylindrical shells are subject to considerable bending moments due to the action of hydraulic forces over a large area (3.6×10^6 in. lbs). These structural attachments, called strongbacks, are therefore designed to have very large moments of inertia at the points of high bending moment. This is accomplished by constructing the strongback in the form of a multi-web I-beam whose depth decreases linearly with distance from the longitudinal centerline. The webs, or gussets, are spaced apart such that the inter-gusset plate bending stresses are maintained at acceptable levels. The tube envelope contact surface (outside of two-inch plate) will be machined after welding to achieve the flatness necessary to provide an adequate tube-ridge support.

Figure 3.1-16. Spherical Segment Construction Detail

During the module construction process, the strongbacks will be aligned relative to the tube hole grid within a specified tolerance before welding. This will be accomplished through the use of jigs and fixtures, and will insure that the final module-to-module alignment procedure can be performed with a minimum of module shifting and shimming.

The strongback provides for dynamic load transmission from the heat exchangers to the skid assembly. Gussets transmit the support forces from the mounting pads to the strongback "bottom" plate through the attaching fillet welds. This mounting scheme provides a clean interface with the ship support structure (mounting skid) and simplifies the design of the electrical isolation and tie down hardware.

Figure 3.1-17. Cylindrical Module Layout 0.625 MWe

Figure 3.1-18. Header Beam and Weld Adaptor

3.1.5.6 Inter-Unit Seals

For the 10 MWe modular assemblies (Figure 3.1-19), the seawater is confined to the area between modules, bounded by the header beams and the strongbacks. The rationale for this decision was two-fold:

- 1) Submersion of the entire module in seawater would invite severe macro-fouling problems in view of the very low peripheral seawater velocity and difficulty of cleaning the strongbacks, piping, etc.
- 2) Massive ship bulkheads would be required under conditions of complete submersion to withstand the hydraulic pressure differential induced when the 4-module bay was drained for inspection
- 3) More pumping power would be required under conditions of complete submersion since the seawater moving around the module periphery would be unavailable for transferring heat, requiring total mass flow to be increased.

Figure 3.1-19. Module Assembly

The principal criterion for selecting the Sealmaster Inflatable Elastomer Seal is its high reliability. Each seal is custom molded into its working configuration and is integrally reinforced with fabric. By avoiding splices, the overall reliability is increased. In addition, these inflatable seals have demonstrated excellent performance in use under adverse conditions by major industries. A secondary consideration is that by deflating the seal under operating conditions, the inter-module region can be flushed of macro-particles.

Finally, the greatest advantage of this sealing technique is the simplicity with which the seal can be installed and replaced and the resulting simplification of replacing individual modules. Since these seals are custom fabricated, their cost is inversely proportional to the quantity purchased. The seal is shown in the installed position in Figure 3.1-20.

Figure 3.1-20. Inter-Unit Seal Detail

3.1.5.7 Nozzles

Inlet and outlet nozzles on the evaporator and condenser modules were sized on the basis of optimum fluid flow velocities. Structural considera-

tions present no problems in the range of pressures and temperatures encountered during testing and in service. Commercially available pipe, normally made in aluminum alloy 3003 (non-heat treatable), 6061 and 6063 (both heat treatable) will be used. Although the nozzles selected are standard sizes and can be purchased intact, the nozzles are planned to be made of rolled and welded 5083 aluminum since the minimum expected mechanical properties of as-welded 5083 are much better than those of as-welded 60XX series alloys (67% higher tensile ultimate).

3.1.5.8 Penetrations

Several penetrations, or connections, through the upper and lower cylindrical shells of both the condenser and evaporator modules will be required in addition to those used to transport the working fluid. These connections are needed to perform control functions and to allow for internal visual inspection of the heat exchanger module.

The upper and lower cylindrical shells at all modules will each have a 1 1/2 NPT female threaded boss to serve as the connection for measuring temperature and pressure through a multi-function probe. As a secondary option, taps can be installed in the inlet and outlet nozzle stubs to accomplish the same objective. In addition, another 1 1/2 NPT female threaded boss through the lower shell will provide non-condensable and non-evaporable extraction outlet connections. The internal passage is through a perforated pipe.

The upper and lower cylindrical shells of both the condenser and evaporator modules will be fitted with two six-inch diameter handholes, one on each end, to be used for inspection purposes as required by the ASME code. These openings could be flanged with glass or quartz covers to enable internal observation of the module to be made during operation. The tentative locations of the penetrations described in the preceding paragraphs are illustrated in Figure 3.1-21.

Figure 3.1-21 Module Penetrations

These auxiliary piping penetrations into the OTEC heat exchangers are provided for the following functions:

- Drain and charging of modules with ammonia
- Venting ammonia vapor to recovery system
- Nitrogen purging
- Non-condensable and non-evaporable removal
- Local instrumentation.

3.2 THERMAL/HYDRAULIC DESIGN AND PERFORMANCE

3.2.1 Configuration

The configuration of the shell-less heat exchanger evaporator and condenser surfaces is physically identical except for the enhanced surfaces. This commonality allows major economies in manufacture and minimum exchanger costs. The design yields superior thermal/hydraulic performance, is structurally sound and can be built at low cost.

The option of fluid flow direction was considered in the Phase I proposal. (Cross-flow, water-flow vertical, water-flow horizontal). Inlet and outlet headers were considered to be rectangular panel extensions with an external collection manifold. Early in Phase I, it became apparent that although the panel concept was satisfactory, the proposed headering technique could be modified to a cleaner design. The counter-flow concept was replaced by a cross-flow concept.

The form of the ammonia headers is dictated by the flow arrangement. In the cross-flow concept (Figure 3.2-1), a simple semicylindrical dome header can be used. In the counter-flow concept, (Figure 3.2-2) dome headers cannot be used because of the need to access the water passages. Therefore, in the counter-flow arrangement, reinforced rectangular headers are welded at the ends to an ammonia manifold.

Disadvantages of counter-flow concept include:

- Headers partially block the water passage openings, making cleaning more difficult unless the ammonia channel width is increased, which reduces heat exchanger compactness
- More expensive to fabricate than the simpler dome header
- Excessive pressure drop because the cross-sectional area for flow is small
- Cannot serve a dual function as a vapor-liquid separator, which dome header can do
- The water passages are not fully accessible for cleaning.

For these reasons, the cross-flow arrangement has been selected.

Figure 3.2-1. Full Module Assembly Cross-Flow Concept

An orientation in which the water flow is horizontal and the ammonia flow is vertical was chosen. The choice was dictated by considerations relating to the flow of ammonia through the evaporator. For the highest performance it is necessary to prevent any of the evaporator area from going; thus, the working fluid cannot be evaporated completely in one pass through the exchanger. Some excess liquid must be provided which separated from the exit vapor and recycled. High performance also requires that the fluid is distributed uniformly between parallel paths through the evaporator.

The simplest and cheapest arrangement for handling the working fluid flow is the vertical tube, natural circulation thermosiphon. This arrangement is used in the PSD II design. In a vertical thermosiphon, the flow loop for the working fluid includes the heat transfer tubes or passages which contain a froth of boiling fluid, a separation volume which receives the froth and separates the liquid and vapor, a vertical downcomer fed by the liquid in the separator and containing single-phase liquid, and

Figure 3.2-2. Counter Flow Concept Core Detail

a lower header which connects the downcomer and heat transfer tubes. The greater density of single-phase liquid in the downcomer, (relative to the froth in the tubes) provides circulation of the fluid.

The vertical thermosiphon has several advantages. Primarily, no recycle pump is needed and fluid distribution among parallel paths is uniform without adding metering or control.

Horizontal flow of ammonia has several disadvantages:

- Ammonia flow in the panel is two-dimensional since support strips have limited ability to block transverse flow. Thus, vapor and liquid in horizontal flow tends to separate with a greater risk of dry-out in the upper part of the panel
- To have the same pressure difference (and thus the flow rate) across the top and bottom of the panel, both inlet and outlet headers contains low density two-phase froth. As a result, the flow rate through the bottom of the panel is considerably greater than through the top, making it difficult to insure complete wetting of all the heat transfer area
- To fill the panel completely, the liquid level in the downcomer must be above the top of the panel. The outlet header then cannot be used as a vapor-liquid separator since the liquid level in the separator also must be above the panel top.

There is no corresponding functional difficulty with the horizontal flow of seawater and vertical ammonia flow. Since the water is in single-phase flow, essentially equal pressure drop and flow occur in all water tubes.

Using the outlet dome header as a vapor-liquid separator makes it possible to employ the internal downcomers. Downcomers are parallel plates stiffened with a sandwich filling of corrugated sheet. They have sufficient flow capacity to return excess liquid to the lower header. Internal separators and downcomers allow greater compactness in the assembly of the exchanger modules with resulting cost savings.

3.2.2 Passage/Panel Dimensions

The heat exchanger dimensions were chosen to give a high-performance low-cost design. The most important single dimension, from which most of the other dimensions follow, is the water-side passage diameter. Note that:

- Water pressure drop is a function of the ratio of the square of the water velocity to the water-side diameter (V^2/D)
- Water-side heat transfer varies as $(V^4/D)^{0.2}$
- Compactness (ft^3 per Btu/hr) varies as D^{-1} .

Since pressure drop is far more sensitive to velocity and diameter than is the heat transfer coefficient, the design task is to make the heat exchangers very compact considering the allowable pressure drop. The PSD II design uses a water-passage diameter of 0.75 inch on the basis that:

- The water-side pressure drop is not excessive
- It is not too small to be cleaned satisfactorily
- It yields module and heat exchanger dimensions which meet material, transportation and ship restraints.

The panel block in a heat exchanger module is 4 x 8.5 x 15.5 feet. The 4 foot length is reasonable for sheet forming, considering material availability. Also, an increase in length causes the loading in the semi-cylindrical heads and the strong-backs to increase, resulting in a structure of excessive weight and size. The 8.5 foot height is a reasonable size for handling and allows the overall module height to meet the 14 foot maximum load width limitation for shipment. The 15.5 foot width gives an exchanger subassembly (consisting of four modules) of manageable size and weight.

Four modules in series make up an exchanger subassembly and provide the optimum system. With the modules grouped in a series-parallel arrangement and at a given seawater velocity, the total sea water-flow rate and the assembly width vary inversely as the number of modules in series. Increasing the number of modules in series results in economies in cold water pipe parasitic power, decreasing the full width and simplifying tube cleaning. On the other hand, due to the change in seawater temperature as a result of heat transfer, the average temperature-difference driving-potential for heat transfer decreases as the number of modules in series increases. As a result, the required heat transfer area increases. By balancing these opposing trends, the system optimization program determined that four modules in series is the economic optimum.

3.2.3 Heat Transfer Enhancement

Enhancement of the ammonia-side area is used in both the condenser and evaporator. For the condenser, a UCC/Linde condensation promoter is used. It is economical because it increases overall condenser performance (U) by more than 150 percent relative to clean surfaces.

For the evaporator, the UCC/Linde "Hi-Flux" porous surface nucleate boiling promoter is used. This surface has been used world-wide for many years with various fluids and metals.

Theoretical analysis of unenhanced panels predicts that the heat transfer coefficient for ammonia liquid at saturation temperatures is low (about 600 Btu/hr ft² °F) in the bottom regions of the panels and gradually increases as vapor is generated in the panel and the two-phase mixture velocity increases. The ammonia liquid will enter the bottom of the panels with 10 to 15°F of subcooling. Vaporizing ammonia initially is difficult without an enhanced surface. Experimental data has demonstrated that the high flux surface maintains its excellent performance in a subcooled liquid.

The entire ammonia side is enhanced because:

- The savings resulting from enhancing only part of the surface are not directly proportional to the area enhanced
- It eliminates the analysis to determine the level at which the evaporator should be enhanced, which is especially difficult in the absence of test data on the evaporator
- It insures maximum performance over a wide range of operating conditions, including seawater temperature variation and ship motion, some combinations of which decrease the panel exit quality to the point where the benefits of enhancement are much higher.

3.2.3.1 Evaporator, Ammonia Side

The performance of the boiling enhanced surface is shown in Figure 3.2-3. This is a composite curve from data from Reference 3-1, which reports on a comprehensive test program using a large ammonia recycle test loop. In the test, pool boiling performance of an enhanced titanium tube and spray boiling performance of an enhanced aluminum tube were obtained. In the range of interest (3,500 to 5,200 Btu/hr ft²), the performances are fairly close.

Figure 3.2-3. Thin Film Ammonia Evaporator Performance

Based on this data, a conservative approach to the design of the evaporator was taken. Experience has shown that when the "Hi-Flux" surface is used inside tubes, performance is at least as good as that for the same surfaces in pool boiling. The equation of the curve is

$$h = 5777 \Delta T^{0.6672}$$

where h = boiling heat transfer coefficient, Btu/hr.ft².F

ΔT = boiling temperature difference, F°

This equation has been verified in tests using full-sized bundles and tubes of production quality at Argonne National Laboratory (Reference 3-2).

3.2.3.2 Condenser, Ammonia Side

Performance of the condensing enhancement was determined experimentally under a UCC/Linde funded program. Ammonia was condensed at 75°F on a horizontal enhanced aluminum tube. The test apparatus drips liquid ammonia on the test tube to simulate loading of a tube in a bundle by the tubes vertically above it. Using tube bundle analogy is appropriate because the present plate heat exchanger has the form of a tube bundle, with tubes connected in the vertical dimension by short webs.

Performance was first obtained for a single tube with no excess loading from above. The curve representing the correlation of this data is shown in Figure 3.2-4. In altered form it can be represented by

$$h_o = 45640 \left(\frac{q}{A} \right)^{-0.2665}$$

where

h_o = condensing heat transfer coefficient, Btu/hr ft² F

q/A = heat flux, Btu/hr ft²

Figure 3.2-4. Condensing Performance of Single Unloaded Tube

Performance was also determined at degrees of loading corresponding to the first tube (no excess loading from above) and loadings equal to 10, 20 and 40 times the loading on the first tube. The curve resulting from these tests is shown in Figure 3.2-5.

Also shown in Figure 3.2-5 is the predicted loading relationship according to Nusselt. The effect of loading is less than predicted by Nusselt, but this is consistent with published results obtained with fluorocarbon refrigerants. Both ammonia and the fluorocarbon compounds have much lower viscosity than water, for which the Nusselt relationship was derived.

Figure 3.2-5. Effect of Tube Loading on Local Condensing Coefficients

3.2.3.3 Water Side Enhancement

The performance of PSD-II heat exchangers is water-side limited, especially when ammonia-side enhancement is used. This condition raises the question of the benefits of water-side enhancement. While it is possible that future generation OTEC heat exchangers may incorporate such enhancement, PSD-II heat exchangers have been designed with a smooth, round water passage because:

- An important consideration of PSD-II is the cleanability of the tubes which would be complicated by water-side enhancement
- The ability to plug tubes is decreased by an extended surface tube
- The effect of erosion-corrosion is greater on a non-circular tube
- The tendency of a non-circular tube to buckle under the ammonia pressure would require greater thickness and may affect the economical production techniques used in PSD-II.

3.2.4 Thermal/Hydraulic Design Program

An existing computer program was modified to describe the thermal/hydraulic performance of the heat exchangers.

3.2.4.1 Evaporator

The program deals with one panel of an evaporator module. The panel is divided into increments in the horizontal (I) and vertical (J) directions. For a given i, starting at the leading edge relative to the sea water flow, the program steps mechanically upward through j (as shown in Figure 3.2-6). For each increment, (i, j), the program iterates on the mean temperature difference $\overline{\Delta T}$. The latter is taken as the arithmetic average of the inlet and output values for the water temperatures (TW) and the ammonia temperatures (TF):

$$\overline{\Delta T} = \frac{T_{Win} + T_{Wout}}{2} - \frac{T_{Fin} + T_{Fout}}{2}$$

Figure 3.2-6. Evaporator Design Program

The mean water-side and ammonia-side temperatures are used to calculate the metal wall temperature; the ammonia side heat transfer coefficient, which is a function of the temperature difference; the fin efficiency of the metal webs between the water tubes, which is a function of the ammonia h ; the overall heat transfer coefficient, including water-side h , water-side fouling, metal wall drop, and ammonia-side h ; the incremental heat duty; the outlet water temperature; the incremental average ammonia quality; the incremental ammonia pressure drop; and the outlet ammonia saturation temperature, which is a function of the outlet pressure. Having new values of the outlet temperatures, the average temperature difference is calculated and checked for convergence. This is repeated until calculations are internally consistent and converge.

After having stepped through I to the top of the panel, a second set of iterations for a given I is necessary to adjust the inlet ammonia flow conditions and achieve the desired outlet conditions. For a given inlet pressure, the ammonia flow rate is varied to give the desired outlet pressure.

In the design calculations a common inlet pressure was used for all four modules in a subassembly. The design average exit quality for a subassembly is 0.5. To achieve the desired average quality, a final iteration is necessary in which the inlet pressure is readjusted.

A detailed explanation of the computer program is given in Appendix II, Section 9. The program:

- Allows for a subcooled ammonia feed
- Calculates the two-phase ammonia-side pressure drop, including the Lockhart-Martinelli correlation for the two-phase multiplier, the Chisholm formulation for two-phase flow-through bends and constrictions from the water passages, the hydrostatic head, the flow acceleration, and the Lockhart head, the flow acceleration, and the Lockhart Martinelli calculation of exit pressure loss
- Calculates water-side pressure drop
- Calculates water-side heat transfer
- Accounts for the effect of the spacers on the ammonia side.

3.2.4.2 Condenser

The same procedure is used for the condenser with changes in the ammonia-side pressure drop and in boundary conditions.

The ammonia-side pressure drop includes frictional, 90° bends, Venturi-type contractions, accelerational and entrance losses. Since the condensate flows as a thin film on the walls, pressure drops are calculated as single-phase vapor flow losses. Local flow rate is for the uncondensed portion of the vapor flow. Since the vapor phase is the continuous phase, hydrostatic head can be neglected. Exit loss is also neglected since the total flow is condensed.

The program now steps in the vertical direction from the top down. With given inlet and outlet pressures the ammonia flow rate per horizontal increment is varied to give zero exit quality at the bottom of the panel by iteration.

3.2.5 Heat Exchanger Performance

The TRW system-optimization program has been used to calculate the operating conditions for the 10 MWe heat exchangers. In addition to calculations for the aluminum design, corresponding calculations for the stainless steel option are presented in support of the conceptual design in Section 7.

3.2.5.1 Performance Summary of Aluminum Evaporator

Figure 3.2-7 lists the operating conditions for the aluminum evaporator at nominal conditions. Items of special interest are:

- Evaporator extracts about 4°F from the warm water during passage through the four modules in series
- Average quality varies from 0.66 in the first module to 0.39 in the last/fourth module
- Pressure loss (ammonia-side) is 1.46 psia which corresponds to about 5-1/2 feet of ammonia head. It is constant for the four modules since they are connected by the inlet and outlet ammonia piping. Recirculation within each module is variable. It is reflected in average quality exiting from the panels in each module along with a variable heat duty

- Water velocity is 6.42 ft/sec and the overall coefficient (U) is about 818 based on water-side area
- Heat duty of each module varies from 23 percent above average for the first module in series to 12 percent below average for the last module in series
- Desired heat duty of 3.63×10^8 Btu/hr is satisfied by 204 panels per module.

OPERATING CONDITIONS	
SATURATION TEMPERATURE (AT OUTLET HEADER), °F	72.28
WATER INLET TEMPERATURE, °F	82.0
WATER VELOCITY, FT/SEC	6.42
FOULING FACTOR, HR FT ² °F/BTU	0.0003
AMMONIA FEED TEMPERATURE, °F	51.69

PANEL GEOMETRY	
HEAT TRANSFER HEIGHT, FT	8.5
TUBE DIAMETER, IN.	0.75
WALL THICKNESS, IN.	0.050
PITCH (LATERAL), IN.	1.019
PANELS/FT	14.4
HEAT TRANSFER AREA, FT ² /PANEL	75.3
TOTAL HEAT DUTY (204 PANELS) x 4 MODULES	3.63×10^8 BTU/HR

PERFORMANCE PARAMETERS	EVAPORATOR MODULES			
	NO. 1	NO. 2	NO. 3	NO. 4
WATER OUTLET TEMP, °F	80.75	79.07	78.73	77.92
MODULE LOCAL LMTD, °F	8.78	7.60	6.58	5.70
AVERAGE QUALITY, EXIT OF PANELS	0.66	0.56	0.47	0.39
AMMONIA PRESSURE LOSS IN PANELS, PSI	1.46	1.46	1.46	1.46
U, OVERALL HEAT TRANSFER COEFFICIENT, BTU/HR FT ² °F*	819.4	818.5	817.5	816.6
AVERAGE WATERSIDE COEFFICIENT, BTU/HR FT ² °F	1375	1375	1375	1375
BOILING COEFFICIENT, BTU/HR FT ² °F RANGE	5847/5786	5787/5733	5741/5681	5683/5630
HEATING RATE/PANEL, 10 ⁶ BTU/HR	0.5420	0.4685	0.4051	0.3505
HEATING RATE/204 PANELS, (5/8 MWe MODULE), 10 ⁹ BTU/HR	0.111	0.096	0.083	0.072
HEATING RATE/56 PANELS, (2/10 MWe TEST UNIT), 10 ⁹ BTU/HR	0.030	0.026	0.023	0.020
MODULE PERFORMANCE COMPARED TO AVERAGE DUTY	1.23	1.06	0.92	0.79

*BASED ON WATERSIDE AREA

Figure 3.2-7. Performance Summary of Aluminum Evaporator

3.2.5.2 Performance of Stainless Steel Evaporator

Figure 3.2-8 presents the performance of an evaporator constructed from stainless steel. Items for comparison with an aluminum evaporator are:

- Water velocity is reduced to 6.31 ft/sec
- Panel geometry is different. Wall thickness is reduced from 0.050 (aluminum) to 0.020 (stainless steel). Heat transfer area per panel (although the heat transfer height remains 8.5 feet) is increased from 75.3 to 83.75 square feet. This results from tighter pitch of tubes due to forming of thinner walls and thus more passages per panel (aluminum has 100 and stainless steel has 111)
- Quality distribution between modules is approximately the same as in an aluminum evaporator
- Pressure loss on ammonia side is the same
- Overall heat transfer coefficient (U) is down from 818 to 706 for stainless steel due to a greater thermal resistance in the panel wall and lower water velocity
- Boiling coefficient of enhanced surface is still in the 5,000 range
- Approximate desired heat duty is also satisfied by 204 panels per module. Exact heat duty can be adjusted by the water velocity selected (in the 0.01 ft/sec range)
- Heat duty distribution shows that the first and last modules are slightly closer to the average duty
- Although the heat duty is the same for aluminum (204 panels) and the flow velocity is similar, there are 111 water passages in each stainless steel panel versus 100 water passages in the aluminum design. Thus, the steel design requires about 10 percent more water mass flow rate.

3.2.5.3 Performance Summary of Aluminum Condenser

Figure 3.2-9 is based on the ammonia state points and heat duty determined by the system optimization program. Ammonia pressure loss across the panels (between the upper manifold and vapor within lower manifold) varies from 0.37 psi in the leading module to 0.21 psi in the last module. The overall coefficient (U) is about 620, considerably less than the aluminum evaporator. The condensing coefficient varies from 3,200 to

OPERATING CONDITIONS	
SATURATION TEMPERATURE (AT OUTLET HEADER), °F	72.28
WATER INLET TEMPERATURE, °F	82.0
WATER VELOCITY, FT/SEC	6.31
FOULING FACTOR, HR FT ² °F/BTU	0.0003
AMMONIA FEED TEMPERATURE, °F	51.00

PANEL GEOMETRY (ALUMINUM)	
HEAT TRANSFER HEIGHT, FT	8.5
TUBE DIAMETER, IN.	0.75
WALL THICKNESS, IN.	0.020
PITCH (LATERAL), IN.	0.916
PANELS/FT	15.09
HEAT TRANSFER AREA, FT ² /PANEL	83.75
TOTAL HEAT DUTY (204 PANELS) x 4 MODULES	3.55 x 10 ⁸ BTU/HR

PERFORMANCE PARAMETERS	EVAPORATOR MODULES			
	NO. 1	NO. 2	NO. 3	NO. 4
WATER OUTLET TEMP, °F	80.80	79.93	79.07	78.32
MODULE LOCAL LMTD, °F	8.80	7.75	6.83	6.02
AVERAGE QUALITY EXIT OF PANELS	0.62	0.53	0.46	0.39
AMMONIA PRESSURE LOSS IN PANELS, PSI	1.46	1.46	1.46	1.46
U, OVERALL HEAT TRANSFER COEFFICIENT, BTU/HR FT ² °F	707.5	706.8	706.1	705.5
AVG WATERSIDE COEFFICIENT, BTU/HR FT ² °F	1358	1358	1358	1358
BOILING COEFFICIENT, BTU/HR FT ² °F RANGE	5757/5794	5748/5711	5720/5666	5675/5621
HEATING RATE/PANEL, 10 ⁸ BTU/HR	0.5215	0.4689	0.4539	0.3557
HEATING RATE/204 PANELS, (5/8 MWe MODULE), 10 ⁹ BTU/HR	0.106	0.094	0.082	0.073
HEATING RATE/56 PANELS, (2/10 MWe TEST UNIT), 10 ⁹ BTU/HR	0.029	0.026	0.023	0.020
MODULE PERFORMANCE COMPARED TO AVERAGE DUTY	1.20	1.05	0.93	0.82

*BASED ON WATER-SIDE AREA

Figure 3.2-8. Performance Summary of Stainless Steel Evaporator

1,900 throughout the system and is dependent on the effect of liquid loading. The 204 panels give the heat duty required for the 10 MWe design based on the water velocity and ammonia temperatures determined by the system optimization program. The higher LMTD driving temperature available offset the much lower U. Finally, the performance of each module in series shows about ±15 percent of average duty.

OPERATING CONDITIONS	
SATURATION TEMPERATURE (AT OUTLET SUMP), °F	51.27
WATER INLET TEMPERATURE, °F	40.00
WATER VELOCITY, FT/SEC	6.05
FOULING FACTOR, HR FT ² °F/BTU	0.0003
AMMONIA INLET TEMPERATURE, °F	51.49

PANEL GEOMETRY (ALUMINUM)	
HEAT TRANSFER HEIGHT, FT	8.5
TUBE DIAMETER, IN.	0.75
WALL THICKNESS, IN.	0.050
PITCH (LATERAL), IN.	1.019
PANELS/FT	14.4
HEAT TRANSFER AREA, FT ² /PANEL	75.3
TOTAL HEAT DUTY (204 PANELS) x 4 MODULES	3.50 x 10 ⁸ BTU/HR

PERFORMANCE PARAMETERS	CONDENSER MODULES			
	NO. 1	NO. 2	NO. 3	NO. 3
WATER OUTLET TEMP, °F	41.22	42.32	43.31	44.20
MODULE LOCAL LMTD, °F	10.79	9.65	8.62	7.70
AMMONIA PRESSURE LOSS IN PANELS, PSI	0.37	0.31	0.25	0.21
U, OVERALL HEAT TRANSFER COEFFICIENT, BTU/HR FT ² °F*	613.6	617.9	622.3	626.5
AVERAGE WATERSIDE COEFFICIENT, BTU/HR FT ² °F	1138	1138	1138	1138
CONDENSING COEFFICIENT, BTU/HR FT ² °F, RANGE	2947/1925	3040/1981	3136/2039	3236/2105
COOLING RATE/PANEL 10 ⁶ BTU/HR	0.4986	0.4491	0.4042	0.3622
COOLING RATE/204 PANELS (5/8 MW _e MODULE) 10 ⁹ BTU/HR	0.102	0.092	0.082	0.074
COOLING RATE/56 PANELS (2/10 MW _e TEST UNIT) 10 ⁹ BTU/HR	0.028	0.025	0.023	0.020
MODULE PERFORMANCE COMPARED TO AVERAGE DUTY	1.16	1.05	0.94	0.85

*BASED ON WATERSIDE AREA

Figure 3.2-9. Performance Summary of Aluminum Condenser

3.2.5.4 Performance Summary of Stainless Steel Condenser

Panel geometry is identical to that of the stainless steel evaporator design. The water flow velocity of 6.05 ft/sec was used for simplicity since the optimum velocity has not been determined. (Heat duty is about 1 percent higher than the aluminum condenser.) The ammonia temperatures remain the same.

Figure 3.2-10 presents a performance summary for the stainless steel condenser. Overall U is now reduced to 548 Btu/hr-ft²-F. The lower U is offset by the greater panel area and greater water mass flow rate even when the velocity is constant. As a consequence, the water discharge temperature for the stainless steel design is lower than for the corresponding aluminum condenser design.

OPERATING CONDITIONS	
SATURATION TEMPERATURE (AT OUTLET SUMP), °F	51.77
WATER INLET TEMPERATURE, °F	40.00
WATER VELOCITY, FT/SEC	6.05
FOULING FACTOR, HR FT ² °F/BTU	0.0003
AMMONIA INLET TEMPERATURE, °F	51.49

PANEL GEOMETRY (ALUMINUM)	
HEAT TRANSFER HEIGHT, FT	8.5
TUBE DIAMETER, IN.	0.75
WALL THICKNESS, IN.	0.020
PITCH (LATERAL), IN.	0.916
PANELS/FT	15.09
HEAT TRANSFER AREA, FT ² /PANEL	83.75
TOTAL HEAT DUTY (204 PANELS) x 4 MODULES	3.53 x 10 ⁸ BTU/HR

PERFORMANCE PARAMETERS	CONDENSER MODULES			
	NO. 1	NO. 2	NO. 3	NO. 4
WATER OUTLET TEMP, °F	41.09	42.08	42.98	43.81
MODULE LOCAL LMTD, °F	10.86	9.84	8.91	8.05
AMMONIA PRESSURE LOSS IN PANELS, PSI	0.37	0.31	0.25	0.21
U, OVERALL HEAT TRANSFER COEFFICIENT, BTU/HR FT ² °F*	544.3	546.9	549.6	553.2
AVG WATERSIDE COEFFICIENT, BTU/HR FT ² °F	1138	1138	1138	1138
CONDENSING COEFFICIENT, BTU/HR FT ² °F, RANGE	2881/ 1937	2944/ 2008	3013/ 2008	3120/ 2008
COOLING RATE/PANEL, 10 ⁶ BTU/HR	0.4953	0.4509	0.4102	0.3733
COOLING RATE/204 PANELS (5/8 MW ₀ MODULE), 10 ⁹ BTU/HR	0.101	0.092	0.084	0.076
COOLING RATE/56 PANELS (2/10 MW ₀ TEST UNIT), 10 ⁹ BTU/HR	0.028	0.025	0.023	0.021
MODULE PERFORMANCE COMPARED TO AVERAGE DUTY	1.15	1.04	0.95	0.86

*BASED ON WATER-SIDE AREA

Figure 3.2-10. Performance Summary of Stainless Steel Condenser

3.2.6 Off-Design Conditions

3.2.6.1 Effect of Liquid Level on Evaporator

A series of computer runs was made in which the ammonia side pressure drop was varied (liquid level in the downcomers was changed). Results are shown in Figure 3.2-11.

The nominal evaporator design liquid level is 5.55 feet. Changing the liquid level has two effects. The flow rate of ammonia percolated through the passage changes and the average temperature-difference driving potential for heat transfer changes because of the hydrostatic effect of the liquid-level on the saturation temperature at the bottom of the passage.

Figure 3.2-11. Sensivity of Heat Duty to Liquid Level

Changing the liquid level by ± 1.5 feet has little effect on heat duty, resulting in ± 1.5 percent change in Q . The panel average exit quality from four modules in series varies from 0.60 to 0.42. The maximum exit quality, which occurs at the leading edge of the first module, varies from 0.81 to 0.59. The exit quality should never be higher than 0.8 for any significant period of time because of the possibility of local dryout (which decreases performance) and the depletion of liquid ammonia to drive the thermosiphon.

3.2.6.2 Effect of Ship Motion

Pitching motion of the ship accelerates the ammonia contained in the evaporator in the vertical direction. The effect of pitching was studied by changing the value of g/g_c in the hydrostatic terms in the program. Results are shown in Figure 3.2-12. They represent quasi-steady state performance with the liquid level constant at the standard value (5.55 feet). Increasing and decreasing the apparent gravity field has the same effect as raising and lowering the actual liquid level. Again, the effect on the heat duty is quite small while the effect on the maximum exit quality is substantial.

If it is required to remain operational (generating power during a ± 0.5 g environment), the data suggest that instantaneous exit qualities of 0.9 are possible at the leading edge of the first evaporator module. However, the dynamics of the liquid ammonia and the capacity of the "Hi-Flux" surface to hold a certain amount of fluid compensate for this and dryout does not occur over the period of the ship's motion. The effects of both changing the downcomer liquid level and the motion of the ship will be examined during the test program (see Section 3.3.4).

3.2.7 Effect of Non-Evaporables on Evaporator Performance

Ammonia as used in the PSD-II cycle is subject to contamination by low-volatility substances such as water and lubricants. Once into the system, they accumulate in the evaporator and affect its performance.

As shown in Section 4, the pump and turbine tube seals have been designed so that the ammonia is not contaminated. However, water can be introduced into the loop through three mechanisms:

Figure 3.2-12. Evaporator Performance During Ship Motion (Quasi Steady State)

- Initial charge with commercial ammonia (2,000 ppm water). While the start-up procedures dry this considerably, some time is required before the loop reaches a steady-state water content
- Ammonia support system continually extracts liquid from the evaporator, partially reduces water content, returns it to the loop. Under steady-state conditions with no other source of water, the concentration of the water in the ammonia extracted from the evaporator sump equals the concentration returned from the support system. Thus, the water concentration in the evaporator equals the limit of the ammonia support system to dry the ammonia
- Damage to the heat exchangers or pitting at end-of-life may allow direct contact between ammonia and seawater. Under such conditions, the ammonia leakage velocity into the water will be high due to differential pressure considerations

However, the high affinity of ammonia and water and the large difference in concentrations may allow water to diffuse into the ammonia through the boundary layer. A tube-plugging system (Section 5.5.7) protects against this. Unless a massive water leak occurs, the ammonia support system removes the water and restores performance.

The effect of dissolved contaminants is twofold. First, some of the evaporator temperature difference is lost due to an increase in the boiling point. The rise due to dissolved water at 72°F is shown in Figure 3.2-13. The boiling point rise due to oil can be estimated from Raolt's law

$$\Delta T = \frac{P_o X}{(dP_o/dT_o)}$$

where

P_o = vapor pressure of pure solvent at its boiling point, T_o

and

X = mol fraction of the solute

Synthetic polyglycol lubricants have molecular weights around 1000. Therefore, a one percent by weight mixture yields a boiling point rise of only 0.01°F.

Secondly, dissolved non-volatile contaminants temporarily reduce the boiling heat transfer coefficient to an extent depending on concentration of the solute and on its nature. Loss of performance is moderate as long as the contaminant is fully soluble in the working fluid. However, if the concentration in the bulk liquid is close to saturation, a deposit may occur on the heat transfer surface leading to performance loss. The effect is due to a mass transfer resistance associated with vaporization of a mixture on the "High Flux" surface.

The effect of dissolved oil and water in ammonia on the boiling heat transfer coefficient on "High Flux" surfaces has not been investigated experimentally. Data do exist on the effect of dissolved oil in other fluids. Figure 3.2-14 shows the effect of oil in R-11, and Figure 3.2-15 deals with oil in propylene. Extensive experience has been accumulated with "High Flux" kettle type chillers boiling oil bearing propylene and halocarbon refrigerants. In the propylene systems, oil buildup due to

Figure 3.2-13. Boiling Point Rise of Ammonia with Addition of Water

compressor seal leakage is low enough so that draining of the kettles is not required more frequently than every 1-1/2 to 2 years. In both R-11 and propylene systems, oil is fully-soluble in the working fluid to concentrations well-above those experimentally studied or encountered in practice. At a heat flux of 5,000, 1 percent oil decreases h by 19 percent in the R-11 system and by 12 percent in the propylene system. Similar concentrations of oil plus water should have similar results in ammonia. However, this quantity of oil is excessive and represents a malfunction.

3.2.8 Effect of Noncondensibles on Condenser Performance

Noncondensibles degrade condenser performance much as nonevaporables do in the evaporator. Under operating conditions, air does not leak into

Figure 3.2-14. Effect of Refrigeration Oil (300 S.U.V.) on Boiling of R-11

the system since the ammonia vapor is at higher than atmospheric pressure. However, there are two sources for noncondensibles in the ammonia vapor.

The first source is residual nitrogen which remains in the system due to purging prior to filling with ammonia. This occurs at initial fill and any time the ammonia system must be opened, such as for pulling a heat exchanger subassembly.

Secondly, according to refrigeration literature, ammonia decomposes to hydrogen and nitrogen in either absorption or mechanical refrigeration cycles. Unfortunately, there seems to be no basis for predicting the rate of decomposition. The literature indicates that the rate is influenced by the compressor temperature and by materials in contact with the ammonia, such as metals, water and oil. The latter materials have a catalytic effect. The rate of decomposition seems to be much greater

Figure 3.2-15. Effect of Compressor Oil Addition on Boiling Performance of High Flux Surface in Propylene at 1 Atmosphere

in absorption refrigeration cycles than in mechanical cycles (Reference 3-3). These observations suggest that the rate of decomposition may be low in the OTEC cycles. With no vapor compressor, the ammonia is never exposed to temperatures higher than ambient. Argonne National Laboratory, in their test program on 1 MWe OTEC heat exchangers, did not observe a non-condensable problem in the condensers. They purged the ammonia loop on startup but did not purge continuously during operation. They did not observe any apparent effect during weeks of operation without purging.

Any noncondensibles in the system are swept into the condenser along with the ammonia vapor. Data obtained in TRW's extensive experience with inert-gas controlled heat pipes are applicable. It has been shown that the motion of the condensing vapor toward the far end of the condenser

contains the noncondensibles so that they do not interfere with condensation. This motion prevents diffusion of the noncondensibles in an upstream direction. The distance between the concentration of essentially pure noncondensibles and pure working fluid is about an inch. Thus, the noncondensibles are retained in the condenser sump.

The effect of noncondensibles in the inlet vapor was calculated using the Colburn-Hougen method (Reference 3-4). The results are given in Figure 3.2-16. Full condenser performance is obtained only if the inlet concentration is about 0.01 ppm. This value is attainable since the only source of noncondensibles in the inlet is ammonia decomposition.

Figure 3.2-16, Variation of Condenser Heat Load With Non-Condensable Concentration

3.2.9 Entrainment and Recirculation

The superficial vapor velocity in the evaporator header (just above the top of the panels) at standard operating conditions is 2.26 ft/sec for the leading module and 1.46 ft/sec for the trailing module. A standard empirical equation for vapor velocity in distillation columns (Reference 3-5) is:

$$U = 0.185 \sqrt{\frac{\rho_L - \rho_V}{\rho_V}}$$

where

- U = vapor velocity, feet per second
- ρ_L = liquid density, pounds per cubic foot
- ρ_V = vapor density, pounds per cubic foot

This is the highest superficial vapor velocity at which entrainment remains negligible. For the present system, this equation yields an allowable velocity of 1.69 ft/sec.

Though this velocity is higher than that in the leading module, entrainment should not be a problem. According to Perry, entrainment can have a variety of sources:

- 1) Excessive foaming. This is a case of gas-in-liquid dispersion
- 2) Droplets formed from the collapse of the bubble dome (see Figure 3.2-17a). These are virtually unavoidable. They are generally under 25 μ , which means that their terminal velocities are low and they will be entrained. Fortunately, because of their small size, they contribute little on a weight basis although they dominate on a numerical basis
- 3) Droplets from the jet caused by liquid rushing to fill the cavity left by the bubble (see Figure 3.2-17e). These droplets range up to 1000 μ , their size depending on bubble size. A number of studies have found that bubbles greater than 0.2 to 0.3 inch yield a jet that is too short and fat to break. Conversely, as bubbles get smaller, the jet thins and yields smaller drops that are ejected to greater heights. This is also of importance at modest loadings. Once foam forms over the surface, drop ejection by this mode decreases sharply
- 4) At higher vapor loads, the kinetic energy of the vapor rather than the bubble burst supplies the thrust for jets and sheets

Figure 3.2-17. Mechanism of the Burst of a Bubble

of liquid that are thrown up in an uneven pattern. This splashing mode can yield much higher levels of entrainment and ultimately causes flooding in distillation trays.

PSD-II operates at low vapor loads. Therefore, droplet formation would be almost entirely by mechanisms 2 and 3. The entrainment expected is related to the size of the bubbles produced by the evaporator as shown in Figure 3.2-18 taken from Reference 3-6. The size of the bubbles is related to the mode of two-phase flow in the panels. Using the flow regime map of Fair (Reference 3-7), large bubbles with diameters of at least 0.25 inch are expected. Data (Figure 3.2-18) indicate an entrainment of 0.04 lb liquid/lb vapor, or an exit quality exceeding 96 percent.

Recirculation of the percolated liquid from the upper header through the downcomers to the lower header has been examined by using the Dukler correlation for turbulent film flow on a vertical wall (Reference 3-8). The downcomer flow rate is 19,600 lbs/hr per downcomer in the trailing module in which the recycle rate is greatest. For this flow rate, the falling film thickness was 0.038 inch. Thus, the downcomers have ample capacity for flow in returning the recycled ammonia.

3.2.10 Thermal/Hydraulic Design and Performance of 0.2 MWe Test Articles

Since the thermal/hydraulic analysis of the 10 MWe heat exchangers basically deals with four panel in series in the seawater flow direction, the performance to be expected from this test article, which is thermally representative of each module, can be determined.

Figure 3.2-18. The Variation of the Entrainment with the Diameter of the Bursting Bubble

3.2.10.1 Selection of Test Article Configuration

The 10 MWe heat exchangers have been designed such that each of the 16 evaporators and 16 condenser modules have a nominal 0.625 MWe duty. Due to mechanical design constraints (using downcomers as structural elements), there are 17 active heat transfer panels between each of 11 downcomers (204 active panels). To maintain hydraulic similarity between the test evaporator and the 0.625 MWe modules for the 10 MWe heat exchanger, the ratio of active panels to number of downcomers is maintained constant. Therefore, the test evaporator was designed with 56 active panels and three downcomers.

The panel arrangement with downcomers is shown in Figure 3.2-19.

For nominal conditions (water velocity 6.42 ft/sec and inlet temperature 82.0°F), the calculated performance is 0.21 MWe for the aluminum evaporator test article.

To have similar construction (to minimize cost) between the evaporator and condenser, the active panel count must be identical. However, for the condenser, the downcomers are inactive as they are in the 10 MWe condenser.

Figure 3.2-19. Test Article Configuration

The heat duty for the condenser test article (56 panels) is calculated to be 0.20 MWe when operating at nominal conditions (6.05 ft/sec and inlet temperature 40.0°F) and simulates the first module in series of the condenser.

3.2.10.2 Performance Summary

Figure 3.2-20 shows the key items which determine the predicted performance of the test evaporator. (These data are also shown in Figure 3.2-7.) The average module performance is an average of modules 2 and 3 or an average for all 10 MWe evaporator modules. Figure 3.2-21 shows similar data for predicting the performance of the condenser test article.

These figures can be used as a guide to plan the variation of test parameters for an onboard test program.

3.2.10.3 Comparison of 0.2 MW and 0.625 MWe (10 MWe) Modules

It is desirable to have the test article simulate in as many respects as possible the larger module (0.625 MWe) for the 10 MWe heat exchanger. As stated previously, the evaporator and condenser are identical in configuration and structure. Figure 3.2-22 compares the test articles and

PARAMETER	FIRST MODULE	AVERAGE MODULE	LAST MODULE
REQUIREMENTS (NOMINAL CONDITION)			
WARM SEAWATER TEMPERATURE, INLET °F	82.0	80.2	78.7
WARM SEAWATER FLOW RATE, LB/SEC	6920	6920	6920
SEAWATER SIDE PRESSURE DROP PSID	0.78	0.78	0.78
SEAWATER VELOCITY IN PASSAGES, FT/SEC	6.42	6.42	6.42
AMMONIA EXIT TEMPERATURE, °F	73.3	73.3	73.3
AMMONIA EXIT PRESSURE, PSIG	120	120	120
AMMONIA SIDE PRESSURE DROP PSID	1.46	1.46	1.46
AMMONIA RECYCLE RATIO, (1-X)/X	0.5	1.0	1.5
GOALS (AT DESIGN FOULING FACTOR 0.0003)			
AMMONIA FLOW RATE AT 97% EXIT QUALITY, LB/SEC	16.5	13.1	10.8
THERMAL DUTY, MBTU/HR	30.0	24.8	20.0
MEAN TEMPERATURE DIFFERENCE °F	8.8	7.2	5.7
OVERALL U, BTU/HR FT ² °F	819	818	817

*TEST ARTICLE HAS 56 ACTIVE ALUMINUM HEAT TRANSFER PANELS

Figure 3.2-20. Evaporator Performance Requirements and Goals (0.2 MWe*)

PARAMETER	FIRST MODULE	AVERAGE MODULE	LAST MODULE
REQUIREMENTS (NOMINAL CONDITIONS)			
COLD SEAWATER TEMPERATURE, INLET °F	40.0	41.8	43.3
COLD SEAWATER FLOW RATE, LB/SEC	6530	6530	6530
SEAWATER SIDE PRESSURE DROP PSID	0.74	0.74	0.74
SEAWATER VELOCITY IN PASSAGES, FT/SEC	6.05	6.05	6.05
AMMONIA INLET TEMPERATURE, °F	51.5	51.5	51.5
AMMONIA INLET PRESSURE, PSIG	77	77	77
AMMONIA SIDE PRESSURE DROP PSID (TWO PHASE)	0.37	0.28	0.21
GOALS (AT DESIGN FOULING FACTOR 0.0003)			
AMMONIA FLOW RATE AT 97% INLET QUALITY, LB/SEC	16.5	13.1	10.8
THERMAL DUTY, MTBU/HR	28.0	24.0	20.0
MEAN TEMPERATURE DIFFERENCE	10.8	8.1	7.7
OVERALL U, BTU/HR FT ² °F	614	620	626

*TEST ARTICLE HAS 56 ACTIVE ALUMINUM HEAT TRANSFER PANELS

Figure 3.2-21. Condenser Performance Requirements and Goals (0.2 MWe*)

ITEM	PRODUCTION	TEST ARTICLE
NOMINAL THERMAL DUTY (MW ₀)	0.625	0.2
NUMBER OF ACTIVE PANELS	204	56
PANEL CONFIGURATION	IDENTICAL	IDENTICAL
PANEL HEIGHT, HEAT TRANSFER (FEET)	8.5	8.5
PANEL STRUCTURAL HEIGHT (FEET)	9.0	9.0
PANEL WIDTH (FEET)	4.0	4.0
WATER PASSAGES/PANEL	100	100
PASSAGE DIAMETER (INCHES)	0.75	0.75
PANEL MATERIAL THICKNESS (INCHES)	0.060	0.060
PANEL MATERIAL	3004 0 ALCLAD	3004 0 ALCLAD
PANEL CLADDING THICKNESS (INCHES)	0.01	0.005
PANEL HOLE PITCH, (INCHES)	1.019	1.019
PANEL DENSITY NUMBER/FEET	14.4	14.4
DOWNCOMERS	11	3
PANELS/DOWNCOMERS	18.55	18.67
DISTANCE BETWEEN DOWNCOMERS (INCHES)	15	15
ENHANCEMENT (AMMONIA SIDE)	LINDE ENHANCED SURFACE	LINDE ENHANCED SURFACE
ENHANCEMENT (WATER SIDE)	NONE	NONE
UPPER HEADER DIAMETER (FEET)	4	4
LOWER HEADER DIAMETER (FEET)	4	4
UPPER MANIFOLD NOZZLE DIAMETER (IN)/VELOCITY (FT/SEC)		
EVAPORATOR OUTLET	24/32	14/32
CONNECTER INLET	24/32	14/32
LOWER MANIFOLD NOZZLE DIAMETER (IN)/VELOCITY (FT/SEC)		
EVAPORATOR INLET	6/6	4/4
CONNECTER OUTLET	6/6	4/4

Figure 3.2-22. Comparison of Test Article (0.2 MWe) Versus Production Module (0.625 MWe)

the 0.625 MWe modules. The panels as well as the upper and lower header dimensions are identical. One exception is the inlet and outlet nozzles which have been deliberately changed to maintain the same vapor discharge velocity from the evaporator and vapor velocity entering the condenser. Liquid velocities are not exactly duplicated because standard nozzle sizes have been used. The internal operation of the heat exchangers are identical to the full-scale modules. The two-phase ammonia mixture leaving the top of the panels and the recirculation are identical along with the mechanism of vapor disengagement.

3.3 0.2 MWe TEST ARTICLES INTEGRATION AND TEST

The test articles for PSD-II are to provide data which validates the design assumptions for the 10 MWe heat exchangers. The test articles consist of representative heat exchangers (evaporator and condenser) and auxiliary support equipment designed for installation and test on board the DOE OTEC-1. The heat exchangers have been specified by DOE to operate at a thermal duty equivalent to 0.2 MWe. These heat exchangers are totally representative of the full size units in every important respect and are designed to obtain 10 MWe design verification data. The auxiliary support equipment includes a biofouling control system (tube cleaners), phase separator, water boxes, transition pieces, accumulator and other structure required for installation, operation and test of the heat exchangers. This section discusses the test objectives, describes the integrated test articles and their interfaces with OTEC-1 and discusses the data collection and test planning.

3.3.1 Test Objectives

The purpose of the Phase II Test Program is to provide data required to design and operate the full scale prototype power module with low risk of failure or expensive retrofitting. In order to verify the design of the 10 MWe unit a list was developed of technical issues and design assumptions which must be substantiated by test. This approach includes:

- Scale Model Tests. These are small scale tests in special test facilities such as heat transfer labs, biofouling labs, or model basins currently being conducted by DOE and contractors
- 0.2 MWe Tests. These are intermediate scale tests which need to be performed on 0.2 MWe test articles in a simulated power loop. Such a simulated power loop could be designed and implemented on land (e.g. at Argonne National Laboratories) or at sea (e.g. OTEC 1 Test Platform)
- 10 MWe Prototype Tests. These are full scale tests on a prototype power system at sea (e.g. OTEC-10/40).

The resulting test data requirements list is shown in Figure 3.3-1. Using this list as a departure point the following test objectives for Phase II have been formulated:

- Confirm and demonstrate the validity of the heat exchanger thermal/hydraulic design basis
- Assess the rate of biofouling growth and effect on the performance of heat exchangers
- Assess the effectiveness of the chlorination biofouling counter-measure approach including low level dose rates for micro-organisms and high level shock applications for macro-organisms.
- Demonstrate the effectiveness of the mechanical tube cleaner and develop baseline operating data for future systems
- Validate the heat exchanger control system approach
- Validate the design and performance of heat exchanger auxiliary equipment - the phase separator and accumulator
- Assess the operability and survivability of PSD-II in the OTEC sea environment particularly with respect to corrosion and erosion effects on the heat exchanger.

3.3.2 System Description

The 0.2 MWe test articles configuration is designed to provide data relevant to the 10 MWe power system heat exchangers and select operational parameters as discussed in Section 3.3.4. As most of the verification data are relative to the thermal/hydraulic performance of these heat exchangers in an operational environment, primary emphasis is on flow rate, temperature and pressure instrumentation and data reduction. The process parameters for nominal conditions are shown on the test loop flow diagram (Figure 3.3-2). Details of the thermal/hydraulic scaling considerations are contained in Section 3.2.10. The thermal/hydraulic parameters such as flow rates, temperatures, etc., have been selected so that the thermal and hydraulic performance is the same as the 10 MWe heat exchangers. This is accomplished by keeping the temperature and pressure the same and scaling down the flow rates by the ratio of test article size to full module size (56/204 panels). The test loop has a throttle valve/desuperheater to simulate a turbine. Since no work is extracted, the state conditions of the test condenser at nominal operating conditions are slightly different from the full scale power system.

Figure 3.3-2. 0.2 MWe Test Article Conceptual Test Loop Process Flow Diagram

The pipe sizes, interconnections and instrumentation points are indicated on Figure 3.3-3. The ammonia line sizes for both the liquid and vapor are selected to maintain the same velocities as in the 10 MWe power loop.

All of the major equipment of a 10 MWe system are included in the test loop except for a turbine which is simulated by the throttle valve and desuperheater. The following TRW and Linde furnished equipment is discussed below with reference to other sections for additional detail:

- Two 0.2 MWe heat exchangers (evaporator and condenser)
- Two tube cleaners (one per heat exchanger)
- One phase separator and one accumulator
- Two water boxes and four transition pieces.

3.3.2.1 Heat Exchanger Test Articles

Design Description. The 0.2 MWe evaporator and condenser test articles are full scale segments of the 0.625 MWe modules described in Section 3.1. A sketch of the test article is shown in Figure 3.3-4. The evaporator and condenser test articles are identical, structurally, in size and appearance; the envelope and weight dimensions (aluminum) are listed in Figure 3.3-5. The test articles are designed to confirm the performance of larger sized modules (0.625 MWe as used for the 10 MWe heat exchangers), and to verify the fabrication methods and materials selection for seawater duty.

The test articles duplicate the following key characteristics:

- Panel geometry/structural configuration
- Seawater and ammonia operating conditions
- Downcomer design
- Panel surface enhancements
- Fabrication processes
- Material formability.

The configuration of the test articles is selected to maximize the utility of the thermal source available (seawater flow) and yet provide excellent simulation of full scale module performance. The test articles will each consist of 56 active heat transfer panels (full scale modules will be 204 active panels) and the ratio of panel/downcomer is identical. No compromise has been made in the panel dimensions as the panels used for the test articles and the full size modules are identical.

The test articles will demonstrate:

- Thermal/hydraulic performance
- Materials compatibility
- Effectiveness of biofouling cleaning techniques and counter-measures
- Fabrication/assembly techniques
- ASME Code certification.

The choice of heat exchanger construction materials for the test articles - stainless steel or aluminum - does not significantly affect the test articles thermal performance or the heat exchanger concept. While both materials will last or significantly exceed the required test period of 5 years, there is obviously less risk with a stainless steel design.

The materials analysis for the heat exchanger test articles is presented in Section 3.5. The advantages and disadvantages of construction materials as related to OTEC heat exchangers are presented in Figure 3.3-6.

The test articles are provided with additional penetration for instrumentation purposes; pressure and temperature measurements. Figure 3.3-7 lists the penetrations and Figure 3.3-8 shows the locations of these items. The test articles also incorporate observation ports to allow for better visibility of internal flow phenomena. Inlet and outlet nozzles have been sized to provide the same ammonia velocities as for the full scale modules. These are shown in Figure 3.3-9.

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

Figure 3.3-4. 0.2 MWe Test Article

PARAMETER	EVAPORATOR	CONDENSER
Overall Width (ft)	8	8
Overall Height (ft)	15	15
Overall Depth (ft)	5	5
Dry Weight (lbs)	12,900	12,900
Operating Weight Including Ammonia (lbs)	15,000	13,500
Operating Weight Including Ammonia & Seawater (lbs)	19,800	18,300

Figure 3.3-5. Test Articles Physical Characteristics (Aluminum)

ADVANTAGES	DISADVANTAGES
<p><u>ALUMINUM</u></p> <ul style="list-style-type: none"> • DEMONSTRATED THERMAL/HYDRAULIC PERFORMANCE • ASME APPROVED MATERIALS • LOWEST COST FIRST ARTICLE PRODUCTION HEAT EXCHANGERS • DEMONSTRATED CORROSION/EROSION MITIGATION APPROACH • DEMONSTRATED PRODUCTION FABRICATION TECHNIQUES 	<ul style="list-style-type: none"> • LIFE UNCERTAINTY • POSSIBLY HIGHER MAINTENANCE/REPAIR COSTS (NOT IN TEST ARTICLE) • SUBSEQUENT CHANGE TO ALTERNATE MATERIAL. REQUIRES FABRICATION DEMONSTRATION • LOWER SYSTEMS AVAILABILITY
<p><u>STAINLESS STEEL</u></p> <ul style="list-style-type: none"> • PROJECTED 30-YEAR LIFE, COMPARABLE WITH LIFE-CYCLE COST OF ALUMINUM • LOWER RISK OPTION THAN ALUMINUM • POTENTIALLY LESS MAINTENANCE/REPAIR • HIGHER SYSTEM AVAILABILITY 	<ul style="list-style-type: none"> • LOST OPPORTUNITY TO ASSESS ALUMINUM • INCREASED COST OF TEST ARTICLE • REQUIRES ADDITIONAL HEAT EXCHANGER DESIGN AND LONGER SCHEDULE

Figure 3.3-6. Advantages/Disadvantages of Alternative Heat Exchanger Construction Materials

MARK	REQUIRED NUMBER	SIZE (INCHES)	RTG FACING	SERVICE
N1	1	4	TBD	AMMONIA LIQUID IN (E)*, OUT (C)**
N2	1	14		AMMONIA VAPOR OUT (E), IN (C)
N3	1	1½		NONEVAPORABLES (E), NONCONDENSABLES (C)
N4	4	1½ (NPT)		TEMPERATURE CONNECTIONS
N5	4	1½ (NPT)		PRESSURE CONNECTIONS
N6	1	1½ (NPT)		DRAIN
N7	1	1½ (NPT)		VENT
01	2	6		OBSERVATION PORTS (SIGHT GLASSES)
02	2	6		OBSERVATION PORTS (SIGHT GLASSES)
03	1	6		HAND HOLE
*E = EVAPORATOR **C = CONDENSER				

Figure 3.3-7. 0.2 MWe Heat Exchanger Penetration List

Figure 3.3-8. Module Penetrations

LOCATION	NOMINAL PIPE SIZE	PIPE SCHEDULE	FLOW VELOCITY
EVAPORATOR IN AND CONDENSER OUT	4-INCH (4.50-INCH OD)	40 STANDARD (0.237-INCH WALL)	4.1 FT/SEC
EVAPORATOR OUT AND CONDENSER IN	14-INCH (14-INCH OD)	40 STANDARD (.375-INCH WALL)	31.8 FT/SEC

Figure 3.3-9. Inlet and Outlet Nozzles for 0.2 MWe Test Articles

Installation Approach. The procedures for installing and handling the test articles are similar to those for the 10 MWe heat exchanger subassemblies described in Section 5.8.6 and Appendix II, Section 11 except that the test articles will be much smaller and easier to maneuver. In addition, the alignment procedures necessary for the heat exchanger subassembly are not required for the test articles.

Connection of the test article process piping will be much simpler than for the 10 MWe heat exchangers. The test articles will have bolted flanged ammonia connections as opposed to the welded connections for the 10 MWe subassemblies. This will simplify the coordination with the OTEC-1 ship systems contractor and the installation of the process piping.

A separate seal assembly will be provided on each side of the module for inlet and outlet of the seawater. It will butt against the compartment type structure which houses the test article module.

Transportation. Since the 0.2 MWe test articles are less than 10 feet wide, no specific transportation problems are foreseen. For over land transportation to the OTEC-1 platform, the module will be laid horizontal with its width in line with the truck's width and its height in line with the truck's length.

Maintenance Approach. The test articles will be in service in the OTEC-1 environment for a period of up to five years and will require scheduled and unscheduled maintenance programs. Although the heat exchangers require minimum mechanical maintenance, since they have no moving parts, it will be necessary to shutdown the test system periodically to check the durability of all exchanger component items. At that time, the exchangers will be

examined closely for wear, corrosion, leaks, biofouling and overall condition.

Removal of the test articles will necessitate the deflation of the water seals between the heat exchanger faces and the inlet/outlet water boxes, and separation of ammonia lines. Thus, it is recommended that the following spare parts be on hand:

- 1) One set of seals for both the evaporator and condenser
- 2) Extra sets of gaskets, or material to make same, for the ammonia piping connections.

The 0.2 MWe test article repair procedures are identical to those used for the 0.625 MWe modules of the 10 MWe heat exchangers. The equipment identified for the 10 MWe heat exchangers will be necessary in the event that panels are damaged during testing. If the damage cannot be repaired by welding, that is, the leakage is in an inaccessible location, the water passage will be blocked by use of an expanding foam-filled insert (see Section 5.5.7 which will prevent ammonia leakage.

Manufacturability and Quality Assurance Procedures. The manufacturing of the 0.2 MWe heat exchanger test articles is essentially identical with that of the 0.625 MWe power modules described in Section 3.6. Since the fabrication of the test articles is within the state of the art, no extraordinary construction time is foreseen for the proposed design. Existing tooling and manufacturing techniques will be used to fabricate the test articles.

A proposed manufacturing facility to be used for the test article fabrication is shown in Figure 3.3-10. The arrows indicate how the components move through the plant and a detailed description of the fabrication procedures is presented in Appendix II, Section 10. The components of the test articles (i.e., the downcomers, panel, header beams, and strong-backs) will be assembled in subassembly areas and transported to the final assembly area. After assembly the test articles will be moved to the pressure test area. Leak tests will be performed with the upper and lower shell assemblies temporarily fastened. Retesting will be performed after completion of any required repairs. The upper and lower shell assemblies

Figure 3.3-10. Planned Plant Flow Diagram 0.2 MWe Facility

will be welded permanently in position and tested for leaks. The completed module will then be pressure-tested to ASME code requirements and stamped. Upon completion of the code tests, the test module will be moved into the paint area where it will be cleaned, masked, and painted, and prepared for shipment.

The die for forming the heat exchanger panels is a critical item. Past experience has shown that it is easy to draw a die shape on paper; whereas the skill to dress the die, to flow the metal, lubricate the die and prevent the metal from being torn requires the knowledge of skilled operators and developmental studies. During Phase I, two sets of experimental dies were fabricated to demonstrate the formability of aluminum and stainless steel alloys to the required 3/4 inch water passages. Then tests were performed to demonstrate that the panels can be fabricated.

The die components are shown in Figure 3.3-11. A few initial samples of 0.050 inch thick aluminum alloy and 0.027 inch stainless steel AL-6X are shown on the figure. The die was designed for the 0.050 inch aluminum stock but was easily adjusted to form the stainless steel. The test demonstrated the excellent formability of the stainless steel and aluminum alloys.

Figure 3.3-11. Formed Material Samples

Subsequent to this initial material test, a longer set of experimental dies 12 inches long were developed. The contours were based on the smaller 3 inch die set. The die components are shown in Figure 3.3-12. The die was used to form an aluminum alloy 5052-0 pressure test panel and 0.040 inch 3004-0 Alclad samples. The results of the test were described in Section 3.1. The knowledge gained during the fabrication of these test samples will be used during fabrication of the 0.2 MWe test articles.

Figure 3.3-12. Die Set (12 Inch Long)

During Phase I a setup and tooling test for trial laser welding of 0.050 inch aluminum alloy 5052 was also performed. The setup was an adaptation of an existing set of tooling to simulate the edge welds required for panel fabrication. The sample work piece was limited to about 18 inches of length. All welds made with this arrangement were satisfactory. The pressure containment capability was over 1000 psi when the sample was constrained as it will be in the heat exchanger. The laser welding with thick materials was approximately 60 in/min. Gas tungsten arc welding, however, will be used to fabricate the 0.2 MWe test articles because laser welding is not a conventional welding technique, necessary for obtaining code qualification.

As it has been considered necessary to design and qualify the 0.2 MWe test articles to the ASME code (i.e., ASME Boiler and Pressure Vessel Code, Section VIII, Division 1) qualification and inspection procedures established by UCC/Linde in conjunction with the code inspector will be used. Linde established procedures also will be followed during manufacture (see Appendix II, Sections 10 and 15). These procedures have been written in order that Linde can comply with ASME code requirements. Any revisions to the manual must be approved by the authorized inspection agency.

The fabrication and testing will be directed as required by the ASME code. The final acceptance test may be witnessed by the interested parties. The ASME inspector will determine the specific "hold points" beyond which fabrication cannot continue until approval is received. These hold points will be established prior to start of fabrication.

3.3.2.2 Auxiliary Equipment

0.2 MWe Tube Cleaner. The tube cleaner has been designed to mechanically remove biofouling material from the seawater passages. As in the 10 MWe tube cleaner design, (Section 3.4) cleaning is accomplished by periodically brushing the seawater tube passages with a brush. However, unlike the 10 MWe design, the 0.2 MW tube cleaner is manually operated.

The tube cleaner is shown in Figure 3.3-13 and its characteristics are given in Figure 3.3-14. Detailed description of the design is in the report contained in Appendix II, Section 7. The procurement specification is in Appendix I, Section 10.

0.2 MWe Phase Separator. The 0.2 MWe phase separator is of the centrifugal type and operates in the horizontal position. The unit is a cylindrical assembly with end inlet and outlet.

The design requirements, with exception of the flow rate are the same as the 10 MWe. (See Section 5.1.5).

The 0.2 MWe phase separator characteristics are summarized in Figure 3.3-15. The procurement specification is provided in Appendix I, Section 10.

0.2 MWe Accumulator Tank. The purpose of this tank is discussed in Section 5.1.5. During startup, when there is a large amount of ammonia vapor and noncondensibles in the liquid part of the system, this tank will perform a gross separation of vapor and gas from the liquid. The vapor/gas will be returned to the condenser inlet.

The need for this device has not been demonstrated. Therefore, the 0.2 MWe test loop will have a bypass line around the accumulator so that by closing one valve and opening a second valve the ammonia flow can be bypassed around the accumulator and the need for it readily assessed.

The characteristics of the accumulator are given in Figure 3.3-16.

FRAME SIZE		
• HEIGHT	FT	14
• LENGTH	FT	7
• WIDTH	FT	4
WEIGHT		
• CLEANING HEAD	LBS	400 TO 500
• FRAME, RAILS & DRIVES	LBS	2000 TO 2100

Figure 3.3-14. PSD-II 0.2 MWe Test Articles Tube Cleaner

SIZE		
• DIAMETER	IN.	24
• LENGTH	IN.	68
• ORIENTATION		HORIZONTAL
WEIGHT		
• DRY	LBS	1200
• OPERATING	LBS	1250
GENERAL		
• OPERATING PRESSURE	PSIG	119
• DESIGN PRESSURE	PSIG	167
• PRESSURE DROP	PSID	0.35 (MAXIMUM)
• MATERIALS		
BODY		CARBON STEEL
BLADES		STAINLESS STEEL 304L

Figure 3.3-15. PSD-II MWe Test Articles Phase Separator Characteristics

SIZE		
• DIAMETER	IN.	8
• LENGTH	IN.	20
• ORIENTATION		VERTICAL
• CONFIGURATION		CYLINDER WITH END CAPS
WEIGHT		
• DRY	LBS	38
• OPERATING	LBS	57
GENERAL		
• OPERATING PRESSURE	PSIG	78
• RELIEF PRESSURE	PSIG	167
• MATERIAL		CARBON STEEL

Figure 3.3-16. PSD-II 0.2 MWe Test Articles Accumulator Tank

Water Boxes and Transition Pieces. The water boxes and transition pieces will be made out of 9/16" carbonsteel and stiffened to withstand the water pressure. Both the water boxes and transition pieces will be epoxy coated to reduce the corrosive effects of the seawater.

The water boxes will be connected to the aluminum heat exchanger by an inflatable seal in order to eliminate galvanic corrosion. This is the same type of seal used for intermodule sealing in the full scale design. The water boxes and transition pieces are shown in the perspective in Figure 3.3-17.

The water boxes are designed such that a suitably formed perforated plate (similar to a conventional tube sheet) can be installed at the exit of each heat exchanger. This plate will be designed to closely simulate flow and fouling conditions between modules. The details of the design will be developed in Phase II.

Water Screens. The water screens will be 3/8 inch carbon steel perforated plates coated with epoxy. The purpose of the screens is to establish even flow distribution across the heat exchanger frontal area, see Figure 3.3-17.

3.3.3 OTEC-1 Integration

The integration of the PSD-II 0.2 MWe test article into the OTEC-1 Early Ocean Test Platform (EOTP), for performance verification testing, is described in this section.

Figure 3.3-17. 0.2 MWe Test Article Arrangement

The vessel selected by DOE for conversion to the OTEC-1 test platform is the USN Tanker T2-SE-A1 CHEPACHET (TAO-78). Figure 3.3-18 shows the CHEPACHET converted to EOTP use. The PSD-II evaporator and condenser (0.2 MWe test articles) will be tested in an enclosed compartment in the forward part of the ship presently being outfitted for the 1 MWe heat exchangers. The compartment, as shown, indicates the relationship between cold and warm seawater intakes and discharges. Ammonia storage is on the main deck above the OTEC-1 test compartment. Controls and instrumentation

Figure 3.3-18. Early Ocean Test Platform

data acquisition for the tests will be located in a self-contained van aft of the midship deckhouse. A biofouling and corrosion laboratory van will be located adjacent to the control van.

3.3.3.1 Test Article Arrangement

The test article general arrangement is illustrated in Figure 3.3-17. The components have been selected and arranged to fulfill the test objectives described in Section 3.3.1.

TRW plans on providing the following components of the 0.2 MWe test article arrangement:

Heat exchangers (condenser and evaporator)	2
Tube cleaners	2
Water boxes including screens	2
Inlet and outlet transitions	4
Phase separator	1
Accumulator	1

The first four components will be packaged for assembly on a common platform as shown in Figure 3.3-19. This packaged assembly design is to minimize the space required in the OTEC-1 EOTP test compartment. The mounting skid is required for support and to provide access for piping connections to be made at the bottom of the heat exchanger modules.

The PSD-II 10 MWe power plant design incorporates open water boxes with a tube cleaning device that provides in service cleaning of heat exchangers to reduce fouling factors and improve performance (see Section 3.4). It is necessary to demonstrate this fouling factor reduction capability and evaluate development improvement modifications during performance testing. After conversion and reclassification, CHEPACHET (OTEC-1 EOTP) will operate with a draft of 24 feet at a displacement of 17,000 LT. This ballasted conversion is to obtain a freeboard of 16 feet to provide a dry operating deck under all operating conditions. The resultant draft and closed seawater manifolding above deck preclude the use of open water boxes in the test compartment. Therefore, the 0.2 MWe heat exchanger/water box assembly is a closed water box with the tube cleaning device inside.

This arrangement does not affect performance and is adapted to accommodate the EOTP configuration. The closed water box is larger than the heat exchanger face area because of the positioning carriage. A perforated plate is included in the inlet transition section to obtain even flow distribution across the heat exchanger face.

3.3.3.2 Shipboard Layouts

The forward test compartment of the OTEC-1 EOTP will be 111 feet long and 35 feet wide providing approximately 3,885 ft² for test articles, ancillary equipment and cold and warm seawater supply and return manifolding. This space is more than ample for the TRW/Linde 0.2 MWe test article assemblies described in Section 3.3.2. However, DOE has indicated a desire to test up to four 0.2 MWe heat exchanger sets (evaporator and condenser) simultaneously in the same compartment. We have examined several conceptual arrangements of the 0.2 MWe test article assemblies to support the DOE goal of simultaneous testing. The two prime concepts are shown in Figure 3.3-20.

Concept A

This conceptual layout considers a side by side arrangement of nested evaporator and condenser assemblies. The nested arrangement achieves a small area requirement with both assemblies on the same level for ease of maintenance and observation. The assembly base height is established by the need for approximately 15 feet between the condenser base and pump intake (NPSH). It is noted that this arrangement allows use of the 1 MWe structural supports, which established a base level for the same NPSH head requirements. Another advantage of this arrangement is that the water inlet and outlet pipe manifolds can be maintained on the same center line elevations as exist in EOTP.

Concept B

This conceptual layout considers stacking the evaporator and condenser assemblies. The objective of this approach is to achieve the absolute minimum area requirement and optimize compartment volume utilization. The condenser assembly is shown on the upper level to obtain the required NPSH. Although the integration design approach optimizes test article packing density to assist DOE in achieving the testing of up to four heat exchanger

MODULE PENETRATIONS SCHEDULE
(NOT TO SCALE)

0.2 MW_e HEAT EXCHANGER PENETRATION SCHEDULE
EVAPORATOR (E) AND CONDENSER (C)

MARK	NUMBER	SIZE	SERVICE
N1	1	4"	AMMONIA LIQUID IN (E), OUT (C)
N2	1	14"	AMMONIA VAPOR OUT (E), IN (C)
N3	1	1 1/2"	NONEVAPORABLE (E)
N4	4	1 1/2" NPT	NONCONDENSABLE (C)
N5	4	1 1/2" NPT	TEMPERATURE CONNECTION
N6	1	1 1/2" NPT	PRESSURE CONNECTION
N7	1	1 1/2" NPT	DRAIN
N8	1	1 1/2" NPT	VENT
O1	2	6"	OBSERVATION PORT (SIGHT GLASS)
O2	2	6"	OBSERVATION PORT (SIGHT GLASS)
O3	1	6"	HAND HOLE

DESIGNED <i>P. J. Brown</i>	OTEC POWER SYSTEM DEVELOPMENT - II	TRW
DRAWN <i>PEG BROWN</i>	0.2 MW _e TEST ARTICLE	FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY
CHECKED <i>J. M. Smith</i>	HEAT EXCHANGER	DRAWING NUMBER 6B50.94-58
APPROVED <i>P. J. Brown</i>	CLOSED WATER BOX ASSEMBLY	ISSUE DATE 5-14-79
RELEASED BY <i>[Signature]</i>		CHK LTR A

Figure 3.3-19. 0.2 MW_e Test Article Heat Exchanger Closed Water Box Assembly

Figure 3.3-20. 0.2 MWe Test Article Conceptual Test Loop OTEC-1 Shipboard Arrangement

sets, there are some disadvantages. One disadvantage is that the two levels complicate the ease of maintenance and simultaneous test observations. Also the inlet and outlet water connections on different levels cause some complications in manifolding to the mains.

3.3.3.3 OTEC-1 Support Services

The OTEC-1 EOTP, as the test bed for the 0.2 MWe heat exchangers, provides the test support services and functions necessary for performance verification testing. The physical and functional data required for integrated planning of these support services is presented in this section. All data are at a preliminary design level and will be revised during Phase II detailed design through the Interface Control Working Group and Test Planning and Instrumentation Working Group activities.

The following interface integration data are presented in the general format requested by the OTEC-1 Test Director Contractor, (TDC), Energy Technology Engineering Center (ETEC).

List of Equipment Provided by TRW/Linde

<u>Equipment</u>	<u>Quantity</u>
Evaporator	1
Condenser	1
Tube Cleaner	2
Water Box	2
Transition	4
Phase Separator	1
Assembly Support	2
Instruments and Controls	1 (Figure 3.3-27/28)
Accumulator	1
Perforated Plate	2

List of Equipment Required but not Supplied by TRW/Linde

<u>Equipment</u>	<u>Quantity</u>
Ammonia Loop Piping	1 Lot (Figure 3.3-3)
Valves and Components	1 Lot (Figure 3.3-3)
Instruments and Controls	1 Lot (Figure 3.3-27/28)
Auxiliary Systems	(defined below)
Ammonia Feed Pump	1

Auxiliary System Requirements

<u>Item</u>	<u>Type</u>	<u>Quantity/Purpose</u>
a. Working Fluid	Liquid Ammonia	3,000 lbs.
b. Loop Purging	Gaseous Nitrogen	1,000 SCFM per Purge Cycle
c. Electric Power	24VDC	Instrumentation
	110/220VAC	Tube Cleaner Drive
d. Compressed Air	90 psig, Oil Free	80 SCFM ea, Tube Cleaner
e. Chlorination	- -	15 + 10 lb/hr, Seawater Supply
f. Vent (Waste Disposal)	Ammonia, Nitrogen Non-Condensibles	Relief Valve and Purge Products

Physical Interfaces

- a. Weights (see Figure 3.3-21)
- b. Inventory of working fluid (ammonia)
 - (1) Evaporator - 2,100 lbs
 - (2) Phase Separator - 50 lbs
 - (3) Condenser - 600 lbs
 - (4) Piping - 250 lbs
- c. Foundation loadings (see Figure 3.3-21)
- d. Envelope dimensions (see Figure 3.3-19)
- e. Inlets
 - (1) Heat exchangers (see Figure 3.3-19)
 - (2) Seawater inlets - 24 in. dia.
- f. Outlets
 - (1) Heat exchangers (see Figure 3.3-19)
 - (2) Seawater outlets - 24 in. dia.
- g. Vents (see Figure 3.3-3)
- h. Drains
 - (1) Heat exchangers (see Figure 3.3-3)
 - (2) Phase separator - 1 in. Raised Flange
- i. Ammonia piping (see Figure 3.3-3)

Functional Interfaces (see Figure 3.3-2)

- a. Ammonia flow rates
 - (1) Evaporator - 59,080 lb/hr
 - (2) Phase separator - 59,080 lb/hr in (1190 lb/hr of liquid returned)
 - (3) Condenser - 60,050 lb/hr

- b. Ammonia fluid pressure
 - (1) Evaporator - 121.5 psig
 - (2) Phase separator - 120 psig
 - (3) Condenser - 78.5 psig
- c. Ammonia pressure loss
 - (1) Evaporator - 1.46 psid
 - (2) Phase Separator - 0.35 psid
 - (3) Condenser - 0.37 psid
- d. Ammonia temperatures
 - (1) Evaporator - 72.3°F (60°F to 80°F)
 - (2) Phase separator - 72.2°F (60°F to 80°F)
 - (3) Condenser - 52.3°F (40°F to 60°F)
- f. Ammonia states at inlet
 - (1) Evaporator - Subcooled liquid
 - (2) Phase separator - Saturated vapor
 - (3) Condenser - Wet vapor

Heat Exchanger Performance Requirements

- a. 0.2 MWe Evaporator (see Figure 3.3-22)
- b. 0.2 MWe Condenser (see Figure 3.3-23)

ITEM	DRY WEIGHT (LB.)	FOUNDATION LOADING OPERATING (LB.)
HEAT EXCHANGER	12,900	19,800
TUBE CLEANER	2,500	2,500
WATER BOX	15,000	93,000
INLET TRANSITION	3,200	16,000
OUTLET TRANSITION	2,500	8,500
SUPPORT FRAME	5,000	5,000
TOTAL	41,100	144,800

(1) SEE FIGURE 3.3-19 FOR DIMENSIONS OF THE HEAT EXCHANGER-CLOSED WATER BOX ASSEMBLY.

(2) ASSEMBLY IS TYPICAL FOR EVAPORATOR AND CONDENSER TEST ARTICLES.

Figure 3.3-21. Heat Exchanger Assembly Weights

PARAMETER	INLET	OUTLET	INSTRUMENT ACCURACY
REQUIREMENTS (NOMINAL CONDITIONS)			
WARM SEAWATER TEMPERATURE (°F)	82.0	80.8	± 0.1°F
WARM SEAWATER FLOW RATE (GPM)	49,500	49,500	± 0.5% OF SPAN
SEAWATER SIDE ΔP (FEET)	—	1.82	± 0.2% OF SPAN
SEAWATER VELOCITY (FPS)	6.42	6.42	CALCULATED
AMMONIA TEMPERATURE (°F)	52.5	72.3	± 0.1°F
AMMONIA PRESSURE (PSIA)	136.16	134.7	± 0.2% OF SPAN
AMMONIA SIDE ΔP (PSID)	—	1.46	± 0.2% OF SPAN
AMMONIA RECYCLE RATIO (1-X)/X	0.52	—	CALCULATED
GOALS (AT DESIGN FOULING FACTOR 0.0003)			
AMMONIA FLOW RATE AT 97 PERCENT EXIT. QUAL. (LB/SEC)	—	10.4	± 0.5% OF SPAN
THERMAL DUTY (MBTU/HR)	—	30.0	CALCULATED
OVERALL U (BTU/HR-FT ² · °F)	819	819	CALCULATED

Figure 3.3-22. Performance Requirements for 0.2 MWe Evaporator

PARAMETER	INLET	OUTLET	INSTRUMENT ACCURACY
REQUIREMENTS (NOMINAL CONDITIONS)			
COLD SEAWATER TEMPERATURE (°F)	40.0	41.3	± 0.1°F
COLD SEAWATER FLOW RATE (GPM)	48,600	48,600	± 0.5% OF SPAN
SEAWATER SIDE ΔP (FEET)	—	1.73	± 0.2% OF SPAN
SEAWATER VELOCITY (FPS)	6.05	6.05	CALCULATED
AMMONIA TEMPERATURE (°F)	52.3	52.3	± 0.1°F
AMMONIA PRESSURE (PSIA)	93.2	92.83	± 0.2% OF SPAN
AMMONIA SIDE ΔP (PSID)	—	0.37	± 0.2% OF SPAN
GOALS (AT DESIGN FOULING FACTOR 0.0003)			
AMMONIA FLOW RATE AT 96.4 PERCENT. (INLET QUAL. LB/SEC)	16.7	—	± 0.5% OF SPAN
THERMAL DUTY (MBTU/HR)	—	30.0	CALCULATED
OVERALL U (BTU/HR-FT ² · °F)	614	614	CALCULATED

Figure 3.3-23. Performance Requirements for 0.2 MWe Condenser

3.3.3.4 Operation and Maintenance

Purging. Initially, air will be purged from the system with nitrogen to avoid a flammable mixture when ammonia is introduced. Then the nitrogen will be purged with ammonia vapor to free the system of noncondensibles before charging the system with liquid ammonia. When maintenance requires opening any part of the system containing ammonia, that part of the system will first be isolated, vented, and purged with nitrogen. If personnel are to enter the system, the nitrogen will be displaced with air. This can be done with portable blowers.

When a system is purged by adding a purge gas, allowing the system pressure to rise, and then venting down to the original pressure, the concentration of the original gas at the end of any number of cycles will be calculated considering the following:

Flammability Limits. The American Gas Association (AGA) recommends dilution of the ammonia vapor down to 1/5 of the safe limit. This is a rather conservative approach. Nevertheless, this guide can be followed without an excessive use of nitrogen.

Nitrogen Purging Requirements. Nitrogen purging requirements will be calculated using 1/5 of the safe limit as recommended by AGA and using formula for dilution when perfect mixing is assumed. When purging with nitrogen to remove air, the oxygen content will be reduced to 1/5 of 14 percent with three volume changes in three cycles using equal system volumes of nitrogen to remove ammonia. The ammonia content will be reduced to 1/5 of 50 percent with three volume changes in six cycles using an amount of nitrogen equal to 1/2 of the system volume each cycle. Using this approach, it will take three volume changes to purge either air or ammonia to acceptable limits.

Purging Nitrogen with Ammonia. To displace the nitrogen in the power loop with ammonia, it is calculated that five volume changes will be adequate. The required ammonia vapor will be drawn from the vapor space of the ammonia storage vessels. It will be introduced at the high points and nitrogen purged from the low points. The ammonia vapor drawn from the vapor space of the ammonia storage vessels will be essentially water free.

Noncondensibles. During operation, any noncondensibles in the system are swept into the condenser along with the ammonia vapor. The ammonia vapor is condensed and pumped to the evaporator, leaving behind the noncondensibles. Noncondensibles collect at the bottom of the condenser and are to be removed from the system through a piccolo tube located immediately under the condenser plates.

It is planned that noncondensibles, with some ammonia, will be vented to the OTEC-1 vent stack. Here, a significant part of the ammonia will be dissolved in seawater which is continuously added to the bottom of the vent stack. The system integration contractor will have to provide for the collection, processing and discharge of these vapors.

Control Requirements. A control concept for the 0.2 MWe has been developed as shown in Figure 3.3-3. Details, sizing, off design point performance and transient response will be completed during detail design.

The control system contains two controllers. The theory of operation of the two main elements is as follows:

Evaporator Liquid Level Control. At nominal conditions the down-comer liquid level in the evaporator should be 5.5 feet. This liquid level will be maintained by measuring the liquid level in a column in parallel with the evaporator, or by measuring evaporator ΔP and using the error signal to adjust feed pump speed. The effect of changing liquid level will be investigated, see Section 3.3.4.

Condenser Liquid Level. The condenser liquid level is separately controlled and maintained at the same optimum level by a liquid level sensor that opens or closes a valve in the liquid ammonia supply line. The liquid level sensor is in a column parallel to the condenser or a direct ΔP measurement will be used.

3.3.4 Test Planning

The 0.2 MWe test articles are representative of the full-scale heat exchangers and will provide data relevant to the 10 MWe power module design. The utilization of either aluminum or stainless steel for the heat exchangers will have minimal impact on the conduct of test operations. Either one provides opportunities to confirm the fabrication processes and material design basis and provides useful data for assessing and applying alternate materials. The plans for thermal/hydraulic data collection and reduction will assure applicability to full scale design, irrespective of the materials of construction.

3.3.4.1 Test Plan

The test program will consist of several phases starting with acceptance and installation of the test articles and continuing through long term biofouling, corrosion and erosion assessment testing. The tests will be structured and scheduled so the test objectives can be achieved without unnecessary duplication of tests.

After the installation of the test articles on board the OTEC-1 test platform, they will be subjected to a series of pressure and functional checks to verify the overall integrity of the test loop (including the test articles) and confirm start up, operational and shutdown (including emergency shutdown) procedures. Testing will be initiated only after the test articles and loop, and operating procedures have been proven safe and adequate to support the testing.

The initial heat exchanger tests will be under various static operating conditions to evaluate the ammonia system characteristics and develop heat balance data. Further tests will be performed to measure the effect of biofouling growth on performance, and to measure the effectiveness of the biofouling cleaning machine and the chlorination countermeasure system. In parallel with these biofouling tests, tests will be performed to assess the effectiveness of the heat exchanger control system under varying environmental operating conditions. Finally, the long term biofouling and heat transfer surface corrosion/erosion testing will be performed.

The major test activities necessary to meet the test objectives will be as follows:

- 1) Steady state thermal hydraulic performance mapping under various operating conditions
 - Establish baseline (unfouled) heat exchanger overall heat transfer coefficient (U).
 - Verify the evaporator exit ammonia vapor quality and flow rate
 - Verify water and ammonia side ΔP .
- 2) Biofouling testing
 - Determine the rate of performance degradation due to biofouling with no countermeasure or cleaning

- Determine the effectiveness of the chlorination countermeasure system in inhibiting performance degradation
- Determine the effectiveness of the biofouling cleaning machine in restoring performance
- Determine the frequency of cleaning and chlorination dose rates necessary for effective and economic biofouling control ($R_f < 0.0003$ average).

3) Operational Testing

- Determine the effect of noncondensibles on the condenser performance and the effectiveness of the noncondensable extraction design approach
- Determine the effect of nonevaporables, primarily water, on the evaporator performance and the effectiveness of the nonevaporables blowdown design approach
- Verify the ability of the control system to maintain proper liquid levels and inventory in the heat exchangers under steady and transient operation
- Establish the performance characteristics of the heat exchangers under sea platform motions and seawater supply surges.

4) Auxiliary Equipment Testing (tube cleaner and phase separator)

- Test and establish effectiveness of various brush designs and stiffnesses
- Verify indexing, alignment and stroking mechanism design
- Verify cleaning cycle time
- Confirm the performance of the phase separator by verifying exit ammonia vapor quality and ammonia ΔP
- Assess if the accumulator is a required item
- Demonstrate the tube plugging technique.

5) Survivability Testing

- Monitor corrosion during test operations
- Monitor leaks and verify operation of leak detection equipment
- After test program, perform corrosion and erosion survey (destructively as necessary).

3.3.4.2 Test Descriptions

Test Sequence. As a general rule, the thermal/hydraulic, biofouling, corrosion monitoring and operational tests are to be conducted in parallel. When potential serious compromise of test results exist, parallel test activities will be suspended in favor of discrete test activities.

Figure 3.3-24 illustrates the anticipated top level test flow. Detailed test planning in Phase II will add further details and modify the test flow as necessary to satisfy best the test objectives and platform/schedule constraints. As noted in the Figure 3.3-24, some tests are serial and will probably control test schedules. In the detail test planing phase, efforts will be made to minimize serial test sequences to reduce test schedules and to ensure the most effective use of test facilities/personnel.

Figure 3.3-24. Test Sequence

Thermal/Hydraulic and Biofouling Tests. The heat exchanger thermal/hydraulic performance verification tests will initially be carried out with the nominal 0.2 MWe parameters of:

Cold seawater flow	46,600 gpm
Warm seawater flow	49,500 gpm
Evaporator ammonia pressure	136.2 psia

At these test parameters, the heat exchangers are expected to yield the following nominal performance.

Condenser ammonia pressure	93.2 psia
Ammonia evaporation rate	16.4 lb/sec
Evaporator ammonia exit quality	> 97 percent
Heat exchanger thermal duty	30,000,000 Btu/hr

During all thermal/hydraulic and biofouling tests, the following data will be recorded by instrumentation provided either with the test articles or by the OTEC-1 test platform. Figure 3.3-3 schematically illustrates the primary instrumentation and location. Measurements and responsibilities are as shown below:

Condenser:

- Seawater inlet and outlet temperature (OTEC-1)
- Seawater flow rate (OTEC-1)
- Ammonia inlet and outlet pressure and temperature (TRW)
- Ammonia inlet quality (OTEC-1)
- Noncondensable extraction flow rate and quantity (OTEC-1)
- Liquid level (TRW)

Evaporator:

- Seawater inlet and outlet temperature (OTEC-1)
- Seawater flow rate (OTEC-1)
- Ammonia inlet and outlet pressure and temperature (TRW)
- Ammonia exit quality (OTEC-1)
- Nonevaporables blowdown rate and quantity (OTEC-1)

Ammonia Feed pump:

- Ammonia flow rate (OTEC-1)
- Pump speed and power (OTEC-1)

Turbine Simulator:

Liquid ammonia injection flow rate (OTEC-1)

Desuperheater inlet pressure and temperature (OTEC-1)

Throttle valve inlet pressure and temperature (OTEC-1)

Phase Separator:

Exit vapor quality (OTEC-1)

Liquid ammonia separation flow rate (TRW)

The data will establish the baseline performance of the system. Following baseline performance characterization, further verification of the thermal/hydraulic design will be performed by sensitivity evaluations. Operating parameters such as seawater flow, ammonia side operating pressure and seawater supply temperature (if capability is provided by the OTEC-1 test platform) will be varied over ranges to be finalized during Phase II planning. Tentatively, seawater flow rates will range from 50 percent to 150 percent of nominal, ammonia side operating pressure ± 10 psi, and seawater temperature differences (warm to cold) from 32 to 45 degrees F.

It is to be noted that the reference thermal/hydraulic performance characterization is predicated on eliminating biofouling effects. This can be assured by performing test very rapidly (probably not reasonable for this test system) or by implementing a vigorous biofouling control (cleaning) program during this test phase. This issue will be addressed and resolved during Phase II test planning/OTEC-1 test platform coordination.

The heat exchanger overall heat transfer coefficient is the primary index used to characterize the heat exchanger performance. With the data obtained and recorded above, U will be computed from the following equation:

$$U = \frac{q}{(A)(F)(LMTD)}$$

where, U = Overall heat transfer coefficient, Btu/hr-ft²-°F

q = Heat transfer rate, Btu/hr

A = Surface area, ft²

LMTD = Log mean temperature difference, °F

$$= \left[\frac{\Delta T_{\text{inlet}} - \Delta T_{\text{outlet}}}{\ln \left(\frac{\Delta T_{\text{inlet}}}{\Delta T_{\text{outlet}}} \right)} \right]$$

ΔT_{inlet} = Water inlet temperature
- ammonia outlet (evap) or inlet (cond) temperature, °F

ΔT_{outlet} = Water outlet temperature
- ammonia outlet (evap) or inlet (cond) temperature, °F

F = Correction factor for cross-flow (computed by UCC/Linde's two-dimensional analysis)

The heat transfer rate will be determined by heat balances on both ammonia and seawater side. Agreement within 10 percent may be used as an acceptance criterion. The change in the seawater temperature from inlet to outlet of the test module is nominally about 1°F with variation of outlet temperature vertically about 0.1°F. Therefore, an average outlet temperature must be used in the heat balance calculation waterside. Direct ΔT measurements between inlet and outlet seawater are recommended to reduce error accumulation.

The rate equation for U , listed above will yield an average U for the heat exchanger (evaporator or condenser). In the evaporator the energy used to preheat the incoming subcooled ammonia is small, about 4 percent of the total evaporator load. Therefore, the method outlined above is justified:

- It measures evaporator performance in the way it is nominally used, i.e., with subcooled feed
- It avoids the necessity of attempting to calculate any weighting factors within the evaporator
- It produces a result which is well within the expected overall accuracy in U .

The accuracy of the U-factors is heavily dependent upon the accuracy of the sensors as stated in ETEC report number R-070E-A01-T1004. The report shows that the accuracy of the temperature sensors is most critical. Therefore, in phase II an error analysis will be performed using the method outlined in the ETEC report. The results of the error analysis will be used to specify instrumentation accuracy requirements.

Biofouling tests will employ the U-factor determined as discussed above. The test loop will be operated continuously and the data analyzed on a regular basis to detect degradation of the U-factor. When the reduction in U-factor reaches predetermined levels, the mechanical cleaning operation will be implemented and its effectiveness evaluated. The operation of the system will be continued in this mode until the data indicates that the rate of biofouling buildup has stabilized and the mechanical cleaning operation maintains the U-factor at a repeatable value. Various mechanical cleaning operations will be tested which will encompass different brush types and stiffnesses as well as cleaning cycle frequencies.

Following the mechanical cleaning tests, chlorination effectiveness will be evaluated. Operation of the system with mechanical cleaning to a stabilized baseline will be achieved. Chlorination of controlled dosages will then be introduced and its effect on inhibiting the rate of biofouling and U-factor degradation assessed. In addition, its impact on the required mechanical cleaning frequency will be assessed.

We are presently not proposing to use control tubes which are maintained in the clean condition by recirculating clean water as proposed for the 1 MWe Heat Exchangers onboard OTEC-1. If experience with this feature of the 1 MWe test program is good, it can easily be implemented.

Auxiliary Equipment Tests. The phase separator performance will be assessed by measuring the inlet and outlet ammonia vapor quality. Of considerable interest is its performance capabilities under off-design conditions. The techniques recommended for measuring quality are discussed in Section 3.3.4.3.

For the Phase II test loop, the tube cleaning machine will be a simplified scale unit operated manually as discussed above. Key operations will be demonstrated which include machine indexing and alignment, brush

stroking, and safety overrides to prevent equipment or heat exchanger damage in case of misalignment or other faults.

Corrosion Monitoring. Corrosion monitoring of the heat transfer surface of the heat exchanger will be accomplished with the use of linear polarization resistance probes in conjunction with flat or spool witness coupons. Relatively inexpensive portable instruments are available from Rohrback Instruments and Petrolite Corporation. One, the Corrator from Rohrback is capable of measuring the instantaneous corrosion rates and assessing the pitting tendency of the corrosive medium.

Flat coupons will be placed at the outlet end of the heat exchanger to serve as witness samples. These will confirm probe readings and provide for metallurgical samples which will be removed periodically. The samples will also be periodically mechanically brushed to simulate the cleaning experienced by the heat exchangers.

Maintenance and Repair. The test program will provide an opportunity to develop and verify maintenance procedures. Methods for cleaning the ammonia side (if required) can be demonstrated, and techniques for leak detection and tube plugging can be verified.

3.3.4.3 Instrumentation

The OTEC-1 platform contains extensive instrumentation for the seawater subsystem, and the ammonia loop equipment. It has an instrumentation and control center that has space for test heat exchanger displays with signal conditioners, computer, software, and recorders to support the 0.2 MWe test article tests.

This section describes the instrumentation required by TRW to verify the performance of the 0.2 MWe test articles and to collect data for design of the 10 MWe plant. Based on discussions with the OTEC-1 contractor, TRW identified the instrumentation that currently exists on the platform. During Phase II, the TRW/Interface Working Group will define the details of the new instrumentation, the availability of signal conditioning channels, the algorithms to be inserted into the data reduction computer, and the format of recorded data.

The instrumentation for the 0.2 MWe test article is designed to perform the following functions:

- Assess nominal and off-nominal thermal/hydraulic performance of the heat exchanger and its auxiliary equipment (steady-state and dynamic)
 - Subsystem performance
 - System performance
- Detect hazardous or abnormal events
- Isolate the cause of hazardous or abnormal events
- Produce a historical record of plant operation
- Determine when maintenance is needed.

To satisfy these functions, the instrumentation is grouped into three categories: 1) Performance and Status Instrumentation, 2) Diagnostic Instrumentation, 3) Alarm Instrumentation. The performance and status instrumentation gives the real time status of the subsystems and the system and allows the operator to evaluate the status or make any computation that is needed for performance evaluation. The diagnostic instrumentation allows the operator to detect failures or the need for maintenance, isolate them, and correct them. The alarm instrumentation detects an out-of-tolerance condition and annunciates it in the OTEC-1 Control Center. Automatic trips are reserved for hazardous events and events with expensive consequences. No hazardous events are forecast in the 0.2 MWe tests. The only events with expensive consequences are over-speed of the ammonia feedpump and low ammonia level in the condenser. The ammonia feedpump will be turned off in both cases. Seawater pump protection is assumed to be included in the OTEC-1 instrumentation.

The instrumentation and its location are shown pictorially in Figure 3.3-3. These instrument sensors are categorized in Figure 3.3-25 for the ammonia loop and in Figure 3.3-26 for the seawater loops. Figures 3.3-27 and 3.3-28 show the sensors to be furnished by TRW as part of the 0.2 MWe test article. The quantities specified do not reflect instrumentation redundancy to fit within the 40-data channel limit that DOE has informally directed, but TRW suggests that it is cost effective to make all flow, temperature and pressure sensors redundant.

COMPONENT	PERFORMANCE							DIAGNOSTICS							ALARMS		
	PRESSURE	TEMPERATURE	FLOW RATE	LIQUID LEVEL	POWER	SPEED	QUALITY	PRESSURE	TEMPERATURE	DIFFERENTIAL PRESSURE	FLOW RATE	LIQUID LEVEL	POWER	SPEED	QUALITY	LIQUID LEVEL	SPEED
FEED PUMP INLET	•	•						•	•								
FEED PUMP OUTLET	•	•						•	•								
EVAPORATOR INLET	•	•	•					•	•		•						
EVAPORATOR OUTLET	•	•					•	•	•						•		
PHASE SEPARATOR INLET	•	•					•	•	•						•		
PHASE SEPARATOR OUTLET	•	•					•	•	•						•		
DESUPERHEATER INLET	•	•						•	•								
DESUPERHEATER OUTLET	•	•					•	•	•						•		
CONDENSER INLET	•	•					•	•	•						•		
CONDENSER OUTLET	•	•	•					•	•		•						
FEED PUMPS					•	•							•	•			•
EVAPORATOR				•							•					•	
PHASE SEPARATOR			•								•						
DESUPERHEATER			•								•						
CONDENSER				•								•				•	
STRAINER										•							
AMMONIA MAKE-UP LINE			•								•						
AMMONIA FILL LINE			•														
NON-EVAPORABLE LINE			•								•						
NON-CONDENSIBLE LINE			•								•						

Figure 3.3-25. 0.2 MWe Ammonia Loop Instrumentation Location and Type

Instrumentation, Type and Accuracy. The instrumentation presented in the following section is a result of a survey of existing technology. The instrumentation has been selected to provide the desired accuracy in the test results.

Temperature Sensors. The temperatures of both the seawater and ammonia are used in the calculation of the thermal performance of the test article. As stated previously, the uncertainty of the U-factor is heavily dependent upon the accuracy of the temperature sensor and this accuracy in turn depends on the desired temperature span. Therefore,

COMPONENT	PERFORMANCE			DIAGNOSTICS			ALARMS
	PRESSURE	TEMPERATURE	FLOW	PRESSURE	TEMPERATURE	FLOW	FLOW
WARM SEAWATER INLET	X	X	X	X	X	X	X
WARM SEAWATER OUTLET	X	X		X	X		
COLD SEAWATER INLET	X	X	X	X	X	X	X
COLD SEAWATER OUTLET	X	X		X	X		

Figure 3.3-26. 0.2 MWe Seawater Loop Instrumentation Location and Type

the span will be limited to 30°F where possible, and the accuracy will be $\pm 0.10^\circ\text{F}$ or less for all temperature sensors that are used to determine the thermal performance of the heat exchangers. The remaining temperature sensors can have an accuracy of $\pm 0.20^\circ\text{F}$. We will consider using thermocouples to measure seawater in-out temperature differences directly.

Pressure Sensors. The pressure sensors will be the electrical pressure transducer type. The accuracy of the pressure sensors will be ± 0.2 percent of the span. The span will be kept as small as possible and in most cases will be 20 psi. Where a pressure difference is desired, a differential pressure sensor will be considered to reduce measurement error.

Flow Meters. The flow meters for the ammonia loop will be the turbine meter type with an accuracy of $\pm 0.5\%$ of the span. The acoustic flow meter was considered but due to the small pipe size and high cost, it was not selected.

Liquid Level Sensors. The liquid level sensors will be the differential pressure type with an accuracy of $\pm 0.20\%$ of the span.

Quality Meter. It will be required to determine quality at three locations in the test loop:

SENSOR	PARAMETER MEASURED	FURNISHED BY	QUANTITY
TEMPERATURE AND PRESSURE	FEED PUMP INLET	OTEC-1	1
	FEED PUMP OUTLET	OTEC-1	1
	EVAPORATOR INLET	TRW	2
	EVAPORATOR OUTLET	TRW	2
	PHASE SEPARATOR OUTLET	OTEC-1	1
	DESUPERHEATER INLET	OTEC-1	1
	CONDENSER INLET	TRW	2
	CONDENSER OUTLET	TRW	2
DIFFERENTIAL PRESSURE	PUMP STRAINER	OTEC-1	1
FLOW	AMMONIA FILL LINE	OTEC-1	1
	EVAPORATOR INLET	OTEC-1	1
	NON-EVAPORABLE LINE	OTEC-1	1
	PHASE SEPARATOR LIQUID RETURN LINE	TRW	1
	DESUPERHEATER LIQUID INJECTION	OTEC-1	1
	CONDENSER OUTLET	OTEC-1	1
	NON-CONDENSIBLE LINE	OTEC-1	1
LIQUID LEVEL AND LEVEL ALARMS	CONDENSER	TRW	1
	EVAPORATOR	TRW	1
QUALITY	EVAPORATOR OUTLET	OTEC-1	1
	PHASE SEPARATOR OUTLET	OTEC-1	1
	CONDENSER INLET	OTEC-1	1
SPEED POWER	FEED PUMP	OTEC-1	1
	FEED PUMP MOTOR	OTEC-1	1
AMMONIA IN AIR *	AMMONIA, LOCATIONS TBD	OTEC-1	10

*FOR SAFETY, NOT TEST INSTRUMENTATION

Figure 3.3-27. 0.2 MWe Instrumentation, Ammonia Loop

- Evaporator outlet, $X > 97\%$
- Separator outlet, $X > 99\%$
- Condenser inlet, $X > 96.4\%$

The values listed above indicate design basis for the 10 MWe power system.

In the test loop, a throttling calorimeter is the recommended approach to measuring quality of the vapor leaving the evaporator. The fluid is sampled and throttled to a superheated state.

SENSOR	PARAMETER MEASURED	FURNISHED BY	QUANTITY
TEMPERATURE AND PRESSURE	WARM SEAWATER INLET	OTEC-1	1
	WARM SEAWATER OUTLET	OTEC-1	1
	COLD SEAWATER INLET	OTEC-1	1
	COLD SEAWATER OUTLET	OTEC-1	1
FLOW	WARM SEAWATER INLET	OTEC-1	1
	COLD SEAWATER INLET	OTEC-1	1
DIFFERENTIAL PRESSURE	ACROSS EVAPORATOR WATER HEADERS	TRW	1
	ACROSS CONDENSER WATER HEADERS	TRW	1
AMMONIA LEAK DETECTORS (MACRO, FOR SEAWATER)	WARM SEAWATER OUTLET	OTEC-1	1
	COLD SEAWATER OUTLET	OTEC-1	1
CHLORINE DETECTOR IN SEAWATER	WARM SEAWATER OUTLET	OTEC-1	1
	COLD SEAWATER OUTLET	OTEC-1	1
CORROSION METER (CORRATOR)	CONDENSER SEAWATER OUTLET	TRW	1
	EVAPORATOR SEAWATER OUTLET	TRW	1

Figure 3.3-28. 0.2 MWe Instrumentation, Seawater

The evaporator outlet quality can be determined by throttling if the quality is above about 95%, otherwise a superheated state cannot be reached unless the calorimeter is coupled to a vacuum pump. If the quality is less than 95% at the outlet of the evaporator, the quality can be determined by a mass and energy balance around the phase separator. A calorimeter would measure phase separator outlet quality and by measuring liquid flow returned, the inlet state can be determined.

If the quality of the vapor leaving the phase separator exceeds 99.1%, the throttling to condenser pressure will provide superheated vapor. In this case, at least in principle, no calorimeter is required. Qualities can be calculated by mass and energy balances. Error analyses are presently being conducted to assess practicality.

A number of different densitometers were investigated such as the gamma ray type, the beta ray type, laser type, and the vibrating reed type. The first three will work satisfactorily in a dense fluid but not in a gas or vapor. The vibrating reed type is unsatisfactory due to the fact that moisture will collect on the reed and give a false reading. The laser approach appears to be most promising but would require development work.

Sensor Input Power and Output Signal. The input power to the sensors is to be 24 VDC and the output signal from the transmitters is 4-20 ma.

3.4 BIOFOULING CONTROL

Biofouling and scaling affect the thermal efficiency of heat exchangers and hence the economic viability of OTEC power plants. Because of the low temperature differences experienced by OTEC heat exchangers, formation of organic or inorganic deposits on the seawater side of the heat exchanger walls can seriously affect the efficiency of heat transfer.

For successful plant operation, it is imperative to control biofouling. While ideally one would like to eliminate fouling completely, the costs in practice would be prohibitive. Thus biofouling control seeks to restrain biofouling to economically tolerable levels. The successful control of biofouling achieves the best balance of initial material and equipment costs, maintenance costs, operational requirements, system life and savings resulting from keeping the heat transfer surfaces clean.

To this end, TRW's design goal of an average 0.0003 fouling factor is moderate and achievable, and affords some design flexibility. An ambitious goal of 0.0001 would be difficult to achieve and maintain, while a goal of 0.0005 appears to be overly conservative.

TRW's basic approach to biofouling control is threefold: design, operation and maintenance. Major control is achieved by the operational measures, the primary method of which is the mechanical brush cleaning of tubes, with supplemental chlorination.

3.4.1 Requirements

The DOE fouling requirement is

- Fouling (biological and chemical) of heat exchangers must be controlled not to exceed a fouling factor of $0.0005 \text{ hr} \cdot \text{ft}^2 \cdot ^\circ\text{F}/\text{Btu}$.

3.4.2 Approach

Figure 3.4-1 summarizes TRW's multiple-step approach to achieving and maintaining an average fouling factor of $0.0003 \text{ hr} \cdot \text{ft}^2 \cdot ^\circ\text{F}/\text{Btu}$.

- For the heat exchangers, a six-step approach has been used:

	DESIGN		OPERATION		MAINTENANCE	
	HIGH SEAWATER VELOCITY	ANTIFOUL COATINGS	MECHANICAL TUBE CLEANER WITH BRUSHES	CHLORINATION CONTINUOUS LEVEL AND INT. SHOCK	HIGH PRESS. SEAWATER HOSE	MANUAL CLEANING (SCHEDULED PREVENTIVE MAINT.)
HEAT EXCHANGERS						
• TUBES	✓		✓	✓		✓
• INTERMODULE GAP		✓		✓	✓	✓
AUXILIARY EQUIPMENT AND OTHER SEAWATER EXPOSED SURFACES		✓		✓	✓	✓

Figure 3.4-1. Summary of Biofouling Control Approach

- Design

- 1) Moderately high water velocity (about 6 ft/sec) through the heat exchanger tubes
- 2) Antifouling coatings on the intermodule gap and for the non-heat transfer surfaces of the heat exchangers which are not usually cleaned mechanically

- Operation

- 3) Periodic mechanical cleaning of tubes with brushes (automatic or manual)
- 4) Continuous low level chlorination of 0.05 ppm with an intermittent high (shock) level of 1.0 ppm

- Maintenance

- 5) High velocity water - manual hose spraying into intermodule gap
- 6) Manual cleaning during preventive maintenance periods.

- For auxiliary equipment and other seawater exposed surfaces, a four-step approach is used:

- 1) Antifouling coatings on the intermodule gap and for the non-heat transfer surfaces of the heat exchangers which are not usually cleaned mechanically
- 2) Continuous low level chlorination of 0.05 ppm with an intermittent high (shock) level of 1.0 ppm
- 3) High velocity water - manual hose spraying into intermodule gap
- 4) Manual cleaning during preventive maintenance periods.

It is emphasized that the tube cleaner design with its operational cleaning frequency capability (up to two cleanings per week) by itself can maintain the fouling factor at or below the design goal of $0.0003 \text{ hr-ft}^2 - ^\circ\text{F/Btu}$. Since we are employing additional methods of biofouling control, we have great confidence of maintaining the heat exchanger fouling resistance at or below our design goal.

3.4.3 Fouling Processes and Data

There are two types of biofouling: micro and macro, both of which must be considered in design and control. The micro fouling is the slime film with organisms too small to be seen by the naked eye. Macro fouling consists of visible organisms such as barnacles, worms, mussels, oysters, etc.

Materials exposed to seawater become rapidly coated with organic films and various micro and macro organisms. When a solid substance is placed in seawater, a thin layer derived from dissolved organics is absorbed on the surface. This layer serves as a substrate to which bacteria are attracted by chemotaxis. Colonizing bacteria secrete a polysaccharide material that anchors them to the surface. This organic biological layer is called the primary film. Dissolved organics in seawater aggregate at the surface of the primary film and may serve as a substrate for other bacteria, micro-organisms, diatoms, protozoans and other materials that impede heat transfer. When seawater flow is stopped, there is a dramatic increase in the production of polysaccharide biopolymer. Bacteria, when put in an anaerobic environment (with no water flow, oxygen supplies cut off immediately begin to produce large amounts of polysaccharide. This slime layer acts as a binder for macrofouler larvae and inorganic matter. Bioadhesion of suspended material by the slime layer is a significant problem in coastal power plant condensers.

In addition to biofouling, waterside inorganic chemical fouling can occur due to low solubility corrosion products, supersaturation of minerals (e.g., calcium carbonate) or alkalinity increases in the seawater due to local ammonia leakage (e.g., magnesium hydroxide).

Extensive microbiofouling data have been accumulated from government and private investigations. Figure 3.4-2 qualitatively depicts the typical fouling rate curve. Induction periods are short after repeated cleanings

Figure 3.4-2. Fouling Resistance Versus Time

since normal operational cleanings do not completely remove the microslime layer. The microfouling rates in seawater summarized in Figure 3.4-3 show that rates of fouling for warm coastal waters are several times higher than in warm ocean water. Figure 3.4-4 shows examples of the actual fouling factor buildup with time, while Figure 3.4-5 illustrates the same at velocities of 3 and 6 ft/sec before and after mechanical tube cleaning with brushes.

3.4.4 Biofouling Effects

Biofouling affects two major classifications of equipment:

- Heat exchangers
- Auxiliary equipment.

3.4.4.1 Heat Exchangers

The presence of even a thin film on the heat exchanger surfaces will seriously degrade heat exchanger performance. Figure 3.4-6 shows how the thickness of fouling deposit affects thermal resistance. From the figure, it is noted that a biofouling layer thickness of only 0.001 inch causes a fouling resistance of about $0.0002 \text{ hr-ft}^2 - ^\circ\text{F/Btu}$. Since our design goal is $R_f < 0.0003 \text{ hr-ft}^2 - ^\circ\text{F/Btu}$, the heat exchanger biofouling layer thickness must be less than 0.0015 inch.

SITE	WATER SOURCE	RATE OF FOULING RESISTANCE INCREASE (HR · °F · FT²/BTU) × 10⁴ PER WEEK	AVERAGE SEAWATER TEMPERATURE °F	FLUID VELOCITY FT/SEC	HEAT TRANSFER MODE/FLOW MODE	HEAT TRANSFER SURFACE
PANAMA CITY, FLORIDA	COASTAL SEAWATER	33	86	6	ELECTRIC HEATERS/TUBULAR	TI AND AL 5052 & 6061
P.S.E. & G. BERGEN STATION	ESTUARY	33	86-95	7	STEAM CONDENSER/TUBULAR	304 S.S.
L.A.P. & W. HAYNES STEAM	COASTAL SEAWATER	18.5 6.5	81 (SURFACE TEMPERATURE)	6 8	ELECTRIC HEATERS/ANNULAR	TI TI
KEAHOLE PT. HAWAII & ST. CROIX	OPEN OCEAN	6.4	77-86	3, 6 & 7	ELECTRIC HEATERS/TUBULAR	TI AL 6061

Figure 3.4-3. Microfouling Rates in Seawater

The OTEC evaporators use warm, oxygen-rich and biologically active surface waters, while the condensers use cold, oxygen-poor, biologically less active waters from a depth of about 3000 feet. It has been assumed, though not demonstrated, that biofouling of the condensers will cause less of a problem than biofouling of the evaporators. Biofouling control for each system has taken these different environments into account.

Figure 3.4-4. Fouling Factor (R_f) Versus Time for St. Croix Experiments

Figure 3.4-5. Fouling Factor (R_f) vs. Time for Buoy Series I Experiments at Keahole Point

Figure 3.4-6. Estimated Relationship Between Thickness of Fouling Deposit ΔX and the Fouling Factor, R_f

3.4.4.2 Auxiliary Equipment

The biofouling of auxiliary equipment — pumps, piping, valves, screens, etc. — affects the operation of an OTEC plant less than biofouling of the heat exchangers, but it must be considered to obtain efficient long term operation and to determine maintenance procedures. Macrofouling can cause restrictions of fluid flow, turbulence and other problems in piping systems and it can cause restriction, clogging, or jamming of valves, screens, and

pumps, particularly when they are operated intermittently. The mass of macrofouling accumulations can even lead to problems in rotating machinery due to an increase in rotating mass or an imbalance condition.

3.4.5 Design Factors Influencing Biofouling Control

Proper design and fouling control can keep the accumulation and effects of fouling organisms within reasonable limits at minimum cost. The numerous factors that must be considered to obtain optimum (lowest cost for design fouling factor) fouling control are discussed below.

3.4.5.1 Mechanical Design Factors

Mechanical design factors that influence the attachment and growth of fouling organisms include geometry, seawater velocity, orientation, layout, surface finishes, cathodic protection, antifouling coatings and cleaning systems.

- Cleaning System

Fouling can be removed from any surface by mechanical cleaning. Simply wiping or mild brushing will remove initial proteinaceous and bacterial films whereas hard-shelled organisms require vigorous brushing to dislodge them from many surfaces. The primary device for biofouling control in the evaporator and condenser is the mechanical tube cleaner. The tube cleaner is automatic and can perform up to two complete tube cleanings per week. Preliminary data (see Figure 3.4-5) indicate that a tube cleaning frequency of once per week is more than adequate to maintain the average fouling resistance below $0.0003 \text{ hr-ft}^2 \text{ -}^\circ\text{F/Btu}$ in conjunction with continuous low-level chlorination. However, since the biofouling resistance buildup is site dependent, the exact cleaning frequency will be determined during operation.

- Velocity

The movement of seawater over a surface can inhibit or prevent attachment of fouling organisms. The velocity of this flow is a major anti-fouling factor that can be directly controlled by system design. The use of velocity to control fouling depends on continuous flow. While the velocity required to inhibit or prevent fouling has not been well defined, it probably lies in the 2-4 ft/sec range (Reference 3-9). Since the seawater flow velocity through the heat exchangers is about 6 ft/sec, it will act to inhibit growth of marine organisms.

- Antifouling Coatings

Antifouling coatings containing copper are lethal to marine organisms. However, copper and its alloys are not suitable for use with the ammonia working fluid nor can they be used on the seawater side as even small concentrations of copper (0.02 ppm) can accelerate corrosion and pitting of aluminum.

However, paints containing organotins are at least as effective as copper in most uses. An antifouling rubber sheeting, such as B. F. Goodrich Company's "NO FOUL" sheet formula 1020, is available for long lasting protection of seawater exposed surfaces.

- Warm Water System

Organolin antifouling paint or rubber sheeting will be used on all seawater surfaces of the warm water system, except for the seawater surfaces of the evaporator.

- Cold Water System

Because of the low temperature and depth of the cold water, the fouling characteristics of the cold water system will be weak and the constant darkness of the cold water pipe will further inhibit marine growth. Therefore, it is expected that cold water sections of the system will not need antifouling coatings.

3.4.5.2 Environmental Design Factors

By properly controlling or modifying the chemical or physical characteristics of seawater, the ability of fouling organisms to live and grow can be limited or totally inhibited.

Introduction of toxic materials into the environment can kill marine organisms. Chlorine is the most widely used chemical agent. Onsite sodium hypochlorite generation is the selected method of chlorine production for PSD-II, as it is safe, convenient and requires no storage of hazardous chlorine gas. Fava and Thomas concluded in their report (Reference 3-10) that on-site sodium hypochlorite generation was the preferred method based on availability, operating costs, transportation, storage, and safety.

3.4.6 10 MWe Heat Exchanger Tube Cleaner

The tube cleaner is the most important element of our overall approach to biofouling control of the evaporator and condenser. Its design and expected performance are such that we anticipate that it alone is capable

of maintaining the fouling factors (R_f) of the heat exchangers at or below the design goal. The biofouling test data shown in Figure 3.4-5 indicate that tube cleaning as infrequently as once every four weeks could maintain $R_f < 0.0003$. Our tube cleaner has a capability of two complete tube cleanings per week.

3.4.6.1 Background and Scope

The fouling problem has been overcome in conventional power plant heat exchangers by cleaning the tubes periodically with the heat exchanger drained and out of service. The tube cleaning devices usually employ rotating brushes which are passed back and forth through the tubes until the proper degree of cleanliness is attained. OTEC power plants, however, impose constraints which negate this approach:

- 1) Frequent shutdowns of heat exchangers will not occur. Tube cleaning operations must then be performed with the heat exchangers operating
- 2) Tube cleaners must operate submerged, possibly in a closed water box, be powered and be capable of remote control
- 3) Access may be limited to the inlet water box only.

Considering these constraints, TRW has proposed using a push-pull, brush-type tube cleaner.

3.4.6.2 Objectives and Requirements

Our goal is that a fouling factor of $0.0003 \text{ hr-Ft}^2\text{-}^\circ\text{F/Btu}$ used to size the heat exchangers be the average fouling factor attained in service. This is a reasonable expectation because of the design and the cleaning steps we are proposing.

Other requirements for the tube cleaner include the provisions that the method selected for cleaning be proven and effective, that the cleaning stroke be easily repeated, that the tube cleaner have an easily maintained indexing and positioning system, that a minimum amount of ancillary or support equipment be required, that the tube cleaner not damage the heat exchanger in any way, and that the tube cleaner be stable under the static and dynamic conditions of the APL plant ship operating in sea state conditions.

3.4.6.3 Technical Approach

To assure that the seawater tube surfaces of the heat exchangers are clean, brushes driven mechanically through the length of the tubes are used. The degree of cleanliness this attains will be assessed in the Tube Cleaner Evaluation Test Program in Phase II proposed by TRW (see Appendix II, Section 7). It is expected that the brushing cycle will be performed once every week. One of the results of this brush test program is to determine the tube cleaning duty cycle more precisely, although the final cleaning cycle must be determined at the plant site since fouling rate is very site dependent.

A tube cleaner using 120 brushes was chosen to perform the tube cleaning function. This number of brushes was selected for simplicity of design, ease of maintainance, time needed to complete a cleaning cycle, and cost.

The brush/bristle characteristics will be determined in the tube cleaner brush test program. A brush that is too stiff or has too great an interference with the tube may, in addition to removing biofouling material, also remove part of the tube base metal or cladding by erosion.

The exchanger will be made of either Allegheny 6X super stainless material or aluminum 3004 alclad material. It is expected that Allegheny 6X material will not be affected by erosion/corrosion because of brush cleaning, water velocity, and the recommended low level chlorination or shock chlorination. Data is lacking on the effect of brushing a 3004 Alclad aluminum tube. Brushing may prevent cells from forming and thus reduce pitting. It may also have the effect of increasing the rate of metal erosion on the tube. TRW is now performing erosion/corrosion tests, but they are of qualitative nature. The proposed brush tests are expected to establish the effect of brushing on the 3004 Alclad aluminum.

3.4.6.4 Interfaces

Interfaces exist between the tube cleaning machine and water box, water box to ship, water box to heat exchanger, cleaning head to heat exchanger, and controls to heat exchanger. These are shown in Figure 3.4-7.

3.4.6.5 Design and Operation

The tube cleaner, shown in Figure 3.4-7, is an automatically operated machine located submerged in seawater at the accessible upstream end of the heat exchanger. A multiple head unit drives 120 brushes simultaneously through 120 heat exchanger tubes and then retracts the brushes after the full length of the heat exchanger tubes is cleaned. The multiple brush driving head unit then repositions on the next array of 120 tubes where the cleaning operation is repeated.

Cleaning of the tubes takes place during normal heat exchanger operations. There is only a momentary interruption of seawater flow through those tubes that are being cleaned.

Figure 3.4-7 shows the overall layout of the tube cleaner and its proximity to the heat exchangers. Figure 3.4-8 illustrates the tube cleaning head.

The tube cleaner subsystem comprises components which support and position the brushes that stroke clean the heat exchanger tubes. The subsystem consists of a cleaning head with cleaning brushes, a positioner to place the cleaning head in preselected positions for executing the tube cleaning function and an automatic control and recorder to command the head and positioner. The tube cleaner also includes the support frame, X and Y drives, cleaning head carriage, machined guide rails, and sensors/controls necessary to perform and monitor the cleaning function. The tube cleaner design is the same for the evaporator and for the condenser. Figure 3.4-9 gives the tube cleaner functional flow diagram.

The tube cleaners will operate submerged with the brushes driven horizontally through the heat exchanger water passages. Power for the tube cleaner will be provided from the plant in the form of 110/220 volt single

phase, 60 cycle AC current to operate the positioner, and dry plant compressed air at a pressure (about 90 psig) sufficient to drive the brushes through the tubes. The positioner will be automatically controlled to progressively place the cleaning head in a predetermined pattern and permit coverage of the entire tube field. Figure 3.4-10 shows the tube cleaner schematic and Figure 3.4-11 the cleaning head control diagram.

A positioner is located on a square bed called the X-Y positioner frame. This frame rests on top of the heat exchanger water box/tube cleaner support structure. The positioner moves the cleaning head in the X, Y, and Z directions by means of air motors through a rack and pinion drive.

The tube cleaner head is a 32-foot long cylinder. The entire head moves horizontally (Z-direction) with a 16-foot stroke. The vertical drive consists of two racks mounted longitudinally on the head with the pinion driven by the Y-drive fluid motor.

The tube cleaner will clean 120 tubes during each stroke, which will take approximately 80 seconds. The cleaning cycle times are given below:

- Startup operations (manual control) — 3 minutes
 1. Release from stowed position
 2. Position to start point (fast, medium and slow traverse speeds)
- Alignment sequence (automatic) — 20 seconds
 1. Brake/lock positioner
 2. Lower cleaning head
 3. Engage guide pin
 4. Sense guide pin engagement
- Forward stroke cleaning sequence (automatic) — 20 seconds
 1. Initiate brush-forward cycle timer, T_1
 2. Sense first brush forward completion
 3. Initiate timer, T_2 (3 second delay to allow completion of all cleaning strokes)

Figure 3.4-7. 10 MWe Power Module Heat Exchanger Tube Cleaner

1 0 1 2 3 4
SCALE INCHES

RELEASED BY *PT*

DESIGNED <i>R. WILDER</i>	OTEC POWER SYSTEM DEVELOPMENT - II	LTR	DATE	REVISION	BY	APP
DRAWN <i>R. WILDER</i>	10 MWe & 0.2 MWe TEST ARTICLE	TRW				
CHECKED <i>W. B. ...</i>	TUBE CLEANER HEAD	DRAWING NUMBER				
APPROVAL <i>M. Khandekar</i>	OPEN OR CLOSED WATER BOX DESIGN	6850.94-70				
DATE OFFER <i>5-10-79</i>		FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY				
		ISSUE DATE 5-10-79				

Figure 3.4-8. 10 MWe & 0.2 MWe Test Article Tube Cleaner Head Open or Closed Water Box Design

Figure 3.4-9. 10 MWe Tube Cleaner Functional Flow Diagram

Figure 3.4-10. Tube Cleaner Schematic

Figure 3.4-11. Cleaning Head Control Block Diagram

4. Scan all forward stroke sensors
 5. Record any incomplete forward cycles.
- Return stroke cleaning sequence (automatic)
1. Initiate brush-return cycle
 2. Sense first brush-return cycle
 3. Initiate timer, T_3 (3 second delay to allow completion of return stroke)
 4. Scan all return stroke sensors
 5. Disengage guide pin (retrace socket cyl.)
 6. Sense guide pin disengagement

- Repositioning sequence
 1. Unlock positioner
 2. Move to next cleaning location
- Repeat sequence - B through E

Total time - 5 minutes, 40 seconds.

The brush rods are coated with nylon or teflon to prevent damage by rubbing on the tube walls and a fail-safe device with collapsible springs will prevent damaging tubes by excessive force.

The tube brushes will be designed with a combination of both hard and soft bristles to remove the biofouling from the tubes without causing damage or erosion to the heat exchanger tubes. The results from the test on brushes in Phase II will be used to design the 10 MW brushes.

3.4.6.6 Special Features

The heat exchanger tube cleaner (HE/TC) has been designed using parts and components that are commercially available. The actuator drive provides ample reserve force with the stroke continuous and controllable. The force may be varied simply by changing air pressure. The HE/TC is designed in a compact package minimizing the obstruction to water flowing to the operating heat exchangers. It provides quick and accurate cleaning head positioning. The total power required to operate the compressor, electric motors, instruments and controls will be less than 25 kW.

Once aboard ship and installed, the HE/TC is maintained permanently in a fixed position relative to the heat exchanger and water box. It must be shimmed or adjusted in position by other means to assure alignment with the heat exchanger. When not in service, the cleaning head is parked in an out of the way parking position relative to the tubes.

3.4.6.7 Brush Test Program

An uncertainty in the design of a push-pull tube cleaner involves the type of brush used. Very little information is available in the process industry or tube cleaning industry on push-pull tube cleaners and brushes. Prior to the detailed design phase of the tube cleaner the following brush parameters must be identified:

- Bristle size and material
- Nominal interference between brush and tube, and physical length of brush required for effective tube cleaning and optimum brush life.
- Configuration, or arrangement, of bristles in central shaft of brush.
- Actuating force required to push a brush through a tube and retract it
- Number of strokes (extend and retract) required to effectively clean a tube by a particular brush
- Abrasive effect (erosion), if any, of prolonged brushing operations by a particular brush on tube surfaces.

TRW has proposed a six month test program in Phase II by which reasonable values of these parameters may be determined. The functional flow diagram for this program is shown in Figure 3.4-12 and is discussed in more detail in Appendix II, Section 7. The proposed brush test program consists of three separate investigations:

- 1) Simulated biofouling tests
- 2) Brush screening tests
- 3) Long term brush service tests.

3.4.7 Chlorination Subsystem

The purpose of the chlorine is to supplement the biofouling control function of the mechanical tube cleaner by deterring micro-organisms from heat exchanger surfaces and inhibiting the growth of micro-organisms.

The chlorine dose required will vary considerably with local conditions. The actual amount and optimum addition of chlorine for inhibiting fouling in the various portions of an OTEC system is expected to be different from the dosages normally used in coastal plants.

Figure 3.4-13 shows the chlorine dose and its effects as reported by a number of investigators.

Due to the expected high level of cleaning from the mechanical tube cleaner, chlorination of seawater will be used only as a supplementary method of biofouling control for the heat exchangers. For this reason, a

Figure 3.4-12. PSD II Tube Cleaner Brush Evaluation Test Program Functional Flow Diagram

- SOFT SHELLLED FORMS CONTROLLED BY INTERMITTENT CHLORINATION (1.0 PPM FREE RESIDUAL CHLORINE) FOR ONE HOUR EVERY EIGHT HOURS
- HARD SHELLLED ORGANISMS CONTROLLED MORE EFFECTIVELY BY CONTINUOUS LOW LEVEL CHLORINATION 0.25 TO 0.50 PPM FREE RESIDUAL CHLORINE AT CONDENSER DISCHARGE
- > 0.25 PPM CONTROLLED ATTACHMENT OF HARD SHELLLED ORGANISMS
- 0.5 PPM CHLORINE RESIDUAL KILLED MICROORGANISMS
- LOW LEVEL CONTINUOUS CHLORINATION IN COOLING WATER SYSTEMS IN GREAT BRITAIN 0.5 PPM REDUCED MUSSEL FOULING
- CARMOROTHER BAY POWER STATION IN GREAT BRITAIN. CHLORINE INJECTED TO GIVE RESIDUAL 0.02 TO 0.50 PPM AT CONDENSER ENTRANCE
- 0.5 TO 1.0 PPM TOTAL CHLORINE, CONTINUOUS OR INTERMITTENT UP TO FOUR HOURS PER DAY
- 0.25 TO 0.50 PPM FREE CHLORINE IN CONDENSER DISCHARGE PREVENTED FOULING
- VELOCITY 3 TO 6 FEET PER SECOND (FPS) MAY PREVENT FOULING
- 4 FPS ENHANCED EFFECT OF CHLORINE (0.5 TO 3.0 PPM) OVER LOWER VELOCITIES

Figure 3.4-13. Summary of Biofouling Survey - Chlorination Dosages

low chlorine doses of 0.05 ppm has been selected in the seawater on a continuous basis. Intermittent shock chlorination (about 1.0 ppm) will be used as required on other seawater exposed surfaces that are not cleaned periodically.

3.4.7.1 Chlorine Generator

The chlorinator will be a standard commercial generator consisting of two separate units, a power supply and a chlorine generator. The power supply takes 480 VAC, 3 phase 60 Hz power and converts it to DC power as required by the chlorine generator.

The chlorine generator electrolyzes a seawater stream producing sodium hypochlorite (NaOCl) which remains in solution. The chlorine generator unit housing contains a seawater pump, electrolytic cells, a chlorine concentration sensor which regulates the power input, a means of disposing safely of the hydrogen generated in the electrolytic process, and the required piping and valves.

A total injected chlorine dose of 0.05 mg/l (equivalent to 0.05 ppm) has been selected for both the warm and the cold water stream. The seawater flow rates are:

369,000,000 lb/hr to the evaporator

349,000,000 lb/hr to the condenser

718,000,000 lb/hr total seawater flow

At 0.05 ppm, 35.9 lb/hr of chlorine must be generated.

A commercially available chlorinator capable of supply 40 lb/hr equivalent chlorine has been selected. For its operation, a unit of this size requires from 40 to 120 gpm of seawater. If this water is at about 80 degrees Fahrenheit, the power consumed in generating chlorine ranges up to 2.5 kW hr/lb of chlorine. Figure 3.4-14 is a block diagram showing the main elements of the chlorinator assembly.

Figure 3.4-14. Chlorinator Block Diagram

Figure 3.4-15 shows the operating cost of continuous chlorination for various chlorine doses and power costs.

Figure 3.4-15. Annualized Operating Cost of Continuous Chlorination with Chlorapac

3.4.7.2 Supplemental and Shock Chlorination

Concern with biofouling and its control has focused on the heat exchanger water side heat transfer surfaces. Biofouling and its control is also of concern in the heat exchanger intermodule gap and also on other surfaces exposed to warm seawater such as in the seawater pumps and heat exchanger inlet and exit water boxes.

These surfaces will be protected with an appropriate anti-fouling paint. Additionally, biofouling will be deterred by periodic additions of high dosages of chlorine (about 1.0 ppm) into the heat exchanger intermodule gap and also at other places in the warm seawater circuit upstream of the evaporator.

3.4.8 Heat Exchanger Intermodule Fouling Control

Intermodule fouling will be controlled passively and actively.

Passively:

- Seawater velocity 3-4 ft/sec between modules
- Receives no sunlight
- Panel surfaces not accessible to brushes will have protective coatings.

Actively:

- Periodic high level doses of chlorine (about 1.0 ppm)
- Intermodule seal will be opened to brush clean or use high pressure hose cleaning as necessary
- Inspection will be made to determine fouling buildup rates.

3.4.9 0.2 MWe Test Articles Tube Cleaner

The tube cleaner design for 0.2 MWe test articles is similar to the one for 10 MWe heat exchangers except that the former has manual controls, a smaller cleaning head (only 24 brushes instead of 120) and utilizes a closed water box design. Appendix 11, Section 7 describes the design of the tube cleaner for the test article heat exchangers.

The 0.2 MWe tube cleaner (see Figure 3.4-16) is a manually operated machine submerged in seawater at the accessible, upstream end of the heat exchanger. One machine is required for each exchanger. It is located upon fixed base and may be moved — by means of independent single axis motors connected to drive screws and alignment rails — up and down or back and forth across the tube bundle face. A compressed air piston drives the non-rotating brushes in and out of the tubes. The cleaning takes place with the exchanger in operation.

A remote operator accomplishes positioning and alignment manually by means of a lighted television camera mounted to survey the tube bundle. The accounting of which tubes have been cleaned will be the responsibility of the operators, who will work from a check-off matrix. It is estimated that the 5600 tube exchanger will be cleaned in about 20 hours. Each brush will be equipped with a plastic lead-in bushing to alleviate the need for precise

alignment and eliminate the possibility of damaging the tubes. Reaction to the forces of moving, cleaning and ship's motions will be accommodated by locking drive screws and rollers retained within closed rails.

Figure 3.4-17 shows the tube cleaner head while tube pattern and cleaning sequence are shown on Figure 3.4-18.

Figure 3.4-19 is a functional flow diagram depicting the sequence of events during operation of the tube cleaner.

Figure 3.4-20 lists the steps in the tube cleaner sequence including the time required for each step.

3.4.10 Phase II Testing

Test operation of the 0.2 MWe test article heat exchangers is expected to provide much useful information on biofouling and control in the following areas:

- Biofouling growth rate for heat exchangers and other surfaces
- Effect of biofouling on heat exchanger performance
- Tube cleaner mechanical operation
- Brush cleaning performance
- Brush cleaning frequency of operations vs fouling factor
- Brush fouling and brush cleaning requirements
- Anti-fouling paint performance
- Effect of seawater velocity on biofouling buildup
- Effect of continuous and intermittent chlorination dose on biofouling growth.

Accumulation of this test data will provide information which will be used to refine the design of the tube cleaner, to determine the frequency requirement of mechanical cleaning, and the dosage and continuity of chlorination required for adequate biofouling control consistent with environmental and economic considerations.

NOT TO SCALE

LTR		DATE	REVISION		BY	APPRO
DESIGNED R. WELTHER			OTEC POWER SYSTEM DEVELOPMENT - II			
DRAWN R. WELTHER			0.2 MWe TEST ARTICLE			
CHECKED W. B. Gault			TUBE CLEANER HEAD			
APPROVALS			CLOSED WATER BOX			
RELEASED BY J. E. V. [Signature]			MANUAL OPERATION			
PROD OFFICE P. T. [Signature]			FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY			
			DRAWING NUMBER			
			6850.94-57			
			ISSUE DATE			
			5-10-79			
			CONS LTR			

Figure 3.4-17. 0.2 MWe Test Article Tube Cleaner Head Closed Water Box Manual Operation

TUBE PATTERN

DETAIL (1/51)
SCALE: HALF SIZE

TUBE CLEANING SEQUENCE

ELEVATION (C/51) REF 53
NTS

1 0 1 2 3 4 5
SCALE INCHES

DESIGNED HUNTINGTON	OTEC POWER SYSTEM DEVELOPMENT - II	TRM	
DRAWN SAKAMOTO	0.2 MWe TEST ARTICLE	DRAWING NUMBER	
CHECKED H. J. Sample	HEAT EXCHANGER	6050.94-51	
APPROVALS	TUBE PATTERN & CLEANING SEQUENCE	FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY	
RELEASED BY: H. J. Sample	PROG OFFICE: J. J. Sample	ISSUE DATE	CHG LTR
		5-10-79	

Figure 3.4-18. 0.2 MWe Test Article Heat Exchanger Tube Pattern & Cleaning Sequence

Figure 3.4-19. 0.2 MWe Tube Cleaner Functional Flow

APPROX 5 MIN	A – STARTUP OPERATIONS 1 – RELEASE POSITIONER FROM STOWED POSITION 2 – POSITION TO START POINT (VARIABLE TRAVERSE SPEEDS)
APPROX 60 SEC	B – ALIGNMENT SEQUENCE 1 – TRAVERSE CLEANING HEAD TO FIRST CLEANING POSITION (VARIABLE TRAVERSE SPEED) 2 – VISUAL ALIGN USING TV MONITOR (BOTH X AND Y AXIS)
APPROX 90 SEC	C – FORWARD STROKE CLEANING SEQUENCE 1 – INITIATE BRUSH-FORWARD CYCLE 2 – SENSE FIRST BRUSH FORWARD COMPLETION (STATUS PANEL) 3 – SCAN ALL FORWARD STROKE SENSORS (STATUS PANEL) 4 – RECORD ANY INCOMPLETE FORWARD CYCLES (LOG BOOK)
APPROX 90 SEC	D – RETURN STROKE CLEANING SEQUENCE 1 – INITIATE BRUSH-RETURN CYCLE 2 – SENSE FIRST BRUSH-RETURN COMPLETION (STATUS PANEL) 3 – SCAN ALL RETURN STROKE SENSORS (STATUS PANEL)
APPROX 60 SEC	E – REPOSITIONING SEQUENCE 1 – UNLOCK CLEANING HEAD AND POSITIONER 2 – MOVE TO NEXT CLEANING LOCATION
APPROX 5 MIN	F – REPEAT SEQUENCE – B THRU E

Figure 3.4-20. HX/TC Sequence of Events (All Manual Control)

3.5 MATERIALS SELECTION

The selection of materials for PSD-II is based on the following requirements:

- Materials compatibility among anhydrous ammonia, seawater, and the various materials used in the heat exchanger. Materials compatibility includes corrosion, which has an extremely important effect on the life of the heat exchanger
- Fabricability, especially in its effect on cost and the ability to obtain leak-free heat exchanger construction
- Cost.

3.5.1 Approach

Prior to the start of the present study, several candidate materials were considered for the heat exchangers: aluminum, titanium, and stainless steel. The baseline approach has been to use aluminum, and the majority of the effort expended during the study was on aluminum alloy construction. As discussed in Section 7, subsequent events have led to the recommendation of Allegheny 6X super stainless steel or equivalent for the 10 MWe heat exchangers, a conceptual design for which is presented in Section 7.1.

The original choice of aluminum was based on its compatibility with ammonia, low cost, ready availability and ease of fabrication. The disadvantage aluminum presents is its corrosion in seawater, which limits the life of the heat exchanger.

3.5.2 Corrosion

The baseline design uses 3004-O clad with 7072 for the heat exchanger panels. The base material carries the pressure load while the cladding is sacrificial to the corrosive effects of seawater. (Alloy 5052 clad with 7072 might have been a superior choice, but it is not an available alloy.)

A comprehensive discussion of the corrosion of the heat exchanger panels, including available test data, is in Appendix II, Section 14. A projection of data shown on Figure 3.5-1 is the basis for an assumed life of the aluminum alloy panels of 15 years.

Crevice corrosion on the seawater side is prevented by bonding the contact areas between panels. The bond will carry no tensile loading. To prevent galvanic corrosion and simultaneously provide a durable,

leak-free heat exchanger, aluminum alloy 5083 is used for the structural components of the heat exchanger. It has excellent strength and is readily weldable.

The welds between panels and structural components will be made with 5183 filler rod which exhibits excellent corrosion resistance in seawater.

Figure 3.5-1. Alcoa Clipper Cladding Performance Life Estimate

Stress calculations performed are shown in Figure 3.5-2; they were prepared for a number of potential aluminum alloys and tempers. Formability tests were also performed. Results were weighed against the environmental information. Alclad 3004-0 was selected for the core material and it is seen that the minimum core thickness required is 32 mils. The formability tests conducted on aluminum sheet stock suggested that an 8 mil allowance for forming was required. Thus, for 3004-0, a minimum substrate thickness of about 40 mils is required. As a consequence, the final requirement is 3004-0 with a 40 mil thick core and clad on one side with 10 mils of cladding optimized for deepwater or surface water for a total thickness of 50 mils.

CORE ALLOY	TEMPER	ALLOWABLE STRESS	CORE THICKNESS W/O CLAD	CALCULATED CORE STRESS
3004	H-32	6,300	0.025	5,300
3004*	0	4,900	0.032	4,800
3003	H-14	4,500	0.036	4,500
5052	H-32	7,700	0.025	5,300
5052	0	6,200	0.025	5,300
5086	H-32	10,000	0.025	5,300
5086	0	8,700	0.025	5,300

*PROPOSED DESIGN

Figure 3.5-2. Minimum Core Thickness (Structural)

3.5.3 Other Considerations

Biofouling, in addition to creating a resistance to heat flow, can also promote corrosive attack by means of crevice or erosion-corrosion mechanisms. Biofouling control is discussed in Section 3.4.

Recent tests conducted by Dow Chemical (Reference 3-11) have shown that localized contamination of seawater by ammonia can result in sudden precipitation of a scale with detrimental effects on heat exchanger performance. This contamination could be caused by a leak in a heat exchanger panel. Economic considerations dictate tube plugging (see Section 5.5), but tube plugging is also necessary to prevent scaling in downstream modules due to leaks.

3.5.4 Sealants and Adhesives

The use of sealants is important to the PSD-II design, since they are used to bond panels together to form the circular seawater passages (it must be noted that the sealant is not required structurally). The early designs exposed the joint area to ammonia; however, as the design has matured, sealant areas which would have been exposed to ammonia have been eliminated. Hence seawater and substrate compatibility are now the major concern. We have performed an extensive review of sealant technology available in the literature and from private and industry sources, and selected epoxy-polyamides as a family with excellent compatibility with seawater and above average compatibility with ammonia in the event of accidental contact.

UCC has previously used sealants as an adhesive joint in the UCAR radiator. Numerous adhesives were evaluated in the test program which involved exposure to harsh automotive environments. The test program demonstrated the importance of surface preparation.

Where adhesives have been utilized, it has been demonstrated that freeze-dry thaw cycles are the worst conditions. Continuous immersion is a much milder condition, even if it involves seawater. Nevertheless, bond line attack is a mechanism of concern.

The choice of sealants will be based on analysis of potential wear due to the biofouling control system and operational life requirements. Current technology allows for a filled joint which will result in a circular passage and minimize potential of crevice problems. Surface treatment techniques developed on the aluminum radiator program will maximize surface adhesion. The Alclad material will provide additional protection for potential crevices and minimize bond line attack by nature of its excellent throwing power.

Four adhesive candidates exhibiting superior characteristics for the application are the following:

- 1) HYSOL, EA 9414.1 - Modified epoxy-nitril family. This adhesive was used extensively on the UCAR Radiator Program. Hence, its behavior is well understood
- 2) B.F. Goodrich, A-1236-B - an epoxy-polyamide exhibiting superior resistance to salt solutions
- 3) Lord Hughson, Chemlok 309 - an epoxy-polyamide
- 4) Tra-Con, Tra Bond 2147 - an epoxy-polyamide.

One or more of these materials will be used as sealants. Inlet erosion will be dealt with by use of epoxy at tube inlets. As a result of potential pitting corrosion acceleration by metal species such as copper and tin, exterior antifouling coatings will not be applied. Where necessary, one of the preceding epoxies will be used.

3.5.5 Alternate Materials

As previously mentioned, the limited life of aluminum means that its application for the 10 MWe module heat exchangers involves a risk. Alternative materials--titanium and stainless steel--have therefore been evaluated.

Although titanium is extremely corrosion resistant, it has been rejected because of its high cost and relatively poor fabricability.

AISI type 300, 400, and particularly 600 series stainless steels are subject to pitting and crevice-corrosion in seawater. However, the addition of molybdenum and chromium improves performance, and Allegheny 6X or equivalent (Fe-20Ni-24Cr-6Mo) is the alloy recommended for the 10 MWe heat exchangers.

Figure 3.5-3 compares Titanium, Allegheny 6X, and Alclad 3004-H34 qualitatively for corrosion and fabricability.

	ALCLAD 3004-H34	TITANIUM GRADE 1	TITANIUM GRADE 2	TITANIUM CODE 12	S. STEEL ALLEGHENY 6X
AVAILABILITY	GOOD	FAIR	GOOD	GOOD	GOOD
WELDABILITY	GOOD	GOOD	GOOD	GOOD	GOOD
FORMABILITY	GOOD	FAIR	FAIR	FAIR	GOOD
BONDABILITY	GOOD	FAIR	FAIR	FAIR	FAIR
GENERAL CORROSION RATE, MILS/YR	0.5	NIL	NIL	NIL	NIL
PITTING CORROSION	YES	NO	NO	NO	NO*
CREVICE CORROSION	YES	NO	NO	NO	NO*
EROSION	YES	NO	NO	NO	NO**
CORROSION FATIGUE	YES	NO	NO	NO	—

*ANNEALED CONDITION

**LIMITED DATA

Figure 3.5-3. Qualitative Fabricability and Performance of Candidate Materials

Figure 3.5-4 is a modified plot by Bond upon which a number of commercial alloys have been superimposed. It is clear that the proper amounts of chromium and molybdenum are required for seawater crevice corrosion resistance and that a number of austenitic and ferritic compositions with the requisite chromium and molybdenum content are available. From the standpoint of formability, welding, and actual application data, the austenitic grades have the edge. A comparison of the alloy content of the austenitic grades which have potential for seawater indicates that a suitable composition for OTEC service would be as follows:

<u>%Cr</u>	<u>%Ni</u>	<u>%Mo</u>	<u>%Fe</u>	<u>Mn, Si, Cu, P, S, C, Carbon Stabilizers</u>
20-23	23-28	4-7	bal.	Minor controlled amounts

Alloys with commercial designations such as AL-6X, JS-777, JS-700, AL-4X, 904L, SANDVIK 2RK65 and Alloy 20 Mod. all fall into this range. There may be a number of other designations. For the 10 MWe stainless steel concept, all compositions falling within this range and which have ASME Code approval, are available in suitable mill forms, and have acceptable seawater performance, have been considered as candidate material options. On the basis of seawater experience and the acceptance of DOE materials consultants, AL-6X at first glance might have an edge with 2RK65 being a strong second because of its seawater experience.

Figure 3.5-4. Commercial Alloy Compositions

AL-6X and 2RK65 have extremely extensive seawater experience favorable to OTEC, although ASME Code approval has not yet been obtained. Furthermore, AL-6X, which is probably the more desirable of the two because of DOE endorsements, cannot currently be supplied by Allegheny Ludlum in widths greater

than the 24". UCC requires a minimum 48" width. Allegheny Ludlum is currently looking into the possibility of outside conversion to obtain wider widths.

Until the issues of ASME Code Approval and mill form availability are settled, other alternatives must be used to obtain an austenitic stainless steel containing 20-23Cr, 23-28Ni and 4-7 Mo. There is a recommended alternative involving the use of ASME Code Case 1668. This is the Code Case for Alloy 20 Mod, an alloy produced by Cabot-Stellite Division. In addition to this Code Case, Alloy 20 Mod. is covered by generic ASTM specifications such as B-619, B-620, B-621, B-622 and B-626.

A perusal of the Cabot-Stellite Division capability has shown that it has the production capacity and a mill form capable of producing wide sheets of Alloy 20 Mod. in the thickness desired. The current width requirement is 48" with a thickness of 20 mils. Only 18 mils are required structurally. Forming and a very slight corrosion allowance makes up the balance. The Cabot-Stellite Division currently has about 10,000 pounds of the alloy on hand. Any quantity greater than this would have an estimated delivery time of 8 months. At the present time, this alloy commands a price of \$3.50/lb. in the required mill form.

3.5.6 0.2 MWe Aluminum Test Articles

Technical considerations and the resulting choice of materials for the 0.2 MWe test articles are identical to the baseline 10 MWe design with the exception of the time element. The effect of time is as follows:

- Some candidate alloys are not currently available in the required mill forms (long lead procurement problem)
- Some candidate alloys do not have ASME Code approval
- For some alloys the surface protection (cladding) may not be fully optimized
- Use of certain candidate alloys, because of the lack of application data, may involve a higher degree of risk.

As the primary purpose of the 0.2 MWe test articles is to confirm the thermal/hydraulic performance of the full size heat exchangers, material

alternatives have been considered. Since the projected lifetime of this unit is five years, it is necessary only to have the reliable materials with sufficient margin to exceed the projected test period. An opportunity exists, then, to develop operating experience, at some risk, with materials which offer future economies to the OTEC program.

3.5.6.1 3004-0 Alclad Concept

The baseline 10 MWe aluminum heat exchanger requires the use of 0.050 inch thick 3004-0 which consists of 0.040 inch 3004 clad on one side with 0.010 inch of sacrificial material similar to 7072, but separately optimized for surface water and deep water applications in the evaporators and condensers. This material, however, is not available in the short term and alternative considerations are warranted.

A compromise was worked out for the 0.2 MWe unit. The compromise allows demonstration of functional performance and fabricability, and based upon current knowledge, will not result in corrosion problems during the short test period contemplated for the 0.2 MWe unit. The compromise involves utilization of 40 mil thick 3004-0 clad on both sides with 5 mils of the standard 7072 alloy for a total composite thickness of 50 mils. The contacts with aluminum producers such as Alcoa have indicated that this combination is available. Figure 3.5-5 is a comparison of the short and long term 3004-0 options preferred for the 0.2 MWe and 10 MWe heat exchangers, respectively.

3.5.6.2 5052-0 Option

While Alclad 3004-0 alloy remains by far the first choice for an aluminum OTEC heat exchanger, 5052-0 is a contingent second choice for the test article. The required core thickness for the heat exchange is 0.025 inch for 5052-0. Forming and corrosion allowances bring the core thickness to 0.050 inch. Hence, 5052-0 can be substituted with no impact on design. The best unclad aluminum alloy in both deep and surface seawater is 5052.

Figure 3.5-5. Materials Selected Based Upon Availability and Development

3.6 MANUFACTURABILITY

The aluminum preliminary design has progressed to the degree that the heat exchanger modules can be manufactured with existing technology. The design is such that all components can be shown to meet ASME Code requirements by standard stress calculations with the exception of the formed panels. The formed panels must be demonstrated by proof testing. Initial discussions with the code inspector (representative of UCC Insurance carrier located at the UCC Linde, Tonawanda Factory) indicate that the proof test will require the assembly of a "Code Test Article". This article will consist of up to 6 full-sized panels (4 x 9 foot) assembled with a downcomer, full-scale strongbacks, and upper and lower manifolds. The unit will be hydrotested to failure, i.e., to a pressure level where a rupture occurs. The proof pressure must be at least five times the design pressure to meet ASME Code requirements. This demonstration of code acceptability will allow subsequent modules of the same design, material and fabrication techniques to be code stamped.

UCC/Linde maintains a manual of acceptable weld procedures for code qualification. Any additional weld procedures necessary for this design

will be qualified during Phase II. Union Carbide, Tonawanda, has a large manufacturing facility which produces coded vessels, primarily fabricated from 5083 aluminum alloy, meeting worldwide codes (ASME, ANCC, DIN, STOOMWESEN and other codes). The codes are rigid and do not allow for deviations. Following code approval, the 0.2 MWe test articles will be completed and shipped.

Once the test articles have demonstrated thermal/hydraulic performance, materials and cleaning techniques, the production of a 10 MWe prototype heat exchanger will begin. The 10 MWe prototype will consist of 16 evaporator modules and 16 condenser modules and will be installed with associated system components (turbines, etc).

Once the prototype system has been demonstrated, the design and building of a facility to manufacture 100 MWe per year will take place.

A realistic production schedule for heat exchangers is:

- Design and build 0.2 MWe test articles
- Test 0.2 MWe test article
- Build 10 MWe prototype heat exchanger
- Test 10 MWe prototype heat exchanger
- Build facility for 100 MWe per year
- Deliver first 10 MWe production heat exchanger (32 modules).

The planned manufacturing technique (for the 0.2 MWe test articles, see Section 3.3.2.) will be based on current technology integrated with the panel-forming experience gained in Phase I. The learning (and code qualification) will be directly related to the larger modules without any extrapolation.

The 10 MWe prototype unit will utilize existing tooling and fabrication facilities. The fabrication procedures will be essentially identical to those planned for the production units. All procedures developed will be used to improve the fabrication and handling techniques for fabrication of the production heat exchanger units. Some exchanger design details may require revision based on the fabrication techniques and testing gathered from the prototype unit.

For the production of 100 MWe per year heat exchangers, a manufacturing facility is proposed as shown in Figure 3.6-1. The description of the facility assembly areas is presented in Figure 3.6-2. The letters within the circles of Figure 3.6-1 correspond with those of Figure 3.6-2. The arrows indicate the flow of exchanger components throughout the plant. The components will be assembled in subassembly areas. The subassemblies (for example, the downcomer panel, header beams, and strongback components) will be transported to the final assembly area for completion. A detailed description of the fabrication procedures is presented in Appendix II, Section 10. A modular subassembly approach will be used.

After assembly the modules will be transported to the pressure test area. Leak tests will be performed with the upper and lower shell assemblies temporarily fastened. Retesting will be performed after all repairs have been effected. The upper and lower shell assemblies will then be welded permanently and tested for leaks. The alignment apparatus will be assembled on the module and the alignment brackets welded to the strongbacks. The completed module will then be placed through a pressure testing and acceptance by the code inspector. The module assembly will be moved into the paint area, where it will be cleaned, masked and painted. The unit can now be readied for shipment and finally transported by truck to the graving dock for assembly aboard the OTEC platform.

In order to obtain ASME Code approval, it is necessary that the fabrication follow qualified procedures and processes as established between UCC/Linde Quality Assurance department and the code inspector. The code inspector will be aware of and will comment on the development of the detailed design as it proceeds on a weekly basis. This will ensure that the designs will not be delayed.

A portion of the Linde Quality Assurance Document is presented in Appendix II, Section 15. The document explains the necessary techniques and procedures used by Linde to obtain ASME code certification of heat exchangers and pressure vessels. The OTEC heat exchangers will be fabricated in accordance with similar procedures.

Figure 3.6-1. Proposed Plant Flow Diagram

(A)	COIL STOCK	— ONE MONTH INVENTORY IN STORAGE AND ONE WEEK INVENTORY AT ROLL FORM MILL
(B)	BAR STOCK	— ONE MONTH INVENTORY IN STORAGE AND ONE WEEK INVENTORY AT ROLL FORM MILL
(C)	STRUCTURAL MATERIALS	— ONE MONTH INVENTORY IN STORAGE
(D)	PANEL HALVES	— ROLL, FORM AND CUT TO LENGTH AND PRESS BRAKE FINAL FORM ENDS
(E)	PANEL INSERT	— ROLL FORM AND CUT TO LENGTH
(F)	SURFACE ENHANCEMENT	— APPLY ENHANCEMENT TO PANEL HALF SURFACES
(G)	PANEL SUB-ASSEMBLY	— COLLECT REQUIRED PANEL HALVES — INSTALL INSERTS AND WELD TO FORM PANEL SUB-ASSEMBLY
(H)	PANEL SUB-ASSEMBLIES ARE LEAK TESTED AND PROCESSED THROUGH DEGREASE SYSTEM	
(J)	PANEL SUB-ASSEMBLY	— SURFACES ARE PREPARED AND EPOXIED, THEN REMOVED FOR ASSEMBLY WITH DOWNCOMER
(K)	COMPLETED DOWNCOMER RECEIVED FROM FABRICATION AREA AND ABRASSED, THEN THE REQUIRED NUMBER OF PANELS ARE PLACED IN FIXTURE	
(L)	REQUIRED MATERIALS ARE REMOVED FROM STORAGE AND MACHINED TO REQUIRED SIZES THEN SENT TO FABRICATION AREA.	
(M)	FABRICATE AND WELD DOWNCOMER ASSEMBLY, STRONGBACK ASSEMBLY, UPPER SHELL ASSEMBLY, LOWER SHELL ASSEMBLY AND MOVE TO SUB-ASSEMBLY STORAGE AREA	
(N)	REQUIRED SUB-ASSEMBLIES AND AUXILIARY PARTS	
(P)	REMOVE FROM SUB-ASSEMBLY STORAGE — ADD ALL DETAILS INTO FIXTURE AND WELD TO FORM COMPLETE MODULE ASSEMBLY	
(R)	MODULE ASSEMBLY IS LEAK TESTED, THEN REMOVED TO SHIPPING AREA FOR FINAL PACKING OPERATIONS	

Figure 3.6-2. Production Plant Flow Diagram Overview

3.7 HEAT EXCHANGER LIFE CYCLE COSTS

This section addresses the initial capital costs and life cycle costs of aluminum and stainless heat exchangers. The heat exchanger life cycle costs developed during this project are the basis for the overall system initial and life cycle costs and power generation costs discussed in Section 6.1. (See Appendix II, Section 13 for details.)

The conclusion reached as a result of this analysis is that non-leaking aluminum PSD-II plate type heat exchangers must last at least 12.5 years to meet the DOE life cycle cost requirement of \$700/kWe. A "lower-level" leakage scenario (i.e., 5 percent holes at end of life, 0.001 inch diameter holes) increase the aluminum minimum life requirement to about 14 years.

Stainless steel, with an expected life of 30 years, has a life cycle cost of \$642/kWe.

3.7.1 Objectives and Requirements

The principal objective as defined by DOE of the PSD-II program is to design a power system which will be integrated into an OTEC system and be cost competitive in the Southeastern United States. In order to meet this objective, the DOE has required that the lifetime cost of the production heat exchangers should not exceed \$700/kWe.

3.7.2 Approach and Assumptions

For the various materials of construction for the heat exchangers, aluminum and super stainless (AL-6X) are the two top choices. Stainless steel is expected to last 30 years. Aluminum, in sea water service is expected to last approximately 10 to 15 years. Due to the shorter life expectancy, the aluminum heat exchangers will have to be replaced once or twice during the 30 year power plant life. This requires future capital investments and additional downtime for replacement. The present value of these additional future costs must be added to the initial capital cost for the first aluminum heat exchanger in order to obtain the total aluminum heat exchangers life cycle costs. Once these present value costs have been determined, aluminum and steel heat exchangers may be compared and evaluated.

3.7.3 10 MWe Heat Exchanger Initial Capital Costs

The production costs for both aluminum and stainless steel heat exchangers are presented in this section. TRW/Linde decided to determine heat exchanger costs at a production rate (evaporators and condensers) of 100 MWe/year. This requires a total of 320 modules to be produced annually in a facility. As a ground rule it was assumed that a new factory would be established which is self-sufficient in all respects. This study is based on the preliminary design of aluminum and on feasibility design for super stainless steel. Each item, production rate, etc. has been evaluated and a realistic cost estimate for the supply of 100 MWe per year has been determined. The costs are presented in the cost statements, Figure 3.7-1 for aluminum and Figure 3.7-2 for stainless.

<u>ANNUAL PRODUCTION</u>		
TRW = (10) - 10 MWe ALUMINUM EVAPORATORS AND CONDENSERS 2 x 160 MODULES/100 MWe x 15,361 FT ² /MODULE = 4,915,520 FT ²		
<u>PRODUCTION AND OTHER COSTS</u>	<u>SCHEDULE</u>	
DIRECT MATERIAL	A	\$11,490,900
DIRECT LABOR	B	2,789,095
INDIRECT MATERIAL	C	81,500
INDIRECT LABOR	D	1,142,639
OTHER SERVICES AND EXPENSES	F	1,014,800
MANUFACTURING STAFF	F	1,008,525
SUB-TOTAL		\$18,427,459
CONTINGENCY 10%		1,842,746
TOTAL		\$20,270,205
WARRANTY EXPENSE AT 2%		405,404
PRODUCT OVERHEAD AT 17%		3,445,935
SUB-TOTAL		\$24,121,544
DEPRECIATION EXPENSE	G	473,560
RETURN ON INVESTMENT AT 20%		1,940,596
COST		\$26,535,700
ENHANCEMENT CHARGES		5,498,945
TOTAL COST		\$32,034,645
AREA = 4,915,520 FT ²		6.52 FT ²
		\$320.35 KWe

Figure 3.7-1. Annual Production - OTEC-100 MWe Aluminum HX Evaporators and Condensers - Operating Statement

ANNUAL PRODUCTION		
TRW = (10) – 10 MWe STAINLESS STEEL EVAPORATORS AND CONDENSERS 2 x 160 MODULES/100 MWe x 17,087 FT ² /MODULE = 5,467,840 FT ²		
PRODUCTION AND OTHER COSTS	SCHEDULE	
DIRECT MATERIAL	A	\$24,414,200
DIRECT LABOR	B	3,671,874
INDIRECT MATERIAL	C	81,500
INDIRECT LABOR	D	1,314,939
OTHER SERVICES AND EXPENSES	E	1,981,000
MANUFACTURING STAFF	F	1,008,525
SUB-TOTAL		\$32,472,038
CONTINGENCY 20%		6,494,408
TOTAL		\$38,966,446
WARRANTY EXPENSE AT 2%		779,329
PRODUCT OVERHEAD AT 17%		6,624,296
SUB-TOTAL		\$46,370,071
DEPRECIATION EXPENSE	G	635,950
RETURN ON INVESTMENT AT 20%		2,943,144
COST		\$49,949,165
ENHANCEMENT CHARGE		6,116,820
TOTAL COST		\$56,065,985
AREA = 5,467,840 FT ²		\$10.25 FT ²
		\$561/KWe

Figure 3.7-2. Annual Production – OTEC-100 MWe Stainless Steel Evaporators and Condensers – Operating Statement

The detailed backup cost data for these fabrication cost statements are contained in Appendix II, Section 13.

3.7.4 Present Value Cost Analysis for Aluminum Heat Exchangers

Basis:

- Heat exchanger replacement cost = 104 percent capital cost
- 30 year power module life
- 10 percent interest rate (i)
- 7 percent labor and material inflation (e)

$$\text{Present value, \$/kW} = C_i \left(\frac{1 + e}{1 + i} \right)^n$$

where C_i = initial capital cost, \$/kW

n = time, years

$$= C_i \left(\frac{1 + .07}{1 + .10} \right)^n = C_i (.9727)^n$$

These values are shown in Figure 3.7-3 and plotted in Figure 3.7-4. Also plotted on the Figure 3.7-4 is the Linde stainless steel PSD-II design, which has an initial capital cost of \$642/kWe* and an expected life of 30 years. Figure 3.7-4 further plots the life cycle costs of a Linde aluminum shell and tube heat exchanger for which the rebuilding costs have been estimated at 42 percent of the initial heat exchanger capital costs. This graph shows that the "cross over point" for stainless steel and aluminum is at an aluminum lifetime of 14 years. Therefore the aluminum heat exchanger must last 14 years to have the same present value as a stainless steel heat exchanger that is expected to last the full 30 years.

Due to the absence of specific leakage data, the power generation costs using aluminum heat exchangers assume zero leakage of NH_3 . In actual practice, it is expected that leaks could develop in OTEC aluminum heat exchangers in seawater service. Section 6 addresses the incremental costs associated with aluminum heat exchanger tube leaks over the life of the heat exchangers and the life of the power module.

These ammonia leakage costs may be viewed in two ways: 1) the present value of the ammonia leakage costs over the 30 year power plant life may be added to the present value of the "non-leaky" aluminum costs previously computed and this total may then be viewed as the effective "leaky" aluminum heat exchanger life cycle cost. This life cycle leak cost is shown in Figure 3.7-4; 2) the cost impact of ammonia leaks may be evaluated as to the impact on electric power generation costs. This is equivalent to saying that the leaky heat exchangers result in higher operating and maintenance costs. This evaluation is detailed in Section 6.

*Initial aluminum heat exchanger capital costs of \$367/kWe and \$642/kWe for stainless steel were used in this analysis. These costs include transportation to New Orleans, LA and installation on the ocean platform.

YEAR	PRESENT WORTH FACTOR	LIFE CYCLE	REPLACEMENT COST (1.04 X 1ST COST) \$/KW	PRESENT VALUE H.E. COST			
				5 YR	10 YR	15 YR	30 YR
0	1.000	367*	—	367	367	367	367
5	0.871	320	333	333	—	—	—
10	0.758	278	289	289	289	—	—
15	0.660	242	252	252	—	252	—
20	0.575	211	219	219	219	—	—
25	0.501	184	191	191	—	—	—
30	0.436	160	166	166	—	—	—
TOTAL PRESENT VALUE				1817	875	619	367

*FIRST COST INCLUDES SHIPPING TO NEW ORLEANS AND INSTALLATION

Figure 3.7-3. Present Value (\$/KWe) of Heat Exchangers Having Lifetimes of 5-30 Years for a Power Plant Designed for 30 Years

Figure 3.7-4. Present Value PSD II Plate Heat Exchanger Costs Versus Life

3.7.5 Present Value Analysis for Stainless Heat Exchangers

The stainless steel heat exchangers are expected to last the full 30 years. Therefore, since there are no costs associated with heat exchangers replacements, the stainless steel life cycle cost is the same as the initial capital cost of \$642/kW. This value is shown as a horizontal line on Figure 3.7-4.

3.7.6 Results and Summary

PSD-II aluminum plate-type heat exchangers with a life of 12.5 years will satisfy the DOE heat exchanger life cycle maximum cost requirement of \$700/kWe. A 15 year life heat exchanger gives a life cycle cost of \$600 kWe. However, these life cycle heat exchanger costs are for zero ammonia leakage. For the case of minimum leaks (5 percent holes at end of life; hole diameter - 0.001 inch), the heat exchangers must last 15.5 years to satisfy the DOE heat exchanger life cycle cost objective of \$700 kWe.

The 30 year life stainless steel heat exchangers at \$642/kWe meet the DOE objectives.

REFERENCES

- 3-1 Union Carbide Corp., "Ocean Thermal Energy Conversion Heat Exchangers Final Report," Contract No. E(49-18)-2448.
- 3-2 Lewis, L. G. and Sather, N. F., "OTEC Performance Tests of the Union Carbide Flooded Bundle Evaporator," ANL/OTEC-PS-1.
- 3-3 Plank, R., "Handbuch der Kältetechnik," Springer, Berlin, Vol. IV, P. 248, (1956), and references cited by Plank.
- 3-4 Industrial Engineering Chemistry, Vol. 26, P. 1178 (1934).
- 3-5 Perry, Chemical Engineers Handbook, 2nd Edition, P. 1449.
- 3-6 Garner, et al., "The Size and Entrainment of Droplets," Transaction of Institute of Chemical Engineers, Vol. 32, P. 222 (1950).
- 3-7 Fair, Petroleum Refining, Vol. 39, P. 105 (1960).
- 3-8 Dukler and Bergelin, Chemical Engineering Progress, Vol. 48, No. 11, P. 557 (1952).
- 3-9 Jane Jenkins "Corrosion and Biofouling of OTEC System Surfaces" Naval Construction Battalion Ctr., Port Hueneme, CA.
- 3-10 "Use of Chlorine for Antifouling on Ocean Thermal Energy Conversion (OTEC) Power Plants," Proceedings of OTEC Biofouling and Corrosion Symposium, October 1977.

4. ROTATING MACHINERY

This section describes the turbine, generator, ammonia pumps and seawater pumps.

4.1 TURBINE

The PSD-II turbine design is based on the PSD-I design with only minor modifications. The PSD-I turbine design was based on results of a comprehensive study and had to meet requirements almost identical to PSD-II turbine requirements. There are two principal changes. For PSD-I, nominal ammonia flow was 807.2 pounds per second. For PSD-II, it is 764 pounds per second. Nominal ammonia inlet pressure has been increased from 128.7 psia for PSD-I to 133.4 psia for PSD-II.

The Elliott Company (who performed the PSD-I turbine design study for TRW) confirmed its applicability to PSD-II with minor modifications to the blade path to accommodate the slightly different ammonia flow conditions. As in the PSD-I design, power output can be reduced to 90 percent before efficiency is affected. Operating capability of about 60 percent of design ammonia flow also was confirmed.

To provide a compact arrangement, we rotated the PSD-II turbine inlet nozzle 90 degrees to eliminate one 90 degree elbow and simplify the piping. Also, the turbine inlet nozzle size was increased to an 88 inch diameter, which decreases the ammonia vapor pressure drop by 0.54 psi and enhances cycle efficiency.

The design meets DOE requirements. The turbine drives the generator to produce the required gross output of 13.87 MWe (at nominal operating conditions) by converting available energy in the ammonia vapor to work with an overall efficiency (total-to-static) of 89 percent or higher. The PSD-II turbine design also:

- Produces maximum power at off-design operating conditions
- Maintains turbine speed control to ensure generated power frequency within tolerance
- Is structurally adequate to withstand dynamic loads of the APL plant ship

- Has an availability in excess of 0.90
- Operates and generates net power with only three heat exchanger subassemblies on-line delivering about 90 percent of the ammonia flow rate normally produced by the four heat exchanger subassemblies (see Section 5.3.1).

Figure 4-1 summarizes the design criteria along with the minimum, nominal and maximum operating conditions.

INLET CONDITIONS	MINIMUM FLOW (WINTER)	NOMINAL FLOW	MAXIMUM FLOW (SUMMER)	VARIATION (APPROX.) ± %
AMMONIA MASS FLOW, LB/SEC	706.1	764.0	800.2	10
AMMONIA TEMPERATURE, °F	68.7	72.0	74.5	5
AMMONIA PRESSURE, PSIA	126.0	133.4	139.3	6
AMMONIA QUALITY, %	> 99.0	> 99.0	> 99.0	—
AMMONIA VOLUME FLOW, ACFS	1562.0	1640.0	1732.0	5
ANGLE OF PITCH, DEGREES	±5	±5	±5	—
ANGLE OF ROLL, DEGREES	±12	±12	±12	—
PERIOD, SEC	14	14	14	—
VERTICAL ACCELERATION, g's	0.30	0.30	0.30	—
HORIZONTAL ACCELERATION, g's	0.15	0.15	0.15	—
TURBINE EFFICIENCY, %	> 88	> 89	> 88	—
GENERATOR EFFICIENCY, %	> 97	> 97	> 97	—
GROSS GENERATOR POWER, MW _e	> 11.2	13.87	> 15.6	20
GENERATOR VOLTAGE KV	4.16	4.16	4.16	—

Figure 4-1. Turbine/Generator Design Criteria and Operating Conditions

4.1.1 Preliminary Turbine Design

The main objectives of the preliminary turbine design work were to:

- Select the optimum type of turbine (axial flow or radial flow)
- Select the optimum flow path (single or double flow)
- Select the optimum number of stages (single or multiple)
- Evaluate critical areas in detail to provide technical and economic credibility
- Arrive at a cost estimate for detail design, development and fabrication.

Much of the preliminary design work was done as part of the PSD-I effort by the Elliott Company, a Division of Carrier Corporation, under subcontract to TRW (see Reference 4-1). Elliott is a leading manufacturer of turbomachinery for power and process industries. Its products include centrifugal and axial compressors, steam turbines, power turbines and expanders. The applicable conclusions of the preliminary design work are:

- Although an ammonia turbine has not been built, its design is well within the state-of-the-art and it can be fabricated with existing shop techniques and facilities. Technology and mechanical design details from the power generation and chemical process industries are applicable.
- Optimum design of 10 MWe net power recovery is a four-stage double-flow turbine running at 1800 rpm connected to a four-pole synchronous generator.
- An efficient (89.6 percent) turbine can be built.
- Variable nozzles for the first expander stage are justified for off-design conditions, for matching the expander to particular site conditions, and for high frequency control.
- Blade stress and frequencies are mechanically safe.
- Critical speeds are safely away from the operating speed.
- Stress corrosion cracking investigation should be initiated early to ensure that material selections and certain design features are suitable before further turbine design work is done.

4.1.2 Optimizing the Turbine Design

4.1.2.1 Efficiency

Increased turbine efficiency reduces the size of other expensive equipment such as evaporators, condensers and seawater pumps. Plant cost decreases by about \$17/kWe for each percentage point increase in turbine efficiency. Therefore, various options were analyzed to achieve a turbine with maximum efficiency.

4.1.2.2 Aerodynamic Design

The aerodynamic design of turbines can be divided into three phases:

- Overall design criteria are set
- These criteria are used to establish the basic turbine geometry, including the number of stages, blade sizes and blade angles
- Blade shapes to achieve second-phase requirements are determined.

All three phases affect the resulting turbine efficiency. The PSD-II preliminary design focused on the regions of high efficiency. A computer program identified promising candidate axial flow expanders (Reference 4-1).

4.1.2.3 State-of-the-Art Technology

Having identified promising candidate expanders, a detailed design study was performed to select the optimum turbine possible with state-of-the-art technology. The study showed that a four-stage axial double-flow machine with exhaust diffuser yields the highest cost-effective efficiency. In performing the detailed design study comparisons, turbine geometry was constrained to the existing manufacturing art and technology and conventional blade shapes were used.

4.1.2.4 Off-Design Performance

Off-design performance is an important design consideration because of the need to maintain high turbine efficiency. Because the plant and turbine are optimized at nominal operating conditions, off-design conditions could produce flow-limiting conditions in a turbine with fixed flow nozzles. Flow choking occurs at the maximum flow conditions of "summer" operation. At the minimum flow conditions of "winter" operation, the pressure in the evaporator drops, resulting in a lower value of pressure and energy available to the expander. The variable inlet stator vanes incorporated in our design provide a cost-effective solution to off-design operations.

4.1.2.5 Variable Stator Vanes

Variable stator vanes are the best means to control power peaking with an axial flow turbine because:

- Large volume flow variations can be handled
- Low pressure drop
- No flow is bypassed around the turbine
- System can adjust to off-design conditions (changing sea-state conditions or different site locations).

Variable stator vanes have not been used for axial flow steam turbines because steam conditions are considerably different from the ammonia conditions expected for OTEC. Steam pressures and temperatures are considerably

higher and steam volume flows are usually much lower. Use of variable stator vanes in steam turbines creates serious deformation problems at the steam pressures and temperatures normally employed. Variable stators have been used successfully for decades by the process industry on axial flow compressors. This control has demonstrated high reliability with minimum maintenance.

Variable stator vanes at the inlet to the first stage of the OTEC axial flow turbine accommodates flow variations from minimum to maximum conditions while maintaining high efficiency. Variable stator vanes increase the net power by about 150 kW at the minimum operating point and about 250 kW at the maximum operating point. Assuming a 360-degree sine wave over a year from minimum to maximum flow conditions, the average yearly increase is 128 kW. Thus, an extra 10^6 kW-hrs are generated each year which, at a replacement cost of \$0.08/kW-hr has a present value of \$805,000 over 30 years at 10 percent interest. Total cost of variable stator vanes is roughly \$55,000. Using variable stator vanes saves money over the life of the turbine and provides better control.

Only one set of variable stator vanes is required at the inlet to the first stage of each flow path. Efficiency is almost constant over the entire range of operating conditions with one set of variable vanes for each flow path.

4.1.2.6 Thermodynamic Operating Conditions

Thermodynamic operating conditions for the four-stage double-flow axial turbine are given in Figure 4-1. Performance maps are given in Reference 4-1 to predict power output over a wide range of operating conditions and consider mass flow, inlet pressure, exhaust pressure, variable stator vane angle and generator efficiency.

4.1.3 Turbine Arrangement

The string arrangement of the turbine-generator is shown in Figure 4-2. A barrel construction is used for the turbine to avoid any leakage problem with a long horizontal joint.

Flow enters the side center and is distributed circumferentially before it turns axially to feed both sets of blading of the double-flow design.

Figure 4-2. Turbine-Generator Arrangement

After passing through the four stages, the ammonia is diffused to exhaust pressure. The two exhaust flows are joined before exiting through the common exhaust flange on the bottom vertical centerline. The stages are located between the journal bearings. The shaft and mechanical seals are inboard of the journal bearing. The thrust bearing and speed control devices are outboard at the journal bearing on the non-drive end.

The inner casing contains the variable stator vanes for each direction flow, three diaphragm assemblies for each direction of flow, and a seal for each diaphragm. One control rod penetration of the outer barrel is required for the ring of variable stator vanes serving each flow direction. The rods penetrating the outer casing are sealed by bushings and O-rings to prevent ammonia leakage to the atmosphere.

The string arrangement on Figure 4-2 shows the pertinent dimensions. Roughly 17 feet of clear space is required to pull the rotor from the turbine barrel; 13 feet of clear space at the other end is required to pull the generator rotor. A laydown area 38 x 24 feet is required for work on the turbine rotor. This area could be used for the generator rotor. If a separate laydown area is necessary for the generator rotor, it can be 20 x 20 feet.

4.1.4 Mechanical Design

4.1.4.1 Stress Corrosion

Contaminated dry liquid ammonia can cause stress corrosion cracking of steel. Oxygen is the main contaminant and high-strength steels are more susceptible than low-strength steels. Water is an inhibitor to stress corrosion cracking by contaminated ammonia. The 1975 DOT regulations require 0.2 weight percent water in all ammonia transported in high-strength steel tanks. If the water content is less, stress-relieved low-strength steels must be used.

Some liquid ammonia will be present in the ammonia turbine. There is a possibility of oxygen contamination during transfer operations required before the ammonia is in the platform storage vessels while activating idle loading lines. Using water to inhibit stress corrosion cracking reduces cycle efficiency by an intolerable amount. The ammonia purification column removes oxygen with the noncondensibles vented from the condenser.

Because past stress-corrosion cracking problems have been mainly confined to storage and transportation vessels, essentially all work has been done on steels used for vessel fabrication. The problems of steels used for the stressed parts of an ammonia turbine (shaft, wheels, blades, and shrouds) have not been adequately investigated. Stress-corrosion cracking susceptibility determines suitable materials and affects certain design features. Therefore, possible materials for the ammonia turbine must be investigated for stress-corrosion cracking susceptibility before further turbine design work is done.

4.1.4.2 Materials

A table showing the material selection for the main components is included in Reference 4-1. Normal steam turbine steels are used for the rotating parts but in an annealed condition, which reduces their yield strength and avoids stress-corrosion cracking problems. Fortunately, operating stresses are low enough in the ammonia turbine to permit this.

The pressure containing parts (outer casing barrel and endwalls) are constructed of low strength materials selected for resistance to stress-corrosion cracking. The materials selected for the pressure-containing

parts are also suitable against low temperature embrittlement. This protection is needed if the system temperature drops to -28°F if it is vented to atmospheric pressure.

4.1.4.3 Coupling

Three types of couplings were considered: solid, gear and diaphragm. A solid type costs the least but requires precise alignment, which is a problem if field maintenance requires removing a coupling hub. The disadvantages of a gear type coupling is that it requires lubrication oil which increases the size of the auxiliary oil equipment. A gear type coupling also requires a separate 2-micron filter and the coupling lockup sometimes is a problem. For a slight additional cost, a dry diaphragm type coupling can be provided. This type of coupling is now widely accepted and is the recommended coupling.

4.1.4.4 Critical Speeds

The four-stage double flow axial turbine has a flexible shaft which has the following advantages:

- More space for the inlet channel and exhaust diffuser
- Better maintenance access to seals and bearings
- Reduced size of bearings and seals for less oil flow and power loss.

The first critical speed is about 1300 rpm or 28 percent below the operating speed of 1800 rpm. The second critical speed is about 2700 rpm or 50 percent above the operating speed. It is common to operate turbine driven generators and compressors between the first and second critical speeds. While the desired spread between critical speeds and operating speeds is well defined by standards for mechanical drive turbines, this is not the case for turbines driving constant speed generators. Some turbine generator clients set the limit to 20 percent below and 20 percent above the operating speed. The selected turbine easily meets these conditions.

4.1.4.5 Blade Stresses

The rotating element is the critical item in any rotating equipment. When the rotating element of a turbine fails, it is usually the blades or shrouds that fail. A Goodman diagram is included in the referenced Elliott

report for the fourth and most critical stage to show that the combination of alternating and steady-state blade stresses are well below the failure line. Barring stress corrosion cracking problems, blade failure problems are not likely.

Another blade design criterion is to design blades so their natural frequency exceeds low multiples of the operating speed and does not coincide with the nozzle passing frequency. The fundamental natural frequencies of the blades range from 8 to 11 times the operating speed or from 240 to 330 cycles per second. Since the passing frequency (speed times number of stator vanes) is 1140 cycles per second, no blade vibration problems are anticipated.

4.1.4.6 Moisture Erosion

Some moisture may be entrained from the evaporator and enter the turbine. Within the turbine, about 2 percent by weight moisture is condensed ahead of the fourth and last stage. This compares with 8 to 10 percent by weight moisture frequently encountered in the exhaust end of steam turbines. No moisture erosion problems are expected with the ammonia turbine because of:

- Low moisture level
- Low velocities encountered in the design
- An apparent "hardness" of an ammonia droplet that is about one-half that of steam
- A stable droplet size of about one-third that of steam
- An erosion coefficient that is only 0.003 compared to about 30 for a typical steam turbine.*

4.1.4.7 Seals

The turbine shaft end seal selection is important since ammonia losses and contamination of the confined hull of the platform must be avoided. This applies to the shutdown condition with the turbine under pressure as

*The erosion coefficient is a function of stator to rotor blade clearance, stator blade trailing edge thickness, moisture content, blade tip speed, and absolute pressure. Based on steam turbine experience, the threshold of significant erosion is a coefficient of 8.

well as to the normal operating conditions. The available seal types include labyrinth seals and dry carbon ring seals. Both the labyrinth and carbon ring seals allow some leakage in the operating condition and even more in the shutdown condition. Bushing and face seals require a sealing oil and are frequently used in compressor applications to avoid leakage of the process gas to the atmosphere.

The bushing type seal requires more seal oil flow and has a considerably greater flow of oil towards the pressurized gas side of the seal which must be drained and separated from the entrained gas. Although bushing seals are in use with shutdown pistons to seal in the shutdown condition without a flow of seal oil, this is not a common feature with this type of seal.

The seal design selected for the turbine is the contact type face seal with shutdown features. A typical seal of this type is shown in Figure 4-3. This seal has a proven performance record in process gas compressor installations. Seal oil flow past the contact face towards the pressurized gas into the contaminated seal oil drain compartment of the seal is about 10 gallons per day. During idle periods, shutdown pistons automatically lock the face seal ring, allowing the seal oil flow to be shutdown with no ammonia leakage even though the turbine is still pressurized.

4.2 GENERATOR

The selected generator (based on the Elliott study, see Reference 4-1) is a totally-enclosed Brown Boveri four-pole synchronous generator which is water-to-air cooled and rated at 18,000 kW. This generator was selected based on its suitability for PSD II, its cost, efficiency and reliability. It is a standard unit.

The Brown Boveri generator meets DOE requirements. It produces an output power of at least 13.87 MWe at the bus bar and can produce any additional output that the turbine can provide when the warm seawater temperatures are above the nominal design conditions. Generator design data are given in Figure 4-4. The off-the-shelf generator meets all of our requirements.

1. ROTATING CARBON RING	8. FLOATING BABBITT-FACED STEEL RING
2. ROTATING SEAL RING	9. SEAL WIPER RING
3. STATIONARY SLEEVE	10. SEAL OIL DRAIN LINE
4. SPRING RETAINER	11. SECONDARY WIPER RING LABYRINTH
5. SPRING	12. BEARING OIL DRAIN LINE
6. SHUTDOWN SEAL PISTON	13. BEARING WIPER RING
7. GAS AND CONTAMINATED OIL DRAIN	

Figure 4-3. Face Seal with Shutdown Features

TYPE	SYNCHRONOUS				
MANUFACTURER	BROWN BOVERI CORPORATION				
RATED (KW)	18,000				
SYNCHRONOUS SPEED (RPM)	1,800				
RATED VOLTAGE	4160				
NO. OF PHASES/FREQUENCY	3/60				
POWER FACTOR	0.8 LAGGING				
SERVICE FACTOR	1.00				
EFFICIENCY PERCENTAGE (AT 4/4, 3/4, 1/2 LOAD)	97.2, 96.9, 96.2				
INSULATION CLASS	F				
MAXIMUM TEMPERATURE RISE (WINDING, OVER 40°C)	80°C				
EXCITATION TYPE	BRUSHLESS				
EXCITATION DC VOLTAGE (AT FULL LOAD)	112				
EXCITATION RESPONSE, SEC	2.0				
SHORT CIRCUIT RATIO	0.55				
SHORT TERM THERMAL CAPABILITY (BALANCED CURRENT)	100 SECONDS				
SHORT TERM THERMAL CAPABILITY (SHORT CURRENT AT MACHINE TERMINALS) UNBALANCED (LINE TO NEUTRAL)	30 SECONDS				
WAVE FORM DEVIATION, MAXIMUM PERCENTAGE	0.8				
CALCULATED TRANSIENT AND SUBTRANSIENT REACTANCE	27, 21				
ENCLOSURE	TEWAC-WEATHERPROOF				
COOLING WATER INLET TEMPERATURE (MAXIMUM), °F	85				
COOLING WATER OUTLET TEMPERATURE °F	95				
COOLING WATER REQUIREMENTS (GPM)	295				
LUBE OIL PRESSURE (PSIG)	15/18				
LUBE OIL REQUIREMENTS (GPM)	8				
WR ² OF MACHINE (LB-FT ²)	24620 GENERATOR/EXCITER				
PERMISSIVE OVERSPEED (RPM)	2250				
VIBRATION MAXIMUM, (MILS) PEAK-TO-PEAK	1.5 (APPROXIMATE)				
NOISE LEVEL, dB (A)	84 + 3 dB (A) TOLERANCE				
WEIGHT (LBS) NET/SHIPPING	86640/100500				
OVERALL DIMENSIONS (LENGTH X WIDTH X HEIGHT, INCLUDING EXCITER)	180 IN. X 96 IN. X 140 IN.				
REACTIVE POWER CAPACITY					
20	40	50	80	100	% OF LOAD
14.4	14	13.3	12.4	11.2	MVA

Figure 4-4 Generator Design Data

The unit is installed in a non-weather - protected, well-ventilated area and subjected to salt spray caused by either its open position or carried through the ventilation system. A low-temperature (per usual industry cooling water standards) cooling water supply is available. For environmental reasons, a totally enclosed water-cooled unit has been specified.

The National Electrical Code and American National Standard ANSI B9-1-1971 classified the area where the generator is installed and operated as Class 1, Division 2. Totally enclosed generators are suitable for service in such areas.

Generators of this small to intermediate size (25,000 Hp) are standard catalog items with size increments (depending on manufacturer) of as much as 5000 kW. Any deviation from standard sizes, features or performance characteristics results in significant cost increases and delivery lead times. Standard units are more reliable. The reliability gains in the same manner as the cost decreases on a learning curve basis.

Some improvement in efficiency (perhaps 0.2 to 0.5 percent) could be achieved with a hydrogen-cooled generator. The utility industry has not found hydrogen-cooling economical below about 35 MWe and they are generally not available below this capacity.

Coupling to the turbine is a dry diaphragm type because of easy maintenance and because this type requires no lubrication (see Section 4.1.4.3 and Reference 4-1).

Generator efficiency for the PSD-II generator is about the same as PSD-I and is shown in Figure 4-4.

4.3 AMMONIA FEED PUMP

Two 100 percent flow pumps (one as standby) were selected for PSD-II. The two-pump system was selected based on a study (Section 5.5) showing that the startup reliability is only 0.93 with a single pump versus 0.97 with two pumps. Therefore, the redundant pumps are required to meet the 0.95 DOE specified startup reliability requirement. Also, a simple cost analysis showed that, at 80 mills/kW-hr, the annual cost savings resulting from a 2 percent

availability increase results in an annual cost savings of \$140,000. At 10 percent interest and 30-year life, this is equivalent to a present value cost savings of \$1.3 million. The additional cost of the redundant pumps is less than this by about a factor of ten.

The ammonia feed pumps selected for PSD-II are centrifugal, horizontally split, single-stage, double-suction pumps with AC adjustable frequency variable speed drives rated at 500 HP. The ammonia feed pump and drive are off-the-shelf designs and were selected for their high efficiency and low net positive suction head (NPSH). Pump curves are shown in Figure 4-5.

Figure 4-5. Selected Ammonia Feed Pump Head-Flow Curves

These pumps meet DOE requirements. Flow and head requirements for the ammonia feed pump are shown in Figure 4-6. Minimum, nominal and maximum flow rates correspond to expected seasonal variations in the cold and warm

	FLOW		SYSTEM ΔP	
	GPM	LBS/SEC	FT	PSI
MAXIMUM	9,317	808.2	177	47.8
NOMINAL	8,807	764.0	165	44.6
MINIMUM	8,141	706.1	150	40.5

Figure 4-6. Normal Feed Pump Operating Requirements

water temperatures. They are the normal flow rates with four heat exchanger subassemblies operating. The feed pump is able to operate at 60 percent of the nominal flow rate.

The pump, pump drive and controls were selected because they satisfied the following requirements:

- Meet system head and flow requirements shown in Figure 4-6
- Meet overall system availability requirement of 0.90
- Minimize the elevation difference between ammonia pump floor level and condenser and evaporator sumps by selecting pumps with minimum NPSH requirements
- Minimize space requirements for pumps, drivers and control to minimize cost penalties due to excess platform space requirements
- Portions of the feed pump in contact with the ammonia be made of low-strength steels to prevent stress-corrosion cracking
- No copper or copper bearing alloys can be used for any components in contact with the ammonia.

Specifications for the ammonia feed pumps and drives are given in Appendix I, Section 8, and pump dimensions are given in Figure 4-7. Figure 4-8 shows a cross-section of the pump (courtesy of Ingersoll-Rand for these two figures).

4.3.1 Feed Pump Selection Approach

Two basic schemes of obtaining the desired range of liquid ammonia flow variation were considered:

- Fixed speed pumps with control valves to change flow
- Variable speed pumps (no control valves) with pump speed varied to obtain the desired flow.

Figure 4-9 shows how the desired liquid ammonia flow rate is obtained using either fixed speed pumps or variable speed pumps. At a fixed speed, the pump operates on a unique head-flow curve. The intersection of the pump head-flow curve with the system head-flow curve results in a unique flow operating point for the system.

To change the flow, it is necessary to change the control valve position, which changes the system head curve. The new system head-flow curve,

DIMENSIONS — BOTTOM SUCTION

SELECTED PUMP: 18 ALV

APPROXIMATE DIMENSIONS (1) — DO NOT USE FOR CONSTRUCTION

Pump	Diameter		X	YY	S	Z	A	HO(2)	HD(2)	Ball Bearing		Sleeve Bearing		C (2)	Ball Brg.	Slv. Brg.	HM(2)	HA(2)	HB(2)	D
	Disch.	Suct.								CP	W	CP	W							
14AFV	14	16	20	33	1-7/8	14	41-7/8	51-1/4	34-3/4	◆59-5/8	◆32-1/2	◆72-3/8	◆32-1/2	48-3/4	◆108-3/8	◆121-1/8	51-3/8	46-1/2	105	26
30AFV	30	36	35	70	0	33-1/2	80-11/16	102-1/2	67	104	57	◆117-1/4	◆56-3/4	65-7/8	169-7/8	◆183-1/8	92	77-7/8	175	34
36AFV	36	48	42	76	0	38-3/4	93	83	42	106-3/4	58-1/4	◆125-3/4	◆61	83-1/4	190	◆209	76-1/4	80-3/4	180	32
14ALV	14	18	26	32	0	18	4E-15/16	57-3/8	38-1/4	◆58-1/4	◆32-11/16	◆70-11/16	◆32-11/16	55-7/8	◆114-1/8	◆126-9/16	58	52-1/2	120	26-1/2
16ALV	16	20	31-1/2	39	0	18-5/8	55	62-1/4	43	61	34	76-1/8	40-3/8	55-7/8	115-7/8	132	62-3/4	52-1/2	130	24
18ALV	18	24	40-1/2	41-1/2	2-1/2	23	68-11/16	72	49	◆76-3/8	◆43-3/8	◆81-3/4	◆39-1/8	71-1/8	◆147-1/2	◆152-7/8	70-1/2	65-7/8	140	32-1/2
20ALV	20	24	44	48	1-3/4	25	73-5/8	65-1/4	41	88-3/4	48-1/8	104-3/8	54-7/8	71-1/8	160-7/8	175-1/2	62-1/2	71-7/8	165	25
24ALV	24	30	44-1/2	54	2	28-3/4	79-3/4	85-3/4	58	83-1/4	◆44-1/2	◆93	◆42	75-1/4	◆153-1/2	◆168-1/4	91-3/4	65-7/8	155	29-3/4
30ALV	30	42	57	70	0	34	101-3/8	97	62	◆38-3/4	◆54	◆115-3/4	◆5E	39	◆137-3/4	◆204-3/4	85-1/2	77-7/8	190	34
18HHV(3)	18	24	32	56	0	30	71-5/16	90	60	NA	NA	91-5/8	48-1/8	83-3/8	NA	175	94	60	168	24
24HHV	24	30	55	51	3	27-3/4	91-1/4	84	54-1/2	91-1/4	55-1/2	119-1/2	89	39	180-1/4	◆208-1/2	85-1/2	84	180	40
10HLV	10	14	20	28	0	14-1/2	39-7/8	45-1/2	30	55-1/4	31-3/8	72-5/8	41-1/8	5E-3/8	111-5/8	129	47-1/4	39-7/8	115	21
12HLV	12	16	28-1/2	34	1-1/2	18-3/4	51-3/4	59-1/4	39-3/4	E2-1/2	33-3/4	77-3/8	40-1/8	5E-7/8	121-3/8	◆136-1/4	59-1/2	52-1/2	120	28-3/4
14HLV	14	18	37	38	2-1/2	20-3/8	61-1/2	58-3/4	38-1/4	◆68-1/4	◆38-3/8	◆77-1/4	◆36-7/8	65-1/8	◆131-3/8	◆140-3/8	59-3/4	52-1/2	130	28
18HLV	18	24	45	41-1/2	2-1/2	22-1/2	74-1/4	69	45	◆80-3/4	93-1/4	◆87-3/4	◆4C	72-7/8	◆153-5/8	◆160-5/8	70	65-7/8	145	32-1/2
12HLVS	12	16	28	30	0	15-1/4	49-5/8	52	36	E1-3/4	34	78-3/8	42-5/8	58	129-3/4	141-3/8	86-1/2	40-1/2	124	24-1/2
20LFV	20	24	31	44	0	18-1/2	E9-1/16	67-1/4	45	70-7/8	38-3/4	◆82-1/8	◆38-3/4	5E-7/8	129-3/4	◆141	64-3/4	57-7/8	135	32-1/2

Footnotes:

- (1) All dimensions in inches.
- (2) Dimensions will vary with size, and type of driver.
- (3) Sleeve brg. dimensions on 18HHV are based on sleeve radial brg. and sleeve ball thrust brg.

◆ Changed

Figure 4-7. Horizontally-Split Single-Stage Double-Suction Pumps

Figure 4-8. Cross Section of Feed Pump

corresponding to the new valve position, intersects the pump head-flow curve at a different point and results in a new and different operating point. Closing the control valve creates a steeper system head-flow curve which intersects the pump head-flow curve at a higher head, lower flow point. Conversely, opening the control valve creates a flatter system head-flow curve which intersects the fixed speed pump head-flow curve at a lower head, higher flow point.

Similar flow changes can be obtained by varying pump speed. Figure 4-9 depicts three pump head-flow curves, each one corresponding to a different pump speed. As pump speed is reduced from its maximum value, the pump head-flow curve intersects the system head-flow curve at lower values of head and flow.

Figure 4-9. Fixed and Variable Speed Pump Head-Flow Characteristics and System Head-Flow Curve

The pump drives have been sized to provide required pump horsepower under all load operating conditions. The drives have high reliability and high electrical and mechanical efficiency.

The requirement for flow control is not only to have the potential for fine tuning the power modules for maximum performance but also to optimize the net electric output for the seasonal seawater temperature variations.

A cost analysis (performed for PSD-I) compared the capital cost plus operating cost of the fixed speed drive versus the variable speed drive at maximum, nominal and minimum flow conditions. The operating cost over the the 30-year power plant life was calculated by determining the present value of the yearly cost of pump power for 30 years. Based on that study, the variable speed drive was selected for the ammonia feed pumps. Section 5.4.1 shows how the variable-speed pumps are used with control loops.

4.3.2 Pump Seals

The seals for the ammonia feed pumps are tandem mechanical seals rather than double seals. Double seals have a higher pressure in the sealing liquid than in the stuffing box. Therefore, they can get sealing liquid into the pumped liquid (ammonia); on the other hand, tandem seals operate with a lower pressure in the sealing liquid than in the stuffing box. Thus, pumped liquid (ammonia) can get into the sealing liquid but not vice versa.

With tandem seals, both the inboard and outboard seals seal in the same direction. Methanol, from a small surge pot provided for each pump, floods the cavity between the tandem seals to lubricate outboard seal faces. Methanol (or a synthetic lube oil) lubricates at the low temperature resulting from liquid ammonia flashing across the inboard seal faces. A vent line with a restriction orifice is connected to the top of the surge pot. A pressure switch on the surge pot signals a large flow of ammonia vapor indicating failure of the inboard seal. A level switch on the surge pot signals loss of methanol by leakage or failure of the outboard seal. The vent line from the surge pot is routed to an atmospheric vent system.

4.4 SEAWATER PUMPS

Power to drive the seawater pumps is the largest parasitic demand on the power module electrical output. Therefore, optimum pump performance is important. Operability also is a major consideration because if a pump shuts down then the power module shuts down unless redundancy is provided.

The seawater pump requirements of Figure 4-10 can be satisfied by commercially available pumps. Figure 4-11 shows a candidate manufacturer's data sheet (courtesy of Pleuger pumps). Asterisks indicate candidate designs.

	HEAD (FT)	FLOW * (GPM)	ASSUMED EFFICIENCY (PERCENT)		POWER REQUIREMENT (MWe)	SHAFT POWER REQUIREMENT (HP)
			PUMP	DRIVE		
COLD WATER PUMP	12	679,600	87	92.4	1.96	2430
WARM WATER PUMP	7	721,800	87	92.4	1.21	1500

*FLOW REQUIREMENT IS SHARED BY TWO PUMPS ON EACH, COLD AND WARM SEAWATER SIDE

Figure 4-10. Seawater Pump Requirements Normal Operating Conditions

APL plant ship drawings indicate two pumps each for the cold and warm seawater sides. However, not enough information was available about the design details of APL's seawater pump design.

In the preliminary design phase, we defined performance requirements for power, efficiency, head and flow rate. We also identified and quantified design requirements to define input power characteristics, fixed speed versus variable speed, and interfaces with heat exchangers.

4.4.1 Fixed Speed Versus Variable Speed

The effect of varying the warm and cold water flow rates in the evaporator and condenser was investigated. In Section 5.3.1.4 we show results for maximum (85°F), nominal (82°F), and minimum (78°F) warm-water temperatures for a 40°F cold-water temperature.

Using a variable-speed cold water pump that varies water flow rate to achieve instantaneous maximum power would generate an additional 0.03 MWe average for 5 months each year. Allowing for a 2-week biennial winter shut-down, an additional 10,000 kW-hrs would be generated each year. The present value over 30 years at 10 percent interest (assuming replacement electricity costs \$0.08/kW-hr) is \$79,000. This is considerably less than the difference between the cost of a variable-speed and fixed-speed pump. Therefore, the extra investment is not worthwhile. As for the warm water pump, controlling its speed saves less than \$25,000 in present value. Therefore, the investment in a variable-speed warm water pump is not justified.

Section 5.3.4.8 discusses the effect of startup requirements on the choice of water-pump drive. It shows that if the OTEC plant is connected to a large grid, one that can supply 3.3 MW, the plant can start using grid power. That is our baseline. However, if the plant were isolated or connected to a small grid, use of variable-speed pumps would permit

OCEAN THERMAL ENERGY CONVERSION (OTEC)
SEA WATER PUMP ARRANGEMENT

DRAWING - NO.
SK 1273

OVERALL DIMENSIONS FOR
AXIAL FLOW PUMP
PLANETARY REDUCTION GEAR
SUBMERSIBLE A.C. MOTOR

P_M = POWER OUTPUT OF SUBMERSIBLE MOTOR (HP)
 n_M = SPEED OF SUBMERSIBLE MOTOR (RPM)
 n_p = SPEED OF IMPELLER (RPM)
 Q = PUMP CAPACITY (USGPM)
 H = TOTAL HEAD (ft)

TYPE		P_M HP	n_M r.p.m.	n_p r.p.m.	Q		H		NW mm	D_1 mm	D_2 mm	d_1 mm	d_2 mm	d_3 mm	L_1 mm	L_2 mm	L_3 mm	L_4 mm	WEIGHT kg
PUMP	MOTOR				USGPM	m ³ /h	ft.	m											
S 5503 - 1	VZRW 50 - 200 - 8	6 400	865	75	1 600 000	363 360	11	3,35	8 000	5 500	7 100	2 100	2 000	1 250	1 800	3 200	4 900	2 200	65 000
S 5903 - 1	VZRW 50 - 150 - 8	4 150	865	65	1 600 000	363 360	7	2,13	8 000	5 900	7 500	2 100	2 000	1 250	1 950	3 400	4 900	1 500	61 000
S 3903 - 1	VZR 40 - 200 - 6	3 200	1 150	115	800 000	181 680	11	3,35	5 600	3 900	5 000	1 400	1 640	935	1 300	2 300	3 500	1 500	25 500
S 4303 - 1	VZRW 40 - 160 - 8	2 100	865	77	800 000	181 680	7	2,13	5 600	4 300	5 600	1 500	1 640	935	1 450	2 500	4 700	--	26 000
* S 2703 - 1	VZR 30 - 130 - 4	1 600	1 750	156	400 000	90 840	11	3,35	4 000	2 700	3 500	970	1 130	800	900	1 600	2 900	1 100	10 500
* S 3003 - 1	VZR 30 - 110 - 6	1 050	1 150	115	400 000	90 840	7	2,13	4 000	3 000	3 800	1 050	1 130	800	1 000	1 750	2 700	500	10 500
S 1903 - 1	VZR 22 - 130 - 4	800	1 750	219	200 000	45 420	11	3,35	2 800	1 900	2 600	700	780	630	650	1 100	2 800	500	5 500
S 2103 - 1	VZR 22 - 90 - 4	515	1 750	156	200 000	45 420	7	2,13	2 800	2 100	2 800	770	780	630	700	1 200	2 400	--	4 700

PLEUGER PROJECT NO. OP 72 (US)

11. Jan. 1978

10.1.78

PLEUGER-UNTERWASSERPUMPEN GMBH, 2 HAMBURG 70

Figure 4-11. Seawater Pump Arrangement

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

startup with 400 kW drawn from a startup source. Reference 4-1 supports that pumps be started at slow-speed to reduce shock. Provisional discussions with manufacturers show that for near-continuous duty, full-speed startup is satisfactory.

The conclusion is that fixed-speed (uncontrolled) pumps are technically feasible and economically justified for both cold and warm water.

4.4.2 Seals and Lubrication

The design of the seals and lubrication system for the seawater pumps is similar to ammonia feed pumps using tandem mechanical seals. Tandem seals prevent leakage of the lubrication into the seawater and prevents possible contamination of the heat exchanger tubes, which lowers thermal performance of the heat exchangers.

4.4.3 Interface with Evaporator and Condenser

The seawater pumps subsystem must interface with the water supply trough supplying seawater to the evaporator and condenser. These interface locations are shown in the interface drawings in Section 5.1.

4.4.4 Input Power Characteristics

The input power for the seawater pumps is 4160 volts, 3 $\emptyset$, 60 hertz AC power at a minimum power factor of 0.80.

REFERENCES

- 4-1 Elliott's Turbine Design Study. Appendix F of TRW PSD-1 Preliminary Design Report, dated 4 December 1978, EG-77-C-03-1570.
- 4-2 Little, T. E., "Seawater Pump Study, OTEC Program," Westinghouse Report C00-4071-2, January 1978.

5. POWER SYSTEM CONFIGURATION AND PERFORMANCE

5.1 SYSTEM DESIGN

This section describes the baseline power module design and includes the process flow diagram, piping and instrumentation diagrams, and arrangement drawings. Mechanical, structural and electrical design features are discussed. Results of a conceptual design study of a stacked heat exchangers option are included here. The system design meets DOE requirements.

5.1.1 Design and Performance Summary

Performance and design characteristics of the selected 10 MWe power system modules are summarized in Figures 5.1-1 through 5.1-5. The power budget includes the hotel load at 450 kWe per 40 MWe power output (or 112.5 kWe per 10 MWe module) and an allocation for miscellaneous support systems of 350 kWe. Figure 5.1-2 summarizes evaporator and condenser assembly characteristics (see Section 3 for details). The water supply and discharge subsystem characteristics are summarized in Figure 5.1-3. The requirements for the seawater pumps (Section 4.4) are derived from the system analysis. Ammonia power loop characteristics are summarized in

PARAMETERS	VALUE
GROSS POWER, MWe	13.87
NET POWER, MWe	10.00
GROSS POWER/NET POWER	1.39
WARM WATER PUMPING POWER, MWe	1.21
COLD WATER PUMPING POWER, MWe	1.96
AMMONIA FEED PUMP POWER, MWe	0.24
HOTEL LOAD (PER 10 MWe)	0.11
MISCELLANEOUS, MWe	0.35
CHLORINATION	
MECHANICAL CLEANING	
INSTRUMENTATION AND CONTROL	
SUPPORT SUBSYSTEMS	

Figure 5.1-1. PSD II Power Budget – 10 MWe Power Module

PARAMETERS	EVAPORATOR	CONDENSER
WATER SIDE		
• "TUBE" ID, IN	0.75	0.75
• VELOCITY, FPS	6.42	6.05
• INLET TEMPERATURE, °F	82.0	40.0
• OUTLET TEMPERATURE, °F	77.91	44.19
• PRESSURE DROP, PSID	2.56	2.44
AMMONIA SIDE		
• INLET TEMPERATURE, °F	51.7	51.5
• OUTLET TEMPERATURE, °F	72.2	51.3
• PRESSURE DROP, PSID	1.46	0.39
OVERALL		
• HEAT TRANSFER AREA, FT ² *	245,700	245,700
• THERMAL DUTY, MBTU/HR	1,444	1,395
• MTD, °F	7.17	9.12
• OVERALL U, BTU/HR - FT ² - °F *	819.7	622.6

*REFERRED TO WATER SIDE

Figure 5.1-2. PSD II Heat Exchanger Assemblies - 10 MWe Power Module

PARAMETERS	WARM	COLD
TEMPERATURE, °F	82	40
VOLUMETRIC FLOW RATE, GPM	721,800	679,600
MASS FLOW RATE, LB/SEC	102,500	96,920
DUCT SIZE (ID BASED ON 6 FPS), FT	18.5	17.9
TOTAL PRESSURE DROP, FT	7.0	12.0
PUMP POWER, MWe	1.21	1.96
SHAFT HORSEPOWER, BHP	1,500	2,420

Figure 5.1-3. PSD II Water Supply and Discharge – 10 MWe Power Module

PARAMETERS	VALUE
AMMONIA VAPOR FLOW RATE, LB/SEC	764.0
AMMONIA VOLUMETRIC FLOW RATES, ACFS	
• TURBINE INLET	1690
• TURBINE OUTLET	2357
AMMONIA QUALITY, %	
• EVAPORATOR OUTLET	97.0
• PHASE SEPARATOR OUTLET	99.0
• TURBINE INLET	99.0
• TURBINE OUTLET	96.4
AMMONIA TEMPERATURES, °F	
• EVAPORATOR OUTLET	72.3
• SEPARATOR INLET	72.2
• TURBINE INLET	72.0
• TURBINE OUTLET	51.6
• CONDENSER INLET	51.5
AMMONIA PRESSURES, PSIA	
• EVAPORATOR OUTLET	134.0
• SEPARATOR INLET	133.9
• TURBINE INLET	133.4
• TURBINE OUTLET	92.0
• CONDENSER INLET	91.8
ENTHALPHY DROP ACROSS TURBINE, BTU/LB	18.6
PLANT EFFICIENCY (NET POWER/EVAPORATOR THERMAL DUTY), %	2.36

Figure 5.1-4. PSD II Ammonia Power Cycle – 10 MWe Power Module

COMPONENTS	EFFICIENCY PERCENTAGES
TURBINE	89
GENERATOR	97
SEAWATER PUMPS	
DRIVE	92.4
PUMP	87
OVERALL	80.4
AMMONIA FEED PUMPS	
DRIVE	90
PUMP	80
OVERALL	72

Figure 5.1-5. PSD II Major Component Efficiencies (Percent) – 10 MWe Power Module

Figure 5.1-4. The most significant state point conditions are also given. Assumed efficiencies of major components are shown in Figure 5.1-5.

5.1.2 Process Flow Diagram

The process flow diagram for the 10 MWe power module (Figure 5.1-6) is based on design tradeoffs and optimization studies further discussed in Section 5.2. This flow diagram is for the required design operating conditions of 82°F warm water and 40°F cold water. Module performance in summer (85°F warm water) and winter (78°F) has also been analyzed with TRW's off-design performance program (see details in Section 5.3). Key performance parameters are summarized in Figure 5.1-7.

Four modules in series form a subassembly and four subassemblies in parallel form the complete heat exchanger assembly. All subassemblies are shown in the flow diagram (E-1 through E-4 and C-1 through C-4). Ammonia vapor from each subassembly (nominally at 97 percent quality) is fed to one of four phase separators. In these separators, quality is increased to 99 percent or higher by impingement and cyclone action.

Four separators in parallel, rather than one common separator, (located after the main manifold) are used based on optimization analysis as well as pipe, valve and packaging considerations. One evaporator (and/or

Figure 5.1-6. 10 MWe Power Module Process Flow

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

PARAMETER	WINTER	NOMINAL	SUMMER
WARM WATER TEMP, °F*	78.	82.	85.
COLD WATER TEMP, °F*	40.	40.	40.
GROSS POWER, MWe	11.3	13.9	15.9
NET POWER, MWe	7.4	10.0	12.0
AMMONIA FLOW RATE, LB/SEC	706.	764.	808.
AMMONIA EVAP TEMP, °F	68.9	72.3	74.8
AMMONIA COND TEMP, °F	50.7	51.5	52.1
AMMONIA EVAP PRESSURE, PSIA	126.4	134.0	140.0
AMMONIA COND PRESSURE, PSIA	90.4	91.8	92.9
EVAP, BTU/HR-FT ² -°F †	814	820	824
COND, BTU/HR-FT ² -°F †	623	623	623
TURBINE EFFICIENCY, %	88.5	89.0	88.8

*CONSTANT FLOW RATE OF WARM AND COLD WATER

†BASED ON WATER SIDE AREA

Figure 5.1-7. Variation of Key Power Loop Performance Parameters with Season

condenser) can be out of service for maintenance without affecting separation efficiency. Below 80 percent of design flow, candidate phase separator designs rapidly drop in efficiency. Module performance under these conditions is predicted in Section 5.3.1.5.

The essentially dry ammonia flows to a four-stage double flow axial turbine of an Elliott design. The vapor manifolds, pipes and valves were selected and sized to cost-effectively minimize vapor side pressure losses. About 0.8 psi pressure loss is expected between evaporator and condenser.

Moderately wet ammonia (96.4 percent quality) from the turbine flows into the main condenser manifold located directly under the turbine. The ammonia is condensed in the condenser assembly and returned to the evaporator. Redundant ammonia feed pumps (not shown) are included.

5.1.3 Piping and Instrumentation Diagram (P&ID)

The piping and instrumentation diagram (Figure 5.1-8) shows the interconnections, piping, component items and instrumentation points for the power loop. P&ID's for ammonia support subsystem and the nitrogen support subsystem are shown in Sections 5.8.1 and 5.8.2.

Figure 5.1-8 also lists the nominal ratings and capacities of major system components, including the turbine generator and evaporator and

condenser subassemblies. The power loop components are further described in Section 5.1.5.

Interfaces with seawater pumps and other supporting subsystems, such as the ammonia supply, nitrogen supply, and vent and purification systems, are shown in Figure 5.1-8. The drawing is keyed to the equipment and line lists in Appendix I, Section 7.

5.1.4 General Arrangement

The 10 MWe power system module fits in the space aft of the moonpool in the OTEC pilot plant ship hull structure. Heat exchanger modules are approximately 20 feet wide, 14 feet high and 4 feet long (Length is parallel to the seawater flow direction). Sixteen of the basic modules form an evaporator assembly about 80 feet wide, 14 feet high, and 17 feet deep. (See Figures 5.1-9 and 5.1-10). Similar 16 basic condenser modules form a condenser assembly with the same dimensions.

Warm water is pumped into a reservoir and channeled to evaporator heat exchanger modules. Ammonia vapor from the evaporator modules flows through phase separators into collection header pipes and then to the turbine generator. The ammonia turbine exhaust discharges to a manifold which feeds the condenser heat exchanger modules located opposite the evaporator array.

The installation concept for the power system module provides easy access for maintenance as shown in Figures 5.1-11 and 5.1-12. The power loop ammonia piping is shown with line codes. Subsystem component reference designators are keyed to the P&ID drawing. Piping has long radius ells to minimize pressure drops and parasitic power losses. Weld joints minimize ammonia leaks. The small ammonia and nitrogen makeup and vent piping which do not impact the system arrangement, have been omitted from the drawings. Piping and equipment supports on the platform are detailed in Section 5.1.6. Space has been provided for turbine removal and for maintenance.

A complete set of preliminary design drawings and specifications describing the 10 Mwe power module and support subsystems and the 0.2 MWe test articles is provided in Appendix I.

Figure 5.1-8. 10 MWe Power Module P&ID

Figure 5.1-9. General Arrangement Plan

DESIGNED BY	DATE	REVISION	BY	APP
DESIGNED BY: P. J. BROWN				
DRAWN BY: P. J. BROWN				
CHECKED BY: P. J. BROWN				
APPROVED BY: P. J. BROWN				
PROJ. OFFICE: P. J. BROWN				
OTEC POWER SYSTEM DEVELOPMENT - II				
10 MW _e POWER MODULE				
GENERAL ARRANGEMENT				
ELEVATION				
FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY			6850.94-11	
ISSUE DATE: 5-9-79			CHG. LTR.	

Figure 5.1-10. General Arrangement Elevation

SECTION A-A
SCALE: 1/8" = 1'-0" RBR. 11

1/8" = 1'-0"
SCALE
0 5 10 15 20
FEET

PIPING PLAN
ELEVATION 48'-0" BELOW
SCALE: 1/8" = 1'-0"

DESIGNED BY: PEG BROWN	OTEC POWER SYSTEM DEVELOPMENT - II	LTR	DATE	REVISION	BY	APP
DRAWN BY: PEG BROWN						
CHECKED BY: R. J. BROWN						
APPROVALS						
M. K. H. H. H.						
PROJ. OFFICE: P. J. BROWN						
10 MWe POWER MODULE GENERAL ARRANGEMENT SECTION & PLAN.		FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY		DRAWING NUMBER 6850.94-13		
				ISSUE DATE 5-9-79		

Figure 5.1-11. General Arrangement Section

1/8" = 1'-0"
SCALE 0 5 10 15 20
FEET

DESIGNED BY: P. J. BROWN	OTEC POWER SYSTEM DEVELOPMENT - II	LTR	DATE	REVISION	BY	APP
DRAWN BY: P. J. BROWN	10 MW POWER MODULE GENERAL ARRANGEMENT SECTION	TRW				
CHECKED BY: P. J. BROWN		DRAWING NUMBER				
APPROVED BY: P. J. BROWN		6850.94-12				
ISSUED BY: P. J. BROWN		FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY				
DATE: 5-9-79		ISSUE DATE				
		5-9-79				

Figure 5.1-12. General Arrangement Section

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

5.1.5 Mechanical Design

This section covers the mechanical design of the end connections, ammonia piping, accumulator, phase separator, pump inlet strainer, shutoff valves, and relief valves.

5.1.5.1 End Connections

The ANSI 150# raised face flange with a Flexitallic, CGI Teflon impregnated gasket was selected for the end connection of the shutoff valves, relief valves, orifice plate, strainers and pumps. The instrument ports are 1/2-inch NPT sealed with teflon tape. The selected end connections meet the following design requirements:

- Leakage less than 1×10^{-4} cc per second
- Low repair costs
- Low initial costs
- Off-the-shelf design
- Easy to maintain
- Design pressure of 167 psig.

A butt weld end connection was considered for PSD II because it produces a leak-tight joint. However, the ANSI raised face flange was selected because of lower cost, easier maintenance, and simpler fabrication.

A butt welded butterfly valve costs four times more than an ANSI raised face flanged valve because it is not off-the-shelf.

Maintenance problems with a butt welded component are greater than with an ANSI raised face flanged component. For example, to service the large shutoff valves (such as a 42, 54 or 60-inch valve), either an access hole is needed in the line or the valve must be cut out of the line for servicing. With an access hole, it may not be possible to service the valve in place (such as changing the seals). Also, a leak-tight joint is not possible with an access hole. Smaller valves must be cut out of the line for servicing.

The weld stubs on the valves must be long to prevent heat damage to the soft seat or the metal portion of the seat during welding.

Discussions were held with several manufacturers of shutoff valves and relief valves including Posi-Seal, Keystone, and Anderson-Greenwood. They all recommended using the ANSI raised faced flanges for ammonia systems. Their experience shows an ammonia system has no leakage problems using this type of end connection. The manufacturers also stated that the butt weld in large valves is a new design and not an off-the-shelf item. Therefore, they would have to purchase new tooling and patterns.

According to the manufacturer of the Flexitallic gasket, the measured average leak rate through ANSI raised face flanges (ranging from 3 through 24 inches with pressures from 150 to 2,500 psig and using Flexitallic gaskets) is 1×10^{-5} cc per second of helium. The manufacturer recommended a surface finish of 150 to 200 μ inches RMS for the flanges and an asbestos impregnated with teflon for the Flexitallic gasket filler to obtain the best seals.

The design criteria for leakage through the flanges seeks to obtain a bubble tight joint. The 1×10^{-4} cc per second more than meets this criteria (0.15 cc = one bubble, ANSI B16.104, and bubble tight is a leak rate of $\approx 1 \times 10^{-3}$ cc per second).

5.1.5.2 Ammonia Piping

Codes used for ammonia piping include ANSI B9.1 (Safety Code for Mechanical Refrigeration), ANSI B16.5 (Steel Pipe Flanges and Flange Fittings), ANSI B31.3 (Chemical Plant and Petroleum Refinery Piping), and ANSI B31.5 (Refrigeration Piping). The design meets the requirements for a design pressure of 167 psig and a design temperature of -28 to 100°F. Ammonia velocity is optimized to minimize parasitic power losses.

Material Selection. Materials selected for the ammonia piping systems are conventional carbon steels commonly used in ammonia manufacturing plants. These materials are generally of the following types:

- ASTM, A106 GR B or C — grade B preferred for this design
- ASTM A333 GR 6
- ASTM 53 GR B
- ASTM A516 GR 70.

While some of these materials are limited to -20°F , the operating temperatures of the loop are between 50°F and 70°F . It may be possible to achieve a temperature as low as -28°F but to do so requires lowering system pressure to 14.7 psia (1 atmosphere). Full design pressure is permitted down to -20°F . However, the code (ANSI B31.3-1976, Chemical Process Plant and Petroleum Refinery Piping, Paragraph 323.2.2) allows for the lower temperatures as follows:

(c) Exceptions to Minimum Temperature Limits: Carbon, low alloy and high alloy steels may be used for piping at design temperatures not lower than -50°F without impact testing required by (a) or (b) above, if the operating pressure will not be more than 15 percent of the maximum design pressure at ambient temperature, and if the combination of longitudinal stresses due to pressure, deadweight and displacement strains (see 319.2.1) does not exceed 6,000 psi.

Material for the ammonia lines (Figures 5.1-13 and -14) was selected for its compatibility with ammonia and its adequate stress value. The allowable working stress is 15,000 psi. The material is good for a temperature range which covers the ammonia lines working range of -28°F to $+100^{\circ}\text{F}$. The ANSI B31.5 code formula was used to determine the wall thickness of the ammonia lines. A corrosion thickness of 0.125 inches was added to the calculated wall thickness of the ammonia lines to determine total wall thickness. Lines sizes, calculated wall thickness, actual wall thickness and actual velocity are given in Appendix I, Section 7.

Ammonia piping is steel unless otherwise specified. Only piping which directly interfaces with the aluminum heat exchangers is of aluminum. Electrical isolation is provided at flanges connecting aluminum and steel.

Design Pressures. The maximum ammonia pressure is 151.7 psig. This pressure corresponds to a saturation temperature of 85°F , which is the maximum seawater temperature and the temperature ammonia reaches in a no-flow condition. The design pressure of the piping is the set pressure of the relief valves which is 10 percent above the maximum operating pressure of 167 psig.

Ammonia Line Sizing. The velocity to size the main loop ammonia liquid was taken from an optimization study done for PSD-I.

COMPONENTS	REQUIREMENT
GENERAL	
MAXIMUM PRESSURE RATING	275 PSIG AT 100°F
MINIMUM TEMPERATURE	-28°F
PIPE	
MINIMUM 1/8 INCH THROUGH 6 INCHES	ASTM A53, GRADE B, OR A106, GRADE B, SCHEDULE 40, SEAMLESS OR ELECTRIC-RESISTANCE WELDED.
8-INCHES THROUGH 42 INCHES	ASTM A53, GRADE B, OR A106, GRADE B, SCHEDULE 20, SEAMLESS OR ELECTRIC-RESISTANCE WELDED
GREATER THAN 42 INCHES	ASTM A53, GRADE B, OR A106, GRADE B ELECTRIC-RESISTANCE WELDED, THICKNESS PER ANSI B 31.5
FITTINGS	
1-1/2 INCHES AND SMALLER	ASTM A105, ASA B16.11, 2000 LB, SOCKET WELD
2 INCHES AND LARGER	ASTM A234, GRADE B, ASA B16.9, STANDARD WEIGHT, BLACK, BUTT WELD (LONG RADIUS ELBOWS)
FLANGES	ASTM A181, CLASS 70, B16.5 150 LB, WELD NECK, RAISED FACE WITH CONCENTRIC SERRATIONS. FINISH SHALL BE BETWEEN 150 AND 250 μ INCHES RMS. BORE TO MATCH PIPE ID
GASKETS	FLEXITALLIC, STYLE CGI, ASBESTOS IMPREGNATED WITH TEFLON
BOLTS	ASTM A183, GRADE B7, ASA B18.2
NUTS	ASTM A194, GRADE 6, ASA B18.2 HEAVY, SEMI-FINISHED HEXAGONAL
PROTECTIVE COATING FOR EXTERIOR SURFACES	SURFACE PREPARATION: SSPC-SP6 PRIME AND FINISH COATING: SSPC-PA-1

Figure 5.1-13. Piping Specification E – Steel

Optimum velocities in the liquid lines are based on trade-off of the parasitic pumping power cost and the cost of piping and valves. Parasitic pumping power cost was determined for 30 years and added to line costs, giving the total cost for a given line size and velocity, Figure 5.1-15. This total cost was determined for several velocities and pipe sizes from which the optimum velocity was about 6 feet per second for the ammonia liquid. Vapor velocity is about 40 feet per second. The equations for determining line size, thickness and velocity are given in Appendix II, Section 4. The line list is given in Appendix I, Section 7.

Purge, vent, fill and drain line sizes are based on having one hour to complete the operation. Since the velocities are not critical, main loop ammonia design velocities of 10 feet per second for liquid and 60 feet per second for vapor were used.

COMPONENTS	REQUIREMENT
GENERAL	
MAXIMUM PRESSURE RATING	275 PSIG AT 100°F
MINIMUM TEMPERATURE	-28°F
PIPE (12 INCHES AND LARGER)	ASTM B 241, ALLOY 5083, TEMPER 0, THICKNESS PER ANSI B 31.5, SEAMLESS OR ELECTRIC-RESISTANCE WELDED
FITTINGS (12 INCHES AND LARGER)	ASTM B 361, ALLOY 5083, TEMPER 0, ASA B 16.9, STANDARD WEIGHT, BUTT WELD (LONG RADIUS ELBOWS)
FLANGES	ASTM B 361, ALLOY WP 5083, TEMPER 0, ASA B 16.5, 150 LB, WELD NECK, RAISED FACE WITH CONCENTRIC SERRATIONS. FINISH SHALL BE BETWEEN 150 AND 250 μ INCHES RMS. BORE TO MATCH PIPE ID
GASKETS	FLEXITALLIC, STYLE CGI, ASBESTOS IMPREGNATED WITH TEFLON
BOLTS	ASTM A 193, GRADE B7, ASA B18.2
NUTS	ASTM A 194, GRADE 6, ASA B18.2 HEAVY, SEMI-FINISHED, HEXAGONAL
PROTECTIVE COATING FOR EXTERIOR SURFACES	SURFACE PREPARATION: SSPC-SP6 PRIME AND FINISH COATING: SSPC-PA-1

Figure 5.1-14. Piping Classification F – Aluminum

Figure 5.1-15. Sum of Capitalized Cost NH₃ Pump Power Plus Piping Plus Values Versus Liquid NH₃ Pipe Velocity

The condenser piccolo tube size is based on a flow rate large enough to allow vapor contained in a condenser module to be removed in one hour. The same piccolo tube is used in the evaporator for removing non-evaporables. The piccolo tube in the condenser is above the liquid level. The piccolo tube in the evaporator is as close to the bottom as possible. The piccolo tube is a 2-inch schedule-40 pipe with two rows of 1/8-inch holes on 2-inch centers. Calculations for sizing the piccolo tube are given in Appendix II, Section 4.

5.1.5.3 Accumulator

There are traces of noncondensibles and ammonia vapor in the ammonia liquid as it leaves the condenser. The accumulator separates these noncondensibles and ammonia vapor from the ammonia liquid before it enters the feed pump.

In the accumulator tank which is a vertical cylinder, the liquid flows down and out the bottom. The tank is sized so that the velocity of the liquid is small enough to allow large bubbles to flow up and out of the top of the cylinder.

The design meets the accumulator requirements:

- Maximum bubble size passing through the accumulator is 0.25 inches
- Accumulator is designed to ASME Boiler and Pressure Vessel Codes, Section VIII, Division 1
- Design pressure is 167 psig.

To size the accumulator, we assumed a steady-state rise velocity by equating drag force on the bubble to the buoyant force. Then, the required velocity of the liquid flowing down through the accumulator can be computed. The accumulator size is computed by using this required velocity in the standard pipe sizing equations. The analysis, for sizing the accumulator is given in Appendix II, Section 4.

The critical need for the accumulator tank will be during the initial startup when there is a large amount of ammonia vapor and noncondensibles in the liquid portion of the system. The accumulator will return this ammonia vapor and noncondensibles to the inlet of the condenser by means of the vapor return line where the ammonia vapor can be condensed and the noncondensibles removed from the system by the piccolo tube.

The 0.2 MW test loop will have a bypass line around the accumulator so that by closing one valve and opening a second valve the ammonia flow can be bypassed around the accumulator. In this way the need for the accumulator can be verified.

5.1.5.4 Phase Separator

The phase separator is a completely enclosed, cylindrical assembly installed on the outlets of each evaporator subassembly and is required to increase the quality of the ammonia vapor.

The proposed phase separator is of centrifugal type and has no moving parts. The unit is installed in the vertical position with the inlet on the side and the outlet on the top. The port on the bottom is the drain for the liquid return. A candidate design is shown in Figure 5.1-16, courtesy Anderson IBEC.

Figure 5.1-16. Anderson IBEC Separator (Model LUS-42-150)

The design meets the phase separator requirements:

- Exit quality of ammonia vapor greater than 99 percent
- Nominal flow rate of ammonia = 764 lbs/sec
- Phase separator designed to the ASME Boiler and Pressure Vessel Codes, Section VIII, Division 1
- Maximum operating pressure 167 psig
- Liquid particle distribution as shown in Figure 5.1-17.

The phase separator increases the ammonia vapor quality from about 97 percent to more than 99 percent for the range of flow conditions:

- Minimum flow - 706.1 lbs/sec
- Nominal flow - 764.0 lbs/sec
- Maximum flow - 808.2 lbs/sec.

Figure 5.1-17. Ammonia Liquid Particle Size Distribution

The mist from a heat exchanger deaerator tray typically has a mean particle size of 15 to 40 microns. Typical particle size distribution (based on Linde's experience) is shown in Figure 5.1-17. Six percent of the entrained particles by weight are 5 microns or less and 30 percent of entrained particles are 10 microns or less. Since there is no experimental data for the enhanced plate type evaporator, it is estimated that the distribution of particles will be similar to that shown in the figure.

The internal blades of the phase separator are 304 stainless steel and the body is carbon steel. The corrosion allowance for the body is 1/8 inch.

The unit is designed for a maximum operating pressure of 167 psig and a temperature range of -28°F to 100°F .

5.1.5.5 Pump Inlet Strainer

Each of the two ammonia feed pumps has an inlet strainer to protect the impeller from foreign particles in the ammonia lines. The strainer filters out particles that are 500 microns in size or greater; this is the largest particle size the pump can safely pass without damage to the impeller.

The strainer is of the cone type with flanges on the ends for easy removal and cleaning. The material of the body is the same as for the main ammonia lines and the screen material is 304 stainless steel.

The maximum pressure drop through the strainer clean is 0.25 psi when flowing the maximum ammonia flow rate. Strainer specifications are given in Appendix I, Section 7.

5.1.5.6 Control Valves and Shutoff Valves

Shutoff Valves. Butterfly shutoff valves are used in the ammonia loop. This type of valve was selected because it offers the lowest cost and is easier to maintain than gate or plug valves. Gate valves have the lowest pressure drop of any of the three types of valves ($K \approx 0.20$ velocity heads). However, the closing force is large. Also, actuators for larger valves require a special support structure. For example, the actuator for a 60-inch gate valve with a manual actuator is more than 13 feet tall when open. Plug valves cost more than butterfly valves and the pressure drop is much greater ($K \approx 0.80$ velocity heads for plug valves and $K \approx 0.40$ velocity heads for the butterfly valves).

Sealing quality also was considered in valve selection. Butterfly valves provide a tight seal during shutoff. The valves have no detectable leak past the seal during shutoff when pressurized with the working fluid to the maximum operating pressure of 167 psig.

The body of the valves are carbon steel with 316 stainless steel trim. The seat material is teflon.

The actuator, if needed, will be pneumatic and requires 100 psig air. All valves have limit switches for both the open and closed position.

Valve specifications are given in Appendix I, Section 7.

Control Valves. The two control valves are in the ammonia loop: emergency trip valve ahead of the turbine and the bypass valve around the turbine.

The trip valve is an 88-inch diameter butterfly valve to match the turbine inlet size. It has been placed as close to the turbine as possible to minimize the maximum overspeed of the string. The bypass valve is a 30-inch diameter butterfly valve with proportional control so it can be used in the startup phase.

It is desirable to have the trip valve closed quickly in case of turbine overspeed. But if it were to slam shut, the valve seat would be damaged. Valve vendors have reported that state-of-the-art closing time for this size of valve is 0.5 seconds. One method of solving the closing problem is to have the valve close quickly until it is only a few degrees open and then ease it completely closed.

The bypass valve can fully open in one second or less during an emergency trip. This action diverts the ammonia around the turbine. The bypass valve also has a tight shutoff to prevent bypassing the ammonia around the turbine during normal operation.

Relief Valves. Relief valves for the liquid lines and components are sized in accordance with the Coast Guard Manual CG-115, Section 54.15-15. Vapor relief valves are sized using ANSI B9.1, Section 10.5. The set pressure of the relief valve is 10 percent above the maximum operating pressure.

Relief valve inlet and outlet lines are sized using a liquid velocity of 10 feet per second and a vapor velocity of 60 feet per second.

The locations of the relief valves meet ANSI B9.1. Any component or portion of the ammonia piping system which can be isolated from the rest of the system by shutoff valves is protected by a relief valve.

The analysis for sizing the relief valves is shown in Appendix II, Section 4, and the specifications are in Appendix I, Section 7.

5.1.6 Structural Design

The proposed plant layout (see Figures 5.1-9 and 5.1-10) provides structural support for all power system components and piping. Final definition of structural support and plant layout requirements requires coordination with the ship system contractor. During detailed design, all modifications required by the ship system contractor will be incorporated.

Existing standards for structural design were used as the basis for the preliminary stress analysis. Structural elements are designed to withstand all loads encountered during the plant's service life. The design of structural steel elements is based on design procedures established by the American Institute of Steel Construction (AISC), "Specifications for the Design, Fabrication and Erection of Structural Steel for Buildings" (1969 edition) using ASTM A572 Grade 55 as the basic material. The design of reinforced concrete elements is based on the strength design method established by the American Concrete Institute (ACI) contained in "Code Requirements for Reinforced Concrete (ACI 318-7.)" and related 1974 supplements. Structural concrete is assumed to be 8,000 pounds per square inch at 28 days. Reinforcing is assumed to conform with ASTM A615-75, Grade 40. All power system weights not known at the time of the preliminary stress analysis were estimated by standard engineering practices.

A detailed dynamic analysis of the structural system supporting the piping layout was not performed for the preliminary design. All dynamic loads are accounted for as equivalent static loads by applying the accelerations (load factors) specified by DOE. The dynamic load factors presented in Figure 5.1-18 for the operational and survival modes have been considered in the design and analysis. Dynamic loads are expressed as multiples of gravitational accelerations (g). In the operational mode (sea state 6 and

less), tanks are empty but piping, heat exchangers and water troughs are full. The analysis assumes that structural steel remains in the elastic range. Concrete members are designed for minimum strength established by ACI specifications for ultimate strength design.

DYNAMIC LOAD FACTORS	DESIGN STATE	
	OPERATIONAL (g)	SURVIVAL (g)
HEAVE	0.3	0.5
SURGE	0.15	0.5
SWAY	0.15	0.5

Figure 5.1-18. Equivalent Dynamic Accelerations

In the survival mode (sea state 7 to 9), tanks are assumed to be full but piping, heat exchangers and water troughs would be empty. Steel members are designed so that member stresses are less than the basic yield stress of the metal. The ultimate strength of concrete members is established by procedures similar to that for the operational mode.

The preliminary stress analysis concentrated on the integrity of the general structural system for the major OTEC power plant components. These major components include ammonia piping and supports, heat exchangers (evaporators and condensers), and the turbine-generator. All interfaces between the ship's system and power system contractors have been identified.

5.1.6.1 Ammonia Piping and Supports

For the piping system, we have tried to optimize design features (flexibility and operational space) while minimizing overall OTEC plant costs (platform hull and power system). A piping flexibility analysis was conducted to assure that piping material does not fail and that anchor structures are not overstressed. All stresses in the piping system are below the minimum allowable stresses stipulated in U. S. Department of Transportation Coast Guard Marine Engineering Regulations (CG-115) and applicable portions of the American National Standard Code for Pressure Piping-Power Piping (ANSI B31.1.1).

The piping system was analyzed for extreme line temperatures (between minus 28°F to plus 100°F) that could occur during shutdown emergency conditions. The power plant's normal operating temperature results in very small expansion or contraction movements and stresses since line temperatures (between 36°F to 85°F) are close to ambient conditions.

All final piping configurations and support details require coordination with the ship system contractor. Typical supports are shown in Figures 5.1-9 through 5.1-12. Locations and sizes ensure that adequate space and clearances exist for operations and maintenance equipment.

Piping that connects with the turbine-generator requires restraints and supports to minimize external loadings (weight, thermal expansion or contraction stresses, and dynamic loads due to platform hull motions) on the turbine-generator. Excessive loads can upset the sensitive balance of the turbine-generator rotor resulting in inefficient operations, excessive displacements at the expansion joints (with increased possibility of leakages), and undesirable vibrations of the turbine deck platform support structure.

A detailed dynamic analysis of the piping system was not performed for preliminary design. Data from the PSD-I stress analysis was used directly, to determine piping layout. Space is provided so that mechanical shock arrestors or additional guided restraints can be added as required to restrain dynamic stresses resulting from platform hull motions (roll, sway, yaw, pitch and heave).

A dynamic analysis of the final piping system must be performed during detailed design after the range of platform hull motions has been determined. Piping system vibrations must be controlled. If excessive, they result in flow pulsations leading to noisy operations and increased flow turbulence with fluctuations in heat transfer rates, larger pressure drops, erosion and impaired flow machine, valve, and other component performance. The analysis also will insure that dynamic stresses do not damage or cause leaks at critical joints and seals.

5.1.6.2 Turbine-Generator Platform

The turbine-generator platform deck consists of structural steel beams supporting a concrete slab-metal deck. The structural members support the turbine-generator, phase separators and all related manifold piping.

The turbine-generator support system must be sufficiently rigid to permanently hold the machine and to prohibit resonant vibrations at start-up and operating speeds. Platform hull motions (wave motions) impose larger deflections on the turbine-generator support system than are normally experienced on dry land. The platform hull, which is more rigid than the turbine-generator supporting structural system, imposes cyclic platform hull motions on the support system. Stresses in the members as well as deflections of the supporting structure in the vertical and horizontal directions must be considered.

The main turbine-generator platform support members are required to span the 81-foot distance between ship station lines B and F. This is a long span considering the heavy loads and structural rigidity requirements of the platform. The compactness of the power plant in the platform hull does not allow space for columns to reduce span lengths. Therefore, the main platform structural members require special design, e.g. vierendeel trusses. Because of long spans and stiffness requirements, the vierendeel truss is one of the most efficient structural support member for the platform.

Truss load carrying capacity and structural stiffness are developed using the bending resistance of short heavy members. Truss member structural sizings and spacings have been chosen to provide adequate support for the turbine-generator. Adequate clearances are provided for the final power system equipment and piping layout. Components of the structural support system were analyzed to insure that resonant vibrations do not occur during plant start-up and operation.

Truss and floor framing details are shown in Figure 5.1-19. Locations of structural members were shown in Figure 5.1-9 through 5.1-12. Member locations and sizes have been selected to insure the structural framing system is developed around the piping system and equipment locations. Adequate clearances are provided.

Figure 5.1-19. Turbine Deck Support

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

The overall truss dimension is 86 feet, which includes attachment with platform hull structural walls. Truss end members can be bolted to insert plates imbedded into the concrete platform hull walls with bearing and vibrational supports provided by a corbel. Final truss dimensions, member sizes and platform hull attachment details require coordination with the ship system contractor.

Analysis of the structural system indicates that resonant vibrations will not occur during turbine-generator operations. The total estimated maximum deflection is less than two-tenths of an inch. While this is greater than that experienced by turbine-generators on dry land, the turbine-generator subcontractor indicates that this deflection will not affect turbine operations as long as resonant vibrations do not occur. During detail design, camber could be added to the truss to minimize deflection.

The concrete slab is bonded mechanically to the top flanges of the structural steel members. A typical attachment detail is shown in Figure 5.1-19. It forces a portion of the slab to act with the floor members, resulting in a concrete-and-steel T beam. This type of floor system efficiently supports heavy floor loads and is desirable because of the high degree of rigidity gained for supporting the turbine-generator. Use of a composite (concrete and steel) structural floor system results in savings of 20 to 30 percent in steel tonnages and in erection costs.

Composite action between the concrete and steel is developed by welding shear studs (through the metal decking) to the top flange of the structural members. The shear studs develop the horizontal shear between the floor beams and concrete slab. Metal decking supports the concrete between structural steel members and provides a rigid horizontal element for transmitting lateral loads into the platform hull structural walls. Lateral loads result from platform hull motions and turbine-generator vibrations.

A composite floor system also simplifies connections with a concrete platform hull. Steel beams can be bolted to insert plates imbedded into the concrete platform hull walls with bearing and vibration supports provided by a corbel. Horizontal shear loads can be transferred through the concrete slab-metal decking system by embedding dowels into

the platform hull walls. A typical attachment detail is shown in Figure 5.1-19. Final member sizes, locations and platform hull attachment details require coordination with the ship system contractor.

The phase separator tanks (tank numbers T-1 through T-4) are located below the turbine deck floor as shown in Figure 5.1-10. To laterally support the separators, a vertically guided bracket is attached to the transverse members of the turbine deck. The support brackets allow for vertical expansion and contraction of the piping system and provide lateral resistance for loads associated with platform hull motions. Removable grating in the platform area above the tanks permits easy access to the tanks during plant operations.

A detailed dynamic analysis of the turbine-generator platform is required during final design. The possibility of damage to equipment or the structure support system makes it imperative to avoid excessive deflections and resonant vibrations during operations of the OTEC plant. Final design and analysis requires coordination with the ship system contractor to include platform hull motions in the structural analysis. The final analysis for the turbine-generator support system must include effects of platform hull motions.

5.1.6.3 Heat Exchanger Supports

The heat exchanger structural support consists of a framing structural steel system of beams and girders to support the following power plant components:

- Condensers (numbers C-1 through C-4)
- Evaporators (numbers E-1 through E-4)
- Cold and warm seawater troughs
- Effluent discharge plenum
- Separator tanks
- Piping.

The structural framing plan is shown in Figure 5.1-20. Member locations and sizes (Figures 5.1-9 through 5.1-12) were selected to insure that the support framing system could be developed around the piping system and equipment locations. Adequate clearances are provided.

HEAT EXCHANGER SUPPORT PLAN - ELEVATION 46'-0
SCALE: 1/8" = 1'-0"

1/8" = 1'-0"
SCALE
0 5 10 15 20
FEET

NOTES:

1. ALL STRUCTURAL STEEL SHALL BE STANDARD ROLLED SHAPES AND PLATE, AND SHALL BE CONSTRUCTED USING ASTM A572, GRADE 55 AS THE BASIC METAL.
2. ALL CONCRETE SHALL HAVE A 28 DAY COMPRESSIVE STRENGTH OF 8,000 PSI.

SECTION (ROTATED 90°) NTS
B 15

DESIGNED	DATE	REVISION	BY	APPD
DRWN RCB				
CHECKED LDM				
APPROVALS				
PROJ OFFICE				
OTEC POWER SYSTEM DEVELOPMENT-II				
10 MW _e POWER MODULE				
EVAPORATOR & CONDENSER SUPPORTS				
PLAN & DETAILS				
FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY			DRAWING NUMBER	
			6850.94-15	
			ISSUE DATE	CHK LTR
			5-9-79	

Figure 5.1-20. Evaporator and Condenser Supports

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

Platform hull space allocations for the lower deck plant layout necessitated long clear spans for heat exchanger support members. Lower deck piping obstructions such as walls and columns, must be minimized. Clearing obstructions requires additional pipe lengths and elbows that decrease power plant efficiency and increase costs.

Structural support members must be specially fabricated open-web expanded girders. Open-web girders are efficient support of heavy loads with long clear spans. Opening up a standard rolled beam increases its section modulus and moment of inertia, resulting in greater strength and rigidity for the same unit weight of the members. The open-web expanded beam is made economically by flame cutting a standard rolled beam's web in a zig-zag pattern along its centerline. Oxygen flame cutting of the beam web is relatively easy on a template equipped machine. One of the two equal halves is then turned end-for-end and is welded (a semi-automatic process is most often used) to the other half. The result is a deeper, stronger and stiffer beam than the original. Openings in the webs route piping and heat and ventilating ducts. The attachment of the beam to a concrete platform hull wall is similar to that described for the turbine-generator platform structural members.

The ship system contractor will supply the design for the warm and cold seawater troughs. Support for the water troughs will be provided through open-web girders. The present configuration (see Figure 5.1-11) assumes that structural stub columns are provided between the water trough and the girders. Final details require coordination with the ship system contractor and depend on final trough design.

The structural framing system uses the effluent discharge pipe as a load carrying member. The pipe must be able to resist all tributary loads from the framing system. In the present design configuration, the discharge pipe is constructed of concrete. However, the structural configuration does not change significantly if the pipe is constructed of another material, such as steel. To meet strength requirements, the concrete wall must be 2-feet, 6-inches thick. Attachment of the structural members requires that corbels be formed in the discharge pipe. The platform hull bottom may require additional strength at the discharge penetration. This

will be studied in detail during final design. Final design of the discharge pipe and the connecting framing system require coordination with the ship system contractor.

Special built-up frames are required to support the heat exchangers. Frames are shown in Figure 5.1-21. Frames are attached to the top flanges of the open-web girder. Corbel supports are required along the ship walls and at the discharge pipe (see Figure 5.1-20).

5.1.7 Electrical Design

The electrical subsystem design meets the following requirements:

- Delivers 10 MWe net power to an external base load
- During startup, energizes auxiliary loads from an external start-up power source
- Provides synchronized coupling of the turbine-generator to the electrical subsystem and provides controlled transfer of electrical load to the turbine-generator
- Provides synchronized coupling of external base load to the electrical subsystem and provides for the controlled assumption of its full load
- Provides for the energization of critical loads when both the turbine-generator and the startup power source are down
- Assures maximum flexibility for the operation and testing of the OTEC system and its subsystems
- Assures safe operation for personnel and equipment
- Cost-effectively performs all of the above tasks.

5.1.7.1 Primary Power Distribution and Control

To satisfy the design requirements, a 4.16 kV split bus system is used to distribute and control primary power (see Figure 5.1-22). Distribution and control of primary power are handled by the 5 kV rated switchgear, its power circuit breakers and its control and instrumentation devices are shown in Figures 5.1-22 and 5.1-23.

Figure 5.1-22. Electrical Distribution Single Line

Figure 5.1-23. 5 kV Switchgear General Arrangement

Major components of the electrical subsystem are:

- System load
- Turbine-generator
- Startup power source
- 480 V subsystem including auxiliary and critical loads (see Figure 5.1-24)
- Seawater pump drives.

The system load and turbine-generator are supported by Bus A. The last three components are supported by Bus B. Buses A and B can be operated independently to permit OTEC power system testing. They can also be tied together by the tie power circuit breaker for normal OTEC system operation.

The primary distribution system is equipped with standard protective relaying to assure personnel and equipment safety. The protective relaying is shown in Figure 5.1-22. All power circuit breakers are tied to instantaneous, time overcurrent and ground fault current protection schemes. Power circuit breaker No. 4 provides additional transformer and associated feeder protection. Power circuit breaker No. 3 assures correct phase rotation and phase matching of the startup power source and the electrical subsystem and provides system under-voltage protection. Where the possibility of reverse current flow exists, reverse power circuit power overcurrent protection is provided.

Power circuit breakers No. 1 and 2 provide reverse power protection. Time and current characteristics are coordinated to assure selective tripping and isolation to the fault. This coordination also is provided with external electrical subsystems protective schemes, including system load, startup power source, and the sea water pumps electrical subsystem. Power circuit breakers are interlocked to prevent any undesirable configuration of the power flow, such as connecting two non-synchronized power sources.

The primary distribution system is equipped with metering and instrumentation. Metering is used for routine operation. Instrumentation is tied to a data acquisition system to assess system performance and show system status. Both metering and instrumentation are shown in Figure 5.1-22.

All 4.16 kV branch circuits are supplied with current metering. The system load and generator branch circuits are also supplied with power factor, watt, var and watthour metering.

For remote display and recording in the control room, transducers generate electrical parametric analog signals and power circuit breaker auxiliary contacts provide breaker status information. The transducers and the auxiliary contacts are part of the 4.16 kV switchgear. Display and recording of information supplied by these devices is part of the instrumentation and control subsystem. The transducers provide system voltage and frequency information as well as watt and var information for each of the 4.16 kV system load, generator and startup power source branch circuits and the auxiliary loads 4.16 kV bus.

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

The electrical subsystem design permits the following modes of operation:

- Normal operation of the OTEC system with the turbine-generator energizing the system load, the auxiliary loads and the critical loads
- Transfer to 480V shipboard power for operating critical loads when both the OTEC system and the grid-startup power source are down
- Independent operation and test of auxiliary loads using startup power only
- If the 10 MW is in a small grid and requires an external startup source, the following mode is needed: simultaneous independent operation and test of auxiliary loads and startup power source and independent operation of the turbine-generator and system load.

Synchronization and power transfer are handled by the synchronizing panel, its associated potential transformers, and respective power circuit breaker.

During startup, power circuit breakers No. 3, 4, 5 and 6 are closed and power circuit breakers 1 and 2 are open. Thus, the 480V auxiliary loads as well as a set of the cold and warm sea water pumps can be energized by the startup power source while the turbine-generator and the system load are kept isolated. The synchronizing panel monitors Bus B (startup power source and auxiliary loads) and the turbine-generator voltages, frequencies and the phase sequences. When the voltages are equal and in phase, the frequencies are stabilized and power circuit breaker No. 2 is closed. This ties the turbine-generator to the electrical subsystem.

By the appropriate excitation and throttling of the startup power source and turbine-generator, energization of the auxiliary loads is transferred from the startup power source to the turbine-generator. After the load transfer, circuit breaker No. 3 is opened to complete the transfer of the auxiliary loads from the startup power source to the turbine-generator. The auxiliary power source is now removed.

To complete the system startup, the turbine-generator is used for starting the second set of cold and warm sea water pumps. To couple the system load to Bus A (turbine-generator), the synchronizing panel monitors the system load and Bus A voltages, frequencies and the phase sequences.

Circuit breaker No. 1 is closed when the system load and Bus A voltages are equal and in phase. This ties the system load to the electrical subsystem.

The tie power circuit breaker No. 6 can also be part of a synchronizing scheme. This breaker and the synchronizing panel can be used to tie two power sources when the turbine-generator energizes partial system load and the startup power source independently energizes the 480V auxiliary loads and a set of cold and warm sea water pumps. During this condition, power circuit breakers No. 1 through 5 are closed and No. 6 is open. In this case, the synchronizing panel monitors the voltages, frequencies and phase sequences of Bus A (system load and turbine-generator) and Bus B (startup power source and auxiliary loads).

Power circuit breaker No. 6 is closed when the voltages are equal and in phase. This ties Buses A and B together. By the appropriate control of the excitation and throttling of the turbine-generator and startup power source, the auxiliary loads can be transferred from the startup power source to the turbine-generator with the turbine-generator also energizing the system load. Power circuit breaker No. 3 is open after the load transfer is completed, removing the startup power source.

5.1.7.2 480 V System

Figure 5.1-24 shows the single line diagram and general arrangement of the 480 V motor control center as well as:

- Motor full load current data based on motor horsepowers and Table No. 430-150 of the National Electrical Code
- Other full load current data based on kVA or kW ratings
- Total full load current and total apparent power (kVA)
- Critical loads full load current and apparent power (kVA).

The critical loads need to be operated when both the startup power source and the turbine-generator are down. Some of these loads are part of the ammonia handling and nitrogen handling systems, the generator auxiliaries, the tube cleaning machine, and control and instrumentation circuits. When the turbine-generator and the startup power source are both down, the automatic transfer switch transfers to the vessels 480 V power system to energize the critical power source and its feeder for

the critical loads only rather than sizing for the full connected load of the motor control center. The automatic transfer switch and its interlock to the nonessential breakers are shown in Figures 5.1-22 and 5.1-23.

Based on the data shown in Figure 5.1-23, a 1,500 kVA dry type power transformer was selected to feed the 480 V motor control center. A dry type enclosed self-ventilated transformer was selected rather than silicon fluid filled because its characteristics make it more suitable for sea-state conditions. It is lighter, requiring less platform seawater displacement. It has no insulating fluid sloshing as well as minor maintenance and cost advantages.

5.1.7.3 Seawater Pumps System

The seawater pumps system is government-furnished. Sections 5.3.2 and 4.4 show that fixed-speed (uncontrolled) pumps are satisfactory. Therefore, for the design of the electrical subsystem, some assumptions were made regarding their electrical system. It is assumed that the seawater pumps are driven by squirrel cage induction motors. Based on the brake horsepower requirements of these drives, 900 HP motor size is assumed for each of the two warm water pumps and 1,500 HP motor size is assumed for each of the two cold water pumps.

The voltage level of 4.16 kV is based on Figure 2.5 of the IEEE, Handbook No. 141, Reference 5-1, Figure 2.5 in that reference shows 460, 2,300, and 4,160-volt cost curves for induction motors, control and appropriate system cost as a function of motor horsepower.

5.1.7.4 Generator Short Circuit Power Capacity and System Voltage

The approximate short circuit duty for a 10 MWe net output OTEC station is 90 MVA. The short circuit interrupting rating of the switchgear must be above the 90 MVA short circuit duty. A 5 kV class switchgear is available with a nominal 75, 250 or 350 MVA interrupting capacity. Therefore, 5 kV class switchgear with 250 MVA short circuit interrupting rating was selected for the implementation of the power distribution scheme.

5.1.7.5 Startup Power

For the OTEC power module to produce power, its auxiliary loads must first be started and operated from a startup power source. For bootstrap startup, the major auxiliary loads are:

- One cold seawater pump motor, 1,500 HP (assumed)
- One warm seawater pump motor, 900 HP (assumed)
- Ammonia feed pump motor, 400 HP.

This section addresses inrush current. Section 5.4 addresses steady state loads during startup.

In the baseline design where PSD-II is connected to a grid, the start-up power source is the grid itself providing power through a transformer and switchgear. If PSD-II is an isolated plant, the startup source could be a nearby OTEC plant, a startup barge or the ship's own generators using the low-power startup scheme described in Section 2.2.5-8 of Reference 5-2.

For sizing the startup power source, only the inrush current of one set of seawater pumps was considered. It was assumed that these pumps are driven by induction motors using auto-transformer type reduced voltage starting to reduce the startup inrush from about 6 to 2.3 times normal running kVA. The 6 to 2.3 ratio reduction (due to reduced voltage starters) permits a proportional reduction in the size of the startup switch gear. It is recommended that the startup cabling be sized to limit the inrush caused voltage drop to a maximum of 10 percent. Larger than 10 percent voltage drop may cause relays or contractors to drop out. It also may cause motors to slow down, stall or fail to accelerate or to interfere with voltage sensitive devices.

Of the four options shown in Figure 5.1-25, Option D is the recommended choice for the OTEC power system starting.

5.1.7.6 Power Wiring and Conduiting

The power wiring and conduiting in Figures 5.1-22 and 5.1-23 are based on:

- Calculated full load currents or National Electrical Code Motor Currents Table No. 430-150
- National Electrical Code, Article No. 430, for motor feeders
- Safety factor of 1.25
- National Electrical Code, Table No. 310-16, 75°C rated insulation for 600 V rated (480 V service) feeders

OPTIONS	MAXIMUM PERCENT VOLTAGE DROP	REDUCED VOLTAGE STARTING	ACROSS- THE-LINE STARTING	START-UP POWER SOURCE SIZE (MVA)
A	15	NO	YES	12
B	15	YES	NO	3
C	10	NO	YES	18
D	10	YES	NO	6

Figure 5.1-25. Startup Power Options

- National Electrical and Code, Table No. 310-43, for 5 kV rated (4.16 kV service) feeders
- National Electrical Code, Table No. 3A, for conduit sizing.

5.1.7.7 Electrical Equipment Room

The electrical equipment room plan is shown in Figure 5.1-26 for a 10 MWe system. The equipment arrangement and the sizing of the electrical equipment room are based on the following design considerations:

- Keep interequipment power feeders as short as practical
- Provide space around equipment necessary for maintenance (e.g., removal of draw-out devices from switchgear or motor control center)
- Comply with National Electrical Code, Article No. 450, for power transformer installation requirements.

The openings required for conduiting and wiring access to other areas of the facility are shown in Section 5.1.8. The connections to the Control Room and the cable tray layouts are discussed in Section 5.4.9.

5.1.8 Critical Interfaces

5.1.8.1 Physical Interfaces

The physical interfaces shown in Figures 5.1-27 and 5.1-28 include:

- Containment dimensions
- Hull penetrations and interfacing pipe materials
- Installed power system module weights
- Water trough duct connections.

Evaporators are mounted to receive warm seawater from a ship system trough with sluice gates located between traverse frames 50 and 80 and longitudinal frames B and F as shown in these figures.

Condensers are mounted to receive cold seawater from a ship system trough located between transverse frames 130 and 160 and longitudinal frames B and F.

The evaporators, condensers, turbine-generator, biofouling, and ammonia power loop subsystem are located in the plant ship between transverse frames 50 and 160 and longitudinal frames B and F.

Electrical equipment and the control room are located at elevation 77 between transverse frames 50 and 160 and longitudinal frames A and B.

The ammonia and nitrogen support subsystem components utilize the space between elevations 4 and 77, transverse frames 50 and 160, and longitudinal frames F and G.

The ship system's effluent discharge plenum and pipe gathering warm and cold water effluents are located as shown in Figures 5.1-27 and 5.1-28.

5.1.8.2 Functional Interfaces

Warm Sea Water. The evaporators receive seawater from the ship systems with the following characteristics:

- Static head, 6.3 feet above mean sea level (minimum)
- Flow, 721,800 GPM (minimum)
- Temperature, 82°F minimum for the design and 82 + 3, -10°F, for the off-design.

Cold Sea Water. The condensers receive seawater from the ship systems with the following characteristics:

- Static head, 6 feet above mean sea level (minimum)
- Cold water pipe, head loss, 5 feet of water (maximum)
- Flow, 679,600 GPM, minimum
- Temperature, 40°F maximum for the design.

Figure 5.1-26. Power Module General Arrangement

Figure 5.1-27. Power/Ship System Interface Plan

Figure 5.1-28: Power/Ship System Interface Sections

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

Electrical. Electrical power is delivered by the power system module to the ship system's 4.16KV bus. The power supply module electrical power subsystem functional interface characteristics include:

- Electrical power delivered to the bus at 4.16KV
- Power delivered is no less than 13.28 MWe with the power system module operating at a ΔT of 42°F. The delivered power is based on satisfying the following ship system load breakdown:

Net Power	10.00 MWe
Cold Water Pumps	1.96 MWe
Warm Water Pumps	1.21 MWe
Hotel	0.11 MWe
Gross Power to Bus	13.28 MWe

- Power system module intrasystem electrical power usage is at 440V, 3-phase to be functionally compatible with ship system use.

5.1.8.3 Ship Service Interfaces

Auxiliary Services. Ship services to be provided by ship system auxiliaries are:

- 50,000 CFM ventilation air to power module equipment room
- 50,000 CFM ventilation air to NH_3/N_2 support systems room
- 15,000 CFM ventilation air to electrical equipment room
- Air conditioning (two tons of refrigeration) for the control room
- Lighting - 100-foot candles for the control room and 80-foot candles for the equipment area
- Fire protection system

Power Plant/Ship Control. Instrumentation and control interfaces with ship systems from the seawater pumps include pump status, pump speed, pump power, water flow rates, and alarms. Interfaces from the ship include voice, TV monitoring of hazardous area, air quality in machinery spaces, wave motion alarm, and ship's electric power states (generation consumption). Interfaces to the ship are trip status, key subsystem status, alarms, gross and net power output, and voice.

Seawater Pump Availabilities. The condenser and evaporation seawater pumps have been allocated the following goals to achieve the required overall power system availability of 0.90:

- MTBF (each pump) = 720 days
- MTTR (each pump) = 80 hours

5.1.9 Stacked Heat Exchanger Option

TRW was requested to investigate the potential of configuring a 10 MWe PSD-II power plant to occupy one-half of the allocated pilot plant ship space.

The TRW conceptual approach considers stacking the heat exchangers as shown in Figure 5.1-29 (elevation) and Figure 5.1-30 (plan). All space is utilized with no maintenance access space available. The ammonia feed pump would have to be of the canned type projecting through the bottom of the hull to accommodate NPSH requirements.

The stacked arrangement also requires more complex piping. Two levels must be manifolded separately because of operating pressure levels.

The system would also require space other than the stacked envelope allocation for turbine removal access, chlorinator, turbine, generator panel, and lube oil cooling unit (as indicated in Figure 5.1-30). Also the cold and warm seawater pumps provided with the plant ship would have to be doubled in capacity.

Figure 5.1-29. Stacking Option-Elevation

Figure 5.1-30. Stacking Option - Plan

5.2 SYSTEM OPTIMIZATION AND ANALYSIS

Tradeoff studies of performance versus cost were carried out extensively to ensure that the system design satisfies DUE requirements at the lowest possible cost with minimum risk.

Section 5.2-1 describes the tradeoffs leading to the selected design. A three-phased approach was used. In the first phase, major design characteristics, such as working fluid and heat exchanger design concept, were selected. In the second phase, the topology of the design was determined based on computerized trade studies and component arrangement studies. Finally, a fine-tuning of the design was performed to meet constraints defined by the heat exchanger designer and interfaces with the APL plant ship. In Section 5.2.2, the sensitivity of the design to various significant design parameters is investigated. No critically sensitive parameters have been identified. Section 5.2.3 presents the seawater system analysis and design features which originated from the analysis. With these features, such as walls and gates, the system can perform in the specified dynamic environment.

5.2.1 System Optimization

This section describes the tradeoff studies which lead to the selected system design, with emphasis on functional description and cost/performance tradeoffs. Arrangement studies and design solutions are discussed in Section 5.1, which includes system piping and instrumentation diagrams and general arrangement drawings.

5.2.1.1 Conceptual Design Tradeoffs

During TRW's PSD-II proposal phase, we performed several tradeoff studies to determine key elements of the functional design. These included:

- Ammonia is the working fluid. No additional data requiring re-examination of this choice has been uncovered
- Basic aluminum panel types heat exchanger design (defined by UCC/Linde during the proposal) is consistent with the present system design. Design parameters based on manufacturing constraints include:
 - Panel dimensions are about 4 feet in the direction of water flow and about 8-1/2 feet high.

Inside diameter of water side tube-shaped passages is 0.75 inches

- No water side enhancement (Linde high flux enhancement on the ammonia side of the evaporator and Linde proprietary enhancement on the ammonia side of the condenser)
- Modular approach in which the evaporator and condenser assemblies are built up from several modules:
 - In series (with respect to water flow) to achieve an optimum water flow passage length (a subassembly)
 - Several subassemblies in parallel (with respect to water flow) to achieve the required (optimized) thermal duty.

The arrangement we proposed (four modules in series to form a subassembly and four subassemblies in parallel to make up each heat exchanger assembly) has been verified as the optimum arrangement using the updated PSD-II design computer program (see Appendix II, Section 1).

5.2.1.2 Module Arrangement Tradeoffs

The updated design computer program was used to derive optimum (minimum life cycle cost) designs for two, four, six and eight modules in series (N). This corresponds to water side tube lengths of 8, 16, 24 and 32 feet not counting the gap between modules (nominally 3.5 inches). No constraint was imposed on the number of panels.

There were several important conclusions of the computer study. Figure 5.2-1 shows that the optimum arrangement is four modules in series corresponding to a 16-foot long water flow path. The figure also shows that the minimum is relatively flat and that only a small (about 2 percent) cost penalty would be incurred by going down to N=3 or up to N=6 modules in series.

Figure 5.2-2 shows the approximate width of the heat exchanger assemblies and relative heat exchanger volumes for the various arrangements. Since the required heat transfer volume is essentially constant for N up to 6, the assembly width decreases as $1/N$ in this range (constant panel height). For $N > 6$, the heat exchanger assembly volume and cost increase rapidly leading to increased power system cost.

The required total seawater flow rates increase rapidly with decreasing N for $N < 4$ (Figure 5.2-3). This figure also shows the optimum tube water

Figure 5.2-1. Modularity Trade-Off Cost Versus Number of Modules in Series (Production Articles)

velocity as a function of N . The increase in water flow rates result in increased system cost for $N < 4$.

5.2.1.3 Design Refinement

To minimize the system envelope and simplify the system arrangement as well as the heat exchanger mechanical design, TRW and UCC/Linde agreed early in the conceptual phase to make the evaporator and condenser assemblies of identical design and envelope (except for ammonia side enhancement and functional design of downcomers). Each module has 204 active panels, which is consistent with 11 downcomers and 12 segments of panels with 17 panels each. Sixteen modules make up an assembly (4x4). With 204 panels per module, the total width of the heat exchanger assembly is 80 feet, which satisfies the APL plant ship envelope constraint of 82 feet.

To constrain the system design by equal number of panels in the evaporator and condenser, the unconstrained optimum design's ammonia evaporation and condensation temperatures was perturbed by trial and error with essentially no cost penalty. (See Section 5.2.2, Design Sensitivities.)

Figure 5.2-2. Heat Exchanger Size versus Module Arrangement

Figure 5.2-3. Variation of Flow Rate with Module Arrangement

To reduce the number of panels to the required 204 per module, the tube-side water velocities were increased to the values given in Figure 5.2-4, the resulting system cost is \$1108/kWe,* which is only \$20/kW higher than the unconstrained case (or 1.8 percent). An added advantage of increased sea-water flow rate is a reduced fouling rate.

5.2.1.4 Final Design Meets DOE Requirements

The system design meets DOE's system optimization requirements (Figure 5.2-5).

* These are computer program costs used for trade-off purposes. Final cost estimates are discussed in Section 6.

	W WATER PIPE	C WATER PIPE	
LENGTH FEET	300	2900.0000	
DIAMETER FT	18.4736	17.9247	
NUMBER OF PIPES	1	1	
H2O VEL FT/S	6.0000	6.0000	
WATER REYNOLDS NUMBER	1.1329E+07	6.4902E+06	
WATER FLOW LB/HR	3.6914E+08	3.4892E+08	
PRESSURE DROP PSI	.5405	2.8797	
	EVAPORATOR	CONDENSER	
HEAT TRAN LENG (4 MODULE)	15.3332	15.3332	
TOTAL LENG FT (4 MODULE)	16.0000	16.0000	
NUMBER PANELS (4 MODULE)	816.0000	816.0000	
TUBE DIAMETER I.D. IN	.7500	.7500	
NUMBER TUBES	81606	81589	
HEAT TRAN AREA SQ. FT.	2.4569E+05	2.4564E+05	
HEAT TRANSFERED BTU/HR	1.4441E+09	1.3954E+09	
OVERALL BTU/HR/F/FOOT	819.6848	622.6391	
NH3 HTC BTU/HR/F/FOOT	5725.0000	2230.0000	
WALL HTC BTU/HR/F/FOOT	25566.6319	25566.6319	
WATER HTC BTU/HR/F/FOOT	1367.8717	1147.8910	
FOULING (FOOT HR F/FTU)	3.0000E-04	3.0000E-04	
H2O ENTRANCE TEMP F	82.0000	40.0000	
CHANGE IN WATER TEMP	4.0900	4.1900	
WATER PRESSURE DROP PSID	2.5587	2.4402	
TOTAL ENT & EXIT K VALUE	2.6200	2.6200	
WATER TUBE VEL FT/SEC	6.4235	6.0457	
WATER REYNOLDS NUMBER	4.1034E+04	2.2814E+04	
NH3 ENT FLOW CFS		2.3617E+03	
NH3 EXIT FLOW CES	1.6830E+03	1.9623E+01	
INLET QUALITY	0.0000	.9641	
OUTLET QUALITY	.9700	0.0000	
NH3 INLET PRES PSIA	135.4321	91.7654	
NH3 OUTLET PRES PSIA	134.0321	91.3754	
NH3 PRES DROP PSID	1.4000	.3900	
ELEVATION FT	25.5000	25.5000	
SAT TEMP AT INLET PRES	72.9015	51.4900	
SAT TEMP AT OUTLET PRES	72.2800	51.2663	
NH3 TEMP DROP F	.6215	.2237	
LOG-MEAN TEMP DIF F	7.1709	9.1234	
	DEMISTER	TURBINE	
INLET			
PRESSURE PSIA	133.8821	133.4321	
TEMPERATURE F	72.2158	72.0231	
QUALITY	.9700	.9900	
MASS FLOW RATE LB/SEC	779.7356	764.0285	
VOLUME FLOW RATE CFS	1684.9058	1690.1264	
OUTLET			
PRESSURE PSIA	133.6821	91.9654	
TEMPERATURE F	72.1302	51.6044	
QUALITY	.9900	.9640	
MASS FLOW RATE LB/SEC	764.0285	764.0285	
VOLUME FLOW RATE CFS	1686.9948	2356.6823	
DEMISTER DRAIN		FEED PUMP	
QUALITY	0.00	INLET PRES PSIA	97.77
FLOW RATE LBS	16.71	OUTLET PRES	142.39
FLOW RATE CFS	0.415	PRES DROP PSID	44.62
	CYCLE DATA		
GROSS POWER MW	13.866630	NET POWER MW	10.000000
HOTEL POWER MW	.112500	MIS POWER MW	.350000
WW PUMP2 MW	1.210254	WW TOT DP PSI	3.099225
CW PUMPS MW	1.955960	CW TOT DP PSI	5.319869
NH3 PUMPS MW	.237412	F PUMP DP PSI	44.516721
TURBINE BTU/LB	17.733570	TUR EX QUALITY	.964009
PLANT EFF	.023627	MIXING TEMP F	51.686614
	COST BREAKDOWN (K\$)		
EVAP HE COST	1474.14	CON HE COST	1473.82
WW PUMP COST	591.33	CW PUMP COST	559.63
NH3 R PUMP	0.00	NH3 F PUMP	149.82
GEN COST	618.93	TURBINE COST	815.78
DELTA CW PIPE	164.05	MISCEL	3150.00
DEMISTER	86.00	TOTAL BOTH HX	2947.96
INSTALLED	9083.50	LIFE CYC COST	11082.21

Figure 5.2-4. Computer Output for System Design

DOE REQUIREMENT	SYSTEM DESIGN MEETS REQUIREMENTS
DESIGN BASED ON OCEAN ENERGY RESOURCES OF 82°F FOR SURFACE SEAWATER AND 40°F FOR DEEP SEAWATER USING ΔT OF 42°F. PERFORMANCE PROVIDES ΔT RANGE FROM 32°F TO 42°F.	SPECIFIED TEMPERATURES ARE USED AS DESIGN BASIS AND VERIFIED BY OFF-DESIGN SIMULATION. SYSTEM PERFORMANCE ANALYZED OVER FULL RANGE (SEE SECTION 5.3).
ALL HEAT EXCHANGERS SHELL-LESS CONSTRUCTION. DESIGN SELECTED CONSIDERS MANUFACTURABILITY, BIOFOULING AND CLEANING.	UCC/LINDE DESIGN AND PERFORMANCE DATA (VERIFIED BY TRW) FOR SHELL-LESS CONSTRUCTION USED IN SYSTEM SIMULATION. MANUFACTURABILITY, BIOFOULING AND CLEANING ARE DISCUSSED IN SECTIONS 5.8 AND 3.4.
WORKING FLUID BASED ON THERMOPHYSICAL AND OTHER APPROPRIATE PROPERTIES.	AMMONIA CHOSEN (JUSTIFIED IN PROPOSAL). SYSTEM MODEL INCORPORATES THERMODYNAMIC DATA DEFINED BY NBS-142.
HEAT EXCHANGER MATERIAL COMPATIBLE WITH SEAWATER AND CHOSEN WORKING FLUID AS WELL AS WITH MATERIALS IN POWER MODULE. MATERIAL EXHIBITS GOOD JOINABILITY, STRENGTH, THERMAL PROPERTIES, ETC.	ALUMINUM SELECTED PROPERTIES INCLUDED IN PERFORMANCE MODEL. MATERIAL CONSTRAINTS DISCUSSED IN SECTION 5.8.
DESIGN OF 10 MW _e POWER MODULE BASED ON 30-YEAR DESIGN LIFE AT 8,000 HOURS PER YEAR OPERATION WITH AT LEAST 1,000 START/STOP CYCLES.	SYSTEM DESIGN OPTIMIZED WITH RESPECT TO LIFE-CYCLE COST ASSUMING 16-YEAR LIFE OF ALUMINUM HEAT EXCHANGERS. RMA DISCUSSED IN SECTION 5.5.
SURFACE PLATFORM/SHIP USED AS BASIC REFERENCE HULL DURING CONCEPTUAL DESIGN.	SYSTEM DESIGN CONSISTENT WITH APL PLANT SHIP ENVELOPE CONSTRAINT. ALTERNATE ARRANGEMENT DEVELOPED (STACKED HEAT EXCHANGERS) FOR HALF OF SHIPS AFT SECTION. SEE SECTION 5.1.
APPROXIMATE TOTAL PRESSURE DROPS FOR WARM AND COLD WATER SYSTEMS CAN NOT EXCEED 10 FEET AND 15 FEET OF WATER RESPECTIVELY.	OPTIMIZED SYSTEM DESIGN HAS TOTAL WATERSIDE PRESSURE DROPS OF 7 AND 12 FEET (10 AND 15-FOOT HEAD CONSTRAINTS ARE NOT "ACTIVE").
AMMONIA (OR OTHER WORKING FLUID) VAPOR PRESSURE DROP WITHIN EACH HEAT EXCHANGER POWER MODULE (INCLUSIVE OF MANIFOLDING) CAN NOT EXCEED 2 PERCENT OF THE VAPOR PRESSURE DIFFERENCE AT 82°F IN THE EVAPORATOR AND AT 40°F IN THE CONDENSER.	TRADEOFF ANALYSIS INDICATED THAT ABOUT 40 FPS VAPOR VELOCITY WAS OPTIMUM COMPROMISE BETWEEN MANIFOLDING LOSSES (AND SUBSEQUENT POWER LOSSES) AND PIPING/VALVE COSTS FOR OUR DESIGN. RESULTING VAPOR PRESSURE DROPS BETWEEN EVAPORATOR AND CONDENSER (INCLUDING MANIFOLDING LOSSES, PHASE SEPARATOR LOSSES AND HEAT EXCHANGER ENTRANCE AND EXIT LOSSES) TOTAL 0.80 PSID. THIS IS WELL WITHIN SPECIFIED 2 PERCENT OF AVAILABLE PRESSURE DIFFERENCE ($P(82)=143.6$ PSIG, $p(40)=58.6$ PSIG; 2 PERCENT OF $\Delta P=1.7$ PSID).
10 MW _e POWER MODULE RATING REFERS TO NET BUS BAR POWER AVAILABLE AFTER ALL PARASITIC LOSSES, AUXILIARY EQUIPMENT AND HOTEL REQUIREMENTS (ABOUT 450 KW FOR HOTEL) ARE SATISFIED.	PARASITIC LOSSES INCLUDE IN ADDITION TO AMMONIA AND WATER PUMPING LOSSES) 450 KW/4 = 112.5 KW PER 10 MW _e MODULE (PER DOE TECHNICAL DIRECTION - HOROWITZ, JANUARY 1979) AND 350 KW ALLOCATION FOR AUXILIARY EQUIPMENT.
FOULING (BIOLOGICAL AND CHEMICAL) OF HEAT EXCHANGERS MUST BE CONTROLLED NOT TO EXCEED FOULING FACTOR OF 0.0005 HR-FT ² -°F/BTU.	DESIGN FOULING FACTOR IS 0.0003 HR-FT ² -°F/BTU FOR BOTH EVAPORATOR AND CONDENSER. CHLORINATION AND MECHANICAL CLEANING INCLUDED IN DESIGN.

Figure 5.2-5. Design Meets DOE System Optimization Requirements

5.2.2 Design Sensitivities

This section addresses the sensitivity of the design concept to key DOE defined design requirements and key design optimization parameters. The sensitivity of the selected baseline design to off-design operating conditions is discussed in Section 5.3.

5.2.2.1 Design Sensitivities to Key Design Requirements

These design requirements include:

- Seawater temperatures - Design values 82°F and 40°F for warm and cold water respectively
- Fouling factor - Design value 0.0003 hr-ft²-°F/Btu for both exchangers; maximum allowable is 0.0005.
- Total pressure drops for warm and cold seawater systems not to exceed 10 and 15 feet respectively
- Ammonia vapor side pressure drop not to exceed 2 percent of vapor pressure difference at 82°F (evaporation) and 40°F (condenser), or 1.7 psid.

Seawater Temperatures. We used the design program to compute design characteristics and cost as a function of warm water temperatures of 72, 76, 80 and 84°F with a fixed cold water temperature of 40°F. Resulting curves are shown in Figure 5.2-6. At 82°F, the total power system cost and heat exchanger cost sensitivities are:

$$\left. \frac{\delta C}{C} \right|_{\text{System}} = -1.56 \frac{\delta(\Delta T)}{\Delta T_{\text{Design}}} \quad (1)$$

Figure 5.2-6. Sensitivity of Power System Cost to Overall ΔT ($T_c = 40^\circ\text{F}$)

$$\left. \frac{\delta C}{C} \right|_{\text{Heat Exchanger}} = -2.62 \frac{\delta(\Delta T)}{\Delta T_{\text{Design}}} \quad (2)$$

In these equations, ΔT is available temperature difference, $\Delta T_{\text{Design}} = 42^\circ\text{F}$, and C denotes cost. δ is a small variation such that $\delta C/C$ denotes relative cost sensitivity. Note that $\Delta T = T_{\text{Warm}} - T_{\text{Cold}}$ is the important parameter and sensitivities apply to variations in warm and cold water temperatures simultaneously. A 1°F or 2.4 percent change in warm minus cold water temperature results in -3.7 percent change in system cost and -6.2 percent change in heat exchanger cost.

Seawater Side Fouling Factor. The computer design program similarly produced the results in Figure 5.2-7. Sensitivities are:

$$\left. \frac{\delta C}{C} \right|_{\text{System}} = +0.110 \frac{\delta R_f}{R_{f, \text{Design}}} \quad (3)$$

$$\left. \frac{\delta C}{C} \right|_{\text{Heat Exchanger}} = +0.212 \frac{\delta R_f}{R_{f, \text{Design}}} \quad (4)$$

If the design fouling factor (for both exchangers) increases from 0.0003 to 0.0005 $\text{hr-ft}^2\text{-}^\circ\text{F/Btu}$ (or about 67 percent), the system cost increases by about 7 percent and the heat exchanger cost by about 14 percent.

Seawater System Pressure Drop Constraints. The baseline design has total warm and cold seawater system pressure drops of 7 and 12 feet respectively. Therefore, the design sensitivity is zero. For constraints less than 7 and 12 feet respectively, the impacts are discussed in Section 5.2.2.2.

Ammonia Vapor Side Pressure Drop. The ammonia side vapor pressure loss between evaporator and condenser (including evaporator exit nozzle and condenser inlet nozzle, valve and manifold losses and phase separator losses) add up to about 0.80 psi for the baseline design. This is about 1 percent of the pressure difference between vapor at 82°F and 40°F , and about 1.9 percent of the actual design vapor pressure difference (corresponding to 72.3°F evaporation temperature and 51.5°F condensation temperature). This is accomplished by selecting a low design vapor velocity of about 40 fps.

$$\begin{aligned} \text{SYSTEM LIFE CYCLE COST} & \left[\frac{\delta C}{C_{\text{SYSTEM}}} = +0.110 \frac{\delta(R_f)_{\text{BOTH EXCH'S}}}{R_{f_{\text{DESIGN}}}} \right] \\ \text{HEAT EXCH'S COST} & \left[\frac{\delta C}{C_{\text{HEAT EXCHG}}} = +0.212 \frac{\delta(R_f)}{R_{f_{\text{DESIGN}}}} \right] \end{aligned}$$

Figure 5.2-7. Sensitivity of Power System Cost to Fouling Factor (Both Exchangers)

The sensitivity to the design pressure loss can be estimated by using the approximation that gross power is proportional to available turbine pressure drop (for constant flow rate). Figure 5.2-8 summarizes a simple tradeoff considering 20, 40 and 60 fps as the candidate design velocity (phase separator pressure drop assumed constant -0.2 psi). The cost of lost power by going from 40 to 60 fps is about \$275,000 which cannot be justified by savings in valves and piping (line size changes from 88 to 72 inches). The savings in gained power by going from 40 to 20 fps is about \$165,000. This cannot be justified because line and valve costs increase due to the significant increase in line size (from 88 to 125 inches).

VAPOR FPS.	ΔP_{LOSS} (PSI) PHASE SEP & OTHERS	ΔP_{TURB} PSID	GROSS POWER (MW)	NET POWER (MW)	Δ POWER KW	Δ COST \$	LINE SIZE INCH
20	0.2 + 0.15	41.85	14.02	10.15	150	-165,000	125
40	0.2 + 0.6	41.4	13.87	10.00	0	0	88
60	0.2 + 1.35	40.65	13.62	9.75	-250	+275,000	72
1) 40 FPS IS BASELINE							
2) COST BASED ON \$1100/KW							

Figure 5.2-8. Ammonia Vapor Side Pressure Drop Trade-Off

5.2.2.2 Design Sensitivities Optimization Parameters

In the PSD-II system optimization program, there are four independent design parameters. These parameters, which the program manipulates to determine an optimum (least cost) design, are:

- Warm water temperature drop, ΔT_{Warm} (which sets warm water tube velocity and pressure drop)
- Cold water temperature increase, ΔT_{Cold} (which sets cold water tube velocity and pressure drop)
- Ammonia evaporation temperature at evaporator exit, T_{Evap}
- Ammonia condensation temperature at condenser inlet, T_{Cond}

The sensitivity of system cost to these parameters is discussed in the subsequent paragraphs.

Water Temperature Change/Water Velocity. Figure 5.2-9 shows:

- Results of varying ΔT_{Warm} around the design value with fixed design ΔT_{Cold} - curve marked Evap
- Results of varying ΔT_{Cold} around the design value with fixed design ΔT_{Warm} - curve marked Cond.

The relative system cost is plotted versus the tube water velocity (resulting from changing ΔT_{Warm} or ΔT_{Cold}). The design velocities are 6.42 fps for the evaporator and 6.05 fps for the condenser.

Power system cost is relatively insensitive to velocity as long as the evaporator water velocity is from 5 to 7 fps and the condenser water velocity is from 4 to 7 fps. The figure shows the cost penalty (less than 2 percent) incurred by increasing the velocities relative to the unconstrained optimum velocities of about 5.70 fps and 4.64 fps for the evaporator and condenser, respectively.

From the results shown in Figure 5.2-9, we can estimate cost impact if the total water side head constraint is less than the baseline 7 and 12 feet for the warm and the cold water system. For the baseline design, the pressure drops associated with the heat exchangers are 5.8 and 5.5 feet for the evaporator and condenser respectively. The difference (1.2 and 6.5 feet respectively) is due to the water supply and return subsystems exclusive of the heat exchangers. These subsystems have been sized based on constant 6 fps velocity. The density head contribution is 3 feet out of the 6.5 feet.

The water levels in the warm and cold water supply troughs are shown in Figure 5.2-10.

Since the heat exchanger pressure drop is proportional to velocity squared, the cost impact of reducing the total head below 7 and 12 feet can be estimated. For example, to reduce total pressure drops to 5 feet and 10 feet for the warm and cold water systems, the tube velocities must be reduced to about 5.2 fps (evaporator) and 4.8 fps (condenser). The power system cost impact would be a 1 to 2 percent reduction in cost (since this closely corresponds to the unconstrained minimum cost design). However, the size of the heat exchangers would increase beyond that compatible with the APL plant ship.

Figure 5.2-9. Cost versus Water Velocity for Fixed T_{EVAP} and T_{COND}

Figure 5.2-10. Nominal Water Level Profile

Evaporator and Condenser Ammonia Temperatures. These temperatures (and corresponding pressures) can be selected by the designer to minimize the cost of the design or satisfy special design constraints. Small changes from the optimum unconstrained values were imposed on the baseline design to make the evaporator surface area equal to the condenser surface areas. The unconstrained optimum temperatures are $T_{\text{EVAP}} = 72.5$ and $T_{\text{COND}} = 51.5^{\circ}\text{F}$; the baseline temperatures are 72.38 and 51.49°F .

Figures 5.2-11 and 5.2-12 show that power system cost is insensitive to the exact value of the evaporation and condensation temperatures. In Figure 5.2-11, ΔT_{Warm} and ΔT_{Cold} are fixed at the design value. The broken curves show the significant variations in warm and cold water velocities.

Figure 5.2-12 shows results with fixed water velocities and resulting variations for ΔT_{Warm} or ΔT_{Cold} . System cost is insensitive to T_{Evap} and T_{Cond} (especially for fixed water velocities). Variations of $\pm 1^{\circ}\text{F}$ in each separately or simultaneously has no cost impact. However, it has a design impact. The most significant design impact is a redistribution of required heat transfer surface between evaporator and condenser.

The impact of changing the design evaporation and condensation temperatures symmetrically around the design values was investigated further.

Figure 5.2-11. Cost versus T_{EVAP} and T_{COND} for Fixed ΔT_{DWRM} and ΔT_{COLD}

Figure 5.2-12. Cost Versus T_{EVAP} and T_{COND} For Fixed Water Velocities

Figure 5.2-13 shows design sensitivities to an increased evaporator temperature of 1°F and a decreased condenser temperature of 1°F and vice versa. Warm and cold water flow rates are held constant at the baseline design values.

T_{EVAP} $^{\circ}\text{F}$	T_{COND} $^{\circ}\text{F}$	$\frac{\Delta T}{\Delta T_{DESIGN}}$	$\frac{A}{A_{DESIGN}}$ EVAP/COND	$\frac{W_{NH3}}{W_{NH3,DESIGN}}$ WEIGHT FLOW	$\frac{\Delta P}{\Delta P_{DESIGN}}$	$\frac{P_G}{P_{G,DESIGN}}$	$\frac{COST}{COST_{DESIGN}}$	
73.28	50.49	1.096	1.025/1.002	0.914	1.099	1.002	1.007	
72.28	51.49	1.000	1.000/1.000	1.000	1.000	1.000	1.000	← DESIGN
71.28	52.49	0.904	1.002/1.021	1.110	0.902	1.003	1.009	
		AMMONIA ΔT RATIO	HEAT EXCH. AREA RATIO	AMMONIA MASS FLOW RATIO	TURBINE ΔP RATIO	GROSS POWER RATIO	SYSTEM COST RATIO	
$V_{WARM} = 6.42 \text{ FPS CONSTANT}$ $V_{COLD} = 6.05 \text{ FPS CONSTANT}$								

Figure 5.2-13. Sensitivity of Design to Evaporator/Condenser Temperature Difference (Const. Net Power)

Figure 5.2-13 shows that the approximately ± 10 percent change in ΔT across the ammonia cycle (at fixed inlet water temperatures 82°F and 40°F) results in:

- Proportional change in Δp across the turbine
- Inversely proportional change in ammonia mass flow rate
- Only about one percent increase in total required heat transfer surface
- Less than one percent increase in gross power and power system cost.

The accuracy of these conclusions depends on computer model cost and performance algorithms. However, the analyses demonstrate that the system designer has considerable latitude in setting these design parameters. From a performance point of view, it is not critical to know accurately turbine flow versus pressure drop relationship. The system pressures and temperatures will adjust themselves with small impact on power output.

5.2.3 Seawater System Dynamics

The seawater pumps supply open troughs with seawater and maintain sufficient head in these troughs to provide (by gravity) the nominal flow rate through the heat exchangers and into the common discharge plenum. The discharge plenum is also of the open type. About +0.5 feet of head relative to sea level is sufficient to drive the water out of the discharge pipe. Figure 5.2-10 showed the nominal water levels. The basis for the design calculations (friction, gravity head, screen losses) is the same as in the PSD-I study (Reference 5-2, Section 2.1.8).

The expected response of the water system to hull motions is discussed in Section 5.2.3.1. Design modifications to reduce motion effects are summarized below. The implementation is shown in the arrangement drawings in Section 5.1, based on the discussion in Section 5.2.3.2.

Fixed walls are installed in the cold water trough dividing it into four smaller troughs (one per condenser subassembly).

The effects of hull motions on the flow of seawater are further reduced by sluice gates or gated walls at three locations:

- Operational gates at the crest of the wall between the moon pool and cold water trough reduce the effects of water motion in the moon pool on the water surface in the cold water trough. They enable repair of condenser subassemblies.
- Gated walls are installed at midlength and quarterpoints in the warm water trough. These reduce amplitude of standing waves in the troughs as well as unsteady flow in the troughs due to changing flow through the pumps with the changing head. They also allow flexibility of operation during repair of heat exchanger subassemblies or seawater pumps.
- There are gated walls at the quarter points and a solid wall at the midlength in the discharge plenum. The solid wall reduces wave motion along the large dimension of the plenum without any pressure drop penalty. The gated walls at the quarter points reduce wave motion during rough seas. During calm sea, the gates are fully opened.

5.2.3.1 Analysis of Hull Motion Effects

According to data supplied by Johns Hopkins Applied Physics Laboratory (APL),* the OTEC power systems should be designed to operate under motions associated with a significant wave height of 18 feet and a period of 9.8 seconds. The midship rms response to this sea state is:

Heave	3.4 feet
Pitch	1.0°
Roll	0.8°
Heave acceleration	0.03 g
Lateral acceleration	0.015 g

The heave accelerations were calculated at the cold water pipe connection. Roll and pitch accelerations can increase these values by about a factor of 2 at heat exchanger locations.

Cold Water Supply. The motion of the hull causes motion of the water in the moon pool with respect to the hull. Heave causes the surface to move vertically, while pitch and roll cause standing waves.

The vertical motion due to heave can be examined using the analysis developed for the cold water pipe and trough in Reference 5-2 Appendices A3

* Private communication to PSD-II contractors from Dennis Richards, January 1979.

and B4. The pump at the top of the cold water pipe can be included as was done in the examination of the completely closed system Reference 5-2 Appendix B2. A pair of equations of this type was developed for the cold water pipe and moon pool for PSD-II. The equations were linearized and used to estimate the vertical motion of the water surface in the moon pool. It is estimated that the motion of the water surface is ± 0.4 feet from the steady level with a calm sea. The period of this motion is about 180 seconds (see Appendix II, Section 3 for details).

Standing waves in the moon pool are caused by roll, pitch and lateral acceleration. The fundamental mode (first harmonic) of these waves has a wave length equal to twice the dimension of the pool in the direction of the wave motion. For the long dimension of the pool, the wave length is 164 feet. The natural period of the wave depends on the length and water depth. With a water depth of 70 feet, the period of the fundamental mode is 3.5 seconds. The higher harmonics have even shorter periods. These periods are all less than the period associated with the significant wave heights of 18 feet. Therefore, seas that create resonance in the moon pool can be expected during regular operation.

When the seas and ship motions create resonance, the heights of the standing waves can increase without limit until they are steep enough to break (Reference 5-3). For the fundamental mode, the standing waves would not necessarily break until a height of 23 feet or an amplitude of ± 11.5 feet.

The change in water-surface elevation in the moon pool due to either vertical motion or standing waves causes a change in the water level in the cold water trough. Seawater flows from the pool to the troughs over submerged weirs. The water depth on the weir crest is at least 6 feet 10 inches. At steady flow, the head loss across the weir is about 0.5 feet. When the water surface in the pool rises or falls due to heave, the water surface in the trough rises or falls by a corresponding amount to maintain about the same head loss. The water surface in the trough can respond to the rise or fall in about one second. Thus, the period of the change in the trough is the same as the period of the vertical motion (180 seconds).

The change in the trough due to standing waves in the pool is more complicated. It is unlikely that the water surface in the trough will rise and fall with the full 11.5-foot amplitude of the standing waves in the moon

pool. When the water surface in the pool is rising, the wave will most likely break over the weir and spill into the trough. The volume that spills into the trough reduces the rise of the surface in both the trough and at the edge of the pool. It is estimated that at the crest of the wave the water surface is about 6 feet above the level at steady flow. Thus, the water reaches the main deck. When the wave lowers the water surface at the edge of the pool, water spills out of the trough into the pool and reduces the lowering. At the trough of the wave, the water surface is about 6 feet below the level at steady flow and reaches the top of the weir crest. The period of this motion is the same as that of the standing wave. For the fundamental mode, the period is 3.5 seconds.

In summary, the water surface in the cold water trough is directly affected by the moon pool. This surface can have a motion of ± 0.4 feet with a period of 180 seconds and of ± 6 feet with a period of 3.5 seconds. To reduce this motion, gates are used on the weir crests. These gates not only permit dewatering of subassemblies, but also can be used to control the water level as described in Section 5.2.3.2.

Warm Water Supply. The effect of hull motion on the warm water supply occurs in two forms:

- Change in head on the warm water pumps
- Standing waves in the warm water trough.

The change in head occurs when the pump moves closer to or further from the ocean surface due to heave, pitch and roll of the hull. The pump intake moves up and down in the water, and the suction head from the surface to the impeller changes. It is not possible to estimate this change in head without detailed knowledge of the motion of the sea surface and the response of the hull.

However, an order of magnitude can be estimated. According to the APL data, the rms heave is 3.4 feet when the significant wave height is 18 feet. It can be shown (Reference 5-3) that for a significant wave height of 18 feet the rms height is $18/1.42$ or 12.7 feet. If the rms values are treated as amplitudes of simple harmonic motion, the head at the suction side of the pump impeller could change by as much as ± 8 feet. The pump head in a calm

sea is only 7 feet. Therefore, the variation in head is almost ± 100 percent from the steady state value. For typical large pumps of the type used for this application, this variation in head would cause the pumped flow rate to vary from -50 to +25 percent of the steady state value.

The effect of standing waves depends on the dimensions of the warm water trough. In the simplest design, the trough is not divided and one pump discharges into each end. With no dividing walls, the length of the first harmonic of the standing waves is twice the length of the trough or 164 feet. The average water depth in the trough is 21 feet, and the period of the fundamental wave is 6.31 seconds. The higher harmonics have even shorter periods. Since these periods are less than the period associated with the significant wave height of 18 feet, seas that create resonance in the trough can be expected during regular operation.

With resonance, the height of the standing waves can increase without limit until they are steep enough to break (Reference 5-3). For the fundamental mode, the height of the standing wave at breaking is 6 feet or an amplitude of ± 3 feet.

Since each warm water pump supplies two subassemblies, it is possible to place a wall across the trough at midlength and produce two troughs each with a length of 41 feet. The length and period of the fundamental mode of the standing waves are reduced to 82 feet and 3.15 seconds, respectively. The wave height at breaking is 11.6 feet, or the amplitude is ± 5.8 feet.

The combined effect of change in head on the pump and standing waves in the trough cannot be estimated without more extensive analysis. For standing waves alone at the resonance frequency and one wall in the trough at midlength, the variation in water-surface elevation can be ± 6 feet.

Discharge Plenum. The motion of water in the discharge plenum is similar to that in the moon pool. The heave of the hull causes the water surface to move vertically, while pitch and roll cause standing waves. The analysis already mentioned in connection with the moon pool can also be used for the plenum.

With no dividing walls across the plenum or with a single wall at midlength, the total horizontal area of the plenum participates in the vertical motion of the water surface due to heave. From the linearized equations

for this motion, it is estimated that the variation in depth in the discharge plenum is ± 0.8 feet.

The standing waves in the plenum have lengths and periods determined by the length of the plenum and the mean water depth. The wave length and period of the fundamental mode are 164 feet and 7.6 seconds respectively. The lengths and periods of the other modes are less. Since all of the periods are less than that associated with the significant wave height of 18 feet, resonance in the plenum can be expected during normal operation. With resonance, the wave heights increase until the waves break or touch the top of the plenum. For the fundamental mode, the waves break when the wave height is 10.8 feet, or an amplitude of ± 5.4 feet from the mean water level in a calm sea. Since the mean water level is only 1.5 feet below the top of the plenum, the waves fill the plenum at some locations before they break. The water at these locations is under pressure. If parts of the top of the plenum are open grating, the water rises through the grating during the wave motion.

Due to symmetry of the steady flow through the plenum, it is possible to place a vertical dividing wall across the plenum at midlength with negligible effect on the steady flow. The wall can be located on the axis of the discharge pipe and can coincide with a diameter. With such a wall, the length of the first harmonic would be reduced to 82 feet and the period to 3.8 seconds. Resonance would still be expected during normal operation, and the wave height at breaking would still be 10.8 feet.

The combined effect of standing waves and vertical motion due to heave could cause the free water-surface elevation in the plenum to vary by ± 6.2 feet from the steady flow level in a calm sea. The water surface cannot increase to $+6.3$ feet because it will touch the top of the plenum at $+1.5$ feet. However, the pressure created at locations where the plenum is filled would be almost equivalent to $+6.2$ feet.

Flow Rate in the Heat Exchangers. The flow through the heat exchangers is caused by the difference in the elevation of the water surfaces at both ends. At steady flow, the pressure difference across the condenser subassembly is 2.44 psi or 5.5 feet of water. The difference across the

evaporator is 2.56 psi or 5.8 feet of water. The effects of vertical motion and standing waves change the differences from the values at steady flow.

For the condenser, the water-surface elevation in the cold water trough can vary by ± 6.8 feet, while the elevation in the plenum can vary by ± 6.2 feet. Due to the complicated combination of sea motions that cause these variations, there is no guarantee that both motions will be in phase. Therefore, there is the possibility of the water surface at the discharge end of a subassembly being higher than at the entrance end. This reverses the flow and causes water to go from the plenum to the cold water trough. At other times, the total difference in water surface elevations can be increased to 18 feet. The flow through the condenser can increase beyond the steady value by 80 percent.

The variations in water surface elevations at the evaporator subassembly are of the same magnitude. Therefore, they can have a similar effect on flow through the evaporator.

In addition to the effect on the flow through the heat exchangers, the variation of water level in the plenum can have another effect. When the water surface falls to a minimum value, it can be more than 2 feet below the top of the heat exchanger tubes. The upper tubes can be unwatered at the discharge end.

Possible Coupling of Effects. The change in water-surface elevations and in flow through the heat exchangers are related. When the surface in the warm or cold water trough rises and the surface in the plenum falls, the flow through the heat exchanger increases. The increased flow rate removes more water from the trough and lowers the water surface there. At the same time, more water is delivered to the plenum and the surface there is raised. Thus, the increased flow rate produces an effect that decreases the flow rate. In a similar manner, a decreased flow rate produces an effect that increases flow rate.

Without extensive analysis using computer models, it is not possible to predict the combined result of coupling of the effects produced by hull motions. In general, however, it appears that the coupling produces

negative feedback. The combined effect is smaller than the sum of the individual effects. Nevertheless, the combined effect is significant.

5.2.3.2 Design Features to Reduce Dynamic Effects

Operational Gates at Inlets to Cold Water Troughs. Gates at the inlets to the cold water troughs are needed for repairs to the condensers. The crest of the weir between the moon pool and the trough is below the normal operating level in the pool. To pump out one compartment of the trough and unwater a subassembly, a gate at the top of the crest must be closed to block the flow into the compartment. However, gates for this purpose alone could be simple perhaps even stop logs.

In the design, these gates are upgraded so they can control flow to and from the compartment during normal operation. When a sea state occurs that causes resonance in the moon pool, these gates can be partially closed to operate as sluice gates. The opening between the crest of the weir and the bottom of the gate becomes an orifice. When the water surface in the pool rises above its steady elevation, the orifice limits the flow into the trough. When the surface in the pool falls below its steady value, the flow back into the pool is restricted.

From a linear approximation, the ratio of the amplitude of motion in the trough to the amplitude in the pool depends on the frequency of the standing waves, the steady state flow under the gate, and the head loss across the gate. For the design values, some examples are given in Figure 5.2-14.

HEAD LOSS ACROSS GATE	AMPLITUDE RATIO
0.5	0.89
1.0	0.71
2.0	0.45
5.0	0.20

Figure 5.2-14. Amplitude Ratio Versus Head Loss Across Gate

With the gated walls, there is still the possibility of standing waves between the walls. In the warm water trough, these waves would have the same characteristics as in the compartments of the cold water trough.

Gated Walls in Discharge Plenum. It is recommended that gated walls similar to those suggested for the warm water trough be placed in the discharge plenum at quarter points. They work according to the same principle as those in the warm water trough and serve the same purpose.

There is also the possibility of standing waves between these walls. For the plenum, the first harmonic of the standing waves has a length of 50 feet and a period of 2.28 seconds. The wave breaks at an amplitude of ± 3.6 feet.

When the gates in the walls at the quarter points of the plenum are closed, the motion of the water surface due to heave is changed. Most of the motion is confined to the center half of the plenum between the gates at the quarter points. The amplitude of the vertical motion between these gates becomes ± 1.6 feet. When the gates are partially opened, the amplitude of the vertical motion is between 0.8 foot and 1 foot.

There must be some parasitic head loss across the gate to reduce the amplitude in the trough. However, this may be less than the loss due to large variation in flow in the heat exchanger. This loss is only incurred when the moon pool is in resonance. Otherwise, the gate is completely open to allow free flow.

When the effect of the moon pool resonance is reduced by the gates, resonance of the standing waves in the compartments of the cold water trough is still possible. The first harmonic of the standing waves in each compartment has a length of about 45 feet and a period of 1.7 seconds. The wave breaks at an amplitude of ± 3.3 feet.

Gated Walls in Warm Water Trough. Since there are four evaporator subassemblies, the trough is divided into four compartments by dividing walls across the trough at midlength and quarter points. The walls at quarter points have openings to allow water from the warm water pumps to reach the inside assembly. The dividing walls occupy the upper half of the cross-section of the trough. Each wall has slide or sluice gates that

can be lowered to close the lower half. Although a solid wall could be placed at midlength, a gated wall was selected for flexibility of operation during repairs.

When the standing waves in the trough appear to be in resonance, the gates can be closed down to create an orifice at the bottom of each wall. The principle is the same as described above for the gates at the inlet to the cold water trough. The transfer of wave motion and amplitude along the trough is damped. The amount of damping is related to the parasitic head loss across the orifices. However, this loss is only incurred when resonance occurs, and the loss may be less than that from large variation of flow rate through the heat exchangers.

5.3 SYSTEM OPERATION AND PERFORMANCE

The steady-state performance of the 10 MW module during nominal and off-nominal conditions is described in Section 5.3.1. Dynamic performance is described in Section 5.3.2, including time constants, response to ship heave, and response to trips and load shedding. Operating requirements, including the interfaces within the APL plant ship, requirements for the control room, and the selected control mechanization, are discussed in Section 5.3.3. Section 5.3.4 describes the interrelationships among the operational modes (startup, shutdown, trip, purge, fill) and the sequence of the events that occur in each mode. Finally, startup power requirements are analyzed.

Instrumentation and controls that implement many of the operating requirements are discussed in Section 5.4.

5.3.1 Steady-State Performance

The steady-state performance analyses of the 10 MWe power module covered full and part power operation. We analyzed part power operation to determine how to achieve control with minimum effect on full power output.

The full power performance analyses investigated evaporator liquid-height sensitivity, fixed and variable speed ammonia pumps, seasonal ΔT performance sensitivity, fouling factor effects, flow losses, and optimum water flow rates. Because plant efficiency is not an issue at less than

full power, the analysis was limited to investigating the alternatives to control. These alternatives include turbine throttle, bypass valve, and ammonia flow rate.

The simulation program developed for this analysis is described in Appendix II, Section 2. The scope of the model is shown in Figure 5.3-1. The program was developed by TRW based on the PSD-I model (Reference 5-2). The simulation models all major system elements (heat exchangers, turbine, phase separator, pumps, pipes, bends, fittings, and valves). Heat exchanger models are based on data provided by UCC/Linde using log-mean-delta-T to determine heat transfer. The turbine model is a scaled version of a model generated by Professor Lawrence Amb's of the University of Massachusetts for single-stage ammonia turbines optimized to PSD-II nominal operating parameters. Regression fits to the off-nominal performance of this design were used to define turbine algorithms.

An example of the program output (Figure 5.3-2) shows the variation in performance with warm water temperatures from 70 to 88°F.

5.3.1.1 Model Verification

The steady-state performance model was checked against the design optimization model and was found to agree within 1 percent in flows, pressures, and temperatures. Nominal power agreed exactly. The model is accurate to 0.1 degree Fahrenheit, 0.1 psi, 0.3 flow rate and 1 percent power.

5.3.1.2 Seasonal Variations

The change in the warm water temperature is expected to be the primary variable affecting steady-state plant performance. Figure 5.3-3 shows the net and gross power as a function of the warm water inlet temperature. The graph shows a linear relationship between power and warm water temperature. Figure 5.3-4 shows the variation of turbine efficiency and ammonia quality with warm water temperature. Figures 5.3-5 and 5.3-6 show the power, efficiency and quality variation with varying cold water temperature. Again, power appears to be nearly a linear function of water temperature.

The warm and cold water temperature effects on power are essentially additive. Therefore, the following expressions for power were developed as a function of these temperatures:

Figure 5.3-1. Flow Diagram of Steady - State Model

CASE	1	2	3	4	5	6	7	8	9	10
VARIABLE TWRM	70.00	72.00	74.00	76.00	78.00	80.00	82.00	84.00	86.00	88.00
POWER & EFFICIENCY	(McGAWATT)									
NET POWER	1.94	3.36	4.76	6.11	7.43	8.72	10.00	11.30	12.64	14.05
GROSS POWER	5.74	7.18	8.58	9.95	11.28	12.59	13.88	15.19	16.55	17.93
COLD WATER PUMP	1.96	1.96	1.96	1.96	1.96	1.96	1.96	1.96	1.96	1.96
WARM WATER PUMP	1.21	1.21	1.21	1.21	1.21	1.21	1.21	1.21	1.21	1.21
CONDENSATE PUMP	.17	.17	.20	.21	.22	.24	.25	.26	.28	.29
MISCELLANEOUS	.46	.46	.46	.46	.46	.46	.46	.46	.46	.46
TURBINE EFFICIENCY	73.06	79.38	84.44	87.09	88.48	89.03	89.08	88.89	88.65	88.56
AMMONIA QUALITY	97.76	97.40	97.15	96.93	96.73	96.56	96.40	96.25	96.11	95.97
FLOW RATES	(LB3/SEC)									
EVAPORATION FLOW	576.07	611.86	644.95	676.17	706.15	735.37	764.31	793.37	823.04	853.77
CONDENSATION FLOW	552.64	595.87	626.49	655.22	683.02	709.98	736.65	763.60	791.14	819.26
TURB INLET FLOW	576.07	611.86	644.95	676.17	706.15	735.37	764.31	793.37	823.04	853.77
BYPASS FLOW	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00
TEMPERATURES	(DEG F)									
WARM WATER DISCHG	66.91	68.72	70.54	72.38	74.22	76.06	77.91	79.75	81.60	83.44
COLD WATER DISCHG	43.22	43.41	43.58	43.74	43.90	44.05	44.20	44.35	44.50	44.66
EVAPORATOR	62.41	64.00	65.62	67.27	68.93	70.60	72.28	73.96	75.63	77.28
CONDENSER	48.66	49.37	49.84	50.27	50.70	51.11	51.51	51.92	52.34	52.76
PRESSURES	(PSIA)									
EVAPORATOR	112.43	115.71	119.14	122.70	126.38	130.16	134.04	138.00	142.04	146.13
CONDENSER	97.38	88.24	89.05	89.80	90.54	91.26	91.98	92.73	93.45	94.21
TURB THROTTLE	112.03	115.29	118.70	122.24	125.90	129.67	133.53	137.48	141.50	145.58
PUMPS AND VALVES										
PUMP SPEED, RPM	641.91	671.07	700.57	730.23	759.85	789.39	818.79	847.98	876.98	905.79
ANGLE, DEGREE	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00
COND NPSH, FEET	23.78	23.63	23.47	23.32	23.16	23.01	22.84	22.67	22.49	22.30
DF PR COND VALV, PSI	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00	0.00
HEAT TRS COEFF EVAP	801.21	834.54	867.79	900.95	914.01	916.95	919.78	922.47	925.03	927.44
HEAT TRS COEFF COND	622.44	622.44	622.44	622.44	622.44	622.44	622.44	622.44	622.44	622.44

Figure 5.3-2. Program Output for Warm-Water Temperature Variation With Cold-Water = 40°F

Figure 5.3-3. Power Output vs. Warm Water Inlet Temperature ($T_{\text{cold}} = 40^{\circ}\text{F}$)

Figure 5.3-4. Efficiency and Quality Vs Warm Water Inlet Temperature ($T_{\text{cold}} = 40^{\circ}\text{F}$)

Figure 5.3-5. Power Output vs Cold Water Inlet Temperature ($T_{\text{warm}} = 82^{\circ}\text{F}$)

Figure 5.3-6. Efficiency and Quality Vs Cold Water Inlet Temperature ($T_{\text{warm}} = 82^{\circ}\text{F}$)

$$P_G = 13.87 + 0.65 (T_W - 82) - 0.65 (T_C - 40) \text{ (MWe)}$$

$$P_N = 10.00 + 0.645 (T_W - 82) - 0.645 (T_C - 40) \text{ (MWe)}$$

where the water temperatures (T_W and T_C) are in $^{\circ}\text{F}$. These expressions match the simulation results within 0.02 to 0.03 MW over the normal temperature range.

Figure 5.3-7 shows the net power output for the baseline seasonal surface temperature profile of Reference 5-4 (the cold water temperature remains at 40°F all year). The annual average power output is 10.0 MW, which is also the power output at the nominal temperature (since the output power is a linear function of temperature).

Figure 5.3-7. Seasonal Power Profile For PSD-11

Total energy produced weekly is:

- Maximum ($\Delta T = 45^{\circ}\text{F}$): 2010 MW-hr/week
- Nominal ($\Delta T = 42^{\circ}\text{F}$): 1680 MW-hr/week
- Minimum ($\Delta T = 38^{\circ}\text{F}$): 1250 MW-hr/week

The evaporator and condenser discharge temperatures and water discharge temperatures as a function of warm water temperatures are shown in Figure 5.3-8.

Figure 5.3-8. Heat Exchange Discharge Temperature Vs Inlet Temperature ($T_{\text{cold}} = 40^{\circ}\text{F}$)

5.3.1.3 Fouling Factor

Heat exchanger fouling affects net power and overall heat transfer coefficient significantly. Figure 5.3-9 shows the effect of warm water fouling at various levels of cold water fouling. It also shows cold water fouling with the nominal warm water fouling factor ($0.0003 \text{ ft}^2\text{-hr-}^\circ\text{F/Btu}$). The fouling factors have a linear, additive effect on net power represented as:

$$P_{N_F} = P_N - (0.367 + 0.009 [T_w - 82])(R_{f_w} - 0.0003) \times 10^4 \\ - (0.367 + 0.010 [T_w - 82])(R_{f_c} - 0.0003) \times 10^4 \text{ (MWe)}$$

where R_{f_w} and R_{f_c} are the warm and cold water fouling factors. P_N is a function of water temperatures as given in Section 5.3.1.2.

Figure 5.3-9, Net Power vs. Warm Water Fouling Factor

Figure 5.3-10 shows the effect on the overall heat transfer coefficients versus the evaporator and condenser fouling factors.

5.3.1.4 Water Flow Rates

The effect of varying the warm and cold water flow rates in the evaporator and condenser was investigated. Figure 5.3-11 shows the results for maximum (85°F), nominal (82°F), and minimum (78°F) warm water temperatures

Figure 5.3-10. Overall Heat Transfer Coefficient vs. Fouling Factor

for a 40°F cold water temperature. The horizontal axis is the cold water flow rate in 5,000 lb/sec steps. For each step, the warm water flow is varied over $\pm 15,000$ lb/sec. Each dot represents an increment of 5,000 lb/sec of warm water flow. The center line represents nominal warm water flow, which appears to be nearly optimal at all temperatures.

These results were used to compare the economics of variable-speed seawater pumps to uncontrolled pumps. As shown in Section 4.4 uncontrolled pumps are economically justified in steady-state operation at all water temperatures. Section 5.3.4.8 shows that controllable speed water pumps reduce the demand for grid power during startup. However, DOE's requirement that the PSD-II plant must be connected to the southwestern United States grid justifies an uncontrolled pump because of its steady-state economics and startup power availability via the grid.

Figure 5.3-11. Water Flow Effects on Power ($T_{\text{cold}} = 40^\circ\text{F}$)

5.3.1.5 Effect of Removing Heat Exchanger Subassembly

The effect of removing one of the four subassemblies from either or both of the evaporator and condenser assemblies was investigated. It was assumed that one subassembly is removed for repair and the empty space is blocked-off. In equilibrium, the ammonia flow is diverted into the

the remaining three heat exchangers. Since the seawater pumps are not controlled, they pump nearly the full flow-rate of water; the water level in the trough rises until the velocity of water through the remaining heat exchanger tubes drains the trough at the same rate as water enters the trough. To calculate the new equilibrium point of the water pump, a normalized head (h) - flow(Q) curve was used (Reference 5-2, Appendix B):

$$\frac{Q}{Q_0} = -0.182 \left(\frac{h}{h_0}\right)^2 - 0.055 \left(\frac{h}{h_0}\right) + 1.24$$

If one subassembly (25 percent of the heat exchanger area) is removed from service, Figure 5.3-12 shows the resulting plant conditions. The net power output only falls 15 percent after removal of a condenser or evaporator subassembly. Removal of both reduces power 30 percent.

PARAMETERS	NO FAILURES (NOMINAL)	FAILURE OF REMOVAL OF SUBASSEMBLY		
		EVAPORATOR REMOVED	CONDENSER REMOVED	BOTH REMOVED
WATER FLOW RATE				
WARM (LB/SEC)	102,500	89,900	102,500	89,900
COLD (LB/SEC)	96,900	96,900	88,900	88,900
AMMONIA TEMPERATURE				
EVAPORATOR (°F)	72.3	70.6	72.4	70.8
CONDENSER (°F)	51.5	51.1	53.7	53.2
AMMONIA FLOW RATE, LB/SEC	764	735	763	725
TURBINE EFFICIENCY, %	89	89	89	89
WATER PUMPING POWER				
WARM (MW _e)	1.21	1.34	1.21	1.34
COLD (MW _e)	1.96	1.96	2.13	2.13
NET POWER OUTPUT (MW _e)	10.0	8.60	8.26	7.00

Figure 5.3-12. Plant Conditions with Failed Heat Exchanger

5.3.2 Transient Performance

The transient performance analysis determines whether high-frequency control is needed to reduce power fluctuations due to ship motions, determines the timing of events during startup, and evaluates system overshoot after a turbine trip or generator disconnect (load-shedding).

The characteristics times of the power module were determined and a model was constructed where appropriate in the preliminary design. It was not necessary to analyze all these effects in detail during preliminary design nor to construct a dynamic model that includes all of these phenomena.

The power cycle exhibits the following characteristic times:

- Transport lag of water flow through the horizontal condenser and evaporator tubes of a subassembly is 2.6 seconds (based on a 6.5 fps water flow rate).
- Thermal lag in the heat exchanger metal can vary from 0.15 seconds (based on 360,000 pounds of wetted aluminum) to 0.22 second (if the 190,000 pounds of wetted steel piping is also included). These times are small because of the large wetted area and high water flow rate.
- The volumetric lag of ammonia vapor filling the heat exchanger manifolds is difficult to compute because of the two-phase ammonia mixture in the evaporator. A simple analysis estimates it at 1 to 3 seconds.
- Transport lag of ammonia flow between the evaporator and turbine is 1.5 seconds.
- Slosh of liquid ammonia among the 16 interconnected modules has many natural modes. The sloshing natural periods vary from 20 to 60 seconds.
- The ammonia pump has a time constant of about 2 seconds when changing speed.

These characteristic times are used to analyze the following key dynamic phenomena:

- Heave-induced power fluctuations
- Event timing
- Trip overshoot
- Trough slosh
- Liquid ammonia slosh
- Interfaces with the ammonia support plant.

5.3.2.1 Heave-induced Power Fluctuations

The plant's gross power output fluctuates about ± 10 percent in response to ship heave as shown in Section 2.2.6 of Reference 5-2. TRW constructed a model of PSD-I using the falling-film heat exchanger. This model calculated the fluctuations in net power produced by ship heave. It consisted of two models run independently. A water model calculated the variations in water flow rate caused by ship motion. An ammonia model calculated the

net power output caused by changing water flow rates. Because the period of ship heave is much larger than any of the plant's characteristic times, the response was quasi-steady-state, attenuated only by the transport lags. The PSD-II response is expected to be about the same, using the specified ship's heave of 3.4 feet at a 10-second period. As explained in Reference 5-2, these power oscillations can be reduced by:

- Varying the speed of the hydraulic pumps to change the hydraulic head on the heat exchangers to keep the flow constant as the ship moves. The hydraulic transient model can be used to verify the technical feasibility of this approach.
- Increasing the shell-space volume of the heat exchangers, thus smoothing the ammonia flow.
- Controlling the ammonia flow to the turbine with an added turbine inlet valve, with a continuously-variable bypass valve, or with the variable nozzles. Any of these are controlled by water temperature or flow rate.

Controlling the ammonia flow causes a penalty in net power output. This penalty results from the presence of the partly open throttle valve or partly closed bypass valve. The penalty is large because the plant would have to be throttled about 10 percent. Another reason for the loss in net power output is the nonlinear characteristic of throttling that causes the average power to be further depressed when the valve oscillates symmetrically. The average power reduction will probably be 0.5 MW.

Heave-induced power oscillations are common to all OTEC designs. During detailed design, power systems will require further analysis as to the amplitude of the oscillations and determine if control is required. It is anticipated that utilities will learn to accept fluctuating loads in the 1980s because of the growing use of solar, wind and OTEC stations.

5.3.2.2 Event Timing Analysis

During the detailed design phase, a large perturbation model should be constructed to predict the time between events during a startup, shutdown or power-level change.

5.3.2.3 Trip Overshoot Analysis

This analysis determines the turbine overshoot caused by load shedding. the effect of key design decisions, such as the configuration and

characteristics of turbine inlet valves, are analyzed to verify that overspeed is within the turbine manufacturer's specifications. Because this is a routine analysis similar to that for a land-based turbine, it was deferred until the detailed design. No other critical overshoots are expected during trips.

5.3.2.4 Trough Slosh Analysis

Section 5.2.3 shows how natural oscillations are excited in the water troughs and how they are reduced with adequate design methods, such as baffling. The slosh analysis should be continued during the detailed design of a power system.

5.3.2.5 Liquid Ammonia Slosh Analysis

As noted above, liquid oscillations can occur among heat exchanger modules when the ship rolls and among subassemblies when the ship pitches. The ship's roll period is estimated to be 15 seconds, based on the 10-second maximum heave period while the platform is operating (Reference 5-5). Because the ship period is much shorter than the 20 to 60-second slosh periods and because the DOE-specified pitch and roll amplitudes are less than $\pm 1.5^\circ$, liquid levels vary less than ± 1 foot. This has little effect on the evaporation rate. OTEC-1 tests and tank tests are expected to measure the importance of slosh and to confirm our ability to predict it in interconnected heat exchangers. If slosh proves to be significant, it can be corrected by:

- Placing orifices in the liquid lines to damp oscillations. These orifices do not cause significant loss in output power.
- Trip the plant when oscillations become excessive.
- Add individual liquid-ammonia valves at the inlet to the outboard heat exchanger modules. Control the flow to each evaporator to maintain equal pressure in each module.

Based on present DOE direction concerning ship motion, slosh of liquid ammonia is not significant.

5.3.2.6 Interface with the Ammonia Support Plant

The NH_3 support plant extracts liquid from the heel of the piping. It injects liquid into the condenser. Control is by measuring liquid level in the condenser well and switching the injection pumps on and off.

Because of the slow pumping rate and large capacity of the plant, the only potential dynamic effect is a limited rate of power-loading. This power-loading may result if the wells are undersized because they cannot inject ammonia fast enough after a long period of part-power operation.

The design of dynamic compensations in the plant control loops is a routine matter and can be done during detailed design and startup. The cost of compensation filters is insignificantly affected by dynamic compensation.

5.3.3 Operational Requirements

5.3.3.1 Power Grid

The DOE objective is to "design a power system which would be integrated into an OTEC system which would be cost-competitive in the southeastern USA". Therefore, the baseline PSD-II power system would be connected directly into the southern U.S. power grid as a base-load plant. We assume that 4 MW of startup power are available. TRW also examined the consequences of operating PSD-II as an isolated plant or as one of a small number of plants in a small grid.

5.3.3.2 Ship Interface

Figure 5.3-13 shows the operational interfaces among the:

- Power module's displays and controls
- GFE seawater subsystem's displays and controls. The seawater subsystem includes the seawater pumps, pipes, troughs, gates, baffles and instrumentation.
- Ship's subsystems (electrical power, television monitor, intercom, air quality measurements, alarms).

It is assumed that the seawater subsystem control panels and power module control panels are collocated in a common control room (see Section 5.4.4) and that the ship's control center is separate (perhaps on the bridge). Information exchange among these three elements is shown in Figure 5.3-14 and 5.3-15. Equipment to transfer that information (which TRW assumes is furnished by DOE) is listed in Figure 5.3-16.

Figure 5.3-13. PSD-II Operational Interfaces

Figure 5.3-14. Operational Interfaces with APL Plant Ship

Voice and television monitoring are provided by the host ship; the power module provides panel space for the intercom and four television monitors. Because the power module may not operate safely above Seastate 6, a wired seastate alarm is assumed to exist from the ship. Status of the ship's electric power generators also is required, especially during start-up and trip of the power module. It is desired that the ship's electric power status be displayed in the PSD-II control room in a form compatible

<u>FROM SEAWATER SUBSYSTEMS:</u>	<u>TO SEAWATER SUBSYSTEMS:</u>
PUMP STATUS	NONE
PUMP SPEED	
PUMP POWER	
WATER FLOW RATES	
TROUGH LEVEL MEASUREMENT	
ALARMS	
DIAGNOSTIC INSTRUMENTATION	
WATER FLOW DYNAMICS	
DISPLAY PANEL	

Figure 5.3-15. Operational Interfaces with Seawater Subsystem

<u>CONTROL PANELS FOR POWER MODULE CONTROL ROOM:</u>
4 TELEVISION MONITORS
2 INTERCOMS
AIR QUALITY PANEL
WAVE MOTION ALARM
SHIP'S ELECTRIC POWER STATUS
SHIP'S KW GENERATION
SHIP'S KW CONSUMPTION
SEAWATER SUBSYSTEM CONTROL PANEL
<u>CONTROL PANELS FOR SHIP'S BRIDGE</u>
KEY POWER MODULE ALARMS AND STATUS
POWER MODULE ELECTRIC POWER GENERATION
<u>SEAWATER INSTRUMENTATION MULTIPLEXER</u>
<u>SHIP'S INSTRUMENTATION MULTIPLEXER/DEMULTIPLEXER</u>

Figure 5.3-16. Assumed Ship's Electrical Interface Equipment Furnished by DOE

with the PSD-II power display and be adjacent to it. PSD-II furnishes some status and alarms to the ship as well as gross and net generated power for display on the bridge. All data are sent via a two-way computer-to-computer link.

5.3.3.3 Control Room Requirements

The power module control room contains all displays and controls needed to run and trip the power cycle and ammonia support plant and to open and

close electrical switchgear. It provides space for DOE-furnished ship's interface panels and hydraulic interface panels. It accommodates all electronics that require frequent or immediate access by the operators (such as magnetic tape records) and provides workstations for a supervisor, operator, and assistant operator. The supervisor and operator sit at the console. The assistant operator sits at a desk when he is not working on the wall panels or in the hull.

Figure 5.3-13 shows the control center interface requirements. The control center must have a console and wall-mounted displays. It also must have mimic boards of the ammonia loops and electric power distribution with dedicated control switches for those actuations that may be required within 5 minutes of an alarm or display.

Redundant alarms are required for all signals that indicate a potentially hazardous condition or that have expensive consequences to the plant.

5.3.3.4 Data Handling Requirements

PSD-II instrumentation performs the following functions:

- Status monitoring — Provide displays of the status of all subsystems and of the system to operators
- Control — Measure the parameters for the control system and for the trips
- Diagnostics.

Diagnostics provide an historical record of the plant's operating status, including subsystem (pumps, turbines, heat exchangers) and system performance. The diagnostics also confirm the mathematical models used in subsystem design and system performance prediction. Results of experiments on the plant are evaluated and the cause of abnormal events (such as trips and accidents) are determined.

The development of computer programs is assumed to take place on a shore-based scientific computer where verification tests can be performed prior to delivery to the ship. Some software may be written in a high-order language and compiled on the scientific computer. It is assumed that a high-order language interpreter is not needed in the plant computer itself. The procedure for software development and the need for such tools

as compilers, editors, emulators and interpreters must be reevaluated during detailed design to ensure that DOE's desires for plant operation are met.

5.3.3.5 Power Loop Control Requirements

The power loop is operated from the control room under normal conditions of full-load and part-load. The plant computer establishes the power output in response to an operator's single set point. The system can also be operated manually with the operator setting each valve and motor individually from the control room. All valves and motors have additional controls near the equipment in the hull.

Steady-state control of the 10 MW power loop is needed to maintain:

- Maximum power output as ocean temperatures change
- Reduced power during startup and for programmed load reductions. There is no need to optimize anything at reduced power since we are using a renewable source.

The required steady-state control scheme is based on simulations with the model. Figure 5.3-17 shows how the ammonia pump speed affects net power output. The pump can be operated over a 4.5:1 speed range and can be slowed to 220 rpm.

Increased pump speed results in increased power output. However, as pump speed increases, the exit vapor velocity increases, eventually increasing the moisture content enough to damage the turbine. Pending test data on the 0.2 MWe test article, maximum pump speed is limited to 880 rpm. A measurement of Δp on the evaporator serves as the ammonia pump control input. It also limits the pumping rate to the experimentally-determined maximum Δp that gives the maximum allowable ammonia moisture.

This is the method of control from 1 to 15 MW gross power output. However, it is necessary to startup at about 5 kW gross power output to check-out the plant prior to loading. The ammonia pump speed is not a satisfactory control variable near zero power since ± 0.1 rpm is needed to control ± 5 kW. Therefore, the bypass control (shown in Figure 5.3-17) is used as startup. The sensitivity is about 0.5 degrees per 5 kW.

An alternative method of control, using the turbine inlet and bypass valves was analyzed by simulation and discarded.

Figure 5.3-17. Variation of Net Power Output with Pump Speed and Bypass Valve

5.3.3.6 Auxiliary Equipment Control Requirements

Seawater Subsystem. The cold water trough is filled passively from the sea as water is pumped into the condenser. Because cold water and warm water pumps run at constant speed, motor-starters are satisfactory for control. No control is provided on water flow because of the large surge power requirements and because the economic analysis (Section 4.4.2) shows it is unnecessary.

Ammonia Support System. A fraction of the ammonia flow is removed at the heel of the power loop and stored in a wet-ammonia tank (Figure 5.3-18). The ammonia is fed to a purification column from which dry ammonia is removed to a storage tank from which it is pumped into the condenser sump (see Section 5.8.1). All controllers are located in the control room.

Figure 5.3-18. Ammonia Control Loops (Redundant Pumps and Tanks not Shown)

The ammonia support subsystem is monitored from the PSD-II control room and can be tripped by the operator. An ammonia plant trip isolates each piece of equipment from the others without immediately affecting the power cycle. If the tripped state persists, the power cycle eventually shuts down.

Turbine Generator. The turbine-control actuator is a set of variable nozzles with a common controller (Section 4.1). During startup, it is used for speed control. After synchronization, it is controlled for maximum net power output. Control is manually or by a hunting program in the central computer. When the generator is connected to an infinite grid, its speed is locked at 1800 rpm and a "wide-open valves" policy produces maximum power.

Power Distribution. Control of the power-distribution circuit breakers is manually self-contained (as described in Section 5.1.7) except for computer-operated trips. Generator-to-line phase angle and important voltages and currents are measured, displayed, recorded and alarmed (see Section 5.4.3). Control of the hydraulic pumps (on-off) is from a panel dedicated to that subsystem.

Tube Cleaning Machine. The tube-cleaning machine is controlled and manually backed-up from a remote station located in the hull near the heat exchangers. Operators can initiate a cleaning cycle which is automatic. The operator can stop the cycle and restart it or reset at any point. The operator can also clean the tubes manually one at a time. Because cleaning is expected to occur once every 1 to 4 weeks, TRW decided not to initiate the cleaning cycle automatically, based on time or on computed fouling factors. Ten status monitoring alarms (nonredundant) are provided in the PSD-II control room.

5.3.3.7 Trips and Alarms

The purposes of trips are:

- To protect the plant against damage after a fault
- To protect the operators against dangerous conditions, such as a massive ammonia release
- To initiate a shutdown procedure.

Alarms alert the operators that a potentially hazardous or costly event which requires their immediate attention has occurred in the plant.

The power cycle, seawater subsystem and ammonia support system can be tripped separately or in combination. Each trip can be initiated manually by the operator or can occur automatically if sensors detect out-of-limit conditions. Following a trip, the plant is either restarted or is shutdown (Figure 5.3-19).

Sensor indications predicting hazardous or potentially costly consequences within 5 minutes are connected to automatic trips and to alarms. Sensors that can foretell hazardous consequences in longer times are connected to alarms. All sensors are also connected to the computer complex for performance calculations, status monitoring and recording.

Figure 5.3-19. Relations Among Plant Operating Procedures

Implementation of trips is discussed in Section 5.4.8.

5.3.4 Startup and Shutdown

Figure 5.3-19 shows the relationship between installation test, purging, ammonia charging, startup, shutdown and trip. The remainder of this section is a first estimate of operational procedures; it does not address installation and checkout procedures.

During detailed design of the 10 MWe plant, TRW would expand these lists of events and determine the times between them.

5.3.4.1 Nitrogen Purging

The air or ammonia in the piping and subsystems is replaced with dry nitrogen stored at 225 psig in five consecutive purges (Section 5.8.1). By closing valves V-32 to V-39 and V-7 to V-14 as shown in Figure 5.1-4, the evaporator, turbine and condenser are isolated and purged. By closing valves V-57 and V-58, each heat exchanger is isolated and purged. Purging ceases when an Orsat analysis shows sufficiently low oxygen and CO₂ content in the nitrogen (if the system was previously filled with air) or sufficiently low ammonia content (if the system was previously filled with ammonia). Purging ends with the power cycle pressurized at about 70 psia.

5.3.4.2 Ammonia Charging

The inert power cycle is charged with nitrogen. At the time of initial installation and after any shutdown that requires removal of the ammonia, the system must be recharged with ammonia and flushed of nitrogen. Ammonia recharge consists of three to five ammonia flushes followed by loading of the desired amount of ammonia.

A first estimate of the sequence of events is as follows, starting with an air-filled piping system:

- 1) Purge (as in Section 5.3.4.1)
- 2) Bleed nitrogen overboard until the power cycle pressure drops to 65 psia by partially opening V-30, V-40, V-41 and V-69
- 3) Open liquid NH₃ supply valves V-15 and V-31 to admit ammonia at 100 psia, 56°F. The power cycle will fill with ammonia vapor. Liquid ammonia will begin to fill the evaporator and condenser

- 4) Vent N_2 overboard. To do so, close V-15 and V-31. Open V-30, V-40, V-41 and V-69 until the pressure drops to 65 psia
- 5) Repeat the ammonia flush (steps 2, 3, 4) two more times. Vent the ammonia-nitrogen mixture to the support plant via V-42, V-43, V-44, and V-45. Condense NH_3 in the seawater condenser and release the N_2 to the atmosphere. Flush ceases when an Orsat analysis shows sufficiently low nitrogen content in the ammonia
- 6) Charge the power cycle with the desired weight of ammonia until the total system pressure reaches 70 psia through V-56 and V-71. To charge the ammonia support subsystem, bottled ammonia is fed into the system until full, then the system is checked out and started. This procedure takes one day.

5.3.4.3 Prestart Checklist

Prior to starting the seawater pumps and ammonia loops, the operators will review a checklist. During preliminary design, TRW prepared an example checklist to be elaborated during detailed design:

- 1) Preoperational testing is successfully completed on all subsystems
- 2) The system is charged with ammonia and residual nitrogen content is satisfactory
- 3) Shiploads are connected to ship generator
- 4) Plant loads are connected to the external power grid
- 5) Turbine/generator is disconnected from the external power grid
- 6) Trip valve at turbine inlet is closed (V-57)
- 7) Turbine bypass valve is open (V-58)
- 8) Tube cleaning machines are off
- 9) All vent and drain valves are closed (e.g., V-9, V-26, V-27, V-30, V-42, V-43, V-44, V-45)
- 10) Remaining ammonia process valves are open (e.g., V-8, V-10, V-12, V-14, V-47 to V-53, V-61, V-63, V-65, V-67)
- 11) Supply and return valves in ammonia purification loop are open (two valves)
- 12) Instruments and analyzers are calibrated.

5.3.4.4 Startup

The normal operation of PSD-II is to supply electricity to an infinite grid. Thus, startup occurs on power drawn from the grid until the generator is synchronized at zero load. During the presynchronization period, ship loads are probably carried by the ship's diesel generators. Based on the preliminary design, TRW envisions the following startup sequence.

- 1) Verify that the prestart checklist (Section 5.3.4.3) has been completed
- 2) Turn on instrument air supply
- 3) Turn on power to instrumentation: recorders, controllers, transmitters, solenoids, valve actuators, indicators, alarms, and annunciators
- 4) Turn on power to process-control computers and self-test them
- 5) Turn on turbine lube pumps and oil seals. Check oil level and pressure. Check operation of redundant pumps and standby pumps
- 6) Turn on cold seawater pump (P-1). Check pump and motor instrumentation. Check seawater temperature and flow rate. Check pump NPSH and moonpool level
- 7) Turn on warm seawater pump (P-2). Check pump and motor instrumentation. Check seawater temperature (TE-11) and flow rate (FR-1). Check pump NPSH
- 8) Allow (TBD) minutes for steps 6 and 7
- 9) Isolate main ammonia pump (P-3) by closing V-27 and V-28. Open V-17 and V-20 for backup feed pump (P-4)
- 10) Check backup pump and motor instrumentation and flow rate (FE-8, 9, 10)
- 11) Isolate backup pump by closing V-17 and V-20 and open main pump valves V-22 and V-28
- 12) Start primary pump and check instrumentation
- 13) Set the pump speed to minimum (220 rpm) and check NPSH
- 14) Allow (TBD) minutes and check heat exchanger Δp (LE-1 and LE-2)

- 15) When ammonia pressure at evaporator outlet (PE-17) is (TBD) psia, set the variable nozzles of the turbine stator to minimum setting and open the trip valve (V-57) to admit a small amount of vapor into the turbine. When enough torque is developed to overcome frictional forces, the turbine/generator will come up to some minimum speed (100 to 200 rpm). Monitor bearing temperature, noise, oil pressure and flow, for turbine and generator.
- 16) Reset the ammonia feed pump (P-3) and bypass valve (V-58) to (TBD) percent flow
- 17) Computer controls the variable nozzles to maintain near-synchronous speed at zero power output. Connect the line circuit breaker (PCB-2) when the phase-meters read zero. Check turbine speed
- 18) Accelerate the ammonia pump and control the bypass valve to approximately 30 percent flow
- 19) Open the variable nozzles gradually to load turbine until 4 MWe (amount of plant and ship loads). Adjust exciter for power factor. Switch ship loads to turbine/generator when appropriate.
- 20) Turn on tube-cleaning machines. Test and enter automatic cycle
- 21) Start chlorination and leak detection subsystems
- 22) Plant is now self-sustaining at zero net power and ready to be set as requested by dispatcher.

5.3.4.5 Trip

As described in Section 5.3.3.7, the power cycle and hydraulic system can be tripped or the ammonia support plant can be tripped. Each of the three trips can be initiated manually or can occur automatically if sensors go out of limits. Following a trip, the plant is either restarted or is shut down (Figure 5.3-19).

5.3.4.6 Shutdown

Shutdown is operator-initiated after a trip (Figure 5.3-19). The power cycle shutdown procedure is:

- 1) Start ship's generator and synchronize
- 2) Switch ship loads to ship generator
- 3) Switch plant loads to external power grid
- 4) Stop warm seawater pump if from partial trip (P-2)

- 5) Stop ammonia feed pump (P-3)
- 6) When pressure in evaporator (PE-17) is equalized with pressure in condenser (PE-27), stop cold seawater pump if from partial trip (P-1)
- 7) Turn off tube cleaning machines
- 8) Stop chlorination and leak detection subsystems.

5.3.4.7 Ammonia Drain

After a shutdown, if the system is to be repaired, the ammonia must be removed and the system purged (Figure 5.3-19). Purging is necessary for safety so workmen do not encounter ammonia when opening components. Nitrogen purge is suggested to reduce the exposure of valve-isolated components to corrosive salt air.

The procedure for removing ammonia following a shutdown is as follows:

- 1) Open ammonia let-down valves, V-42, V-43, V-44 and V-45. Start let-down (drain) pumps to remove liquid ammonia from sumps
- 2) When completely drained, stop let-down pumps. Close valves V-42 and V-45
- 3) Start nitrogen support subsystem and purge the system (see Section 5.3.4.1)
- 4) Components are now accessible and ready for maintenance.

5.3.4.8 Startup Power

Parasitic power requirements during startup are summarized in Figure 5.3-20. The full-power load of 3.87 MW can only be reduced to 3.3 MW during startup with fixed-speed hydraulic motors. Section 5.1.7 shows the inrush currents required with low-voltage and full-voltage starting.

An OTEC plant connected to the baseline infinite grid starts with power drawn from the grid through a transformer and switchgear. If 3.3 MW is not available from the grid, variable-speed seawater pumps reduce the startup power drain from the startup source to 400 kW (Figure 5.3-21). The plant then uses the startup source to pump enough water to evaporate and condense enough ammonia to generate 400+ kW. The bypass valve is gradually closed, generating enough excess power to accelerate the

PARASITIC LOAD	OPERATING AT FULL POWER	START-UP WITH FIXED- SPEED SEAWATER PUMPS
PUMPS		
SEAWATER	3170 KW	3170 KW
AMMONIA FEED	240	40
SUPPORT PLANT	185	0
OTHER LOADS		
HEATERS, CONTROLS, TURBINE AUXILIARIES	40	40
HOTEL LOAD	110	30
TUBE CLEANER AND CHLORINATOR	125	0
PARASITIC LOAD	3870 KW	3280 KW

Figure 5.3-20. Start-Up Power Budget

Figure 5.3-21. Start-Up Power with Variable-Speed Seawater Pumps

water pumps. When gross output power equals 3.28 MW, the plant is self-sustaining at reduced auxiliary loads. At 3.87 MW, the plant sustains itself at full parasitic load and further acceleration of the feed pump produces excess power for sale. Reference 5-6 suggests that hydraulic pumps should be started slowly even when fixed-speed operation is planned in the steady state. TRW's hydraulic and motor experts believe that full-power startup is satisfactory.

The baseline 10 MWe plant will be connected to the southeastern U.S. grid and uses fixed-speed pumps, drawing their starting power from the grid.

5.4 INSTRUMENTATION AND CONTROLS

5.4.1 Requirements

The instrumentation and control system performs the following functions:

- Manual operation of the plant
- Efficient automatic operation with provision for manual disconnect
- Automatic trips to protect against damage and to assure the safety of the operators
- Data collection and alarms for real-time display to the operators
- Data collection for evaluation of plant performance and detection of faults
- Flexibility to permit experimentation with process variables or procedures and a method to collect data about the experiments

Section 5.3.3.4 defined the data-handling requirements for the 10 MW plant while Sections 5.3.3.5 and 5.3.3.6 defined the control requirements. Section 5.4.2 describes the implementation of those requirements that is the best compromise between cost and flexibility for the 10 MW plant. The remainder of this section amplifies details of the implementation.

Section 3.3.3 described the instrumentation for the 0.2 MW test articles.

5.4.2 Implementation

The equipment chosen to implement the instrumentation and control design consists of:

- Sensors and actuators
- Control center including displays and operator controls
- Eight analog controllers located in the control room
- Plant digital computer, signal conditioners, and peripherals
- Instrument wiring

Figure 5.4-1 is a block diagram of the system. The control measurements go to analog computers in the control room where actuations are calculated for ten automatic control loops (eight analog and two discrete). All measurements enter the control room where many of them are recorded and displayed. A plant digital computer calculates the set points for the analog computers when the operator places the power loop in the "automatic" mode. Reference 5-2, Appendix K describes trade studies done by TRW that

Figure 5.4-1 OTEC Instrumentation and Control System Block Diagram

compare this implementation to a direct-digital-control approach and explain the reasons for the selection of the baseline design. The preliminary specifications that were developed for the procurement of the sensors are in Appendix I, Section 7 of this report; while the specifications for the computers and peripherals are in Appendix K of Reference 5-2.

Implementation of the 0.2 MW test article instrumentation is discussed in Section 3.3.3.4 of this report.

5.4.3 Sensors

The instrumentation lists for the ammonia power loop are shown in Appendix I, Section 7 of this report; the remainder of the instrumentation is shown in Appendix K of Reference 5-2. Both instrumentation lists for the 10 MW plant are summarized in Figure 5.4-2. The instrumentation for the 0.2 MW test article is summarized in Section 3.3.3.4.

TYPE	NON REDUNDANT	REDUNDANT	TOTAL/RECORD	DISPLAY	*ALARM
FLOW	24	2	26	4	2
TEMPERATURE	73	30	103	16	7
PRESSURE	79	34	113	21	10
DIFFERENTIAL PRESSURE	3	3	6	3	2
OIL GAUGE	11	11	22	11	11
PITOT TUBE	4		4		
LIQUID LEVEL	32	17	49	12	9
VIBRATION PROBE	9		9		
CL ₂ LEAK DETECTOR	4	8	12	4	
NH ₃ LEAK DETECTOR	2	4	6	2	2
TUBE CLEANER	10				10
SPEED	2	1	3	1	1
KW POWER	2		2		
PHASE DETECTOR	1		1	1	
VOLTMETER	10		10	10	
AMMETER	10		10	10	
TOTAL POINTS	277	110	377	94	64
50 PERCENT UNCERTAINTY	139	55	189	47	27
NET AMOUNT	419	165	566	141	91

*ALARMS ARE BOTH WIRED AND COMPUTER-DISPLAYED.

Figure 5.4-2. Summary of Point Count: Sensors

For the 10 MW plant, critical sensors (those that can detect an impending costly accident) and control sensors (those used in the computation of actuator commands) are at least dually redundant. Where access to a sensor is difficult, sensor redundancy is required, as computed from the life-cycle cost of failures. All other sensors and transducers can be nonredundant. Both sets of redundant control transducers connect to the computer complex, as do all nonredundant transducers. In summary, 110 points are redundant out of 277 identified points. In addition, a 50 percent allowance is added for uncertainty (EPRI Report NP-254, Reference 5-7, suggests 30 percent spares for a conventional plant during the design phases. Therefore, 50 percent uncertainty for a first OTEC plant is reasonable). The point counts of Figure 5.4-2 serve as the basis for the layout of console and wall space, and for software estimates.

Conventional industrial instrumentation concepts are utilized to minimize risks and cost. Sensor accuracy is specified in the sensor lists of Appendix K, Reference 5-2. Figure 5.4-3 shows typical manufacturers of each sensor.

FUNCTION	SENSOR TYPE	TYPICAL MANUFACTURER
PRESSURE	RESISTANCE STRAIN GAUGE	TAYLOR
DIFFERENTIAL PRESSURE	RESISTANCE STRAIN GAUGE	TAYLOR
LIQUID LEVEL (ΔP)	RESISTANCE STRAIN GAUGE	TAYLOR
TEMPERATURE	RTD	TAYLOR
FLOW	PARITY TURBINE	BROOKSTASER

Figure 5.4-3. Typical Sensors for PSD-II

The sensors chosen were based upon tradeoffs between various types. Resistance strain gauge pressure sensors were picked over piezo resistance gauges due to the fact that the latter needs a damping element at higher ranges which introduces the possibility of added error. RTD temperature elements are more accurate, more easily calibrated, and have faster response than thermocouples.

The baseline uses switch-type sensors for driving alarms. During detailed design of the 10 MW unit, TRW will compare the then available continuous sensors plus level settings versus switch sensors. The continuous sensors can be tested in-place, as state variables vary normally, at the expense of added computer software. On the other hand, the switch sensors must be removed periodically for testing but do not need remote level settings or comparison software.

All analog transmitters will produce a 4 to 20 mA output signal. Where practical, the transmitter and sensor elements are mounted near each other. All transducers will be excited at 24 VDC. All instrumentation within the OTEC PSD-II plant will be explosion-proof, conforming with Class I, Group D, as described in Article 500 of the National Electrical Code.

5.4.4 Control Room

A plan view of the control center is shown in Figure 5.4-4. The three operators operate the entire power station from the center including the ammonia loop and support plant and the government-furnished seawater subsystem. The control center contains wall displays, a console, some electronic equipment, and a desk for the assistant operator required by Section 5.3.3.3.

Figure 5.4-5 shows the allocations for wall-display space and for console space. Two wall-mounted mimic boards will be furnished, one for the PSD-II electrical system and one for the ammonia power cycle and top-level support plant (the detailed support plant is mimicked on a local control board in the hull of the ship). Status lights on the mimic boards in the control room are driven directly from field contacts while hand-switches drive valves and circuit breakers. Eighteen computer-driven digital displays on the console convey added information (voltages, current, net and gross power, flow rates, pressures, temperatures). The electrical mimic board reproduces the power buses shown in Figures 5.1.7-1 and 5.1.7-2. It includes plant auxiliary loads, emergency power, and interfaces to the ship's power and to the power mains. The ammonia mimic board displays the status of all valves and motors and permits remote manual set-point control of the actuators listed in Figure 5.4-3. In the automatic control mode the mimic board shows the status of all valves.

Figure 5.4-4. Floor Plan of Control Room

The wall-mounted turbine-generator panel has manual controls for the lube system, seals, variable nozzles, and exciter. It also has an auto-manual switch for disengaging the speed control loop after synchronization on an infinite grid.

Figure 5.4-1 shows how the interfaces from the field sensors and actuators are wired to the control room. Section 5.4.9 describes the wiring practices in more detail. The reliability of critical measurements is assured by duplication of sensors and alarm indicators for those critical parameters.

The DOE is expected to furnish some ship's interface equipment and seawater interface equipment, Section 5.3.3.2. For the purpose of sizing the console and wall space requirements, the assumptions of Figure 5.4-5 were made, leading to a requirement for 1.25 ft² of console space and 31 ft² of wall space. TRW would like the DOE-furnished ship's electric power displays (included in these totals) to be adjacent to the PSD-II electric power display.

The requirements for PSD-II alarms are discussed in Section 5.3.3.7 and the implementation is in Section 5.4.8. Figure 5.4-2 shows that 91 alarms are necessary. For purposes of sizing the control center, these alarm indicators are grouped above each subsystem panel on the wall. An audible annunciator will sound each time an alarm is detected. The visual alarm indicators will remain illuminated until the trouble has been cleared; the audible tone can be cancelled by the operators.

The alarms are actuated by out-of-limit conditions detected as follows:

- High and low limit contacts on actuators, sensors, detectors, and switches
- Computer recognized limits compared to previously-recorded upper and lower limit levels stored in computer memory

The alarm panel occupies approximately 11 ft² of wall space. The trip initiation panel has three guarded trip buttons, three indicators, and an annunciate-cancel button. It occupies 3/4 ft of console space.

PARAMETER TO BE DISPLAYED	DISPLAY/QUANTITY	DISPLAY CONSOLE (FT ²)	WALL DISPLAY (FT ²)
ELECTRICAL	MIMIC BOARD (AT 3 x 3 FEET)		9
	OUTPUT METERS (GROSS AND NET POWER, VOLTAGE, POWER FACTOR)	1	
AMMONIA LOOP	MIMIC BOARD (3 x 4 FEET = 12 FT ²) INCLUDING 16 COMPUTER DRIVEN DISPLAYS		12
TURBINE/GENERATOR	10 DISPLAYS 10 CONTROLS		3
SHIP INTERFACES*	4 TV MONITORS		12
	2 INTERCOMS (AT 8 x 10 INCHES = 80 IN ²)	1.25	
	AIR QUALITY PANEL AND WAVE MOTION ALARM		2
	ELECTRICAL POWER (MIMIC) CB STATUS, POWER GENERATION AND CONSUMPTION		9
	SEAWATER SUBSYSTEM PANEL (2 CRT's, 16 ALARMS, 10 METERS)		8
ALARMS (WIRED)	91 AT 4 x 4 INCHES		11
TRIP INDICATORS	3 AT 4 x 6 INCHES = 24 IN ²	0.75	
DEDICATED DISPLAYS (NOT ON MIMICS)	20	1.5	
COMPUTER CONTROL/DISPLAY PANEL	2 CRT's PLUS 2 FOR PANEL	11	
TOTAL		15.5	66

Figure 5.4-5. Control Room Display Space for 10 MWe Unit

Two CRTs with keyboards are installed on the console for calling-up detailed status and diagnostic data. Eighteen computer-driven dedicated displays are included on the console for key outputs (gross and net power generated, output voltage and power factor, condenser and evaporator temperature, etc). For planning purposes, 26 more are included on the wall boards.

The total wall space is about 66 ft² and the total console space is 15.5 ft². Figure 5.4-6 shows an artist's rendering of the appearance of the control room. During detailed design of the 10 MW unit, TRW would analyze the operator work tasks to confirm that three operators are satisfactory. If more operators are needed, the possibility of further automation or increasing the size of the control room to accommodate additional people would be evaluated.

Figure 5.4-6. Control Room Wall and Console Displays

5.4.5 Control System

The actuators are either motors or valves. All motors are started and stopped from the motor control center. Those that are automatically tripped or controlled also have remote actuations. All valves have integral electrical on-off provisions.

The actuators are shown in the ammonia power cycle drawing (Figure 5.1-8) and on the ammonia support system drawing (Figure 5.8-3).

The ten actuators identified on Figure 5.4-7 are required for sustained plant operation and are under computer control. They have set-points established manually from the control room. The three valves needed for setting generated power must also be operated by the computer complex, based on demanded power output. Those valves used intermittently for plant operation are set manually in the control room. Trip actuators are driven from "or" gates (one out of two logic elements) that trip the wired logic or by computer trips.

The remote actuators are operated from switches on the mimic board in the control room. Direct-reading lights and computer-driven digital displays on the mimic board and console confirm that operator actions have been executed.

As indicated in Sections 5.3.3.6 and 5.3.3.7, the plant computer drives the set-points for the ammonia feed pump, bypass valve, and variable turbine nozzles during steady-state operation. It drives the feed pump and bypass as a function of desired power output and inlet water temperatures and drives the nozzles in a hunting mode, searching for the maximum net output power. When the plant is starting-up, the computer establishes the set-point for the ammonia pump but the variable nozzles are controlled by an analog computer, whose input is turbine speed and whose frequency response requirements are far higher than those of the plant computer. Software requirements for the control loops are estimated to be 50 words of data storage, 200 words of program, and 400 computer operations per iteration.

Full-Power Control

The basic condition is one of generating the largest possible net power and delivering it to an infinite grid. The turbine will be synchronized by the grid and the plant operated "valves-wide-open." The evaporator will be

ACTUATOR	SETPOINT CONTROL			SENSOR
	COMPUTER	MANUAL CONTROL BOARD		
		MAIN	LOCAL	
<u>POWER LOOP</u>				
AMMONIA FEED PUMP SPEED (P3 AND P4)	P	A	A	LIQUID AMMONIA FLOW RATE, NET POWER OUTPUT, WATER TEMPERATURE
BY-PASS; BY-PASS NH ₃ AROUND TURBINE (V-58)	P	A	A	AMMONIA FLOW RATE, NET POWER OUTPUT, WATER TEMPERATURE
TURBINE VARIABLE NOZZLES	P	A	P*	TURBINE SPEED OR GENERATOR POWER
GENERATOR DC EXCITER		P	A	OUTPUT VOLTAGE AND POWER FACTOR
<u>AMMONIA SUPPORT PLANT</u>				
PURIFICATION COLUMN REFLUX VALVE		P	A	LEVEL IN COLUMN
AMMONIA COLUMN FEED VALVE		P	A	AMMONIA FLOW RATE
AMMONIA PRODUCT FLOW VALVE		P	A	AMMONIA FLOW RATE
REBOILER SEAWATER FLOW VALVE		P	A	REBOILER ΔP, FLOW RATE
NON-CONDENSIBLE VENT VALVE (OPEN OR CLOSED)		P	A	COLUMN ΔP
BOILER BLOWDOWN VALVE (OPEN OR CLOSED)		P	A	LEVEL AND TEMPERATURE

P = PRIMARY
 A = ALTERNATE
 P* = STARTUP ONLY

Figure 5.4-7. Control Loops for the 10 MW Plant

controlled to give the maximum evaporation rate. (This rate occurs when the downcomer liquid height is approximately 5.5 feet.) Thus, the control will be through varying the ammonia pump speed as a function of evaporator Δp . Fine tuning can be obtained through the turbine-nozzle controls taking advantage of slight improvements in turbine efficiency. The water pumps will be run at the same speed for all water temperatures.

The ammonia support plant operates unattended, using remote set points. The tube-cleaning machine operates remotely under control of its computer. If a problem should develop in either system, an alarm will appear in the control center. If the problem is serious, an automatic trip may occur, or the operator may trip the support plant from the control room. All shutdowns are manually controlled to save computer interfaces and software and to permit maximum flexibility for experiments.

If the plant is connected to a small grid, the turbine speed must be controlled independently. For this case, the turbine nozzles act as the speed control with the evaporators controlled to optimum output.

Part-Power Control

If required, the OTEC plant can follow an external power-demand. Since OTEC uses no consumable resources, efficiency is of little interest.

At part-power, the ammonia feed-pump speed will be reduced and the bypass valve partly opened. The plant computer will coordinate these two actuators, unless the operator adjusts them manually, to the set-points needed to generate the desired net power. Fine-tuning will be done through control of the turbine nozzles. All other control loops operate at part-power exactly as they do at full power.

Startup and synchronization will be done at zero power output with the auxiliary loads taken from the power mains. The ammonia bypass valve and pump will establish a low steady-state evaporation rate. The turbine variable speed nozzles will control the turbine speed. If the plant is connected to an infinite grid, the speed control will disengage after synchronization. If heave-induced oscillations require attenuation, the computer will calculate instantaneous set points and the plant will be controlled to throttle the peaks of the oscillations.

5.4.6 Diagnostics

The points summarized in Figure 5.4-2 are for both operational instrumentation and diagnostic instrumentation of the PSD II power module. Because later operational units may require less instrumentation, one entire input signal conditioning unit services the diagnostic instrumentation and can be removed. Section 5.4.7 describes the signal conditioning units.

When a recording is made, all plant data, operational and diagnostic, are scanned once each second and stored. Historical data that are still resident in core can be called on the CRT in tabular form under seven categories of "system" and "subsystem". Section 5.4.7 shows the software budget for recording and display formats.

TRW identified a steady-state model (Section 5.3.1) and dynamic models (Section 5.3.2) that predict plant performance. In addition, many subsystems require detailed performance calculations. One of the principal functions of PSD-II is to validate these simulation models. Therefore, all measurements needed to validate the models and calculations were included in the Measurements List.

The data required to assess normal plant performance, to determine the cause of abnormal performance and trips, to validate the models, and to evaluate the results of experiments are called "diagnostics". Some diagnostic data are computed in the plant digital computer; most are reduced at an on-shore DOE central processing facility. The mix is presently unknown between the two kinds of calculations desired by DOE. Therefore, some estimates have been made of the amount of diagnostic software that should be resident in the plant computer.

Calculations are needed for such parameters as evaporator liquid level, ammonia quality, and local heat exchange coefficients. To do these calculations in the plant computer would require approximately 500 storage registers and 300 words of program. Assuming that the other six systems and subsystems are equally complex, a total of 3500 words of data storage and 2100 words of program storage is needed.

5.4.7 Plant Computer

Figure 5.4-8 shows the functions performed by the plant computer, as required by Section 5.3.3.5. Each function has been sized in terms of memory and in terms of the number of computer operations to be executed.

For costing purposes, the off-the-shelf MAX II/III executive was chosen to meet software functional requirements with the assumption that software development would be performed on a scientific computer. The MAX II/III

SOFTWARE FUNCTION	WORDS MEMORY	EXECUTIONS PER SECOND	EQUIVALENT ADD-OPERATIONS PER SECOND KIPS
EXECUTIVE	14,000	1	80,000
SELF-TEST	500	1	500
KEYBOARD CRT	1,000	1	1,000
ANALOG/DISCRETE I/O	1,500	1	3,000
RECORDER FORMAT	1,000		
TAPE AND DISK DRIVE	1,000		
CRT FORMATS	11,000		6,000
ALARMS	250	1	500
CONTROL LAW	250	1	400
DIAGNOSTICS	5,600	1	3,000
SUBTOTAL	38,100		94,400
PAD FOR UNCERTAINTY	25,000		94,400
TOTAL	61,100		188,800

Figure 5.4-8. Functions of Plant Computer and Software Budget

requires 14 K words of main memory. Though it contains more functions than are needed for the PSD-II job, it is less expensive than developing a new executive. Self-test software is estimated at 500 words, while 1K words are allocated for keyboard and CRT drivers. Handlers for input-output to the signal conditioners are sized at 1500 words for 550 inputs. Historical data are recorded on magnetic tape. 1000 words are needed to drive the interim disc storage and tape driver and 1000 words to format the data. CRT format generation assumes that 6 CRT formats are generated for each subsystem, for a total of 42 formats, of which 18 are different. Allowing 600 words of code per format requires a total allocation of 11K words for CRT formatting. The CRT unit has internal refresh capability so it need only be driven once per second as data are scanned. The timing estimate assumes 2 CRT formats are being generated at all times. Alarm and trip computations are sized for 90 alarms requiring 100 fixed limits, 100 storage registers, and 50 words of program. Control function requirements discussed in Section 5.4.3 are 250 words. System diagnostic requirements are estimated in Section 5.4.6 to be 800 words per system and subsystem for a total of 5600 words.

Total known software requirements are 36,000 words. At this early stage, a large pad is prudent so a 64,000 word requirement is imposed on the computer. If an on-board high-order language interpreter is desired, if graphic formats are needed, if diagnostic software grows sharply, and if real-time review of historical data is needed beyond 10 seconds, a disk would be needed for virtual memory.

Some of the software may be written in high order language and compiled on a scientific computer. Those programs would require 300 percent more memory and execution time. A resident interpreter may or may not be desired to simplify software changes by the plant operator (DOE may prefer to prepare and verify new programs at a shore-based facility). A resident interpreter would add approximately 40,000 words to the program and would require virtual memory, stored on supplementary discs.

Based on this analysis of computer functions, a Modcomp II was chosen as the baseline computer for costing purposes. It is a standard production model 16-bit digital processor with a proven record of reliable performance in difficult industrial applications. Computer operation is managed by a real-time operating system residing in core. The program is modular and therefore flexible and adaptable to changing requirements of OTEC plant operation and data processing.

The basic executive software program includes codes that control the multi-programming environment, perform task check-pointing, power failure recovery, and handle system traps. The file control services enable the user to perform data recording and other functions required for file control such as open, close, wait, and delete.

The monitor control routine (MCR) is the terminal interface between the user and the real-time operating system. MCR includes: initialization commands, status, messages, task control commands, and system maintenance commands. The MCR organization permits users to add commands to meet special application needs. The real-time operating system provides a dedicated, execute-only environment for monitoring and controlling many real-time processes concurrently.

Program development and system generation takes place in another host computer. This means that all of the system's resources are devoted to supervising real-time application execution.

The main memory is a random-access memory (RAM) of 128 kilobytes (64,000 words). If added memory is needed, as noted above, we plan to add 5 million words of virtual memory of disc.

A disc and magnetic tape are provided to facilitate data recording for permanent archive storage. Each tape can accommodate data for several days of operations. It can be conveniently filed for future reference, for on-shore data reduction, and for off-line simulation studies.

Three signal conditioners (Figure 5.4-1) provide the input and output ports needed from the instrumentation sensors to the computer and from the computer to the control actuators and switches.

Figure 5.4-1 shows an operational input signal conditioner that handles approximately 425 signals, a diagnostic input signal conditioner that handles approximately 150 signals, and an output signal conditioner that handles approximately 50 continuous signals and 90 discretes, all operational. Each signal conditioner consists of multiplexers, sample-hold circuits, analog-to-digital converters or digital-to-analog converters, a power supply, and electromagnetic interference filters. One shelf unit of the signal conditioner can accommodate 256 analog inputs or 64 analog outputs, or any combination. The signal conditioner can be expanded to a maximum of 2048 differential inputs or 4096 single-ended inputs. This capacity provides more than adequate flexibility for future expansion. A requirement is imposed on the instrumentation system to sample all data once per second. A 10 second burst of all data is recorded each hour, on operator command, and when an alarm is detected by the plant computer. A running record of the past 2 minutes of data is stored on disc (120 samples of 550 measurements) for display or recording by the operator. Records are made on tape that are stored in the control room and transported to DOE data processing centers.

5.4.8 Trips and Alarms

The operational requirements for trip and alarms are discussed in Section 5.3.3.8. This section describes the implementation.

Three kinds of trips are:

- Full trip
 - Operator action
 - Ammonia overpressure in evaporator
 - Ammonia overpressure in condenser
 - Seawater subsystem trip (GFE)
 - Wave action trip (GFE)
- Trip to zero power
 - Operator action
 - Excessive ammonia pump power
 - Generator overload or underload (motoring)
 - Turbine overspeed
 - Loss of turbine oil pressure
- Ammonia Plant Trip
 - Operator action
 - Automatic trip sensors to be defined.

A full trip stops the water pumps and the ammonia pumps, shuts the turbine inlet trip valve, opens the bypass and does other actions in the sequence described in Section 5.3.4. The second kind of trip is to zero power, which stops the ammonia pumps, shuts the turbine valve, and lets the water pumps and ammonia support plant operate. The sequence of events is shown in Section 5.3.4.

A zero-power trip allows a rapid restart. An ammonia support subsystem trip places the ammonia plant in a safe state without affecting the ability to generate power. It is initiated manually from the PSD-II control room or from the local panel, or is initiated automatically.

Redundancy requirements for the protective trips are based solely on economics. If any safety trips are identified, their design will be based on redundant logic. Pending the results of the economic analysis, dual

sensors and transducers are required for all trips. Sensors and transducers may be shared with the control systems. One channel of trip logic must be wired and independent of the control computer. The other can be wired or can be performed in the computer; the latter is chosen for PSD-II. Each trip actuator has logic that trips if the computer channel or the wired channel indicates a trip. Though such logic may cause a few inadvertent trips, it has the great advantage of increasing the probability of protecting the costly experimental system from damage. The detailed design will determine, from MTBF and the cost of OTEC outages, whether dual redundancy is economically correct.

Approximately 90 alarms have already been defined, Figure 5.4-2, for all PSD-II subsystems. The alarmed-sensors connect to a device that permits upper, lower, or upper and lower alarm levels to be set. Alarms operate lights on the mimic board, lights on an annunciator panel, and an audible annunciation. The second alarmed-sensor channel passes into the computer where an out-of-limit condition trips the recorder and is displayed on the status CRTs.

Interlocks are provided in the manual and automatic modes. Two typical interlocks might be:

- Verify turbine oil pressure before opening a closed turbine trip valve
- Remove nonessential loads when transferring to ship's power

As usual in complex control system designs, interlocks are only provided to protect against damage; unnecessary interlocks are avoided since the plant designer cannot predict all actions that an operator may take, especially in abnormal conditions.

5.4.9 Instrumentation Wiring

Figure 5.4-1 shows the wiring plan. Individual field wires are brought into the cable-spreading room, above the control room, where they connect to terminal blocks. The terminal blocks are wired downward to the control room with cable bundles of approximately #18 wire. Wiring from the control room to the computer room below is also with #18 wires, many of which are shielded. Cabling to the console in the control room is run beneath the floor, not to obstruct the operators' view of the wall boards.

The average horizontal length of wiring from the field to the terminal blocks is 60 feet. Adding 30 percent for vertical runs, the average length is 90 feet.

For estimating purposes, 220 points are assumed to require two wires and 350 points are required to require four wires. As a result, there are 1800 wires from the control room to the field and there are 3600 terminations to be connected. A circumferential cable tray runs around the machinery room (in addition to cable trays for power wiring) 12 feet above the floor. Tray length was estimated at 550 feet with dual trays at the entrance to the cable-spreading room. The trays are filled to 50 percent capacity allowing for growth. To minimize wire length and tray length and to help protect against fire, half of the wire goes around the tray in one sense and the other half in the other sense. Instrumentation wiring is run in separate trays and conducts from power wiring to reduce electromagnetic interference. Drops to transducers and actuators from the trays are in conduit. Estimates are based on 400 conduits, each 12 feet long, for a total of 4800 feet of conduit.

5.5 RELIABILITY, AVAILABILITY AND MAINTAINABILITY

5.5.1 Introduction and Conclusions

Analyses of the power system for reliability, availability, and maintainability indicates that

- The 10 MWe power system with aluminum heat exchangers can meet the DOE objectives of 90 percent availability and 95 percent startup reliability for scenarios ranging from zero leakage up to an end-of-life (EOL) cumulative 10 percent leaky tubes.
- System availability is enhanced due to heat exchanger modularization which permits shutdown and repair of heat exchangers on a subassembly basis (quarter heat exchanger) while the remaining three subassemblies are kept in operation.
- Although we do not expect a significant number of leaky tubes in the Alclad aluminum heat exchangers, we have made plans and provisions for determining, isolating and repairing leaky tubes.
- The major impact of a significant number of leaky tubes is a reduction in system availability and an increase in power generation costs.

- Redundant ammonia feed pumps are required to provide 0.95 startup reliability.
- Nominal major preventive maintenance cycle calls for 2 weeks total plant shutdown and repair every 2 years.

5.5.2 Reliability, Availability, Maintainability (RAM) Requirements

The system RAM requirements are defined by the DOE as follows:

- Design of the 10 MWe power system shall be based on a 30 year design life at 8000 hours of operation per year with at least 1000 start/stop cycles.
- Redundancy of design shall ensure continuity of key functions as well as fail safe operations.
- Provisions shall be made for efficient maintenance during downtime.
- Operability assurance shall be, after an initial checkout period, 90 percent at a 60 percent confidence level.
- System startup reliability (successful starts divided by attempted starts) shall be 95 percent at a 60 percent confidence level.

5.5.3 Approach and Assumptions

The approach to satisfying these requirements is to choose system components with a long life consistent with initial capital and operating costs targets and constraints. To determine the best arrangements and/or components, a cost analysis is performed in which the present value cost of the arrangement and/or component is determined for the 30 year life of the power plant. This analysis provides the true life cycle costs and permits effective comparisons for choosing various system and/or component options. The power module design life requirement of 30 years can be readily achieved for most system components, including the turbine, generator, pumps, piping, valves, and tanks. Rotating machinery will require nominal maintenance for adjustment, monitoring wear, and replacing seals and bearings. With maintenance these components should last 30 years.

The aluminum heat exchangers are the major system components that do not have a 30 year life expectancy. The life of aluminum heat exchangers is projected as 15 years. Thus the heat exchangers must be replaced once during the 30 year life of the plant. Stainless steel heat exchangers are expected to last 30 years and would not require replacement.

Heat exchanger maintenance and replacement is simplified by the configuration and modularity concept of the Linde plate-type heat exchanger modules. The evaporator and condenser are formed of heat exchanger modules (see Section 3) such that one heat exchanger subassembly (25 percent of the heat exchanger) may be replaced while the remaining three subassemblies continue to operate. This improves plant availability and reduces the size of the maintenance crew.

Modularization of the heat exchangers also permits tube repair and plugging of one subassembly while the other three subassemblies are kept in operation. The availability analysis (Section 5.5.4) shows what maintenance schedules must be formulated to permit 8000 hours per year operation and to give an operability assurance of 90 percent.

The availability analysis has evaluated startup reliability and indicates the component redundancy required to meet the startup reliability requirement of 0.95. The significant result is that redundant ammonia feed pumps are required to achieve a system startup reliability of 0.95.

5.5.4 Availability and Reliability

5.5.4.1 Basic Definitions

The utility industry is now in the process of creating industry-wide unified definitions of reliability and availability through an Edison Electric Institute (EEI) committee. These terms are currently defined as follows, according to EEI and Federal Energy Administration reports (References 5-8 and 5-9).

The calendar elapsed time, T_C , at a power plant is subdivided as follows:

- 1) "On" time = service time = T_S . Includes full power and part power service time
- 2) Outage time = $T_O = T_{OD} + T_{OF} + T_{OS}$
 - a) Scheduled outage time = T_{OD}
 - b) Forced outage time - unscheduled outage time = T_{OF}
 - c) Startup time, T_{OS} , when plant is being started or restarted and is not connected to the grid.

The energy, E , delivered during the service time allows for fluctuations in net power:

$$E = \int_0^{T_S} P(t) dt$$

where $P(t)$ is the instantaneous net power output at the time, t . The average output power, P_a is E/T_S . Over a period of time, which the availability analysis takes to be a year:

$$\text{Reliability} = R = \frac{\text{Service Time}}{\text{Service Time} + \text{Forced Outage Time}} = \frac{T_S}{T_S + T_{OF}}$$

$$\text{Availability} = A = \frac{\text{Service Time}}{\text{Elapsed Time}} = \frac{T_S}{T_C} = \frac{T_S}{T_S + T_0}$$

Reliability is the probability that the plant will deliver any power at all when it is not down from scheduled maintenance. Availability is the probability that the plant delivers any power at all; it penalizes the plant for schedule outages and forced outages alike. The availability analysis computes availability, averaged over yearly periods. To allow for plant operation at part-power, "equivalent reliability" and "equivalent availability" are defined, based on power-weighted operating time.

During the elapsed time T_C , N_S attempts are made to start the plant. N_{SS} of them are successful on the first try whereas N_{SU} are unsuccessful. The following startup parameters are introduced:

$$\text{Startup Reliability} = \frac{\text{Number of Successful Starts}}{\text{Number of Attempts to Start}} = \frac{N_{SS}}{N_S}$$

$$\text{Startup Failure Ratio} = \frac{\text{Number of Failures to Start}}{\text{Number of Attempts to Start}} = \frac{N_{SU}}{N_S}$$

$$\text{Mean Time to Start} = \frac{\text{Startup Time}}{\text{Number of Attempts to Start}} = \frac{T_{OS}}{N_S}$$

5.5.4.2 Equipment Failure and Repair Rates

The failure-modes-and effects-analysis (FMEA, in Section 5.5.7) identifies the contribution of the equipment and components to plant outages. This section describes how we model the failure rates of those pieces of equipment and their repair times.

Wearout Failures. Figure 5.5-1 shows the equipment that is assumed to wear out, due to causes such as bearing wear, contact wear and corrosion. An overall average wearout time of 740 days was chosen with a normal distribution whose standard deviation is 120 days, based on the frequency of failures reported in Reference 5-2.

EQUIPMENT	WEAROUT PART
TURBINE/GENERATOR	SEAL HOT RADIAL BEARING HOT THRUST BEARING LABYRINTH BLADE CONTROL VALVE
NH ₃ EVAPORATOR AND CONDENSER	TUBES SEAM WELDS
NH ₃ FEED PUMP/MOTOR	SEAL BEARING WEAR-RINGS SWITCHES
NH ₃ CONTROL VALVES	REPLACEABLE VALVE INSERTS ON ENTIRE VALVES
NH ₃ SUPPORT/HORIZONTAL RADIAL PUMP	SEAL BEARING WEAR RINGS SWITCHES
NH ₃ SUPPORT/VERTICAL SUNDYNE PUMP	SEAL BEARING SWITCHES IMPELLER

Figure 5.5-1 Wearout Failures

After each wearout failure, unless there is a redundant backup, the plant is assumed to shutdown for a repair time equal to the random failure mean time to repair (MTTR).

Scheduled Maintenance. A tradeoff study was performed in order to determine the effect on system availability, performance and cost of various strategies of performing scheduled (preventive) maintenance. The two periods for scheduled maintenance chosen are at 360 days and 720 days.

During the scheduled maintenance period, the plant will be completely shutdown (i.e., no power production). The estimated downtime is 7 days for a 360 day cycle and 14 days for a 720 day cycle, after which the plant is assumed to be restored to as-new condition.

During the shutdown, maintenance checks and repairs will be performed on all rotating machinery, valves, support systems and instrumentation. Additionally, leaky tubes will be plugged. If the time for plugging leaky tubes exceeds the scheduled downtime, then plugging of leaky tubes will continue on either 1 or 2 of the heat exchanger subassemblies while the remaining heat exchanger subassemblies and the power system will be started and brought up to partial power. The modularity of the heat exchangers permits this partial operation during tube plugging which improves the system capacity factor and reduces power generation costs. Section 5.3.1.6 shows that the plant delivers 85 percent of rated power with one subassembly removed.

A significant result of the system reliability simulation is that a 2 year scheduled maintenance cycle is required in order to meet the startup reliability requirement of 0.95 at a 60 percent confidence level. The 1 year preventive maintenance (PM) cycle gives a 60 percent confidence startup reliability of 0.938, which is somewhat less than the 0.950 requirement. The 2 year PM cycle gives a value of 0.957. Evaluating all the pertinent factors shows that system availability, startup reliability, number of leaky tubes, time period before a leaky tube is plugged, and amount of ammonia leaked are all interrelated. The results indicate that incorporating a 2 year PM cycle to satisfy startup reliability requirements results in a larger cost penalty due to a greater amount of leaked NH_3 before a perforated tube is plugged.

It is important to realize just what the costs are to achieve the required startup reliability. These costs are discussed in more detail in Section 6.1.

Random Failures. Any equipment that does not exhibit wearout is assumed to fail at random, with an exponentially-distributed probability of failure. The mean-times-between-failures (MTBF) are shown in Figure 5.5-2 and the mean-times-to-repair (MTTR) are shown in Figure 5.5-3

for each component. The MTTR include the time necessary to isolate the fault (from the monitored data); to locate defective parts or failed equipment; to access the equipment for repair or replacement(s); to perform the repair or effect the replacement(s); to checkout the corrective maintenance, and to prepare the system for startup. MTTRs do not include extended logistics delay (to order parts).

ITEM/NOMENCLATURE	QUANTITY	MTBF (HR)	DATA SOURCE(S) USED
1. COLD WATER PUMP/MOTOR	1	17,280	FARADA
2. WARM WATER PUMP/MOTOR	1	17,280	FARADA
3. GENERATOR	1	69,500	TRW REPORT, C. F. BRAUN, RADC
4. SWITCHGEAR	1	43,800	TRW REPORT, C. F. BRAUN
5. NH ₃ POWER LOOP PIPING	1	104,100	REACTOR SAFETY STUDY
6. BUTTERFLY VALVE (ISOLATION)	21	333,400	REACTOR SAFETY STUDY, RADC
7. CHECK VALVE	1	331,800	REACTOR SAFETY STUDY, RADC
RELIEF VALVE	8	100,000	REACTOR SAFETY STUDY, RADC
TRIP VALVE	1	87,800	C. F. BRAUN (EVAPORATOR/CONTROL VALVE ESTIMATES)
BYPASS VALVE	1	87,800	C. F. BRAUN (EVAPORATOR/CONTROL VALVE ESTIMATES)
FLOW CONTROL VALVE	1	87,600	C. F. BRAUN
8. CONDENSER SUMP AND CONNECTIONS	1	48,700	TRW REPORT, EPRI (CONDENSER DATA)
EVAPORATOR SUMP AND CONNECTIONS	1	48,700	TRW REPORT, EPRI (CONDENSER DATA)
9. TURBINE	1	17,600	TRW REPORT, C. F. BRAUN
10. TURBINE STATOR VANE CONTROL	1	17,600	C. F. BRAUN
11. CONDENSER AND CONNECTIONS	1	48,700	TRW REPORT, EPRI
EVAPORATOR AND CONNECTIONS	1	48,700	TRW REPORT, EPRI
12. CONDENSER TUBES ***	81,800	11,500	EPRI, TRW ESTIMATE ***
13. EVAPORATOR TUBES ***	81,600	11,500	EPRI, TRW ESTIMATE
14. PUMP/MOTOR (FEED)	2	8,800	TRW REPORT, C. F. BRAUN, REACTOR SAFETY STUDY
15. SYSTEM AUXILIARIES	1	10,000**	TRW ESTIMATE
16. NH ₃ SUPPORT SUBSYSTEM	1	88,000	REACTOR SAFETY STUDY
17. PHASE SEPARATORS	4	400,000	TRW ESTIMATE

**INCLUDES INSTRUMENTATION AND CONTROL COMPONENTS.

***ENCOMPASSES ALL OTHER TUBE/TUBE SEAM TYPE FAILURES BUT DOES NOT INCLUDE PERFORATION OF ALUMINUM TUBE WALL.

Figure 5.5-2. Mean-Time-Between-Failures (MTBF) Estimates for 10 MWe Equipment

ITEM/NOMENCLATURE	MTTR (HR)	DATA SOURCE(S) USED
1. COLD WATER PUMP/MOTOR	80	TRW REPORT, C. F. BRAUN
2. WARM WATER PUMP/MOTOR	80	TRW REPORT, C. F. BRAUN
3. GENERATOR	80	TRW REPORT, C. F. BRAUN
4. SWITCHGEAR	8	TRW REPORT, C. F. BRAUN
5. NH ₃ POWER LOOP PIPING	14	TRW ESTIMATE
6. BUTTERFLY VALVE (ISOLATION)	11	TRW ESTIMATE
7. CHECK VALVE	18	TRW ESTIMATE
RELIEF VALVE	16	TRW ESTIMATE
TRIP VALVE	18	C. J. BRAUN (EVAPORATOR CONTROL VALVE ESTIMATE)
BYPASS VALVE	18	C. J. BRAUN (EVAPORATOR CONTROL VALVE ESTIMATE)
FLOW CONTROL VALVE	18	C. F. BRAUN
8. CONDENSER SUMP AND CONNECTIONS	52	EPRI (CONDENSER DATA)
EVAPORATOR SUMP AND CONNECTS	52	EPRI (CONDENSER DATA)
9. TURBINE	90	C. F. BRAUN
10. TURBINE STATOR VANE CONTROL	26	C. F. BRAUN
11. CONDENSER LIQUID SUMP AND VAPOR HEADER	52	EPRI (CONDENSER DATA)
EVAPORATOR LIQUID SUMP AND VAPOR HEADER	52	EPRI (CONDENSER DATA)
12. CONDENSER TUBES AND CONNECTIONS	•	TRW ESTIMATE
13. EVAPORATOR TUBE AND CONNECTIONS	•	TRW ESTIMATE
14. PUMP/MOTOR (FEED)	12	C. F. BRAUN
15. SYSTEM AUXILIARIES	50	TRW ESTIMATE
16. NH ₃ SUPPORT SUBSYSTEM	24	TRW ESTIMATE
17. PHASE SEPARATOR	18	TRW ESTIMATE

*SEE SECTION 5.5.4.2, TUBE REPAIR ACTION TIME (HOURS)

Figure 5.5-3. Mean-Time-To-Repair (MTTR) Estimates for 10 MWe Equipment

Heat Exchanger Tube Failures and Repair. The timeline sequence for the corrective maintenance (repair) action is accomplished in five steps: Shutdown, N₂ purge, tube repair (which includes identifying and plugging leaks), NH₃ fill, and startup. The time (in-house) to repair tubes in the condenser and evaporator is:

Shutdown	1
N ₂ purge	4
Tube repair identification and plugging (n = number of leaky tubes)	n/3
NH ₃ charge	4
Startup	1

$$10 + n/3 \text{ hrs}$$

5.5.4.3 Computer Simulation

The availability/reliability analysis is a simulation of the 10 MWe power system for a 30-year period using a TRW-developed computer program, OTECSOS. The program is a Monte Carlo analysis, which is far more accurate than the conventional calculation of the uptime ratio = $MTBF / (MTBF + MTTR)$, because the latter does not allow for:

- 1) Buildup of service queue when several parts wearout within a short time of each other.
- 2) Scheduled outages for preventive maintenance.

OTECOS models the wearout and random failures described in Section 5.5.4.2. Using random-number generators, OTECSOS predicts the unscheduled failures that occur over thousands of lifetimes of the simulated plant, taking twelve trials per day for 30 years. Scheduled and unscheduled failures can cause plant outages. Other random-number generators predict the repair time as the failures leave the repair queue. The statistics of plant outages are collected in the computer memory and are analyzed. Figure 5.5-4 shows the flow diagram of the program which is described in detail in Reference 5-2. Figure 5.5-5 shows the reliability model of the PSD-II power cycle. This flow diagram shows the power system components whose failures disable the plant. Single-point failure components are drawn in series; dual redundant components are drawn in parallel.

5.5.4.4 Heat Exchanger Tube Leakage and Plugging Model

Tube leakage and plugging of leaky heat exchanger tubes impact system availability and maintenance requirements. In order to evaluate these impacts, it was necessary to formulate a mathematic model which describes the rate at which ammonia leaks would develop in the heat exchanger as a function of the length of time the heat exchanger has been in operation. This model was integrated into the OTECSOS computer program to reflect the effects of tube leakage and plugging on:

- Availability/capacity factor
- Operational power-average and minimum
- Downtime and preventive maintenance

Figure 5.5-4. Flow Diagram OTECSOS Program

Availability/capacity factor is affected by this model because of the effects of leakage and plugging on operational power and downtime, both of which contribute to reduce the availability. Leakage results in NH_3 loss, while plugging controls such loss at the expense of reduced power. Plugging also requires periodically a crew of maintenance personnel and partial exchanger shutdown. The model accommodates the alternatives of different periodic preventive maintenance and heat exchanger renewal policies, leakage and plugging rates, and renewal times.

Figure 5.5-5. Operable Simulation Input Data Block Program for Failure Repair Expectation

In the simulations, a leakage algorithm was empirically developed that would accelerate the number of leaks with each sequential time period:

$$\text{Cumulative percentage leaky tubes} = \frac{(N)(N+1)(N+2)(N+3)}{C}$$

where

C = constant

N = age of heat exchanger, years

Figure 5.5-6 depicts the rate at which tube leaks develop as a function of the fractional life of the heat exchanger. This leak generation algorithm was chosen to quantitatively represent the expected rate at which aluminum would corrode and develop pits, eventually leading to perforations in the tube wall.

Figure 5.5-6. Hole Generation Model (Normalized)

At the alternative 10 and 15 year heat exchanger life configurations, potential end-of-life 5 and 10 percent tube leakages were modeled. Depending on 1 or 2 year preventive maintenance, plugging of tubes was simulated at the expense of lost power and partial downtime of the plant. Loss of power generation capacity was equated in the model as directly proportional to the proportion of heat exchanger tubes plugged.

5.5.4.5 Pump Redundancy

The availability of the power module was calculated with and without redundant ammonia feed pumps. The MTBF and MTTR of the pumps are shown in Figure 5.5-2 and 5.5-3. In the redundant configuration, the MTBF of random failures in the operating and standby pumps are assigned to be identical. However, wearout failures are charged only to the operating pump. It was assumed to take 5 minutes to detect and switch from a failed operating pump to the standby pump. A failure of the standby pump while the first pump is being repaired causes a plant outage until one of the pumps is repaired.

5.5.4.6 Startup Reliability

OTEC SOS was used to estimate startup reliability using the definitions of Section 5.5.4.1. When maintenance on a failed component is completed and the component is checked out, a plant startup is attempted. Failure to start can occur because a new failure has occurred, because the repair was improperly done and not discovered during checkout, or because the repaired component was incorrectly connected in the system. These probabilities were difficult to compute, so an approximation was made that startup failures historically resulted in unusually long MTTR. Thus in the analysis failures to start occur when the randomly selected repair time exceeds 3 times the average expected repair time.

5.5.4.7 Results of Availability/Reliability Analysis

Some 30 cases were simulated on the computer using the OTEC SOS program and varying the basic parameters of heat exchanger life, numbers of leaking tubes, and preventive maintenance cycles.

A typical computer input/output printout for the case of 10 year heat exchanger life with 5 percent tube leaks (at end-of-life) and 2 year preventive maintenance cycle is shown in Figure 5.5-7.

Simulation results are summarized in Figure 5.5-8 and are briefly discussed below. The redundant pump configuration gives a higher availability, fewer outages and less downtime on the average than does the non-redundant pump configuration. The redundant pump configuration was chosen as the baseline because it met the DOE availability and startup reliability goals, while the non-redundant configuration did not, as shown in Figure 5.5-9.

OTECOS-SYSTEM OPERABILITY SIMULATION OTEC- I. DASHAY

R = .28415061

MEAN SVC TIMES FOR UNIT ACCESSIBILITIES, MTBF FOR EACH UNIT
NO. OF REDUNDANT UNITS RED SWITCH RATIO TO SVC TIME

S(1) = 3.330	FU(1) = 720.000	RU(1) = 0.000	SWTH(1) = .01000
S(2) = 3.330	FU(2) = 720.000	RU(2) = 0.000	SWTH(2) = .01000
S(3) = 3.333	FU(3) = 2692.000	RU(3) = 0.000	SWTH(3) = .01000
S(4) = .333	FU(4) = 1825.000	RU(4) = 0.000	SWTH(4) = .01000
S(5) = .580	FU(5) = 4338.000	RU(5) = 0.000	SWTH(5) = .01000
S(6) = .460	FU(6) = 661.000	RU(6) = 0.000	SWTH(6) = .01000
S(7) = .750	FU(7) = 347.000	RU(7) = 0.000	SWTH(7) = .01000
S(8) = 2.170	FU(8) = 1013.000	RU(8) = 0.000	SWTH(8) = .01000
S(9) = 3.750	FU(9) = 720.000	RU(9) = 0.000	SWTH(9) = .01000
S(10) = 1.080	FU(10) = 720.000	RU(10) = 0.000	SWTH(10) = .01000
S(11) = 2.170	FU(11) = 1013.000	RU(11) = 0.000	SWTH(11) = .01000
S(12) = 2.290	FU(12) = 460.000	RU(12) = 0.000	SWTH(12) = .01000
S(13) = 2.290	FU(13) = 460.000	RU(13) = 0.000	SWTH(13) = .01000
S(14) = .500	FU(14) = 360.000	RU(14) = 1.000	SWTH(14) = .01000
S(15) = 2.080	FU(15) = 916.000	RU(15) = 0.000	SWTH(15) = .01000
S(16) = 1.000	FU(16) = 3600.000	RU(16) = 0.000	SWTH(16) = .01000

ENTER SERV ASSN TIMES PER DAY, NO. OF SYSTEMS, REDUNDANCY ADDED
RATIO DOWN/OPERATING FAULTS, AND TIME FOR CHECKOUT

C = 12.0 R = 1.0 RED = 0.0 FDR = 1.000 CT = .0031 SW = .0005

ENTER MECH EQUIP EXP WEAR TIME, STD DEV, MULTIPLE OF DPR EQUIP SVC TIME

U = 740 DD = 120 K = 2

ENTER MECH MAINTENANCE TIME /MONTHS, AUTO CHK EFFECTIVENESS

L = 720.00 ACHK = 1.000

ENTER NO. SVC OPNS, NO. OF YEARS AND A 1 FOR YEARLY DETAIL

P = 4 I = 30 D = 1.00

ENTER PERIODIC PREVENTIVE MAINTENANCE DAYS DOWN = 14.00

STARTUP FAIL DOWNTIME SPEC, XMD = 3.0000 CAPACITY UNITS,

CAP = 10.000 TRAFFIC UNITS, TRAF = 10.000

STAND DEV TRAF, SDTRAF = 2.500, TRAVEL TIME, TRAV = .00001

UNITS PER SYSTEM, UPS = 1, ALLOW FAIL, ALF = 0

REP TURNARND, TRD = 30, POWER CAPACITY, PWRCAP = 10

HEAT EXCHANGER TIME-TO-REPLACE, HERPT = 3.500, CONST = 171600

HEAT EXCHANGER TOTAL TUBES, TUBES = 21600, PLUG RR = 3

M.E. REPLACE PERIOD, REPO = 10.0

PM PERIOD SIMULATION RESULTS

AVAILABILITY	SY RELIA	START SVC	DWNTIME	RAND FAIL	WEAR FAIL	LKYSR	CUM	AVAIL	SPARES	PM	PWRAV
.9522404	1.0000	0	34.05	14	0	39	.9522404	1	14.97	9.99512	
.9387241	.9474	1	42.13	19	0	200	.9454823	1	17.74	9.97064	
.9326019	.9286	1	41.74	14	1	569	.9412188	1	25.64	9.90094	
.8977153	.9565	1	57.06	23	0	1232	.9303429	1	42.76	9.74989	
.9229162	1.0000	0	55.50	19	1	1019	.9288576	1	17.51	9.99996	
.9579116	1.0000	0	29.96	14	0	35	.9337116	1	14.91	9.99569	
.9234357	.9000	1	53.25	10	1	195	.9322435	1	17.61	9.97179	
.9451993	1.0000	0	32.60	12	0	584	.9338631	1	25.73	9.90019	
.8991304	.9474	1	55.26	19	0	1317	.9300039	1	44.02	9.73853	
.9476775	.9286	1	37.67	14	0	1065	.9317713	1	17.50	9.99999	
.9397342	.9565	1	43.12	23	0	16	.9324952	1	14.87	9.99598	
.9202495	1.0000	0	55.55	19	1	197	.9314746	1	17.61	9.97185	
.9409268	1.0000	0	35.52	14	0	607	.9322017	1	26.03	9.89752	
.8821121	.9000	1	67.09	10	0	1387	.9266239	1	45.30	9.72751	
.9330850	1.0000	0	18.28	12	1	1003	.9289213	1	12.29	9.55207	

SUMMARY BASED ON 30 YEARS OF SIMULATION

AVAILABILITY = .9289213, TOT DOWNTIME DAYS = 656.36, WEAR FAIL = 5, TOT STARTUP FAIL = 8
CUM SY RELTA = .96680 SPARE REQ = 1 CUM FAIL = 241 XSTRAF = 79, TOT HEAT XCHNG PLUGS = 10230
TOT AVG POWER, MW = 9.893

Figure 5.5-7. Typical Computer Printout Showing Availability Analysis Results

SIMULATION RESULTS	PERCENTAGE OF TUBE LEAKS AT END-OF-LIFE			
	5% (10-YEAR REPLACEMENT LIFE)	10% (10-YEAR REPLACEMENT LIFE)	5% (15-YEAR REPLACEMENT LIFE)	10% (15-YEAR REPLACEMENT LIFE)
30-YEAR AVAILABILITY				
-1 YEAR PM (PREVENTIVE MAINTENANCE)	.9083	.8773	0.910	0.880
-2 YEAR PM	.929	.912	0.925	0.904
30-YEAR CUMULATIVE FAILURES (RANDOM AND WEAROUT)				
-1 YEAR PM	209	209	209	209
-2 YEAR PM	241	241	241	241
30-YEAR DOWNTIME				
-1 YEAR PM	854	1069	843	1048
-2 YEAR PM	659	733	678	772
30-YEAR STARTUP RELIABILITY				
-1 YEAR PM	.9522	.9522	.9522	.9522
-2 YEAR PM	.9669	.9669	.9669	.9669
30-YEAR STARTUP RELIABILITY (60 PERCENT CONFIDENCE)				
-1 YEAR PM	.9348	.9384	.9384	.9384
-2 YEAR PM	.9569	.9569	.9569	.9569
30-YEAR AVERAGE OPERATING POWER, MW				
-1 YEAR PM	9.858	9.718	9.865	9.730
-2 YEAR PM	9.893	9.787	9.884	9.729
STARTUP RELIABILITY - SINGLE NH ₃ FEED PUMP				
-2 YEAR PM			0.9337	
DOE GOALS (60 PERCENT CONFIDENCE)				
- OPERATING AVAILABILITY			0.90	
- STARTUP RELIABILITY			0.95	

Figure 5.5-8. Key Simulation Results

The results indicate that the 10 MWe power system with aluminum heat exchangers can meet the DOE objectives of 90 percent (average annual) availability and 95 percent startup (average) availability for up to 10 percent of leaking tubes (at end-of-life of heat exchangers), even if the heat exchanger lasts only 10 years (with 2 years preventive maintenance cycle).

The results of these computer simulation analyses are useful for system design, operation and maintenance planning. TRW's approach to an operability/maintainability plan is based on this analysis.

5.5.5 Operability/Maintainability Plan

The basic operability plan is summarized in Figure 5.5-10. Operability of the 10 MWe system is predicted on the need to perform daily

AVAILABILITY PARAMETERS	REDUNDANT PUMPS	NON-REDUNDANT PUMPS
• ANNUAL AVAILABILITY		
MINIMUM	0.9174	0.9053
AVERAGE	0.9418	0.9355
MAXIMUM	0.9707	0.9562
• TOTAL DOWNTIME, DAYS (30-YEAR PLANT LIFE)	603	671
• STARTUP RELIABILITY		
MINIMUM	0.9000	0.8182
AVERAGE	0.9668	0.9337
MAXIMUM	1.000	1.000

Figure 5.5-9. Availability/Reliability of Ammonia Feed Pumps

DAILY OPERATION MONITORING AND CORRECTIVE MAINTENANCE	ANNUAL/BI-ANNUAL PREVENTIVE MAINTENANCE
<ul style="list-style-type: none"> • RECORD CRITICAL PRESSURES, TEMPERATURES, VOLTAGES, CURRENTS, FLOW RATES AND OTHER KEY PARAMETERS AND INITIATE CORRECTIVE MAINTENANCE • NOTE VIBRATIONS OR UNUSUAL SOUNDS AND INITIATE CORRECTIVE MAINTENANCE • MAINTAIN OIL AND OTHER FLUID LEVELS PER MANUFACTURER REQUIREMENTS • DETECT LEAKAGE FROM CONNECTIONS, PIPING, TUBING, TANKS OR OTHER ENCLOSURES AND INITIATE CORRECTIVE MAINTENANCE • CHECK VALVE OPERATION FOR STICKING OR LEAKAGE AND INITIATE CORRECTIVE MAINTENANCE • FOR MATERIAL SURFACES, NOTE NEED FOR ADDED PROTECTION AND/OR REPAIR AT NEXT CORRECTIVE OR PREVENTIVE MAINTENANCE • ASSURE PROPER OPERATION OF TUBE CLEANER 	<ul style="list-style-type: none"> • INSPECT TURBINE, GENERATOR, PUMPS, MOTORS, AND ROTATIONAL SENSORS OR OTHER DEVICES FOR WEAR OF BEARINGS OR MOVING CONTACT SURFACES AND REPLACE AS NECESSARY • INSPECT SEALS AT ALL CONNECTIONS/POINTS AND REPLACE IN ALL COMPONENTS PER MANUFACTURER RECOMMENDATIONS OF IF LEAKS EXIST • INSPECT ALL VALVES FOR PROPER RESPONSE AND REPLACE AS NECESSARY • INSPECT NH₃ AND WATER VESSELS AND REPAIR OR REPLACE WHERE LEAKS OR MATERIAL DETERIORATION IS EVIDENT • INSPECT ALL ELECTRICAL COMPONENTS FOR INSULATION DETERIORATION, POOR CONTACT OR IMPROPER PERFORMANCE AND REPLACE AS NECESSARY • INSPECT HEAT EXCHANGER AND PLUG LEAKING TUBES • MANUAL CLEANING OF BIOFOULED SURFACES • REPLACE HEAT EXCHANGER AT REQUIRED INTERVALS

Figure 5.5-10. Basic Operability Maintainability Plan

inspections and reviews of monitored data to detect any signs or trends of anomalous behavior. It is further assured by the periodic maintenance of equipment that is subject to wear or other known environmental deterioration rates with respect to time. A preliminary maintenance plan to implement the desired system operability is described in the paragraphs below. It covers both system and critical component aspects of preventive and corrective maintenance, as well as overhaul and spares support. An extensive electronics instrumentation system monitors the plant and computes diagnostic data (Section 5.4).

5.6.5.1 System Maintenance

To minimize equipment downtime, maintenance on-board the vessel will be supported by a round-the-clock maintenance crew. PSD-II power system equipment design supports this level of maintenance with provisions for isolation of malfunctions to the faulty component (turbine, generator, heat exchanger, pump) which are repairable by trained and experienced personnel. Diagnostic computer software and equipment manuals isolate the fault to a replaceable component part (e.g., seals, bearings, connectors, switches, etc.). Repair on-board will include limited welding and machining. A minimum of one complete set of spare items is required on-board the vessel at the time of installation. Spares will be obtainable directly from the manufacturer.

Based on the initial operability analysis, an estimated 10-person maintenance crew is required to maintain the 10 MWe power system on a 24-hour-per-day basis:

- Two mechanic/pipefitters

- Two mechanic/welders

- One roving operator (oiler)

- Two millwrights

- Three electrician/instrumentation engineers.

A crew schedule of 12-hours-on and 12-hours-off shifts for two foremen/engineers and three 8-hour shifts for mechanics may be used. The crew will perform all routine preventive maintenance activities, as well as normal corrective maintenance. Additionally, the crew will prepare for

major nonroutine repairs such as tube plugging. During preventive maintenance shutdowns, the equipment will be inspected and appropriate service actions accomplished.

5.5.5.2 Equipment Maintenance

Turbine. The maintenance concept for the turbine is to perform preventive and corrective maintenance on-board the platform. Corrective maintenance consists of fault isolation and replacement of bearings, seals, labyrinths, and maintenance of lube and seal oil system, etc. A complete inventory of spare radial bearings, thrust bearings, couplings, coupling hubs and seals, interstage labyrinths, interstage diaphragms, oil pump bearings and seals will be maintained on-board. Following replacement of a failed item of equipment, a new part will be ordered.

The turbine fault isolation will include data from constant monitoring of vibration, speed, bearing temperature, oil temperature, and turbine efficiency.

A general inspection and on-board overhaul will be accomplished during the preventive maintenance period. It is anticipated that the on-board overhaul interval will be 4 years and the overall time out of service will be 140 hours.

Generator. The maintenance concept for the generator is to perform preventive and corrective maintenance on-board the ocean vessel. Corrective maintenance consists of fault isolation and replacement of bearings, field windings and maintenance of cooling and lubrication systems, in addition to replacement of worn components.

The generator fault isolation incorporates monitoring of bearing temperature, oil temperature, vibration, voltage, frequency and winding temperature by instrumentation and alarms. The field windings will be tested and results recorded periodically in order to detect insulation degradation.

Ammonia Feed Pumps/Motors. The maintenance concept for the pumps is to perform preventive and corrective maintenance on-board the platform. Corrective maintenance consists of fault isolation and replacement of bearings, seals, etc. A complete inventory of spare parts or packing, sleeves, wear rings, and bearings will be maintained on the platform. Following replacement of a failed item of equipment, a new part will be ordered.

Preventive maintenance will include review of data from a daily inspection and bearing oil level check as well as the periodic test of the redundant pumps/motors. Additional requirements will be refined during detail design and identified in the individual equipment manuals.

Heat Exchangers. The maintenance concept for the heat exchangers is to perform corrective maintenance (tube plugging) on-board the platform. In addition to corrective maintenance, intermodule heat exchanger gaps will be periodically inspected and cleaned. Requirements will be refined during detail design and identified in the individual equipment manual. The heat exchanger tubes will be cleaned on a regularly scheduled basis (see Section 3.4). Low level chlorine will be injected into the seawater continuously to reduce the fouling. Corrective maintenance consists of identifying and plugging leaking tubes (see Section 5.5.7) when the leak rate exceeds an acceptable limit. Crews will be specially trained for this. A general inspection will be accomplished during scheduled shutdown regardless of performance. Any discrepancies noted will be corrected.

Flow Control, Bypass, Relief, and Butterfly (Isolation) Valves. Corrective maintenance consists of fault isolation and replacement of packing, seal rings, or actuator components. A complete inventory of spare packing, seals, and actuator components will be maintained on-board.

Preventive maintenance of these valves consists of a daily inspection for leaks in the packing and for open/close status. Excessive leakage will be cause for module shutdown for replacement. A complete inspection/refurbishment will be accomplished on an as needed basis during scheduled shutdown.

Switchgear. Corrective maintenance includes replacement of faulty circuit breakers, relays, transducers, transformers, and fuses. A complete inventory of spares will be maintained on the platform.

Preventive maintenance consists of:

- 1) Annual testing/calibration of 5 kV switchgear and testing of all power circuit breaker tripping mechanism, during plant shutdown.
- 2) Annual exercising of automatic transfer switch and annual testing/calibration of transfer switch voltage sensing relays.

5.5.6 Ammonia Leak Detection

5.5.6.1 Objectives and Requirements

The ammonia leak detection system must detect leakage of ammonia into ambient air, (from pumps, valves, fittings, etc.) and leakage into seawater from heat exchanger tubes and tube panel joints). The detectors will be capable of sensing 0.1 ppm of ammonia in the exit water box for bulk detection, 1.0 ppm level of ammonia concentration in the composite (cluster of 120 tubes) and 1.0 ppm in individual tubes.

5.5.6.2 Leak Detection in Ambient Air

Leakage of ammonia gas into ambient air will be detected with an infrared analyzer calibrated for a full-scale range of 0 to 300 ppm ammonia in air. Fourteen sampling locations will be strategically selected to provide ammonia concentrations to a central panel, and alarm when leakage occurs. This is a conventional method of ammonia leakage detection.

5.5.6.3 Leak Detection in Seawater

The concentration of ammonia in seawater will be measured using a Technicon Autoanalyzer Monitor IV system. This is an integral monitoring unit incorporating a phototube calorimeter capable of detecting 0.01 ppm ammonia. Each heat exchanger has a unit sampling water effluent in the water box.

Leaks in the heat exchanger to the seawater must be detected at a sensitivity level less than 0.10 ppm ammonia. Each heat exchanger

contains 81,600 tubes with a nominal ID of 0.75 inch. The evaporator and condenser, each, has one tube cleaner (see Section 3.4) which cleans 120 tubes simultaneously with three dimensional position controls. The cleaning head indexes to each group of 120 tubes every 6 minutes until the lot has been cleaned by traversing brushes in and out of each tube.

The ammonia leak detector design is similar to that developed for PSD-1 and is fully described in Section 2.6.4 and Appendix H of Reference 5-2.

The ammonia leak detection sampling system has three modes of operation: 1) bulk outlet sampling, 2) composite tube sampling, and 3) individual tube sampling.

The bulk outlet sampling mode consists of aspirating tubes located in the outlet stream of each subassembly of the heat exchanger tube bundle. Individual samples can be withdrawn from each tube by pumping into a mixture reservoir at atmospheric pressure. The reservoir provides a continuous flow sample to an auto-analyzer monitoring continuously. When the bulk sample exceeds a recorded 0.10 ppm level, an audio/visual alarm is initiated. The general leak location of the particular subassembly can be determined by sampling the subassembly sampling tubes individually by sequencing the air operated valves.

After the bulk outlet sampling mode identifies that a bulk leak exists, two methods of identification of leaking tubes are available. If the leak is major (tube rupture or equivalent) the subassembly will be shutdown for leak identification. If the leak is minor, permitting system operation while identifying and repairing the leak, the composite sampling mode of leak detection may be employed.

This concept consists of directing a modified tube cleaner to the indicated subassembly and commencing a composite sampling of a group of 120 heat exchanger tubes. Sample seawater is taken from each tube. The tube cleaner will be modified with hollow tubes to allow sample seawater flow from heat exchanger tubes through the tube cleaner to the storage reservoir (see Figure 5.5-11). Transporting the sample fluid is accomplished by differential pressure from the heat exchanger outlet to a reduced pressure reservoir. Two reservoirs are provided since the chemical

diagnostic auto-analyzer has a lag time of 3 to 7 minutes and the cleaning cycle is 6 minutes. The first reservoir contains 120 individual containers which are filled with a sample from each tube. These samples are sized to contain 50 ml of seawater. A composite sample from 2 to 120 tubes may be obtained by the overflow from the 50 ml container which is collected at the bottom of the reservoir. A labeled sample is drawn at atmospheric pressure from a preprogrammed composite size for analysis. The cleaning head progresses to the next group of 120 tubes with only a composite sample stored in a second reservoir. If the first sample does not indicate a composite leak, all the effluents will be discharged.

Figure 5, 5-11. Reservoir Location and Brush Assembly

In the event the first composite reservoir sample indicates ammonia concentration above 1.0 ppm, then samples are taken from each of 120 tubes sequentially (from samples previously stored and labeled within the first reservoir). The unique feature of this mode is the transportation of seawater samples by a single pump (vacuum) and the labeling and storage of these samples which separates both a composite and an individual sample. A degree of complexity is required for the valving of 120 samples. If there is no leak indication from the original bulk sample, then all samples are discarded for readiness of subsequent groups. During the analyzing time of 3 to 7 minutes, the other composite samples are collected and distributed to the auto-analyzer after 6 minutes. If either of the composite reservoirs indicate excessive ammonia, then the individual tube reservoirs will repeat the process for that group. The existing tube cleaner is utilized to minimize costs.

5.5.7 Heat Exchanger Tube Plugging

As discussed in Section 3.5, there are data that suggest an Alclad aluminum heat exchange could have a life of 10-15 years in seawater. However, because of the variability and scatter of the test data, there is no great certainty that leaks would not develop during the life of the aluminum heat exchangers. Because of this uncertainty, a maintenance plan encompassing plugging of leaky tubes was developed as well as several conceptual designs for tube plugging devices.

5.5.7.1 Requirements, Assumptions and Approach

The necessity of plugging heat exchanger tube leaks is based upon cost, performance, environmental factors and safety issues. Large numbers of leaking tubes could result in an excessive loss of ammonia with a resultant cost and performance penalty which can become significant. Excessive release of ammonia could have detrimental environmental impact.

A hole size of only 0.001 inch will leak NH_3 at the rate of approximately 0.0053 lbs per hour. A 0.010 inch diameter hole will leak approximately 0.53 lbs per hour. The type, number and size of holes that would develop in aluminum tubes exposed to seawater are unknown at this time. However, the possibility exists of a significant number of leaks developing in the aluminum heat exchangers especially after many years in service.

The operability and maintenance plan for dealing with leaking heat exchanger tubes considers two types of leaks:

- Catastrophic - tube rupture with attendant rapid loss of large quantities of ammonia
- Non-catastrophic - pin hole leaks (0.001 to 0.010 inch diameter)

In a catastrophic tube failure, the leaking heat exchanger subassembly will have to be shut down immediately for repairs. Non-catastrophic leaks can be dealt with on a routine preventive maintenance schedule which provides for partial heat exchanger shut down every year or two.

The desire to minimize the quantity of leaking ammonia drives the repair schedule to plug tubes as soon as possible after leak detection. However, considering the time (labor and plant downtime) to repair, and the reduced power output after tube plugging, leads to a stretched out repair schedule. Minimization of the impact on the power system, then, would consider all these factors to arrive at an optimum tube plugging schedule. The power generation cost impact due to ammonia leakage, tube plugging and subsequent reduced power plant net output power is further discussed in Section 6.1.

Due to the rate at which holes are expected to develop in aluminum tubes with time (see Figure 5.5-6), a preventive maintenance cycle to accommodate tube plugging is one that would allow for plugging more and more tubes as the life of the heat exchanger increases. This will reflect back into determination of an optimum preventive maintenance cycle which will probably allow for shorter preventive maintenance cycles as the operating life of the aluminum heat exchangers increases. Minimum power generation cost is the significant optimization parameter. However, a DOE 30 year availability requirement of 0.90 must be met. This requirement may set a lower limit for the frequency of shutdown for tube plugging.

5.5.7.2 Heat Exchanger Tube Plugging Concepts

Three concepts have been developed for tube plugging:

- 1) "In-situ" concept
- 2) "Hypodermic" concept
- 3) Expandable Hose concept

All concepts require shutdown of the heat exchanger subassembly and require prior identification, cleaning, draining, purging and drying of the leaky tubes. The concepts completely block off the leaky tube of a heat exchanger module as well as the other three heat exchanger tubes in the downstream and/or upstream modules, i.e., the four lengths of heat exchanger tubes representing a single seawater flow "tube" through the heat exchanger subassembly are all completely sealed off even though only one of the four tubes in series is leaking.

The reason for this is when one tube is blocked off, biofouling cleaning of the other three tubes is no longer practical. Since fouled tubes are more prone to develop leaks via pitting under biogrowths, they must be either kept free of fouling, or they must be plugged.

- 1) In the "in-situ concept" (see Figure 5.5-12) a tube of special design is inserted in the full length of the four modules forming a heat exchanger subassembly. This tube has many perforations along its length and is fitted with expanding rubber "donuts" located to line up with the tube entrance and exit of each of the four modules of a heat exchanger subassembly. After this tube is inserted in place, tube plugging material is injected into the tube which; (1) fills and expands the rubber donuts isolating each module, and (2) flows through the injection tube wall holes filling up the annular space between the injection tube and the heat exchanger tube. This complete unit is left in place and becomes an integral part of the bonding matrix.
- 2) In the "hypodermic concept" (see Figure 5.5-13) a long tube is inserted in the full length of all four modules of the subassembly. Plug material is injected through this tube into the perforated heat exchanger tube. The injection tube is slowly withdrawn as the plug material fills the tube. Indexing of the injection tube will allow cessation of plug material injection as the injection tube is pulled through the heat exchanger intermodule gaps, thus precluding extraneous deposition of plugging material in the intermodule gap.
- 3) Expanding hose concept (see Figure 5.5-14) - This concept involves insertion of a thin walled, flexible and expandable plastic or rubber tube down the full length of the leaky heat exchanger tube. After the tube is fully inserted, foaming compound is injected into the flexible tube. The injected material then foams causing the rubber tube to expand and set, resulting in complete blockage of the leaky tube.

Figure 5.5-12. Tube Plugging: "In-Situ" Concept

Presently concept No. 1 is the leading candidate tube plugging option. It offers the best possibility of a positive closure of leaky tubes and features controlled injection of sealant fluid without spillage into the heat exchangers inter-module gap. Further design definition and development is however indicated in the detail design phase.

Figure 5.5-13. Tube Plugging: "Hypodermic" Concept

Figure 5.5-14. Tube Plugging "Expandable Hose" Concept

5.5.8 Failure Modes and Effects Analysis

The purpose of the failure modes and effects analysis (FMEA) is to identify those equipment failures that can cause safety hazards, reduce power output, or cause a plant outage. The probability of plant outage was discussed in Section 5.5.4, using the results of the FMEA and the failure rates of the components. The subtle effects of failures on power reductions, as compared to power outages are discussed in Section 5.5.4.3.

The results of FMEA are shown in Figure 5.5-15A and B. The key failure modes are identified and the detection methods are noted for each failure effect.

The failure modes identified in this table are those that are (in most cases) likely to cause degradation and may eventually require module shutdown for repair. A notable exception is failure of the air-operated valve controller for the butterfly isolation valves because manual override will be incorporated.

The FMEA includes the instrumentation and control component switch and the auxiliary equipment, as noted in Figures 5.5-2 and 5.5-3. The instrumentation and control design (Section 5.4) includes enough redundancy that plant operation can continue after loss of an electronic component

The methods of detecting each failure in Figure 5.5-15 are included in the diagnostic sensors and diagnostic software described in Section 5.4.

5.6 MATERIALS COMPATIBILITY

The materials of the power system are chosen to be compatible with seawater, the working fluid ammonia and with other materials in the power module system.

This section discusses the overall system materials compatibility, including potential problems, approaches and design solutions.

Section 3.4 addresses the biofouling and control measures. Section 3.5 discusses heat exchangers materials selection and corrosion. Section 3.7 discusses life cycle cost analysis of heat exchangers, because the materials (aluminum alloys) are expected to deteriorate from exposure to the OTEC environment.

NOMENCLATURE	FUNCTION	FAILURE MODE/MECHANISM	COMPONENT/ FUNCTION	SYSTEM	DETECTION METHOD	PROVISIONS REDUCED TO CRITICALITY
SEAWATER PUMPS/ MOTORS*	PROVIDE FLOW OF SEAWATER TO HEAT EXCHANGERS	THRUST BEARING WEAR	DEGRADED PUMP SPEED/FLOW	DEGRADED OUTPUT EVEN- TUAL MODULE	MEASURE PUMP HEAD AND FLOW NOISE VIBRATION	DESIGN FOR LONG LIFE; PREVENTIVE MAINTENANCE; PROVIDE ADEQUATE LUBRI- CATION
		STEADY BEARINGS OR BUSHINGS	DEGRADED PUMP PERFORMANCE	SAME AS ABOVE	SAME AS ABOVE	DESIGN FOR LONG LIFE; PROVIDE FOR CLEAN SEA- WATER FOR LUBRICATION
		SHAFT SEAL WEAR	STEADY BEARING DAMAGE	SAME AS ABOVE	SAME AS ABOVE	DESIGN FOR LONG LIFE; PREVENTIVE MAINTENANCE
		DRIVE SHAFT OR OPEN FRACTURE	LOSS OF DRIVE/ NO OUTPUT	MODULE SHUT- DOWN	NO OUTPUT; NO FLOW PRESSURE	DESIGN FOR WORST CASE LOADS (I.E., STARTUP/ SHUTDOWN)
		MOTOR FAILURE	NO OUTPUT	MODULE SHUT- DOWN	NO OUTPUT; NO FLOW	PROVIDE FOR PERIODIC TEST/ RECORD TO DETECT DEGRA- DATION
GENERATOR*	GENERATE ELECTRIC POWER	BEARING WEAR	VIBRATION OR SEIZURE	MODULE SHUT- DOWN	DEGRADED OR NO OUTPUT	DESIGN FOR LONG LIFE; PROVIDE FOR ADEQUATE LUBRICATION MAINTENANCE
		LOSS OF COOLING SYSTEM	OVERHEAT	MODULE SHUT- DOWN	TEMPERATURE ALARM	PROVIDE FOR PREVENTIVE MAINTENANCE
		ROTOR OR STATOR	NO OUTPUT	MODULE SHUT- DOWN	NO OUTPUT	PROVIDE FOR PERIODIC TEST/ RECORD TO DETECT DEGRA- DATION
TURBINE STATUS VANE CONTROL*	PROVIDES FOR TUR- BINE SPEED CONTROL	LINKAGE AND BUSHING WEAR	DEGRADED PERFORMANCE	LOSS OF EFFICIENCY	DEGRADED OUTPUT	PERIODIC INSPECTION/ REFURBISHMENT
TURBINE	CONVERT HEAT ENER- GY TO ROTATIONAL	BEARING WEAR	VIBRATION DEGRADED PERFORMANCE	MODULE SHUT- DOWN	DEGRADED OUTPUT	DESIGN FOR LONG LIFE; PROVIDE FOR ADEQUATE LUBRICATION AND PREVEN- TIVE MAINTENANCE
		RADIAL BEARING OVERHEAT	SEIZURE	MODULE SHUT- DOWN	LUBRICATION TEMPERATURE	DESIGN FOR LONG LIFE; PROVIDE FOR PREVENTIVE MAINTENANCE, I.E. PERIODIC TURNAROUND INSPECTION/ REPAIR
		THRUST BEARING OVERHEAT	BLADE RUBBING	MODULE SHUT- DOWN	LUBRICATION TEMPERATURE	
		SEAL WEAR	DEGRADED PERFORMANCE	REDUCED OUTPUT	NH ₃ MAKEUP/ RECOVERY	
		INTERSTAGE LABYRINTH WEAR	LOSS OF EFFICIENCY	REDUCED OUTPUT	REDUCED OUTPUT	PERIODIC TURNAROUND INSPECTION/REPAIR
		LUBRICATION AND SEAL OIL SYSTEM FAILURE	TURBINE TRIP	NO OUTPUT	TURBINE TRIP	PROVIDE REDUNDANCY
NH ₃ FEED PUMP MOTOR	SUPPLY NH ₃ TO EVAPORATOR SUMP	BLADE FAILURE	EXCESSIVE VIBRATION	MODULE SHUT- DOWN	LOSS OF POWER	SPECIAL ATTENTION TO MATERIALS SELECTION, NAT- URAL FREQUENCY, OPERAT- ING SPEED, AND NOZZLE FLOWING MURKIN DESIGN PERIODIC TURNAROUND FOR INSPECTION/REPAIR
		SEAL WEAR	PRESSURE LOSS	DEGRADED PERFORMANCE; POSSIBLE SHUTDOWN	LOSS OF FLUID	REDUNDANT PUMPS, DOUBLE MECHANICAL SEALS
		BEARING WEAR	DEGRADED PERFORMANCE	REDUCED OUT- PUT; POSSIBLE MODULE SHUTDOWN	PRESSURE/ TEMPERATURE SENSORS	REDUNDANT PUMPS
		DRIVE SHAFT FAILURE	NO OUTPUT	POSSIBLE MOD- ULE SHUTDOWN	PRESSURE SENSOR	REDUNDANT PUMPS
SWITCHGEAR	TRANSFER ELECTRICAL POWER TO DIS- TRIBUTION POINTS; PROVIDES CIRCUIT PROTECTION	MOTOR FAILURE	NO OUTPUT	POSSIBLE MOD- ULE SHUTDOWN	PRESSURE SENSOR	REDUNDANT PUMPS
		PROTECTIVE RELAY FAILURE	LOSS OF PROTECTION		TEST AND INSPECTION	PROVIDE FOR PERIODIC TEST/INSPECTION AND CALI- BRATION
HEAT EXCHANGERS**	TRANSFER HEAT TO/ FROM NH ₃	TRANSFORMER	CIRCUIT DISCON- TINUITY	NO OUTPUT	NO OUTPUT	PROVIDE FOR PERIODIC OPERATING TEMPERATURE MONITORING
		TUBE LEAK OR RUPTURE	NH ₃ LOSS INTO SEAWATER	DECREASE IN EFFICIENCY; EVENTUAL MODULE SHUTDOWN	NH ₃ LEAK DE- TECTION IN SEAWATER NH ₃ MAKEUP	PROPER DESIGN AND MATER- IALS SELECTION; PERIODIC CLEANING; FLUID LEAKING TUBES; REPLACE HEAT EX- CHANGER SUB-ASSEMBLY WHEN AMMONIA LEAK RATE EXCESSIVE OR WHEN MAXI- MUM NUMBER OF TUBES HAVE BEEN PLUGGED
		SHELL CORROSION AND OR LEAKING CONNECTIONS	NH ₃ LOSS	MODULE SHUT- DOWN	NH ₃ MAKEUP SENSORS (GNIFFERS)	PROPER DESIGN AND MATER- IALS SELECTION; PERIODIC CLEANING AND PAINTING CATHODIC PROTECTION

* SHIP'S EQUIPMENT

** TURNAROUND INSPECTION REFURBISHMENT SHOULD COINCIDE WITH OCEAN VESSEL TURNAROUND.

Figure 5.5-15A. Analysis of 10 MWe Failure Mode and Effects

NOMENCLATURE	FUNCTION	FAILURE MODE/MECHANISM	COMPONENT/ FUNCTION	SYSTEM	DETECTION METHOD	PROVISIONS REDUCED TO CRITICALITY
NH ₃ SUMPS	STORAGE OF NH ₃ FOR POWER LOOP	CORROSION AND/OR LEAKING CONNECTIONS	NH ₃ LOSS	MODULE SHUT-DOWN	NH ₃ MAKEUP SENSORS (SNIFFERS)	PROPER DESIGN AND MATERIALS SELECTION, PERIODIC CLEANING AND PRUNING
NH ₃ PIPING	PROVIDES FLOW OF NH ₃ THROUGH POWER LOOP	PIPE RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN	PRESSURE DROP SENSORS (SNIFFERS)	ENSURE PROPER MATERIAL SOLUTION AND PREVENTIVE MAINTENANCE
		WELD LEAK	NH ₃ LOSS	MODULE SHUT-DOWN	PRESSURE DROP SENSORS (SNIFFER); NH ₃ MAKEUP	ENSURE PROPER WELDING
		GASKET LEAK/ RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN (RUPTURE) OR DEGRADED PER PERFORMANCE	PRESSURE DROP SENSORS (SNIFFER); NH ₃ MAKEUP	ENSURE PROPER GASKET MATERIAL SELECTION AND PROVIDE FOR PREVENTIVE MAINTENANCE
VALVES, RELIEF	PROTECTS POWER LOOP FROM OVER-PRESSURE	FAILS TO OPEN	POSSIBLE DAMAGE TO POWER LOOP FROM OVER-PRESSURE	POSSIBLE MODULE SHUTDOWN	PRESSURE SENSORS	PROPER DESIGN AND PERIODIC INSPECTION/TEST AND CALIBRATION
		PREMATURE OPEN	NH ₃ LOSS	POSSIBLE MODULE SHUTDOWN	NH ₃ MAKEUP PRESSURE SENSORS	SAME AS ABOVE
VALVE, FLOW CONTROL	CONTROLS NH ₃ FLOW TO EVAPORATOR	EXTERNAL LEAK/ RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN	NH ₃ MAKEUP PRESSURE SENSORS (SNIFFER)	PROPER DESIGN AND PERIODIC INSPECTION/TEST
		FAILS TO OPERATE	ABILITY TO CONTROL FLOW OF NH ₃ TO EVAPORATOR	POSSIBLE MODULE SHUTDOWN	FLOW INDICATION	PROVIDE MANUAL OVERRIDE TO PERMIT MANUAL CONTROL
		EXTERNAL LEAK (STEM PACKING)	NH ₃ LOSS	POSSIBLE MODULE SHUTDOWN	FLOW INDICATION SENSORS (SNIFFER)	PERIODIC INSPECTION AND PACKING REPLACEMENT
		EXTERNAL LEAK/ RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN	NH ₃ MAKEUP PRESSURE SENSORS (SNIFFER)	PROPER DESIGN AND PERIODIC INSPECTION/TEST
		STEM FRACTURE	LOSS OF CONTROL	MODULE SHUT-DOWN	FLOW INDICATION	PERIODIC INSPECTION
		STUCK DISC	LOSS OF CONTROL	POSSIBLE MODULE SHUTDOWN	FLOW INDICATION	PERIODIC INSPECTION
		INTERNAL SEAL LEAKAGE				
VALVE, TRIP AND VALVE, BYPASS	PROVIDES FOR TURBINE/GENERATOR SAFETY PROTECTION	FAILS TO OPERATE	ABILITY TO STARTUP OR ISOLATE TURBINE	MODULE START-UP DELAY OR LOSS OF TURBINE; CONTROL MODULE SHUT-DOWN	TURBINE INSTRUMENTATION NH ₃ FLOW INDICATION	DESIGN FOR FAIL SAFE POSITION; PERIODIC INSPECTION PROVIDE MANUAL OVERRIDE
		EXTERNAL LEAK (STEM PACKING)	NH ₃ LOSS	POSSIBLE MODULE SHUTDOWN	NH ₃ MAKEUP SENSORS (SNIFFER)	PERIODIC INSPECTION AND PACKING REPLACEMENT
		EXTERNAL LEAK/ RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN	NH ₃ MAKEUP PRESSURE SENSORS; SENSORS (SNIFFER)	PROPER DESIGN; PERIODIC INSPECTION/TEST
		STEM FRACTURE	LOSS OF CONTROL	MODULE SHUT-DOWN	FLOW INDICATOR	PERIODIC INSPECTION
		STUCK DISC	LOSS OF CONTROL	MODULE SHUT-DOWN	FLOW INDICATOR	PERIODIC INSPECTION
		INTERNAL SEAL LEAKAGE	LOSS OF POSITIVE SHUTOFF			PERIODIC SEAL INSPECTION/ REPLACEMENT
						PROVIDE MANUAL OVERRIDE
VALVE, BUTTERFLY (ISOLATION)	PROVIDES FOR ISOLATION OF POWER LOOP COMPONENTS DURING REPAIR	FAILS TO OPERATE (AIR OPERATED VALVE)	LOSS OF REMOTE CONTROL	POSSIBLE DELAY IN STARTUP OR SHUTDOWN		
		EXTERNAL LEAK (STEM PACKING)	NH ₃ LOSS	POSSIBLE MODULE SHUTDOWN	NH ₃ MAKEUP SENSORS (SNIFFER)	PERIODIC INSPECTION AND PACKING REPLACEMENT
		EXTERNAL LEAK/ RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN	NH ₃ MAKEUP PRESSURE SENSORS (STIFFNESS)	PROPER DESIGN; PERIODIC INSPECTION/TEST
		STEM FRACTURE	LOSS OF CONTROL	MODULE SHUT-DOWN	FLOW INDICATION	PERIODIC INSPECTION
		STUCK DISC	LOSS OF CONTROL	MODULE SHUT-DOWN	FLOW INDICATION	PERIODIC INSPECTION
		INTERNAL SEAL LEAKAGE	LOSS OF POSITIVE SHUTOFF	POSSIBLE TOTAL PURGE TO REPAIR COMPONENT BEING ISOLATED		PERIODIC SEAL INSPECTION/ REPLACEMENT
VALVE, CHECK	PREVENT REVERSE FLOW FROM EVAPORATOR SUMP TO NH ₃ FEED PUMPS	FAILS TO OPEN	LOSS OF FLOW	MODULE SHUT-DOWN	NO FLOW INDICATION	PERIODIC INSPECTION/TEST
		REVERSE LEAK	ABILITY TO PREVENT REVERSE FLOW	POSSIBLE MODULE SHUTDOWN		PERIODIC INSPECTION/TEST
		EXTERNAL LEAK, RUPTURE	NH ₃ LOSS	MODULE SHUT-DOWN	NH ₃ MAKEUP FLOW INDICATION SENSORS (SNIFFER)	PROPER DESIGN; PERIODIC INSPECTION
NH ₃ SUPPORT SUBSYSTEM****	SUPPLY MAKEUP TO POWER LOOP	SUBSYSTEM INOPERATIVE	NO MAKEUP NH ₃	MINIMAL IMPACT		

*** POWER LOOP WILL CONTINUE TO OPERATE. OPERATING TIME WILL DEPEND ON TOTAL LEAKAGE AND NH₃ LEVELS OF SUMPS AT TIME OF SUBSYSTEM SHUTDOWN.

Figure 5.5-15B. Analysis of 10 MWe Failure Mode and Effects (Continued)

5.6.1 Requirements and Objectives

- a. The hardware shall have an operational life in the ocean environment (saltwater corrosion, biofouling) consistent with the design life noted in Section 2. Sealing problems associated with the subsystems shall be addressed.
- b. Equipment that cannot be fabricated of materials resistant to an ocean environment will be designed with sealed casings, compartments, or protective coatings to ensure that design life, availability, and reliability goals are met.
- c. As materials are evaluated and selected for operation in these environments, they shall be clearly identified with the criteria for selection.

5.6.2 Design Approach

The materials for the power module components and auxiliary equipment are selected with the objective of satisfying the 30 year design life through an optimum repair/replacement/maintenance program. In selecting specific materials, the following guidelines were used:

- All selected materials must have a reasonable delivery (availability) and be fabricable by methods currently available to the industry.
- Ammonia-side materials must conform to OSHA Standard 1910.11, "Storage and Handling of Anhydrous Ammonia," and the proposed amendments to the standard published in the Employment Safety and Health Guides, Number 259, 7 March 1976.
- The pressure containing portions of the heat exchangers must conform to the applicable portions of the ASME pressure vessel codes (Sections II, V, VIII Division 1, and IX).
- The selected materials must meet the applicable structural and thermal requirements of the power system.
- Dissimilar metals, as defined in MS3358G, shall not be in direct contact.
- Fungus nutrient materials shall be avoided. When these materials are used and not hermetically sealed, they shall be treated with a suitable fungicidal agent.
- Standard and commercial parts shall be used wherever practical.
- The surface preparation, finish and curing of each component shall meet applicable requirements and be adequate to prevent deterioration from exposure to specified environments that might jeopardize required performance. Finishes shall meet applicable bonding requirements.

5.6.3 Design Materials

Recommended design materials for the PSD-II power system are summarized in Figure 5.6-1. The basic tradeoffs were performed during PSD-I and conceptual design phase of PSD-II.

<u>HEAT EXCHANGER</u>	
PANEL (TUBES)	ALUMINUM ALLOY 3004 CLAD
CLADDING	ALUMINUM ALLOY 7072
STRUCTURAL MEMBERS	ALUMINUM ALLOY 5083
WATER BOXES	SA516, SA283, SA285 STEEL, GLASS FIBER — REINFORCED PLASTIC
WATER BOX, SHELL OR PIPE COATING	GACO N-200-1/N-11R NEOPRENE (OR) NAPKO NO. 5635 COAL TAR EPOXY
<u>SYSTEM</u>	
AMMONIA SYSTEM	STEEL OR CRES* (SPECIFIC COMPOSITION DEPENDENT ON AVAILABILITY)
WATER SYSTEM COMPONENTS	STEEL OR CRES* (SPECIFIC COMPOSITION DEPENDENT ON AVAILABILITY), GLASS FIBER REINFORCED PLASTIC
DESIGNATIONS ARE ASME EXCEPT WHERE NOTED	
*CRES = CORROSION RESISTANT STEEL (AUSTENITIC STAINLESS STEEL)	

Figure 5.6-1. Recommended Design Materials

The materials for the heat exchangers, the principal materials concern, are detailed in Section 3.5. Materials for turbine are addressed in Section 4.1, while pump materials are included in Section 4.3. Piping and valve materials are in Section 5.1. Materials for all components, equipments, valves, piping and instruments are specified on their respective specifications, included in Appendix I Section 8.

5.6.4 Compatibility Issues

The major compatibility issues and our design solutions are presented below.

5.6.4.1 Marine Atmosphere

The water box exterior surfaces of the heat exchanger will be covered with a protective coating. The coating candidates are a zinc-rich inorganic primer overcoated with an epoxy-polyamide and a neoprene based elastomeric coating for the water box.

The neoprene coating has been successfully employed for 32 years in similar applications at the Portishead "A" Power Station in Bristol, England. The coating has shown no signs of degradation and the only maintenance necessary has been recoating of areas damaged by maintenance workers. This material is preferred for coating; however, specific selection will occur during detail design. (Information on this coating can be found in Appendix D2 of PSD-I, Reference 5-2.)

The marine coating system that employs a zinc-rich inorganic primer overcoated with an epoxy-polyamide has a history of ocean service that includes a successful 6-year service under rough-handling conditions on the lift system pipes of the mining ship Glomar Explorer. This service is more severe than that expected for the PSD-II. The manufacturer's data for this coating, Dimetcote 6 solvent-based inorganic zinc primer and Amercoat 83/84 polyamide-cured epoxy top coat (Ameron Corrosion Control Division, Brea, California), is included in Reference 5-2, Appendix D2.

Periodic maintenance and repair is planned for the PSD-II power module. For the heat exchanger the prime areas of concern are the coated surfaces of the water boxes. If the coating is damaged or fails by some mechanism, then corrosion of the steel substrate can occur. Periodic inspection and repair of the coatings will prevent unacceptable corrosive attack. If the cathodic protection system (assumed to be provided by the hull designer) is inadequate, galvanic attack at the supports and connections can occur. Again, periodic inspection and repair will be required to assure structural integrity. Any leak/failure of the tubes will be detected by the ammonia leak detection system. Individual tubes will be plugged to prevent further leakage (see Sections 5.5.6 and 5.5.7).

The ammonia and water system components will be maintained using standard shipboard practices. Replacement of seals, wear parts and maintenance of coatings are routine. Special attention will be given

to erosion and impingement attack of lines (especially at elbows, tees, etc.), valves and pumps. A discussion of the maintenance plan is presented in Section 5.5.5.

5.6.4.2 Ammonia Compatibility of Steel

Bonewitz (Reference 5-10) has shown that stress corrosion cracking (SCC) occurs in mild steel and stainless steel if ammonia is contaminated with air. In the PSD-II system, the operation of the closed loop ammonia cycle causes non-condensibles, including air, and nitrogen and hydrogen from ammonia decomposition, to be continuously swept into the condenser bottom sump (an aluminum vessel). These noncondensibles are periodically purged, thus deaerating ammonia.

Steels that have tensile strengths of approximately 100 ksi are susceptible to SCC in anhydrous liquid ammonia. Susceptibility to SCC is dependent on a number of factors including the operating temperature, strength of the steel, post-weld heat treatment, and purity of ammonia. Experimental and service experience has shown that the presence of 0.2 percent water in ammonia inhibits the SCC of these high strength steels. However, the PSD-II ammonia cycle has water and other non-evaporables present in measurable quantity only in the evaporator sump. Because of this, only steels with a tensile strength of 85 ksi or less and yield strengths of 50 ksi or less have been specified. These steels are of sufficiently low strength so that they can be considered insusceptible to SCC.

5.6.4.3 Dissimilar Metals

Galvanic corrosion occurs when two dissimilar metals are electrically joined and are exposed to a conducting medium (electrolyte) such as seawater. In essence, a battery is formed resulting in dissolution of metal at the anode and generation of hydrogen at the cathode. A current flows through the dissimilar metal couple to sustain the reaction. Aluminum is anodic to most materials of construction, including iron and steel, which are major materials in the system exclusive of the heat exchangers.

In the entire system, the major dissimilar metal couplings are at the inlet manifold, the outlet manifold and the base support structure of the heat exchangers. There are minor dissimilar metal couplings at the vent,

drain and instrumentation line connections to the heat exchangers. Dissimilar metal couplings are okay in the system. The resulting galvanic couplings have been minimized by proper design and material selection.

Galvanic corrosion at the heat exchangers has been minimized by providing complete electrical insulation of the exchangers. Non-metallic gasketing between the inlet and outlet pipes and the heat exchanger manifolds (including isolation of the flange bolts), insulated structural mounts, and isolated instrumentation lines on the seawater side have been included in the design.

Aluminizing steel by means of hot dipping or flame spraying also alleviates galvanic corrosion. However, this method was not recommended because the coatings must be free of voids and be dependable in service. Additional maintenance is required to assure its reliability.

Cathodic protection may be employed using either sacrificial anodes or impressed current techniques. The geometry of the interfaces and system surfaces are such that the cost and complexity of a cathodic protection system is prohibitive. This was not considered further in the design.

5.6.4.4 Avoidance of Heavy Metal Ions

It is known that pitting attack on aluminum can be accelerated in the presence of heavy metal ions, particularly copper ions. Concentrations of 0.02 to 0.05 ppm of copper ions reportedly cause localized dissolution of the aluminum oxide surface which leads to pit initiation. Therefore, no copper-bearing alloys are specified in the system, nor should they be used in the seawater pumps.

5.7 SYSTEM SAFETY, REGULATORY REQUIREMENTS & ENVIRONMENTAL IMPACT

5.7.1 System Safety

The power module system is designed for safe operation and maintenance. Potential hazards have been identified and will be minimized using proper design. During the detail design and fabrication phase, additional system safety analyses will be conducted. Consequently, in the preliminary design phase, system safety effort has been oriented towards identification and elimination of potential hazards that might affect the system in service.

5.7.1.1 Safety Issues

The most significant hazards arise from ammonia. These include ammonia combustion and explosion, ammonia spills, physiological effects and corrosion. Other hazards may arise from oil and electrical fires, rotating machinery, for which overspeed, leak and personnel protection must be considered, and electrical shocks. The hazards of chlorine include spills, physiological effects and corrosion.

5.7.1.2 Design Features and Safety Precautions

The system will satisfy applicable ASME codes, Coast Guard regulations and other government and industrial codes as appropriate. It is designed to Chemical Safety Data Sheet Sd-8 of the Manufacturing Chemists' Association and Pamphlet G-2 of Compressed Gas Association. System specifications and procurement specifications reflect accelerations (g loadings) established by DOE. Adequate safety margins have been included in the structural design. Preliminary failure mode and effects analysis was conducted (refer to Section 5.5.8), and the entire system design is basically fail safe.

Seals and glands are designed with an ammonia recovery system that passes the leaked ammonia vapor to the treatment plant. Leak detection subsystem is designed to detect quickly ammonia leaking into seawater, and tube plugging procedures have been developed to seal ammonia leaks. See Sections 5.5.6 and 5.5.7) To minimize ammonia leakage axial joints have been used. The turbine utilizes barrel construction with end wall joints which are easier to seal. Mechanical shaft and seals are used for the turbine. For centrifugal pumps tandem mechanical seals are specified.

The instrumentation and controls provide safety protection in the form of alarms, easily operated trip switches and automatic trips for critical

parameters. Remote operation and redundancy ensure the safety of the crew. Redundant overspeed trips are provided for the turbine generator. All other rotating machinery is AC-motor driven and is limited to the synchronous speed of the motor field. Exposed rotating parts, such as couplings, have guards in accordance with OSHA requirements, Paragraphs 1910.211 through 1910.222. The power module is designed to avoid ignition sources. The flash and ignition points of all oils are moderately high. The electrical system is designed in accordance with Class I Group D Environment and National Electrical Code Article 501. All instrumentation is explosion-proof.

The generator switch gear and wiring design includes features for electric shock protection of operating and maintenance personnel, e.g., interlock barriers, automatic guards, capacitor discharge, connector codes, alarms and electrical grounding.

The design and specifications restrict the use of copper, silver, zinc, mercury and copper base alloys such as brass and bronze in connection with the storage or handling of ammonia. Since aluminum is anodic to common materials of construction, heat exchangers are electrically isolated from surrounding dissimilar metal structures. Installation and maintenance procedures specify these requirements.

Materials are specified to be stress relieved to eliminate residual stresses. Air, oil and other contaminants are kept out of the system by noncondensable/nonvaporable removal, reducing the possibility of stress corrosion.

5.7.1.3 Safety Plan

During the detail design and fabrication phase, system safety analyses and studies will be conducted to ensure that all potential hazards are identified, evaluated and acted upon. The program safety goal is elimination of accidents and the identification of safety concerns and risks that could result in injury to personnel or damage to equipment.

5.7.1.4 Safety Interfaces

It is recognized that the DOE has the responsibility for establishing the overall safety requirements on the plant ship. Therefore, the system integration contractor (SIC) must be responsible for ensuring

installation of appropriate protection systems such as ammonia/chlorine/nitrogen leak detection systems, smoke detection and fire protection systems, ventilation and deluge systems, personnel protection and emergency rescue/evacuation systems, etc.

5.7.2 Regulatory Requirements

Although the DOE is the lead agency for the PSD-II project, three primary federal agencies also influence licensing, since the OTEC-1 vessel will be situated within the 200-mile US Economic Resource Zone: The Environmental Protection Agency (EPA), the Army Corps of Engineers (ACE) and the US Coast Guard (USCG). Regulatory requirements and permits are discussed below. Based on previous experience with the OTEC-1 project, no problems are expected in obtaining permits from these agencies.

5.7.2.1 Environmental Protection Agency

In accordance with the Clear Water Act and the Federal Water Pollution Control Act Amendments of 1972 (PL 92-500), EPA is the agency with regulatory jurisdiction over the discharge of pollutants (i.e., as the OTEC discharge) into the waterway from a point source (i.e., the OTEC-1 vessel). Such discharges are authorized only by permits issued either by EPA or an approved state agency, and are part of the National Pollutant Discharge Elimination System (NPDES). The OTEC-1 vessel is considered by EPA to be a new point source discharge on a vessel at sea; therefore, an NPDES permit is required to operate OTEC-1.

5.7.2.2 Army Corps of Engineers

In accordance with the Rivers and Harbor Act of 1899, the Marine Protection and Sanctuaries Act of 1972, and the Federal Water Pollution Control Act Amendments of 1972, ACE permits are issued to protect the nation's water resources, to maintain water quality by protecting environmentally valuable wetland resources, to prevent alteration or obstruction of navigable U.S. waters, and to control dumping into ocean waters.

A Department of the Army permit is required for testing PSD-II heat exchangers aboard the OTEC-1 vessel since the platform is considered an obstruction to navigation.

5.7.2.3 U. S. Coast Guard

The regulatory scope of the Coast Guard is primarily safety, enforcement and navigation. The Marine Inspection Office (MIO) requires a vessel permit that stipulates allowable types of vessel markings (i.e., lights, structures, etc.), safety equipment, and marine sanitation devices. The MIO also publishes a Notice to Mariners and can have a vessel charted (mapped).

Marine sanitation devices similar to those of the OTEC-1 test vessel have been considered and found to comply with current federal standards of performance as stipulated in Coast Guard regulations.

5.7.3 Environmental Impact and Awareness

The potential environmental impacts which may result from the operation of PSD II have been identified as follows:

- Organism entrainment
- Ocean water mixing
- Metallic ion releases
- Chlorine releases
- Ammonia leakage to the sea
- Atmospheric pollution.

Organism Entrainment. Because PSD II takes in large volumes of seawater (about 1,300,000 gallons per minute per 10 MWe), small marine organisms such as plankton and nekton will be drawn through the powerplant. They will be subjected to mechanical, thermal, and chemical stresses before being discharged to the ocean, which may increase their rate of mortality. However, the number of organisms ingested will be extremely small compared to the overall population of the region.

Ocean Water Mixing. The cold water supply drawn into PSD II will be taken from a depth of 3,000 to 4,000 feet and will be rich in nutrients. After passing through the condenser system, it will be mixed with warm surface water and then discharged at an intermediate depth. The discharged water will contain a higher concentration of nutrients than the incoming warm water (since the cold water is richer in nutrients). In addition, the

discharged water will be 7° to 18°F colder than the incoming warm water. Finally, the discharged water will contain debris from ingested marine organisms. All of this may result in an increase in marine life in the vicinity of the discharge. No adverse effects on nearshore marine life are expected.

Metallic Ion Releases. Leaching of metallic ions from the PSD II aluminum heat exchangers may result in minor impacts to marine life. Although aluminum is a commonly used material, the question of its toxicity is difficult to resolve. Aluminum can be toxic to many floral and faunal species; however, the aluminum percentage in the marine environment shows no measurable effect.

Chlorine Releases. Chlorine will be used to control biofouling in the heat exchangers and some of the chemical will be passed through the ship's water discharges. Although chlorine can be harmful to some marine organisms, the residual amounts will be very small and are not expected to be toxic. Chlorine also can react chemically to form long-lived chlorinated organic compounds which can accumulate in the food chain. The impact of these compounds is expected to be minor.

Ammonia Leakage. Ammonia accidentally released to the sea could react with the chlorine discharge to form toxic, persistent chloramines. The amounts of chloramine that might be formed would be small and would rarely occur. Thus, impacts would be minor and localized.

Atmospheric Pollution. Although the PSD II system is theoretically a closed loop, some ammonia will be lost to the atmosphere. Start-up and subsequent maintenance of the ammonia system will require purging with nitrogen and thus release of ammonia and nitrogen to the atmosphere.

If ammonia had to be vented quickly from the heat exchangers under some very unusual atmospheric conditions, the smell might be noted on the shoreline. However, such ammonia concentrations would be well below any hazardous limits.

5.8 AUXILIARY EQUIPMENT

The ammonia and nitrogen support subsystem auxiliaries in the OTEC pilot plant ship are located in a compartment about 300 feet forward of the space allocated for PSD-II. Support facilities are only adequate to support the APL pilot power plant and cannot support simultaneous operation of both APL and PSD-II.

Therefore the PSD-II ammonia and nitrogen purge support subsystems are located adjacent to the power plant in the starboard wing well as indicated in Figure 5.1-11.

5.8.1 Ammonia Support Subsystem

5.8.1.1 Subsystem Requirements

Startup, operation and shutdown of the ammonia power loop requires storage, supply, conditioning and recovery of the ammonia energy transfer medium performed in the ammonia support system. The system stores the entire ammonia power loop inventory and purifies contaminated ammonia in a column. Ammonia leaks are recovered and reclaimed in a vent piping network. The power loop makeup and initial charging is from wet ammonia storage.

Figure 5.8-1 presents a simplified version of the equipment involved in storing, purifying and recovering ammonia. It includes three storage tanks and associated pumps, a purification column system and an ammonia vent gas compression system.

Prior to startup or when removing ammonia for performing maintenance work on the ammonia power loop, the loop must be purged with gaseous nitrogen to prevent flammable oxygen-ammonia mixtures. To provide the nitrogen for this purpose, a liquid nitrogen storage and vaporization facility is included (Figure 5.8-2). This system includes a liquid nitrogen shipping tank with pump, an onboard nitrogen storage tank system and vaporizer.

5.8.1.2 Ammonia Storage, Conditioning and Recovery Subsystem

The preliminary design of the ammonia support subsystem has followed the conceptual design. Equipment sizes have been adjusted to meet the requirements of the 10 MWe power unit. Figure 5.8-3 shows the ammonia support subsystem piping and instrumentation diagram. The subsystem can

Figure 5.8-1. Ammonia Support System Schematic

Figure 5.8-2. Nitrogen Storage, Conditioning, and Supply Subsystem

be divided into ammonia storage and transfer facilities, an ammonia purification system, and an ammonia vent and recovery system.

Ammonia Storage System. The ammonia storage system includes (numbers in parentheses are keyed to Figure 5.8-3):

- Ammonia heel storage drum (D-100)
- Wet ammonia storage drum (D-101)
- Dry ammonia storage drum (D-102)
- Blowdown pump (P-100)
- Ammonia transfer pump (P-101).

Each of the three carbon steel drums has a 29,000-gallon capacity in a 14x25-ft vessel with 2-to-1 semi-elliptical heads. The design pressure of 250 psig satisfies the Code of Federal Regulations (CFR), Section 46, and OSHA requirements. The drums have a local level indication and board-mounted level and pressure recorders and high level and pressure alarms (per CFR-46).

Two drums are ammonia storage drums and one drum is used for heel storage. Ammonia heel is defined as the ammonia liquid blowdown from the power loop evaporator.

Figure 5.8-3. Ammonia Support System P&ID

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

Code requirements limit filling drums to 82 percent of the total volume. The available capacity of each drum is 29,000 gallons or 147,200 pounds of 99.5 percent ammonia at 70°F. Total capacity of three drums is 442,000 pounds of 99.5 percent ammonia with 0.5 percent water.

Initially, the three ammonia storage drums are filled with 442,000 pounds of 99.5 percent ammonia from a transport vessel. About 6,400 pounds of 99.5 percent ammonia are used to purge nitrogen from the power loop. This leaves 435,600 pounds of 99.5 percent ammonia in the three storage tanks of 433,400 pounds of 100 percent ammonia and 2,200 pounds of water. In the ammonia purification process, three pounds of ammonia are lost for every one pound of water removed. Therefore, 6,600 pounds of ammonia are lost in the purification process. Of the 426,800 pounds of 100 percent ammonia left, 239,000 pounds are used in the power loop charge. This leaves 187,800 pounds of 100 percent ammonia in storage after the system is charged and the purification process is completed.

The remaining ammonia in storage sustains 45 days of continuous operation with power loop system ammonia losses up to 170 pounds per hour. This is adequate for a platform location in a remote area.

Ammonia losses can be divided into continuous and intermittent losses. Examples of continuous losses include the glands of pumps and valves, the turbine seal system, and the evaporator and condenser panel losses. The magnitude of the continuous loss from these items varies. Leakproof design of all equipment containing ammonia and operational and preventive maintenance procedures reduces continuous losses.

Intermittent ammonia losses can be caused by manual opening of vent and drain of instrument valves, relief valve activation, startup and shutdown, equipment venting and ammonia loading operations.

Ammonia makeup and blowdown quantities depend on the overall leakage and ammonia contamination rate from the power loop. The blowdown pump has been sized at 3 gpm and requires a minimum flow bypass. Again, actual experience will determine the blowdown rate from the evaporator and whether a low continuous rate or intermittent blowdown at a high rate is preferable. The type and quantity of contaminants, their buildup rate and effect on overall system performance dictate the optimum removal method. The heel

tank stores 7 days of continuous blowdown at 3 gpm and allows ample time for repairs or turnaround of the ammonia purification system and its associated equipment.

The storage system also includes ammonia transfer pump (P-101). This pump is sized for 500 gpm to either fill or unload the power loop in about 90 minutes. The pump rate can be controlled with a control valve. The discharge and suction lines of the pump are provided with automatic on/off type valves to allow ammonia supply for the power loop after the manual block valves have been set as required.

The inlet and outlet lines of each drum are provided with excess flow valves and the inlet line with a check valve. The dual relief valves in each drum are sized to handle the fire load and any overflow from the shipping supply vessel. Board mounted control allows remote shutoff of the valves in the fill and vent lines to and from the drums. It is assumed that the drums are filled with a pump or loading compressor associated with the ammonia supply container on the transport vessel.

Ammonia Conditioning System. This system removes oil, contaminants, solids (such as iron and magnesium hydroxide) and water from the circulating ammonia in the power loop.

The overall power module efficiency is decreased by roughly 2 percent for every percent of water in the ammonia evaporator. Maintenance of a low water level in the power loop ammonia is therefore essential for optimum power recovery. The initial power loop charge of 99.5 percent ammonia can be dewatered in the evaporator at startup to a dryness of 100 ppm to maximize power module efficiency. The remaining high-water ammonia heel can be removed from the evaporator sump to the ammonia heel storage drum (D-100).

The carbon steel ammonia conditioning system includes a 12-inch diameter by 27-foot purification column (T-101). This column has a 20-foot section packed with 3/4-inch ceramic saddles. Vapor is generated by a horizontal ammonia column reboiler (E-102). This reboiler is heated by a mixture of warm and cold seawater at a controlled rate to maintain the top temperature of the column. The overhead is condensed in the ammonia overhead condenser (E-100) and flows to the reflux accumulator (D-103).

The ammonia overhead condenser is cooled with cold (40°F) seawater. Reflux and feed are on manual control. System pressure is maintained by varying the product rate which changes the level in the overhead condenser. Further study is required to evaluate the sensitivity of the overhead pressure control as a function of level fluctuations in the flooded condenser, column stability, and water and ammonia separation.

Another control system considered uses an inert gas (such as nitrogen) to maintain system pressure. In this case, it is not necessary to operate with a flooded condenser. However, the inert gas dissolves in the liquid ammonia product and requires an additional vent from the power loop condenser.

The bottom product of the column is removed on level control from the reboiler section. It consists of oily dregs, water, ammonia, higher boiling contaminants and some solids. The mixture is flashed in the blowdown drum (D-104). Flashed ammonia is recovered and the residue removed by gravity flow to a central disposal system which is part of the support vessel. This column is designed for 1,000 pounds of ammonia product per hour.

Ammonia Vent and Recovery System. There is a significant economic incentive to recover the ammonia and to reduce continuous and frequently occurring ammonia leaks. With reduced leakage, the size of the equipment in the recovery system can be reduced and crew safety improved. Leakproof design should be part of the early design requirements of all equipment. Ammonia from leaking tubes in the evaporator and condenser dissolve in seawater. The pungent odor of ammonia provides adequate detection of atmospheric leaks. However, a number of equipment items (such as relief valves, compressors, pump and valve glands) are connected to the vent system. Leak detection from these items requires special techniques. It might be desirable to instrument the vent systems to facilitate leak detection.

All vent and relief headers and lines discharge to the ammonia knock-out drum (D-104), which removes any liquid carryover. Large quantities of liquid ammonia separated in this drum do not vaporize and can be returned to the heel drum on manual control with the ammonia blowdown drum pump (P-105).

Vapor flow is detected with a wide range anemotherm after the knock-out drum. Normal vapor flow is recovered with the ammonia compressors (C-101A and B). Vapor flow in excess of the compressor capacity bypasses to the bottom of the vent stack.

The ammonia compressor is redundant because of the rapid payout from recovered ammonia in case one compressor is down. Each compressor is equipped with suction valve unloaders and a bypass to control the suction pressure slightly above atmospheric pressure.

Compressed ammonia is condensed in the recovered ammonia condenser (F-101) and flows to the recovered ammonia drum (D-105). The recovered ammonia pump (P-104) removes the liquid ammonia to the heel drum (D-100) for preprocessing. A local pressure controller maintains the discharge pressure of the compressor at 200 psig for ammonia condensation.

Noncondensables and some ammonia are vented to the vent stack. Here, a significant part of the ammonia dissolves in the seawater, which is continuously added to the bottom of the vent stack. Per CFR-46 regulations, any excess vapor discharges through a stack 10 feet above the highest occupied structure on the support vessel. Ti-metal as well as plastics will be considered in the detailed design for equipment and piping items in contact with seawater.

5.8.1.3 Electric Power Requirements During Startup and Shutdown

Part of the ammonia storage and conditioning systems must be operational prior to startup and after shutdown. The ammonia transfer pump is required. The recovery compressor system should also be operational. The ammonia purification system probably does not have to be operational during startup or shutdown. The nitrogen system is activated during startup and shutdown. Adequate electric power (about 300 hp) to operate these systems must be available in addition to the power generated in the power loop.

5.8.1.4 Instrumentation and Interlocks for Nitrogen and Ammonia Support System

To the extent that CFR-46 regulations permit, most instrumentation associated with the two systems is located on a local board. Remote set

point control from the main control room is provided on the ammonia blow-down and supply for the power loop and on critical variables (such as feed and reflux rate) which affect purification system control.

For personnel protection in the below-deck ammonia and nitrogen support systems area, an interlock and shutdown system can be activated from the central control facility.

5.8.2 Nitrogen Support Subsystem

5.8.2.1 Purging

Initially, air must be purged from the system with nitrogen to avoid a flammable mixture when ammonia is introduced. Then the nitrogen can be purged with ammonia vapor to free the system of noncondensibles before charging the system with liquid ammonia. When maintenance requires opening any part of the system containing ammonia, that part of the system must first be isolated, vented to atmospheric pressure, and purged with nitrogen. If personnel are to enter the system, the nitrogen must be displaced with air. This can be done with portable blowers.

If a system is purged by adding a purge gas, allowing the system pressure to rise, then venting down to the original pressure, the concentration of the original gas can be calculated at the end of any number of cycles.

5.8.2.2 Flammability Limits

One of the main objectives of purging is to avoid flammable mixtures. Figure 5.8-4 is a plot showing the range of flammable mixtures for ammonia, nitrogen and oxygen. This plot is based on four data points found after a literature search. Only straight-line boundaries can be drawn through the four points. It is assumed the data points apply for ambient pressure and temperature. Higher pressures do not significantly increase the flammable range but higher temperatures do. For the PSD II design, the temperature is close to ambient or lower. Therefore, the plot is a sufficiently accurate guide for the amount of purging required to avoid flammable mixtures.

The dashed lines on the plot show safe purging limits. Fourteen percent oxygen is the minimum oxygen content to support combustion. Once the oxygen in the system is diluted below 14 percent by purging with nitrogen,

Figure 5.8-4 Ammonia Support Subsystems

it is safe to introduce ammonia. Once ammonia is diluted to 50 percent by purging with nitrogen, air can be safely introduced into the system. The American Gas Association (AGA) recommends diluting down to one-fifth of the safe limit. Though conservative, this guide can be followed without excessively using nitrogen.

5.8.2.3 Nitrogen Purging Requirements

Nitrogen purging requirements were calculated using one-fifth of the safe limit recommended by AGA and using a dilution formula when perfect mixing is assumed. When purging with nitrogen to remove air, the oxygen content can be reduced to one-fifth of 14 percent with three volume changes in three cycles using equal system volumes of nitrogen each cycle. When purging with nitrogen to remove ammonia, the ammonia content can be reduced to one-fifth of 50 percent with three volume changes in six cycles using an amount of nitrogen equal to half of the system volume each cycle. Using this approach, it takes three volume changes to purge either air or ammonia to safe limits.

The volume of a 10 MWe power unit is about 27,500 cubic feet. Therefore, it takes about 82,500 standard cubic feet of nitrogen to either purge air or to purge ammonia. If it is assumed that each power system startup/shutdown cycle requires a complete purge, the consumption of nitrogen is about 165,000 standard cubic feet, or about 12,200 pounds of nitrogen.

5.8.2.4 Purging Nitrogen with Ammonia

To displace the nitrogen in the power loop with ammonia, it is assumed that five volume changes are adequate. The required ammonia vapor is drawn from the vapor space of the ammonia storage vessels or supplied as liquid with the ammonia column feed pump (P-102). It is introduced at the high points and nitrogen is purged from the low points. The ammonia vapor drawn from the vapor space of the ammonia storage vessels is essentially water-free. About 6,400 pounds of ammonia are required for five volume changes of the 27,500 cubic foot power loop.

5.8.2.5 Noncondensible Removal

During the start-up and after maintenance on the ammonia loop, some noncondensable gases (such as air and purge nitrogen) remain in the system. While charging and purge procedures can be structured to reduce the quantity of noncondensibles remaining in the power loop, complete elimination is not practical. Fortunately, it is easy to collect, isolate and extract noncondensibles. During operation, noncondensibles are swept by the ammonia vapor to the condenser. In the condenser, the ammonia vapor is condensed and pumped to the evaporator, leaving behind the noncondensibles. Noncondensibles collect at the bottom of the condenser. They are removed from the system by a piccolo tube located immediately under the condenser plates and vented to the vent stack in the ammonia support subsystem.

Piccolo tube size is based on a flow rate large enough to allow the ammonia vapor and noncondensibles contained in a condenser module to be removed in one hour. The piccolo tube in the condenser is above the liquid level and is a 2-inch schedule 40 pipe with two rows of 1/8-inch holes on 2-inch centers. Calculations for sizing the piccolo tube are given in Appendix II, Section 4.

Ammonia losses occur when purging nitrogen and inerts from the system and no attempt is made to recover them. To do so requires a water scrubbing column, heat exchanger to remove the heat of solution and cool the stripped scrubbing water, and a water circulation pump. The normal design of such a scrubber has 25 weight-percent ammonia in the water leaving the scrubber. A stripper to strip the ammonia out of this water requires electrically heated reboilers. As an alternative, refrigeration can condense the ammonia out of the purge gas. Recovering ammonia from purge gas requires additional equipment and adds parasitic loads. If the purge gas is diluted, recovery appears uneconomical.

5.8.2.6 Nitrogen Package Unit Equipment

Figure 5.8-5 shows the piping and instrumentation diagram for the nitrogen support subsystem.

Nitrogen Storage. Industrial practice for nitrogen storage in the capacity required for the PSD II concept is to use pressurized cryogenic storage. For the preliminary design, a storage pressure of 225 psig was selected. Pressure control is by a simple pressure regulator. At a storage pressure of 225 psig, the vaporization loss due to heat in leakage is about one-fourth of 1 percent per day of the nitrogen in storage.

Nitrogen Storage Vessel

One 11,000-gallon nitrogen storage tank provides about 1,024,000 standard cubic feet of nitrogen to purge six complete power system shutdown startup cycles.

The selected nitrogen storage vessel is a standard size modified to meet shipboard requirements. The vertical vessel is mounted on three legs with a 122-inch outside diameter and 32 feet, 7 inches high. Empty weight is 47,000 pounds and filled weight is 120,000 pounds. Design conditions are 250 psig and -320°F. The vessel is of double-wall construction with an inner shell of stainless steel and an outer shell of carbon steel. The annular space between the shells is evacuated to a pressure of 50 microns of mercury and filled with Perlite.

D-107
LIQUID NITROGEN SHIPPING TANK
96" OD x 33' TT
6000 GALLON AVAILABLE CAPACITY
DP 25 PSIG DT -320°F
(INCLUDES TRANSFER PUMP P-106)

D-106
NITROGEN STORAGE TANK
122" OD x 31'-7" T/T
11,000 GAL AVAILABLE CAPACITY
DP 250 PSIG, DT -320°F

E-103
NITROGEN HEATER
DUTY 1.07 MM BTU/HR AREA 94 SQ. FT
TUBE DP 250 PSIG, DT -320°F TI
TROUGH CS

NOTES

1. REFER TO 46 CFR (CODE OF FEDERAL REGULATIONS) FOR ALL EQUIPMENT ON THIS P&I FLOW DIAGRAM
2. ALL MODULATING DIAPHRAGM CONTROL VALVES HAVE AN INTEGRAL ELECTRO-PNEUMATIC TRANSDUCER
3. ALL LIQUID NITROGEN LINES ARE INSULATED
4. THE INSTRUMENTATION & CONTROL OF THE LIQUID NITROGEN SHIPPING TANK D-107 IS NOT SHOWN. HOWEVER, IT IS IDENTICAL TO THAT SHOWN ON THE NITROGEN STORAGE TANK D-106.

ALHAMBRA C F BRAUN & CO CALIFORNIA		REV	DATE	REVISION	BY	APPD
DESIGNED	TERRELL	OTEC POWER SYSTEM DEVELOPMENT - II				
DRAWN	TERRELL	TRW				
CHECKED	TERRELL	10 MW & POWER MODULE				
APPROVALS		NITROGEN SUPPORT SYSTEM				
PAID OFFICE		PIPING & INSTRUMENTATION DIAGRAM				
		FACILITIES, MECHANICAL AND POWER INTEGRATION LABORATORY		DRAWING NUMBER		
				6850.94-09		
				ISSUE DATE		
				5-9-79		
				CHG. REV.		

Figure 5.8-5. Nitrogen Support System P & ID

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

The nitrogen storage vessel is not excessively large. However, this vessel provides the nitrogen requirement with considerable contingency. Vessels of this size have been supplied for use on LNG supertankers. Smaller standard size vessels are available and a 13,000-gallon size is also standard. Any larger size is a special design.

The nitrogen storage vessel can be purchased complete with all pressure controls, level indication instruments, and required safety valves and rupture discs.

Autorefrigeration causes some reduction in storage pressure as liquid nitrogen is withdrawn from the vessel. A heater is also provided to overcome this effect and allows rapid removal of liquid nitrogen from the storage vessel.

Nitrogen Shipments. Liquid nitrogen is transported in special tanks mounted on a truck trailer. The largest transport tanks in use have a working capacity of 8,000 gallons. Transport regulations limit the pressure in the tank to 17 psig. It is planned to ship the truck trailer to the platform, lift the trailer onto the platform, and pump the liquid nitrogen to the onboard nitrogen storage vessels. This is considerably safer than trying to use a flexible hose designed for -320°F between the barge and the platform.

Nitrogen Transport Tank. The liquid nitrogen transport tank is of double-wall construction with an inner shell of stainless steel and an outer shell of carbon steel. The annular space between the shells is evacuated to a pressure of 50 microns of mercury and filled with Perlite. Empty weight of an 8,000-gallon tank is 38,000 pounds and filled weight is 91,000 pounds. Design conditions are 25 psig and -320°F . This vessel can be purchased complete with all required instrumentation and safety devices. A heater is also included to overcome the autorefrigeration effect when liquid ammonia is rapidly removed from the tank. This tank is a standard design modified to meet shipboard requirements. A 100 gpm pump is mounted on the transport tank and pumps out the 8,000 gallons of nitrogen in less than 1-1/2 hours.

Nitrogen Vaporization. When nitrogen is needed for purging, the 225 psig storage pressure can supply the required amount. The heater supplied with the storage vessel overcomes the autorefrigeration effect when liquid nitrogen is removed from the vessel. However, the liquid nitrogen from storage must be vaporized and heated before it can be used for purging.

Nitrogen Heater. A nitrogen heater developed by C. F. Braun has been used for the preliminary design. It requires further detailed design by suppliers. Vaporizers of this type have been used in liquid natural gas service. The heater must vaporize 7,200 pounds of nitrogen per hour and heat the nitrogen to 60°F. In the preliminary design, this is accomplished by spraying warm seawater over 4x192-inch titanium pipe coil contained in an epoxy lined carbon steel box. The box has access doors in the lower part for de-icing the lower coils. The exchanger is rated at about 10^6 Btu/hr and the design is based on seawater entering at 80°F. Testing or further calculations are required to determine whether water freeze-up could occur on the outside. The dry weight of the vaporizer is estimated at 3,500 pounds and the operating weight is estimated at 4,300 pounds. The overall dimensions are about 2-12/x5x20 feet.

The nitrogen heater has a shutdown feature if nitrogen vapor temperature to the distribution header system drops below 40°F. Shutdown protects the carbon steel nitrogen steel distribution network.

5.8.3 Special Support Equipment

The OTEC PSD-II power modules require special support equipment which interface with and affect the operation and maintainability of the PSD-II modules.

Equipment required to support operations includes:

- Tube cleaner
- Leak detection equipment
- Tube plugging equipment
- Ammonia resupply system — A ship, barge or work boat mounted tank for transporting ammonia to an OTEC platform (not part of this contract)
- Nitrogen resupply system — A vacuum jacketed tank which can be transported by ship, barge or work boat to an OTEC platform and has an approximate capacity of 8,000 gallons

- Startup power unit — A 6 MVA power source is required for initial startup of a 10 MWe module (not part of this contract)
- Standby power — A 563 KVA power source for orderly shutdown of the 10 MWe module during system shutdowns (not part of this contract). It is anticipated that this power will be available from the platform's main power source
- 150-ton primary crane for installing heat exchangers, turbine generator and other heavy components. This crane may be part of the OTEC platform or may be provided by a separate service and installation ship
- Material handling equipment for other components on the power module — On-board hoists, cranes and monorails may be required for installing, servicing and replacing major components, such as pumps, valves and strainers. These items have not been defined but will be in the final design.
- Heat exchanger shipping fixtures to transport the heat exchangers from the manufacturer to the installation points. They will be defined as part of the heat exchanger final design.

Maintainability and installation equipment for the power module heat exchangers and their support equipment are shown in Figure 5.8-6. The first three items are fabricated from the equipment list items. Item 4 is part of the turbine-generator package deliverable.

Other items may be identified during final design. Conventional tools required for normal maintenance are not included.

Spare parts (such as circuit breakers, motors, pump and valve seals, stem and shaft packing, tube cleaner brushes, instrumentation sensors) will be defined during final design.

COMPONENT SUPPORTED	SUPPORT EQUIPMENT	NUMBER REQUIRED
EVAPORATOR AND CONDENSER	LIFTING AND POSITIONING FIXTURE	1
TUBE CLEANING POSITIONER	LIFTING FIXTURE	1
TUBE CLEANING HEAD	LIFTING FIXTURE	1
TURBINE GENERATOR	INNER CASING REMOVAL RAILS	2
	CENTERING RINGS	2
	ENDWALL COUNTERWEIGHT	1

Figure 5.8-6. Support Equipment for Maintainability and Installation

5.8.4 Producibility

Most components are of standard manufacture. The only unique components are the heat exchangers. Detailed fabrication plans are presented in Appendix II Section 10. Design and manufacture of the turbine is discussed in Section 4.1.

Most components are subassembled at the suppliers' facilities prior to shipment to the platform hull contractor assembly and outfitting dock. Certain subcontractors must ship their components to others for modular buildup and inspection. The remaining major subsystem components can be shipped directly to the portside assembly dock for sequential installation aboard the platform hull.

5.8.5 Transportation

Only the heat exchanger modules present unique transportation requirements. Other major components such as the turbine, generator and pumps are similar in size and weight to conventional power plant components. A weight and envelope summary is given in Figure 5.8-7. The heat exchangers can be transported by either rail or truck. Restrictions on size must be considered during detailed design.

Bridge clearance is the limiting factor for rail shipment and depends on the routing. For items leaving the Buffalo area, the limit is 18 feet. A flatbed rail car has a floor height of 3-2/3 feet and a usable load height of 14-1/3 feet. Load width limits for rail shipment are 10 feet at the rail car floor height tapering to a 13-foot maximum at the top of the load (18 feet above the ground). Load length limits are large enough and present no constraints. OTEC heat exchanger modules 14 feet high can be shipped upright by rail on flat rail car.

Over-the-road dimensions are summarized in Figure 5.8-8 for the lower 48 states. Height dimensions are for the total package of load and vehicle. Therefore, the allowable height of the load is the numerical value in the figure less the vehicle height.

OTEC heat exchanger components loaded on a truck are not more than 14 feet wide and 12 feet high. OTEC heat exchanger modules each 14 feet high, 20 feet long, and 4 feet deep can be shipped by truck if the units

DESCRIPTION	WEIGHT (LBS)	DIMENSIONS (IN.)		
		H	W	L
EVAPORATOR MODULE	30,000	168	50	240
SUBASSEMBLY	120,000	168	200	240
10MW _e EVAP	480,000	168	200	960
CONDENSER MODULE	30,000	168	50	240
SUBASSEMBLY	120,000	168	200	240
10 MW _e COND	480,000	168	200	960
TURBINE/GENERATOR	200,000	196	196	426
LUBE OIL CONSOLE	40,000	84	66	180
SEPARATOR (4)	10,200	66 DIA		144
FEED PUMP/MTR (2)	10,100	102	156	84
5 KV SWITCH GEAR	20,600	90	194	88
480 V TRANSFORMER	5,800	90	64	60
480 V MTR. CONTROL	3,415	90	140	20
CHLORINATOR	4,300	78	60	156
TUBE CLEANER HEAD	15,000	15 DIA		216
NITROGEN VAPORIZER	4,300	28	60	192
LIQUID N ₂ STORAGE DEWAR	47,000	122 DIA		384
LIQUID N ₂ SHIPPING DEWAR	38,000	96 DIA		396
NH ₃ PURIFICATION COL.	8,100	12 DIA		324
NH ₃ HEEL STORAGE DRUM	135,000	168 DIA		300
WET NH ₃ STORAGE DRUM	135,000	168 DIA		300
DRY NH ₃ STORAGE DRUM	135,000	168 DIA		300
NH ₃ REFLUX ACCUMULATOR	1,100	24 DIA		36
NH ₃ BLOWDOWN DRUM	7,000	72 DIA		120
RECOVERED NH ₃ DRUM	1,000	24 DIA		36
NH ₃ OVERHEAD COND	2,100	13 1/2 DIA		168
NH ₃ COMPRESSOR COND	1,800	12 DIA		168
NH ₃ SUPPORT PIPING	38,000	NA		NA
N ₂ SUPPORT PIPING	12,000	NA		NA
POWER LOOP NH ₃ PIPING/VALVES	162,900	NA		NA
WIRING AND CONDUIT	10,650	NA		NA

Figure 5.8-7. Major Component Weights and Dimensions

are laid on the truck bed. This estimate excludes packaging. Overall power module height was limited to no more than 14 feet so the module can be shipped by either rail or truck.

	DIMENSION	NUMBER OF STATES
LEGAL HEIGHT	13 FEET 6 INCHES OR GREATER	48
MAXIMUM HEIGHT ¹	14 FEET 8 INCHES OR GREATER	48
	15 FEET OR GREATER	15
LEGAL WIDTH	8 FEET OR GREATER	48
MAXIMUM WIDTH ²	14 FEET OR GREATER	41
	15 FEET OR GREATER	13
LEGAL LENGTH	55 FEET OR GREATER	48
MAXIMUM LENGTH ³	90 FEET OR GREATER	44

¹REQUIRES PERMIT IN MOST STATES.

²EXCEPTIONS ARE: 12 FEET FOR CONNECTICUT, FLORIDA, NEBRASKA, SOUTH CAROLINA, VIRGINIA; 12 FEET, 4 INCHES FOR MISSOURI; AND 13 FEET FOR WEST VIRGINIA.

³WIDTH AND LENGTH CAN BE GREATER IN ALL STATES WITH GOVERNMENT SUPPORT.

Figure 5.8-8. Over-the-Road Dimension Summary for Lower 48 States

To protect the core section, the module should be placed on a skid. The skid removes the load due to material weight off the core and weld attachments and prevents movement of the heat exchangers which could damage the core. To further protect the module, a set of tiedowns to prevent movement on the truck trailer and a rubber pad between the module and skid or between the skids to dampen vibrations are recommended.

Since truck height is 12 feet maximum and the heat exchanger with skid is greater than 4 feet, there can be only two exchangers per truck load. A set of rollers could be designed either into the skid or within the truck for easy loading and unloading.

To protect the module from the environment during transit, the seawater side of the core is wrapped in a plastic and plywood cover. This cover keeps heat transfer surfaces dry and free of foreign matter.

The heat exchanger module is transported with a nominal positive internal pressure of 10 to 15 psig. This provides a clean and dry module internally and adequate pressure to prevent panel fatigue.

The blanket should be nitrogen and self-contained or supplied by appropriately regulated external flasks. The blanket is created by shipping the module with gas tight closures over the nozzles. Gas can be

supplied through one of the pressure taps. A relief valve and pressure gauge can be installed on the other.

5.8.6 Installation

The majority of power module component installations are completed in the shipyard at the assembly dock. Component subassembly modular buildup minimizes construction schedule time at the assembly dock. The inter-relationships between unions and construction trades (steam fitters, boiler-makers, pipe fitters, iron workers, electricians) required for construction installation of the power module must be considered. The large cost for construction and installation at sea must be minimized.

A typical breakdown for heat exchanger installation is shown in Figure 5.8-9. Most of these activities are routine and similar to those encountered by the construction industry. Final installation plans and schedules will be developed during final design.

Power module installation into the platform hull requires assembly at an outfitting dock. The equipment locations and piping system layout have been arranged so that potential platform hull contractors can perform assembly.

On-board power module installation can be performed in the shipyard graving dock where the platform hull is constructed or at an outfitting dock located near the shipyard. The latter approach minimizes the high cost of using an established shipyard (or one built for OTEC requirements). This method also is more attractive in regard to the schedule for multiple full-scale development OTEC plant constructions.

The power module equipment layout has been arranged so that the installation sequence is not critical. Normal installation trade practices can be followed to minimize costs.

Lower deck equipment and piping is installed first. The electrical equipment, ammonia and nitrogen subsystems are installed next, followed by the heat exchangers as described below. The turbine generator is then installed. With all major inboard equipment installed, the remaining piping, instrumentation, equipment and piping testing, inspection and checkout can be completed. No special inspection problems impact the construction schedule.

Figure 5.8-9. Pert Chart for Manufacturing and Installation of 10 MWe Power System Module

Heat exchanger operation and performance depends on packaging, handling, and installation and accurate alignment of the seawater passages for each power module subassembly.

At the top of the lower plate on each strongback are two holes equally spaced. These are the lifting points for each module. A crane containing either a lifting plate or fixture for four tie supports joined at the center of the module top could be used. The box structure made up by the cylindrical headers and strongbacks and reinforced by the down-comers is an adequate support framework for lifting (see Figure 5.8-10).

Figure 5.8-10. Module Sub-Assembly

Once the truck is at the ship site, each heat exchanger module with skid can be separately unloaded. Each module can be hoisted onto the subassembly ship skid. At this time, each module pressure blanket can be blown down.

Welded at the bottom of each module strongback are mounting pads or plates to bolt the heat exchanger module to the ship skid. Since the skid

is made from carbon steel, an insulating pad is necessary and could be a suitable electrical isolator or grout type.

Before positioning the final tiedown to the ship skid, each of the four modules which make up each subassembly must be accurately aligned. Proper functioning of the mechanical cleaning system depends on accurate alignment of the seawater passages of the four heat exchangers which form each power module subassembly.

Since each module is shipped separately, we must ensure they can be aligned when mounted on the ship skid to form the subassemblies. This is accomplished by an alignment sight mounted at each upper corner of each module. Each alignment sight is placed in a large roughly preformed hole by an alignment yoke. The yoke holds the alignment sights in a fixed geometrical relationship with several seawater passages in the core selected as reference passages (see Figure 5.8-11). The yoke and its clamps maintain the optical axis of the alignment sight normal to the face of the core and parallel with the axis of the seawater passages when the sights are mounted on the module.

Figure 5.8-11. Use of Alignment Yoke to Locate Alignment Sights

Two yokes temporarily mounted on each face of the core locate each of the four alignment sights required. Each alignment sight can be attached permanently to the module by bonding the alignment sight's attachment flange to the strongback stiffener with a rigid durable adhesive or by spot welding the attachment flange to the stiffener (see Figure 5.8-12 and 5.8-13). Once the sights are firmly attached, the yokes are removed.

The sights have a reticle, peep-hole or other precise means of optical alignment compatible with the field alignment instruments. Provision will also be made for readjustment later if required.

Figure 5.8-12. Alignment Sight Installation Detail

Figure 5.8-13. Alignment Sight

Upon arrival at the site where the subassemblies are to be erected, the modules are lifted onto the skid. Each module can then be aligned and leveled using the alignment sights and line of sight optical equipment such as a He-Ne laser or a conventional transit (Figure 5.8-14). Once aligned, modules are firmly anchored to the skid using the grout method shown in Figure 5.8-15. Grout materials are available for this purpose.

The subassembly module with skid is hoisted and positioned in the ship hull using a 100-ton crane. The subassembly module skid must be mounted with a damping device held securely in position at installation to minimize vibration.

Figure 5.8-14. Alignment of Four Modules on a Skid

Having positioned each module subassembly, the piping for both the inlet and outlet nozzles is connected. Each module has a separate weld connection which runs in series to the main flange connection. It is advisable to bolt the flange connection before any weld connections are made.

Finally, the rubber seal is inflated. Sufficient pressure must be used for a reliable water tight connection. It is advisable to start from one end and work down to the other.

The subassembly module with skid weighs approximately 70 tons. The required lift therefore indicates the need for a 100-ton crane.

5.8.7 Long-Lead Items

Long-lead items (Figure 5.8-16) include deliverable hardware items which are peculiar to the project and require extensive fabrication and delivery time. Remaining deliverable items are currently available within 9 months after contract award.

Figure 5. 8-15. Shimming and Electrical Isolation Mount

LONG LEAD ITEM	EXPECTED PROCUREMENT OR FABRICATION TIME (MONTH)
10 MH ₂ HEAT EXCHANGER PROTOTYPE, CONDENSER	38
10 MH ₂ HEAT EXCHANGER PROTOTYPE, EVAPORATOR	38
EVAPORATOR AND CONDENSER MANIFOLD	14
TUBE CLEANER	24
FEED PUMP	12
TURBINE/GENERATOR	18
24, 42, 54 AND 88-INCH VALVES	12

Figure 5.8-16. Long-Lead Items.

REFERENCES

- 5-1 IEEE Handbook No.141, "Electrical Power Distribution for Industrial Plants", 1969
- 5-2 TRW PSD-I Preliminary Design Report, 4 December 1978, EG-77-C-03-1570
- 5-3 U. S. Army Coastal Engineering Research Center, Shore Protection Manual, Volume 1, Department of the Army, Corps of Engineers, 1977
- 5-4 Horowitz, J. W., "Letter Resulting from Conceptual Design Briefing," Argonne National Laboratories, 17 January 1979
- 5-5 Report on Preliminary Engineering Design of OTEC Pilot Plant Ship, Johns-Hopkins University Applied Physics Lab, 20 November 1978
- 5-6 Little, T. E., "Seawater Pump Study, OTEC Program," Westinghouse Report C00-4071-2, January 1978 (two volumes)
- 5-7 EPRI Report NP-254, "Study of Remote Multiplexing for Power Plant Applications," Volume 3, September 1977
- 5-8 "Report on Equipment Availability for the Ten Year Period 1967-1976," EEI Equipment Availability Task Force, December 1977
- 5-9 "A Report on Improving the Producibility of Electric Power Plants," FEA, March 1975
- 5-10 R. A. Bonewitz, "Concurrent Studies of Enhanced Heat Transfer & Materials for Ocean Thermal Exchangers," ERDA Contract Report No.E (11-1)-2641, October 29, 1976

6. POWER SYSTEM COST AND NET ENERGY ANALYSIS

6.1 POWER MODULE LIFE-CYCLE COSTS

The principal objective of the PSD-II program is to design a power system to be integrated into an OTEC system which is cost-competitive in the southeastern United States. To achieve this goal, it is necessary to determine capital costs and power generation costs for the power system and any options having significant cost impacts.

Total system initial capital costs were determined for the 10 MWe power module employing aluminum and stainless heat exchangers. Aluminum heat exchangers are not expected to last the full 30-year design life of the power plant. Aluminum heat exchangers will have to be replaced once or twice during the 30-year life of the power plant. The life-cycle cost associated with replacing aluminum heat exchangers becomes the single most significant variable parameter affecting total system costs. Unlike aluminum heat exchangers, stainless steel heat exchangers are expected to last 30 years. Therefore, the life-cycle cost for a stainless steel heat exchanger is essentially the same as its initial cost. Once the heat exchanger life-cycle costs have been determined (see Section 3.7), total system life-cycle costs are obtained by summing the heat exchangers life-cycle costs and the remainder of system costs. These total life-cycle costs are then used to compute power generation costs.

An additional cost impact for aluminum heat exchangers is the susceptibility for developing leaks and the subsequent loss of ammonia and eventual requirement for plugging leaking tubes. This results in an additional cost penalty against aluminum in terms of increased power generation costs.

The 10MWe power system power generation costs for aluminum and stainless steel heat exchangers (as a function of heat exchanger life) are shown in Figure 6-1.

For stainless heat exchangers, a 30-year life is anticipated. For aluminum heat exchangers, a 10 to 15-year life is anticipated. Also shown in Figure 6-1 is a probable range of the cost impact due to ammonia leakage in the aluminum heat exchangers.

Figure 6-1. 10 MW_e Power Generation Costs Aluminium and Stainless Heat Exchangers

Some significant results show up in Figure 6-1:

- Non-leaky aluminum heat exchangers must have a life ≥ 15.3 years to be competitive with stainless heat exchangers
- Range of power generation cost impact due to NH₃ leaks in heat exchangers is about 2 to 20 mills/kw hr
- Estimated minimum leak scenerio for aluminum heat exchangers pushes their required life expectancy to 18.5 years to be competitive with stainless heat exchangers.

It should be noted that all life-cycle costs discussed in this section are based on the 10MWe power system only and do not include the ocean platform and the cold water pipe.

The 10MWe power system component initial cost data is presented in Section 6.1.1. The power system total life-cycle cost analysis, including cost impact of leaky aluminum heat exchangers, is presented in Sections 6.1.2 - 6.1.4.

6.1.1 Power System Initial Cost Estimates

Initial cost summaries for 10MWe power system components and sub-systems are shown in Figure 6-2 for aluminum heat exchangers and in Figure 6-3 for stainless steel heat exchangers.

Preliminary design drawings were developed in sufficient detail to provide a basis for developing credible initial cost estimates for equipment. Specifications were then developed based on the design and drawings and sent to vendors for quote.

Cost estimates were projected for a prototype 10 MWe plant, a first-production 10 MWe plant, and for a production rate of 100 MWe per year based on the following assumptions.

All costs are for first quarter 1979. Costs include freight to, and installation at, New Orleans, Louisiana. We have included a 10 percent contingency for aluminum and a 20 percent contingency for stainless steel heat exchangers. Contingencies of 5 to 10 percent were added to in-house estimates, such as piping, electrical wiring and ammonia support systems.

ITEM	COST (\$/KW)*		
	PROTOTYPE 10 MWe	FIRST PRODUCTION 10 MWe	PRODUCTION 100 MWe/YR
HEAT EXCHANGERS	763	455	367
PHASE SEPARATORS	9	8	5
TURBINE/GENERATOR	328	263	214
AMMONIA FEED PUMPS	25	23	13
AMMONIA PIPING	140	127	85
AMMONIA VALVES	222	200	126
CONTROL SYSTEMS	80	74	55
CHLORINATION SYSTEM	21	19	11
MECHANICAL CLEANING SYSTEM	92	81	19
ELECTRICAL EQUIPMENT	39	35	24
AMMONIA SUPPORT SYSTEM	208	112	72
SEAWATER PUMPS	340	310	217
TOTALS	2,267	1,697	1,208

*FIRST QUARTER 1979 COSTS

Figure 6-2. Power Plant Initial Cost Breakdown Summary (Aluminum Heat Exchangers)

ITEM	COST (\$/KW)*		
	PROTOTYPE 10 MWe	FIRST PRODUCTION 10 MWe	PRODUCTION 100 MWe/YR
HEAT EXCHANGERS	1,337	796	642
PHASE SEPARATORS	9	8	5
TURBINE/GENERATOR	328	253	214
AMMONIA FEED PUMPS	25	23	13
AMMONIA PIPING	140	127	85
AMMONIA VALVES	222	200	126
CONTROL SYSTEMS	80	74	55
CHLORINATION SYSTEM	21	19	11
MECHANICAL CLEANING SYSTEM	92	81	19
ELECTRICAL EQUIPMENT	39	35	24
AMMONIA SUPPORT SYSTEM	208	112	72
SEAWATER PUMPS	357	328	228
TOTALS	2,858	2,054	1,494

*FIRST QUARTER 1979 COSTS

Figure 6-3. Power Plant Initial Cost Breakdown Summary (Stainless Heat Exchangers)

Piping and electrical wiring cost estimates are based on preliminary drawings using the 1979 edition of "Building Construction Cost Data" (R. S. Means) as the data source and New Orleans as the installation site.

Procured equipment includes combined G&A and a procurement burden of 24 percent for items less than \$300,000 and a reduced factor of 9.5 percent for procured items more than \$300,000.

Indirect costs include engineering services and home office costs. Engineering includes preliminary engineering, optimization studies, specifications, detail engineering, vendor drawing review and resident engineering services during construction. Indirect costs for the prototype are based on developed detailed cost estimates. The sum of these two categories (engineering and home office) for production plants falls into historically consistent percentages in the range of 5 to 15 percent, depending on the complexity of the project. The apportionment of percentages by plant type is shown in Figure 6-4.

PLANT TYPE	ENGINEERING (PERCENT)	HOME OFFICE (PERCENT)	TOTAL (PERCENT)
10 MWe PROTOTYPE	17.7	10.5	28.2
10 MWe FIRST PRODUCTION	12.5	3.0	15.5
PRODUCTION 100 MWe/YR	5.0	3.0	8.0

Figure 6-4. Indirect Cost Percentages

Learning curve adjustments are based on the following assumptions. Labor and materials costs are listed separately if the information was developed or (in the case of vendor bids) provided separately. In these cases, where a total dollar amount was provided, a best-engineering-judgment estimate was made for the portion that represented labor.

For learning curve computations, the Wright/Northrup curve is used by TRW manufacturing and defined as

$$(Tavg)_{2n} = L (Tavg)_n$$

where $(Tavg)_{2n}$ = average cost or time per unit to produce 2n units

$(Tavg)_n$ = average cost or time per unit to produce n units

L = learning curve factor (usually expressed as a percentage).

For this analysis, the actual cost of the n^{th} unit rather than the average cost is used. The choice of factor L is based on the amount of hand labor represented in a particular item. For items where there is a high level of hand labor, TRW has found that $L = 85$ percent is a representative factor for scaling labor. For items where there is a high level of repetition or where the labor is performed by machine, the curve defined by $L = 90$ percent is more appropriate.

6.1.2 Power Module Cost Analysis

An evaluation of the true effective cost of an OTEC power plant must take into account initial capital investment costs for the power system plus all additional costs incurred over the life of the power plant.

Life-cycle costing reduces all costs to present dollars. Included are the initial capital costs plus the present value of all expenses expected to be incurred. Future expenses are estimated using today's costs

plus inflation factors to determine expected future material and labor costs. These estimated future costs are then multiplied by appropriate present worth factors to arrive at present value costs. Present value costs are added to the initial capital investment costs to determine an equivalent overall present value capital investment cost which is more commonly termed as the life-cycle cost.

This life-cycle cost is then used to determine the power generation cost in mills per kw-hr.

The present value analysis sequence is as follows:

- 1) Determine aluminum heat exchanger life-cycle costs as a function of heat exchanger life for a 30-year plant life
- 2) Determine super stainless steel heat exchanger life-cycle costs for a 30-year plant life
- 3) Determine life-cycle cost impacts for various scenerios for the number of tube leak holes developed per year and leak hole diameter
- 4) Compare aluminum and super stainless steel heat exchangers on a present-value basis for a 30-year plant life
- 5) Determine power generation costs for power systems using aluminum and stainless heat exchangers
- 6) Determine power generation incremental costs for those cases involving tube leaks
- 7) Do steps 5 and 6 for fixed charge rates representative of a public utility, private utility, industrial plant, and TRW estimates

The results of the present value cost analysis (see Section 3.7) for the heat exchangers is shown in Figure 6-5. Figure 6-6 shows the heat exchanger life-cycle costs as a function of heat exchanger life.

Total power module present value costs are obtained by summing the heat exchanger life-cycle costs plus the balance of plant costs. The balance of plant component costs are shown in Figures 6-2 and 6-3.

Total system present value costs are tabulated in Figure 6-5 and plotted in Figure 6-7.

MATERIAL	HEAT EXCHANGER LIFE (YEARS)	PRESENT VALUE HEAT EXCHANGER COST (\$/KW)	SYSTEM COST EXCLUSIVE OF HEAT EXCHANGER (\$/KW)	TOTAL PRESENT VALUE SYSTEM COST (\$/KW)
ALUMINUM	5	1817	841	2658
	10	875	841	1716
	15	619	841	1460
	30	367	841	1208
STAINLESS STEEL	30	642	852	1494

Figure 6-5. Power Module Present Value Costs for Aluminum and Stainless Heat Exchangers

Figure 6-6. TRW/LINDE PSD-II 10 MWe Heat Exchangers Present Value Cost Versus Life

Figure 6-7. PSD-II Total Power System Present Value Cost vs. Heat Exchanger Life

6.1.3 Power Generation Cost

Major cost factors affecting the per kw cost of electricity produced include the capital cost of the plant, the plant capacity factor, the fixed annual charge rate, cost of fuel, and the cost of operation and maintenance. The relationship is as follows:

$$\text{Busbar cost of electricity} = \frac{(FCR)(C/KW) \times 1,000}{(FA)T} + (CF) + (COM)$$

in mills per kilowatt hour

Busbar cost — cost in mills/kWh at the point of production with no transmission charges (one mill = one/tenth of one cent)

FCR — fixed charged rate: a percentage figure representing estimates about the long-term costs of debt and equity capital. During the 1960s, FCRs of 8 to 10 percent were standard for the American utility industry. During the 1970s, 16 and 17 percent FCRs have been common.

C/kW — capital investment in dollars per kilowatt.

1000 — a conversion figure used to convert dollars to mills.

FA — capacity factor: the ratio of the kilowatt hours actually produced during a given period to the total which a plant operated at constant full power could theoretically produce during the same period: 0.90

T — total hours in a year: 8,760.

CF — cost of fuel in mills per kilowatt hour: seawater is the equivalent of fuel for OTEC and there is no charge.

COM — cost of operation and maintenance in mills/kWh. 4 mills/kWh is an estimate used by proponents of OTEC for the power system.

The fixed charge rate (FCR) consists of:

- Return on invested capital
- Income tax
- Depreciation
- Ad valorem tax
- General administrative expenses
- Insurance.

Various values are used for these fixed charge rate components depending on whether the rate is computed for a public utility, a private utility or a private corporation.

Figure 6-8 shows the values for the various fixed charge rate components and their total for utilities and private industry.

Power generation costs in mills/kw-hr are shown in Figure 6-9 for PSD-II power modules using aluminum heat exchangers of different lifetimes and for stainless heat exchangers having a 30-year life. These results are plotted in Figure 6-10. As seen from Figure 6-10 for equivalent power generation costs, zero-leak aluminum heat exchangers must have a life of from 14 to 15.5 years to be competitive with stainless steel.

	PUBLIC UTILITY	PRIVATE UTILITY	PRIVATE CORPORATIONS	PRIOR TRW
RETURN	7 + 1 = 8.0	7 + 3 = 10.0	7 + 7 = 14.0	10.5
INCOME TAX	0.0	4.0	4.0	2.0
DEPRECIATION	1.8	1.5	1.5	0.9
AD VALOREM TAX	0.0	2.25	2.25	1.5
GENERAL ADMINISTRATIVE EXPENSES	1.25	1.25	1.25	1.0
INSURANCE	0.25	0.25	0.20	0.6
TOTAL	11.25%	19.20%	23.2%	16.5%

Figure 6-8. Fixed Charge Rate

MATERIAL	H.E. LIFE YEARS	PRESENT VALUE H.E. COST. \$/KW	SYSTEM COST EXCL. OF H.E. \$/KW	TOTAL SYSTEM COST \$/KW	POWER GENERATION COST MILLS/KW-HR			
					PUBLIC UTILITY FCR=.1125	PRIVATE UTILITY FCR=.192	PRIVATE CORP. FCR=.232	TRW PRIOR FCR=.165
ALUMINUM	5	1817	841	2658	41.9	68.7	78.2	59.6
	10	875	841	1716	28.5	45.8	54.5	39.9
	15	619	841	1460	24.8	39.6	47.0	34.6
	30	367	841	1208	21.2	33.4	39.9	29.3
STAINLESS STEEL	30	642	852	1494	25.3	40.4	48.0	34.3

Figure 6-9. PSD-II System Life Cycle Cost and Power Generation Cost

6.1.4 Cost Impact of NH₃ Leaks in Aluminum Heat Exchangers

A major concern with aluminum heat exchangers is the probability of developing leaks in the tubes which could result in loss of significant amounts of ammonia prior to plugging. Anticipated heat exchanger maintenance would occur on a 1 or 2-year basis (except for catastrophic failures). Therefore, it is imperative to determine the impact of heat exchanger leaks on the system maintenance plan and on operating costs. In our NH₃ leak analysis, we assumed that once a leak developed, leakage continued until the time of the next normal preventive maintenance.

Figure 6-10. PSD-II 10 MWe Power Generation Costs

The variable parameters investigated include:

- Preventive maintenance cycle; 1 and 2 years
- Heat exchanger life; 10 and 15 years
- Total percentage of holes at end-of-life; 0, 5 and 10 percent
- Leak hole diameter; 0.001 and 0.010 inches

When the preventive maintenance time is reached, leaky tubes are plugged. Total costs between maintenance periods include tube plugging costs (labor, maintenance, downtime) and leaked NH_3 (prior to plugging).

After leaky tubes are plugged, there is a loss in effective area of the heat exchangers. It is assumed that the loss in gross power is proportional to the percentage of tubes plugged.

Each preventive maintenance period has costs associated with:

- Tube plugging
- Cumulative quantity of leaked ammonia
- Reduced system power due to plugged tubes
- Excessive downtime required to plug leaky tubes. (Excessive downtime is that which exceeds the allotted preventive maintenance time, either 7 days per year or 14 days every 2 years).

The cumulative sum of the present value of each of these leakage cost factors are determined for every preventive maintenance cycle during the heat exchanger life and for the total 30-year power plant life. Thus, the total life-cycle cost impact of leaks can be determined and compared to the life-cycle cost of the heat exchangers assuming no leaks. Also, the incremental increase in power generation cost in mills/kw-hr can be determined and compared to power generation costs with no leaks. With these cost factors, it then becomes possible to compare the total 30-year life-cycle costs for leaky and nonleaky heat exchangers.

Figure 6-11 shows the analytical model used predict leak formation as a function of heat exchanger life. The equation of the curve is:

$$\text{Total percentage of holes} = \frac{(N)(N+1)(N+2)(N+3)}{C}$$

where N = number of years

C = constant.

This analysis was discussed in Section 5.5.4.3.

Figure 6-11. Hole Generation Model (Normalized)

Once the present value of the incremental 30-year costs due to leaks is evaluated, the incremental power generation costs are determined as follows:

$$\text{Incremental power generation cost} = \frac{(\text{FCR}) (\Delta\text{Cpv}) (1000)}{(\text{FA}) (T)}$$

where FCR = Fixed charge rate

ΔCpv = 30-year present value cost of plugging and leaked NH_3

FA = 30-year availability factor

T = Number hours/year = 8760.

Figure 6-12 shows the incremental present value capital and power generation costs for a heat exchanger with a 5-percent cumulative total number of holes developed during heat exchanger life. Results are given for a heat exchanger life of 10 and 15 years and for leak hole diameters of 0.001 and .010 inches.

Figure 6-13 plots this data showing the incremental power generation costs due to NH_3 leaks and plugging. For small holes, (.001 inch in diameter) and 5 percent holes end-of-life, incremental power generation costs are moderate (about 2 to 3 mills/kw-hr). However, for larger holes (about .010 inch in diameter), incremental power generation costs become significant (about 9 to 20 mills/kw-hr).

Figure 6-1 previously showed the cost impact of leaks as an overlay on the base power generation costs for a non-leaky heat exchanger. Extrapolation of the minimum leak cost curve shows that a minimum-leak aluminum heat exchanger must last 18.5 years (vs. 15.3 years for a no-leak aluminum heat exchanger) to give the same power generation costs as a power plant using stainless steel heat exchangers with a 30-year life.

Higher ammonia leakage from the aluminum heat exchangers results in aluminum heat exchanger life requirements of 20 to 25 years to give the same power generation cost as non-leaky stainless steel heat exchangers. Since the life expectations for aluminum are from 10 to 15 years, the stainless steel option offers the prospect of producing power at a lower rate than for aluminum.

HEAT EXCHANGER LIFE (YEARS)	PRESENT VALUE LEAK + PLUG COSTS (\$/KW)		INCREMENTAL POWER GENERATION COST (MILLS/KW-HR)	
	0.001 INCH	0.010 INCH	0.001 INCH	0.010 INCH
10	138	932	2.9	19.5
15	104	450	2.2	9.4

Figure 12. Incremental Present Value Capital and Power Generation Costs for Leaky Heat Exchangers

Figure 6-13. Incremental Power Generation Cost Due to Leaked Ammonia and Tube Plugging

The larger incremental power generation rate increases (9 to 20 mills/kw-hr) discussed earlier probably are economically intolerable. Should such a condition occur, partial shutdown of the heat exchanger is required to plug leaky tubes. This impacts system availability. Thus, a tradeoff exists between system availability and the cost of plugging leaks. Allowing leaks to go unplugged for a longer time increases system availability but increases costs because of the increasing cost of leaked NH_3 .

We must attain a balance between satisfying the DOE system availability requirement of 0.90 and producing power at minimum rates.

As discussed in Section 5.5, our baseline system design and our anticipated maintenance plan satisfies the 0.90 availability requirement. A 2-year preventive maintenance cycle is required if the number of leaky

tubes is from 5 to 10 percent. A 1-year preventive maintenance cycle may be used for up to 5 percent tube leaks. With the higher level leakage (5 to 10 percent end-of-life) scenario, operation of the power plant to minimize power generation costs (by using a 1-year preventive maintenance cycle) results in a 30-year power system availability somewhat less than 0.90 (about 0.88). The 0.90 availability requirement is an extraordinarily high requirement. Conventional nuclear and fossil power plants typically are in the 0.60 to 0.80 range.

Further detailed analysis is required to clarify heat exchanger leak parameters and their impact on system costs and operation.

6.2 NET ENERGY AND RESOURCE ANALYSIS

Net energy analysis compares the amount of energy used to build and operate a plant with the amount of energy the plant is expected to produce. The net energy to produce and operate one power system is 3.67×10^{11} Btu (see Figure 6-14). The power output of one 10 MWe power system at 90 percent availability for 30 years is 8.07×10^{12} Btu. The output is about 22 times the energy needed to build and operate the system. Thus, there is a positive return on the energy investment.

Our analysis estimates the energy represented in the components of one power system (the evaporator, condenser, turbine, generator, storage tanks, pumps, valves, pipe runs, control systems, and switchgear). In addition, energy estimates are given for fabrication, assembly, operation and maintenance.

Our analysis does not encompass the entire system. Some components, such as the ship system, do not produce energy. Thus, the net energy return ratio for the full system is lower than the ratio for a power system alone. Typical OTEC power system ratios given in the literature are around 7 or 8.

The methods used in this analysis are similar to those of Perry et al (Reference 6-1). They are based on weights of materials and parts rather than costs since weight estimates are more reliable at this stage of design development. Figure 6-14 lists the components of one power system, with estimated weight for each. Energy coefficients in Btu/ton have been

Figure 6-14. Net Energy Content of 10 MWe Power System

COMPONENT	WEIGHT POUNDS*	WEIGHT TONS (2000 LB)	AVERAGE PRIMARY ENERGY REQUIRED 10 ⁶ BTU TON	INDUSTRY IDENTIFICATION NUMBER	BTU PER COMPONENT
(EVAPORATOR)					
CORES	480,000	240.0	222	38.08	5.33 x 10 ¹⁰
STRUCTURE	56,180	28.0	222	38.08	6.20 x 10 ⁹
(CONDENSER)					
CORES	480,000	240.0	222	38.08	5.33 x 10 ¹⁰
STRUCTURE	56,180	28.0	222	38.08	6.20 x 10 ⁹
TURBINE GENERATOR		100.0	332	43.01	2.32 x 10 ¹⁰
TRIP VALVE (60")	8,000	2.0	111	40.06	2.22 x 10 ⁸
BYPASS VALVE (30")	3,600	1.8	111	40.06	2.00 x 10 ⁸
ACTUATOR & ACCUMULATOR	600	0.3	146	49.05	4.38 x 10 ⁷
LUBE OIL CONSOLE (WET)	40,000	20.0	110	49.01	2.20 x 10 ⁹
(PIPING)					
LIQUID LINES/VALVES PUMP TO EVAP.	15,050	89.0	111	40.06	9.9 x 10 ⁹
LIQUID LINES/VALVES COND. TO PUMP	14,120				
VAPOR LINES/VALVES EVAP. TO TURB.	70,160				
VAPOR LINES/VALVES TURB. TO COND.	78,650				
STRAINERS	8,760	4.4	111	40.06	4.88 x 10 ⁸
SEPARATORS	40,800	20.4	111	40.06	2.26 x 10 ⁹
FEED PUMPS	14,200	7.1	110	49.01	7.81 x 10 ⁸
MOTORS & CONTROLLERS	6,000	3.0	131	53.04	3.93 x 10 ⁸
PIPING SUPPORTS	90,000	45.0	111	40.06	5.00 x 10 ⁹
(BIOPULPING CONTROL)					
TUBE CLEANING AND POSITIONER	14,000	7.0	114	46.03	7.98 x 10 ⁸
TUBE CLEANING HEAD	1,000	0.5	251	49.07	1.26 x 10 ⁸
CONTROLLER-RECORDER	50	0.1	256	53.05	2.56 x 10 ⁷
CHLORINE GENERATOR	2,100	1.1	251	49.07	2.63 x 10 ⁸
POWER SUPPLY	2,200	1.1	256	53.05	2.82 x 10 ⁸
AMMONIA LEAK DETECTION	5,270	2.6	256	53.05	6.66 x 10 ⁹
(ELECTRICAL POWER DISTRIBUTION & CONTROL)					
4.16 SWITCHGEAR	38,000	19.0	252	53.03	4.79 x 10 ⁹
440 V POWER TRANSFORMER	5,000	2.5	85	53.02	
440 V MOTOR CONTROL CENTER	4,800	2.4	256	53.05	6.14 x 10 ⁸
SWITCH, CONTROL, WIRING	10,650	5.3	256	53.05	
(INSTRUMENTATION & CONTROL SUBSYSTEM)					
CONTROL CENTER	6,400	3.2	431	53.01	1.38 x 10 ⁹
	25,000	12.5	1,022	51.01	1.28 x 10 ¹⁰
(AMMONIA STORAGE CONDITIONING & SUPPLY SUBSYSTEM)					
PURIFICATION COLUMN	8,100	4.1	111	40.06	2.43 x 10 ¹⁰
HEEL STORAGE	135,000	67.5			
WET STORAGE DRUM	135,000	67.5			
DRY STORAGE DRUM	135,000	67.5			
REFLUX ACCUMULATOR	1,100	5.5	110	49.01	2.64 x 10 ⁸
BLOWDOWN DRUM	7,900	4.0			
RECIRCULATION AMMONIA DRUM	1,000	0.5			
OVERHEAD CONDENSER	2,100	1.1			
RECIRCULATION AMMONIA CONDENSER	1,800	0.9	110	49.01	6.60 x 10 ⁸
PUMPS (6)	4,811	2.4			
COMPRESSORS (2)	12,000	6.0			
PIPING (12" & SMALLER)	38,000	19.0			
(NITROGEN STORAGE CONDITIONING & SUPPLY SUBSYSTEM)					
STORAGE LN ₂	47,000	23.5	111	40.06	4.96 x 10 ⁹
TRANSPORT LN ₂	38,000	19.0			
VAPORIZER	4,300	2.2			
PUMPS (4)	6,449	3.2			
PIPING (6" & SMALLER)	12,000	6.0	97	42.08	5.82 x 10 ⁸
(AMMONIA LIQUID)	238,710	119.4	33	*PERRY ET. AL. 1977	3.94 x 10 ⁹

TOTAL 1,068.1

SUBTOTAL = 2.31 x 10¹¹

AMMONIA MAKEUP AT 10% PER YEAR FOR 30 YEARS 1.18 x 10¹⁰
(PERRY ET. AL. 1977, PG. 25)

COMPONENT FABRICATION AND ASSEMBLY AT 20% OF SUBTOTAL 4.62 x 10¹⁰
(PERRY ET. AL. 1977, PG. 24)

OPERATION AND MAINTENANCE (MOSTLY SPARE PARTS) AT 0.7% OF NET POWER 7.85 x 10¹⁰

TOTAL = 3.67 x 10¹¹

10 MWe OUTPUT FOR 30 YEARS AT 90% AVAILABILITY = 2.37 x 10⁹ Kwhr
= 8.07 x 10¹² Btu

THEREFORE DELIVERED ENERGY
DIRECT & INDIRECT ENERGY = 22

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

estimated for many classes of industrial products in previous publications (Perry et al; Reister, Reference 6-2). These are listed in Figure 6-14 (taken from Perry et al except as noted) for the categories appropriate to the power system components. Multiplying each weight by its energy coefficient and summing the products gives the energy embodied in the power system components, excluding the energy of shipboard assembly.

The energy coefficients are derived from an input-output analysis that traces the multiple flows of energy from primary sources (coal and crude petroleum, hydroelectric and nuclear) through the entire national economy. The rationale of this analysis is set out by Bullard et al (Reference 6-3), who also provide a table of energy coefficients in Btu/dollar for industrial products. Btu/dollars are used because of the economic statistics available for the input-output analysis. Reister has converted some of them to coefficients in Btu/ton using data on the weights and values of industrial shipments. The definitions and conventions that apply to the coefficients in Figure 6-14 are set out in Perry et al (Reference 6-1), with references to Reister and Bullard et al.

REFERENCES

- 6-1 A.M. Perry, et al, Net Energy Analysis of an Ocean Thermal Energy Conversion (OTEC) System, Oak Ridge Associated Universities Research Memorandum ORAU/IEA(M)-77-1, February 1977.
- 6-2 D. B. Reister, The Energy Embodied in Goods, Oak Ridge Associated Universities Research Memorandum ORAU/IEA(M)-77-6, February 1977.
- 6-3 C. W. Bullard, et al, Net Energy Analysis: Handbook for Combining Process and Input-Output Analysis, Energy Research Group, CAC Document 214, University of Illinois, Urbana, October 1976.

7. STAINLESS STEEL FEASIBILITY STUDY

A conceptual design study was performed to assess the feasibility of using stainless steel heat exchanger panels with carbon steel structural support members (strongbacks, headers). The design impact is given here and appropriate sections of the report are referenced for details.

The stainless steel heat exchanger design is as viable as the aluminum design. Although the initial cost is higher, it is competitive with aluminum on a life-cycle cost basis. It also appears to present less risk to the program. The power system design is almost identical for the two heat exchanger options.

7.1 STAINLESS STEEL HEAT EXCHANGERS

The structural design of the full-scale (10 MWe) stainless steel heat exchangers is similar to the baseline aluminum design except for material effects. Stainless steel panels and carbon steel structural support members can be welded together.

Conceptual stress calculations have been made for this design and are reported in Appendix II, Section 12. The panel overall dimensions, panel count and overall heat exchanger dimensions are similar to that of the all-aluminum design. The thermal/hydraulic performance is discussed in Section 3.2, and the cost study of the stainless steel design is included in Section 3.7 and Appendix II, Section 13. The selected materials are summarized in Figure 7-1 and the basis for the selections discussed below.

7.1.1 10 MWe Heat Exchangers Material Selection

7.1.1.1 Panel Composition

A number of austenitic and ferritic compositions with the requisite chromium and molybdenum content are available. Based on formability, welding and actual application data, the austenitic grades are better. A comparison of the alloy content of the austenitic grades (which have potential for seawater) indicates that a suitable composition for OTEC service is:

<u>%Cr</u>	<u>%Ni</u>	<u>%Mo</u>	<u>%Fe</u>	<u>Mn, Si, Cu, P, S, C</u>
20-23	23-28	4-7	bal.	Minor controlled amounts

GENERAL COMPONENT	SUB-COMPONENT	MATERIAL	DIMENSIONS
PANELS		AL-6X (OR EQUIVALENT)	<ul style="list-style-type: none"> • 204 ACTIVE PANELS AT DENSITY OF 15.1/FOOT • 17 PANELS BETWEEN EACH DOWNCOMER
DOWNCOMER	2 SIDE PLATES 2 END PLATES		<ul style="list-style-type: none"> • 48 X 108 X 1/8 INCHES • 1 X 5 INCHES
CYLINDER HEADER (TOP)	SHELL 2 HEADER PLATES 2 END REINFORCEMENT PLATES	ASTM A516 ASTM A516 ASTM A516	<ul style="list-style-type: none"> • 1/2 INCH (24 INCH RADIUS) • 1 X 5 INCHES • 12 X 72 X 5/8 INCHES
CYLINDER HEADER (BOTTOM)	SHELL 2 HEADER PLATES 2 END REINFORCEMENT PLATES	ASTM A516 ASTM A510 ASTM A516	<ul style="list-style-type: none"> • 3/4 INCHES (25 INCH RADIUS) • 1 X 5 INCHES • 12 X 72 X 5/8 INCHES
STRONGBACKS	2 LOWER (INNER) PLATES 6 UPPER (OUTER) PLATES 6 RIB PLATES	AISI 1040 AISI 1040 AISI 1040	<ul style="list-style-type: none"> • 50 X 168 X 1 1/4 INCHES • 34 X 48 X 1 INCHES • 1/2 INCH THICK

Figure 7-1. Stainless Steel Heat Exchanger Component and Materials List

AL-6X, SANDVIK 2RK65, Alloy 20 Mod fall into this range along with a number of other designations. For the 10 MWe concept, all compositions falling in this range and available in suitable mill forms with acceptable seawater performance are interchangeable candidates.

While AL-6X and 2RK65 have had extensive seawater experience, they have not received ASME Code approval. Tentatively, an austenitic alloy with the desired composition of Cr, Ni and Mo should be ordered to meet ASME Code Case 1668. This is the Code Case for Alloy 20 Mod.

The Cabot-Stellite Division has the production capacity and mill form capability to produce Alloy 20 Mod at the required width and at a thickness of 20 mils. Because only 18 mils are required structurally, the extra 2 mils provide forming and corrosion allowances.

7.1.1.2 Headers and Welding Wire

Carbon steel headers are fabricated from ASME SA-516 material. This specification ensures adequate toughness required because of stress corrosion in contaminated anhydrous ammonia. Carbon steel filler metal compatible with the toughness requirements for SA-516 are used for carbon steel welds.

Welded subassemblies are stress relieved at 1200°F to remove residual stresses associated with fabrication. Eliminating residual stresses associated with fabrication mitigates stress corrosion cracking.

Inconel 625 is the welding filler metal to join carbon steel headers to the stainless steel core. It is a universal filler metal used by UCC/Linde to join stainless steels to carbon steel and weld 9 percent nickel steel tanks. The alloy resists corrosion.

7.1.1.3 Sealant

It is not necessary to perfectly blend with sealant the interpanel joint in the stainless steel heat exchanger. Crevices which occur have minimal corrosion effect because of the alloy content of the heat exchanger.

There is little concern about the interpanel sealant in the stainless heat exchanger since it is merely a manufacturing aid or fixture. Leakage between seawater passages in the absence or loss of sealant is of no concern with stainless, eliminating one area which was a concern in the aluminum design. Sealants under consideration are the same as for the baseline aluminum design discussed in Section 3.5.

7.1.1.4 Exterior Surfaces

Antifouling paint containing cuprous or stannous compounds are applied to exterior surfaces of the stainless heat exchangers to minimize macro/micro-fouling and to mitigate concerns in the intermodule area. Weld joints involving carbon steel are coated on the seawater side to minimize galvanic corrosion effects. Ammonia side galvanic corrosion effects are expected to be minimal between the SA-516 and stainless steel.

7.1.2 0.2 MWe Stainless Steel Test Articles Material Selection

Guidelines for material selection for 0.2 MWe test units fabricated from stainless steel include:

- The alloy should have ASME Code approval and ASTM specifications
- The alloy should be available without extensive long-lead times
- The producer should have the capability to produce the mill forms without installing new equipment which causes delays.

Of the compositions which fall within the candidate OTEC composition range, Alloy 20 Mod has the following advantages:

- ASME Code approval
- Standard ASTM and ASME specifications cover its mill forms
- Available in wide sheet up to 48 inches
- Composition is intermediate to such alloys as AL-6X and SANDVIK 2RK65 which have years of applications data. Figure 7-2 shows this composition relative to AL-6X. However, it has not been tested as extensively as AL-6X or 2RK65.

Figure 7-2, Analytic Composition of AL-6X vs. Alloy 20Mod

Therefore, Alloy 20 Mod in sheet form is recommended for the test articles.

AL-6X with nominal composition of 20.25Cr, 24.5Ni, and 6.25Mo has shown excellent seawater service properties and has been endorsed by OTEC consultants to DOE. However, there are problems associated with a near-term application, since the composition does not yet have ASTM specification or ASME Code approval and is not available in wide sheets.

Another candidate, the alloy 21Cr, 25.5Ni and 4.5Mo, (known as SANDVIK 2RK65, AL-4X, 904L, JS-777) has been in use for years but has limited specifications and no ASME Code approval.

Even if alloy 20 Mod proves inferior to alloys such as AL-6X or 2RK65, it will not jeopardize test program objectives (demonstrating functionality, operation and manufacturing expertise). More likely, as a result of the high nominal alloy content of 22Cr 26 Ni 5Mo, it will prove suitable for the 10 MWe unit and as an alternate to AL-6X.

7.1.3 Performance of Stainless Steel Exchangers

The functional characteristics of the stainless steel design are similar to the aluminum design. Key differences are:

- Panel geometry – Wall thickness is reduced from 0.050 inches (aluminum) to 0.020 inches (stainless steel). The heat transfer area per panel (although the heat transfer height remains 8.5 feet) is increased from 75.3 to 83.75 square feet. This increase is a result of tighter pitch of tubes due to thinner walls and thus more passages per panel. Aluminum has 100 and stainless steel has 111 passages.
- Thermal conductivity of stainless steel is considerably lower than aluminum. AL-6X has thermal conductivity of 7.9 Btu/hr-ft-°F; A13004's is about 100.
- Stainless steel "tubing" is expected to remain smoother than aluminum tubing.
- Stainless steel design has higher ratio of water side heat transfer surface to exchanger volume than the aluminum design due to change in panel geometry (111 versus 100 passages per panel). Under otherwise identical operating conditions, the stainless steel design requires about 11 percent higher flow rate of seawater.

7.1.4 Cost of Stainless Steel Exchangers

Appendix II, Section 13, contains details of a cost study for both aluminum and stainless steel heat exchangers. The following initial cost estimates for production articles per square feet of water-side heat transfer surface were used in the system optimization and tradeoff studies:

- Aluminum - \$6/ft²
- Stainless steel - \$10/ft²

Power system cost including life-cycle cost considerations are discussed in Section 6.

7.2 POWER SYSTEM DESIGN

The PSD II system design and optimization model described in Appendix II, Section 1, was modified to incorporate the characteristics of a stainless steel heat exchanger design. Using the aluminum design as a basis, the physical and functional system design characteristics of an optimum stainless design were developed which satisfy all constraints defined by TRW and UCC/Linde.

7.2.1 Changes to the Computer Model

To reflect the changes in functional and physical characteristics and cost of a stainless steel design relative to the baseline aluminum design, several changes were made.

Each panel has 111 tubes (versus 100 for the aluminum design), as a result of the thinner walls and relatively shorter pitch resulting from easier forming.

Tube wall thickness is 0.020 inches (versus 0.050 for aluminum). This implies changes in the area factors relating ammonia and water-side effective heat transfer areas. The condenser uses an outside-to-inside diameter ratio consistent with UCC/Linde's definition of the condensing coefficient:

$$\frac{A_o}{A_i} = \frac{0.79}{0.75} = 1.0533 \text{ (versus } \frac{0.85}{0.75} = 1.133)$$

In the evaporator, for aluminum the effective area ratio was calculated by UCC/Linde as 1.166. This included the fin-effect of tube-to-tube material. For stainless steel, we modified this effective area ratio by the outer diameter area ratio 0.79/0.85:

$$\left(\frac{A_o}{A_i} \right)_{\text{effective, incl. fin-effect}} = 1.166 \frac{0.79}{0.85} = 1.0837 \text{ (versus 1.166)}$$

Thermal conductivity of stainless steel (AL-6X) is 7.9 Btu/hr-ft-°F (versus 100 for aluminum). Combined with the change in wall thickness, this

implies that the thermal conductance of the wall based on inside area is 4865 Btu/hr-ft²-°F (versus 25,567 for aluminum).

Stainless steel tubing is expected to be smoother than aluminum tubing. The relative roughness factor is:

$$\frac{\epsilon}{D} = 0.00008 \text{ (versus } 0.001 \text{)}$$

This is Cranes value for drawn tubing of 0.75 inches inner diameter.

The initial cost, which is equal to life-cycle cost for stainless steel (assuming a 30-year life), is per UCC/Linde's estimation of \$10/ft² based on water-side area (versus \$6/ft² for aluminum). This is for production articles. In the system model, we used the factor 1.678 to relate initial and life-cycle cost of aluminum heat exchangers. This factor is based on preliminary life-cycle cost estimates assuming a 15-year life of aluminum exchangers.

In agreement with UCC/Linde's conceptual design study of the stainless option, we assumed no change in the following parameters:

- Ammonia side heat transfer coefficient relationships (see Appendix II, Section 1)
- Ammonia side pressure drops
- Average exit quality of the evaporator
- Panel size (after forming) and water side geometry.

7.2.2 Results

The stainless steel system design was constrained to the topology which was optimum for the aluminum heat exchangers (16 modules with four in series and four in parallel and identical panel size). The optimum design (with no constraint on the number of panels per module) resulted in a power system production cost of \$1153/kWe versus \$1088/kWe for the unconstrained aluminum design.*

For the baseline aluminum design discussed in Section 5.2.1, the number of panels per module was constrained to be equal for evaporator and condenser

*) These are computer model costs, final cost estimates are slightly different.

to simplify mechanical design. Also, with only a small cost penalty, water velocities were increased to reduce total heat exchanger volume to comply with APL plant ship space constraints. The total number of active panels per module was 204, allowing 11 downcomers per module with 12 segments of 17 active panels in each (see Section 3.1).

To maintain the mechanical design features of the aluminum design in the stainless design, the identical panel count and arrangement must be maintained. The thermal duty required to produce 10 MWe net could only be obtained by slightly adjusting the design fouling factor from 0.0003 to 0.00029 hr-ft²-°F/Btu. There are indications that it may be easier to clean stainless tubes; thus, a lower average fouling factor may be maintained in a stainless design.

The resulting computer printout for the baseline stainless steel system design is shown in Figure 7-3. For comparison with the baseline aluminum design, see Figure 5.2-4. Based on the computer results, the process flow diagram in Figure 7-4 was prepared. It can be compared to Figure 5.1-6.

7.2.3 Conclusions

The stainless and aluminum baseline designs are functionally similar. The intensive state variables, temperature and pressure, are equal throughout the ammonia power loop (by design). The extensive variables are almost equal. For example, the loop ammonia flow rates are 764.0 lb/sec (aluminum) and 767.3 lb/sec (stainless). The increase in heat transfer area to compensate for increased wall thermal resistance is accomplished by increasing the number of water side passages resulting from decreased pitch. The gross power is almost identical (13.93 MWe for stainless versus 13.87 MWe for aluminum). Parasitic power required for seawater pumping is less than one percent higher for stainless. The increase in total water flow rates (about 9 percent) is partially compensated by smaller pressure drop (resulting from lower water velocity and smoother tubes).

The overall heat transfer coefficients for the stainless evaporator/condenser are 719/553 versus 820/623 for the aluminum evaporator/condenser, an average reduction of about 12 percent.

S STEEL			
	W WATER PIPE	C WATER PIPE	
LENGTH FEET	300	2900.0000	
DIAMETER FT	19.4117	13.8424	
NUMBER OF PIPES	1	1	
H2O VEL FT/S	5.0000	5.0000	
WATER REYNOLDS NUMBER	1.1925E+07	6.7342E+06	
WATER FLOW LB/HR	4.0757E+03	3.7742E+03	
PRESSURE DROP PSI	.5356	2.3431	
	EVAPORATOR	CONDENSER	
HEAT TRAN LENG (4 MODULE)	15.3332	15.3332	
TOTAL LENG FT (4 MODULE)	15.0000	15.0000	
NUMBER PANELS (4 MODULE)	315.0000	315.0000	
TUBE DIAMETER I.D. IN	.7500	.7500	
NUMBER TUBES	90554	90539	
HEAT TRAN AREA SQ. FT.	2.7263E+05	2.7258E+05	
HEAT TRANSFERED BTU/HR	1.4502E+09	1.4013E+09	
OVERALL BTU/HR/F/SQFT	719.4427	552.3349	
NH3 HTC BTU/HR/F/SQFT	5725.0000	2230.0000	
WALL HTC BTU/HR/F/SQFT	4355.3054	4355.3054	
WATER HTC BTU/HR/F/SQFT	1353.7934	1126.3533	
FOULING (SQFT HR F/BTU)	2.9000E-04	2.9000E-04	
H2O ENTRANCE TEMP F	32.0000	40.0000	
CHANGE IN WATER TEMP	3.7200	3.3960	
WATER PRESSURE DROP PSID	2.3053	2.1347	
TOTAL ENT & EXIT K VALUE	2.6200	2.6200	
WATER TUBE VEL FT/SEC	5.3915	5.3960	
WATER REYNOLDS NUMBER	4.0906E+04	2.2136E+04	
NH3 ENT FLOW CFS		2.3717E+03	
NH3 EXIT FLOW CFS	1.6902E+03	1.9705E+01	
INLET QUALITY	0.0000	.9541	
OUTLET QUALITY	.9700	0.0000	
NH3 INLET PRES PSIA	135.4921	91.7554	
NH3 OUTLET PRES PSIA	134.0321	91.3754	
NH3 PRES DROP PSID	1.4600	.3760	
ELEVATION FT	25.5000	25.5000	
SAT TEMP AT INLET PRES	72.9015	51.4900	
SAT TEMP AT OUTLET PRES	72.2300	51.2563	
NH3 TEMP DROP F	.6215	.2237	
LOG-MEAN TEMP DIF F	7.3939	9.2979	
INLET	DEMISTER	TURBINE	
PRESSURE PSIA	133.3321	133.4321	
TEMPERATURE F	72.2153	72.0231	
QUALITY	.9700	.9900	
MASS FLOW RATE LB/SEC	733.0369	767.2633	
VOLUME FLOW RATE CFS	1692.0396	1697.2323	
OUTLET			
PRESSURE PSIA	133.3321	91.9554	
TEMPERATURE F	72.1302	51.5044	
QUALITY	.9900	.9540	
MASS FLOW RATE LB/SEC	767.2633	767.2633	
VOLUME FLOW RATE CFS	1694.1375	2366.6604	
DEMISTER DRAIN		FEED PUMP	
QUALITY	0.00	INLET PRES PSIA	97.77
FLOW RATE LBS	15.77	OUTLET PRES	142.39
FLOW RATE CFS	.42	PRES DROP PSID	44.62
CYCLE DATA			
GROSS POWER MW	13.925341	NET POWER MW	10.000000
HOTEL POWER MW	.112500	MIS POWER MW	.350000
WW PUMPS MW	1.225021	WW TOT DP PSI	2.340946
CW PUMPS MW	1.399543	CW TOT DP PSI	5.027751
NH3 PUMPS MW	.233417	F PUMP DP PSI	44.616721
TURBINE BTU/LB	17.733570	TUR EX QUALITY	.954009
PLANT EFF	.023527	MIXING TEMP F	51.686614
COST BREAKDOWN (K\$)			
EVAP HE COST	2726.23	CON HE COST	2725.33
WW PUMP COST	547.70	CW PUMP COST	501.25
NH3 R PUMP	0.00	NH3 F PUMP	150.14
GEN COST	620.23	TURBINE COST	313.96
DELTA CW PIPE	229.43	MISCEL	3150.00
DEMISTER	35.00	TOTAL BOTH HX	5452.11
INSTALLED	11755.33	LIFE CYC COST	11755.33

Figure 7-3. Stainless Steel Baseline

The physical arrangement of the two designs are practically identical. Heat exchanger envelopes are essentially the same. Depending on the detailed design of the ammonia passages, the width of the stainless module is equal or slightly less than the aluminum module.

The cost of a production power module calculated by the computer model is \$1176/kWe for stainless versus \$1108/kWe for aluminum (based on a 15-year life). Note that if the design sensitivity coefficient to fouling (discussed in Section 5.2.2) is applied, the cost per kWe for stainless at $R_f = 0.0003$ is only slightly higher, \$1180/kWe. The stainless design is about 7 percent more expensive than the aluminum design.

Based on preliminary results of DOE's biofouling control program, stainless steel tubes may be easier to keep clean than aluminum tubes. A lower average fouling factor may be maintained for the stainless design. The off-design performance study discussed in Section 5.3 shows that if the average fouling factor decreases from 0.0003 to 0.0002, the net power increases from 10 MWe to about 10.7 MWe for the baseline aluminum design. For the stainless design, the increase is slightly less since the overall heat transfer coefficients are lower.

Finally, it should be pointed out that the comparison of stainless and aluminum heat exchanger designs by UCC/Linde and discussed in Section 3.2 were performed prior to the systems study reported here. This explains minor differences in the data presented.

Figure 7-4. Process Flow Diagram for Stainless Steel Option