12/4-6-92 JSD

PNL-7988

UC-602

Engineering-Scale In Situ Vitrification of Simulated Oak Ridge National Laboratory Liquid Waste Seepage Trenches

**M. E. Peterson
T. D. Powell
C. L. Timmerman**

March 1992

**Prepared for the
Oak Ridge National Laboratory
under a Related Services Agreement
with the U.S. Department of Energy
Contract DE-AC06-76RLO 1830**

**Pacific Northwest Laboratory
Operated for the U.S. Department of Energy
by Battelle Memorial Institute**

MASTER

PNL-7988

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor Battelle Memorial Institute, nor any of their employees, makes **any warranty, expressed or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights.** Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or Battelle Memorial Institute. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

PACIFIC NORTHWEST LABORATORY
operated by
BATTELLE MEMORIAL INSTITUTE
for the
UNITED STATES DEPARTMENT OF ENERGY
under Contract DE-AC06-76RLO 1830

Printed in the United States of America

Available to DOE and DOE contractors from the
Office of Scientific and Technical Information, P.O. Box 62, Oak Ridge, TN 37831;
prices available from (615) 576-8401. FTS 626-8401.

Available to the public from the National Technical Information Service,
U.S. Department of Commerce, 5285 Port Royal Rd., Springfield, VA 22161.

PNL--7988

DE92 010383

ENGINEERING-SCALE IN SITU VITRIFICATION
OF SIMULATED OAK RIDGE NATIONAL LABORATORY
LIQUID WASTE SEEPAGE TRENCHES

M. E. Peterson
T. D. Powell
C. L. Timmerman

March 1992

Prepared for the
Oak Ridge National Laboratory
under a Related Services Agreement
with the U.S. Department of Energy
Contract DE-AC06-76RLO 1830

Pacific Northwest Laboratory
Richland, Washington 99352

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED ^{2P}

SUMMARY

An engineering-scale test of in situ vitrification (ISV) was successfully completed in January 1990 using Oak Ridge National Laboratory (ORNL) nonradioactive cesium (Cs)-spiked soils. The objectives of this engineering-scale ISV test were to: 1) assess the application of electrode feeding to ORNL soils; 2) evaluate several real-time temperature monitoring methods for the melt; 3) evaluate Cs retention in the glass; and 4) determine the effectiveness of a pretreatment filter for removal of Cs from the off-gas stream. The test was part of a larger program to determine the applicability of the ISV process as a remedial action technique for the treatment of ORNL liquid waste seepage trenches.

The test produced a 51 cm (20 in.) x 51 cm (20 in.) x 56 cm (22 in.) deep glass block that weighed 235 kg (518 lb). The subsidence was 28 cm (11 in.) from the original surface grade, which is typical of ISV melts and results from the densification of the soil and decomposition of the limestone in the trench. The electrode feeding system operated with no problems during the test indicating the feasibility of using this system with ORNL soils. The electrode feeding system eliminated the need for preplacement of the electrodes in contaminated soils before initiating ISV operations. The thermal monitoring data showed that the melt operating temperature (1300° to 1475°C) corresponded with the laboratory-measured temperature at a viscosity of 100 poise, which is typical of most ISV operations.

Cesium retention within the melt was measured at 99.63 wt%, which was less than the results (99.99% and 99.90%) from previous tests operated under similar conditions (Carter, Bates, and Maupin 1987; Carter, Koegler, and Bates, 1988). When the ISV process is changed from engineering to full scale, this 0.37 wt% loss to the off gas would create a radiation dose to the operating personnel during ISV remediation of the waste trench. Therefore, a prefiltering method was tested to remove the Cs from the off gas prior to the gases reaching the off-gas treatment system and the operators. By using an in-line high-efficiency particulate air (HEPA) filter prior to the off-gas treatment system, all of the Cs was removed without rapid loading of the

filter, which indicated the viability of this method for removing Cs during processing of the Cs-contaminated portion of the waste trench. In addition to this prefiltering technique, thermal monitoring data indicated that reductions in power reduced the melt operating temperature and correspondingly increased melt viscosity. This method could be used to potentially enhance the Cs retention within the melt by reducing its vapor pressure and its mechanisms of release, such as convective transport within the melt and enhancement of a more impenetrable cold cap to minimize diffusion and increase entrainment at the melt surface.

ACKNOWLEDGMENTS

Pacific Northwest Laboratory gratefully acknowledges Oak Ridge National Laboratory (ORNL) for providing the opportunity to perform this engineering-scale test. We especially appreciate the support of Gary Jacobs the ORNL scientist responsible for the test, and Mike Naney, the ORNL scientist responsible for the optical thermometry and Type C thermocouples.

Pacific Northwest Laboratory is operated by Battelle Memorial Institute for the U.S. Department of Energy under Contract DE-AC06-76RLO 1830.

CONTENTS

SUMMARY	iii
ACKNOWLEDGMENTS	v
INTRODUCTION	1
CONCLUSIONS	5
TEST DESCRIPTION	7
ISV TEST EQUIPMENT	7
TRENCH CONFIGURATION	14
THERMAL MONITORING AND PRESSURE INSTRUMENTATION	17
TEST OPERATIONS AND RESULTS	23
MELT DEPTH VERSUS TIME	24
Melt Processing Temperature	26
Electrical Power	27
Melt Cooldown Temperature	31
Off-Gas System	32
Glass Samples	34
Pressure Measurements	35
REFERENCES	37
APPENDIX - LABORATORY ANALYTICAL PROCEDURES	A.1

FIGURES

1	ISV Process	2
2	Engineering-Scale ISV Equipment	8
3	ISV Engineering-Scale Electrode Feed System	9
4	ISV Engineering-Scale Motor Control Valves for Electrode Feed System	10
5	Engineering-Scale ISV Off-Gas Treatment System	12
6	MM5 Sampling System	13
7	ORNL Engineering-Scale Trench Configuration	16
8	ORNL Engineering-Scale Limestone Trench Before Vitrification	17
9	Blackbody Well/Protection Tube for Accufiber Pyrometer	19
10	Blackbody Well/Protection Tube for Accufiber Light Pipe	20
11	Placement of Thermocouples	21
12	Placement of Blackbody Optical Devices	22
13	ISV Block Produced During Engineering-Scale Test	23
14	Glass Block After Walls Were Removed	24
15	Melt Depth vs Time as Determined by Type K Thermocouples	25
16	Type C Thermocouple Data	26
17	Engineering-Scale Power Data	27
18	Voltage and Amperage Data for Engineering-Scale Test	28
19	Calculated Electrical Resistance During the Engineering-Scale Test	29
20	Effects of Power Fluctuation on Melt Temperature	30
21	Melt Cooldown Temperature	31

TABLES

1	Composition of ORNL Soil and Limestone	14
2	ORNL Type C Thermocouple Protection	21
3	Cs Release to the Off-Gas System During the Test	33
4	Analysis of Glass Samples	34

INTRODUCTION

The Pacific Northwest Laboratory (PNL) is developing a remedial action process for contaminated soils that is significant in its application to immobilize or destroy contaminated materials. The process, in situ vitrification (ISV), was developed for the U.S. Department of Energy (DOE) to demonstrate a potential technology for disposal of soil contaminated with transuranic waste at the Hanford Site in southeastern Washington. Tests have demonstrated that hazardous chemical wastes are also destroyed or immobilized as a result of the process. This report presents continuing efforts and further evidence of the applicability of ISV to Oak Ridge National Laboratory (ORNL) liquid waste seepage trenches.

In situ vitrification is a thermal treatment process that melts contaminated soils to form a glass and crystalline substance. Figure 1 illustrates the ISV process. Four graphite electrodes are inserted a few inches into the ground in a square array. Because soil is not electrically conductive, a mixture of flaked graphite and glass frit is placed among the electrodes to serve as a starter path. Once an electrical potential is applied to the electrodes, an electrical current is initiated in the starter path to begin the melt. The graphite starter path is eventually consumed by oxidation, and the current is transferred to the molten soil, which is processed at temperatures between 1200° and 2000°C. As the molten or vitrified zone grows, it incorporates or encapsulates any radionuclides and nonvolatile hazardous elements into the glass structure. The high temperature of the process destroys organic components by pyrolysis. The pyrolyzed by-products migrate to the surface of the vitrified zone and combust in the presence of air. A hood placed over the area being vitrified directs the gaseous effluent to an off-gas treatment system. The molten material, which is trapped in the glass and crystalline product, is then allowed to cool.

FIGURE 1. ISV Process

This report presents the results of an engineering-scale ISV test conducted for ORNL. The objectives of this engineering-scale ISV test were to: 1) assess the application of electrode feeding to ORNL soils, 2) evaluate several real-time temperature monitoring methods for the melt, 3) evaluate Cs retention in the glass, and 4) determine the effectiveness of a pretreatment filter for removal of Cs from the off-gas stream. This test is part of a larger program to determine the applicability of the ISV process as a remedial action technique for the treatment of ORNL liquid waste seepage trenches.

CONCLUSIONS

An engineering-scale ISV process verification test was successfully completed using ORNL nonradioactive Cs-contaminated soils. Analysis of test data provided the following conclusions:

- The electrode feeding system operated without problem in the engineering-scale test, therefore, the application of this system to ORNL soils is feasible.
- The instrumentation (blackbody optical devices and Type C thermocouples with various coatings and sheaths) used to monitor melt temperatures performed well. Data from this portion of the test will provide the basis for a decision on which instrumentation to use in the pilot-scale test.
- Cesium retention within the melt was measured at 99.63 wt%, which is less than measurements taken from previous tests. The release of 0.37 wt% Cs to the off gas will create a radiation dose to operating personnel; therefore, the off gas will require prefiltering.
- A high-efficiency particulate air (HEPA) filter was tested with the standard ISV quenching, scrubbing, and filtering off-gas treatment system to evaluate its effectiveness for Cs removal before Cs reached the off-gas treatment system (0.37 wt% Cs was released to the off gas). The HEPA filter proved effective; after filtering, no Cs was detected downstream.
- In addition to this prefiltering technique, which removes Cs from the off gas, thermal monitoring data indicated that reductions in power reduced the melt operating temperature and therefore, increased melt viscosity. This method could potentially enhance Cs retention within the melt by reducing vapor pressure and mechanisms of release, such as convective transport within the melt and enhancement of a more impenetrable cold cap to minimize diffusion and entrainment at the melt surface. This method will be further evaluated in the pilot-scale test.

TEST DESCRIPTION

This section describes the engineering-scale ISV test equipment, the trench configuration, and thermal and pressure monitoring instrumentation.

ISV TEST EQUIPMENT

The engineering-scale ISV unit used for this test is shown in Figure 2. The unit consists of an aluminum container, measuring 1.8 m (6 ft) in diameter by 2.4 m (8 ft) in height, with an electrode feed system mounted on the cover of the container. The container is sealed allowing the off-gas system to remove any gases or particulate generated during the vitrification process.

The four electrodes are powered by a 30-kVA (30-kW) variable voltage transformer. Power is controlled with two saturable core reactors on the secondary side of the transformer. Using a paint brush, the four graphite electrodes, each 5 cm (2 in.) in diameter, were coated with three layers of silicon carbide (SiC) to minimize oxidation during the ISV process. The bottom 15.2 cm (6 in.) of the electrodes remained uncoated to prevent any initial adherence of the molten soil to the graphite electrodes, which may cause the electrodes to become hung up or frozen in the cooler, partially solidified surface glass.^(a) Of these uncoated portions of the electrodes, 10 cm (4 in.) was inserted into the soil prior to start up. (Subsequent ISV tests have shown that the SiC electrode coating resulted in the electrodes adhering to the cold cap; therefore, the coating is no longer recommended.)

The electrode feed system and motor control valves for the system are shown in Figures 3 and 4, respectively. The electrodes were spaced 30.5 cm (12 in.) apart. The feed system consists of a pneumatic motor and gripper for each electrode to provide control of the rate of electrode movement within the melt. With the gripper deactivated, the electrodes are free to move down with the advancing melt. By activating the gripper, the electrode can be held stationary or the motor can be used to raise or lower the electrode as needed.

(a) Graphite is not "wetted" or adhered to by the molten glass; SiC-coated graphite will allow the molten glass to adhere to the electrodes.

FIGURE 2. Engineering-Scale ISV Equipment

FIGURE 3. ISV Engineering-Scale Electrode Feed System

FIGURE 4. ISV Engineering-Scale Motor Control Valves for Electrode Feed System

The electrode feed system is economical and efficient because the graphite electrodes are less expensive than the molybdenum graphite electrodes (Buel et al. 1987). Electrode emplacement costs are also reduced by eliminating the drilling into contaminated sites for preplacement of the electrodes. Also, this system provides a mechanism to alleviate an electrical shorting condition in the melt (Buel and Farnsworth 1990).

The engineering-scale ISV off-gas treatment system (shown in Figure 5) consists of a condenser with knockout pot, a heater, and a HEPA filter. For this test, another HEPA filter was installed in the off-gas treatment system upstream from the condenser in order to evaluate the effectiveness of this filter for removing Cs. This HEPA filter was manufactured by Flanders and had dimensions of 30.5 cm (12 in.) x 30.5 cm (12 in.) x 30.5 cm (12 in.). The filter had a removal efficiency of 99.97% at 260°C (500°F) for particulate sized 0.3 μ m and larger.

Throughout the test, the off gases from the vitrification process were sampled throughout the test using a U.S. Environmental Protection Agency (EPA) referenced Modified Method 5 (MM5) sample train (40 CFR 60 Appendix A). The MM5 sampling system is shown in Figure 6. Off gases were sampled from the 5-cm (2-in.) off-gas line through a 0.95 cm (0.375 in.) in diameter heated probe assembly. Particulate in the off gas was collected on a glass fiber filter. The probe and glass fiber filter were maintained at approximately 130°C (250°F) to prevent condensation on the filter. After exiting the filter, the off gas entered a series of four impingers contained in an ice bath. The first impinger was empty, the second and third impingers contained deionized water, and the fourth impinger contained silica gel. The impingers were used to remove condensibles and soluble components from the off gas and to remove any particulate that may have passed through the fiber filter. The silica gel dried the off gas before the gas reached the sampling system control unit. The moisture removed using the silica gel was measured and used to determine total water content. The sampling system control unit controlled the sampling rate and monitored the off-gas sampling volume and the temperatures of the probe, filter, and impingers.

FIGURE 5. Engineering-Scale ISV Off-Gas Treatment System

The primary objective of the off-gas sampling was to verify the effectiveness of the HEPA filter for removing Cs from the off gas prior to the gases reaching the off-gas treatment system. Engineering measures such as this filter will be necessary for large-scale ORNL trench remedial applications in order to minimize radiation exposures to workers from the ^{137}Cs collecting in the off-gas system. The HEPA filter was installed with a valved bypass to allow the off-gas flow to be routed through the bypass line until the melt approached the center of the Cs zone, at which time the off-gas flow was redirected through the HEPA filter. Figure 5 illustrates the location of the prefilter and the sampling location.

FIGURE 6. MM5 Sampling System

The MM5 sampling system was implemented after the start-up material (frit/graphite starter path) had been consumed to eliminate loading the fiber filter with this particulate material. Four distinct phases of sampling were performed. Phase I consisted of sampling the off gas from the start of the test until the thermocouple data indicated that the melt was approaching the

top of the Cs-containing zone. At this point, the glass fiber filter was replaced with a new filter. Phase 2 consisted of sampling the off gas until the melt reached the upper half of the Cs-containing zone. The prefilter was not used during this phase. The fiber filter again was replaced with a new filter, and the deionized water in the second and third impingers was replaced with new water. In Phase 3, the off-gas flow was routed through the HEPA filter. This phase consisted of sampling the off gas until the melt reached the lower half of the Cs-containing zone. The fiber filter was replaced with a new filter. Phase 4 consisted of sampling the off gas as the melt proceeded below the Cs-containing zone without using the prefilter. During Phase 4, power to the melt was fluctuated. Changing of the fiber filters allowed for a measurement of Cs release as a function of time.

TRENCH CONFIGURATION

The compositions of the ORNL soil and the limestone used in this test are provided in Table 1. The soil and limestone compositions were the same as those used in a laboratory study that evaluated the effect of varying soil and limestone ratios, as well as the addition of a sodium flux on melt viscosity,

TABLE 1. Composition of ORNL Soil and Limestone

<u>Oxide</u>	<u>Oxide (wt%)</u>	
	<u>Soil</u>	<u>Limestone</u>
Al ₂ O ₃	16.3	1.7
CaO	5.4	47.6
Fe ₂ O ₃	5.6	0.7
K ₂ O	4.1	1.5
MgO	2.0	3.6
MnO ₂	0.1	0.03
Na ₂ O	1.3	0.5
SiO ₂	55.6	5.3
SrO	0.02	0.05
TiO ₂	0.70	--
Total	91.12	60.98

electrical conductivity, and Cs volatility (Shade and Piepel 1990). The trench for the engineering-scale test was composed of limestone with cesium carbonate added within the voids of the limestone. A small amount of sodium carbonate was also added to the limestone trench region to simulate the Na content in the ORNL trenches and to evaluate the effect on Cs volatility in the presence of increased Na content. The remaining processed soil was from ORNL and was representative of the soil encountered at that site.

The trench configuration is shown in Figure 7. Oak Ridge soil was placed in the center of the container in a 91.4-cm (36-in.) circle starting at the 91.4-cm (36-in.) depth. The limestone trench was constructed between the 20.3-cm (8-in.) to 45.7-cm (18-in.) depth and contained 7.0 kg of Na_2CO_3 and 25.9 kg of limestone. At the 35.6-cm (14-in.) to 45.7-cm (18-in.) depth, 1220 g of cesium carbonate was mixed with the limestone and Na_2CO_3 in the area of the trench between the electrodes. The Cs was positioned in the trench so that all the Cs would be consumed during the vitrification process. Type K thermocouples were located on the top, bottom, and center of the Cs area to monitor melt progress through this area. The limestone trench pictured in Figure 8 measured 43.2 cm (17 in.) long by 25.4 cm (10 in.) deep with the area external to the trench filled with Oak Ridge soil out to the 91.4 cm (36 in.) diameter. Hanford soil was placed in the engineering-scale container in areas that would not be vitrified.

A starter path 2.5 cm (1 in.) x 2.5 cm (1 in.) consisting of graphite and glass frit was placed between the electrodes in an "X" and square pattern. A 2.5-cm (1-in.) pure graphite flake layer was placed around each electrode, and then a 2.5-cm (1-in.) layer of graphite and glass frit was placed on top of the pure graphite flake. Sand was blended with the ORNL soil that filled the top 5 cm (4 in.) of the trench in order to eliminate the void space in the coarse ORNL soil. This ensured that continuity of the electrode path would not be disturbed by the molten soil flowing into the voids during the initial start-up period. The area between the electrodes was covered with 2.5 cm (1 in.) of soil and 2.5 cm (1 in.) of alumino-silicate insulating blanket to minimize heat surface loss and promote melt surface subsidence during processing. A gap in the insulation around each electrode provided a gas vent.

FIGURE 7. ORNL Engineering-Scale Trench Configuration

FIGURE 8. Engineering-Scale Limestone Trench Before Vitrification

THERMAL MONITORING AND PRESSURE INSTRUMENTATION

Type K thermocouples were used to monitor the depth of the vitrification process. These thermocouples were located in the center of the vitrification zone. The first thermocouple was placed 5 cm (2 in.) below the soil surface, and subsequent thermocouples were placed every 5 cm (2 in.). The last thermocouple was located at a depth of 61 cm (24 in.). The thermocouple measurements were recorded on a strip chart recorder located in the engineering-scale control console.

Oak Ridge scientists tested and evaluated two blackbody optical devices and six Type C thermocouples with varying protective coatings and sheaths. The blackbody optical devices are shown in Figures 9 and 10. The six Type C thermocouples and their associated protective coatings and sheaths are listed in Table 2. The sheathing protected the thermocouples from corrosion and oxidation, and the sheathing and thermocouples were evaluated in combination to

obtain performance data. These thermal measuring systems were monitored on a real-time basis using a separate data acquisition system. These Type C thermocouples were located at a depth of 16 in. The placement of the thermocouples and blackbody optical devices is shown in Figures 11 and 12. The two blackbody optical devices were at a depth of 18 to 21 in.

Two pressure transducers were installed in the engineering-scale container. These transducers were manufactured by Omega and had a range of 0 to 50 psi with an accuracy of ± 1.0 psi. The transducers were buried in the soil and connected with 0.25-in. tubing to digital displays for monitoring. One was placed 25.4 cm (10 in.) below the soil surface near the center of the vitrification area, and the other was placed 50.8 cm (20 in.) below the soil surface near the center of the vitrification area. These pressure transducers were installed to monitor pressure gradients due to moisture ahead of the advancing melt.

FIGURE 9. Blackbody Well/Protection Tube for Accufiber Pyrometer

Graphite
Stainless Steel

FIGURE 10. Blackbody Well/Protection Tube for Accufiber Light Pipe

TABLE 2. ORNL Type C Thermocouple Protection

Thermocouple Number	Protection Description
1	0.25-in. alumina tube inside a 0.5-in. alumina tube purged with Ar
2	Al coating on thermocouple inside a 0.5-in. alumina tube
3	0.25-in. alumina tube inside a 1-in. graphite tube purged with Ar
4	0.5-in. alumina tube
5	Rustoleum® Al coating on thermocouple inside a 1-in. graphite tube
6	0.25-in. alumina tube purged with Ar

FIGURE 11. Placement of Thermocouples

FIGURE 12. Placement of Blackbody Optical Devices

TEST OPERATIONS AND RESULTS

The test duration was 20.5 h and resulted in a 235-kg (518-lb) glass block that measured 51 cm (20 in.) wide on both sides and 56 cm (22 in.) deep. The block produced is shown in Figure 13. The resulting glass was composed of 87% soil and 13% limestone. The block had a large surface subsidence, approximately 40% of the block size that measured 28 cm (11 in.) deep from the original surface grade. The subsidence was created by the densification of the soil and decomposition of the limestone trench. The subsidence portion of the block was included in the overall dimensions of the block due to the significant amount of glass that formed the walls of the subsidence cavity. A small hammer and wire brush were used to remove nonvitrified material from the block to achieve an accurate weight of the glass produced. The walls of the

FIGURE 13. ISV Block Produced During Engineering-Scale Test

subsidence cavity, which weighed 25 kg, were removed from the block. The block without the walls is shown in Figure 14. Earlier tests using electrode feeding on soils with high metal content have produced blocks with near vertical walls and minimal lateral growth (Farnsworth, Oma, and Bigelow 1990), possibly attributable to the metal pooling and corresponding power concentration at the bottom of the melt. With ORNL soils and trench configuration, the electrode feed system did not affect the melt shape as the resulting tear-drop melt shape was typical of ISV melts.

MELT DEPTH VERSUS TIME

The Type K thermocouple measurements obtained from the center of the melt were used to assess the melt depth versus time. When the glass reached the depth at which the thermocouple was located, these readings went off-scale. The melt depth versus time is shown in Figure 15. During the initial

FIGURE 14. Glass Block After Walls Were Removed

FIGURE 15. Melt Depth Versus Time as Determined by Type K Thermocouples

4.6 h of the test, the melt progressed downward fairly rapidly at a rate of approximately 2.6 in./h. As the melt proceeded, the melt rate slowed to approximately 0.35 in./h. The inclusion of limestone in the melt resulted in a decrease in the melt temperature, an increase in electrical conductivity, and a decrease in viscosity; these changes resulted in a slightly increased melt rate (Shade and Piepel 1990). As the melt proceeded past the limestone trench, soil was incorporated into the melt and resulted in an increase in the melt temperature, a slight decrease in electrical conductivity, and an increase in viscosity. Therefore, the melt depth rate slightly decreased. In Phase 4 of this test, power to the melt was reduced to evaluate the effect of power reduction on the melt temperature. The reduction in power slowed down the melt rate. Power was increased at the end of the test to observe a corresponding increase in melt temperature and melt rate. (The phases are described in the test description section of this report).

Melt Processing Temperature

The melt temperature was monitored continuously during the test. The plot of the six Type C thermocouples is provided in Figure 16. Thermocouple #5 was not in the melt region during a majority of the test operations and should be disregarded. The temperature data showed that the melt temperature ranged from 1300° to 1400°C during this test. This corresponded closely with the 1330°C temperature measured in the laboratory for a melt viscosity of 100 poise (T100P). An ISV melt typically operates near the T100P temperature

FIGURE 16. Type C Thermocouple Data

(Buelt et al. 1987). All of the Type C thermocouple protection survived the conditions of the ISV melt. The graphite tubes from the pyrometers were significantly oxidized.

Electrical Power

A representation of the electrical power used during this test is shown in Figure 17. The total energy consumed for the test was 335 kWh. This resulted in an energy-to-mass ratio of 1.4 kWh/kg of soil and limestone that were vitrified. The mass of soil and limestone incorporated into the block

FIGURE 17. Engineering-Scale Power Data

weighed approximately 245 kg. The voltage and amps supplied to the melt are shown in Figure 18, and the calculated electrical resistance is shown in Figure 19.

After 16.9 h of operation, the power to the melt was fluctuated to obtain data on the dynamic effects of power reductions on melt temperature. These corresponding data on reduced melt temperature and increased molten soil viscosity may benefit ORNL ISV remediation of the radioactive trenches. The reduced melt temperature may reduce the Cs volatility. The Cs-contaminated zone is only a small section of the vertical profile of the trench and is also at the bottom of the trench. If the ISV melting process was operated at reduced power levels during the period of time that the melt is passing through the contaminated zone, the reduced melt temperature may enhance the Cs retention within the melt by reducing vapor pressure and its mechanisms of release, such as convective transport within the melt and diffusion to the

FIGURE 18. Voltage and Amperage Data for Engineering-Scale Test

FIGURE 19. Calculated Electrical Resistance During the Engineering-Scale Test

melt surface where it may become entrained into the off-gas stream. The reduce melt temperature would enhance the formation of a more impenetrable cold cap to reduce the release of Cs to the off-gas system.

The effects of power fluctuation on the melt temperature are illustrated in Figure 20. The melt temperature was monitored with the Type C thermocouples. Thermocouple #5 was not in the melt region during the power fluctuation period and therefore, it is not included in Figure 20. The left side of the graph shows a reduction in melt temperature of approximately 200°C when the power was reduced from 100% to 50% (from 18 to 9 kW). The center of the graph indicates the effect of increasing the power from 50% to 75% (from 9 to

FIGURE 20. Effects of Power Fluctuation on Melt Temperature

14 kW). The melt temperature increased approximately 75°C but the melt temperature was still 100°C less than the melt temperature at 100% power. The right side of the graph shows the increase in the melt temperature at 100% power. The melt temperature was slightly higher when 100% power was restored. The power to the melt was higher because the glass resistance had increased due to cooling.

As shown in Figure 20, within a period of about 1 h after a power fluctuation, the melt temperature reached a new equilibrium. These data show the significant effect that the power level had on the melt temperature and its potential use for reducing Cs volatility in ORNL trenches.

Melt Cooldown Temperature

After the test, the melt temperatures were monitored during the cooldown period and are shown in Figure 21. These temperature data show that the melt cooldown matches the projected exponential-type curve identified from previous ISV studies (Buel et al. 1987). The curve shows that the typical rapid cooling at the beginning slowed as the surrounding soil and glass block reached a slow transition equilibrium temperature.

FIGURE 21. Melt Cooldown Temperature

Off-Gas System

The average off-gas flow during the test was 872 L/min [30.8 dry standard cubic feet (dscf)]. A representative off-gas sample was drawn at 15.1 L/min (0.77 dscf/min) through the MM5 particulate sample train to analyze the off-gas stream for Cs releases. The MM5 sample train filters, the prefilter, and the engineering-scale containment vessel smears were analyzed in order to quantify the release of Cs and other elements from the melt during ISV operations. Off-gas sampling was performed in the four phases first described in Test Equipment. Phase 1 samples were taken during the period from the start of the test until the melt reached the top of the Cs-containing zone; Phase 2 samples were taken until the melt reached the upper half of the same zone; Phase 3, until the melt reached the lower half of the zone; and Phase 4, as the melt proceeded below the zone. Power to the melt was fluctuated during this final phase.

The MM5 sampling system showed no Cs release during Phase 1. Minor amounts of Cs releases were detected during Phase 2 while the melt was incorporating the upper region of the Cs zone. With the prefilter in-line during Phase 3, no Cs reached the downstream sampling system, illustrating that the filter was effective in removing all of the Cs prior to the off gases reaching a typical ISV wet scrubbing and filtration off-gas system. The highest release of Cs to the off gas occurred during Phase 4 when all the Cs-containing zone had been encompassed into the melt and the prefilter was not used. The higher release of Cs during Phase 4 may have occurred because of the longer residence time for the Cs to become distributed within the melt and exposed to the surface of the melt where it could be diffused and be swept into the off-gas system. The relative Cs releases for these various sampling phases and the amount of Cs captured in the in-line prefilter are presented in Table 3. Filters 1, 2, 3, and 4 listed in Table 3 are from the MM5 sample train. The total Cs release was calculated by multiplying the Cs concentration found on the filter by the off-gas volume divided by the sample volume. Filters 1 and 3 exhibited concentrations of Cs that were less than those concentrations found in the filter blank.

The data in Table 3 confirm the acceptability of a prefilter to remove Cs prior to its reaching the ISV off-gas treatment system and creating a potential dose to the operating personnel. Other suggested methods may also hold promise as engineered measures to reduce Cs exposure to the ISV operator. These methods include a silver zeolite adsorber bed for selective removal of Cs from the scrub solution, or operating adjustments to the ISV power input to reduce the operating melt temperature and thereby reduce Cs volatility.

The total off-gas release of Cs based on the sampling system, HEPA filter, and container smear data showed that a total of 3.73 g of elemental Cs was released. This corresponded to a 0.37 wt% release of Cs to the off gas or a 99.63 wt% retention of Cs within the ISV vitrified product. This amount of Cs released from an ORNL simulated trench further indicated that appropriate engineering measures need to be applied to remove the Cs during actual trench remediation to prevent significant radiological dose to the ISV operating personnel.

TABLE 3. Cs Release to the Off-Gas System During the Test

<u>Samples</u>	<u>Cs Concentration</u>	<u>Total Cs Release (g)</u>
MM5 System Filters:		
Phase 1	229.6 $\mu\text{g}/\text{filter}$	0.0
Phase 2	3,757.8 $\mu\text{g}/\text{filter}$	0.14
Phase 3	220.1 $\mu\text{g}/\text{filter}$	0.0
Phase 4	64,483.6 $\mu\text{g}/\text{filter}$	2.27
Filter Blank	257.1 blank	blank
MM5 Probe Flush	35.4 $\mu\text{g}/\text{L}$	0.122
HEPA Filter	46,784.9 $\mu\text{g}/\text{L}$	1.10
HEPA Line Flush	123.5 $\mu\text{g}/\text{L}$	0.0145
Hood Smear	1303.8 $\mu\text{g}/\text{L}$	<u>0.086</u>
		3.7325

Glass Samples

Data from three samples taken from the glass block are provided in Table 4. Initial glass elemental and Cs analyses were obtained from a private analytical laboratory. The elemental analyses were incorrect, and the glass was reanalyzed at PNL's analytical laboratory. (We were unable to identify the cause for the erroneous analyses.) Most constituents were fairly evenly distributed among the three samples. A higher concentration of Cs was found in the third sample, which was obtained from the middle of the block. (The first sample was toward the glass surface, and the second sample was toward the middle.) The Cs_2O in the glass did bracket the projected homogeneous concentration of 0.40 wt%. An earlier study illustrated that larger-scale ISV blocks will provide a more homogeneous distribution of the vitrified components (Buehl et al. 1987) than engineering-scale-generated ISV blocks. The target composition was obtained by multiplying the wt% soil in the glass by the soil composition and the wt% limestone in the glass by the limestone composition. The Na_2CO_3 added to the trench was included in the target Na_2O concentration. No leach testing was performed on this vitrified product since previous testing (Carter, Koegler, and Bates 1988; Spalding and Jacobs 1989).

TABLE 4. Analysis of Glass Samples (wt%)

<u>Oxide</u>	<u>Sample 1</u>	<u>Sample 2</u>	<u>Sample 3</u>	<u>Calculated Target</u>
Al_2O_3	14.5	14.5	14.5	14.4
CaO	12.5	12.5	12.5	10.9
Cs_2O	0.28	0.24	0.68	0.40
Fe_2O_3	4.1	4.1	4.05	4.96
K_2O	3.0	3.0	3.0	0
MgO	6.65	6.4	6.55	2.21
Na_2O	5.2	4.8	4.7	2.94
SiO_2	51	51	51	49.06
TiO_2	0.64	0.62	0.66	0.61
Total	97.9	97.1	97.7	85.48

shows the acceptability of the product by the Materials Characterization Center (MCC), Extraction Procedure Toxicity (EP Tox), and Toxic Characteristics Leach Procedure (TCLP) techniques.

Pressure Measurements

Data collected to monitor pressure gradients ahead of the advancing melt were inconclusive. No pressure was indicated on the display until the tubing installed in the soil actually melted. The range of the transducers may have been too high to reveal a small pressure build-up ahead of the melt. This effort will be continued in pilot-scale ISV testing to further understand the impact of electrode feeding with respect to water vapor release from the ISV melt.

REFERENCES

40 CFR 60 Appendix A. 1988. *Determination of Particulate Emissions from Stationary Sources.* U.S. Code of Federal Regulations.

Buelit, J. L., and R. K. Farnsworth. 1990. "In Situ Vittrification of Soils Containing Various Metals." Presented at the Waste Management '90 Symposium, Tucson, Arizona. PNL SA-17242, Pacific Northwest Laboratory, Richland, Washington.

Buelit, J. L., C. L. Timmerman, K. H. Oma, V. F. FitzPatrick, and J. G. Carter. 1987. *In Situ Vittrification of Transuramic Waste: An Updated Systems Evaluation and Applications Assessment.* PNL-4800 Suppl. 1, Pacific Northwest Laboratory, Richland, Washington.

Carter, J. G., S. O. Bates, and G. D. Maupin. 1987. *In Situ Vittrification of Oak Ridge National Laboratory Soil and Limestone.* PNL-6174, Pacific Northwest Laboratory, Richland, Washington.

Carter, J. G., S. S. Koegler, and S. O. Bates. 1988. *Process Performance of the Pilot-Scale In Situ Vittrification of a Simulated Waste Disposal Site at the Oak Ridge National Laboratory.* PNL-6530, Pacific Northwest Laboratory, Richland, Washington.

Farnsworth, R. K., K. H. Oma, and C. E. Bigelow. 1990. *Initial Tests on In Situ Vittrification Using Electrode Feeding Techniques.* PNL-7355, Pacific Northwest Laboratory, Richland, Washington.

Shade, J. W., and G. F. Piepel. 1990. *Viscosity, Electrical Conductivity, and Cesium Volatility of ORNL Vittrified Soils with Limestone and Sodium Additives.* PNL-7331, Pacific Northwest Laboratory, Richland, Washington.

Spalding, B. P., and G. K. Jacobs. 1989. *Evaluation of an In Situ Vittrification Field Demonstration of a Simulated Radioactive Liquid Waste Disposal Trench.* ORNL/TM-10992, Oak Ridge National Laboratory, Oak Ridge, Tennessee.

APPENDIX

LABORATORY ANALYTICAL PROCEDURES

APPENDIX

LABORATORY ANALYTICAL PROCEDURES

The elements in the glass filters, smears, and flush solutions were analyzed with an inductively coupled plasma/atomic emission spectrometer (ICP), and Cs was analyzed using a graphite furnace atomic absorption spectrophotometer (AA). In preparation for elemental analysis, portions of the glass samples were fused with sodium hydroxide and sodium peroxide in a zirconium crucible. The glass samples were placed in a muffle furnace at 500°C for 30 min. The fused sample was dissolved in hydrochloric acid. The dissolved sample was then analyzed using the ICP. In preparation for the Cs analysis, portions of the glass samples were dissolved using a microwave dissolution method. The samples were dissolved in a sealed teflon crucible using hydrofluoric acid. The dissolved sample was then analyzed using AA. In preparation for both elemental and Cs analysis, the filters and smears were subjected to a nitric acid leach. The flush solutions were analyzed directly.

DISTRIBUTION

No. of
Copies

No. of
Copies

OFFSITE

12 DOE/Office of Scientific and
Technical Information

J. Haugen
DOE Chicago Field Office
9800 South Cass Avenue
Argonne, IL 60439

21 DOE Office of Environmental
Restoration and Waste
Management

J. Hall
DOE Nevada Field Office
P.O. Box 98518
Las Vegas, NV 89193-8518

Trevion II Building
12800 Middlebrook Road
Germantown, MD 20874

ATTN: W. W. Alexander
T. D. Anderson
J. E. Baublitz
D. L. Biancasino
J. O. Boda
J. Coleman
S. P. Cowan
J. J. Fiore
C. W. Frank
K. O. Hain
J. M. Lankford
J. C. Lehr
S. C. Lein
J. E. Lytle
S. A. Mann
S. M. Prestwich
M. Shupe
C. H. Sink
L. H. Taylor
H. F. Walter
R. P. Whitfield

R. Tyler
DOE Rocky Flats Office
DOE Building 116
Golden, CO 80402-0928

S. Ketola
DOE West Valley Project
P.O. Box 191
West Valley, NY 14171

W. Fitch
DOE Idaho Operations Office
785 DOE Place
Idaho Falls, ID 83402

M. O'Rear
DOE Savannah River Operations
Office
P.O. Box A
Aiken, SC 29801

2 DOE Albuquerque Operations
Office

P.O. Box 5400
Albuquerque, NM 87115
ATTN: P. A. Saxman
D. H. Bandy

4 DOE Oak Ridge Office
P.O. Box 2001
Oak Ridge, TN 37831
ATTN: J. Moore (2)
J. Sweeney (2)

W. Holman
DOE San Francisco Field
Office
1333 Broadway
Oakland, CA 94612

3 Battelle Memorial Institute
505 King Avenue
Columbus, OH 43201
ATTN: W. A. Carbeiner
R. A. Nathan
Technical Library

No. of
Copies

Jesse L. Yow, Jr.
Lawrence Livermore National
Laboratory
7000 East Avenue
Livermore, CA 94550

M.A.H. Reimus
Los Alamos National Laboratory
P.O. Box 1663
Los Alamos, NM 87545

J. Koger
Martin Marietta Energy Systems
P.O. Box 2009
Oak Ridge, TN 37831-8097

- 8 Oak Ridge National Laboratory
P.O. Box Y
Oak Ridge, TN 37830
ATTN: G. K. Jacobs (4)
M. Naney (2)
B. P. Spalding (2)

K. Nuhfer
Westinghouse Materials Co. of
Ohio
P.O. Box 398704
Cincinnati, OH 45239-8704

- 5 Sandia Laboratories
P.O. Box 5800
Albuquerque, NM 87185
ATTN: D. Berry
R. Knowlton
J. Phelan
L. D. Tyler
Technical Library

- 4 EG&G Idaho
P.O. Box 1625
Idaho Falls, ID 83415
ATTN: S. K. Merrill
D. F. Nickelson
R. R. Stiger
S. Stiger

No. of
Copies

L. Rogers
EG&G Energy Measurements, Inc.
P.O. Box 1912, MS RSL-11
Las Vegas, NV 89125

J. R. Berreth
Westinghouse Idaho Nuclear
Co., Inc.
P.O. Box 4000
Idaho Falls, ID 83401

B. Haas
Ames Laboratory
7 Spedding Hall
Iowa State University
Ames, IA 50011

- 6 Westinghouse Savannah River
Company
P.O. Box 616
Aiken, SC 29801
ATTN: J. S. Haselow
C. M. Jantzen
M. J. Plodinec
J. F. Sproull
J. L. Steele
T. Walton

J. M. Pope
West Valley Nuclear
Services Co.
P.O. Box 191
West Valley, NY 14171

- 3 Geosafe Corporation
2000 Logston Boulevard
Richland, WA 99352
ATTN: C. L. Timmerman (2)
B. E. Campbell

No. of
Copies

ONSITE

13 DOE Richland Field Office

E. A. Bracken, A6-95
K. W. Bracken, A5-22
R. P. Carter, A5-21
P. K. Clark, A6-80
P. F. Dunigan, A6-95
J. K. Erickson, A5-19
R. D. Freeburg, A5-19
M. J. Furman, A6-80
R. E. Gerton, A6-80
J. D. Goodenough, A5-22
J. M. Hennig, A5-21
R. D. Izatt, A6-95
J. J. Sutey, A5-90

14 Westinghouse Hanford Company

W. C. Alaconis, L4-92
H. Babad, B3-68
J. D. Berger, L0-18
J. W. Cammann, H4-54
K. R. Fecht, H4-56
R. E. Lerch, B2-35
H. E. McGuire, B2-35
J. L. Scott, R2-87
J. W. Shade, R4-03
D. A. Turner, R1-10
D. D. Wodrich, R1-48
R. D. Wojtasek, B2-15
B. A. Wolfe, L5-61
R. L. Gilchrist, L5-63

No. of
Copies

35 Pacific Northwest Laboratory

L. Ballou, P7-18
T. M. Bergsman, P7-41
W. F. Bonner, P7-44
J. L. Buel, P7-41
H. C. Burkholder, P7-41
C. C. Chapman, P7-41
T. T. Claudson, K1-66
W. O. Heath, P7-41
C. H. Kindle, P7-41
W. L. Kuhn, P8-38
J. Luey, P7-41
J. L. McElroy, P7-46
M. E. Peterson, P7-41 (5)
T. D. Powell, P7-39
M. R. Shay, K6-25
S. C. Slate, K1-25
S. L. Stein, PNWD
L. E. Thompson, P7-41 (5)
J. S. Tixier, P7-41
R. G. Winkelman, P7-41
S. L. Woosley, P7-41
Publishing Coordination
Technical Report Files (5)

END

**DATE
FILMED
4 129 192**