WSRC-TR--90-97

DE92 017945

MEMORANDUM

W. J. Engle
Engineer

WESTINGHOUSE

1992

Westinghouse Savannah River Company
Savannah River Laboratory
Aiken, SC 29808

Prepared for the U.S. Department of Energy
under Contract DE-AC05-84OR21400

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

WSRC-TR-90-97

NRTSC
NUCLEAR REACTOR TECHNOLOGY
AND SCIENTIFIC COMPUTATIONS

KEYWORDS: LOCA LIMITS
FLOWTRAN
FLOW INSTABILITY
K-14.1 LIMITS
RETENTION: PERMANENT

BENCHMARKING OF FLOWTRAN WITH MARK-22 MOCKUP FLOW EXCURSION
TEST DATA FROM BABCOCK & WILCOX

by

KUO-FU CHEN

ISSUED: JUNE, 1990

J.P. Faraci *6/19/90*

Authorized Derivative Classifier Date

SRL SAVANNAH RIVER LABORATORY, AIKEN, SC 29808
Westinghouse Savannah River Company
Prepared for the U. S. Department of Energy under
Contract DE-AC09-80SR18035

MASTER

DM
DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

PROJECT:

DOCUMENT: WSRC-TR-90-97

TITLE: PRELIMINARY BENCHMARKING OF FLOWTRAN WITH MARK-22
MOCKUP FLOW EXCURSION TEST DATA FROM BABCOCK & WILCOX (U)

QA TASK NUMBER: 89-004-0

REVISION NUMBER: 0

APPROVALS

J. E. Laurinat 6-27-90
J. E. LAURINAT, TECHNICAL REVIEWER DATE

N. H. Kuehn 6-27-90
N. H. KUEHN, TECHNICAL ADVISOR DATE

J. D. Menna 6-27-90
J. D. MENNA, RESEARCH SUPERVISOR DATE

A. J. Garrett 6/27/90
A. J. GARRETT, TECHNICAL MANAGER DATE

K. L. Huffman 6/27/90
K. L. HUFFMAN, RESEARCH MANAGER DATE

ACKNOWLEDGEMENTS

The author wishes to acknowledge G. C. Rush, J. E. Blake, and S. Reed of the Babcock & Wilcox Alliance Research Center for design, construction, and execution of the MK-22 mockup flow excursion test program. Special thanks are extended to F. G. Smith for providing assistance in using the FLOWTRAN code and R. L. Miller for helping to run the FLOWTRAN code and to process the results. The author thanks N. H. Kuehn for careful review and comments on the manuscripts and thanks J. E. Laurinat for conducting a thorough technical review. The author thanks R. B. Pagett for contract administration and C. A. Nash for technical coordination of the test program.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

This report has been reproduced directly from the best available copy.

Available to DOE and DOE contractors from the Office of Scientific and Technical Information, P.O. Box 62, Oak Ridge, TN 37831; prices available from (615) 576-8401, FTS 626-8401.

Available to the public from the National Technical Information Service, U.S. Department of Commerce, 5285 Port Royal Rd., Springfield, VA 22161.

TABLE OF CONTENTS

SUMMARY	9
1. INTRODUCTION	10
2. TEST FACILITY	11
2.1 Test Assembly - Mark 22 Mockup	11
2.2 General Facility Arrangement and Test Operation	13
2.3 Instrumentation	14
2.4 Data Acquisition	15
3. TEST MATRIX	16
4. DATA ANALYSIS	17
4.1 FLOWTRAN Model of Mockup Test Assembly	18
4.2 Hydraulic Characteristics of the Mockup Assembly	21
4.3 Steady State Heated Tests	23
4.4 Transient Test	27
4.5 Quasi-Steady State Power Ramp Tests	28
4.6 LOCA Tests	30
5. CONCLUSIONS	31
REFERENCES	32
APPENDIX A FLOWTRAN INPUT FOR TEST 827_01	142

LIST OF TABLES

1.1	Test Matrix	3 3
2.1	Dimensions Used by FLOWTRAN to Model the Test Section	3 5
2.2	List of Data Acquisition System Instruments	3 6
4.1	Test Conditions for Tests 827_01 to 827_20	4 1
4.2	Derived Channel Surface Roughness and Local Form Losses	4 2
4.3	Measured Pressure Drops for Tests 827_01 to 827_20	4 3
4.4	Measured Flow Distributions for Tests 827_01 to 827_20	4 4
4.5	Comparisons between the Calculated and Measured Pressures (Tests 827_01 to 827_20)	4 5
4.6	Comparisons between the Calculated and Measured Flow Distributions (Tests 827_01 to 827_20)	4 9
4.7	Steady State Heated Test Conditions (Tests 833_01 to 833_02)	5 0
4.8	One Heater Powered Steady state Test Conditions and Measured Channel 3 Exit Fluid Temperature	5 1
4.9	Measured Pressure Drops (Tests 833_01 to 833_02)	5 2
4.1	Measured Flow Distributions (Tests 833_01 to 833_02)	5 3
4.11	Comparisons between the Calculated and the Measured Pressures (Tests 833_01 to 833_02)	5 4
4.12	Comparisons between the Measured and Calculated Flow Distributions (Tests 833_01 to 833_02)	5 8
4.13	Quasi-Steady State Power Ramp Results	5 9
4.14	FLOWTRAN Calculations of the OSV Power for B&W LOCA	6 0

LIST OF FIGURES

2.1	Cross-Section View of Mock-Up Test Assembly	61
2.2	Model Axial Power Profiles for the Inner and Outer Heater Tubes	62
2.3	Heater and Target Tube Rib Details	63
2.4	Test Facility Schematic	64
2.5	Top Fitting Instruments	65
2.6	Channel 2 Pressure and Differential Pressure Taps	66
2.7	Channel 2 and Outer Heater Tube Instruments	67
2.8	Channel 3 Pressure and Differential Pressure Taps	68
2.9	Channel 3 and Inner Heater Tube Instruments	69
2.10	Channel 4 Pressure and Differential Pressure Taps	70
2.11	Channel 4 and Inner Target Tube Instruments	71
2.12	Bottom Fitting Instruments	72
4.1	Illustration of FLOWTRAN Application	73
4.2	Upper Plenum Pressure vs. Assembly Flow, Tests 827_01 to 827_10	74
4.3	Channel 2 Pressure Distributions vs. Assembly Flow, Tests 827_01 to 827_10	75
4.4	Channel 3 Pressure Distributions vs. Assembly Flow, Tests 827_01 to 827_10	76
4.5	Channel 4 Pressure Distributions vs. Assembly Flow, Tests 827_01 to 827_10	77
4.6	Channel Pressure Drop vs. Assembly Flow, Tests 827_11 to 827_20	78

4.7	Upper Plenum Pressure vs. Assembly Flow, Tests 827_11 to 827_20	79
4.8	Channel 2 Pressure Distributions vs. Assembly Flow, Tests 827_11 to 827_20	80
4.9	Channel 3 Pressure Distributions vs. Assembly Flow, Tests 827_11 to 827_20	81
4.10	Channel 4 Pressure Distributions vs. Assembly Flow, Tests 827_11 to 827_20	82
4.11	Channel Pressure Drop vs. Assembly Flow, Tests 827_11 to 827_20	83
4.12	Flow Split vs. Assembly Flow, Tests 827_01 to 827_10	84
4.13	Flow Split vs. Assembly Flow, Tests 827_11 to 827_20	85
4.14	Section View of Mock-Up Test Assembly Depicting Channel Fluid Thermocouple Locations	86
4.15	Measured Channel Fluid Temperature 833_06PW6, Inner Heater Tube Powered	87
4.16	Measured Channel Fluid Temperature 833_05PW6, Outer Heater Powered	88
4.17	Channel Fluid Temperature Test 833_06PW6, Inner Heater Tube Powered	89
4.18	Channel Fluid Temperature Test 833_05PW6, Outer Heater Tube Powered	90
4.19	Channel Fluid Temperature (Test 833_01PW1)	91
4.20	Channel Fluid Temperature (Test 833_01PW2)	92
4.21	Channel Fluid Temperature (Test 833_01PW3)	93
4.22	Channel Fluid Temperature (Test 833_02PW1)	94

4.23 Channel Fluid Temperature (Test 833_02PW2)	95
4.24 Channel Fluid Temperature (Test 833_02PW3)	96
4.25 Channel Fluid Temperature Test 833_01PW1 (with T/C Corrections)	97
4.26 Channel Fluid Temperature Test 833_01PW2 (with T/C Corrections)	98
4.27 Channel Fluid Temperature Test 833_01PW3 (with T/C Corrections)	99
4.28 Channel Fluid Temperature Test 833_02PW1 (with T/C Corrections)	100
4.29 Channel Fluid Temperature Test 833_02PW2 (with T/C Corrections)	101
4.30 Channel Fluid Temperature Test 833_02PW3 (with T/C Corrections)	102
4.31 Channel 2 Pressure Drop (Tests 833_01 to 833_02)	103
4.32 Channel 3 Pressure Drop (Tests 833_01 to 833_02)	104
4.33 Channel 4 Pressure Drop (Tests 833_01 to 833_02)	105
4.34 Flow Split (Tests 833_01 to 833_02)	106
4.35 Measured Pressure Boundary Conditions (Test- 867_02)	107
4.36 Measured Power Decay (Test 867_02)	108
4.37 Test Section Inlet Flow and Flow Distribution (Test 867_02)	109
4.38 Pressure at Channel 2 Inlet and Outlet (Test 867_02)	110
4.39 Pressure at Channel 3 Inlet and Outlet (Test 867_02)	111
4.40 Pressure at Channel 4 Inlet and Outlet (Test 867_02)	112

4.41 Channel 2 Fluid Temperature at T/C Locations (Test 867_02)	113
4.42 Channel 3 Fluid Temperature at T/C Locations (Test 867_02)	114
4.43 Channel 4 Fluid Temperature at T/C Locations (Test 867_02)	115
4.44 Channel 2 Fluid Temperature at T/C Locations (Test 867_02) (With T/C Corrections)	116
4.45 Channel 3 Fluid Temperature at T/C Locations (Test 867_02) (With T/C Corrections)	117
4.46 Channel 4 Fluid Temperature at T/C Locations (Test 867_02) (With T/C Corrections)	118
4.47 Power Ramp Test 836_01	119
4.48 Power Ramp Test 836_02	120
4.49 Power Ramp Test 836_03	121
4.50 Power Ramp Test 836_04	122
4.51 Power Ramp Test 836_05	123
4.52 Power Ramp Test 836_06	124
4.53 Power Ramp Test 836_07	125
4.54 LOCA Test 867_04	126
4.55 FLOWTRAN Calculations of OSV Power for B&W LOCA Tests (Normal Power Decay)	127
4.56 FLOWTRAN Calculations of OSV Power for B&W LOCA Tests (Fast Power Decay)	128
4.57 FLOWTRAN Calculation of Stanton Number (B&W Test 867_04)	129

4.58 FLOWTRAN Calculation of Stanton Number (B&W Test 867_07)	130
4.59 FLOWTRAN Calculation of Stanton Number (B&W Test 867_08)	131
4.60 FLOWTRAN Calculation of Stanton Number (B&W Test 867_10)	132
4.61 FLOWTRAN Calculation of Stanton Number (B&W Test 867_11)	133
4.62 FLOWTRAN Calculation of Stanton Number (B&W Test 867_12)	134
4.63 FLOWTRAN Calculation of Stanton Number (B&W Test 867_13)	135
4.64 FLOWTRAN Calculation of Stanton Number (B&W Test 867_15)	136
4.65 FLOWTRAN Calculation of Stanton Number (B&W Test 867_19)	137
4.66 FLOWTRAN Calculation of Stanton Number (B&W Test 867_22)	138
4.67 FLOWTRAN Calculation of Stanton Number (B&W Test 867_23)	139
4.68 FLOWTRAN Calculation of Stanton Number (B&W Test 867_16)	140
4.69 FLOWTRAN Calculation of Stanton Number (B&W Test 867_21)	141

SUMMARY

Version 16.2 of the FLOWTRAN code with a Savannah River Site (SRS) working criterion ($St=0.00455$) for the onset of significant void (OSV) was benchmarked against power and flow excursion data derived from tests at the Babcock & Wilcox Alliance Research Center test facility.

The analyses show that FLOWTRAN accurately predicts the mockup test assembly thermal-hydraulic behavior during the steady state and LOCA transient conditions, and that FLOWTRAN with a Savannah River Site (SRS) working limits criterion ($St=0.00455$) conservatively predicts the OFI power. Results for LOCA simulations which include a power decay transient for a safety rod SCRAM are shown below. For all of these tests, the calculated test assembly initial power or operating power limit was at least 15.3% below the initial power level for which the test assembly went into flow instability. These calculations were made using the SRS LOCA FI limits methodology adapted to the test assembly.

FLOWTRAN CALCULATIONS OF OSV POWER FOR B&W LOCA TESTS (NORMAL POWER DECAY)

1. INTRODUCTION

Mathematical modeling of reactor power and flow transients is necessary to determine maximum safe operating limits for Savannah River Site (SRS) reactors. These limits ensure that if a postulated accident were to occur, the reactor would shut down safely without damage to the fuel assemblies. The FLOWTRAN, Versior 16.2, computer code [1] models an individual assembly's thermal-hydraulic behavior during normal operating and hypothetical accident transient conditions and calculates the operating power limits. These operating limits are set to prevent the onset of flow instability (OFI) for the most restrictive flow or reactivity induced accident. FLOWTRAN uses a SRS working criterion ($St=0.00455$) for Onset of Significant Void (OSV) [1,2,3] to determine a conservative OFI operating limit.

Flow excursion tests were conducted at the Babcock & Wilcox (B&W) Alliance Research Center test facility using an electrically heated full-scale model of an SRS Mark 22 fuel assembly. The thermal-hydraulic behavior of the test assembly during simulations of postulated accidents was measured. This test program provides data for the FLOWTRAN computer code assessment.

The initial purpose of the SRS FLOWTRAN flow instability benchmark program is to demonstrate that FLOWTRAN with a SRS limit criterion ($St=0.00455$) is a conservative predictor of OFI. This report is based on preliminary data (i.e. data forwarded to SRL before the final B&W test report was issued) and compares calculations to nominal measured data. An updated report which includes uncertainty in the measured data is planned.

Table 1.1 presents the test cases conducted by B&W. Section 2 presents a brief discussion of the test assembly, test loop, test operation, instrumentation, and data acquisition pertinent to the data analysis. Section 3 discusses the test matrix. Section 4 presents the FLOWTRAN analyses of the tests, and Section 5 presents the conclusions.

2. TEST FACILITY

A brief discussion of the test loop, test operation, test assembly, instrumentation, and data acquisition pertinent to the data analysis is presented in this section. The B&W test report [4] describes these tests in detail.

2.1 Test Assembly - Mark 22 Mockup

The test section fuel assembly mockup consisted of parts fabricated at B&W and actual Mark 22 parts supplied by SRS. These were assembled to create a mockup that replicated the Mark 22 fuel assembly in most respects. A Mark 22 fuel assembly consists of an entrance region which is fed from a pressurized plenum, an annular core region composed of two uranium-aluminum fuel tubes and two lithium-aluminum target tubes, and an exit region where flow passes into a tank filled with moderator which surrounds the assembly. The entrance and core region are contained within an annular sleeve housing. The alignment and spacing of the annular tubes is maintained by ribs which subdivide the annular coolant channels into four subchannels (See Figure 2.1). Notable features of the mockup fuel assembly and comparison to an actual Mark 22 are discussed below.

I. The top of the mockup employed an actual universal sleeve housing (USH) entrance, top fitting insert, and spider. The USH was inserted into an exact replica of a permanent sleeve housing that was welded into a replica of a small part of an SRS reactor plenum. This inlet plenum had six dummy permanent sleeves that surrounded the active mockup sleeve and intake slots.

II. The mockup had five flow channels in its heated section as in a Mark 22. The uranium-aluminum fuel tubes in a Mark 22 were simulated by Monel heater tubes. The assembly axial power profile was modeled by varying the wall thickness of the Monel tubes. This resulted in some differences between the channel dimensions of the mockup assembly and those of an actual Mark 22 assembly. In the mockup assembly the coolant channel geometry was scaled to preserve the flow distribution among the channels at prototypic heated section pressure drops. There was no power generation in the simulated target tubes in the mockup tests assembly, since the power generation from the Mark 22 target tubes is very low.

III. The two mockup heater tubes were made of Monel 400 center sections with tapered walls and 70-30 and 90-10 copper-nickel end pieces. By such an arrangement, the transient thermal responses of the heater tubes simulate those of the MK-22 aluminum fuel tubes. The model heater tubes were designed to have a prototypic chopped-cosine axial power profile (Figure 2.2). There was a 52/48 power split between the inner and outer heater tubes, respectively.

IV. The heated section was terminated with thick copper blocks that (1) maintained the concentric annular geometry and (2) provided current paths (up to 25,000 amps/tube) to each of the two heater tubes. The tubes were serviced by a split block at the top. This split block provided the freedom for separate axial thermal expansion, and provided for independent "hot" current sources for the tubes. The bottom end connector mechanically fixed the bottom of the heaters and provided a common ground.

V. Aluminum ribs prototypic of Mark 22 fuel and target tubes could not be used in the mock-up assembly. Instead, thicker ceramic ribs were used to form the subchannels for the inner three coolant channels (Channels 2-4). They provided electrical isolation between the model heater tubes and target tubes. The rib tip clearance as is found in a Mark 22 was preserved in the mockup test assembly to allow crossflow. Figure 2.3 presents the model ribs in detail.

VI. An extension was added to the model inner target tube to provide an instrumentation conduit to the top end of the mockup, where the thermocouple extension wires exited. This tube protected the thermocouple lead wires. The axial stem running down through the top fitting hardware did not change the geometry enough to significantly affect the hydraulics.

VII. Actual aluminum hardware that would be used in a Mark 22 was installed at the bottom of this mockup. It included the bottom of a prototypic universal sleeve housing and an actual "P,L" bottom endfitting insert with a double pressure plate. The monitor pin at the bottom was machined to prototypic dimensions and was instrumented similarly to those of SRS P or L production reactors.

VIII. Instrumentation consisting of thermocouples, pressure sensing lines, Pitot tubes, and void fraction probes was present in the mockup.

Figure 2.1 shows the cross-sectional view of the mockup test section. Reference 4 gives detailed dimensions of the heater tubes. Table 2.1 lists the dimensions used by FLOWTRAN to model the test section.

2.2 General Facility Arrangement and Test Operation

The flow excursion test facility, illustrated in Figure 2.4, is a once-through flow design as opposed to a closed loop design. The testing was of short duration (15 minutes or less). During each transient test initial steady state conditions were established, and then a flow excursion transient was induced. The test loop had two modes of operation, the first at steady-state initial conditions and the second during flow excursion transients.

A 2200 gpm pump provided flow to the test apparatus from a 25,000-gallon reservoir. At steady-state conditions, a substantial portion of this output bypassed the test assembly was returned to the reservoir. This provided a relatively constant pressure source to the mockup facility. This recycle loop also heated the water to the desired temperature using pump power. Flow to the mockup, usually at a nominal rate of 400 gpm, was taken off the recycle loop as shown in Figure 2.4. The water temperature in the reservoir could be set over the range of 77 to 125 F. Flow from the loop was directed to the water-solid 1200-gallon inlet reservoir above the test section. It was carried to the inlet plenum of the mockup, through three symmetric connecting pipes. In steady state, flow exited the bottom of the test section to a holding basin outside of the test facility, which was vented to the atmosphere. The existence of automatic control valves in the discharge line and upstream of the test section inlet reservoir allowed a full range of assembly exit pressures and flow rates to be established at steady state.

When transient simulations were performed, they were initiated after the desired steady flow rate and power conditions were achieved with the mockup. Pressure transients were initiated by activating a quick-closing valve at the inlet to the reservoir tank. At the same time, a gas valve opened, connecting that tank to a gas pressure control system. The control system imposed the desired inlet pressure transient by controlling the pressure of nitrogen gas applied to the inlet reservoir. The gas was introduced at the top of the tank, forcing water down the three bottom-mounted lines going

to the (always water solid) inlet plenum. Gas pressure applied to the inlet reservoir was controlled by a regulator that sensed pressure at the mockup inlet, making dynamic adjustments as the transient progressed.

At the transient initiation, the outlet pressure control system also was activated. Flow output from the mockup was diverted from the holding basin pipe to a pipe connected to the water-solid quench tank that is shown. The water in the quench tank was close to ambient temperature and was intended to quench any steam that might be generated in the transient. The quench tank was connected through a vertical rise of 8-inch pipe to the collection tank, where a nitrogen pressure control system monitored and changed the pressure at the mockup outlet as desired. To reduce outlet pressure during transients, gas was vented from the collection tank. Both the inlet reservoir and collection tank were sized so that post-transient operation of over a minute was easily accommodated.

Characterization tests were conducted to establish the time sequencing of the quick-acting and control valves relative to the start of the power transient to compensate for valve response time.

The power supply was capable of up to 10 MW DC using silicon rectifier controller (SRC) controllers. Powers of up to 6.3 MW were applied in this program. An analog drum controller was used to establish the time-dependent power level for transient runs. Both heater tubes were operated in parallel as opposed to independently, for the LOCA test program.

A protection system was always online to shut off the test section power in the event of operation that endangered the test assembly. It monitored inlet flow to the mockup and also monitored all of the heater metal thermocouples during testing. Different flow and temperature trip levels were set depending on what type of test was being run. A metal temperature trip of 400 °F and flow reduction of 80% below the lowest flow measured from the previous unheated LOCA transient were typical for most LOCA simulations.

2.3 Instrumentation

The data acquisition system received input from 126 instruments. A complete list of the instruments is in Table 2.2 obtained from

Reference 4. Figures 2.5 through 2.12 show the instruments pertinent to the test data analysis. The instruments were used 1) to measure the thermal-hydraulic conditions (power, static pressures, pressure drops, fluid temperatures, heater metal temperatures, and channel exit flow velocities and void fractions) within the heated length, 2) to monitor balance of facility applied conditions including pressure and temperature at the inlet and outlet plena, top and bottom fittings, and the coolant supply and collection systems, and 3) for monitoring ambient conditions or as reference instruments.

2.4 Data Acquisition

The data acquisition system had an Analogic ANDS5400 front end, which was supported by a DEC MicroVAX II computer. The computer stored data during testing and provided real-time data display to the operator. It also performed post test data processing such as conversion of raw data to engineering units and generation of data plots for each test.

The computer software performed pre- and post-test calibration and consistency checks of the instrumentation. Zeroes of the instrument readings were checked and stored before each test. Instruments were checked for reasonable readings and were flagged for repair or removal from the data base between each run. The software also was able to perform simple consistency tests of data from the test bundle.

The data recording rate was usually 1.0 or 100.0 Hz, depending on the test being performed. The 1.0 Hz rate was used for data acquisition during steady state operations, when system changes were slow or absent. Use of this slow acquisition rate was necessary because the computer had a finite storage of 12,000 instrument readings per test. The data acquisition system was switched to the 100.0 Hz rate before a fast transient event was initiated during a test.

The post-test processing included conversion of all data to engineering units, range checking, and consistency checks. Data were eventually stored on magnetic tape. A large series of plots were generated as soon as possible after each test so that both B&W and SRS engineers could examine the run in detail.

3. TEST MATRIX

The tests can be divided into 5 major categories; 1) zero power steady state tests, 2) zero power flow transient tests, 3) steady state heated tests, 4) power ramp flow instability (FI) tests and 5) Loss of Coolant Accident (LOCA) transient tests. The test matrix is summarized in Table 1.1.

1) Zero Power Steady State Tests - Pressure Profile Characterization

These tests were designed to establish the hydraulic characteristics (channel roughness and local losses) of the as-built mockup assembly. In this series of tests, the inlet flow rate, the inlet flow temperature, and the tank bottom pressure were set. The static pressure at the upper plenum, at the channel inlets and outlets as well as the pressure drops cross the channels were measured. The flow distribution among the channels was determined from Pitot tube measurements.

2) Zero Power Transient Tests - Pressure Transient Characterization

These tests were designed to enable the operators of the test to learn to coordinate control valves in both the upper plenum and tank bottom pressure control systems so that a prototypic pressure transient (LOCA induced pressure transient) was produced in the flow system.

3) Steady State Heated Tests

These tests were designed to provide data to qualify the validity of the mockup assembly thermal-hydraulic behavior predicted by FLOWTRAN. In this series of tests, the test section power, the inlet flow, the inlet temperature and the tank bottom pressure were fixed. The pressure, flow, and fluid temperature distributions were measured.

4) Quasi-Steady State Power Ramp Tests

These test data were valuable in benchmarking the ability of FLOWTRAN to conservatively predict the onset of flow instability. In this series of tests, steady state was established at a given inlet flow rate, inlet flow temperature, power level, and tank bottom pressure. Then the power level was increased at a rate of 1,000 KW per

minute, while the rest of the parameters were kept constant. The power was shut off when flow instability occurred.

5) LOCA Transient Tests

LOCA transient tests imposed a pressure transient and power decay transient on the mockup after a steady state heated condition was reached, so that a design basis DEGB LOCA was simulated. In this series of tests, the mockup was started out at a steady state flow condition with specified power level, pressure boundary conditions, and inlet temperature. After a steady state was achieved, a test control sequence was initiated that first imposed an abrupt change in pressure boundary conditions. Then, a power decay transient was imposed to simulate the reactor shutdown system (i.e. the insertion of safety rods). These tests were terminated by one of two means. To protect the test assembly integrity, power was shut off if a high metal temperature or a low water flow, which usually resulted from flow instability, was detected. If the high metal temperature or low flow cut off criteria were not exceeded, the test was allowed to run for a preset time of 30 to 60 seconds after transient initiation.

Test parameters that were varied were 1) inlet temperature, 2) initial power level for a given relative power decay, and 3) relative power transients, which simulated the effects of both a safety rod scram and a proposed fast shutdown system for the LOCA. A single set of transient pressure boundary conditions was used to model all LOCA tests.

4. DATA ANALYSIS

FLOWTRAN is a single-phase transient computer code developed at the Savannah River Laboratory (SRL) to model the SRS fuel assembly thermal-hydraulic behavior during normal reactor operation and hypothetical accident conditions. Version 16.2 of FLOWTRAN is the assembly analysis tool for SRS flow instability limits calculations. To model the B&W tests several features were added to Version 16.2 of FLOWTRAN. These features include 1) an option to exclude the non-conductive rib surface from the heat transfer area calculations, 2) an option to use the heated perimeter to calculate the heat transfer coefficient (discussed in Section 4.1.2), 3) an option to apply a separate heat flux peaking factor at each heater surface, and 4) an

option to print output in engineering units. Option 3 was not used in this study. This modified version of FLOWTRAN is designated as Version 16.3. For identical input, Versions 16.2 and 16.3 give identical results.

Figure 4.1 illustrates the application of the FLOWTRAN computer code to limits calculations. A similar process was used for the test analyses, except that the upper plenum and tank bottom pressure boundary conditions and the power decay were derived from the test data instead of a reactor system model calculation. The major input parameters required by FLOWTRAN are the geometry, the channel roughness, and the local losses of the assembly to be modeled, and the boundary conditions imposed on the assembly. The boundary conditions are inlet temperature, power, tank bottom pressure and upper plenum pressure or inlet flow. FLOWTRAN calculates the pressures, flows, temperatures, and heat fluxes inside the assembly. The calculated flows, pressures and fluid temperatures are used to compute the Stanton number for each segment of the heated surfaces. This Stanton number is compared to the SRS limit criterion to provide a basis for adjusting the initial power in the calculations or to signal the time at which the test rig exceeded the limit criterion. For these analyses and in setting SRS reactor limits, an OSV based criterion (SRS working criterion) is used as a conservative predictor of OFI.

4.1 FLOWTRAN Model of Mockup Test Assembly

This section presents the FLOWTRAN model of the mockup test assembly.

4.1.1 Hydraulics of the Mockup Test Assembly

To model the mockup test assembly, the geometry, the channel roughness, and the local form losses of the as-built mockup test assembly must be known. The geometric data for the mockup assembly were provided by B&W based on mockup assembly dimensions. The Test 827_01 measurements were used to establish the mockup assembly channel roughness and the local form losses, which are discussed in Section 4.2.

4.1.2 Heat Transfer to the Flow channels of the Mockup Test Assembly

The following modified Colburn equation is used by FLOWTRAN to calculate the heat transfer coefficient in the turbulent flow regime.

$$Nu = h D_h / k_b = 0.023 Re^{0.8} Pr^{1/3} \quad (1)$$

where:

$$\begin{aligned} Re &= G D_h / \mu_f \\ Pr &= \mu_f C_{pb} / k_b \\ G &= \text{mass flux in lb}_m/(\text{s-ft}^2) \\ \mu_f &= \text{dynamic viscosity at the film temperature in lb}_m/(\text{s-ft}) \\ C_{pb} &= \text{bulk fluid specific heat capacity at constant pressure in Btu/(lb}_m\text{-F)} \\ k_b &= \text{bulk fluid thermal conductivity in Btu/(s-ft-F)} \end{aligned}$$

One of the differences between the mockup test assembly and the Mark 22 fuel assembly is that Channels 2 and 4, as shown in Figure 2.1, are heated on only one side in the mockup test assembly, while in a Mark 22 fuel assembly Channels 2 and 4 are heated on both sides. The modified Colburn heat transfer correlation uses an equivalent hydraulic diameter to calculate the Nusselt number. The equivalent hydraulic diameter is defined as four times the flow area divided by the wetted parameter. For an annular flow channel heated on only one side, the heat transfer coefficient between the heated surface and the fluid is more dependent on the heated surface and less influenced by the opposite unheated surface. Therefore, the heat transfer coefficient in Channels 2 and 4, which are heated on only one side, are evaluated by replacing the equivalent hydraulic diameter, D_h , in Equation 1 with the equivalent thermal diameter, D_t . The equivalent thermal diameter is defined as four times the flow area divided by the heated perimeter. This method of using the heated parameter instead of the wetted parameter in annular flow was suggested by Jordan [5] and later by Nusselt [6].

4.1.3 Heated Wall Effect

FLOWTRAN uses the following correlation to account for the friction factor change due to the fluid viscosity change along the heated surface. This effect is called heated wall effect.

$$f/f_b = 1 + [(\mu_w/\mu_b)^n - 1] P_h/P_w \quad (2)$$

where

f_b = friction factor evaluated at the bulk fluid temperature

P_h = heated perimeter

P_w = wetted perimeter

μ_w = dynamic viscosity evaluated at the wall temperature

μ_b = bulk fluid dynamic viscosity

n = an input that varies with diameter

The viscosity correction exponent, n , was set as 0.14 which was suggested by Sieder-Tate [7].

4.1.4. OFI Power Calculations for the Mockup Test Assembly

As discussed in Section 2.1, non-thermally conducting ceramic ribs were used in the mockup test assembly. These ribs thermally insulate the heater tube surface at locations where they contact or abut these surfaces. The insulation of the heater tube surface opposite the rib diverts heat flow around the insulated areas, thus increasing the surface heat flux on both sides of the rib. The increase in the local surface heat flux due to the ribs results in an increase in the Stanton number in the vicinity of the ribs and is expected to precipitate OSV at this location. This effect is modeled in limits analyses and was also included in the model for the mockup test assembly. The magnitude of this local heat flux increase in the Mark-22 assembly with aluminum ribs was calculated as 1.209 [8]. The same calculational procedures were used to calculate the

magnitude of the local heat flux increase in the mockup test assembly with insulating ribs. The calculated local heat flux increase in mockup test assembly was 1.52078. This value was derived from the peaking factor of 1.659 [8] with a correction to account for difference in the calculation of the nominal heat flux. The local heat flux increase of 1.52078 was used to calculate the OSV based power limit for the quasi steady-state power ramp and LOCA tests.

4.2 Hydraulic Characteristics of the Mockup Assembly

Tests 827_01 through 827_20 were zero power level, steady state hydraulic tests. The inlet flow, the inlet temperature, and the tank bottom pressure were fixed (see Table 4.1), and the pressure and flow distributions among the flow channels were measured. The data from Test 827_01 were used to determine the channel roughness and the local losses of the mockup assembly. The FLOWTRAN input parameters (channel roughness and local losses) were adjusted so that the FLOWTRAN calculation of the flow distributions among the flow channels, the pressure drops across the channels, and the static pressure at the pressure tap locations were in agreement with the measurements. The channel roughness and the local losses (Table 4.2) were kept the same in the analyses of the remainder of the test cases. Appendix A presents the FLOWTRAN input for Test 827_01.

4.2.1 Measured Pressure Drop

The measured pressure drop (psi) between two pressure taps is expressed as:

$$(\Delta P)_m = (\Delta P_s)_m + (\Delta P)_e \quad (3)$$

where $(\Delta P_s)_m$ is the measured static pressure difference between two pressure tap locations and $(\Delta P)_e$ is the elevation loss, which is calculated using the fluid density in the pressure taps and the distance between the tap locations. Table 4.3 presents the measurements of the static pressure difference and the measured pressure drops for Tests 827_01 through 827_20.

4.2.2 Measured Flow Distribution

The flow distribution is derived from the measurements with the Pitot tubes which are installed upstream of the channel exit. The relationship to determine the flow distributions was given by B&W and is expressed as:

$$R_i = A_i * \text{SQRT}[(\text{Pitot})_i] / \text{SUM} \quad i = 2, 3, 4 \quad (4)$$

where

R_i = fraction of flow in Channel i

A_i = flow area measured by B&W at the Pitot tube location

$(\text{Pitot})_i$ = Channel i Pitot measurement

$$\text{SUM} = A_2 * \text{SQRT}[(\text{Pitot})_2] + A_3 * \text{SQRT}[(\text{Pitot})_3] + A_4 * \text{SQRT}[(\text{Pitot})_4]$$

The values for the areas are:

$$A_2 = 0.3420 \text{ in}^2$$

$$A_3 = 0.5716 \text{ in}^2$$

$$A_4 = 0.2196 \text{ in}^2$$

Table 4.4 contains the Pitot measurements of Tests 827_01 through 827_20 and the derived flow distributions based on Equation 3

The FLOWTRAN calculations modeled pressure drops for Tests 827_02 through 827_20 using the channel roughness and local losses derived in Section 4.1. The static pressure at the pressure tap locations and the pressure drops across the channels are in good agreement with the measurements, as shown in Table 4.5 and Figures 4.2 through 4.11. The flow distributions calculated by FLOWTRAN also are in good agreement with the measurements, as shown in Table 4.6 and Figures 4.12 and 4.13.

4.3 Steady State Heated Tests

The 833 series tests provided the channel fluid temperature distribution data for FLOWTRAN benchmarking. The flow, temperature, and pressure distributions among the flow channels were measured at given boundary conditions, including inlet flow, inlet temperature, tank bottom pressure, and assembly power. Table 4.7 presents the test conditions.

The channel hydraulic resistances established in Section 4.2 and the measured boundary conditions (Table 4.7) were input to FLOWTRAN to model the steady state heated tests.

The initial comparisons of the temperature measurements and FLOWTRAN calculations, Figures 4.19 through 4.24, indicated a bias in the difference between the measured and calculated channel fluid temperatures. It was postulated that this bias was due to the geometric positioning of the thermocouples. As discussed in the next subsection, additional tests were run to support this postulate and to provide data to quantify the bias.

4.3.1 Fluid Temperature Measurements Qualification

FLOWTRAN calculates bulk fluid temperatures for each flow channel. Because there is a radial temperature gradient inside the flow channels and the thermocouples measure local fluid temperatures, it is expected that there will be a bias between the bulk fluid temperature and the measured fluid temperature. This section presents the method used to estimate the thermocouple measurement bias with respect to bulk fluid temperature.

I. Evidence of Thermocouple Measurement Biases with Respect to the Bulk Fluid Temperature

Two series of supplemental steady state tests were run in which only one heater tube generated power. The 833_05 series tests were run with power generated only in the outer heater tube. The 833_06 series tests were run with power generated only in the inner heater tube. As shown in Table 4.8 the power in the heated tube and the total flow rate were the parameters that were varied and there was an effort to have a symmetric set of tests (i.e. same heater power and flow for both an inner and an outer heater case)

Figure 4.15 shows measured channel fluid temperatures for test 833_06PW6. Figure 4.15 also shows the measured flow split among Channels 2, 3 and 4. Two anomalies are observed in Figure 4.15. 1) Channel 3 has twice the flow of Channel 4. However, the measured fluid temperature rise in Channel 3 inside the heated length is almost the same as in Channel 4. Two phenomena could explain these measured temperatures. One is that twice as much heat is deposited in Channel 3 because of a higher heat transfer, the other is that the measured temperatures are not bulk fluid temperatures. The calculated heat transfer coefficient to Channel 3 fluid is only about 22% larger than the heat transfer coefficient to Channel 4 fluid. Therefore, the bulk fluid temperature rise in Channel 3 should not equal the bulk fluid temperature rise in Channel 4, and 2) the measurement of the thermocouple (BFTC02) outside the Channel 3 heated length near the channel exit is lower than the measurement of the thermocouple (C3TC03) about 40 inches upstream from the end of the heated length. Physically, this should not occur because there is heat input to the Channel 3 fluid between the axial location of C3TC03 and the axial location of BFTC02. Therefore the fluid temperature at the channel exit should be higher than that inside the channel. These anomalies are evidence of a thermocouple measurement bias with respect to the bulk fluid temperature and are discussed in the following paragraphs.

The effect of the temperature gradients in Channels 3 and 4 (Figure 4.14) should be more noticeable for this test when the annular channel is heated on one side only. The fluid temperatures in Channels 3 and 4 near the inner heater tube surfaces should be higher than the fluid temperatures at locations farther away from the inner heater tube surfaces. If the thermocouples in Channel 3 were installed closer to the inner heater surface or were bent toward the inner heater surface by flow forces and the thermocouples in Channel 4 were installed or bent closer to the unheated surface it would explain why the measured fluid temperatures in Channel 3 were nearly the same as the measured temperatures in Channel 4 even though the measured Channel 3 flow was twice as large as the measured flow in Channel 4. (see Figure 4.15)

Because of mixing, the fluid temperature outside the heated length is expected to be more uniform and thus a measurement at any radial location in the annulus should be close to the bulk temperature. Therefore, the reading at thermocouple BFTC02 which is outside the

heated length (Figure 2.9) is taken to be a bulk temperature. The fact that this measured temperature is lower than a temperature measured farther up in Channel 3 (C3TC03) is additional evidence that the Channel 3 thermocouples in the heated section are measuring fluid temperatures close to the heated wall. Similar behavior was observed in the other tests in which only the inner heater generated power.

II. Determination of the Thermocouple Measurement Biases with Respect to the Bulk Fluid Temperature - One Heater Tube Heated

Test 833_05PW6 was a repeat of Test 833_06PW6 with the same flow, inlet temperature, tank bottom pressure, and power, except that in Test 833_05PW6, power was only applied to the outer heater tube. In Test 833_05PW6, the Channel 3 fluid temperature near the outer heater tube was higher than the fluid temperature near the inner heater tube surface, which had no power generation. With the placement of the Channel 3 thermocouple assumed to be close the inner heater, as was done for the analysis of the 833_06PW6 test, the Channel 3 thermocouple measurements for this test, 833_05PW6, should be lower than the bulk fluid temperature.

Because the tests with only one heater powered were run at similar powers, flows, inlet temperatures and tank bottom pressures, the Channel 3 bulk fluid temperatures of the 833_05 series tests should be about same as that of corresponding 833_06 series tests. This was confirmed by the measurements of thermocouple BFTC02 which measured the bulk fluid temperature (see Table 4.8, and Figures 4.15 and 4.16). Therefore, the Channel 3 thermocouple measurement data from the one heater powered tests were combined to estimate the bulk fluid temperature and the temperature bias. The bulk fluid temperature inside the Channel 3 heated length was estimated by

$$T_{bk}(i,j) = [T(i,833_05PWj) + T(i,833_06PWj)] / 2 \quad (5)$$

where T_{bk} is estimated bulk fluid temperature
 T is the fluid temperature measured by the thermocouple
 i is the thermocouple C3TC0i ($i=1,2,3$)
 $j = 1,2,3,...,6$ (for different tests)

The thermocouple measurement bias with respect to the bulk fluid temperature is estimated by

$$T_b(i,j) = T(i,833_06PWj) - T_{bk}(i,j) \quad (6)$$

This same bias correction was assumed to apply for Channels 2 and 4 when the power was applied to the heater adjacent to these channels.

III. Correction for the Thermocouple Measurements - One Heater Tube Heated

Figure 4.17 shows the FLOWTRAN calculations of the fluid temperatures of Test 833_06PW6 and the thermocouple measurements as well as the corrected thermocouple measurements. These thermocouple measurement corrections account for the channel fluid temperature gradients. No corrections were made to the measurements by the thermocouples outside the heated length (BFTC02 and BFTC03), because the fluid temperature gradients presumably were negligible there. No corrections were made to the thermocouple measurements in Channel 2. The radial temperature gradient in Channel 2 was negligible, since Channel 2 did not have a heated source. Figure 4.18 presents the FLOWTRAN calculations for Test 833_05PW6. Fluid temperatures calculated by FLOWTRAN agree with the corrected thermocouple measurements except for thermocouples BFTC02 and BFTC03, which are outside the heat section of the channel as indicated in Figures 4.17 and 4.18. The large differences between the FLOWTRAN calculations and the measurements of thermocouples BFTC02 and BFTC03 are observed in all the tests and are discussed in Section 4.3.2.

4.3.2 FLOWTRAN Calculations for Tests 833_01 and 833_02

The steady-state heated tests were designed to provide data to test the validity of the mockup assembly thermal-hydraulic behavior predicted by FLOWTRAN. The measured boundary conditions (Table 4.7) were input to FLOWTRAN to model the steady state heated tests. The FLOWTRAN calculations of the flows, the pressures and the fluid temperatures inside the channels were compared with the measurements to benchmark FLOWTRAN.

I. FLOWTRAN Calculations of Channel Fluid Temperature

Tests 833_01 and 833_02 were steady-state thermal-hydraulic tests in which both heater tubes were heated. As stated earlier, the tests were first analyzed assuming no bias with respect to the bulk or mixed mean temperature in the temperature measurements (Figure 4.19 through 4.24). Then they were analyzed after applying a bias to the measured temperature. The fluid temperature gradient in Channel 3 of the tests with two heater tubes powered should be less than that for the tests with one heater tube powered. Therefore, the biases of the Channel 3 fluid temperature measurements for test series 833_01 and 833_02 were assumed to be half of that derived in the previous section. Figures 4.25 through 4.30 present measured channel fluid temperature with corrections to account for the channel fluid temperature gradients. The channel fluid temperatures calculated by FLOWTRAN are in good agreement with the thermocouple measurements except for thermocouple BFTC03, which is located in Channel 4 below the heated section. The large discrepancy between the BFTC03 measurements and calculations is still under investigation.

The agreement between the calculations and measurements adjusted by a relatively simple model to account for temperature gradients validates the FLOWTRAN model for use in this initial benchmarking against LOCA simulation and power ramp tests.

II. FLOWTRAN Calculations of Pressure and Flow Distributions Inside the Test Assembly

Table 4.9 shows the measured pressure drops for Tests 833_01 through 833_02, and Table 4.10 presents the measured flow splits. Table 4.11 and Figures 4.31 through 4.33 present the pressure calculations. These calculations agree with the measurements. Table 4.12 and Figure 4.34 show that flow splits calculated by FLOWTRAN agree with the test data.

4.4 Transient Test

A LOCA transient test with low initial power level (2.11 MW) was conducted. There was no vapor generation during this test. The measured pressure, flow and fluid temperature distributions inside the mockup test assembly were used to verify the FLOWTRAN

calculations. The measured upper plenum and tank bottom pressures (Figure 4.35), the power decay (Figure 4.36), and the inlet temperature were input to the FLOWTRAN. Figure 4.37 shows that the FLOWTRAN calculations of the total assembly flow and the flow distribution are in good agreement with the test data. FLOWTRAN also predicts the pressure distributions inside the test assembly very well, as shown in Figures 4.38 through 4.40.

The channel fluid temperatures calculated by FLOWTRAN are compared with the measurements (without measurement biases correction) in Figures 4.41 through 4.43. The FLOWTRAN calculations of the channel fluid temperature are in good agreement with the corrected measurements (Figures 4.44 to 4.46). The correction terms derived from Section 4.4.1 were added to the measurements to account for the channel fluid temperature radial gradient. There was about a 0.2 seconds delay that has been attributed to the thermocouple response time as shown in Figures 4.44 thru 4.46. FLOWTRAN calculations of the channel fluid temperature would agree with the measurements more closely if a thermocouple response time delay were included.

Sections 4.2 to 4.4 have established the validity of the FLOWTRAN calculations of the flows, pressures and the fluid temperatures inside the channels during the steady-state and transient conditions. The calculated flows, pressures and fluid temperatures were used to compute the Stanton number for each segment of the heated surfaces. This Stanton number was compared to the SRS limit criterion to provide a basis for adjusting the initial power in the calculations or to signal the time at which the test rig exceeded the limit criterion. For these analyses and in setting SRS reactor limits, an OSV-based criterion (SRS working criterion) is used as a conservative predictor of OFI. The next two sections show that FLOWTRAN with the SRS working criterion ($St=0.00455$) conservatively predicts the OFI power.

4.5 Quasi-Steady State Power Ramp Tests

Seven quasi-steady state power ramp tests were run at various inlet temperatures and flow rates. In these tests, the initial inlet flow, inlet temperature and the tank bottom pressure were constant. The test section power was increased at a rate of 1,000 KW per minute. The test section power was shut off when OFI was detected. Figure

4.47 illustrates Test 836_01. The inlet flow was fixed at 158.478 gpm. The inlet temperature and the tank bottom pressure, which are not shown in the figure, were fixed at 78.8° F and 28.8 psia. Test section power was increased at a rate of 1,000 KW per minute after steady state was established at a power of 2050 KW. About 42 seconds after the start of the transient, the test assembly power was 2710 KW, and OSV, indicated by the rapid increase in void fraction, occurred in Channel 3. At 2790 KW, 46.4 seconds after the start of the transient, flow instability occurred, as indicated by a sudden reduction of the test assembly inlet flow. The test assembly power was shut off at 47.1 seconds.

4.5.1 FLOWTRAN Calculation of Quasi-Steady State Power Ramp Test

FLOWTRAN calculates the Stanton number at each axial location of each heated surface at each time step. As discussed in Section 4.1.3, the local heat flux increase in the vicinity of the ribs is postulated to trigger OSV. This local heat flux increase was included in the Stanton number calculation. The calculated local heat flux increase for the ceramic ribs of B&W test assembly is 1.5208. Figure 4.47 presents the largest calculated Stanton number for each heated surface at each time step. FLOWTRAN calculates that the SRS working criterion based limit with the ceramic rib effect (1.5208 peaking factor) was reached 35.12 seconds into the transient at a power of 2603 KW. The measured OSV, as determined by fiber optical void measurement, occurred at about 42.1 seconds with the power at 2723 KW. The measured OFI, as determined by rapid flow reduction, occurred at 46.4 seconds with the power at 2790 KW. Thus, FLOWTRAN with the SRS working criterion ($St=0.00455$) was shown to be a conservative predictor of OSV and OFI in the geometrically prototypic test assembly.

Similar comparisons for Tests 836_02 thru 836_07 are shown in Figures 4.48 thru 4.53 respectively. These comparisons also show that FLOWTRAN with the SRS working criterion ($St=0.00455$) is a conservative predictor of OFI. Table 4.13 summarizes the calculated results.

4.6 LOCA Tests

Test 867_04 is used to illustrate a LOCA test in which the test assembly went into flow instability. As shown in Figure 4.54, steady-state conditions were established at the initial power of 4338.0 KW, an inlet flow of 353.0 GPM and an inlet temperature of 127.0 F. After the LOCA pressure boundaries were imposed on the test assembly at time zero, there was a fast inlet flow decay due to the depressurization of the system, as shown in Figure 4.54. The channel flow measured by the Pitot tube at the channel exit dropped at the same time. The test assembly power was kept almost constant as the inlet flow was reduced. This caused a power/flow mismatch and vapor formation in Channel 3 about 0.5 seconds after the start of the transient. The Channel 3 flow velocity increased dramatically due the conversion of liquid to vapor, as shown by the Pitot tube measurements. The flow resistance of the test assembly increased rapidly after the vapor was generated inside flow Channels 3 and 4. This resulted in a further steep reduction of the inlet flow (after 0.5 seconds) and drove the system into the flow instability. The protection system detected the flow instability (flow loss) and shut off the power 0.7 seconds after the start of the transient. Finally, the system stabilized and the test was terminated.

Two methods were used to compare the FLOWTRAN calculations with the experimental results. Discussion of these methods follows:

Method 1

The measured time histories of the pressure boundaries (upper plenum and tank bottom), the inlet temperature and the relative power transient were input to FLOWTRAN. FLOWTRAN iterated on the initial power level to find the power level at which the OSV based limit ($St=0.00455$) was calculated to just be met during this simulated LOCA transient. This process follows the FI limits calculation procedure. As discussed in Section 4.1.3, a local peaking factor of 1.5208, which accounts for the mockup test assembly rib effect, was used to calculate the OSV power. The calculated OSV powers were lower than the measured powers for those LOCA test cases in which flow instability was detected, as shown in Table 4.14. For all of these tests the calculated test assembly initial power or operating power limit was at least 15.3% below the initial power level for which the test assembly went into flow instability. Figures

4.55 and 4.56 present the comparisons of the measured powers and the FLOWTRAN calculated OSV powers for tests which modeled a normal safety rod SCRAM and tests which modeled a proposed fast shutdown system. In the fast shutdown system, high pressure He³ gas is injected into empty rods in the core in about 200 mileseconds and the safety rods are also inserted. Figures 4.55 and 4.56 show that FLOWTRAN with SRS working criterion ($St=0.00455$) conservatively predicts the OFI powers.

Method 2

The measured time histories of the pressure boundaries (upper plenum and tank bottom), the inlet temperature, and the test power history were input to FLOWTRAN. FLOWTRAN calculated the Stanton number at each axial location of each heated surface at each time step. Figure 4.57 presents the largest calculated Stanton number for any heated surface at each time step for the Test 867_04. The calculation shows that at 0.13 seconds after the LOCA initiation, the thermal-hydraulic conditions inside Channel 3 met the SRS working criterion ($St=0.00455$). The measurement shows that OSV as indicated by the rapid increase in void fraction occurs about 0.42 seconds after the LOCA initiation.

Figures 4.58 to 4.69 present the rest of the LOCA test cases. Figures 4.58 to 4.67 show the tests with the normal safety rod SCRAM power decay. Figures 4.68 and 4.69 show the tests with the fast shutdown power decay. Figures 4.57 to 4.69 show that FLOWTRAN with $St=0.00455$ conservatively predicts both the OSV and OFI.

5. CONCLUSIONS

The test cases analyzed show that 1) FLOWTRAN accurately predicts the thermal-hydraulic behavior of the MK-22 mockup test assembly during the steady-state and transient test conditions, and 2) FLOWTRAN using the SRS working criterion ($St=0.00455$) conservatively predicts the MK-22 mockup test assembly OFI power for both LOCA transient tests and quasi-steady state power ramp tests.

REFERENCES

1. Aleman, S. E., Gregory, M. V., Hamm, L. L., Pevey, R. E., Reed, W. H., and Smith, F. G., DPSTM-140, "FLOWTRAN: An Algorithm for Describing the Thermal-Hydraulic Behavior of SRP Assemblies," September, 1989.
2. Saha, P., and Zuber, N., 'Point of Vapor Generation and Vapor Void Fraction in Subcooled Boiling,' International Heat Transfer Conference, 5th Proceeding, Tokyo, Japan, Vol. 4, Paper B4, September 3-7, 1974.
3. Goodwin, K. E., Sjostrom, L. C., Witmer, F. E., and Buckner, M. L., signatories, "Agreements and Commitments: Review of FI Limits Methodology Meeting, August 30-September 2, 1988, Savannah River Laboratory," September 2, 1988.
4. B&W Report NO. RDD:4427-13-01-01:01, "WSRC Flow Excursion Test Program with a Mark 22 Mockup Fuel Assembly in Downflow," Babcock & Wilcox, Alliance Research Center, February 1990.
5. Jordan, H., "On the Rate of Heat Transmission between Fluids and Metal Surfaces," Proc. Inst. Mech. Engrs. (London), 4, 1317, (1909).
6. Nusselt, W., Z. Ver. Deut. Ing., 57, 199, (1913).
7. Sieder, E. N., and Tate, G. E., "Heat Transfer and Pressure Drop of Liquids in Tubes," Ind. Eng. Chem., 28, 1429 (1936).
8. Laurinat, J. E., "Effect of Ribs on the OSV Criterion Used for FLOW Instability Limits, Rev. 1," NES-RFI-90004, FIU-89-68, Rev. 1, January 8, 1990.

TABLE 1.1 TEST MATRIX

1. Zero Power Steady state Tests - Pressure Profile Characterization:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
827-01 to	125 and	-none-	Pressure profiles were measured for 10 flows x 2 temperatures
827-20	80		

2. Zero Power Transient Tests - Pressure Transient Characterization:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
811-04, 11, 13, 17	100 ± 5	-none-	The last in a series of runs was considered an acceptable transient

3. Steady State Heated Tests:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
833-01	80 ± 5	1,2,3 MW	No void or flow instability (FI). Flowrate = 259 GPM
833-02	80 ± 5	1.3, 2.7 4.0 MW	No void or flow instability (FI). Flowrate = 345 GPM
833-05	82	0.5 to 2.0 MW	No void or flow instability (FI). Flowrate = 258 to 345 GPM, outer heater powered
833-06	82	0.5 to 2.0 MW	No void or flow instability (FI). Flowrate = 258 to 345 GPM, inner heater powered

4. Quasi-Steady State Power Ramps:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
836-01	79	2.80 MW for FI	158.0 gpm, T _{bot} = 28.5 psia
836-02	81	2.75 MW for FI	167.5 gpm, T _{bot} = 21.0 psia
836-03	124	3.06 MW for FI	229.4 gpm, T _{bot} = 21.0 psia
836-04	81	3.87 MW for FI	211.9 gpm, T _{bot} = 28.5 psia
836-05	80	3.80 MW for FI	220.5 gpm, T _{bot} = 21.0 psia
836-06	123	2.68 MW for FI	204.9 gpm, T _{bot} = 21.0 psia
836-07	125	4.00 MW for FI	285.8 gpm, T _{bot} = 21.0 psia

TABLE 1.1 Cont'd

5. LOCA Transient Tests

<u>RUN</u>	<u>INLET TEMP.</u> °F	<u>INITIAL POWER.</u> MW	<u>NOTES</u>
867-02	125	2.12 N	No void or flow instability (FI)
867-03	126	3.31 N	Momentary boiling osc. detected- No FI or Void
867-04	127	4.34 N	Flow instability occurred
867-05	124	4.05 N	Void seen, no flow instability
867-06	125	4.50 F	FAST POWER SCRAM - no flow instability, and <20% void
867-07	124	4.33 N	Flow instability occurred
867-08	82	5.32 N	Flow instability occurred
867-09	81	4.93 N	Small amt. of void only - no FI
867-10	125	4.28 N	Flow instability occurred - Thermal Recovery, then (delayed) Shutdown
867-11	123	4.28 N	Flow instability occurred. *Recovery*
867-12	125	4.58 N	Flow instability occurred, SEVERE Dryout
867-13	82	5.35 N	Flow instability occurred
867-14	125	4.53 F	Fast Scram w/ no FI (Close), void seen
867-15	124	4.10 N	Flow instability occurred
867-16	124	4.75 F	Fast Scram where flow instability occurred
867-17	123	4.60 F	Fast Scram w/ no FI (Close), void seen
867-18	81	6.04 F	Fast Scram w/ no FI (Close), void seen
867-19	81	5.21 N	Flow instability occurred
867-20	82	5.13 N	No Flow Instability. Void was seen.
867-21	81	6.23 F	Fast Scram w/ FI and Recovery
867-22	125.4	4.04 N	FI, shutdown due to high metal T
867-23	122.7	4.03 N	Flow Reduction, "recovery", Void Ch 3,4

N: Normal power decay

F: Fast power decay

TABLE 2.1 DIMENSIONS USED BY FLOWTRAN TO MODEL THE TEST SECTION

CORE HIGHT (IN)	161.595
HEATED LENGTH (IN)	143.000
UPPER UNHEATED SECTION (IN)	8.995
BOTTOM UNHEATED SECTION (IN)	9.600

CHANNEL DIMENSIONS:

CHANNEL	FLOW AREA (IN ²)	HYDRAULIC DIAMETER (IN)
1	1.840	0.295
2	2.302	0.4335
3	2.3328	0.5163
4	1.5484	0.4546
5	1.6742	1.460

TUBE	ID (IN)	OD (IN)
INNER TARGET	1.460	1.77435
INNER HEATER	2.31185	2.407
OUTER HEATER	2.997	3.0650
OUTER TARGET	3.5376	3.7
UHS	4.010	4.110

TABLE 2.2

LIST OF DATA ACQUISITION SYSTEM INSTRUMENTS

<u>Component</u>	<u>ID</u>	<u>Instrument</u>	<u>Description</u>
Coolant Supply	WSLS01	limit switch	Water Inlet Valve Full Closed
	WSLS02	limit switch	Water Inlet Valve Full Open
	WSLS03	limit switch	Gas Inlet Valve Full Closed
	WSLS04	limit switch	Gas Inlet Valve Full Open
	WSTC01	fluid thermocouple	Temperature of Water Supply at Turbine Meter
	WSTM01	turbine meter	Flow Rate of Water Supply
Inlet Plenum	IPAP01	pressure	Absolute Pressure in Inlet Plenum
	IPDP01	differential pressure	Low Range Differential Pressure for Venturi 1
	IPDP02	differential pressure	Low Range Differential Pressure for Venturi 2
	IPDP03	differential pressure	Low Range Differential Pressure for Venturi 3
	IPDP04	differential pressure	High Range Differential Pressure for Venturi 1
	IPDP05	differential pressure	High Range Differential Pressure for Venturi 2
	IPDP06	differential pressure	High Range Differential Pressure for Venturi 3
	IPTC01	fluid temperature	Fluid Temperature at Venturi 1
	IPTC02	fluid temperature	Fluid Temperature at Venturi 2
	IPTC03	fluid temperature	Fluid Temperature at Venturi 3
Top Fitting of Fuel Assembly	TFAP01	pressure	Pressure at Inlet to Heater Tubes
	TFDP01	differential pressure	Differential Pressure Upper Plenum to 69.5" below top of sleeve housing
	TFDP02	differential pressure	Differential Pressure Overall Fuel Assembly
	TFRT01	fluid temperature	Fluid Temperature in Top Fitting
Universal Sleeve Housing (USH)	USMT01	metal temperature	Outer USH Tube Temperature, 152.40 inches
	USMT02	metal temperature	Outer USH Tube Temperature, 96.65 inches
	USMT03	metal temperature	Outer USH Tube Temperature, 41.40 inches
Channel 2	C2AP01	pressure	Pressure at Subchannel 2A, 129.65 inches
	C2AP02	pressure	Pressure at Subchannel 2C, 129.65 inches
	C2AP03	pressure	Pressure at Subchannel 2A, 96.65 inches
	C2AP04	pressure	Pressure at Subchannel 2C, 96.65 inches
	C2AP05	pressure	Pressure at Subchannel 2A, 63.65 inches
	C2AP06	pressure	Pressure at Subchannel 2C, 63.65 inches
	C2AP07	pressure	Pressure at Subchannel 2A, at Upper Electrical Connector, 173.55 inches
	C2AP08	pressure	Pressure at Subchannel 2C, at Upper Electrical Connector, 173.55 inches
	C2AP09	pressure	Pressure at Subchannel 2A, at Lower Electrical Connector, 23.65 inches
	C2AP10	pressure	Pressure at Subchannel 2C, at Lower Electrical Connector, 23.65 inches

Table 2.2 (cont'd.)

Component	ID	Instrument	Description
Channel 2	C2DP01	differential pressure	Differential Pressure Subchannel 2A, 25.65-173.55 inches
	C2DP02	differential pressure	Differential Pressure for Pitot Tube, Subchannel 2A
	C2DP03	differential pressure	Differential Pressure Subchannel 2C, 25.65-173.55 inches
	C2TC01	fluid temperature	Differential Pressure at Subchannel 2C, 129.65 inches
	C2TC02	fluid temperature	Differential Pressure at Subchannel 2C, 96.65 inches
	C2TC03	fluid temperature	Differential Pressure at Subchannel 2C, 63.65 inches
	C2CP01	optical probe	Void Fraction Subchannel 2C
Outer Fuel Tube	OFMT01	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 152.40 inches
	OFMT02	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 152.4 inches
	OFMT03	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 129.65 inches
	OFMT04	metal temperature	Heater Temperature Subchannel 2B, 135.0 Degrees, 129.65 inches
	OFMT05	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 129.65 inches
	OFMT06	metal temperature	Heater Temperature Subchannel 2D, 315.0 Degrees, 129.65 inches
	OFMT07	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 96.65 inches
	OFMT08	metal temperature	Heater Temperature at Rib, Subchannel 2A, 90.0 Degrees, 96.65 inches
	OFMT09	metal temperature	Heater Temperature Subchannel 2B, 135.0 Degrees, 96.65 inches
	OFMT10	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 96.65 inches
	OFMT11	metal temperature	Heater Temperature at Rib, Subchannel 2C, 270.0 Degrees, 96.65 inches
	OFMT12	metal temperature	Heater Temperature Subchannel 2D, 315.0 Degrees, 63.65 inches
	OFMT13	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 63.65 inches
	OFMT14	metal temperature	Heater Temperature Subchannel 2B, 135.0 Degrees, 63.65 inches
	OFMT15	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 63.65 inches
	OFMT16	metal temperature	Heater Temperature Subchannel 2D, 315.0 Degrees, 63.65 inches
	OFMT17	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 41.40 inches
	OFMT18	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 41.40 inches
Channel 3	C3AP01	pressure	Pressure at Subchannel 3C, at Upper Electrical Connector, 173.55 inches
	C3AP02	pressure	Pressure at Subchannel 3A, at Lower Electrical Connector, 25.65 inches
	C3AP03	pressure	Pressure at Subchannel 3C, at Lower Electrical Connector, 25.65 inches
	C3DP01	differential pressure	Differential Pressure at Subchannel 3A, 25.65-173.55 inches
	C3DP02	differential pressure	Differential Pressure for Pitot Tube, Subchannel 3A
	C3TC01	fluid temperature	Fluid Temperature at Subchannel 3A, 129.65 inches
	C3TC02	fluid temperature	Fluid Temperature at Subchannel 3A, 96.65 inches
	C3TC03	fluid temperature	Fluid Temperature at Subchannel 3A, 63.65 inches
	C3CP01	optical probe	Void Fraction Subchannel 3C

Table 2.2 (cont'd.)

Component	ID	Instrument	Description	
Inner Fuel Tube	IFMT01	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 152.40 inches	
	IFMT02	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 152.40 inches	
	IFMT03	metal temperature	Heater Temperature Subchannel 3C, 0.0 Degrees, 129.65 inches	
	IFMT04	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 129.65 inches	
	IFMT05	metal temperature	Heater Temperature Subchannel 3B, 180.0 Degrees, 129.65 inches	
	IFMT06	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 129.65 inches	
	IFMT07	metal temperature	Heater Temperature Subchannel 3A, 0.0 Degrees, 96.65 inches	
	IFMT08	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 96.65 inches	
	IFMT09	metal temperature	Heater Temperature Subchannel 3B, 180.0 Degrees, 96.65 inches	
	IFMT10	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 96.65 inches	
	IFMT11	metal temperature	Heater Temperature Subchannel 3D, 0.0 Degrees, 63.65 inches	
	IFMT12	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 63.65 inches	
	IFMT13	metal temperature	Heater Temperature Subchannel 3B, 180.0 Degrees, 63.65 inches	
	IFMT14	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 63.65 inches	
	IFMT15	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 41.40 inches	
	IFMT16	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 41.40 inches	
Channel 4	C4AP01	pressure	Pressure at Subchannel 4B, at Upper Electrical Connector, 173.55 inches	
	C4AP02	pressure	Pressure at Subchannel 4B, at Lower Electrical Connector, 25.65 inches	
	C4AP03	pressure	Pressure at Subchannel 4D, at Lower Electrical Connector, 25.65 inches	
	C4DP01	differential pressure	Differential Pressure Subchannel 4B, 25.65-173.55 inches	
	C4DP02	differential pressure	Differential Pressure Subchannel 4B, for pitot Tube	
	C4TC01	fluid temperature	Fluid Temperature at Subchannel 4B, 129.65 inches	
	C4TC02	fluid temperature	Fluid Temperature at Subchannel 4B, 96.65 inches	
	C4TC03	fluid temperature	Fluid Temperature at Subchannel 4B, 63.35 inches	
	C4CP01	optical probe	Void Fraction Subchannel 4D	
Bottom Fitting Insert	BFAP01	pressure	Pressure at Channel Exits	
	BFAP02	pressure	Pressure at Channel Limit (venturi)	
	BFDP01	differential pressure	Differential Pressure Assembly Limit to Tank Bottom	
	BFDP02	differential pressure	Differential Pressure Monitor Pin to Tank Bottom	
	BFRT01	fluid temperature	Fluid Temperature Top of Monitor Pin	
	BFTC01	fluid temperature	Fluid Temperature Exit Channel 2	
	BFTC02	fluid temperature	Fluid Temperature Exit Channel 3	
	BFTC03	fluid temperature	Fluid Temperature Exit Channel 4	
	BFTC04	fluid temperature	Fluid Temperature Inside Shell Holes	
	BFTC05	fluid temperature	Temperature at Monitor Pin Subchannel A	
	BFTC06	fluid temperature	Temperature at Monitor Pin Subchannel B	
	BFTC07	fluid temperature	Temperature at Monitor Pin Subchannel C	
	BFTC08	fluid temperature	Temperature at Monitor Pin Subchannel D	

Table 2.2 (cont'd.)

<u>Component</u>	<u>ID</u>	<u>Instrument</u>	<u>Description</u>
Reactor Outlet Tank	RTAP01	pressure	Pressure at Tank Bottom
Water Collection	WCLS01	limit switch	Holding Tank Valve Full Closed
	WCLS02	limit switch	Holding Tank Valve Full Open
	WCLS03	limit switch	Quench Tank Valve Full Closed
	WCLS04	limit switch	Quench Tank Valve Full Open
Power Supply	PSAM01	ammeter	Current Through Outer Heater
	PSAM02	ammeter	Current Through Inner Heater
	PSVM01	voltage divider	Current Through Outer Heater
	PSVM02	voltage divider	Current Through Inner Heater
Miscellaneous Instrumentation	MSRF01	voltmeter	Voltage Across Resistance Temperature Detector
	MSTC01	reference temperature	Temperature of Data Acquisition System
	MSTC02	reference temperature	Ambient Temperature in Test Bay
	MSTC03	reference temperature	Thermocouple Reference Oven Temperature

TABLE 2.2 (Con't)

LIST OF DATA ACQUISITION SYSTEM INSTRUMENTS

The instrument ID is composed of three parts. The first two characters designate the component, as follows:

BF	Bottom Fitting Insert of the Fuel Assembly
C2	Coolant Channel 2 (between the Outer Target and the Outer Heater)
C3	Coolant Channel 3 (between the Outer Heater and the Inner Heater)
C4	Coolant Channel 4 (between the Inner Heater and the Inner Target)
IF	Inner Fuel (Heater) Tube
IP	Inlet plenum, which includes the inlet flowmeters
IT	Inner Target Tube
MS	Miscellaneous
OF	Outer Fuel (Heater) Tube
OT	Outer Target Tube
PL	Purge Line (inlet piping to outlet plenum)
PS	Electrical Power Supply
RT	Reactor Outlet Tank
TF	Top Fitting of the Fuel Assembly
US	Universal Sleeve Housing (USH)
WC	Water Collection, including Quench tank, Collection Tank, and Holding Tank
WS	Water Supply, including 4000 gpm loop and the inlet reservoir.

The next two characters designate the type of measurement or derived quantity as follows:

AM	Ammeter
AP	Absolute Pressure
CP	Conductivity Probe
DP	Differential Pressure
GP	Gauge Pressure
LS	Limit Switch
LV	Water Level
MT	Metal Thermocouple
OP	Optical Phase Detector
RT	Pitot Tube
RF	Reference
RT	Resistance Temperature Detector (RTD)
TC	Fluid Thermocouple
TM	Turbine Meter
VM	Voltmeter
VN	Venturi Flowmeter
VT	Voltage Tap
WM	Wattmeter

The final two characters (numbers) designate the individual measurement.

TABLE 4.1

ZERO POWERED STEADY STATE TEST CONDITIONS (TESTS 827_01 TO 827_20)

TEST ID	POWER KW	TANK BOTTOM PRESS. PSIA	INLET TEMP. F	FLOW RATE GPM
827_01	0	28.24	127.50	359.531
827_02	0	28.73	123.60	179.300
827_03	0	28.67	125.33	251.013
827_04	0	28.56	123.43	322.165
827_05	0	28.64	123.50	396.076
827_06	0	28.44	124.49	359.628
827_07	0	28.55	124.67	284.550
827_08	0	28.50	124.17	221.560
827_09	0	28.50	125.05	304.923
827_10	0	28.65	124.66	400.535
827_11	0	28.56	80.72	359.677
827_12	0	28.71	79.54	190.090
827_13	0	28.47	79.46	253.668
827_14	0	28.71	79.77	326.968
827_15	0	28.59	79.79	402.371
827_16	0	28.45	81.69	355.980
827_17	0	28.26	81.61	289.164
827_18	0	28.34	82.06	217.794
827_19	0	27.91	82.27	309.589
827_20	0	28.78	81.12	394.514

TABLE 4.2

Derived Channel Surface Roughness and Local Form Loss

<u>Channel</u>	<u>Roughness</u> in	<u>Local Form Loss</u>		
		<u>Channel inlet</u>	<u>Inside Channel</u>	<u>Channel Exit</u>
1	2.2534E-04	31100.000	0.000	0.100 0
2	6.0E-05	15.00 0	0.020	5.50000
3	6.0E-05	2.750	0.000	2.32000
4	6.0E-05	11.000	0.065	1.17000
5	6.0E-05	2000.000	0.000	78.22236

TABLE 4.3 MEASURED PRESSURE DROP

TEST ID	DENSITY LB/FT ³	ELEVATION LOSS	CHANNEL 1		CHANNEL 2		CHANNEL 3		CHANNEL 4	
			PRESSURE		PRESSURE		PRESSURE		PRESSURE	
			C2DP01* PSID	DROP ** PSID	C2DP03* PSID	DROP ** PSID	C3D-01* PSID	DROP ** PSID	C4DP01* PSID	DROP ** PSID
827_01	61.716	5.286	-3.680	8.97	-4.645	9.93	-10.78	15.46	-7.320	12.61
827_02	61.599	5.276	2.793	2.48	2.492	2.78	0.993	4.28	1.756	3.52
827_03	61.580	5.274	0.672	4.60	0.127	5.15	-2.724	8.00	-1.183	6.46
827_04	61.523	5.269	-1.988	7.26	-2.708	7.98	-7.249	12.52	-4.822	10.09
827_05	61.687	5.283	-5.378	10.66	-6.459	11.74	-13.147	18.33	-9.564	14.85
827_06	61.700	5.284	-3.649	8.93	-4.561	9.85	-10.101	15.29	-7.198	12.48
827_07	61.770	5.290	-0.531	5.82	-1.203	6.49	-4.772	10.06	-2.922	8.21
827_08	61.327	5.253	1.669	3.58	1.318	3.93	-1.198	6.45	0.163	5.09
827_09	61.731	5.287	-1.246	6.53	-1.910	7.20	-6.295	11.58	-3.915	9.20
827_10	61.623	5.278	-5.565	10.84	-6.699	11.98	-13.179	18.86	-9.879	15.16
827_11	62.385	5.343	-4.463	9.81	-5.365	10.71	-11.752	16.50	-8.084	13.43
827_12	62.233	5.330	2.162	3.17	1.846	3.48	0.27	5.20	0.958	4.37
827_13	62.410	5.345	0.079	5.27	-0.429	5.77	-3.144	8.79	-1.912	7.26
827_14	62.144	5.323	-2.936	8.26	-3.693	9.02	-8.103	13.93	-6.039	11.36
827_15	62.271	5.333	-6.723	12.06	-7.789	13.12	-14.133	20.27	-11.195	16.53
827_16	62.332	5.339	-4.252	9.59	-5.120	10.46	-10.106	16.24	-7.878	13.22
827_17	62.078	5.317	-1.236	6.55	-1.847	7.16	-5.784	11.10	-3.714	9.03
827_18	62.388	5.343	1.290	4.05	0.890	4.45	-1.449	6.79	-0.277	5.62
827_19	62.009	5.311	-2.090	7.40	-2.805	8.12	-7.248	12.56	-4.948	10.26
827_20	62.247	5.331	-6.330	11.66	-7.452	12.78	-14.331	19.66	-10.619	15.95

* MEASURED STATIC PRESSURE DIFFERENCE BETWEEN THE PRESSURE TAPS

** MEASURED PRESSURE DROP = ELEVATION LOSS - STATIC PRESSURE DIFFERENCE

ELEVATION LOSS = DENSITY * 148 / 12 / 144 (psi)

TABLE 4.4 MEASURED FLOW DISTRIBUTIONS

TEST ID	PITOT TUBE MEASUREMENT (PSID)				FLOW DISTRIBUTIONS		
	C2DP02	C3DP02	C4DP02		CHANNEL 2	CHANNEL 3	CHANNEL 4
	CHANNEL 2	CHANNEL 3	CHANNEL 4				
827_01	4.31	3.65	6.31		0.3017	0.4640	0.2344
827_02	1.08	0.97	1.58		0.2976	0.4713	0.2311
827_03	2.11	1.88	3.09		0.2981	0.4703	0.2316
827_04	3.42	3.02	5.00		0.2988	0.4693	0.2320
827_05	5.16	4.52	7.46		0.2997	0.4689	0.2314
827_06	4.25	3.74	6.18		0.2992	0.4691	0.2317
827_07	2.71	2.39	3.96		0.2989	0.4691	0.2320
827_08	1.63	1.45	2.37		0.2985	0.4705	0.2311
827_09	3.03	2.73	4.47		0.2971	0.4713	0.2317
827_10	5.30	4.64	7.63		0.2999	0.4690	0.2311
827_11	4.34	3.84	6.28		0.2990	0.4701	0.2309
827_12	1.24	1.11	1.80		0.2981	0.4713	0.2306
827_13	2.18	1.95	3.19		0.2978	0.4708	0.2313
827_14	3.59	3.19	5.25		0.2983	0.4700	0.2317
827_15	5.41	4.77	7.91		0.2989	0.4691	0.2321
827_16	4.26	3.78	6.25		0.2983	0.4697	0.2320
827_17	2.81	2.52	4.12		0.2976	0.4710	0.2314
827_18	1.63	1.47	2.40		0.2971	0.4715	0.2315
827_19	3.21	2.87	4.73		0.2976	0.4704	0.2320
827_20	5.23	4.62	7.62		0.2989	0.4695	0.2316

FLOW DISTRIBUTION (i) = A(i) * SQRT[PITOT(i)] / SUM
SUM = SUMMATION(A(i) * SQRT[PITOT(i)])
A(2) = 0.3420 ; A(3) = 0.5716 ; A(4) = 0.2196

TABLE 4.5 COMPARISONS BETWEEN THE CALCULATED AND MEASURED PRESSURES

TEST ID	CHANNEL 2 INLET PRESSURE (PSIA)*		CHANNEL 2 EXIT PRESSURE (PSIA)*		CHANNEL 2 PRESSURE DROP (PSID)*	
	MEAS	CALC	MEAS	CALC	MEAS	CALC
827_01	56.20	56.70	52.40	52.10	8.97	9.93
827_02	31.20	31.30	33.90	33.80	2.48	2.78
827_03	39.30	39.50	39.90	39.70	4.60	5.15
827_04	49.60	50.00	47.60	47.30	7.26	7.98
827_05	63.30	63.90	57.90	57.60	10.66	11.74
827_06	56.00	56.60	52.40	52.10	8.93	9.85
827_07	43.90	44.40	43.40	43.20	5.82	6.49
827_08	35.30	35.50	36.90	36.80	3.58	3.93
827_09	46.70	47.10	45.40	45.20	6.53	7.20
827_10	64.30	65.00	58.70	58.30	10.84	11.98
827_11	57.20	57.70	52.70	52.40	9.81	10.71
827_12	32.70	32.80	34.80	34.70	3.17	3.48
827_13	40.00	40.30	40.00	39.90	5.27	5.77
827_14	51.60	52.00	48.60	48.30	8.26	9.02
827_15	66.20	66.70	59.40	59.00	12.06	13.12
827_16	56.80	57.20	52.40	52.20	9.59	10.46
827_17	44.80	45.10	43.50	43.30	6.55	7.16
827_18	35.40	35.70	36.70	36.60	4.05	4.45
827_19	47.70	48.10	45.60	45.40	7.40	8.12
827_20	64.60	65.20	58.20	57.90	11.66	12.78

* There are two pressure taps at the same axial location but 180° apart.

TABLE 4.5 (Cont'd)

TEST ID	CHANNEL 3 INLET PRESSURE (PSIA)			CHANNEL 3 EXIT PRESSURE (PSIA)*			CHANNEL 3 PRESSURE DROP (PSID)		
	MEAS	CALC	%ERROR	MEAS	MEAS	CALC	MEAS	CALC	%ERROR
827_01	60.50	60.44	-0.1	50.30	50.40	50.33	15.46	15.40	-0.4
827_02	32.50	32.77	0.8	33.40	33.40	33.74	4.28	4.31	0.6
827_03	41.70	41.79	0.2	38.90	38.90	39.11	8.00	7.95	-0.6
827_04	53.30	53.55	0.5	45.90	45.90	46.19	12.52	12.63	0.9
827_05	68.50	68.87	0.5	55.50	55.50	55.62	18.33	18.53	1.1
827_06	60.40	60.75	0.6	50.40	50.40	50.56	15.29	15.47	1.2
827_07	46.90	46.91	0.0	42.10	42.10	42.15	10.06	10.04	-0.2
827_08	37.20	37.55	0.9	36.20	36.10	36.49	6.45	6.31	-2.1
827_09	50.10	50.33	0.5	44.40	44.40	44.22	11.58	11.40	-1.6
827_10	69.60	69.85	0.4	56.20	56.20	56.25	18.86	18.89	0.2
827_11	61.90	62.35	0.7	50.60	50.70	50.94	16.50	16.75	1.6
827_12	34.20	34.41	0.6	34.20	34.20	34.48	5.20	5.26	1.1
827_13	42.50	42.82	0.7	38.90	38.90	39.27	8.79	8.89	1.1
827_14	55.50	55.85	0.6	46.80	46.80	47.09	13.93	14.08	1.1
827_15	71.80	72.04	0.3	56.80	56.80	56.76	20.27	20.61	1.7
827_16	61.40	61.41	0.0	50.40	50.40	50.35	16.24	16.40	1.0
827_17	48.00	48.37	0.8	42.10	42.10	42.49	11.10	11.20	0.9
827_18	37.40	37.48	0.2	35.90	35.90	36.12	6.79	6.70	-1.3
827_19	51.30	51.66	0.7	44.00	44.00	44.31	12.56	12.66	0.8
827_20	70.10	69.82	-0.4	55.70	55.80	55.33	19.66	19.82	0.8

* There are two pressure taps at the same axial location but 180° apart.

TABLE 4.5 (Cont'd)

TEST ID	CHANNEL 4 INLET PRESSURE (PSIA)			CHANNEL 4 EXIT PRESSURE (PSIA)*			CHANNEL 4 PRESSURE DROP (PSID)		
	MEAS	CALC	% ERROR	MEAS	MEAS	CALC	MEAS	CALC	% ERROR
827_01	56.20	56.34	0.2	49.00	49.10	49.06	12.61	12.56	-0.3
827_02	31.30	31.71	1.3	33.10	33.10	33.42	3.52	3.56	1.3
827_03	39.40	39.75	0.9	38.30	38.30	38.49	6.46	6.53	1.1
827_04	49.70	50.22	1.1	44.90	45.10	45.17	10.09	10.33	2.3
827_05	63.30	63.89	0.9	53.80	54.10	54.07	14.85	15.10	1.7
827_06	56.20	56.63	0.8	49.00	49.30	49.29	12.48	12.63	1.2
827_07	44.20	44.30	0.2	41.30	41.40	41.36	8.21	8.23	0.2
827_08	35.50	35.95	1.3	35.70	35.80	36.01	5.09	5.20	2.1
827_09	46.90	47.34	0.9	43.10	43.20	43.30	9.20	9.33	1.4
827_10	64.30	64.77	0.7	54.50	54.80	54.66	15.16	15.39	1.5
827_11	57.50	58.09	1.0	49.40	49.70	49.65	13.43	13.79	2.7
827_12	32.90	33.18	0.8	33.90	33.90	34.12	4.37	4.38	0.3
827_13	40.30	40.66	0.9	38.40	38.50	38.63	7.26	7.37	1.5
827_14	51.90	52.31	0.8	45.90	46.00	46.03	11.36	11.61	2.2
827_15	66.50	66.75	0.4	55.30	55.50	55.15	16.53	16.93	2.4
827_16	57.10	57.25	0.3	49.20	49.40	49.09	13.22	13.50	2.1
827_17	45.10	45.59	1.1	41.40	41.50	41.66	9.03	9.25	2.4
827_18	35.70	35.88	0.5	35.50	35.60	35.65	5.62	5.57	-0.9
827_19	48.10	48.49	0.8	43.10	43.30	43.36	10.26	10.44	1.8
827_20	64.80	64.73	-0.1	54.30	54.50	53.78	15.95	16.28	2.1

* There are two pressure taps at the same axial location but 180° apart.

TABLE 4.5 (Cont'd)

TEST ID	UPPER PLENUM PRESSURE		
	MEAS PSIA	CALC PSIA	% ERROR
827_01	68.7	68.54	-0.2
827_02	32.7	32.92	0.7
827_03	44.5	44.46	-0.1
827_04	59.4	59.56	0.3
827_05	79.0	79.23	0.3
827_06	68.7	68.85	0.2
827_07	51.3	51.05	-0.5
827_08	38.9	39.09	0.5
827_09	55.4	55.45	0.1
827_10	80.4	80.51	0.1
827_11	70.2	70.48	0.4
827_12	34.8	34.88	0.2
827_13	45.5	45.59	0.2
827_14	62.0	62.13	0.2
827_15	82.8	82.86	0.1
827_16	69.5	69.32	-0.3
827_17	52.5	52.73	0.4
827_18	39.0	38.87	-0.3
827_19	56.8	57.03	0.4
827_20	80.7	80.12	-0.7

TABLE 4.6 COMPARISONS BETWEEN THE MEASURED AND CALCULATED FLOW DISTRIBUTIONS

TEST ID	CHANNEL 2 FLOW FRACTION			CHANNEL 3 FLOW FRACTION			CHANNEL 4 FLOW FRACTION		
	MEAS	CALC	%ERROR	MEAS	CALC	%ERROR	MEAS	CALC	%ERROR
827_01	0.3017	0.3049	1.1	0.4640	0.4602	-0.8	0.2344	0.2349	0.2
827_02	0.2976	0.3074	3.3	0.4713	0.4570	-3.0	0.2311	0.2356	2.0
827_03	0.2981	0.3061	2.7	0.4703	0.4586	-2.5	0.2316	0.2352	1.6
827_04	0.2988	0.3054	2.2	0.4693	0.4596	-2.1	0.2320	0.2350	1.3
827_05	0.2997	0.3048	1.7	0.4689	0.4604	-1.8	0.2314	0.2348	1.5
827_06	0.2992	0.3050	1.9	0.4691	0.4601	-1.9	0.2317	0.2349	1.4
827_07	0.2989	0.3057	2.3	0.4691	0.4591	-2.1	0.2320	0.2351	1.4
827_08	0.2985	0.3066	2.7	0.4705	0.4580	-2.6	0.2311	0.2354	1.9
827_09	0.2971	0.3055	2.8	0.4713	0.4594	-2.5	0.2317	0.2351	1.5
827_10	0.2999	0.3047	1.6	0.4690	0.4605	-1.8	0.2311	0.2348	1.6
827_11	0.2990	0.3065	2.5	0.4701	0.4582	-2.5	0.2309	0.2353	1.9
827_12	0.2981	0.3090	3.7	0.4713	0.4549	-3.5	0.2306	0.2361	2.4
827_13	0.2978	0.3078	3.4	0.4708	0.4564	-3.1	0.2313	0.2357	1.9
827_14	0.2983	0.3068	2.9	0.4700	0.4577	-2.6	0.2317	0.2355	1.6
827_15	0.2989	0.3061	2.4	0.4691	0.4587	-2.2	0.2321	0.2352	1.4
827_16	0.2983	0.3065	2.7	0.4697	0.4582	-2.4	0.2320	0.2353	1.4
827_17	0.2976	0.3072	3.2	0.4710	0.4572	-2.9	0.2314	0.2356	1.8
827_18	0.2971	0.3083	3.8	0.4715	0.4558	-3.3	0.2315	0.2359	1.9
827_19	0.2976	0.3069	3.1	0.4704	0.4576	-2.7	0.2320	0.2355	1.5
827_20	0.2989	0.3061	2.4	0.4695	0.4586	-2.3	0.2316	0.2352	1.6

TABLE 4.7

POWERED STEADY STATE TEST CONDITIONS

TEST ID	POWER KW	INNER HEATER	OUTER HEATER	TB PRESS. PSIA	INLET TEMP. F	FLOW RATE GPM
833_01PW1	0.9825	ON	ON	28.8	83.3	258.789
833_01PW2	1.7806	ON	ON	28.7	82.9	259.989
833_01PW3	2.9219	ON	ON	28.6	82.6	260.711
833_02PW1	1.3297	ON	ON	28.5	86.6	350.023
833_02PW2	2.5500	ON	ON	28.5	86.5	351.455
833_02PW3	3.8826	ON	ON	28.5	86.3	352.200

TABLE 4.8

ONE HEATER POWERED STEADY STATE TEST CONDITIONS
AND MEASURED CHANNEL 3 EXIT FLUID TEMPERATURE

TEST ID	POWER KW	INNER HEATER	OUTER HEATER	TB PRESS. PSIA	INLET TEMP. F	FLOW RATE GPM	BFTC02 F
833_05PW1	500.3	OFF	ON	28.0	81.0	258.992	99.3
833_05PW2	975.8	OFF	ON	27.9	82.0	256.787	116.4
933_05PW3	1488.6	OFF	ON	27.9	82.3	256.431	134.6
833_05PW4	638.0	OFF	ON	27.9	78.4	345.867	95.3
933_05PW5	1345.7	OFF	ON	27.6	80.2	343.925	115.8
833_05PW6	1984.7	OFF	ON	27.9	81.0	342.204	133.5
833_06PW1	507.9	ON	OFF	27.9	82.7	259.628	99.8
833_06PW2	1022.9	ON	OFF	27.9	82.4	259.360	116.9
833_06PW3	1507.7	ON	OFF	27.8	82.3	258.650	133.2
833_06PW4	667.7	ON	OFF	27.9	82.1	343.392	99.0
833_06PW5	1312.4	ON	OFF	27.8	82.1	343.786	115.5
833_06PW6	2012.4	ON	OFF	27.8	82.1	343.303	133.3

TABLE 4.9 MEASURED PRESSURE (Tests 833_01 to 833_02)

TEST ID	CHANNEL 2				CHANNEL 3				CHANNEL 4			
	C2DP01*	PSID	PRESSURE DROP **	PSID	C2DP03*	PSID	PRESSURE DROP **	PSID	C3DP01*	PSID	PRESSURE DROP **	PSID
833_01PW1	0.3	5.02	-0.2	5.52	-0.2	5.52	-3.2	8.51	-1.6	6.91		
833_01PW2	0.4	4.91	-0.1	5.41	-0.1	5.41	-3.1	8.39	-1.5	6.80		
833_01PW3	0.5	4.79	-0.1	5.33	-0.1	5.33	-2.9	8.16	-1.4	6.67		
833_02PW1	-3.3	8.61	-4.0	9.31	-4.0	9.31	-9.2	14.51	-6.5	11.81		
833_02PW2	-3.2	8.50	-3.9	9.20	-3.9	9.20	-9.1	14.39	-6.5	11.79		
833_02PW3	-3.0	8.28	-3.7	8.98	-3.7	8.98	-8.9	14.16	-6.5	11.77		

TEST ID	CHANNEL 2			CHANNEL 3			CHANNEL 4		
	DENSITY LB/FT3	ELEVATION LOSS (PSID)		DENSITY LB/FT3	ELEVATION LOSS (PSID)		DENSITY LB/FT3	ELEVATION LOSS (PSID)	
833_01PW1	62.063	5.316		61.991	5.309		62.021	5.312	
833_01PW2	61.942	5.305		61.792	5.292		61.851	5.297	
833_01PW3	61.733	5.287		61.448	5.263		61.554	5.272	
833_02PW1	62.023	5.312		61.950	5.306		61.977	5.308	
833_02PW2	61.877	5.300		61.712	5.286		61.776	5.291	
833_02PW3	61.691	5.284		61.408	5.259		61.504	5.268	

* MEASURED STATIC PRESSURE DIFFERENCE BETWEEN THE PRESSURE TAPS

** MEASURED PRESSURE DROP = ELEVATION LOSS - STATIC PRESSURE DIFFERENCE

ELEVATION LOSS = DENSITY * 148 / 12 / 144 (psi)

DENSITY = THE AVERAGE DENSITY OF THE CHANNEL INLET AND OUTLET

Test 4.10 MEASURED FLOW DISTRIBUTIONS (Tests 833_01 to 833_02)

TEST ID	PITOT TUBE MEASUREMENT (PSID)				FLOW DISTRIBUTIONS			
	C2DP02	C3DP02	C4DP02		CHANNEL 2	CHANNEL 3	CHANNEL 4	
	CHANNEL 2	CHANNEL 3	CHANNEL 4					
833_01PW1	2.2	2.0	3.2		0.2969	0.4732	0.2299	
833_01PW2	2.2	2.1	3.2		0.2935	0.4792	0.2273	
833_01PW3	2.2	2.1	3.2		0.2935	0.4792	0.2273	
833_02PW1	4.0	3.7	5.8		0.2958	0.4751	0.2287	
833_02PW2	4.1	3.7	5.9		0.2978	0.4721	0.2294	
833_02PW3	4.1	3.8	5.9		0.2959	0.476	0.2279	

FLOW DISTRIBUTION (i) = $A(i) \cdot \text{SQRT}[\text{PITOT}(i)] / \text{SUM}$
 $\text{SUM} = \text{SUMMATION}[A(i) \cdot \text{SQRT}[\text{PITOT}(i)]] \quad i=2, 3, 4$
 $A(2) = 0.3420$; $A(3) = 0.5716$; $A(4) = 0.2196$

TABLE 4.11

COMPARISONS BETWEEN THE CALCULATED AND MEASURED PRESSURES (TESTS 833_01 TO 833_02)

TEST ID	CHANNEL 2 INLET PRESSURE (PSIA)*		CHANNEL 2 EXIT PRESSURE (PSIA)*		CHANNEL 2 PRESSURE DROP (PSID)*	
	MEAS	CALC	MEAS	CALC	MEAS	CALC
833_01PW1	40.6	40.9	40.8	40.7	5.02	5.52
833_01PW2	40.5	40.8	40.8	40.8	4.91	5.41
833_01PW3	40.5	40.8	40.9	40.8	4.79	5.39
833_02PW1	54.7	55.3	51.4	51.3	8.61	9.31
833_02PW2	54.8	55.4	51.7	51.5	8.50	9.20
833_02PW3	54.8	55.5	51.9	51.8	8.28	8.98

* There are two pressure taps at the same axial location but 180° apart.

TABLE 4.11 (Cont'd)

TEST ID	CHANNEL 3 INLET PRESSURE (PSIA)			CHANNEL 3 EXIT PRESSURE (PSIA)*			CHANNEL 3 PRESSURE DROP (PSID)		
	MEAS	CALC	%ERROR	MEAS	CALC	%ERROR	MEAS	CALC	%ERROR
833_01PW1	43.0	43.42	1.0	39.7	39.7	40.1	8.51	8.53	0.2
833_01PW2	42.9	43.34	1.0	39.8	39.7	40.1	8.39	8.42	0.3
833_01PW3	42.9	43.24	0.8	39.9	39.9	40.8	8.16	8.22	0.7
833_02PW1	58.9	59.32	0.7	49.5	49.5	49.6	14.51	14.87	2.5
833_02PW2	58.9	59.32	0.7	49.8	49.8	50.7	14.39	14.53	1.0
833_02PW3	59.0	59.34	0.6	50.0	50	50.4	14.16	14.26	0.7

* There are two pressure taps at the same axial location but 180° apart.

TABLE 4.11 (Cont'd)

TEST ID	CHANNEL 4 INLET PRESSURE (PSIA)			CHANNEL 4 EXIT PRESSURE (PSIA)*			CHANNEL 4 PRESSURE DROP (PSID)		
	MEAS	CALC	% ERROR	MEAS	MEAS	CALC	MEAS	CALC	% ERROR
833_01PW1	40.6	41.18	1.7	39.0	39.1	39.52	6.91	7.07	2.3
833_01PW2	40.5	41.22	1.8	39.0	39.1	39.52	6.80	6.99	2.9
833_01PW3	40.4	41.14	1.8	39.1	39.2	39.59	6.67	6.83	2.3
833_02PW1	54.7	55.47	1.4	48.2	48.3	48.53	11.81	12.25	3.8
833_02PW2	54.7	55.52	1.5	48.3	48.4	48.82	11.79	11.98	1.6
833_02PW3	54.7	55.57	1.6	48.4	48.6	49.07	11.77	11.76	0.0

* There are two pressure taps at the same axial location but 180° apart.

TABLE 4.11 (Cont'd)

TEST ID	UPPER PLENUM PRESSURE		
	MEAS PSIA	CALC PSIA	% ERROR
833_01PW1	46.2	46.48	0.6
833_01PW2	46.2	46.48	0.6
833_01PW3	46.2	46.43	0.5
833_02PW1	66.7	67.00	0.4
833_02PW2	66.8	67.13	0.5
833_02PW3	67.0	67.23	0.3

TABLE 4.12

COMPARISONS BETWEEN THE MEASURED AND CALCULATED FLOW DISTRIBUTIONS (TESTS 833_01 TO 833_02)

TEST ID	CHANNEL 2 FLOW FRACTION			CHANNEL 3 FLOW FRACTION			CHANNEL 4 FLOW FRACTION		
	MEAS	CALC	%ERROR	MEAS	CALC	%ERROR	MEAS	CALC	%ERROR
833_01PW1	0.2969	0.3042	2.5	0.4732	0.4609	-2.6	0.2299	0.2349	2.1
833_01PW2	0.2935	0.3024	3.1	0.4792	0.4631	-3.4	0.2273	0.2345	3.2
833_01PW3	0.2935	0.3005	2.4	0.4792	0.4654	-2.9	0.2273	0.2341	3.0
833_02PW1	0.2958	0.3031	2.5	0.4755	0.4623	-2.8	0.2287	0.2346	2.6
833_02PW2	0.2978	0.3012	1.2	0.4728	0.4646	-1.7	0.2294	0.2342	2.1
833_02PW3	0.2959	0.2996	1.3	0.4761	0.4664	-2.0	0.2279	0.2339	2.6

A

TABLE 4.13

QUASI-STEADY STATE POWER RAMP RESULTS

TEST ID	OFI MEASUREMENTS		OSV CALCULATIONS	
	POWER (KW)	TIME (SEC)	POWER (KW)	TIME (SEC)
836_01	2790.0	46.4	2603.0	35.12
836_02	2823.0	42.0	2507.0	27.16
836_03	3078.0	58.4	2714.0	36.71
836_04	3942.0	9.8	3024.0	*
836_05	3783.0	35.2	3480.0	15.20
836_06	2588.0	35.1	2348.0	17.70
836_07	4170.0	48.7	3622.0	26.00

* The OSV power calculated by FLOWTRAN is less than the measured initial power

Table 4.14

FLOWTRAN CALCULATIONS OF THE OSV POWER FOR B&W LOCA TESTS

TEST ID	INLET TEMP (F)	POWER DECAY	FI STATUS	TEST POWER (MW)	FLOWTRAN CALCULATIONS OF OSV POWER RIB EFFECT USED IN CALCULATION	MARGIN*
867_03	125.0	NORMAL	NO	3.31	B&W ^b 3.385	
867_04	127.0	NORMAL	YES	4.34	3.344	22.9
867_05	125.0	NORMAL	NO	4.05	3.446	
867_06	125.0	FAST	NO	4.50	3.997	
867_07	125.0	NORMAL	YES	4.33	3.420	21.0
867_08	82.0	NORMAL	YES	5.32	4.505	15.3**
867_09	81.0	NORMAL	NO	4.93	4.450	
867_10	125.0	NORMAL	YES	4.28	3.389	20.8
867_11	123.0	NORMAL	YES	4.28	3.507	18.1
867_12	125.0	NORMAL	YES	4.58	3.384	26.1
867_13	82.0	NORMAL	YES	5.35	4.230	20.9
867_14	125.0	FAST	NO	4.53	3.643	
867_15	124.0	NORMAL	YES	4.10	3.204	21.9
867_16	124.0	FAST	YES	4.75	3.758	20.9**
867_17	123.0	FAST	NO	4.60	3.969	
867_18	81.0	FAST	NO	6.04	5.006	
867_19	81.0	NORMAL	YES	5.13	4.279	16.6
867_20	82.0	NORMAL	NO	5.13	4.450	
867_21	82.0	FAST	YES	6.23	4.973	20.2**
867_22	125.4	NORMAL	YES	4.04	3.210	
867_23	122.7	NORMAL	YES	4.03	3.375	16.3**

^aB&W = a peaking factor of 1.52078 was used to account for the rib effect for the B&W test rig.

*Margin = (Test Power-OSV Power)/Test Power *100%

**Test Conditions were close to the threshold of OFI.

FIGURE 2.1

CROSS-SECTION VIEW OF MOCK-UP
TEST ASSEMBLY

Model and Specified Power Profiles for the Inner and Outer Heater Tubes

FIGURE 2.2

	CERAMIC RIB			METAL CLIP			MATERIAL
	W	H	C	t	h	r	
INNER TARGET	0.1575	0.237	0.0313	0.016	0.125	0.0313	6061 ALUMINUM
INNER HEATER	0.1575	0.265	0.0313	0.015	0.125	0.0313	304 STAINLESS
OUTER HEATER	0.1650	0.206	0.0156	0.015	0.125	0.0156	304 STAINLESS

Heater and Target Tube Rib Details

FIGURE 2.3

TEST FACILITY SCHEMATIC

FIGURE 2.4

FIGURE 2.5

Top Fitting Instruments

Mark 22 Mode
Fuel Assembly

Ⓐ ABSOLUTE PRESSURE
⇒ THERMOCOUPLE JUNCTION

Ⓓ DIFFERENTIAL PRESSURE
▨ RESISTANCE TEMPERATURE DETECTOR

FIGURE 2.6

Channel 2 Pressure and Differential Pressure Taps

FIGURE 2.7

Channel 2 and Outer Heater Tube Instruments

Channel 3 Pressure and Differential Pressure Taps

FIGURE 2.9

Channel 3 and Inner Heater Tube Instruments

FIGURE 2.10

Channel 4 Pressure and Differential Pressure Taps

FIGURE 2.11

Channel 4 and Inner Target Tube Instruments

FIGURE 2.12

Bottom Fitting Instruments

FIGURE 4.2

UPPER PLENUM PRESSURE VS. ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

FIGURE 4.3

**CHANNEL 2 PRESSURE DISTRIBUTIONS VS ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA**

FIGURE 4.4

CHANNEL 3 PRESSURE DISTRIBUTIONS VS ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

Figure 4.1

FLOWTRAN APPLICATION

FIGURE 4.5

**CHANNEL 4 PRESSURE DISTRIBUTIONS VS ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA**

FIGURE 4.6

**CHANNEL PRESSURE DROP VS. ASSEMBLY INLET FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

FIGURE 4.7

UPPER PLENUM PRESSURE VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA

FIGURE 4.8

**CHANNEL 2 PRESSURE DISTRIBUTIONS VS ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

FIGURE 4.9

**CHANNEL 3 PRESSURE DISTRIBUTIONS VS ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

FIGURE 4.10

**CHANNEL 4 PRESSURE DISTRIBUTIONS VS ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

FIGURE 4.11

CHANNEL PRESSURE DROP VS. ASSEMBLY INLET FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

FIGURE 4.12

FLOW SPLIT VS. ASSEMBLY FLOW

TESTS 827_01 TO 827_10

INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

FIGURE 4.13

FLOW SPLIT VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA

FIGURE 4.14 SECTION VIEW OF MOCK-UP TEST ASSEMBLY
DEPICTING CHANNEL FLUID THERMOCOUPLE LOCATIONS

LEGEND

	INNER TARGET TUBE
	INNER HEATER TUBE
	OUTER HEATER TUBE
	OUTER TARGET TUBE
	OUTER HOUSING (USH)

NOTES:

1. DEPICTED THERMOCOUPLES HAVE A SHEATH OD OF .032".
2. CHANNEL #3 AND #4 THERMOCOUPLES ARE AXIALLY ROUTED THROUGH THE CENTER OF THE INNER-MOST TUBE.
3. SEE FIGURES 2.7, 2.9, AND 2.11 FOR AXIAL PLACEMENT OF THERMOCOUPLES.

FIGURE 4.15

MEASURED CHANNEL FLUID TEMPERATURE 833_06PW6, INNER HEATER POWERED

FIGURE 4.16

**MEASURED CHANNEL FLUID TEMPERATURE
833_05PW6 OUTER HEATER POWERED**

FIGURE 4.17

CHANNEL FLUID TEMPERATURE TEST 833_06PW6, INNER HEATER POWERED

FIGURE 4.18

FIGURE 4.19

CHANNEL FLUID TEMPERATURE TEST 833_01PW1

FIGURE 4.20

**CHANNEL FLUID TEMPERARURE
TEST 833_01PW2**

FIGURE 4.21

**CHANNEL FLUID TEMPERATURE
TEST 833_01PW3**

FIGURE 4.22

CHANNEL FLUID TEMPERATURE
TEST 833_02PW1

FIGURE 4.23

CHANNEL FLUID TEMPERATURE
TEST 833_02PW2

FIGURE 4.24

CHANNEL FLUID TEMPERATURE TEST 833_02PW3

FIGURE 4.25

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.26

CHANNEL FLUID TEMPERATURE TEST 833_01PW2 (WITH T/C CORRECTIONS)

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.27

**CHANNEL FLUID TEMPERATURE
TEST 833_01PW3 (WITH T/C CORRECTIONS)**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.28

**CHANNEL FLUID TEMPERATURE
TEST 833_02PW1 (WITH T/C CORRECTIONS)**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.29

**CHANNEL FLUID TEMPERATURE
TEST 833_02PW2 (WITH T/C CORRECTIONS)**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT THE T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.30

**CHANNEL FLUID TEMPERATURE
TEST 833_02PW3 (WITH T/C CORRECTIONS)**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.31

CHANNEL 2 PRESSURE DROP TESTS 833_01 AND 833_02

NOTE: Channel 2 has two DP cells at the same axial but different azimuthal locations.

FIGURE 4.32

CHANNEL 3 PRESSURE DROP
TESTS 833_01 AND 833_02

FIGURE 4.33

FIGURE 4.34

FLOW SPLIT
TESTS 833_01 AND 833_02

FIGURE 4.35

MEASURED PRESSURE BOUNDARY CONDITIONS TEST 827_02

FIGURE 4.36

**MEASURED POWER DECAY
TEST 867_02**

FIGURE 4.37

FIGURE 4.38

STATIC PRESSURE AT CHANNEL 2 INLET TEST 867_2

STATIC PRESSURE AT CHANNEL 2 OUTLET TEST 867_02

FIGURE 4.39

**STATIC PRESSURE AT CHANNEL 3 INLET
TEST 867_02**

**STATIC PRESSURE AT CHANNEL 3 OUTLET
TEST 867_02**

FIGURE 4.40

**STATIC PRESSURE AT CHANNEL 4 INLET
TEST 867_02**

**STATIC PRESSURE AT CHANNEL 4 OUTLET
TEST 867_02**

FIGURE 4.41

CHANNEL 2 FLUID TEMPERATURE AT T/C LOCATIONS TEST 867_02

FIGURE 4.42

CHANNEL 3 FLUID TEMPERATURE AT T/C LOCATIONS
TEST 867_02

FIGURE 4.43

CHANNEL 4 FLUID TEMPERATURE AT T/C LOCATIONS TEST 867_02

* MEASUREMENT ERROR (REF. SECTION 2.2.1)

FIGURE 4.44

CHANNEL 2 FLUID TEMPERATURE AT T/C LOCATIONS TEST 867_02

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

FIGURE 4.45

CHANNEL 3 FLUID TEMPERATURE AT T/C LOCATIONS TEST 867_02

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

+ OUTSIDE THE HEATED LENGTH

FIGURE 4.46

CHANNEL 4 FLUID TEMPERATURE AT T/C LOCATIONS TEST 867_02

* MEASUREMENT BIASES WERE ADDED TO TH T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

+ OUTSIDE THE HEATED LENGTH

FIGURE 4.47

FIGURE 4.48

FIGURE 4.49

TEST 836_03 MEASURED POWER AND FLOW VS. TIME

TEST 836_03 MEASURED VOID FRACTION

FLOWTRAN CALCULATION OF STANTON NUMBER

TEST 836_03
(RIB EFFECT $f = 1.52078$)

FIGURE 4.50

FIGURE 4.51

FIGURE 4.52

TEST 836_06 MEASURED POWER AND FLOW VS. TIME

TEST 836_06 MEASURED VOID FRACTION

FLOWTRAN CALCULATION OF STANTON NUMBER

TEST 836_06
(RIB EFFECT $f = 1.52078$)

FIGURE 4.53

TEST 836_07 MEASURED POWER AND FLOW VS. TIME

TEST 836_07 MEASURED VOID FRACTION

FLOWTRAN CALCULATION OF STANTON NUMBER
TEST 836_07
(RIB EFFECT $f = 1.52078$)

FIGURE 4.54

FIGURE 4.55

FLOWTRAN CALCULATIONS OF OSV POWER FOR B&W LOCA TESTS (NORMAL POWER DECAY)

FIGURE 4.56

FLOWTRAN CALCULATIONS OF OSV POWER FOR B&W LOCA TESTS (FAST POWER DECAY)

FIGURE 4.57

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_04
PEAKING FACTOR= 1.52078**

FIGURE 4.58

FLOWTRAN CALCULATION OF STANTON NUMBER

B&W TEST 867_07

PEAKING FACTOR= 1.52078

FIGURE 4.59

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_08
PEAKING FACTOR= 1.52078**

FIGURE 4.60

FLOWFIELD CALCULATION OF STANTON NUMBER
B&W TEST 867_10
PEAKING FACTOR= 1.52078

FIGURE 4.61

FLOWTRAN CALCULATION OF STANTON NUMBER

B&W TEST 867_11

PEAKING FACTOR= 1.52078

FIGURE 4.62

FLOWTRAN CALCULATION OF STANTON NUMBER
 B&W TEST 867_12
 PEAKING FACTOR= 1.52078

FIGURE 4.63

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_13
PEAKING FACTOR= 1.52078**

FIGURE 4.64

FLOWTRAN CALCULATION OF STANTON NUMBER

B&W TEST 867_15

PEAKING FACTOR= 1.52078

FIGURE 4.65

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_19
PEAKING FACTOR= 1.52078**

FIGURE 4.66

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_22
PEAKING FACTOR= 1.52078**

FIGURE 4.67

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_23
PEAKING FACTOR= 1.52078**

FIGURE 4.68

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_16
PEAKING FACTOR= 1.52078**

FIGURE 4.69

**FLOWTRAN CALCULATION OF STANTON NUMBER
B&W TEST 867_21
PEAKING FACTOR= 1.52078**

APPENDIX A FLOWTRAN INPUT FOR TEST 827_01

```

/B&W SIMULATES MARK22 827_01 SS POW0 T53 F359.53 P28.24/
/RUN TIME SEC, NZONE, TMIN, TIME ZONE DATA/
  0.0  1  0.0
  10.0  0.10
/IPRTF, IPRTS, IP RTP, IDMPS, IBALN, ICRIT, IPRTSS/
  1000  1000  1000
  1000  1000  1  1  0  0
/CRITERIA CHECKING FLAGS: ONB, TSAT, CHF/
  0  0  0  1  0
/TOLERANCES, ITERATIONS, AND INITIAL POWER/
  1.0D-4  20  0.0
  1.0D-5  100
  1.0D-5  100
/FLUID ITERATIONS, TOLERANCES, AND OPTIONS/
  1  1  1.0D-06
  1  1  1.0D-06
  1  1  1  2  1  2  1  0  0
  1
/POWER ARRAY PARAMETERS/
  3  3  1
  105  105  2  21  2  2  2  29  1  1  1
/MA MCYLN ICENT AND NCELLS/
  1  5  0
  7  42  13
/RADIAL CELLS AND SUBCHANNELS/
  5  5  5  5  3
  1  1  1  1  1
/SURFACE CHECK FLAGS/
  0  0  0  1  1  1  1  0  0  0  0
    1.0  1.460  0.52499  0.52499  0.5163  0.5163
    0.51508  0.51508  0.295  0.295  0.295
/CYLINDER #1/
  1.0  1
  1  0.265  0.07875
  40  2  2  2  2  2
  1.460
  1.52287
  1.58574
  1.64861
  1.71148

```

1.77435
 /CYLINDER #2/
 28.0 3
 1 .237 0.07875
 4 9 9 9 9 9
 36 6 6 6 6 6
 40 9 9 9 9 9
 2.31185
 2.33088
 2.34991
 2.36894
 2.38797
 2.407
 /CYLINDER #3/
 28.0 3
 1 0.206 0.0825
 4 9 9 9 9 9
 36 6 6 6 6 6
 40 9 9 9 9 9
 2.997
 3.0106
 3.0242
 3.0378
 3.0514
 3.065
 /CYLINDER #4/
 1.0 1
 0 0.0 0.0
 40 2 2 2 2 2
 3.5376
 3.57008
 3.60256
 3.63504
 3.66752
 3.700
 /CYLINDER #5/
 0.0 1
 -1 0.135 0.03
 40 2 2 2
 4.010
 4.040
 4.080
 4.110

/FLUID GEOMETRIC DATA SET/

161.595	143.0	8.995	22.0	1.0	
13.254	99.903				
0.10000	0.19900	0.32400	0.27700	0.10000	
0.10000	0.19900	0.32400	0.27700	0.10000	
1.674155	1.5484	2.3228	2.3020	1.840	
1.460	0.4546	0.5163	0.4335	0.295	
2000.0	11.0	2.750	15.0	31100.0	
0.0	0.0650	0.0	0.02	0.0	
78.22236	1.170	2.320	5.50	.1	
6.0000D-05	60.0D-06	60.0D-06	60.0D-06	2.2534D-04	
1	249.983	13.254	0.0	0.000	2.605
1	109.956	13.254	8.75	0.0	0.0
2	141.372	12.566	0.0	1.000	0.000
2	172.788	12.566	13.75	0.0	0.0
3	151.550	12.566	0.0	1.000	0.000
3	130.313	12.566	10.37	0.0	0.0
4	144.827	12.566	0.0	1.000	0.000
4	159.342	12.566	12.68	0.0	0.0
5	123.101	11.781	0.0	1.000	2.380
5	71.476	7.839	10.50	0.0	0.0
6	60.571	4.832	0.0	1.000	0.002
6	65.052	7.839	9.75	0.0	0.0
7	39.570	8.884	0.0	1.000	0.010
7	17.768	8.884	2.00	0.0	0.0
1	17.768	8.884	2.00	0.0	0.0
1	13.959	8.884	0.0	1.000	0.0
2	10.149	8.982	1.13	0.0	0.0
2	7.340	9.079	0.0	1.000	0.0
3	4.421	6.801	0.65	0.0	0.0
3	3.342	4.524	0.0	1.000	0.000
4	2.262	4.524	0.50	0.0	0.0
4	4.166	4.524	0.0	1.000	0.000
5	6.070	5.781	1.05	0.0	0.0
5	5.946	7.037	0.0	1.000	0.000
6	5.821	7.277	0.80	0.0	0.0
6	3.269	2.867	0.0	1.000	10.50
7	0.717	2.867	0.25	0.0	0.0
7	3.563	2.867	0.0	1.000	0.000
8	6.409	8.011	0.80	0.0	0.0
8	3.563	2.867	0.0	1.000	0.000
9	0.717	2.867	0.25	0.0	0.0
9	2.362	2.867	0.0	1.000	0.000

10	4.006	8.011	0.50	0.0	0.0
10	8.212	8.011	0.0	1.000	0.000
11	12.417	8.011	1.55	0.0	0.0
11	16.823	8.011	0.0	1.000	0.000
12	21.229	8.011	2.65	0.0	0.0
12	11.164	4.396	0.0	0.000	30.95
13	1.099	4.396	0.25	0.0	0.0
13	2.389	4.396	0.0	0.000	0.000
1.0	1.5	1.5	1.5	1.5	0.14

/POWER FRACTIONS /

5 1

0.0	0.0	0.0	0.0
0.5	0.0	0.0	0.0
0.5	0.0	0.0	0.0
0.0	0.0	0.0	0.0
0.0	0.0	0.0	0.0

/RADIAL SHAPES /

5 3 3

1	0	0	0	0
1.0	0.0	0.0		
1.0	0.0	0.0		
1.0	0.0	0.0		
2	0	0	0	0
1.0	0.0	0.0		
1.0	0.0	0.0		
1.0	0.0	0.0		
3	0	0	0	0
1.0	0.0	0.0		
1.0	0.0	0.0		
1.0	0.0	0.0		
4	0	0	0	0
1.0	0.0	0.0		
1.0	0.0	0.0		
1.0	0.0	0.0		
5	0	0	0	0
1.0	0.0	0.0		
1.0	0.0	0.0		
1.0	0.0	0.0		

/WET TANK SHAPE POWER FRACTIONS/

0

/DRY TANK SHAPE POWER FRACTIONS/

0

/AZIMUTHAL SHAPES /

1 1 5
 1 2 3 4 5
 1.
 1. 1. 1. 1. 1.
 /DRY DECAYH RESPNS/

30

0.0	1.0000
0.1	0.99953
0.2	0.99735
0.3	0.99334
0.4	0.98855
0.5	0.98373
0.6	0.97938
0.7	0.97560
0.8	0.97026
0.9	0.94883
1.0	0.88044
1.1	0.75652
1.2	0.60868
1.3	0.44966
1.4	0.31654
1.5	0.25682
1.6	0.23043
1.8	0.21816
2.0	0.20886
2.2	0.19412
2.4	0.18437
2.6	0.17543
2.8	0.16750
3.0	0.16041
3.5	0.14415
4.0	0.13013
4.5	0.11232
5.0	0.10737
6.0	0.08908
7.0	0.07598

/AXIAL POWR RESPNS WORST COS 9-88/

22 3

0.0

.00	.00
.047619	.32
.095238	.55
.142857	.78

.190478	.99
.238095	1.08
.285714	1.16
.333333	1.22
.380952	1.28
.428571	1.30
.476190	1.32
.523810	1.32
.571429	1.30
.619048	1.28
.666667	1.22
.714286	1.16
.761905	1.08
.809524	0.99
.857143	0.78
.904762	0.55
.952381	0.32

1.0	0.00
-----	------

0.00	0.32	0.55	0.78	0.99
1.08	1.16	1.22	1.28	1.30
1.32	1.32	1.30	1.28	1.22
1.16	1.08	0.99	0.78	0.55
0.32	0.00			
0.00	0.32	0.55	0.78	0.99
1.08	1.16	1.22	1.28	1.30
1.32	1.32	1.30	1.28	1.22
1.16	1.08	0.99	0.78	0.55
0.32	0.00			

/PLEN PRESS TRANS HARD (TRAC: RING 2-SECTOR 5 2/88) /

106

0.000000	359.53082
0.005001	44.6519
0.010032	42.9867
0.015113	40.0856
0.020410	45.5207
0.026149	42.5109
0.031801	44.0426
0.037453	43.9295
0.042478	45.2625
0.047522	44.3182
0.052556	41.1561
0.057593	38.4755
0.062597	36.8625

0.067598	37.1511
0.072641	38.8758
0.077782	39.1819
0.082783	41.9118
0.087980	40.5672
0.093102	39.6156
0.098112	35.4337
0.103230	36.9176
0.108470	38.7569
0.113750	40.2509
0.119150	39.9333
0.124290	43.8164
0.129700	39.7418
0.135580	38.3174
0.141450	38.3159
0.146480	38.8990
0.152220	39.2008
0.157360	39.6751
0.162960	42.7111
0.168610	39.5503
0.174100	41.0458
0.179420	39.1268
0.184640	39.6925
0.190010	41.2663
0.195800	38.8048
0.210790	40.0218
0.220820	38.1361
0.231090	39.8999
0.241650	39.7244
0.252010	38.9687
0.264180	39.3400
0.274520	39.7171
0.287090	39.7491
0.298260	39.5039
0.310770	39.3937
0.325030	39.3211
0.335240	39.2341
0.346280	39.0078
0.357910	38.9962
0.369020	38.9817
0.380070	39.0151
0.393520	38.9904
0.405460	38.9832

0.419300	39.2066
0.429710	39.2907
0.441190	39.2254
0.453850	39.1166
0.467810	39.1195
0.482670	39.0310
0.497580	38.8729
0.609530	38.7830
0.711700	38.5074
0.819950	38.2826
0.925510	38.5524
1.025500	38.2768
1.125900	38.1027
1.230000	37.8706
1.336200	37.6849
1.443700	37.5181
1.545700	37.4064
1.649800	37.2773
1.751200	37.1540
1.853700	37.0598
1.957300	36.9524
2.059300	36.8610
2.159300	36.7972
2.263200	36.7842
2.366200	36.8930
2.468200	37.1613
2.569100	37.5167
2.670200	37.8938
2.771100	38.0461
2.871000	38.1448
2.971600	38.1303
3.072300	38.1056
3.172700	38.0896
3.273600	38.0693
3.375100	38.0418
3.475200	38.0128
3.575400	37.9968
3.675800	37.9780
3.777200	37.9489
3.878200	37.9330
3.979000	37.9098
4.079500	37.8837
4.181400	37.8721

4.283000	37.8097
4.386000	37.8126
4.487400	37.8010
4.591300	37.7372
4.696000	37.7067
4.800300	37.6994
4.900400	37.6632

/TANK BOT PRESS TRANS HARD (TRAC: RING 2-SECTOR 5 2/88)/

106

0.000000	28.240
0.005001	28.4871
0.010032	26.5347
0.015113	23.3696
0.020410	20.5265
0.026149	20.1654
0.031801	22.6661
0.037453	24.9405
0.042478	25.8370
0.047522	25.3090
0.052556	24.0238
0.057593	22.3238
0.062597	21.4186
0.067598	21.5753
0.072641	22.5631
0.077782	23.5074
0.082783	23.8671
0.087980	23.6307
0.093102	23.6031
0.098112	23.5147
0.103230	23.8410
0.108470	24.0180
0.113750	24.9971
0.119150	26.0241
0.124290	26.3505
0.129700	25.7688
0.135580	24.8433
0.141450	24.2428
0.146480	24.2762
0.152220	24.8143
0.157360	25.3307
0.162960	25.6484
0.168610	25.4352
0.174100	25.1465

0.179420	24.6707
0.184640	24.4386
0.190010	24.3066
0.195800	24.4343
0.210790	23.8091
0.220820	24.4125
0.231090	24.9492
0.241650	24.8071
0.252010	24.2704
0.264180	24.4372
0.274520	24.7911
0.287090	24.6896
0.298260	24.3444
0.310770	24.1471
0.325030	24.0397
0.335240	23.8874
0.346280	23.7903
0.357910	23.7641
0.369020	23.7438
0.380070	23.7859
0.393520	23.5669
0.405460	23.4494
0.419300	23.5379
0.429710	23.4813
0.441190	23.2956
0.453850	23.1390
0.467810	23.1578
0.482670	23.0432
0.497580	22.8706
0.609530	22.2759
0.711700	21.7044
0.819950	21.2620
0.925510	21.0545
1.025500	21.1271
1.125900	20.8906
1.230000	20.5410
1.336200	20.2640
1.443700	20.0203
1.545700	19.8462
1.649800	19.6432
1.751200	19.4459
1.853700	19.2907
1.957300	19.1137

2.059300	18.9643
2.159300	18.8541
2.263200	18.8178
2.366200	18.9542
2.468200	19.3270
2.569100	19.8187
2.670200	20.3394
2.771100	20.5498
2.871000	20.6701
2.971600	20.6484
3.072300	20.6005
3.172700	20.5657
3.273600	20.5207
3.375100	20.4758
3.475200	20.4265
3.575400	20.3960
3.675800	20.3684
3.777200	20.3206
3.878200	20.3003
3.979000	20.2553
4.079500	20.2451
4.181400	20.2205
4.283000	20.1567
4.386000	20.1581
4.487400	20.1378
4.591300	20.0841
4.696000	20.0522
4.800300	20.0609
4.900400	20.0189

/ASS TINLET TRANSIENT/

3

0.00000	53.056
1.00000	35.00
2.00000	35.00

/TANK LEVEL TRANSIENT/

3

0.0	1.0000
1.0	1.0000
2.0	1.0000

/FLUID INITIAL GUESS DATA/

0.0056	0.1158	0.318	0.39	0.1752
359.53082	88.00000	53.056	0.0	
0.0019	0.1818	0.5015	0.3071	0.0077

END

**DATE
FILMED**

8 / 28 / 92