AIM

Association for Information and Image Management

1100 Wayne Avenue, Suite 1100
Silver Spring, Maryland 20910
301/587-8202

Centimeter

Inches

MANUFACTURED TO AIM STANDARDS
BY APPLIED IMAGE, INC.

1 of 2

WSRC-TR-92-422

NRTSC

NUCLEAR REACTOR TECHNOLOGY
AND SCIENTIFIC COMPUTATIONS

KEYWORDS: LOCA LIMITS
FLOWTRAN
FLOW INSTABILITY
K-14.1 LIMITS
RETENTION: PERMANENT

EFFECT OF FLOW LEAKAGE ON THE BENCHMARKING OF
FLOWTRAN WITH MARK-22 MOCKUP FLOW EXCURSION TEST DATA
FROM BABCOCK & WILCOX (U)

by

KUO-FU CHEN

ISSUED: OCTOBER, 1992

James E. Fennell
Authorized Derivative Classifier

10-7-92
Date

SRL SAVANNAH RIVER LABORATORY, AIKEN, SC 29808
Westinghouse Savannah River Company
Prepared for the U. S. Department of Energy under
Contract DE-AC09-84SR18035

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

PROJECT:
DOCUMENT: WSRC-TR-92-422
TITLE: EFFECT OF FLOW LEAKAGE ON THE BENCHMARKING OF
FLOWTRAN WITH MARK-22 MOCKUP FLOW EXCURSION TEST DATA
FROM BABCOCK & WILCOX (U)
QA TASK NUMBER: 89-004-0
REVISION NUMBER: 0

APPROVALS

James E. Laurinat 10-2-92
J. E. LAURINAT, TECHNICAL REVIEWER DATE

J. D. Menna 10-5-92
J. D. MENNA, RESEARCH SUPERVISOR DATE

A. J. Garrett 10/6/92
A. J. GARRETT, TECHNICAL MANAGER DATE

TABLE OF CONTENTS

SUMMARY.....	1
1. INTRODUCTION.....	2
2. TEST FACILITY.....	2
2.1 TEST ASSEMBLY - MARK 22 MOCKUP	3
2.2 GENERAL FACILITY ARRANGEMENT AND TEST OPERATION	4
2.3 INSTRUMENTATION.....	6
2.4 DATA ACQUISITION.....	6
3. TEST MATRIX	7
4. EVIDENCE OF FLOW LEAKAGE IN UPFLOW TESTS	8
5. FLOWTRAN MODEL TO ACCOUNT FOR LEAKAGE FLOW.....	8
6. HYDRAULIC CHARACTERISTICS OF THE MOCKUP ASSEMBLY.....	9
6.1 MEASURED PRESSURE DROP	9
6.2 MEASURED FLOW DISTRIBUTION	10
7. STEADY STATE HEATED TESTS	11
7.1 FLUID TEMPERATURE MEASUREMENTS QUALIFICATION.	11
7.2 FLOWTRAN CALCULATIONS FOR TESTS 833_01 AND 833_02.....	14
8. TRANSIENT TEST.....	15
9. QUASI-STEADY STATE POWER RAMP TESTS.....	15
9.1 FLOWTRAN CALCULATION OF QUASI-STEADY STATE POWER RAMP TESTS	16
10. LOCA TESTS	16
11. UNCERTAINTY ANALYSIS.....	17
11.1 EFFECT OF MEASUREMENT UNCERTAINTIES ON CALCULATED STANTON NUMBER FOR THE QUASI-STEADY STATE POWER RAMP TESTS	18
11.2 EFFECT OF MEASUREMENT UNCERTAINTIES ON CALCULATED STANTON NUMBER FOR THE LOCA TESTS.....	20
12. DISCUSSIONS OF LEAKAGE FLOW IN CHANNEL 1	21
13. CONCLUSIONS.....	21
REFERENCES.....	22

APPENDIX A FLOWTRAN-FI INPUT FOR UPFLOW TEST 039_04	153
153	
APPENDIX B FLOWTRAN-FI INPUT FOR DOWNFLOW TEST 827_19	158

LIST OF TABLES

2.1	Dimensions Used by FLOWTRAN to Model the Test Section.....	23
2.2	List of Data Acquisition System Instruments	24
3.1	Test Matrix	29
4.1	Comparisons of the Measured Channel Pressure Drops and the Velocities for the B&W Upflow and Downflow Tests at Comparable Test Conditions	31
4.2	Estimates of the Relative Flow Rate for the Upflow and the Downflow Tests Based on the Measured Frictional Pressure Drops and the Pitot Tube Data.....	32
5.1	Derived Upflow Test Assembly Channel Surface Roughness and Local Form Loss.....	33
5.2	Comparisons of the Measured Channel Pressure Drops and the Flow Splits with the FLOWTRAN-FI Calculations (B&W Upflow Test 039_04).....	34
5.3	Derived Upflow Test Assembly Channel Surface Roughness and Local Form Loss.....	35
5.4	Comparisons of the Measured Channel Pressure Drops and the Flow Splits with the FLOWTRAN-FI Calculations (B&W Downflow Test 827_19).....	36
6.1	Zero Powered Steady State Test Conditions (Tests 827_01 to 827_20)	37
6.2	Measured Pressure Drops for Tests 827_01 to 827_20.....	38
6.3	Measured Flow Distributions for Tests 827_01 to 827_20.....	39
6.4	Comparisons between the Calculated and Measured Pressures (Tests 827_01 to 827_20).....	40
6.5	Comparisons between the Calculated and Measured Flow Distributions (Tests 827_01 to 827_20).....	44
7.1	Steady State Heated Test Conditions (Tests 833_01 to 833_02)	45
7.2	One Heater Powered Steady state Test Conditions and Measured Channel 3 Exit Fluid Temperature	46
7.3	Measured Pressure Drops (Tests 833_01 to 833_02).....	47

7.4	Measured Flow Distributions (Tests 833_01 to 833_02)	48
7.5	Comparisons between the Calculated and the Measured Pressures (Tests 833_01 to 833_02).....	49
7.6	Comparisons between the Measured and Calculated Flow Distributions (Tests 833_01 to 833_02).....	53
9.1	Quasi-Steady State Power Ramp Results.....	54
10.1	FLOWTRAN Calculations of the OSV Power for B&W LOCA Tests	55
11.1	FLOWTRAN Calculations of the OSV Power for B&W LOCA Tests (WITH MEASUREMENT UNCERTAINTIES).....	56
12.1	Revised Downflow Test Assembly Channel Surface Roughness and Local Form Loss	57
12.2	Flows and Pressures Calculated by the Revised FLOWTRAN Model for Test 833_01PW1.....	58

LIST OF FIGURES

2.1	Cross-Section View of Mock-Up Test Assembly.....	59
2.2	Model Axial Power Profiles for the Inner and Outer Heater Tubes.....	60
2.3	Heater and Target Tube Rib Details.....	61
2.4	Test Facility Schematic.....	62
2.5	Top Fitting Instruments.....	63
2.6	Channel 2 Pressure and Differential Pressure Taps.....	64
2.7	Channel 2 and Outer Heater Tube Instruments.....	65
2.8	Channel 3 Pressure and Differential Pressure Taps.....	66
2.9	Channel 3 and Inner Heater Tube Instruments	67
2.10	Channel 4 Pressure and Differential Pressure Taps.....	68
2.11	Channel 4 and Inner Target Tube Instruments.....	69
2.12	Bottom Fitting Instruments	70
6.1	Upper Plenum Pressure vs. Assembly Flow, Tests 827_01 to 827_10.....	71
6.2	Channel 2 Pressure Distributions vs. Assembly Flow, Tests 827_01 to 827_10.....	72
6.3	Channel 3 Pressure Distributions vs. Assembly Flow, Tests 827_01 to 827_10.....	73
6.4	Channel 4 Pressure Distributions vs. Assembly Flow, Tests 827_01 to 827_10.....	74
6.5	Channel Pressure Drop vs. Assembly Flow, Tests 827_11 to 827_20.....	75
6.6	Upper Plenum Pressure vs. Assembly Flow, Tests 827_01 to 827_10.....	76
6.7	Channel 2 Pressure Distributions vs. Assembly Flow, Tests 827_11 to 827_20.....	77

6.8	Channel 3 Pressure Distributions vs. Assembly Flow, Tests 827_11 to 827_20.....	78
6.9	Channel 4 Pressure Distributions vs. Assembly Flow, Tests 827_11 to 827_20.....	79
6.10	Channel Pressure Drop vs. Assembly Flow, Tests 827_11 to 827_20.....	80
6.11	Flow Split vs. Assembly Flow, Tests 827_01 to 827_10.....	81
6.12	Flow Split vs. Assembly Flow, Tests 827_11 to 827_20.....	82
7.1	Section View of Mock-Up Test Assembly Depicting Channel Fluid Thermocouple Locations.....	83
7.2	Measured Channel Fluid Temperature 833_06PW6, Inner Heater Tube Powered	84
7.3	Measured Channel Fluid Temperature 833_05Pw6, Outer Heater Powered	85
7.4	Channel Fluid Temperature Test 833_06PW6, Inner Heater Tube Powered	86
7.5	Channel Fluid Temperature Test 833_05PW6, Outer Heater Tube Powered.....	87
7.6	Channel Fluid Temperature (Test 833_01PW1).....	88
7.7	Channel Fluid Temperature (Test 833_01PW2).....	89
7.8	Channel Fluid Temperature (Test 833_01PW3).....	90
7.9	Channel Fluid Temperature (Test 833_02PW1).....	91
7.10	Channel Fluid Temperature (Test 833_02PW2).....	92
7.11	Channel Fluid Temperature (Test 833_02PW3).....	93
7.12	Channel Fluid Temperature Test 833_01PW1 (with T/C Corrections).....	94
7.13	Channel Fluid Temperature Test 833_01PW2 (with T/C Corrections).....	95
7.14	Channel Fluid Temperature Test 833_01PW3 (with T/C Corrections).....	96

7.15	Channel Fluid Temperature Test 833_02PW1 (with T/C Corrections).....	97
7.16	Channel Fluid Temperature Test 833_02PW2 (with T/C Corrections).....	98
7.17	Channel Fluid Temperature Test 833_02PW3 (with T/C Corrections).....	99
7.18	Channel 2 Pressure Drop (Tests 833_01 to 833_02).....	100
7.19	Channel 3 Pressure Drop (Tests 833_01 to 833_02).....	101
7.20	Channel 4 Pressure Drop (Tests 833_01 to 833_02).....	102
7.21	Flow Split (Tests 833_01 to 833_02).....	103
8.1	Measured Pressure Boundary Conditions (Test 867_02).....	104
8.2	Measured Power Decay (Test 867_02).....	105
8.3	Test Section Inlet Flow (Test 867_02).....	106
8.4	Flow Distribution (Test 867_02)	107
8.5	Pressure at Channel 2 Inlet (Test 867_02)	108
8.6	Pressure at Channel 2 Outlet (Test 867_02).....	109
8.7	Pressure at Channel 3 Inlet (Test 867_02)	110
8.8	Pressure at Channel 3 Outlet (Test 867_02).....	111
8.9	Pressure at Channel 4 Inlet (Test 867_02)	112
8.10	Pressure at Channel 4 Outlet (Test 867_02).....	113
8.11	Channel 2 Fluid Temperature at T/C Locations (Test 867_02).....	114
8.12	Channel 3 Fluid Temperature at T/C Locations (Test 867_02).....	115
8.13	Channel 4 Fluid Temperature at T/C Locations (Test 867_02).....	116
9.1	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_01	117

9.2	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_02	118
9.3	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_03	119
9.4	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_04	120
9.5	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_05	121
9.6	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_06	122
9.7	Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_07	123
10.1	Time Variations of Flow, Void Fraction, Pitot Tube, and Power for LOCA Test 867_04	124
10.2	FLOWTRAN Calculation of Stanton Number (B&W Test 867_04).....	125
10.3	FLOWTRAN Calculation of Stanton Number (B&W Test 867_07).....	126
10.4	FLOWTRAN Calculation of Stanton Number (B&W Test 867_08).....	127
10.5	FLOWTRAN Calculation of Stanton Number (B&W Test 867_10).....	128
10.6	FLOWTRAN Calculation of Stanton Number (B&W Test 867_11).....	129
10.7	FLOWTRAN Calculation of Stanton Number (B&W Test 867_12).....	130
10.8	FLOWTRAN Calculation of Stanton Number (B&W Test 867_13).....	131
10.9	FLOWTRAN Calculation of Stanton Number (B&W Test 867_15).....	132
10.10	FLOWTRAN Calculation of Stanton Number (B&W Test 867_19).....	133

10.11	FLOWTRAN Calculation of Stanton Number (B&W Test 867_22).....	134
10.12	FLOWTRAN Calculation of Stanton Number (B&W Test 867_23).....	135
10.13	FLOWTRAN Calculation of Stanton Number (B&W Test 867_16).....	136
10.14	FLOWTRAN Calculation of Stanton Number (B&W Test 867_21).....	137
11.1	Absolute Pressure Measurement Uncertainty.....	138
11.2	Measurement Uncertainty for Resistance Temperature Detector.....	139
11.3	Uncertainty in Total Flow	140
11.4	Uncertainty in Total Power	141
11.5	Variation of Calculated Stanton Number Due to the Measurement Uncertainties (B&W Test 836_01)	142
11.6	Variation of Calculated Stanton Number Due to the Measurement Uncertainties (B&W Test 836_02)	143
11.7	Variation of Calculated Stanton Number Due to the Measurement Uncertainties (B&W Test 836_03)	144
11.8	Variation of Calculated Stanton Number Due to the Measurement Uncertainties (B&W Test 836_04)	145
11.9	Variation of Calculated Stanton Number Due to the Measurement Uncertainties (B&W Test 836_05)	146
11.10	Variation of Calculated Stanton Number Due to the Measurement Uncertainties B&W Test 836_06)	147
11.11	Variation of Calculated Stanton Number Due to the Measurement Uncertainties B&W Test 836_07)	148
11.12	FLOWTRAN Calculations of OSV Power for B&W LOCA Tests with measurement uncertainties (Normal Power Decay).....	149
11.13	FLOWTRAN Calculations of OSV Power for B&W LOCA Tests with measurement uncertainties (Fast Power Decay).....	150

12.1	Channel Fluid Temperatures Calculated by the Revised Model (Test 833_01pw1, with T/C Corrections).....	151
12.2	FLOWTRAN Calculations for Stanton Number Test 836_01 (Peaking Factor=1.0, Leakage Flow in Channel 1)	152

SUMMARY

This report presents a revised analysis of the Babcock & Wilcox (B&W) downflow flow excursion tests that accounts for leakage between flow channels in the test assembly. Leak rates were estimated by comparing results from the downflow tests with those for upflow tests conducted using an identical assembly with some minor modifications. The upflow test assembly did not contain leaks.

In this revised analyses show that FLOWTRAN with the SRS working criterion ($St=0.00455$) conservatively predicts onset of flow instability (OFI) without using a local peaking factor to model heat transfer variations near the ribs.

1. INTRODUCTION

Two test assemblies were made for the Mark-22 mockup flow excursion test program. One test assembly was used in the Babcock & Wilcox (B&W) downflow flow excursion tests [1]. The other test assembly was a backup. This backup test assembly was later used in the B&W upflow flow excursion tests for the New Production Reactor Program [2]. A comparison of results from B&W upflow and downflow flow excursion tests indicates that there may have been a significant flow leak from the active flow channel (Channels 2,3, and 3) to the purge channels (Channels 1 and 5) during the downflow tests. This observation was communicated to M. T. Childerson and J. E. Blake of the B&W Alliance Research Center. Their review supports this observation. They proposed means to inspect the test assembly and measure the size of the leakage gap [3]. This report presents a revised analysis to account for flow leakage.

A list of major differences between this revised analysis and the original analysis [4] follows.

1. In Reference 4, the active channel flow (in Channels 2, 3 and 4) was higher than the actual flow. Therefore, the heat transfer coefficient from the Colburn equation was modified, as indicated in Section 4.1.2 of Reference 4, to make the calculated fluid temperatures to agree with the measured temperatures.

2. The predicted OFI powers for some cases were higher than the measurements due to the excess flow in Channel 3. A peaking factor of 1.5208 was used in Reference 4 to lower the predicted OFI power.

3. The leakage flow is accounted for in this revised analysis. Therefore, there is no excess flow in Channel 3. Consequently, no heat transfer coefficient modification and peaking factor were used in this analysis.

The revised analysis shows that FLOWTRAN [5] with the SRS working criterion ($St=0.00455$) [6] conservatively predicts onset of flow instability (OFI) without using a local rib heat flux peaking factor. This implies that the peaking factor of 1.209 used in Mark 22 assembly power limits analysis to account for the rib effect for aluminum surfaces adds a measure of conservatism to these limits.

2. TEST FACILITY

A brief discussion of the test loop, test operation, test assembly, instrumentation, and data acquisition pertinent to the data analysis is presented in this section. The B&W test report [1] describes these tests in detail.

2.1 Test Assembly - Mark 22 Mockup

The test section fuel assembly mockup consisted of parts fabricated at B&W and actual Mark 22 parts supplied by SRS. These were assembled to create a mockup that replicated the Mark 22 fuel assembly in most respects. A Mark 22 fuel assembly consists of an entrance region which is fed from a pressurized plenum, an annular core region composed of two uranium-aluminum fuel tubes and two lithium-aluminum target tubes, and an exit region where flow passes into a tank filled with moderator that surrounds the assembly. The entrance and core region are contained within an annular sleeve housing. The alignment and spacing of the annular tubes is maintained by ribs that subdivide each annular coolant channel into four subchannels (see Figure 2.1). A discussion of notable features of the mockup fuel assembly and a comparison to an actual Mark 22 assembly follow.

I. The top of the mockup employed a universal sleeve housing (USH) entrance, a top fitting insert, and a spider from a Mark 22 assembly. The USH was inserted into an exact replica of a permanent sleeve housing that was welded into a replica of a small part of an SRS reactor plenum. This inlet plenum had six dummy permanent sleeves that surrounded the active mockup sleeve and intake slots.

II. The mockup had five flow channels in its heated section, as does a Mark 22 assembly. The uranium-aluminum fuel tubes in the Mark 22 were simulated using electrically heated Monel tubes. The assembly axial power profile was modeled by varying the wall thickness of the Monel heater tubes. This resulted in some differences between the channel dimensions of the mockup assembly and those of an actual Mark 22 assembly. In the mockup assembly the coolant channel geometry was scaled to preserve the flow distribution among the channels at prototypic heated section pressure drops. The simulated target tubes in the mockup assembly were not heated, since the power generation in the Mark 22 target tubes is very low.

III. The two mockup heater tubes were made of Monel 400 center sections with tapered walls and 70-30 and 90-10 copper-nickel end pieces. By such an arrangement, the transient thermal responses of the heater tubes simulated those of the MK-22 aluminum fuel tubes. The model heater tubes were designed to have a prototypic chopped-cosine axial power profile (Figure 2.2). There was a 52/48 power split between the inner and outer heater tubes, respectively.

IV. The heated section was terminated with thick copper blocks that (1) maintained the concentric annular geometry and (2) provided current paths (up to 25,000 amps/tube) to each of the two heater tubes. The tubes were serviced by a split block at the top. This split block allowed for different rates of axial thermal expansion of the heater tubes, and provided independent "hot" current sources for the tubes. The bottom end connector

mechanically fixed the bottom of the heaters and provided a common ground.

V. Aluminum ribs prototypic of Mark 22 fuel and target tubes could not be used in the mock-up assembly. Instead, thicker ceramic ribs were used to form the subchannels for the inner three coolant channels (Channels 2-4). They electrically isolated the model heater tubes and target tubes. The rib tip clearance found in a Mark 22 was preserved in the mockup test assembly to allow crossflow. Figure 2.3 illustrates the model ribs in detail.

VI. An extension was added to the model inner target tube to provide an instrumentation conduit to the top end of the mockup, where the thermocouple extension wires exited. This tube protected the thermocouple lead wires. The axial stem running down through the top fitting hardware did not change the geometry enough to significantly affect the hydraulics.

VII. Actual aluminum hardware that would be used in a Mark 22 was installed at the bottom of this mockup. This included the bottom of a prototypic universal sleeve housing and an actual "P,L" bottom endfitting insert with a double pressure plate. The monitor pin at the bottom was machined to prototypic dimensions and was instrumented similarly to those of SRS P or L production reactors.

VIII. Mockup instrumentation consisted of thermocouples, pressure sensing lines, Pitot tubes, and void fraction probes.

Figure 2.1 shows the cross-sectional view of the mockup test section. Reference 4 gives detailed dimensions of the heater tubes. Table 2.1 lists the dimensions used by FLOWTRAN to model the test section.

2.2 General Facility Arrangement and Test Operation

The flow excursion test facility, illustrated in Figure 2.4, is a once-through flow design as opposed to a closed loop design.

The testing was of short duration (15 minutes or less). During each transient test, initial steady state conditions were established, and then a flow excursion transient was initiated. The test loop had two modes of operation, one to establish steady-state initial conditions and the other to run flow excursion transients.

A 2200 gpm pump provided flow to the test apparatus from a 25,000-gallon reservoir. At steady-state conditions, a substantial portion of this output bypassed the test assembly and returned to the reservoir. This provided a relatively constant pressure source to the mockup facility. This bypass loop was used to heat the water to the desired temperature using pump power. Flow to the mockup, usually at a nominal rate of 400 gpm, was taken off the recycle loop as shown in Figure 2.4. The water temperature in the reservoir could be set over the range of 77 to 125 F. Flow from the loop was

directed to a water-solid 1200-gallon inlet reservoir above the test section. It was carried to the inlet plenum of the mockup through three symmetric connecting pipes. At steady state, flow exited the bottom of the test section to a holding basin outside of the test facility, which was vented to the atmosphere. The existence of automatic control valves in the discharge line and upstream of the test section inlet reservoir allowed a full range of assembly exit pressures and flow rates to be established at steady state.

When transient simulations were performed, they were initiated after the desired steady flow rate and power conditions were achieved with the mockup. Pressure transients were initiated by activating a quick-closing valve at the inlet to the reservoir tank. At the same time, a gas valve opened, connecting that tank to a gas pressure control system. The control system imposed the desired inlet pressure transient by controlling the pressure of nitrogen gas applied to the inlet reservoir. The gas was introduced at the top of the tank, forcing water down the three bottom-mounted lines going to the (always water solid) inlet plenum. Gas pressure applied to the inlet reservoir was controlled by a regulator that sensed pressure at the mockup inlet, making dynamic adjustments as the transient progressed.

At the transient initiation, the outlet pressure control system also was activated. Flow output from the mockup was diverted from the holding basin pipe to a pipe connected to the water-solid quench tank shown in Figure 2.4. The water in the quench tank was close to ambient temperature and was intended to quench any steam that might be generated in the transient. The quench tank was connected through a vertical rise of 8-inch pipe to the collection tank, where a nitrogen pressure control system monitored and changed the pressure at the mockup outlet as desired. To reduce outlet pressure during transients, gas was vented from the collection tank. Both the inlet reservoir and collection tank were sized to accommodate post-transient operation of over a minute.

Characterization tests were conducted to establish the time sequencing of the quick-acting and control valves relative to the start of the power transient to compensate for valve response time.

The power supply was capable of up to 10 MW DC using silicon rectifier controller (SRC) controllers. Powers of up to 6.3 MW were applied in this program. An analog drum controller was used to establish the time-dependent power level for transient runs. Both heater tubes were operated in parallel as opposed to independently for the LOCA test program.

A protection system was always online to shut off the test section power to protect the test assembly from overheating. The protecting system monitored inlet flow to the mockup and all of the heater metal thermocouples. Different flow and temperature trip levels were set depending on what type of test was being run. Typical trip levels were

metal temperature trip of 400 °F and flow reduction of 80% below the lowest flow measured during the previous unheated LOCA transient.

2.3 Instrumentation

The data acquisition system received input from 126 instruments. Table 2.2, reproduced from Reference 1, contains a complete list of instruments. Figures 2.5 through 2.12 show the instruments pertinent to the test data analysis. These instruments were used 1) to measure the thermal-hydraulic conditions (power, static pressures, pressure drops, fluid temperatures, heater metal temperatures, and channel exit flow velocities and void fractions) within the heated length, 2) to monitor conditions in the remainder of the test loop, including pressures and temperatures at the inlet and outlet plena, top and bottom fittings, and the coolant supply and collection systems, and 3) as reference instruments to monitor ambient conditions.

2.4 Data Acquisition

The data acquisition system had an Analogic ANDS5400 front end, which was supported by a DEC MicroVAX II computer. The computer stored data during testing and provided real-time data display to the operator. It also performed post-test data processing such as conversion of raw data to engineering units and generation of data plots for each test.

The computer software performed pre- and post-test calibration and consistency checks of the instrumentation. Zeroes of the instrument readings were checked and stored before each test. Instruments were checked for reasonable readings and were flagged for repair or removal from the data base between each run. The software also was able to perform simple consistency tests of data from the test bundle.

The data recording rate was usually 1.0 or 100.0 Hz, depending on the test being performed. The 1.0 Hz rate was used for data acquisition during steady state operations, when system changes were slow or absent. Use of this slow acquisition rate was necessary because the computer had a finite storage of 12,000 instrument readings per test. The data acquisition system was switched to the 100.0 Hz rate before a fast transient event was initiated during a test.

The post-test processing included conversion of all data to engineering units, range checking, and consistency checks. Data were eventually stored on magnetic tape. A large number of plots were generated as soon as possible after each test so that both B&W and SRS engineers could examine the run in detail.

3. TEST MATRIX

The tests can be divided into 5 major categories; 1) zero power steady state tests, 2) zero power flow transient tests, 3) steady state heated tests, 4) power ramp flow instability (FI) tests and 5) Loss of Coolant Accident (LOCA) transient tests. The test matrix is summarized in Table 3.1.

1) Zero Power Steady State Tests - Pressure Profile Characterization

These tests were designed to establish the hydraulic characteristics (channel roughness and local losses) of the as-built mockup assembly. In this series of tests, the inlet flow rate, the inlet flow temperature, and the tank bottom pressure were set. The static pressure at the upper plenum, at the channel inlets and outlets as well as the pressure drops across the channels were measured. The flow distribution among the channels was determined from Pitot tube measurements.

2) Zero Power Transient Tests - Pressure Transient Characterization

These tests were designed to enable the operators of the test to learn to coordinate control valves in both the upper plenum and tank bottom pressure control systems to produce a prototypic pressure transient for LOCA simulations.

3) Steady State Heated Tests

These tests were designed to provide data to qualify the validity of the mockup assembly thermal-hydraulic behavior predicted by FLOWTRAN. In this series of tests, the test section power, the inlet flow, the inlet temperature and the tank bottom pressure were fixed. The pressure, flow, and fluid temperature distributions were measured.

4) Quasi-Steady State Power Ramp Tests

These test data were valuable in benchmarking the ability of FLOWTRAN to conservatively predict the onset of flow instability. In this series of tests, steady state was established at a given inlet flow rate, inlet flow temperature, power level, and tank bottom pressure. The power level then was increased at a rate of 1,000 KW per minute, while the rest of the parameters were kept constant. The power was shut off when flow instability occurred.

5) LOCA Transient Tests

LOCA transient tests imposed a pressure transient and power decay transient on the mockup after a steady state heated condition was reached, so that a design basis DEGB LOCA was simulated. In this series of tests, the mockup was started out at a steady state flow condition with specified power level, pressure boundary conditions, and inlet temperature. After a

steady state was achieved, a test control sequence was initiated that first imposed an abrupt change in pressure boundary conditions. Then, a power decay transient was imposed to simulate the reactor shutdown system (i.e. the insertion of safety rods). These tests were terminated by one of two means. To protect the test assembly integrity, power was shut off if a high metal temperature or a low water flow, which usually resulted from flow instability, was detected. If the high metal temperature or low flow cut off criteria were not exceeded, the test was allowed to run for a preset time of 30 to 60 seconds after transient initiation.

Test parameters that were varied were 1) inlet temperature, 2) initial power level for a given relative power decay, and 3) relative power transients, which simulated the effects of both a safety rod scram and a proposed fast shutdown system for the LOCA. A single set of transient pressure boundary conditions was used to model all LOCA tests.

4. EVIDENCE OF FLOW LEAKAGE IN UPFLOW TESTS

Table 4.1 presents measurements of channel frictional pressure drops and Pitot tube pressure differentials at the channel exits for B&W upflow and downflow tests at comparable inlet flow rates and temperatures. The results in this table show that the measured channel pressure drops and Pitot tube pressure differentials for the upflow test are significantly higher than for the downflow test. Table 4.1 also lists the calculated surface roughness for Channel 3 based on the measured pressure drops. In the surface roughness calculations, it was assumed that there was no leakage between the channels. The calculated surface roughness for Channel 3 is 6.6×10^{-4} in for the upflow test and 3.3×10^{-5} in for the downflow test. The surface roughness for a smooth drawn tubing listed in Perry's Chemical Engineering Handbook [7] is 6.0×10^{-5} in. This implies that the Channel 3 surface roughness for the downflow test is too smooth to be real.

Table 4.2 gives estimates of the ratios of upflow and downflow flow rates for each channel. These ratios assume that the frictional pressure drops and Pitot tube pressure differentials are proportional to the square of the flow rates. The results in Table 4.2 show that the flow rates for Channels 2, 3, and 4 are significantly higher for the upflow test than for the downflow test.

Based on the results in Tables 4.1 and 4.2, it is estimated that the flow in Channels 2, 3 and 4 for the downflow tests should be about 85.3 per cent of the total flow instead of 96.3 per cent, as assumed previously.

5. FLOWTRAN MODEL TO ACCOUNT FOR LEAKAGE FLOW

Since the test assemblies for the upflow and downflow tests were fabricated using the same design, materials and manufacturing process, it could be assumed that these test assemblies had the same surface roughness.

Thus, the surface roughness obtained from the upflow test assembly could be used for downflow test analyses. A description of the procedure to obtain the upflow test assembly surface roughness follows.

Results from steady state, zero power upflow test (Test 039_04) were used to estimate local form losses and channel surface roughnesses. These parameters were varied to match FLOWTRAN calculations of flow distributions among the channels, pressure drops across the channels, and static pressures with measured values. Table 5.1 shows the upflow test assembly channel roughness and local form losses derived from upflow Test 039_04. Table 5.2 presents the comparison between the FLOWTRAN calculations and the measurements for upflow Test 039_04. Appendix A presents the FLOWTRAN input for upflow Test 039_04.

The channel roughnesses obtained from the upflow test assembly were applied to the downflow test assembly. At this stage, the upflow test assembly hydraulic parameters to be determined were the local losses. Data from downflow Test 827_19 were used to determine the local losses of the downflow test assembly. Local losses for each flow channel were adjusted so that the FLOWTRAN calculation of the flow distributions among the flow channels, the pressure drops across the channels, and the static pressure at the pressure tap locations were in agreement with the measurements. Table 5.3 lists the downflow test assembly channel local form losses derived from downflow Test 827_19. Table 5.4 compares the FLOWTRAN calculations with the measurements for downflow Test 827_19. Appendix B presents the FLOWTRAN input for these calculations. The channel roughness and the local losses in Table 5.3 were used to re-analyze all of the downflow flow excursion tests.

6. HYDRAULIC CHARACTERISTICS OF THE MOCKUP ASSEMBLY

Tests 827_01 through 827_20 were zero power level, steady state tests that were used to characterize hydraulics of the downflow test assembly. In these tests, the inlet flow, the inlet temperature, and the tank bottom pressure were fixed (see Table 6.1), and the pressure and flow distributions among the flow channels were measured.

6.1 Measured Pressure Drop

The measured pressure drop (psi) between two pressure taps is expressed as:

$$(\Delta P)_m = (\Delta P_s)_m + (\Delta P)_e \quad (1)$$

where $(\Delta P_s)_m$ is the measured static pressure difference between two pressure tap locations and $(\Delta P)_e$ is the elevation loss, which is calculated

using the fluid density in the pressure taps and the distance between the tap locations. Table 6.2 presents the measurements of the static pressure difference and the measured pressure drops for Tests 827_01 through 827_20.

6.2 Measured Flow Distribution

The flow distribution is derived from the measurements with the Pitot tubes which were installed upstream from the channel exit. The relationship to determine the flow distributions was given by B&W and is expressed as:

$$R_i = A_i * \text{SQRT}[(\text{Pitot})_i] / \text{SUM} \quad i = 2, 3, 4 \quad (2)$$

where

R_i = fraction of flow in Channel i

A_i = flow area measured by B&W at the Pitot tube location

$(\text{Pitot})_i$ = Channel i Pitot measurement

$$\text{SUM} = A_2 * \text{SQRT}[(\text{Pitot})_2] + A_3 * \text{SQRT}[(\text{Pitot})_3] + A_4 * \text{SQRT}[(\text{Pitot})_4]$$

The values for the areas are:

$$A_2 = 0.3420 \text{ in}^2$$

$$A_3 = 0.5716 \text{ in}^2$$

$$A_4 = 0.2196 \text{ in}^2$$

Table 6.2 reports the Pitot measurements for Tests 827_01 through 827_20 and the derived flow distributions based on Equation 2.

The FLOWTRAN calculations modeled pressure drops for Tests 827_02 through 827_20 using the channel roughness and local losses derived in Section 5. The static pressure at the pressure tap locations and the pressure drops across the channels are in good agreement with the measurements, as shown in Table 6.4 and Figures 6.1 through 6.10. The flow distributions calculated by FLOWTRAN also are in good agreement with the measurements, as shown in Table 6.5 and Figures 6.11 and 6.12.

7. STEADY STATE HEATED TESTS

The 833 series tests provided the channel fluid temperature distribution data for FLOWTRAN benchmarking. The flow, temperature, and pressure distributions among the flow channels were measured at given boundary conditions, including inlet flow, inlet temperature, tank bottom pressure, and assembly power. Table 7.1 presents the test conditions.

The channel hydraulic resistances established in Section 5 and the measured boundary conditions (Table 7.1) were input to FLOWTRAN to model the steady state heated tests.

The initial comparisons of the temperature measurements and FLOWTRAN calculations indicated a bias in the difference between the measured and calculated channel fluid temperatures. It was postulated that this bias was due to the geometric positioning of the thermocouples. As discussed in the next subsection, additional tests were run to support this postulate and to provide data to quantify the bias.

7.1 Fluid Temperature Measurements Qualification

FLOWTRAN calculates bulk fluid temperatures for each flow channel. Because there is a radial temperature gradient inside the flow channels and the thermocouples measure local fluid temperatures, it is presumed that there was a bias between the bulk fluid temperature and the measured fluid temperature. This section presents the method used to estimate the thermocouple measurement bias with respect to bulk fluid temperature.

I. Evidence of Thermocouple Measurement Biases with Respect to the Bulk Fluid Temperature

Two series of supplemental steady state tests were run in which only one heater tube generated power. The 833_05 series tests were run with power generated only in the outer heater tube. The 833_06 series tests were run with power generated only in the inner heater tube. As shown in Table 7.2 the power in the heated tube and the total flow rate were the parameters that were varied and there was an effort to have a symmetric set of tests (i.e. the same heater power and flow for both an inner and an outer heater test)

Figure 7.2 shows measured channel fluid temperatures for Test 833_06PW6. Figure 7.2 also shows the measured flow split among Channels 2, 3 and 4. Two anomalies are observed in Figure 7.2. The first is that Channel 3 has twice the flow of Channel 4 despite the fact that the measured fluid temperature rise in Channel 3 inside the heated length is almost the same as in Channel 4. There are two explanations for this apparent discrepancy. One is that twice as much heat is deposited in Channel 3 because of a higher heat transfer rate; the other is that the measured temperatures do not represent bulk fluid temperatures.

The calculated heat transfer coefficient to Channel 3 fluid is only about 22% larger than the heat transfer coefficient to Channel 4 fluid. Therefore, the bulk fluid temperature rise in Channel 3 should not equal the bulk fluid temperature rise in Channel 4. It can be concluded that the measured fluid temperatures do not equal the bulk fluid temperatures. The second anomaly is that the measured temperature outside the Channel 3 heated length near the channel exit (from the thermocouple BFTC02) is lower than the measured temperature about 40 inches upstream from the end of the heated length (from the thermocouple C3TC03). Physically, this should not occur because there is heat input to the Channel 3 fluid between the axial locations of C3TC03 and BFTC02. Therefore, the fluid temperature at the channel exit should be higher than that inside the channel. These anomalies are evidence of a thermocouple measurement bias with respect to the bulk fluid temperature, which is discussed in the following paragraphs.

The effect of the temperature gradients in Channels 3 and 4 (see Figure 7.1) should be more noticeable for this test when the annular channel is heated on one side only. The fluid temperatures in Channels 3 and 4 near the inner heater tube surfaces should be higher than the fluid temperatures farther away from the inner heater tube surfaces. If the thermocouples in Channel 3 were installed closer to the inner heater surface or were bent toward the inner heater surface by flow forces and the thermocouples in Channel 4 were installed or bent closer to the unheated surface, the measured fluid temperatures in Channel 3 would be nearly the same as the measured temperatures in Channel 4, even though the measured Channel 3 flow was twice as large as the measured flow in Channel 4. (see Figure 7.2)

Because of mixing, the fluid temperature outside the heated length is expected to be more uniform than in the heated channels. Thus, a measurement at any radial location in the annulus should be close to the bulk temperature. The reading from thermocouple BFTC02, which is outside the heated length (Figure 2.9), is taken to be a bulk temperature. The fact that this measured temperature is lower than a temperature measured farther up in Channel 3 (C3TC03) offers additional evidence that the Channel 3 thermocouples in the heated section are measuring fluid temperatures close to the heated wall. Similar behavior was observed in the other tests in which only the inner heater generated power.

II. Determination of the Thermocouple Measurement Biases with Respect to the Bulk Fluid Temperature - One Heater Tube Heated

Test 833_05PW6 was a repeat of Test 833_06PW6 with the same flow, inlet temperature, tank bottom pressure, and power, except that in Test 833_05PW6, power was applied only to the outer heater tube. In Test 833_05PW6, the Channel 3 fluid temperature near the outer heater tube was higher than the fluid temperature near surface at the inner heater

tube, which had no power generation. With the placement of the Channel 3 thermocouple assumed to be close the inner heater, as was done for the analysis of the 833_06PW6 test, the Channel 3 thermocouple measurements for this test, 833_05PW6, should have been lower than the bulk fluid temperature.

Because the tests with only one heater powered were run at similar powers, flows, inlet temperatures and tank bottom pressures, the Channel 3 bulk fluid temperatures for the 833_05 series tests should have been about same as that for corresponding 833_06 series tests. This was confirmed by the bulk fluid temperature measurements from thermocouple BFTC02 (see Table 7.2 and Figures 7.2 and 7.3). The Channel 3 thermocouple measurement data from the one heater powered tests were combined to estimate the bulk fluid temperature and the temperature bias. The bulk fluid temperature inside the Channel 3 heated length was estimated by

$$T_{bk}(i,j) = [T(i,833\_05PWj) + T(i,833\_06PWj)] / 2 \quad (3)$$

where T_{bk} is estimated bulk fluid temperature
 T is the fluid temperature measured by the thermocouple
 i is the thermocouple C3TC0i at axial location i (1 thru 3)
 j is test number (1 thru 6)

The thermocouple measurement bias with respect to the bulk fluid temperature is estimated by

$$T_b(i,j) = T(i,833\_06PWj) - T_{bk}(i,j) \quad (4)$$

This same bias correction was assumed to apply for Channels 2 and 4 when the power was applied to the heater adjacent to these channels.

III. Correction for the Thermocouple Measurements - One Heater Tube Heated

Figure 7.4 comparess the FLOWTRAN calculations of the fluid temperatures for Test 833_06PW6 with the thermocouple measurements as well as with corrected thermocouple measurements. The thermocouple measurement corrections account for the channel fluid temperature gradients. No corrections were made to the measurements from the thermocouples outside the heated length (BFTC02 and BFTC03), because the fluid temperature gradients presumably were negligible there. No corrections were made to the thermocouple measurements in Channel 2. The radial temperature gradient in Channel 2 was negligible, since this channel did not have a heat source. Figure 7.5 presents the FLOWTRAN calculations for Test 833_05PW6. As indicated in Figures 7.4 and 7.5, fluid temperatures calculated by FLOWTRAN agree with the corrected thermocouple measurements.

7.2 FLOWTRAN Calculations for Tests 833_01 and 833_02

The steady-state heated tests were designed to provide data to benchmark of the mockup assembly thermal-hydraulic behavior predicted by FLOWTRAN. The measured boundary conditions listed in Table 7.1 were input to FLOWTRAN to model the steady state heated tests. The FLOWTRAN calculations of the flows, the pressures and the fluid temperatures inside the channels were compared with the measurements to benchmark FLOWTRAN.

I. FLOWTRAN Calculations of Channel Fluid Temperature

Tests 833_01 and 833_02 were steady-state thermal-hydraulic tests in which both heater tubes were heated. As stated earlier, the tests were first analyzed assuming no bias with respect to the bulk or mixed mean temperature in the temperature measurements (see Figure 7.6 through 7.11). Later, they were analyzed after applying a bias to the measured temperature. It was assumed that the fluid temperature gradient in Channel 3 for the tests with two heater tubes powered should be much less than that for the tests with one heater tube powered. Therefore, the biases of the Channel 3 fluid temperature measurements for test series 833_01 and 833_02 were set equal to zero. Figures 7.12 through 7.17 present measured channel fluid temperature with corrections to account for the channel fluid temperature gradients. The channel fluid temperatures calculated by FLOWTRAN are in good agreement with the thermocouple measurements except for the Channel 2 fluid temperature measurements. The cause of this discrepancy in Channel 2 fluid temperature measurement is presented next.

In this study, the FLOWTRAN model for the excess leakage flow was assigned to Channel 5. However, the leakage found by B&W during a recent inspection was located in Channel 1 [8]. This means that FLOWTRAN would underestimate flow in Channel 1. FLOWTRAN also would underestimate the heat transfer from Channel 2 to Channel 1, since heat transfer is proportional to Channel 1 flow. It follows that FLOWTRAN would overestimate Channel 2 fluid temperature. The assumption of excess leakage flow to Channel 5 instead of Channel 1 does not affect the FLOWTRAN prediction of Channel 3 thermal-hydraulic behavior, as shown in Figures 7.12 through 7.17. OSV power predictions also were not affected because Channel 3 is the limiting channel.

The agreement between the calculations and measurements adjusted by a relatively simple model to account for temperature gradients validates the FLOWTRAN model for use in benchmarking LOCA simulation and power ramp tests.

II. FLOWTRAN Calculations of Pressure and Flow Distributions Inside the Test Assembly

Table 7.3 shows the measured pressure drops for Tests 833_01 through 833_02, and Table 7.4 presents the measured flow splits. Table 7.5 and Figures 7.18 through 7.20 present the pressure calculations. These calculations agree with the measurements. Table 7.6 and Figure 7.21 show that flow splits calculated by FLOWTRAN agree with the test data.

8. TRANSIENT TEST

A LOCA transient test with low initial power level (2.11 MW) was conducted. There was no vapor generation during this test. The measured pressure, flow and fluid temperature distributions inside the mockup test assembly were used to verify the FLOWTRAN calculations. The measured upper plenum and tank bottom pressures (Figure 8.1), the power decay (Figure 8.2), and the inlet temperature were input to FLOWTRAN. Figures 8.3 and 8.4 show that the FLOWTRAN calculations of the total assembly flow and the flow distribution are in good agreement with the test data. FLOWTRAN also predicts the pressure distributions inside the test assembly very well, as shown in Figures 8.5 through 8.10.

The FLOWTRAN calculations of the channel fluid temperature are in good agreement with the measurements (Figures 8.11 to 8.13) except for Channel 2, as described in Section 7.2.

Sections 6 through 8 have established the validity of the FLOWTRAN calculations of the flows, pressures and the fluid temperatures inside the channels during steady-state and transient conditions. The calculated flows, pressures and fluid temperatures were used to compute the Stanton number for each segment of the heated surfaces. This Stanton number was compared to the SRS limit criterion to provide a basis for adjusting the initial power in the calculations or to signal the time at which the test rig exceeded the limit criterion. For these analyses and in setting SRS reactor limits, an OSV based criterion (SRS working criterion) is used as a conservative predictor of OFI. The next two sections show that FLOWTRAN with the SRS working criterion ($St=0.00455$) conservatively predicts the OFI power.

9. QUASI-STEADY STATE POWER RAMP TESTS

Seven quasi-steady state power ramp tests were run at various inlet temperatures and flow rates. In these tests, the initial inlet flow, inlet temperature and the tank bottom pressure were constant. The test section power was increased at a rate of 1,000 KW per minute. The test section power was shut off when OFI was detected. Figure 9.1 illustrates results from Test 836_01. The inlet flow was fixed at 158.478 gpm. The inlet

temperature and the tank bottom pressure, which are not shown in the figure, were fixed at 78.8° F and 28.8 psia. Test section power was increased at a rate of 1,000 KW per minute after steady state was established at a power of 2050 KW. About 42 seconds after the start of the transient, the test assembly power was 2710 KW, and OSV, indicated by a rapid increase in void fraction, occurred in Channel 3. At 2790 KW, 46.4 seconds after the start of the transient, flow instability occurred, as indicated by a sudden reduction of the test assembly inlet flow. The test assembly power was shut off at 47.1 seconds.

9.1 FLOWTRAN Calculation of Quasi-Steady State Power Ramp Test

FLOWTRAN calculates the Stanton number at each axial location of each heated surface at each time step. Figure 9.1 presents the largest calculated Stanton number for each heated surface at each time step. FLOWTRAN calculates that the SRS working criterion was reached 38.37 seconds into the transient at a power of 2653 KW. The measured OSV, as determined by fiber optical void measurement, occurred at 42.1 seconds with the power at 2723 KW. The measured OFI, as determined by rapid flow reduction, occurred at 46.4 seconds with the power at 2790 KW. Thus, FLOWTRAN with the SRS working criterion ($St=0.00455$) was shown to be a conservative predictor of OSV and OFI in the geometrically prototypic test assembly.

Similar comparisons for Tests 836_02 thru 836_07 are shown in Figures 9.2 thru 9.7 respectively. These comparisons also show that FLOWTRAN with the SRS working criterion ($St=0.00455$) is a conservative predictor of OFI. Table 9.1 summarizes the calculated results.

10. LOCA TESTS

Test 867_04 is an example of LOCA test in which the test assembly went into flow instability. As shown in Figure 10.1, steady-state conditions were established at the initial power of 4338.0 KW, an inlet flow of 353.0 gpm and an inlet temperature of 127.0 F. After the LOCA pressure boundaries were imposed on the test assembly at time zero, there was a rapid inlet flow decay due to the depressurization of the system. The channel flow measured by the Pitot tube at the channel exit dropped at the same time. The test assembly power was kept almost constant as the inlet flow was reduced. This caused a power/flow mismatch and vapor formation in Channel 3 about 0.5 seconds after the start of the transient. The Channel 3 flow velocity increased dramatically due to vaporization, as shown by the Pitot tube measurements. The flow resistance of the test assembly increased rapidly after vapor was generated inside flow Channels 3 and 4. This resulted in a further steep reduction of the inlet flow (after 0.5 seconds) and drove the system into the flow instability. The protection system detected a reduction of flow and shut off the power 0.7 seconds after the start of the transient. Finally, the system stabilized and the test was terminated.

Two methods were used to compare the FLOWTRAN calculations with the experimental results. Discussion of these methods follows.

Method 1

The measured time histories of the pressure boundaries (upper plenum and tank bottom), the inlet temperature and the relative power transient were input to FLOWTRAN. FLOWTRAN iterated on the initial power level to find the power level at which the OSV based limit ($St=0.00455$) was calculated to just be met during the simulated LOCA transient. The calculated OSV powers were lower than the measured powers for those LOCA tests for which flow instability was detected, as shown in Table 10.1. For all of these tests the calculated test assembly initial power or operating power limit was at least 13% below the initial power level for which the test assembly went into flow instability.

Method 2

The measured time histories of the pressure boundaries (upper plenum and tank bottom), the inlet temperature, and the test power history were input to FLOWTRAN. FLOWTRAN calculated the Stanton number at each axial location of each heated surface at each time step. Figure 10.2 presents the largest calculated Stanton number for any heated surface at each time step for the Test 867_04. The calculations show that 0.12 seconds after the LOCA initiation, the thermal-hydraulic conditions inside Channel 3 met the SRS working criterion ($St=0.00455$). The test indicates that OSV as indicated by a rapid increase in void fraction occurred 0.42 seconds after the LOCA initiation.

Figures 10.3 to 10.14 present the results for remainder of the LOCA tests. Figures 10.2 to 10.12 show results for tests with the normal safety rod SCRAM power decay. Figures 10.13 and 10.14 show results for tests with the simulated fast shutdown power decay. In the fast shutdown system, high pressure He^3 gas is injected into empty rods in the core in about 200 milliseconds and the safety rods also are inserted. Figures 10.2 to 10.14 show that FLOWTRAN with $St=0.00455$ conservatively predicts both OSV and OFI for both series of tests.

11. UNCERTAINTY ANALYSIS

This section evaluates the effect of measurement uncertainties on predicted OFI powers. The measurement uncertainties given by B&W (Volume 3 of Reference 1) are expressed in terms of biases and random components with a best-estimate, 95% level of confidence. Figure 11.1 presents the upper plenum pressure measurement uncertainty as a function of ambient temperature at which the instrument was calibrated. A conservative value of 0.2 psi was assumed for the upper plenum pressure measurement

uncertainty. Table 5.6 in Volume 3 of Reference 1 lists the uncertainty in the tank bottom pressure measurement as +0.2/-0.234 psi. Figures 11.2 to 11.4 show the inlet temperature, the inlet flow, and the total power measurement uncertainties, respectively. The inlet temperature uncertainties are obtained from Figure 11.2. The uncertainty is 0.19 F at 81 F and 0.2 F at 125 F. The power uncertainties are obtained from Figure 11.4.

11.1 Effect of Measurement Uncertainties on Calculated Stanton Number for the Quasi-Steady State Power Ramp Tests

FLOWTRAN was used to calculate the Stanton number at each node of the heated surfaces of the test rig as a function of time. These calculations were performed to show that the SRS working criterion ($St=0.00455$) conservatively predicted the measured OSV condition. This was demonstrated by showing that the maximum Stanton number at any location prior to the time OSV was detected did not exceed the working criterion. The Stanton number calculated by FLOWTRAN depends on the measurement uncertainties for power, inlet flow, inlet temperature and tank bottom pressure, as shown in the following derivations.

The Stanton number is defined as:

$$St = \frac{q}{C_p G (T_{sat} - T_f)} \quad (5)$$

where

q = heat flux

C_p = specific heat

G = mass flux

T_{sat} = saturation temperature

T_f = bulk fluid temperature

Using an energy balance, the bulk fluid temperature can be expressed as:

$$T_f = T_{in} + \frac{L_h \int_0^z q(z) dz}{m c_p} \quad (6)$$

where

T_{in} = inlet temperature

L_h = heated parameter

$m = aG$ = mass flow rate

a = flow area

A uniform heat flux is assumed to simplified the illustration. Thus, Equation 6 becomes

$$T_f = T_{in} + \frac{A q}{m c_p} \quad (7)$$

where A is heat transfer area.

By replacing the bulk fluid temperature with the expression in Equation 7, the Stanton number becomes

$$St = \frac{q a}{C_p m (T_{sat} - T_{in}) - q A} \quad (8)$$

Variations of the Stanton number with the heat flux, the mass flow rate, the inlet temperature, and the saturation temperature are obtained by taking partial derivative of Equation 8 with respect to each of these quantities. The following equations give the results of these differentiations.

$$\frac{\partial St}{\partial q} = \left[\frac{1}{q} + \frac{A}{c_p m (T_{sat} - T_{in}) - q A} \right] \partial q \quad (9)$$

$$\frac{\partial St}{\partial m} = - \frac{c_p (T_{sat} - T_{in}) \partial m}{c_p m (T_{sat} - T_{in}) - q A} \quad (10)$$

$$\frac{\partial St}{\partial T_{in}} = \frac{c_p m \partial T_{in}}{c_p m (T_{sat} - T_{in}) - q A} \quad (11)$$

$$\frac{\partial St}{\partial T_{sat}} = - \frac{c_p m \partial T_{sat}}{c_p m (T_{sat} - T_{in}) - q A} \quad (12)$$

These equations show that the Stanton number increases with increasing power, decreases with increasing flow rate, increases with increasing inlet temperature, and decreases with increasing saturation temperature.

The following table groups the measurement uncertainties according to how they affect the calculated Stanton number, as shown in Equations 9 to 12. The table lists three columns, one with the combination of uncertainties that gives maximum Stanton numbers, one with no measurement uncertainties that gives nominal Stanton numbers, and one with the combination of measurement uncertainties that gives the minimum Stanton numbers. A positive sign preceding a measurement uncertainty δ indicates that the uncertainty is added to the nominal measurement N, while a negative sign preceding a measurement uncertainty indicates that the uncertainty is subtracted from the nominal measurement.

<u>Measurement Parameter</u>	<u>FLOWTRAN Calculation of St Number</u>		
	<u>Maximum</u>	<u>Nominal</u>	<u>Minimum</u>
Power	$N_{pw} + \delta_{pw}$	N_{pw}	$N_{pw} - \delta_{pw}$
Inlet Flow	$N_{fw} - \delta_{fw}$	N_{fw}	$N_{fw} + \delta_{fw}$
Tank Bottom Pressure	$N_{Tp} - \delta_{Tp}$	N_{Tp}	$N_{Tp} + \delta_{Tp}$
Inlet Temperature	$N_{IT} + \delta_{IT}$	N_{IT}	$N_{IT} - \delta_{IT}$

The subscript pw denotes power, fw denotes inlet flow, Tp denotes tank bottom pressure, and IT denotes inlet temperature.

Figures 11.5 thru 11.11 present the variation of the calculated Stanton number due to the measurement uncertainties for Tests 836_01 thru 836_07. These figures show that the SRS working criterion conservatively predicts OSV.

11.2 Effect of Measurement Uncertainties on Calculated Stanton Number for the LOCA Tests

For LOCA tests, the boundary conditions are upper plenum and tank bottom pressures. The pressure difference between the upper plenum and the tank bottom determines the assembly flow, which affects the calculated Stanton number and OFI power. The assembly flow increases as the pressure difference increases. This results in a lower Stanton number and a higher OFI power. A decrease in the inlet temperature causes a lower Stanton, which results in a higher OFI power.

The OFI powers calculated by FLOWTRAN depend on the measurement uncertainties for the upper plenum pressure, the tank bottom pressure, and the inlet temperature, as shown in the following table. This table groups the measurement uncertainties according to how they affect the calculated OFI power in the same manner as the table in the previous section.

<u>Measurement Parameter</u>	<u>FLOWTRAN Calculations of OFI Power</u>		
	<u>Maximum</u>	<u>Nominal</u>	<u>Minimum</u>
Upper plenum Pressure	$N_{Up} + \delta_{Up}$	N_{Up}	$N_{Up} - \delta_{Up}$
Tank Bottom Pressure	$N_{Tp} - \delta_{Tp}$	N_{Tp}	$N_{Tp} + \delta_{Tp}$
Inlet Temperature	$N_{IT} - \delta_{IT}$	N_{IT}	$N_{IT} + \delta_{IT}$

The subscript Up denotes upper plenum pressure.

Table 11.1 lists changes in the calculated LOCA OFI power due to the measurement uncertainties. Figures 11.12 and 11.13 compare measured powers with OSV powers calculated using the SRS working criterion.

12. DISCUSSIONS OF LEAKAGE FLOW IN CHANNEL 1

As discussed in Section 7.2, in the FLOWTRAN model the excess leakage flow was assigned to Channel 5. However, during a recent inspection B&W determined that the leak was located in Channels 1. Consequently, FLOWTRAN would underestimate the flow in Channel 1 and the heat transfer from Channel 2 to Channel 1. To determine the effect of relocating the leak, selected test cases were reanalyzed using a revised FLOWTRAN model in which the leak was assigned to Channel 1. This section presents results calculated by the revised model.

The only differences between the revised and the old FLOWTRAN models are the local form losses for Channels 1 and 5. Table 12.1 lists the local form losses employed in this revised model. Table 12.2 shows that the flows and pressures calculated by the revised model for Test 833_01PW1 (steady state heated test) agree with the old model calculations except for the Channel 1 and Channel 5 flows. As shown in Figure 12.1, the revised model is able to predict measured fluid temperatures. A comparison of this figure and Figure 7.8 demonstrates that the revised model predicts Channel 2 fluid temperatures substantially more accurately than the old model.

The assumption of excess leakage flow to Channel 5 instead of Channel 1 does not affect the FLOWTRAN prediction of Channel 3 thermal-hydraulic behavior, as shown in Figures 7.12 through 7.17. OSV power predictions also were not affected because Channel 3 is the limiting channel. Figure 12.2 shows that the calculated Stanton numbers for Power Ramp Test 836_01 by both models are the same. The OSV power calculated by the revised model for LOCA Test 867_08 was 4.6127 MW, and the OSV power calculated by the old model for the same test was 4.6124 MW.

13. CONCLUSIONS

The test cases analyzed show that 1) FLOWTRAN accurately predicts the thermal-hydraulic behavior of the MK-22 mockup test assembly during the steady-state and transient test conditions, and 2) FLOWTRAN using the SRS working criterion ($St=0.00455$) conservatively predicts the MK-22 mockup test assembly OFI power for both LOCA transient tests and quasi-steady state power ramp tests, without using a peaking factor to account for heat flux variations near ribs. This implies that the peaking factor of 1.209 used in Mark-22 assembly power limits analysis to account for aluminum rib effect adds a measure of conservatism to these limits.

REFERENCES

1. B&W Report No. RDD:4427-13-01-01:01, "WSRC Flow Excursion Test Program with a Mark 22 Mockup Fuel Assembly in Downflow," Babcock & Wilcox, Alliance Research Center, February, 1990.
2. Ohrn, T. R. and Privette, R. M. "New Production Reactor Flow Instability Experiments with Coolant Upflow," RDD:92:4024-01-01:01, Babcock & Wilcox, Alliance Research Center, April, 1992.
3. Letter M. T. Childerson and J. E. Blake, Babcock & Wilcox to J. E. Halverson, "Flow Excursion Test Leakage Questions, NPR-566," Contract No. AA-12848-P, November 5, 1991.
4. Chen, Kuo-Fu, "Benchmarking of FLOWTRAN with Mark-22 Mockup Flow Excursion Test Data from Babcock & Wilcox," WSRC-TR-91-629, November, 1991.
5. Aleman, S. E., Gregory, M. V., Hamm, L. L., Pevey, R. E., Reed, W. H., and Smith, F. G., DPSTM-140, "FLOWTRAN: An Algorithm for Describing the Thermal-Hydraulic Behavior of SRP Assemblies," September, 1989.
6. Goodwin, K. E., Sjostrom, L. C., Witmer, F. E., and Buckner, M. L., signatories, "Agreements and Commitments: Review of FI Limits Methodology Meeting, August 30-September 2, 1988, Savannah River Laboratory," September 2, 1988.
7. Perry's Chemical Engineering Handbook
8. Walters, T. W., "Final Report for the Flow Excursion Follow-on Testing," Babcock & Wilcox Report RDD:93:44260-102-006:01, August 7, 1992.

**Table 2.1 DIMENSIONS USED BY FLOWTRAN TO MODEL THE TEST
SECTION**

CORE HIGHT (IN)	161.595
HEATED LENGTH (IN)	143.000
UPPER UNHEATED SECTION (IN)	8.995
BOTTOM UNHEATED SECTION (IN)	9.600

CHANNEL DIMENSIONS:

CHANNEL (IN)	FLOW AREA (IN ²)	HYDRAULIC DIAMETER
1	1.840	0.295
2	2.302	0.4335
3	2.3328	0.5163
4	1.5484	0.4546
5	1.6742	1.460

TUBE	ID (IN)	OD (IN)
INNER TARGET	1.460	1.77435
INNER HEATER	2.31185	2.407
OUTER HEATER	2.997	3.0650
OUTER TARGET	3.5376	3.7
UHS	4.010	4.110

Table 2.2

LIST OF DATA ACQUISITION SYSTEM INSTRUMENTS

Component	ID	Instrument	Description
Coolant Supply	WSLS01	limit switch	Water Inlet Valve Full Closed
	WSLS02	limit switch	Water Inlet Valve Full Open
	WSLS03	limit switch	Gas Inlet Valve Full Closed
	WSLS04	limit switch	Gas Inlet Valve Full Open
	WSTC01	fluid thermocouple	Temperature of Water Supply at Turbine Meter
	WSTM01	turbine meter	Flow Rate of Water Supply
Inlet Plenum	IPAP01	pressure	Absolute Pressure in Inlet Plenum
	IPDP01	differential pressure	Low Range Differential Pressure for Venturi 1
	IPDP02	differential pressure	Low Range Differential Pressure for Venturi 2
	IPDP03	differential pressure	Low Range Differential Pressure for Venturi 3
	IPDP04	differential pressure	High Range Differential Pressure for Venturi 1
	IPDP05	differential pressure	High Range Differential Pressure for Venturi 2
	IPDP06	differential pressure	High Range Differential Pressure for Venturi 3
	IPTC01	fluid temperature	Fluid Temperature at Venturi 1
	IPTC02	fluid temperature	Fluid Temperature at Venturi 2
	IPTC03	fluid temperature	Fluid Temperature at Venturi 3
Top Fitting of Fuel Assembly	TFAP01	pressure	Pressure at Inlet to Heater Tubes
	TFDP01	differential pressure	Differential Pressure Upper Plenum to 69.5" below top of sleeve housing
	TFDP02	differential pressure	Differential Pressure Overall Fuel Assembly
	TFRT01	fluid temperature	Fluid Temperature in Top Fitting
Universal Sleeve Housing (USH)	USMT01	metal temperature	Outer USH Tube Temperature, 152.40 inches
	USMT02	metal temperature	Outer USH Tube Temperature, 96.65 inches
	USMT03	metal temperature	Outer USH Tube Temperature, 41.40 inches
Channel 2	C2AP01	pressure	Pressure at Subchannel 2A, 129.65 inches
	C2AP02	pressure	Pressure at Subchannel 2C, 129.65 inches
	C2AP03	pressure	Pressure at Subchannel 2A, 96.65 inches
	C2AP04	pressure	Pressure at Subchannel 2C, 96.65 inches
	C2AP05	pressure	Pressure at Subchannel 2A, 63.65 inches
	C2AP06	pressure	Pressure at Subchannel 2C, 63.65 inches
	C2AP07	pressure	Pressure at Subchannel 2A, at Upper Electrical Connector, 173.55 inches
	C2AP08	pressure	Pressure at Subchannel 2C, at Upper Electrical Connector, 173.55 inches
	C2AP09	pressure	Pressure at Subchannel 2A, at Lower Electrical Connector, 23.65 inches
	C2AP10	pressure	Pressure at Subchannel 2C, at Lower Electrical Connector, 23.65 inches

Table 2.2 (cont'd)

Component	ID	Instrument	Description
Channel 2	C2DP01	differential pressure	Differential Pressure Subchannel 2A, 25.65-173.55 inches
	C2DP02	differential pressure	Differential Pressure for Pitot Tube, Subchannel 2A
	C2DP03	differential pressure	Differential Pressure Subchannel 2C, 25.65-173.55 inches
	C2TC01	fluid temperature	Differential Pressure at Subchannel 2C, 129.65 inches
	C2TC02	fluid temperature	Differential Pressure at Subchannel 2C, 96.65 inches
	C2TC03	fluid temperature	Differential Pressure at Subchannel 2C, 63.65 inches
	C2CP01	optical probe	Void Fraction Subchannel 2C
Outer Fuel Tube	OFMT01	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 152.40 inches
	OFMT02	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 152.4 inches
	OFMT03	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 129.65 inches
	OFMT04	metal temperature	Heater Temperature Subchannel 2B, 135.0 Degrees, 129.65 inches
	OFMT05	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 129.65 inches
	OFMT06	metal temperature	Heater Temperature Subchannel 2D, 315.0 Degrees, 129.65 inches
	OFMT07	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 96.65 inches
	OFMT08	metal temperature	Heater Temperature at Rib, Subchannel 2A, 90.0 Degrees, 96.65 inches
	OFMT09	metal temperature	Heater Temperature Subchannel 2B, 135.0 Degrees, 96.65 inches
	OFMT10	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 96.65 inches
	OFMT11	metal temperature	Heater Temperature at Rib, Subchannel 2C, 270.0 Degrees, 96.65 inches
	OFMT12	metal temperature	Heater Temperature Subchannel 2D, 315.0 Degrees, 63.65 inches
	OFMT13	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 63.65 inches
	OFMT14	metal temperature	Heater Temperature Subchannel 2B, 135.0 Degrees, 63.65 inches
	OFMT15	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 63.65 inches
	OFMT16	metal temperature	Heater Temperature Subchannel 2D, 315.0 Degrees, 63.65 inches
	OFMT17	metal temperature	Heater Temperature Subchannel 2A, 22.5 Degrees, 41.40 inches
	OFMT18	metal temperature	Heater Temperature Subchannel 2C, 202.5 Degrees, 41.40 inches
Channel 3	C3AP01	pressure	Pressure at Subchannel 3C, at Upper Electrical Connector, 173.55 inches
	C3AP02	pressure	Pressure at Subchannel 3A, at Lower Electrical Connector, 25.65 inches
	C3AP03	pressure	Pressure at Subchannel 3C, at Lower Electrical Connector, 25.65 inches
	C3DP01	differential pressure	Differential Pressure at Subchannel 3A, 25.65-173.55 inches
	C3DP02	differential pressure	Differential Pressure for Pitot Tube, Subchannel 3A
	C3TC01	fluid temperature	Fluid Temperature at Subchannel 3A, 129.65 inches
	C3TC02	fluid temperature	Fluid Temperature at Subchannel 3A, 96.65 inches
	C3TC03	fluid temperature	Fluid Temperature at Subchannel 3A, 63.65 inches
	C3CP01	optical probe	Void Fraction Subchannel 3C

Table 2.2 (cont'd)

<u>Component</u>	<u>ID</u>	<u>Instrument</u>	<u>Description</u>
Inner Fuel Tube	IFMT01	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 152.40 inches
	IFMT02	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 152.40 inches
	IFMT03	metal temperature	Heater Temperature Subchannel 3C, 0.0 Degrees, 129.65 inches
	IFMT04	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 129.65 inches
	IFMT05	metal temperature	Heater Temperature Subchannel 3B, 180.0 Degrees, 129.65 inches
	IFMT06	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 129.65 inches
	IFMT07	metal temperature	Heater Temperature Subchannel 3D, 0.0 Degrees, 96.65 inches
	IFMT08	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 96.65 inches
	IFMT09	metal temperature	Heater Temperature Subchannel 3B, 180.0 Degrees, 96.65 inches
	IFMT10	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 96.65 inches
	IFMT11	metal temperature	Heater Temperature Subchannel 3D, 0.0 Degrees, 63.65 inches
	IFMT12	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 63.65 inches
	IFMT13	metal temperature	Heater Temperature Subchannel 3B, 180.0 Degrees, 63.65 inches
	IFMT14	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 63.65 inches
	IFMT15	metal temperature	Heater Temperature Subchannel 3A, 112.5 Degrees, 41.40 inches
	IFMT16	metal temperature	Heater Temperature Subchannel 3C, 292.5 Degrees, 41.40 inches
Channel 4	C4AP01	pressure	Pressure at Subchannel 4B, at Upper Electrical Connector, 173.55 inches
	C4AP02	pressure	Pressure at Subchannel 4B, at Lower Electrical Connector, 25.65 inches
	C4AP03	pressure	Pressure at Subchannel 4D, at Lower Electrical Connector, 25.65 inches
	C4DP01	differential pressure	Differential Pressure Subchannel 4B, 25.65-173.55 inches
	C4DP02	differential pressure	Differential Pressure Subchannel 4B, for pitot Tube
	C4TC01	fluid temperature	Fluid Temperature at Subchannel 4B, 129.65 inches
	C4TC02	fluid temperature	Fluid Temperature at Subchannel 4B, 96.65 inches
	C4TC03	fluid temperature	Fluid Temperature at Subchannel 4B, 63.35 inches
	C4CP01	optical probe	Void Fraction Subchannel 4D
Bottom Fitting Insert	BFAP01	pressure	Pressure at Channel Exits
	BFAP02	pressure	Pressure at Channel Limit (venturi)
	BFDP01	differential pressure	Differential Pressure Assembly Limit to Tank Bottom
	BFDP02	differential pressure	Differential Pressure Monitor Pin to Tank Bottom
	BFRT01	fluid temperature	Fluid Temperature Top of Monitor Pin
	BFTC01	fluid temperature	Fluid Temperature Exit Channel 2
	BFTC02	fluid temperature	Fluid Temperature Exit Channel 3
	BFTC03	fluid temperature	Fluid Temperature Exit Channel 4
	BFTC04	fluid temperature	Fluid Temperature Inside Shell Holes
	BFTC05	fluid temperature	Temperature at Monitor Pin Subchannel A
	BFTC06	fluid temperature	Temperature at Monitor Pin Subchannel B
	BFTC07	fluid temperature	Temperature at Monitor Pin Subchannel C
	BFTC08	fluid temperature	Temperature at Monitor Pin Subchannel D

Table 2.2 (cont'd)

Component	ID	Instrument	Description
Reactor Outlet Tank	RTAP01	pressure	Pressure at Tank Bottom
Water Collection	WCLS01	limit switch	Holding Tank Valve Full Closed
	WCLS02	limit switch	Holding Tank Valve Full Open
	WCLS03	limit switch	Quench Tank Valve Full Closed
	WCLS04	limit switch	Quench Tank Valve Full Open
Power Supply	PSAM01	ammeter	Current Through Outer Heater
	PSAM02	ammeter	Current Through Inner Heater
	PSVM01	voltage divider	Current Through Outer Heater
	PSVM02	voltage divider	Current Through Inner Heater
Miscellaneous Instrumentation	MSRF01	voltmeter	Voltage Across Resistance Temperature Detector Reference Resistor
	MSTC01	reference temperature	Temperature of Data Acquisition System Analogic Chassis
	MSTC02	reference temperature	Ambient Temperature in Test Bay
	MSTC03	reference temperature	Thermocouple Reference Oven Temperature

LIST OF DATA ACQUISITION SYSTEM INSTRUMENTS

The instrument ID is composed of three parts. The first two characters designate the component, as follows:

BF	Bottom Fitting Insert of the Fuel Assembly
C2	Coolant Channel 2 (between the Outer Target and the Outer Heater)
C3	Coolant Channel 3 (between the Outer Heater and the Inner Heater)
C4	Coolant Channel 4 (between the Inner Heater and the Inner Target)
IF	Inner Fuel (Heater) Tube
IP	Inlet plenum, which includes the inlet flowmeters
IT	Inner Target Tube
MS	Miscellaneous
OF	Outer Fuel (Heater) Tube
OT	Outer Target Tube
PL	Purge Line (inlet piping to outlet plenum)
PS	Electrical Power Supply
RT	Reactor Outlet Tank
TF	Top Fitting of the Fuel Assembly
US	Universal Sleeve Housing (USH)
WC	Water Collection, including Quench tank, Collection Tank, and Holding Tank
WS	Water Supply, including 4000 gpm loop and the inlet reservoir.

The next two characters designate the type of measurement or derived quantity as follows:

AM	Ammeter
AP	Absolute Pressure
CP	Conductivity Probe
DP	Differential Pressure
GP	Gauge Pressure
LS	Limit Switch
LV	Water Level
MT	Metal Thermocouple
OP	Optical Phase Detector
RT	Pitot Tube
RF	Reference
RT	Resistance Temperature Detector (RTD)
TC	Fluid Thermocouple
TM	Turbine Meter
VM	Voltmeter
VN	Venturi Flowmeter
VT	Voltage Tap
WM	Wattmeter

The final two characters (numbers) designate the individual measurement.

Table 3.1 TEST MATRIX

1. Zero Power Steady state Tests - Pressure Profile Characterization:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
827-01 to 827-20	125 and 80	-none-	Pressure profiles were measured for 10 flows x 2 temperatures

2. Zero Power Transient Tests - Pressure Transient Characterization:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
811-04, 11, 13, 17	100±5	-none-	The last in a series of runs was considered an acceptable transient

3. Steady State Heated Tests:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
833-01	80 ±5	1,2,3 MW	No void or flow instability (FI). Flowrate = 259 GPM
833-02	80 ±5	1.3, 2.7 4.0 MW	No void or flow instability (FI). Flowrate = 345 GPM
833-05	82	0.5 to 2.0 MW	No void or flow instability (FI). Flowrate = 258 to 345 GPM, outer heater powered
833-06	82	0.5 to 2.0 MW	No void or flow instability (FI). Flowrate = 258 to 345 GPM, inner heater powered

4. Quasi-Steady State Power Ramps:

<u>RUN</u>	<u>INLET TEMP.</u>	<u>INITIAL POWER.</u>	<u>NOTES</u>
	<u>°F</u>	<u>MW</u>	
836-01	79	2.80 MW for FI	158.0 gpm, Tbot = 28.5 psia
836-02	81	2.75 MW for FI	167.5 gpm, Tbot = 21.0 psia
836-03	124	3.06 MW for FI	229.4 gpm, Tbot = 21.0 psia
836-04	81	3.87 MW for FI	211.9 gpm, Tbot = 28.5 psia
836-05	80	3.80 MW for FI	220.5 gpm, Tbot = 21.0 psia
836-06	123	2.68 MW for FI	204.9 gpm, Tbot = 21.0 psia
836-07	125	4.00 MW for FI	285.8 gpm, Tbot = 21.0 psia

Table 3.1 (cont'd)

5. LOCA Transient Tests

<u>RUN</u>	<u>INLET TEMP.</u> °F	<u>INITIAL POWER.</u> MW	<u>NOTES</u>
867-02	125	2.12 N	No void or flow instability (FI)
867-03	124.5	3.31 N	Momentary boiling osc. detected- No FI or Void
867-04	127.4	4.34 N	Flow instability occurred
867-05	123.6	4.05 N	Void seen, no flow instability
867-06	123.7	4.50 F	FAST POWER SCRAM - no flow instability, and <20% void
867-07	123.6	4.33 N	Flow instability occurred
867-08	81.6	5.32 N	Flow instability occurred
867-09	81.4	4.93 N	Small amt. of void only - no FI
867-10	123.3	4.28 N	Flow instability occurred - Thermal Recovery, then (delayed) Shutdown
867-11	123.3	4.28 N	Flow instability occurred, *Recovery*
867-12	122.9	4.58 N	Flow instability occurred, SEVERE Dryout
867-13	81.7	5.35 N	Flow instability occurred
867-14	124.6	4.53 F	Fast Scram w/ no FI (Close), void seen
867-15	124.1	4.10 N	Flow instability occurred
867-16	124.1	4.75 F	Fast Scram where flow instability occurred
867-17	123.2	4.60 F	Fast Scram w/ no FI (Close), void seen
867-18	80.7	6.04 F	Fast Scram w/ no FI (Close), void seen
867-19	81.3	5.21 N	Flow instability occurred
867-20	81.7	5.13 N	No Flow Instability. Void was seen.
867-21	81.6	6.23 F	Fast Scram w/ FI and Recovery
867-22	125.3	4.04 N	FI, shutdown due to high metal T
867-23	122.8	4.03 N	Flow Reduction, "recovery", Void Ch 3,4

N: Normal power decay

F: Fast power decay

Table 4.1
Comparisons of the Measured Channel Pressure Drops and the Velocities
for the B&W Upflow and Downflow Tests at Comparable Test Conditions

Instruments		Test 039_04 Upflow	Test 827_19 Downflow
TFRT01	Inlet Temp. (F)	81.45	82.27
WSTM01	Inlet Flow (GPM)	310.43	309.589
IPAP01	Inlet Plenum Press. (psia)	133.124	56.84
OPAP01/RTAP01	Outlet Plenum Press. (psia)	89.37	27.91
C2DP01	Channel 2 Diff. P. (psi)	17.382	-2.090
C2DP03	Channel 2 Diff. P. (psi)	15.529	-2.805
C3DP01	Channel 3 Diff. P. (psi)	21.996	-7.248
C4DP01	Channel 4 Diff. P. (psi)	18.541	-4.948
C2DP02	Channel 2 Pitot (psi)	4.76	3.21
C3DP02	Channel 3 Pitot (psi)	3.70	2.87
C4DP02	Channel 4 Pitot (psi)	6.90	4.73
Channel 2 Frictional Loss from C2DP01(psi)		12.076	7.396
Channel 2 Frictional Loss from C2DP03 (psi)		10.223	8.106
Channel 3 Frictional Loss from C3DP01 (psi)		16.690	12.556
Channel 4 Frictional Loss from C4DP01 (psi)		13.235	10.256
Calculated Channel 3 Surface Roughness (in)			
(Assumes no flow leakage for downflow test)		6.66E-4	3.3E-5

The surface roughness for a drawn tubing (such as brass, lead and glass) listed in Perry's Chemical Engineering Handbook is 6.0E-5 in.

Table 4.2
Estimates of the Relative Flow Rate for the Upflow and the Downflow Tests
Based on the Measured Frictional Pressure Drops and the Pitot Tube Data

BASED ON FRICTIONAL PRESSURE DROP:

$(Q^u / Q^d)_{ch2}$ (from C2DP01)	1.278
$(Q^u / Q^d)_{ch2}$ (from C2DP03)	1.123
$(Q^u / Q^d)_{ch3}$	1.115
$(Q^u / Q^d)_{ch4}$	1.135

BASED ON PITOT TUBE MEASUREMENTS:

$(Q^u / Q^d)_{ch2}$	1.217
$(Q^u / Q^d)_{ch3}$	1.135
$(Q^u / Q^d)_{ch4}$	1.207

Q^u = flow rate for upflow test, Q^d = flow rate for downflow test

Table 5.1

Derived Upflow Test Assembly Channel Surface Roughness and Local
Form Loss

<u>Channel</u>	<u>Roughness</u> in	<u>Local Form Loss (psi/(100 gpm)²)</u>		
		<u>Channel inlet</u>	<u>Inside Channel</u>	<u>Channel Exit</u>
1	6.0E-04	31100.000	0.000	0.1000
2	6.0E-04	11.000	0.030	4.0000
3	6.0E-04	2.750	0.000	1.6000
4	6.0E-04	7.500	0.065	1.1404
5	6.0E-04	5000.000	0.000	70.0000

Table 5.2

**Comparisons of the Measured Channel Pressure Drops and the Flow Splits
with the FLOWTRAN Calculations
B&W Upflow Test 039 04**

Instruments		Measurement	FLOWTRAN
IPTC03	Inlet Temp. (F)	81.45	81.45*
IPVN20	Inlet Flow (GPM)	410.43	410.43*
OPAP01	Outlet Plenum Press. (psia)	89.37	89.37*
IPAP01	Inlet Plenum Press. (psia)	133.124	133.168
C2AP07**	Channel 2 Inlet P. (psia)	118.733	117.088
C2AP08**	Channel 2 Inlet P. (psia)	117.17	
C2AP09**	Channel 2 Outlet P. (psia)	101.46	101.453
C2AP10**	Channel 2 Outlet P. (psia)	101.46	
C2DP01**	Channel 2 Diff. P. (psi)	17.382	15.634
C2DP03**	Channel 2 Diff. P. (psi)	15.529	
C3AP01	Channel 3 Inlet P. (psia)	121.63	121.507
C3AP02**	Channel 3 Outlet P. (psia)	100.45	99.856
C3AP03**	Channel 3 Outlet P. (psia)	99.87	
C3DP01	Channel 3 Diff. P. (psi)	21.996	21.651
C4AP01	Channel 4 Inlet P. (psia)	117.96	118.016
C4AP02**	Channel 4 Outlet P. (psia)	99.59	99.456
C4AP03**	Channel 4 Outlet P. (psia)	100.38	
C4DP01	Channel 4 Diff. P. (psi)	18.541	18.559
Channel Flow Split (%):			
Channel 2		30.81	30.83
Channel 3		45.38	45.43
Channel 4		23.81	23.74

* FLOWTRAN input boundary conditions

** Two pressure taps are at the same axial location but 180° apart azimuthally.

Table 5.3

Derived Downflow Test Assembly Channel Surface Roughness and Local Form Loss

<u>Channel</u>	<u>Roughness</u> <u>in</u>	<u>Local Form Loss (psi/(100 gpm)²)</u>		
		<u>Channel inlet</u>	<u>Inside Channel</u>	<u>Channel Exit</u>
1	6.0E-04	31100.000	0.000	0.1000
2	6.0E-04	21.000	0.030	6.0000
3	6.0E-04	4.300	0.000	2.1000
4	6.0E-04	14.000	0.065	0.5000
5	6.0E-04	75.000	0.000	10.0000

Table 5.4

Comparisons of the Measured Channel Pressure Drops and the Flow Splits
with the FLOWTRAN Calculations
B&W Downflow Test 827 19

Instruments		Measurement	FLOWTRAN
IPTC03	Inlet Temp. (F)	82.27	82.27*
IPVN20	Inlet Flow (GPM)	309.589	309.589*
RTAP01	Outlet Plenum Press. (psia)	27.91	27.91*
IPAP01	Inlet Plenum Press. (psia)	56.84	56.788
C2AP07**	Channel 2 Inlet P. (psia)	47.70	47.903
C2AP08**	Channel 2 Inlet P. (psia)	48.10	
C2AP09**	Channel 2 Outlet P. (psia)	45.60	45.517
C2AP10**	Channel 2 Outlet P. (psia)	45.40	
C2DP01**	Channel 2 Diff. P. (psi)	-2.090	-2.386
C2DP03**	Channel 2 Diff. P. (psi)	-2.805	
C3AP01	Channel 3 Inlet P. (psia)	51.30	51.293
C3AP02**	Channel 3 Outlet P. (psia)	44.00	44.050
C3AP03**	Channel 3 Outlet P. (psia)	44.00	
C3DP01	Channel 3 Diff. P. (psi)	-7.248	-7.243
C4AP01	Channel 4 Inlet P. (psia)	48.10	48.179
C4AP02**	Channel 4 Outlet P. (psia)	43.10	43.091
C4AP03**	Channel 4 Outlet P. (psia)	43.30	
C4DP01	Channel 4 Diff. P. (psi)	-4.948	-5.088
Channel Flow Split (%):			
Channel 2		29.76	30.397
Channel 3		47.04	45.542
Channel 4		23.20	24.061

* FLOWTRAN input boundary conditions

** Two pressure taps are at the same axial location but 180° apart azimuthally.

Table 6.1

Zero Powered Steady State Test Conditions (Tests 827_01 TO 827_20)

TEST ID	POWER KW	EXIT PRESS. PSIA	INLET TEMP. F	FLOW RATE GPM
827_01	0	28.24	127.50	359.531
827_02	0	28.73	123.60	179.300
827_03	0	28.67	125.33	251.013
827_04	0	28.56	123.43	322.165
827_05	0	28.64	123.50	396.076
827_06	0	28.44	124.49	359.628
827_07	0	28.55	124.67	284.550
827_08	0	28.50	124.17	221.560
827_09	0	28.50	125.05	304.923
827_10	0	28.65	124.66	400.535
827_11	0	28.56	80.72	359.677
827_12	0	28.71	79.54	190.090
827_13	0	28.47	79.46	253.668
827_14	0	28.71	79.77	326.968
827_15	0	28.59	79.79	402.371
827_16	0	28.45	81.69	355.980
827_17	0	28.26	81.61	289.164
827_18	0	28.34	82.06	217.794
827_19	0	27.91	82.27	309.589
827_20	0	28.78	81.12	394.514

Table 6.2 Measured Pressure Drop (Tests 827_01 to 827_20)

TEST ID	DENSITY LB/FT ³	ELEVATION LOSS	CHANNEL 2				CHANNEL 3				CHANNEL 4			
			PRESSURE		PRESSURE		PRESSURE		PRESSURE		PRESSURE		PRESSURE	
			PSID	C2DP01*	PSID	DROP **	PSID	C2DP03*	PSID	DROP **	PSID	C3DP01*	PSID	DROP **
827_01	61.716	5.286	-3.680	8.97	-4.645	9.93	-10.178	15.46	-7.320	12.61	-10.178	15.46	-7.320	12.61
827_02	61.599	5.276	2.793	2.48	2.492	2.78	0.993	4.28	1.756	3.52	0.993	4.28	1.756	3.52
827_03	61.580	5.274	0.672	4.60	0.127	5.15	-2.724	8.00	-1.183	6.46	-2.724	8.00	-1.183	6.46
827_04	61.523	5.269	-1.988	7.26	-2.708	7.98	-7.249	12.52	-4.822	10.09	-7.249	12.52	-4.822	10.09
827_05	61.687	5.283	-5.378	10.66	-6.459	11.74	-13.047	18.33	-9.564	14.85	-13.047	18.33	-9.564	14.85
827_06	61.700	5.284	-3.649	8.93	-4.561	9.85	-10.001	15.29	-7.198	12.48	-10.001	15.29	-7.198	12.48
827_07	61.770	5.290	-0.531	5.82	-1.203	6.49	-4.772	10.06	-2.922	8.21	-4.772	10.06	-2.922	8.21
827_08	61.327	5.253	1.669	3.58	1.318	3.93	-1.198	6.45	0.163	5.09	-1.198	6.45	0.163	5.09
827_09	61.731	5.287	-1.246	6.53	-1.910	7.20	-6.295	11.58	-3.915	9.20	-6.295	11.58	-3.915	9.20
827_10	61.623	5.278	-5.565	10.84	-6.699	11.98	-13.579	18.86	-9.879	15.16	-13.579	18.86	-9.879	15.16
827_11	62.385	5.343	-4.463	9.81	-5.365	10.71	-11.152	16.50	-8.084	13.43	-11.152	16.50	-8.084	13.43
827_12	62.233	5.330	2.162	3.17	1.846	3.48	0.127	5.20	0.958	4.37	0.127	5.20	0.958	4.37
827_13	62.410	5.345	0.079	5.27	-0.429	5.77	-3.444	8.79	-1.912	7.26	-3.444	8.79	-1.912	7.26
827_14	62.144	5.323	-2.936	8.26	-3.693	9.02	-8.603	13.93	-6.039	11.36	-8.603	13.93	-6.039	11.36
827_15	62.271	5.333	-6.723	12.06	-7.789	13.12	-14.933	20.27	-11.195	16.53	-14.933	20.27	-11.195	16.53
827_16	62.332	5.339	-4.252	9.59	-5.120	10.46	-10.906	16.24	-7.878	13.22	-10.906	16.24	-7.878	13.22
827_17	62.078	5.317	-1.236	6.55	-1.847	7.16	-5.784	11.10	-3.714	9.03	-5.784	11.10	-3.714	9.03
827_18	62.388	5.343	1.290	4.05	0.890	4.45	-1.449	6.79	-0.277	5.62	-1.449	6.79	-0.277	5.62
827_19	62.009	5.311	-2.090	7.40	-2.805	8.12	-7.248	12.56	-4.948	10.26	-7.248	12.56	-4.948	10.26
827_20	62.247	5.331	-6.330	11.66	-7.452	12.78	-14.331	19.66	-10.619	15.95	-14.331	19.66	-10.619	15.95

* MEASURED STATIC PRESSURE DIFFERENCE BETWEEN THE PRESSURE TAPS

** MEASURED PRESSURE DROP = ELEVATION LOSS - STATIC PRESSURE DIFFERENCE

ELEVATION LOSS = DENSITY * 148 / 12 / 144 (psi)

Table 6.3 Measured Flow Distributions (Tests 827_01 to 827_20)

TEST ID	PITOT TUBE MEASUREMENT (PSID)				FLOW DISTRIBUTIONS			
	C2DP02	C3DP02	C4DP02	CHANNEL 4	CHANNEL 2			CHANNEL 4
	CHANNEL 2	CHANNEL 3	CHANNEL 4		CHANNEL 2	CHANNEL 3	CHANNEL 4	
827_01	4.31	3.65	6.31		0.3017	0.4640	0.2344	
827_02	1.08	0.97	1.58		0.2976	0.4713	0.2311	
827_03	2.11	1.88	3.09		0.2981	0.4703	0.2316	
827_04	3.42	3.02	5.00		0.2988	0.4693	0.2320	
827_05	5.16	4.52	7.46		0.2997	0.4689	0.2314	
827_06	4.25	3.74	6.18		0.2992	0.4691	0.2317	
827_07	2.71	2.39	3.96		0.2989	0.4691	0.2320	
827_08	1.63	1.45	2.37		0.2985	0.4705	0.2311	
827_09	3.03	2.73	4.47		0.2971	0.4713	0.2317	
827_10	5.30	4.64	7.63		0.2999	0.4690	0.2311	
827_11	4.34	3.84	6.28		0.2990	0.4701	0.2309	
827_12	1.24	1.11	1.80		0.2981	0.4713	0.2306	
827_13	2.18	1.95	3.19		0.2978	0.4708	0.2313	
827_14	3.59	3.19	5.25		0.2983	0.4700	0.2317	
827_15	5.41	4.77	7.91		0.2989	0.4691	0.2321	
827_16	4.26	3.78	6.25		0.2983	0.4697	0.2320	
827_17	2.81	2.52	4.12		0.2976	0.4710	0.2314	
827_18	1.63	1.47	2.40		0.2971	0.4715	0.2315	
827_19	3.21	2.87	4.73		0.2976	0.4704	0.2320	
827_20	5.23	4.62	7.62		0.2989	0.4695	0.2316	

FLOW DISTRIBUTION (i) = A(i) * Sqrt[PITOT(i)] / SUM

SUM = SUMMATION[A(i) * Sqrt[PITOT(i)]] i=2, 3, 4

A(2) = 0.3420 ; A(3) = 0.5716 ; A(4) = 0.2196

Table 6.4 Comparisons between the Calculated and Measured Pressures (Tests 827_01 to 827_20)

TEST ID	CHANNEL 2 INLET PRESSURE (PSIA)*			CHANNEL 2 EXIT PRESSURE (PSIA)*			CHANNEL 2 PRESSURE DROP (PSID)*		
	MEAS 1	MEAS 2	CALC	MEAS 1	MEAS 2	CALC	MEAS 1	MEAS 2	CALC
827_01	56.20	56.70	56.41	52.40	52.10	51.95	8.97	9.93	9.74
827_02	31.20	31.30	31.46	33.90	33.80	34.13	2.48	2.78	2.60
827_03	39.30	39.50	39.53	39.90	39.70	39.89	4.60	5.15	4.91
827_04	49.60	50.00	50.12	47.60	47.30	47.49	7.26	7.98	7.90
827_05	63.30	63.90	64.07	57.90	57.60	57.59	10.66	11.74	11.77
827_06	56.00	56.60	56.67	52.40	52.10	52.18	8.93	9.85	9.77
827_07	43.90	44.40	44.12	43.40	43.20	43.17	5.82	6.49	6.25
827_08	35.30	35.50	35.70	36.90	36.80	37.10	3.58	3.93	3.85
827_09	46.70	47.10	47.22	45.40	45.20	45.38	6.53	7.20	7.12
827_10	64.30	65.00	64.99	58.70	58.30	58.26	10.84	11.98	12.01
827_11	57.20	57.70	57.50	52.70	52.40	52.57	9.81	10.71	10.28
827_12	32.70	32.80	32.72	34.80	34.70	34.93	3.17	3.48	3.12
827_13	40.00	40.30	40.08	40.00	39.90	40.08	5.27	5.77	5.35
827_14	51.60	52.00	51.69	48.60	48.30	48.44	8.26	9.02	8.58
827_15	66.20	66.70	66.19	59.40	59.00	58.81	12.06	13.12	12.72
827_16	56.80	57.20	56.67	52.40	52.20	51.95	9.59	10.16	10.06
827_17	44.80	45.10	45.00	43.50	43.30	43.54	6.55	7.16	6.78
827_18	35.40	35.70	35.38	36.70	36.60	36.72	4.05	4.45	4.01
827_19	47.70	48.10	47.90	45.60	45.40	45.52	7.40	8.12	7.70
827_20	64.60	65.20	64.19	58.20	57.90	57.29	11.66	12.78	12.23

* There are two pressure taps at the same axial locations but 180 degree apart.

Table 6.4 (Cont'd)

TEST ID	CHANNEL 3 INLET PRESSURE (PSIA)			CHANNEL 3 EXIT PRESSURE (PSIA)*			CHANNEL 3 PRESSURE DROP (PSID)		
	MEAS	CALC	% ERROR	MEAS 1	MEAS 2	CALC	MEAS	CALC	% ERROR
827_01	60.50	60.88	0.62	50.30	50.40	49.99	15.46	16.17	4.55
827_02	32.50	32.59	0.29	33.40	33.40	33.65	4.28	4.22	-1.41
827_03	41.70	41.72	0.05	38.90	38.90	38.94	8.00	8.05	0.70
827_04	53.30	53.72	0.80	45.90	45.90	45.92	12.52	13.08	4.46
827_05	68.50	69.50	1.46	55.50	55.50	55.21	18.33	19.57	6.77
827_06	60.40	61.15	1.23	50.40	50.40	50.22	15.29	16.21	6.02
827_07	46.90	46.94	0.08	42.10	42.10	41.94	10.06	10.29	2.24
827_08	37.20	37.42	0.59	36.20	36.10	36.36	6.45	6.31	-2.12
827_09	50.10	50.44	0.68	44.40	44.40	43.97	11.58	11.76	1.51
827_10	69.60	70.54	1.35	56.20	56.20	55.83	18.86	19.98	5.98
827_11	61.90	62.06	0.27	50.60	50.70	50.59	16.50	16.82	1.98
827_12	34.20	34.02	-0.51	34.20	34.20	34.38	5.20	4.97	-4.41
827_13	42.50	42.37	-0.30	38.90	38.90	39.09	8.79	8.62	-1.87
827_14	55.50	55.47	-0.05	46.80	46.80	46.80	13.93	13.99	0.49
827_15	71.80	71.89	0.13	56.80	56.80	56.33	20.27	20.90	3.12
827_16	61.40	61.14	-0.43	50.40	50.40	50.01	16.24	16.47	1.39
827_17	48.00	47.96	-0.08	42.10	42.10	42.26	11.10	11.02	-0.70
827_18	37.40	37.08	-0.86	35.90	35.90	35.99	6.79	6.43	-5.30
827_19	51.30	51.29	-0.01	44.00	44.00	44.05	12.56	12.55	-0.04
827_20	70.10	69.67	-0.61	55.70	55.80	54.91	19.66	20.09	2.17

* There are two pressure taps at the same axial locations but 180 degree apart.

Table 6.4 (Cont'd)

TEST ID	CHANNEL 4 INLET PRESSURE (PSIA)			CHANNEL 4 EXIT PRESSURE (PSIA)*			CHANNEL 4 PRESSURE DROP (PSID)		
	MEAS	CALC	% ERROR	MEAS 1	MEAS 2	CALC	MEAS	CALC	% ERROR
827_01	56.20	56.73	0.95	49.00	49.10	48.71	12.61	13.31	5.56
827_02	31.30	31.56	0.82	33.10	33.10	33.33	3.52	3.51	-0.42
827_03	39.40	39.70	0.75	38.30	38.30	38.32	6.46	6.65	3.06
827_04	49.70	50.39	1.39	44.90	45.10	44.89	10.09	10.78	6.78
827_05	63.30	64.47	1.84	53.80	54.10	53.65	14.85	16.10	8.42
827_06	56.20	57.00	1.42	49.00	49.30	48.94	12.48	13.34	6.87
827_07	44.20	44.34	0.31	41.30	41.40	41.14	8.21	8.49	3.39
827_08	35.50	35.84	0.96	35.70	35.80	35.87	5.09	5.22	2.59
827_09	46.90	47.46	1.19	43.10	43.20	43.05	9.20	9.69	5.35
827_10	64.30	65.39	1.70	54.50	54.80	54.24	15.16	16.43	8.42
827_11	57.50	57.86	0.63	49.40	49.70	49.29	13.43	13.92	3.64
827_12	32.90	32.84	-0.17	33.90	33.90	34.02	4.37	4.15	-5.00
827_13	40.30	40.28	-0.06	38.40	38.50	38.45	7.26	7.17	-1.17
827_14	51.90	52.00	0.19	45.90	46.00	45.73	11.36	11.59	2.00
827_15	66.50	66.64	0.20	55.30	55.50	54.70	16.53	17.26	4.45
827_16	57.10	57.02	-0.13	49.20	49.40	48.74	13.22	13.62	3.09
827_17	45.10	45.25	0.32	41.40	41.50	41.42	9.03	9.14	1.22
827_18	35.70	35.53	-0.47	35.50	35.60	35.52	5.62	5.36	-4.64
827_19	48.10	48.18	0.16	43.10	43.30	43.09	10.26	10.40	1.36
827_20	64.80	64.62	-0.28	54.30	54.50	53.35	15.95	16.60	4.05

* There are two pressure taps at the same axial locations but 180 degree apart.

Table 6.4 (Cont'd)

TEST ID	UPPER PLENUM PRESSURE (PSIA) MEAS	CALC	% ERROR
827_01	68.70	69.10	0.58
827_02	32.70	32.79	0.29
827_03	44.50	44.47	-0.07
827_04	59.40	59.85	0.75
827_05	79.00	80.02	1.29
827_06	68.70	69.38	0.99
827_07	51.30	51.17	-0.25
827_08	38.90	39.02	0.30
827_09	55.40	55.67	0.49
827_10	80.40	81.35	1.18
827_11	70.20	70.36	0.22
827_12	34.80	34.54	-0.73
827_13	45.50	45.24	-0.57
827_14	62.00	61.89	-0.18
827_15	82.80	82.30	0.12
827_16	69.50	69.21	-0.42
827_17	52.50	52.44	-0.12
827_18	39.00	38.54	-1.18
827_19	56.80	56.79	-0.02
827_20	80.70	80.16	-0.68

Table 6.5 Comparisons between the Calculated and Measured Flow Distributions (Tests 827_01 to 827_20)

TEST ID	CHANNEL 2 FLOW DISTRIBUTION			CHANNEL 3 FLOW DISTRIBUTION			CHANNEL 4 FLOW DISTRIBUTION		
	MEAS	CALC	% ERROR	MEAS	CALC	% ERROR	MEAS	CALC	% ERROR
827_01	0.3017	0.3034	0.6	0.4640	0.4561	-1.7	0.2344	0.2406	2.6
827_02	0.2976	0.3041	2.2	0.4713	0.4552	-3.4	0.2311	0.2406	4.1
827_03	0.2981	0.3037	1.9	0.4703	0.4557	-3.1	0.2316	0.2406	3.9
827_04	0.2988	0.3035	1.6	0.4693	0.4560	-2.8	0.2320	0.2406	3.7
827_05	0.2997	0.3033	1.2	0.4689	0.4561	-2.7	0.2314	0.2406	4.0
827_06	0.2992	0.3034	1.4	0.4691	0.4561	-2.8	0.2317	0.2406	3.8
827_07	0.2989	0.3036	1.6	0.4691	0.4558	-2.8	0.2320	0.2406	3.7
827_08	0.2985	0.3039	1.8	0.4705	0.4555	-3.2	0.2311	0.2406	4.1
827_09	0.2971	0.3035	2.2	0.4713	0.4559	-3.3	0.2317	0.2406	3.8
827_10	0.2999	0.3033	1.1	0.4690	0.4562	-2.7	0.2311	0.2406	4.1
827_11	0.2990	0.3038	1.6	0.4701	0.4556	-3.1	0.2309	0.2406	4.2
827_12	0.2981	0.3048	2.3	0.4713	0.4545	-3.6	0.2306	0.2407	4.4
827_13	0.2978	0.3043	2.2	0.4708	0.4550	-3.3	0.2313	0.2406	4.0
827_14	0.2983	0.3039	1.9	0.4700	0.4555	-3.1	0.2317	0.2406	3.9
827_15	0.2989	0.3037	1.6	0.4691	0.4557	-2.8	0.2321	0.2406	3.7
827_16	0.2983	0.3038	1.8	0.4697	0.4556	-3.0	0.2320	0.2406	3.7
827_17	0.2976	0.3041	2.2	0.4710	0.4553	-3.3	0.2314	0.2406	4.0
827_18	0.2971	0.3045	2.5	0.4715	0.4548	-3.5	0.2315	0.2407	4.0
827_19	0.2976	0.3040	2.1	0.4704	0.4554	-3.2	0.2320	0.2406	3.7
827_20	0.2989	0.3037	1.6	0.4695	0.4557	-2.9	0.2316	0.2406	3.9

Table 7.1

Powered Steady State Test Conditions

TEST ID	POWER KW	INNER HEATER	OUTER HEATER	TB PRESS. PSIA	INLET TEMP. F	FLOW GPM
833_01PW1	982.5	ON	ON	28.8	83.3	258.789
833_01PW2	1780.6	ON	ON	28.7	82.9	259.989
833_01PW3	2921.9	ON	ON	28.6	82.6	260.711
833_02PW1	1329.7	ON	ON	28.5	86.6	350.023
833_02PW2	2550.0	ON	ON	28.5	86.5	351.455
833_02PW3	3882.6	ON	ON	28.5	86.3	352.200

Table 7.2
One Heater Powered Steady State Test Conditions and Measured Channel 3
Exit Fluid Temperature

TEST ID	POWER KW	INNER HEATER	OUTER HEATER	TB PRESS PSIA	INLET TEMP F	FLOW GPM	BFTC02 F
833_05PW1	500.3	OFF	ON	28.0	81.0	258.992	99.3
833_05PW2	975.8	OFF	ON	27.9	82.0	256.787	116.4
833_05PW3	1488.6	OFF	ON	27.9	82.3	256.431	134.6
833_05PW4	638.0	OFF	ON	27.9	78.4	345.867	95.3
833_05PW5	1345.7	OFF	ON	27.6	80.2	343.925	115.8
833_05PW6	1984.7	OFF	ON	27.9	81.0	342.204	133.5
833_06PW1	507.9	ON	OFF	27.9	82.7	259.628	99.8
833_06PW2	1022.9	ON	OFF	27.9	82.4	259.360	116.9
833_06PW3	1507.7	ON	OFF	27.8	82.3	258.650	133.2
833_06PW4	667.7	ON	OFF	27.9	82.1	343.392	99.0
833_06PW5	1312.4	ON	OFF	27.8	82.1	343.786	115.5
833_06PW6	2012.4	ON	OFF	27.8	82.1	343.303	133.3

Table 7.3 Measured Pressure (Tests 833_01 to 833_02)

TEST ID	CHANNEL 2-----				CHANNEL 3				CHANNEL 4			
	PRESSURE		PRESSURE		PRESSURE		PRESSURE		PRESSURE		PRESSURE	
	C2DP01* PSID	DROP ** PSID	C2DP03* PSID	DROP ** PSID	C3DP01* PSID	DROP ** PSID	C3DP01* PSID	DROP ** PSID	C4DP01* PSID	DROP ** PSID	C4DP01* PSID	DROP ** PSID
833_01PW1	0.3	5.02	-0.2	5.52	-3.2	8.51	-1.6	6.91				
833_01PW2	0.4	4.91	-0.1	5.41	-3.1	8.39	-1.5	6.80				
833_01PW3	0.5	4.79	-0.1	5.39	-2.9	8.16	-1.4	6.67				
833_02PW1	-3.3	8.61	-4.0	9.31	-9.2	14.51	-6.5	11.81				
833_02PW2	-3.2	8.50	-3.9	9.20	-9.1	14.39	-6.5	11.79				
833_02PW3	-3.0	8.28	-3.7	8.98	-8.9	14.16	-6.5	11.77				

TEST ID	CHANNEL 2				CHANNEL 3				CHANNEL 4			
	DENSITY		ELEVATION		DENSITY		ELEVATION		DENSITY		ELEVATION	
	LB/FT3	LOSS (PSID)	LB/FT3	LOSS (PSID)	LB/FT3	LOSS (PSID)	LB/FT3	LOSS (PSID)	LB/FT3	LOSS (PSID)	LB/FT3	LOSS (PSID)
833_01PW1	62.063	5.316	61.991	5.309	62.021	5.312	61.851	5.297	62.021	5.312	61.851	5.297
833_01PW2	61.942	5.305	61.792	5.292	61.851	5.297	61.554	5.272	61.851	5.297	61.554	5.272
833_01PW3	61.733	5.287	61.448	5.263	61.950	5.306	61.977	5.308	61.977	5.308	61.977	5.308
833_02PW1	62.023	5.312	61.712	5.286	61.776	5.291	61.504	5.268	61.776	5.291	61.504	5.268
833_02PW2	61.877	5.300	61.408	5.259								
833_02PW3	61.691	5.284										

* MEASURED STATIC PRESSURE DIFFERENCE BETWEEN THE PRESSURE TAPS

** MEASURED PRESSURE DROP = ELEVATION LOSS - STATIC PRESSURE DIFFERENCE

ELEVATION LOSS = DENSITY * 148 / 12 / 144 (psi)

DENSITY = THE AVERAGE DENSITY OF THE CHANNEL INLET AND OUTLET

Table 7.4 Measured Flow Distributions (Tests 833_01 to 833_02)

TEST ID	PITOT TUBE MEASUREMENT (PSID)		FLOW DISTRIBUTIONS			
	C2DP02	C3DP02	C4DP02	CHANNEL 2	CHANNEL 3	CHANNEL 4
	CHANNEL 2	CHANNEL 3	CHANNEL 4			
833_01PW1	2.2	2.0	3.2	0.2969	0.4732	0.2299
833_01PW2	2.2	2.1	3.2	0.2935	0.4792	0.2273
833_01PW3	2.2	2.1	3.2	0.2935	0.4792	0.2273
833_02PW1	4.0	3.7	5.8	0.2958	0.4755	0.2287
833_02PW2	4.1	3.7	5.9	0.2978	0.4728	0.2294
833_02PW3	4.1	3.8	5.9	0.2959	0.4761	0.2279

FLOW DISTRIBUTION (i) = A(i) * SQRT[PITOT(i)] / SUM
SUM = SUMMATION(A(i) * SQRT[PITOT(i)]) i=2, 3, 4
A(2) = 0.3420 ; A(3) = 0.5716 ; A(4) = 0.2196

Table 7.5

Comparisons between the Calculated and the Measured Pressures (Tests 833_01 to 833_02)

TEST ID	CHANNEL 2 INLET PRESSURE (PSIA)*		CHANNEL 2 EXIT PRESSURE (PSIA)*		CHANNEL 2 PRESSURE DROP (PSID)*	
	MEAS 1	MEAS 2	CALC	MEAS 1	MEAS 2	CALC
833_01PW1	40.6	40.9	40.92	40.8	40.7	40.96
833_01PW2	40.5	40.8	40.95	40.8	40.8	41.05
833_01PW3	40.5	40.8	40.99	40.9	40.8	41.13
833_02PW1	54.7	55.3	55.27	51.4	51.3	51.29
833_02PW2	54.8	55.4	55.50	51.7	51.5	51.62
833_02PW3	54.8	55.5	55.71	51.9	51.8	51.90

* There are two pressure taps at the same axial location but 180° apart.

Table 7.5 (Cont'd)

TEST ID	CHANNEL 3 INLET PRESSURE (PSIA)		% ERROR	CHANNEL 3 EXIT PRESSURE (PSIA)*		MEAS 1	MEAS 2	CALC	CHANNEL 3 PRESSURE DROP (PSID)	
	MEAS	CALC		MEAS 1	MEAS 2				MEAS	CALC
833_01PW1	43.0	43.17	0.4	39.7	39.7	39.7	39.7	39.95	8.51	8.53
833_01PW2	42.9	43.18	0.7	39.8	39.7	39.7	39.7	40.02	8.39	8.45
833_01PW3	42.9	43.21	0.7	39.9	39.9	39.9	39.9	40.10	8.16	8.37
833_02PW1	58.9	59.36	0.8	49.5	49.5	49.5	49.5	49.43	14.51	15.23
833_02PW2	58.9	59.54	1.1	49.8	49.8	49.8	49.8	49.74	14.39	15.08
833_02PW3	59.0	59.73	1.2	50.0	50.0	50.0	50.0	50.01	14.16	14.97

* There are two pressure taps at the same axial location but 180° apart.

Table 7.5 (Cont'd)

TEST ID	CHANNEL 4 INLET PRESSURE (PSIA)			CHANNEL 4 EXIT PRESSURE (PSIA)*			CHANNEL 4 PRESSURE DROP (PSID)		
	MEAS	CALC	% ERROR	MEAS 1	MEAS 2	CALC	MEAS	CALC	% ERROR
833_01PW1	40.6	41.06	1.1	39.0	39.1	39.27	6.91	7.10	2.8
833_01PW2	40.5	41.08	1.4	39.0	39.1	39.34	6.80	7.05	3.6
833_01PW3	40.4	41.11	1.8	39.1	39.2	39.40	6.67	6.98	4.7
833_02PW1	54.7	55.51	1.5	48.2	48.3	48.19	11.81	12.63	6.9
833_02PW2	54.7	55.71	1.8	48.3	48.4	48.49	11.79	12.51	6.1
833_02PW3	54.7	55.91	2.2	48.4	48.6	48.74	11.77	12.44	5.7

* There are two pressure taps at the same axial location but 180° apart.

Table 7.5 (Cont'd)

TEST ID	UPPER PLENUM PRESSURE		
	MEAS PSIA	CALC PSIA	% ERROR
833_01PW1	46.2	46.32	0.3
833_01PW2	46.2	46.41	0.5
833_01PW3	46.2	46.48	0.6
833_02PW1	66.7	67.18	0.7
833_02PW2	66.8	67.49	1.0
833_02PW3	67.0	67.75	1.1

Table 7.6

Comparisons between the Measured and Calculated Flow Distributions (Tests 833_01 to 833_02)

TEST ID	CHANNEL 2 FLOW FRACTION			CHANNEL 3 FLOW FRACTION			CHANNEL 4 FLOW FRACTION		
	MEAS	CALC	% ERROR	MEAS	CALC	% ERROR	MEAS	CALC	% ERROR
833_01PW1	0.2969	0.3016	1.6	0.4732	0.4584	-3.1	0.2299	0.2400	4.4
833_01PW2	0.2935	0.3003	2.3	0.4792	0.4600	-4.0	0.2273	0.2397	5.5
833_01PW3	0.2935	0.2990	1.9	0.4792	0.4616	-3.7	0.2273	0.2394	5.3
833_02PW1	0.2958	0.3012	1.8	0.4755	0.4588	-3.5	0.2287	0.2400	4.9
833_02PW2	0.2978	0.2998	0.7	0.4728	0.4605	-2.6	0.2294	0.2396	4.5
833_02PW3	0.2959	0.2987	0.9	0.4761	0.4619	-3.0	0.2279	0.2394	5.0

Table 9.1

Quasi Steady State Power Ramp Results

TEST ID	OFI MEASUREMENTS		OSV CALCULATIONS	
	POWER (KW)	TIME (SEC)	POWER (KW)	TIME (SEC)
836_01	2790.0	46.4	2653.0	38.37
836_02	2823.0	42.0	2556.0	31.57
836_03	3078.0	58.4	2797.0	41.48
836_04	3942.0	9.8	3654.0	0.14
836_05	3783.0	35.2	3588.0	22.82
836_06	2588.0	35.1	2372.0	21.08
836_07	4170.0	48.7	3645.0	28.92

Table 10.1
FLOWTRAN Calculations of the OSV Power for B&W LOCA Tests

TEST ID	INLET TEMP. (F)	POWER DECAY	FI STATUS	TEST POWER (MW)	FLOWTRAN CALCULATIONS (PEAKING FACTOR = 1.0) OSV POWER (MW)	MARGIN*
867_03	124.5	NORMAL	NO	3.31	3.424	
867_04	127.4	NORMAL	YES	4.34	3.434	20.9
867_05	123.6	NORMAL	NO	4.05	3.529	
867_06	123.7	FAST	NO	4.50	4.020	
867_07	123.6	NORMAL	YES	4.33	3.513	18.9
867_08	81.6	NORMAL	YES	5.32	4.612	13.3**
867_09	81.4	NORMAL	NO	4.93	4.505	
867_10	123.3	NORMAL	YES	4.28	3.427	19.9
867_11	123.3	NORMAL	YES	4.28	3.549	17.1
867_12	122.9	NORMAL	YES	4.58	3.483	24.0
867_13	81.7	NORMAL	YES	5.35	4.405	17.7
867_14	124.6	FAST	NO	4.53	3.696	
867_15	124.1	NORMAL	YES	4.10	3.256	20.6
867_16	124.1	FAST	YES	4.75	3.802	20.0**
867_17	123.2	FAST	NO	4.60	3.997	
867_18	80.7	FAST	NO	6.04	5.183	15.6
867_19	81.3	NORMAL	YES	5.21	4.397	
867_20	81.7	NORMAL	NO	5.13	4.642	17.3**
867_21	81.6	FAST	YES	6.23	5.155	17.9
867_22	125.3	NORMAL	YES	4.04	3.316	13.3**
867_23	122.8	NORMAL	YES	4.03	3.495	

* MARGIN = (Test Power - OSV Power) / Test Power x 100%

** Test conditions were close to the threshold of OFI.

Table 11.1

FLOWTRAN Calculations of the OSV Power for B&W LOCA Tests
(WITH MEASUREMENT UNCERTAINTIES)

TEST ID	INLET TEMP.	TEST POWER (MW)	POWER DECAY	FI STATUS	CALCULATIONS FOR OSV POWER (MW) (PEAKING FACTOR = 1.0)		
					MINIMUM	NORMAL	MAXIMUM
867_03	124.5	3.31	NORMAL	NO	3.393	3.424	3.455
867_04	127.4	4.34	NORMAL	YES	3.408	3.434	3.460
867_05	123.6	4.05	NORMAL	NO	3.502	3.529	3.557
867_06	123.7	4.50	FAST	NO	3.994	4.020	4.047
867_07	123.6	4.33	NORMAL	YES	3.486	3.513	3.541
867_08	81.6	5.32	NORMAL	YES	4.574	4.612	4.653
867_09	81.4	4.93	NORMAL	NO	4.465	4.505	4.546
867_10	123.3	4.28	NORMAL	YES	3.394	3.427	3.461
867_11	123.3	4.28	NORMAL	YES	3.519	3.549	3.580
867_12	122.9	4.58	NORMAL	YES	3.457	3.483	3.510
867_13	81.7	5.35	NORMAL	YES	4.430	4.405	4.501
867_14	124.6	4.53	FAST	NO	3.669	3.696	3.724
867_15	124.1	4.10	NORMAL	YES	3.229	3.256	3.284
867_16	124.1	4.75	FAST	YES	3.774	3.802	3.832
867_17	123.2	4.60	FAST	NO	3.970	3.997	4.023
867_18	80.7	6.04	FAST	NO	5.151	5.183	5.217
867_19	81.3	5.21	NORMAL	YES	4.359	4.397	4.437
867_20	81.7	5.13	NORMAL	NO	4.602	4.642	4.680
867_21	81.6	6.23	FAST	YES	5.122	5.155	5.189
867_22	125.3	4.04	NORMAL	YES	3.290	3.316	3.343
867_23	122.8	4.03	NORMAL	YES	3.469	3.495	3.523

Table 12.1

Revised Downflow Test Assembly Channel Surface Roughness and Local
Form Loss

<u>Channel</u>	<u>Roughness</u> <u>in</u>	<u>Local Form Loss (psi/(100 gpm)²)</u>		
		<u>Channel inlet</u>	<u>Inside Channel</u>	<u>Channel Exit</u>
1	6.0E-04	80.000	0.000	0.1000
2	6.0E-04	21.000	0.030	6.0000
3	6.0E-04	4.300	0.000	2.1000
4	6.0E-04	14.000	0.065	0.5000
5	6.0E-04	12000.000	0.000	70.0000

Table 12.2
Flows and Pressures Calculated by the Revised FLOWTRAN Model for
Test 833_01PW1

		<u>OLD MODEL</u>	<u>REVISED MODEL</u>
Inlet Temperature	(F)	83.3*	83.3*
Tank Bottom Pressure	(psia)	28.8*	28.8*
Assembly Inlet Flow	(gpm)	258.78893*	258.78893*
Assembly Power	(KW)	982.5*	982.5*
Upper Plenum Pressure	(psia)	46.31963	46.31965
Channel 2 inlet pressure	(psia)	40.91598	40.92295
Channel 2 Exit Pressure	(psia)	40.96108	40.95936
Channel 3 Inlet Pressure	(psia)	43.16984	43.17000
Channel 3 Exit Pressure	(psia)	39.94538	39.94538
Channel 4 Inlet Pressure	(psia)	41.06194	41.05534
Channel 4 Exit Pressure	(psia)	39.26991	39.26905
Channel 1 Inlet Flow	(gpm)	2.08949	34.43284
Channel 2 Inlet Flow	(gpm)	66.85742	66.82006
Channel 3 Inlet Flow	(gpm)	101.33618	101.33434
Channel 4 Inlet Flow	(gpm)	53.11719	53.14608
Channel 5 Inlet Flow	(gpm)	35.38864	3.05560

* FLOWTRAN input values

Figure 2.1 Cross-Section View of Mock-Up Test Assembly

Figure 2.2 Model Axial Power Profiles for the Inner and Outer Heater Tubes.

Figure 2.3 Heater and Target Tube Rib Details

	CERAMIC RIB			METAL CLIP			MATERIAL
	W	H	C	t	h	r	
INNER TARGET	0.1575	0.237	0.0313	0.016	0.125	0.0313	6061 ALUMINUM
INNER HEATER	0.1575	0.265	0.0313	0.015	0.125	0.0313	304 STAINLESS
OUTER HEATER	0.1650	0.206	0.0156	0.015	0.125	0.0156	304 STAINLESS

Figure 2.4 Test Facility Schematic

Figure 2.5 Top Fitting Instruments

Top Fitting Instruments

Mark 22 Model
Fuel Assembly

Ⓐ ABSOLUTE PRESSURE
➤ THERMOCOUPLE JUNCTION

Ⓓ DIFFERENTIAL PRESSURE
⊞ RESISTANCE TEMPERATURE DETECTOR

Figure 2.6 Channel 2 Pressure and Differential Pressure Taps

Figure 2.7 Channel 2 and Outer Heater Tube Instruments

Figure 2.8 Channel 3 Pressure and Differential Pressure Taps

Figure 2.9 Channel 3 and Inner Heater Tube Instruments

Figure 2.10 Channel 4 Pressure and Differential Pressure Taps

Figure 2.11 Channel 4 and Inner Target Tube Instruments

Figure 2.12 Bottom Fitting Instruments

Figure 6.1

UPPER PLENUM PRESSURE VS. ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

Figure 6.2

**CHANNEL 2 PRESSURE DISTRIBUTIONS VS. ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.3

**CHANNEL 3 PRESSURE DISTRIBUTIONS VS. ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.4

**CHANNEL 4 PRESSURE DISTRIBUTIONS VS. ASSEMBLY FLOW
TEST 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.5

CHANNEL PRESSURE DROP VS. ASSEMBLY FLOW
TESTS 827_01 TO 827_10
INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

Figure 6.6

**UPPER PLENUM PRESSURE VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.7

**CHANNEL 2 PRESSURE DISTRIBUTIONS VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.8

**CHANNEL 3 PRESSURE DISTRIBUTIONS VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.9

**CHANNEL 4 PRESSURE DISTRIBUTIONS VS. ASSEMBLY FLOW
TEST 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.10

**CHANNEL PRESSURE DROP VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA**

Figure 6.11

FLOW SPLIT VS. ASSEMBLY FLOW

TEST 827_01 TO 827_10

INLET TEMP. 125 F ; TANK BOTTOM PRESS. 28.5 PSIA

Figure 6.12

FLOW SPLIT VS. ASSEMBLY FLOW
TESTS 827_11 TO 827_20
INLET TEMP. 80 F ; TANK BOTTOM PRESS. 28.5 PSIA

Figure 7.1 Section View of Mock-Up Test Assembly Depicting Channel Fluid Thermocouple Locations

AIM

Association for Information and Image Management

1100 Wayne Avenue, Suite 1100
Silver Spring, Maryland 20910
301/587-8202

Centimeter

Inches

MANUFACTURED TO AIM STANDARDS
BY APPLIED IMAGE, INC.

---

2 of 2

Figure 7.2

**MEASURED CHANNEL FLUID TEMPERATURE
833_06PW6, INNER HEATER POWERED**

Figure 7.3

**MEASURED CHANNEL FLUID TEMPERATURE
833_05PW6 OUTER HEATER POWERED**

Figure 7.4

**CHANNEL FLUID TEMPERATURE
TEST 833_06PW6, INNER HEATER POWERED**

* Measurement biases were added to the T/C readings
to account for channel fluid temperature gradients

Figure 7.5

**CHANNEL FLUID TEMPERATURE
TEST 833_05PW6, OUTER HEATER POWERED**

* Measurement biases were added to the T/C readings to account for channel fluid temperature gradients

Figure 7.6

Figure 7.7

Figure 7.8

**CHANNEL FLUID TEMPERATURE,
TEST 833_01PW3**

Figure 7.9

Figure 7.10

**CHANNEL FLUID TEMPERATURE
TEST 833_02PW2**

Figure 7.11

**CHANNEL FLUID TEMPERATURE
TEST 833_02PW3**

Figure 7.12

**CHANNEL FLUID TEMPERATURE
TEST 833_01PW1 (WITH T/C CORRECTIONS)**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 7.13

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 7.14

Figure 7.15

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 7.16

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 7.17

Figure 7.18

Figure 7.19

**CHANNEL 3 PRESSURE DROP
TEST 833_01 AND 833_02**

Figure 7.20

**CHANNEL 4 PRESSURE DROP
TESTS 833_01 AND 833_02**

Figure 7.21

Figure 8.1

**MEASURED PRESSURE BOUNDARY CONDITIONS
TEST 867_02**

Figure 8.2

**MEASURED POWER DECAY
TEST 867_02**

Figure 8.3 Test Section Inlet Flow(Test 867_02)

Figure 8.4

Figure 8.5

**STATIC PRESSURE AT CHANNEL 2 INLET
TEST 867_02**

Figure 8.6

**STATIC PRESSURE AT CHANNEL 2 OUTLET
TEST 867_02**

Figure 8.7

**STATIC PRESSURE AT CHANNEL 3 INLET
TEST 867_02**

Figure 8.8

**STATIC PRESSURE AT CHANNEL 3 OUTLET
TEST 867_02**

Figure 8.9

**STATIC PRESSURE AT CHANNEL 4 INLET
TEST 867_02**

Figure 8.10

**STATIC PRESSURE AT CHANNEL 4 OUTLET
TEST 867_02**

Figure 8.11

**CHANNEL 2 FLUID TEMPERATURE AT T/C LOCATIONS
TEST 867_02**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READING TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 8.12

**CHANNEL 3 FLUID TEMPERATURE AT T/C LOCATIONS
TEST 867_02**

Figure 8.13

**CHANNEL 4 FLUID TEMPERATURE AT T/C LOCATIONS
TEST 867_02**

* MEASUREMENT BIASES WERE ADDED TO THE T/C READING TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 9.1 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_01

Figure 9.2 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_02

Figure 9.3 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_03

Figure 9.4 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_04

Figure 9.5 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_05

Figure 9.6 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_06

Figure 9.7 Variation of Power, Flow, Void Fraction, and Calculated Stanton Number for Power Ramp Test 836_07

Figure 10.1 Time Variations of Flow, Void Fraction, Pitot Tube, and Power for LOCA Test 867_04

Figure 10.2

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_04 (PEAKING FACTOR=1.0)**

Figure 10.3

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_07 (PEAKING FACTOR=1.0)**

Figure 10.4

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_08 (PEAKING FACTOR=1.0)**

Figure 10.5

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_10 (PEAKING FACTOR=1.0)**

Figure 10.6

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_11 (PEAKING FACTOR=1.0)**

Figure 10.7

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_12 (PEAKING FACTOR=1.0)**

Figure 10.8

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_13 (PEAKING FACTOR=1.0)**

Figure 10.9

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_15 (PEAKING FACTOR=1.0)**

Figure 10.10

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_19 (PEAKING FACTOR=1.0)**

Figure 10.11

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_22 (PEAKING FACTOR=1.0)**

Figure 10.12

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_23 (PEAKING FACTOR=1.0)**

Figure 10.13

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_16 (PEAKING FACTOR=1.0)**

Figure 10.14

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 867_21 (PEAKING FACTOR=1.0)**

Figure 11.1 Absolute Pressure Measurement Uncertainty

Figure 11.2 Measurement Uncertainty for Resistance Temperature Detector.

Figure 11.3 Uncertainty in Total Flow

Figure 11.4 Uncertainty in Total Power

Figure 11.5

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_01 (PEAKING FACTOR=1.0)**

Figure 11.6

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_02 (PEAKING FACTOR=1.0)**

Figure 11.7

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_03 (PEAKING FACTOR=1.0)**

Figure 11.8

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_04 (PEAKING FACTOR=1.0)**

Figure 11.9

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_05 (PEAKING FACTOR=1.0)**

Figure 11.10

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_06 (PEAKING FACTOR=1.0)**

Figure 11.11

**VARIATION OF CALCULATED STANTON NUMBER
DUE TO THE MEASUREMENT UNCERTAINTIES
B&W TEST 836_07 (PEAKING FACTOR=1.0)**

**FLOWTRAN CALCULATIONS OF OSV POWER FOR
B&W LOCA TESTS WITH A PEAKING FACTOR OF 1.0
(NORMAL POWER DECAY)**

Figure 11.13

**FLOWTRAN CALCULATIONS OF OSV POWER FOR
B&W LOCA TESTS WITH A PEAKING FACTOR OF 1.0
(FAST POWER DECAY)**

Figure 12.1
CHANNEL FLUID TEMPERATURE
LEAKAGE FLOW IN CHANNEL 1
TEST 833_01PW1 (WITH T/C CORRECTIONS)

* MEASUREMENT BIASES WERE ADDED TO THE T/C READINGS TO ACCOUNT FOR CHANNEL FLUID TEMPERATURE GRADIENTS, EXCEPT FOR T/Cs OUTSIDE THE HEATED LENGTH

Figure 12.2

**FLOWTRAN CALCULATIONS FOR STANTON NUMBER
TEST 836_01 (PEAKING FACTOR=1.0)
(LEAKAGE FLOW IN CHANNEL 1)**

APPENDIX A FLOWTRAN INPUT FOR UPFLOW TEST 039_04

```

/1. B&W UP 039_04 POST/
/2. RUN TIME SEC, NZONE, TMIN, TIME ZONE DATA/
0.0 1 0.0
9000.0 1000.0
/IPRTF, IPRTS, IP RTP, IDMPS, IBALN, ICRIT, IPRTSS, IPTIME, IPTER/
1 1 1
1000 1000 1 1 0 0
/4. CRITERIA CHECKING FLAGS: ONB, TSAT, CHF, TMAX/
0 0 0 0 0
/5. TOLERANCES, ITERATIONS, AND INITIAL POWER/
1.0D-4 0 0.0
1.0D-5 100
1.0D-5 100
/6. FLUID ITERATIONS, TOLERANCES, AND OPTIONS/
1 1 1.0D-06
1 1 1.0D-06
1 1 1 2 1 2 1 0 0
1 1
/7. POWER ARRAY PARAMETERS/
3 3 1
5 5 2 2 1 5 2 2 5 1 1 1
/8. MA MCYLN ICENT AND NCELLS/
1 5 0
7 42 11
/9. RADIAL CELLS AND SUBCHANNELS/
5 5 5 5 3
1 1 1 1 1
/10. SURFACE CHECK FLAGS/
000111 10000
1.01460 0.4546 0.4546 0.5163 0.5163
0.4335 0.4335 0.295 0.295 0.295
/11. CYLINDER #1/
1.0 1
2 0.265 .07875
402 2 2 2 2
1.460
1.52287
1.58574
1.64861
1.71148
1.77435
/CYLINDER #2/
28.0 3
2 .237 0.07875
4 9 9 9 9
36 6 6 6 6 6
40 9 9 9 9 9
2.31185
2.33088
2.34991

```

2.36894
 2.38797
 2.407
 /CYLINDER #3/
 28.0 3
 2 0.206 0.0825
 4 9 9 9 9
 36 6 6 6 6 6
 40 9 9 9 9 9
 2.997
 3.0106
 3.0242
 3.0378
 3.0514
 3.065
 /CYLINDER #4/
 1.0 1
 0 0.0 0.0
 40 2 2 2 2 2
 3.5376
 3.57008
 3.60256
 3.63504
 3.66752
 3.700
 /CYLINDER #5/
 0.0 1
 -1 0.135 0.03
 40 2 2 2
 4.010
 4.040
 4.080
 4.110
 /12. FLUID GEOMETRIC DATA SET/
 161.53 143.15 9.0 22.0 -1.0
 27.00 27.00
 0.10000 0.19900 0.32400 0.27700 0.10000
 0.10000 0.19900 0.32400 0.27700 0.10000
 1.674155 1.5484 2.3228 2.3020 1.840
 1.460 0.4546 0.5163 0.4335 0.295
 5000.0 7.5 2.750 11.0 31100.0
 0.0 0.0650 0.0 0.03 0.0
 70.0 1.1404 16 4.0 0.1
 6.0000D-04 6.0D-04 6.0D-04 6.0D-04 6.0D-04
 1 249.983 27.0000 0.000 0.000 1.000
 1 286.7017 27.0000 24.000 0.000 0.0
 2 213.1628 11.9459 0.000 -1.000 0.000
 2 139.6238 11.9459 11.688 0.000 0.0
 3 70.5585 11.9459 0.000 -1.000 0.000
 3 14932 11.9459 0.125 0.000 0.0
 4 60.4763 11.9459 0.000 -1.000 0.000
 4 119.4591 11.9459 10.000 0.000 0.0
 5 126.1786 11.9459 0.000 -1.000 0.000
 5 132.8982 11.9459 11.125 0.000 0.0

6	67.1957	11.9459	0.000	-1.000	0.000
6	1.4932	11.9459	0.125	0.000	0.0
7	88.4774	11.9459	0.000	-1.000	0.000
7	175.4615	11.9459	14.688	0.000	0.0
1	56.7550	11.9459	4.751	0.00	0.0
1	29.1241	11.9459	0.000	-1.00	0.400
2	1.4932	11.9459	0.125	0.00	0.0
2	60.4762	11.9459	0.000	-1.00	0.010
3	119.4591	11.9459	10.000	0.00	0.0
3	134.7677	11.9459	0.000	-1.00	1.000
4	150.0764	11.9459	12.563	0.00	0.0
4	134.7677	11.9459	0.000	-1.00	6.200
5	119.4591	11.9459	10.000	0.00	0.0
5	119.4591	11.9459	0.000	-1.00	6.000
6	119.4591	11.9459	10.000	0.00	0.0
6	119.4591	11.9459	0.000	-1.00	1.000
7	119.4591	11.9459	10.000	0.00	0.0
7	60.4762	11.9459	0.000	-1.00	1.000
8	1.4932	11.9459	0.125	0.00	0.0
8	70.5585	11.9459	0.000	-1.00	0.010
9	139.6238	11.9459	11.688	0.00	0.0
9	213.1628	11.9459	0.000	-1.00	1.100
10	286.7018	11.9459	24.000	0.00	0.0
10	146.5571	27.0000	0.000	0.00	2.400
11	6.4125	27.0000	0.2375	0.00	0.0
11	50.0000	27.0000	0.000	0.00	0.140
1.0	1.5	1.5	1.5	1.5	0.14

/14. POWER FRACTIONS MEASURED/

5 1

0.0	0.0	0.0	0.0
0.52	0.0	0.0	0.0
0.48	0.0	0.0	0.0
0.0	0.0	0.0	0.0
0.0	0.0	0.0	0.0

/15. RADIAL SHAPES /

5 3 3

1	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
2	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
3	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
4	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
5	0	0	0	0
1.0	0.0	0.0	0.0	0.0

```

1.0 0.0 0.0
1.0 0.0 0.0
/WET TANK SHAPE POWER FRACTIONS/
0
/DRY TANK SHAPE POWER FRACTIONS/
0
/16. AZIMUTHAL SHAPES /
1 1 5
1 2 3 4 5
1.
1. 1. 1. 1. 1.
/19. DRY DECAYH RESPON/
6
0.0      10000
1000.0    1.0000
2000.0    1.0000
3000.0    1.0000
4000.0    1.0000
9000.0    1.0000
/20. AXIAL POWR RESPON WORST COS 9-88/
22 3
0.0      1000.0      10000.0
.00      .00
.047619   .32
.095238   .55
.142857   .78
.190478   .99
.238095   1.08
.285714   1.16
.333333   1.22
.380952   1.28
.428571   1.30
.476190   1.32
.523810   1.32
.571429   1.30
.619048   1.28
.666667   1.22
.714286   1.16
.761905   1.08
.809524   0.99
.857143   0.78
.904762   0.55
.952381   0.32
1.0      0.00
0.00 0.32 0.55 0.78 0.99 1.08 1.16 1.22 1.28 1.30 1.32
1.32 1.30 1.28 1.22 1.16 1.08 0.99 0.78 0.55 0.32 0.00
0.00 0.32 0.55 0.78 0.99 1.08 1.16 1.22 1.28 1.30 1.32
1.32 1.30 1.28 1.22 1.16 1.08 0.99 0.78 0.55 0.32 0.00
/21. INLET FLOW/
6
0.000000   310.43
1000.000   310.43
2000.000   310.43
3000.000    80.0

```

```

4000.000  80.0
9000.000  80.0
/22. TANK BOT PRESS TRANS HARD/
6
0.000000  89.37
1000.0    89.37
2000.0    89.37
3000.0    89.37
4000.0    89.37
9000.0    89.37
/23. ASS TINLET TRANSIENT/
6
0.00000  27.461111
1000.00  27.461111
2000.00  27.461111
3000.00  27.461111
4000.00  51.666667
9000.00  51.666667
/TANK LEVEL TRANSIENT/
3
0.0      10000
1000.0   10000
9000.0   10000
/25. FLUID INITIAL GUESS DATA/
0.0056 0.1158 0.318 0.39 0.1752
310.43 88.00000 27.461111 0.0
0.0019 0.1818 0.5015 0.3071 0.0077
0.0D0  0.0D0  0.0D0
0.0  30.0  19.7 3.937D-05
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
/INITIAL SOLID TEMPERATURES/
27.461111 27.461111

```

APPENDIX B FLOWTRAN INPUT FOR DOWNFLOW TEST 827_19

```

/B&W SIMULATES MARK22 827_19 USE UPFLOW LOSSES/
/RUN TIME SEC, NZONE, TMIN, TIME ZONE DATA/
0.0 1 0.0
10.0 0.10
/IPRTF, IPRTS, IP RTP, IDMPS, IBALN, ICRIT, IPRTSS/
1000 1000 1000
1000 1000 1 1 0 0
/CRITERIA CHECKING FLAGS: ONB, TSAT, CHF/
0 0 0 0 0
/TOLERANCES, ITERATIONS, AND INITIAL POWER/
1.0D-4 20 0.0
1.0D-5 100
1.0D-5 100
/FLUID ITERATIONS, TOLERANCES, AND OPTIONS/
1 1 1.0D-06
1 1 1.0D-06
1 1 1 2 1 2 1 0 0
1 0
/POWER ARRAY PARAMETERS/
3 1 1
105 105 2 21 2 2 2 29 1 1 1
/MA MCYLN ICENT AND NCELLS/
1 5 0
7 42 13
/RADIAL CELLS AND SUBCHANNELS/
5 5 5 5 3
1 1 1 1 1
/SURFACE CHECK FLAGS/
000111 10000
1.01460 0.4546 0.4546 0.5163 0.5163
0.4335 0.4335 0.295 0.295 0.295
/CYLINDER #1/
1.0 1
1 0.265 0.07875
402 2 2 2 2
1.460
1.52287
1.58574
1.64861
1.71148
1.77435
/CYLINDER #2/
28.0 3
1 0.237 0.07875
4 9 9 9 9
36 6 6 6 6 6
409 9 9 9 9
2.31185
2.33088
2.34991

```

2.36894
 2.38797
 2.407
 /CYLINDER #3/
 28.0 3
 1 0.206 0.0825
 4 9 9 9 9
 36 6 6 6 6
 40 9 9 9 9
 2.997
 3.0106
 3.0242
 3.0378
 3.0514
 3.065
 /CYLINDER #4/
 1.0 1
 0 0.0 0.0
 40 2 2 2 2
 3.5376
 3.57008
 3.60256
 3.63504
 3.66752
 3.700
 /CYLINDER #5/
 0.0 1
 -1 0.135 0.03
 40 2 2 2
 4.010
 4.040
 4.080
 4.110
 /FLUID GEOMETRIC DATA SET/
 161.595 143.0 8.995 22.0 1.0
 13.254 99.903
 0.10000 0.19900 0.32400 0.27700 0.10000
 0.10000 0.19900 0.32400 0.27700 0.10000
 1.674155 1.5484 2.3228 2.3020 1.840
 1.460 0.4546 0.5163 0.4335 0.295
 75.0 14.0 4.300 21.0 31100.0
 0.0 0.0650 0.0 0.03 0.0
 10.0 0.5000 2.1 6.0 0.1
 6.0000D-04 6.0D-04 6.0D-04 6.0D-04 6.0D-04
 1 249.983 13.254 0.0 0.000 2.605
 1 109.956 13.254 8.75 0.0 0.0
 2 141.372 12.566 0.0 1.000 0.000
 2 172.788 12.566 13.75 0.0 0.0
 3 151.550 12.566 0.0 1.000 0.000
 3 130.313 12.566 10.37 0.0 0.0
 4 144.827 12.566 0.0 1.000 0.000
 4 159.342 12.566 12.68 0.0 0.0
 5 123.101 11.781 0.0 1.000 2.380
 5 71.476 7.839 10.50 0.0 0.0

6	60.571	4.832	0.0	1.000	0.002
6	65.052	7.839	9.75	0.0	0.0
7	39.570	8.884	0.0	1.000	0.010
7	17.768	8.884	2.00	0.0	0.0
1	17.768	8.884	2.00	0.0	0.0
1	13.959	8.884	0.0	1.000	0.0
2	10.149	8.982	1.13	0.0	0.0
2	7.340	9.079	0.0	1.000	0.0
3	4.421	6.801	0.65	0.0	0.0
3	3.342	4.524	0.0	1.000	0.000
4	2.262	4.524	0.50	0.0	0.0
4	4.166	4.524	0.0	1.000	0.000
5	6.070	5.781	1.05	0.0	0.0
5	5.946	7.037	0.0	1.000	0.000
6	5.821	7.277	0.80	0.0	0.0
6	3.269	2.867	0.0	1.000	10.50
7	0.717	2.867	0.25	0.0	0.0
7	3.563	2.867	0.0	1.000	0.000
8	6.409	8.011	0.80	0.0	0.0
8	3.563	2.867	0.0	1.000	0.000
9	0.717	2.867	0.25	0.0	0.0
9	2.362	2.867	0.0	1.000	0.000
10	4.006	8.011	0.50	0.0	0.0
10	8.212	8.011	0.0	1.000	0.000
11	12.417	8.011	1.55	0.0	0.0
11	16.823	8.011	0.0	1.000	0.000
12	21.229	8.011	2.65	0.0	0.0
12	11.164	4.396	0.0	0.000	30.95
13	1.099	4.396	0.25	0.0	0.0
13	2.389	4.396	0.0	0.000	0.000
1.0	1.5	1.5	1.5	1.5	0.14

/POWER FRACTIONS /

5 1

0.0	0.0	0.0	0.0
0.5	0.0	0.0	0.0
0.5	0.0	0.0	0.0
0.0	0.0	0.0	0.0
0.0	0.0	0.0	0.0

/RADIAL SHAPES /

5 3 3

1	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
2	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
3	0	0	0	0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
1.0	0.0	0.0	0.0	0.0
4	0	0	0	0
0	0.0	0.0	0.0	0.0


```

1.0 0.0 0.0
1.0 0.0 0.0
5 0 0 0
1.0 0.0 0.0
1.0 0.0 0.0
1.0 0.0 0.0
/WET TANK SHAPE POWER FRACTIONS/
0
/DRY TANK SHAPE POWER FRACTIONS/
0
/AZIMUTHAL SHAPES /
1 1 5
1 2 3 4 5
1.
1. 1. 1. 1. 1.
/DRY DECAYH RESPONSH/
30
0.0 1.0000
0.1 0.99953
0.2 0.99735
0.3 0.99334
0.4 0.98855
0.5 0.98373
0.6 0.97938
0.7 0.97560
0.8 0.97026
0.9 0.94883
1.0 0.88044
1.1 0.75652
1.2 0.60868
1.3 0.44966
1.4 0.31654
1.5 0.25682
1.6 0.23043
1.8 0.21816
2.0 0.20886
2.2 0.19412
2.4 0.18437
2.6 0.17543
2.8 0.16750
3.0 0.16041
3.5 0.14415
4.0 0.13013
4.5 0.11232
5.0 0.10737
6.0 0.08908
7.0 0.07598
/AXIAL POWR RESPONSH WORST COS 9-88/
22 1
0.0
.00 .00
.047619 .32
.095238 .55
.142857 .78

```

.190478	.99
.238095	1.08
.285714	1.16
.333333	1.22
.380952	1.28
.428571	1.30
.476190	1.32
.523810	1.32
.571429	1.30
.619048	1.28
.666667	1.22
.714286	1.16
.761905	1.08
.809524	0.99
.857143	0.78
.904762	0.55
.952381	0.32
1.0	0.00

/PLEN PRESS TRANS HARD (TRAC: RING 2-SECTOR 5 2/88) 74.8636,74.345SS/
106

0.000000	309.589359
0.005001	44.6519
0.010032	42.9867
0.015113	40.0856
0.020410	45.5207
0.026149	42.5109
0.031801	44.0426
0.037453	43.9295
0.042478	45.2625
0.047522	44.3182
0.052556	41.1561
0.057593	38.4755
0.062597	36.8625
0.067598	37.1511
0.072641	38.8758
0.077782	39.1819
0.082783	41.9118
0.087980	40.5672
0.093102	39.6156
0.098112	35.4337
0.103230	36.9176
0.108470	38.7569
0.113750	40.2509
0.119150	39.9333
0.124290	43.8164
0.129700	39.7418
0.135580	38.3174
0.141450	38.3159
0.146480	38.8990
0.152220	39.2008
0.157360	39.6751
0.162960	42.7111
0.168610	39.5503
0.174100	41.0458

0.179420	39.1268
0.184640	39.6925
0.190010	41.2663
0.195800	38.8048
0.210790	40.0218
0.220820	38.1361
0.231090	39.8999
0.241650	39.7244
0.252010	38.9687
0.264180	39.3400
0.274520	39.7171
0.287090	39.7491
0.298260	39.5039
0.310770	39.3937
0.325030	39.3211
0.335240	39.2341
0.346280	39.0078
0.357910	38.9962
0.369020	38.9817
0.380070	39.0151
0.393520	38.9904
0.405460	38.9832
0.419300	39.2066
0.429710	39.2907
0.441190	39.2254
0.453850	39.1166
0.467810	39.1195
0.482670	39.0310
0.497580	38.8729
0.609530	38.7830
0.711700	38.5074
0.819950	38.2826
0.925510	38.5524
1.025500	38.2768
1.125900	38.1027
1.230000	37.8706
1.336200	37.6849
1.443700	37.5181
1.545700	37.4064
1.649800	37.2773
1.751200	37.1540
1.853700	37.0598
1.957300	36.9524
2.059300	36.8610
2.159300	36.7972
2.263200	36.7842
2.366200	36.8930
2.468200	37.1613
2.569100	37.5167
2.670200	37.8938
2.771100	38.0461
2.871000	38.1448
2.971600	38.1303
3.072300	38.1056

3.172700	38.0896
3.273600	38.0693
3.375100	38.0418
3.475200	38.0128
3.575400	37.9968
3.675800	37.9780
3.777200	37.9489
3.878200	37.9330
3.979000	37.9098
4.079500	37.8837
4.181400	37.8721
4.283000	37.8097
4.386000	37.8126
4.487400	37.8010
4.591300	37.7372
4.696000	37.7067
4.800300	37.6994
4.900400	37.6632

/TANK BOT PRESS TRANS HARD (TRAC: RING 2-SECTOR 5 2/88) 28.4856,28.51SS/
106

0.000000	27.910
0.005001	28.4871
0.010032	26.5347
0.015113	23.3696
0.020410	20.5265
0.026149	20.1654
0.031801	22.6661
0.037453	24.9405
0.042478	25.8370
0.047522	25.3090
0.052556	24.0238
0.057593	22.3238
0.062597	21.4186
0.067598	21.5753
0.072641	22.5631
0.077782	23.5074
0.082783	23.8671
0.087980	23.6307
0.093102	23.6031
0.098112	23.5147
0.103230	23.8410
0.108470	24.0180
0.113750	24.9971
0.119150	26.0241
0.124290	26.3505
0.129700	25.7688
0.135580	24.8433
0.141450	24.2428
0.146480	24.2762
0.152220	24.8143
0.157360	25.3307
0.162960	25.6484
0.168610	25.4352
0.174100	25.1465

0.179420	24.6707
0.184640	24.4386
0.190010	24.3066
0.195800	24.4343
0.210790	23.8091
0.220820	24.4125
0.231090	24.9492
0.241650	24.8071
0.252010	24.2701
0.264180	24.4372
0.274520	24.7911
0.287090	24.6896
0.298260	24.3444
0.310770	24.1471
0.325030	24.0397
0.335240	23.8874
0.346280	23.7903
0.357910	23.7641
0.369020	23.7438
0.380070	23.7859
0.393520	23.5669
0.405460	23.4494
0.419300	23.5379
0.429710	23.4813
0.441190	23.2956
0.453850	23.1390
0.467810	23.1578
0.482670	23.0432
0.497580	22.8706
0.609530	22.2759
0.71 700	21.7044
0.819950	21.2620
0.925510	21.0545
1.025500	21.1271
1.125900	20.8906
1.230000	20.5410
1.336200	20.2640
1.443700	20.0203
1.545700	19.8462
1.649800	19.6432
1.751200	19.4459
1.853700	19.2907
1.957300	19.1137
2.059300	18.9643
2.159300	18.8541
2.263200	18.8178
2.366200	18.9542
2.468200	19.3270
2.569100	19.8187
2.670200	20.3394
2.771100	20.5498
2.871000	20.6701
2.971600	20.6484
3.072300	20.6005

3.172700	20.5657
3.273600	20.5207
3.375100	20.4758
3.475200	20.4265
3.575400	20.3960
3.675800	20.3684
3.777200	20.3206
3.878200	20.3003
3.979000	20.2553
4.079500	20.2451
4.181400	20.2205
4.283000	20.1567
4.386000	20.1581
4.487400	20.1378
4.591300	20.0841
4.696000	20.0522
4.800300	20.0609
4.900400	20.0189

/ASS TINLET TRANSIENT/
3
0.00000 27.92777778
1.00000 35.00
2.00000 35.00

/TANK LEVEL TRANSIENT/
3
0.0 1.0000
1.0 1.0000
2.0 1.0000

/FLUID INITIAL GUESS DATA/
0.0056 0.1158 0.318 0.39 0.1752
309.589359 88.00000 27.92777 0.0
0.0019 0.1818 0.5015 0.3071 0.0077
0.0D0 0.0D0 0.0D0
0.0 30.0 19.7 3.937D-05
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 0.7 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0
1.0 1.0 1.0 1.0 1.0

/INITIAL SOLID TEMPERATURES/
27.92777 27.92777

**DATE
FILMED**

9 / 9 / 93

END