DOE/mc/24258-T13

DOE/MC/24258--T13

DE92 017794

INTEGRATED LOW EMISSION CLEANUP SYSTEM FOR DIRECT
COAL-FUELED TURBINES (ELECTROSTATIC AGGLOMERATION)

DOE CONTRACT NO. DE-AC21-88 MC-24258

PROJECT QUARTERLY REPORT

FEBRUARY 1992

FOR THE PERIOD OF 9/01/91-12/31/91

Prepared By

J. M. QUIMBY

RESEARCH-COTTRELL ENVIRONMENTAL SERVICES AND TECHNOLOGIES
P.O. BOX 1500
SOMERVILLE, NEW JERSEY

PREPARED FOR THE
MORGANTOWN ENERGY TECHNOLOGY CENTER
U.S. DEPARTMENT OF ENERGY
P.O. BOX 8080
MORGANTOWN, WEST VIRGINIA 26507-0880

DOE CONTRACT SPECIALIST: R. DIANE MANILLA

DOE PROJECT MANAGER: CHARLES ZEH

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

APPROVED FOR RELEASE OR
DISTRIBUTION TO THE PUBLIC GROUP
DATE 7/28/92
WGB

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

1. Objective

The objective of this contract is to investigate the removal of SO_x and particulate matter from direct coal-fired combustion gas streams at high temperature and high pressure conditions. This investigation will be accomplished through a bench-scale testing and evaluation program employing sorbent mixed with a coal-water slurry for SO_x removal, and an innovative particulate control concept. The particulate control device utilizes electrostatic agglomeration followed by a high efficiency mechanical collector (cyclone.)

The process goal is to achieve particulate collection efficiency better than that required by the 1979 new source performance standards. An additional goal is to demonstrate 70% SO_x removal efficiency.

2. Technical Approach

This research project is now in the second of a 3 phase (phase II) project. Phase II is to fabricate the combustor and particulate control devices and install the system at a test facility located at Research-Cottrell's, KVB Western Laboratory, Santa Ana, CA. There are three functional categories, or tasks which are to be completed in sequence. These tasks are itemized as follows:

1. Design, procurement, and installation.
2. Shakedown and startup.
3. Reporting.

CES (R-C, EST) is the Project Manager of the team effort by CES and KVB. KVB (R-C, EST - Western Laboratory) is the sub-contractor to CES for the design and construction of the combustor test facility. KVB will also operate the combustor and gas clean up system to be located at the Santa Ana laboratory. CES (R-C, EST) is responsible for the overall testing and evaluation effort including the design and construction of the electrostatic agglomerator and high efficiency cyclone.

3. Results/Accomplishments

Phase I of this contract has been completed. A topical report covering the Phase I effort has been submitted to DOE in March.

PARTICULATE CONTROL CONCEPT

The DCFT gas turbine operates at much higher temperatures than pressurized fluidized bed combustors. At these temperature levels the particulate is likely to contain liquidus species such as sodium sulfate and the potential for stickiness should not be underestimated. In view of this likely tendency, a particle control concept that utilizes a "flow-through" collection concept will offer an advantage that may not be available on barrier filters. Barrier filtration methods may be more prone to plugging at DCFT conditions when compared with flow-through devices such as cyclones.

However, cyclones are known to be deficient in the collection of particulate below 5 microns. Any concept that can help the growth of fine particulate into sizes larger than 10 microns should be promising.

One of the concerns relating to particulate charging is the effect of thermal ionization. The problem associated with thermal ionization is the potential for excessive current flow caused by the presence of an excessive number of thermally generated ions in the combustion gases. In the extreme case even a small voltage applied to a heavily ionized gas would cause runaway currents. Cooperman's⁽¹⁾ calculations however, indicate that excessive current should not be encountered up to 1500°F. Thus, a process limitation because of thermal ionization is not expected.

To test the process where thermal ionization may represent a significant service of ions the electrostatic agglomerator will be first tested during shakedown and startup using stainless steel components. These stainless steel components will provide information on the characteristics of the Electrostatic Agglomerator concept while avoiding sticky particles and thermally

generated ions. Thus comparison to an electrostatic precipitator, in terms of current voltage characteristics in particle charging can be more readily determined.

Once the metal internals verify that the electrostatic agglomerator concept is valid the temperature of the system can be raised to approximately 2100°F using high-voltage components fabricated of Hastelloy alloy. The stainless steel internals of the agglomerator that serve as guide plates, baffles, and tube sheets for the high-voltage components will be replaced with ceramic duplicate components.

A complete set of high voltage ceramic internals will replace the Hastelloy metal internals for temperatures above approximately 2100°F.

If, however, thermal ionization does occur, there are ways to deal with it depending on the extent of the problem. In the extreme case, where an independent electric field cannot be applied without provoking runaway currents, conditions actually exist which favor self operation of the concept: In the charging section ample thermal ions would be available to charge the particles, and in the agglomerating section, with appropriate electrode spacings, the thermal ion space charge could be adequate to drive the charged particles to the electrodes for contact agglomeration. Thus, even in the extreme case the ESA concept may be valid, although operation would be different from normal.

In the more likely case of little or moderate thermal ionization we have proposed the use of pulse energization to control the current flow. Pulse energization means the application of short-duration fast-rising, high-voltage pulses to a DC base voltage. This provides more degrees of freedom in controlling current production at a given base voltage than in normal DC operation. For example, the DC base voltage can be set below corona starting voltage. Corona starting voltage can be obtained by superimposing a pulsed DC voltage over the base while also controlling parameters of pulse repetition rate, pulse voltage, pulse rise time and duration. Particulate charging and migration,

and the resultant inter particulate contact are enhanced by the longer residence time of particulates in the agglomerator. A high efficiency cyclone follows the electrostatic agglomerator. The collection efficiency of advanced cyclone has to address the requirements of a 20 ppm outlet so that both turbine requirements and New Source Performance Standards could be simultaneously met.

The commercial ESA design for a 200 MW DCFT plant has an interelectrode clearance of 3 inches, and the plate height is 8 feet. A gas velocity of 25 feet per second was chosen in the design of commercial size agglomerator. The fabricability of ceramic internal parts was the main consideration. A vessel diameter of sixteen feet was considered to be the maximum practical size that could be used because of the 8-9 foot limitation on ceramic structural beams. Though presently limited to about 8' due to fabrication considerations, considerations of moment stress that could be tolerated by ceramics limit structural members to this maximum length. Two 9' ceramic members could be telescoped to provide the 16' span and hence the sixteen foot diameter limit on pressure vessels for this application. Once the cross section of ESA is defined, then the length depends on residence time. A length of 30 feet would result in a residence time of 1.2 seconds for a 25 ft/second velocity.

A pulsed energization system using nanosecond risetimes will energize each section. There will be four electrodes serviced by pulsed power for the 1.2 second residence time operation, and only two for operation with 0.6 seconds residence time. Reliable pulsed power supplies are now available in the industry and the design by Ion Physics Corporation will be utilized for these tests.

COMBUSTOR DESIGNS FOR TEST FACILITY

A CWS combustor with a thermal input of 150,000 - 300,000 Btu/hr was initially proposed by AVCO Research Laboratories for simulating gas turbine combustor conditions at the ESA inlet. However, it was later realized that such a small CWS combustor

would be difficult to operate reliably due to the large heat losses and difficulties associated with atomizing CWS at flow rates below 20 lb/hr. Another very important consideration was the heatup time requirements of the ESA. At the low thermal ratings, the time required to bring the ESA up to the operating temperatures was estimated to be more than 10 hours. In order to alleviate these concerns, the combustor rating was increased to 300,000 - 1×10^6 Btu/hr. The AVCO subcontract for combustor fabrication and test facility fabrication was changed over to the R-C, KVB Laboratory facility. A report on the combustor design specifications was issued to DOE under separate cover in July 1990. An overall schematic of the design is attached as Figure 1. The reactor specifications are as follows:

- a) operating temperature range 1600°F - 2500°F
- b) operating pressure: 10-15 atmospheres
- c) mass flow: 0.15 - 0.3 lbs/s (gas)
- d) fuels: CWS or natural gas

A summary of calculated gas temperature data for various loads and excess air levels are shown in Figure 2. The temperatures shown are the gas temperatures at the transition between the 5" and 2" section. These calculations show that the desired range of temperature (2500°F-1600°F) can be achieved by varying load between 100% and 50% and excess air between 5% and 100%.

The reactor is designed to provide a suitable residence time to complete combustion of large slurry droplets. Over the range of temperature operating conditions the residence time ranges between 0.4s and 1.0s. Burnout times for a 200 microns bituminous coal char range from 100 to 200ms at temperatures between 3000°F and 2200°F under 15 atm pressure and an average O₂ concentration of 5%.

The burner design and expected flow pattern is shown in Figure 3. The burner uses swirling flow to stabilize the flame and a curved quarl to delay impingement on the furnace wall. The burner can be fired on natural gas, coal/water slurry or if required, a combination of the two fuels.

Figure 1. DOE - HTHP Combustor Matl - Carbon Steel

Figure 2. Calculated reactor exit gas temperatures.

A Parker Hannifin air atomizer designed for CWS will be used to atomize slurry (Figure 4). Two designs of the nozzle are being obtained, a conventional design and a reduced air flow design. The reduced air design uses about 25 lb/hr air which corresponds to a air/CWS rate of about 20%.

A list of flow, temperature, pressure and sampling instrumentation which has been installed on the combustor is given below:

- CWS mass flow rate and pressure
- Natural gas flow rate and pressure
- Atomizing air and pressure
- Staging air flow rate and pressure
- Combustor temperatures
- Combustor pressure
- Cooling water flow rate and exit temperature
- Combustor exit gas composition (O_2 , CO_2 , CO , NO_x , SO_2)

The flow rates and pressures will be controlled using a process control and monitoring program.

APPROACH TO HOT GAS CLEANUP EVALUATION

Particulate collection for the test facility consists of an electrostatic agglomerator followed by a Stairmand type high efficiency mechanical collector.

The electrostatic agglomerator is designed to handle flowrates between 30 - 80 acfm at the DCFT conditions of interest. Figure 5 is a schematic of the agglomerator concept. The ESA consists of a charging section and agglomerating section each comprised of 4 grounded electrode tubes. The high voltage sections are located concentrically within these tubes. A pulsed energization system will be used to energize the agglomerator. The agglomerating sections will have smooth hollow tubes as high voltage electrodes for providing uniform fields while the charging sections will have controlled curvature on the discharge electrodes for the provision of corona current. Flow can be controlled through any of the tubes

Figure 4. Parker Hannifin CHS Nozzle.

Figure 5 Schematic of Electrostatic Agglomerator

in each section. Residence time through ESA can thus be controlled between 0.5 to 3 seconds by a combination of flowrate and number of tubes.

The electrostatic agglomerator performance will depend on the nature of ash and its agglomerative behavior in addition to the parameters such as residence time, applied electric field strengths and the operating temperatures. Therefore the test program should include as variables temperature, gas velocity, residence time and the applied electrical pulsed energization levels as variables for a given process condition. Figure 6 is a schematic of how the agglomerator system components will fit together.

FUEL SPECIFICATIONS

It is estimated that 50 tons of coal water slurry will be required for Startup, Testing, and Analysis. Slurry will be manufactured and shipped in 55 gallon drums. Two drums per day will be emptied into a slurry supply tank, connected to the combustor. Slurry specifications are as follows:

- a) solids content: 65-70%
- b) particle size: 90% less than 75 μm
- c) ash content: 8-10%
- d) volatile content: 30%
- e) heating value: 9000 Btu/pound
- f) ultimate analysis to be provided.

4. Quarterly Results

Electrostatic agglomerator performance depends on the nature of ash and the agglomerative behavior of the ash in addition to the parameters such as residence time, applied electric field strengths, and the operating temperatures. Therefore the planned test program included as variables: operating temperature, gas velocity, and the applied electrical pulsed energization levels for a given process condition. Also, process conditions such as coal type (sulfur content) and sorbent injection levels were planned as

Figure 6 Schematic of How Agglomerator Components Fit Together

controllable variables.

The key goal was to identify those parameters that affected the maximum growth of particulate by electrostatic agglomeration. Data collection that was planned included the particulate loading and size distribution at the agglomerator inlet, outlet, and cyclone outlet. Also, to be measured was the sorbent injection rate, SO_2 concentrations at the particulate metering locations, and the pressure and temperature at these locations.

Shakedown consisted of first debugging the individual components and support systems for the combustor. The combustor was designed to fire on both natural gas or coal-water-slurry. Natural gas combustion was used to cure the refractor material and provide information on temperature and pressure ranges of the system as well as temperature stability. Combustion coal-water-slurry was essential for providing coal derived fly ash to the ESA. The individual components and systems that supported the combustor and analytical systems are listed below:

- Main air compressor
- atomizing air compressor
- natural gas compressor
- coal water slurry pump
- pressurizing orifice valve
- control valves
- mass flow meters
- pressure transducers
- thermocouples
- emission gas quench system
- continuous gas analyzers
- flame out alarm system
- data acquisition hardware and software

The combustor and agglomerator were checked for leaks. Leaks were stopped up to an operating pressure of 15 atmospheres.

Following checkout of the individual components, control systems, continuous analyzers, and data acquisition system the combustor was fired on natural gas. During start up on natural gas

the following tasks were completed:

- cure castable refractory
- Develop O_2/CO curves for natural gas operation to determine safe operating excess air levels over the load range.
- Determine load/exit temperature curves at 5%, 25%, 50%, and 100% excess air over the load range.
- Check control software logic for load under natural gas operation.

After successful continuous operation of the combustor fired on natural gas, coal-water-slurry shakedown testing was to be implemented.

During shakedown of the combustor the temperature maximum of the system was limited to 1800°F because of the temperature limitation of the stainless steel agglomerator internals (for example baffle, tube-sheet, and collection(grounded) electrodes).

At the time combustor operation was being tested for temperature stability and pressure stability on natural gas, the electrostatic agglomerator was to be tested for electrical stability by plotting current versus voltage relationships under different temperatures and pressures. Also, the temperature profile across the agglomerator was to be measured. Successful demonstration of ESA electrical performance was demonstrated in the range of 800°F to 1600°F and from 1 atmosphere to 15 atmospheres. Under the shakedown test conditions of the agglomerator the corona producing electrodes (concentration section) were inserted in place of the smooth electrodes (agglomerating section). This was done so that particles leaving the concentration section could be sampled for charge-to-mass measurement once coal water slurry combustion was successful.

The intent of the charge-to-mass measurement determination on the particles exiting the concentrator section was to provide further evidence of the electrostatic charging capabilities under high temperature, high pressure conditions. After successful demonstration of electrostatic charging of fly-ash particles using

the charge-to-mass measurement technique the ESA was to be reassembled as planned; the discharge (finned) electrodes were to be placed in the inlet (concentrating section) of the agglomerator and the non-discharge (smooth) current producing electrodes were to be placed in the outlet (agglomerating section) of the ESA.

Completion of system debugging (shakedown) was planned with the successful operation of the combustor fired on coal-water-slurry and with the ESA operating with metal internals at a temperature of 1800°F at 10 to 15 atmospheres. Measurement of particle concentration and particle size distribution at the inlet, outlet, and outlet cyclone were planned. Also planned was the monitoring of flue gas constituents by continuous monitors (CO, CO₂, SO₂, O₂, and NO_x).

Unanticipated Problems and Corrective Actions

Combustor startup and operation with natural gas were successful after minor corrections were implemented.

Combustor startup issues that needed correction are listed as follows:

1. Water jacket to combustor required new plumbing to increase cooling water flow,
2. Air compressor was purchased as a used unit and needed replacement parts,
3. The flame out sensor repeatedly went off. An air filter was placed in line with the air compressor to remove fine oil mist that coated the sensor window,
4. Minor gas leaks in feed line were corrected.

Burner Modifications for Natural Gas

There were two locations in the burner for natural gas input:

1. an annulus around the CWS atomizer, and 2. radial injection ports downstream of the primary air swirl vanes. Initially, natural gas was plumbed to the radial location, with high pressure

"core air" plumbed to the annular location to cool and protect the CWS atomizer. However, due to difficulty experienced in lighting off the combustor with gas, the annular location was used for natural gas input.

Coal-Water-Slurry (CWS) Combustion

During light off with CWS, two problems were identified with this arrangement. First, the atomizer became too hot and caused the atomizer internal parts to become seized together which prevented atomizer cleaning. Second, the CWS was interfering with the UV sensor while gas was introduced at the annulus, causing the combustor to shut down, even when there was a stable gas flame.

Piping for pressurized natural gas was modified to allow gas to be directed to either the annular or radial location. After the combustor had reached operating temperature, gas could be switched from the annular start up location to the radial location. With gas directed to the radial location and core air directed to the annulus, the combustor was operated with CWS until the atomizer became plugged without a loss of UV signal from the gas flame. In addition, after operation with CWS, the nozzle could be completely disassembled and cleaned without seizing up internally.

However, sustained combustion of CWS as not achieved. Different nozzle designs were tried at varied locations using different atomizing (air/slurry) conditions. Several experiments were successful in igniting the slurry but the flame would be unsteady and eventually burn out after 20 minutes. The orifice of the atomizing nozzle would eventually plug rendering the system ineffective in achieving a steady temperature.

Fly-Ash Slurry to Replace CWS

It was decided to abandon CWS combustion as a means to introduce ash to the electrostatic agglomerator. A fly-ash-slurry mixture was thought to be an effective means of introducing fly ash

into the agglomerator without having to sustain combustion of CWS. Also, since fly ash has smaller diameter particles as compared to pulverized coal the plugging problems of atomizing nozzles could be alleviated. A 20% ash-slurry mixture with water would yield the same grain loadings as attempted with CWS combustion. Coal derived fly-ash was obtained from Nevada Electric's electrostatic precipitator hopper. Nevada Electric burns pulverized coal.

Attempts to atomize 20% ash-slurry mixture in the combustor while firing 1.5 mBtu/hr on natural gas were successful. Flame out problems were corrected and no plugging problems were encountered. However, the temperature of the combustor (Ca 2700°F) melted the fly-ash and the combustor acted as a slagging combustor. The efficiency of ash collection on a weight by difference calculation (input ash versus ash collected in the slag pit) was nearly 100%. Sampling of the agglomerator inlet yielded 97% and 95% ash collection efficiency in the combustor. The remaining fly ash entering the agglomerator was too low in concentration to be of any use.

The burner was modified by replacing the blind flange, directly opposite to the agglomerator inlet, with a nozzle that could inject ash slurry. In this arrangement the slurry spray could be directed to the 2" ID inlet section of the agglomerator. By using the nozzle opposite to the inlet of the transport duct 50% of the ash was transported to the inlet connection of the agglomerator at 1680°F. However, agglomerator inlet temperatures of 1680°F were not sufficient to heat the agglomerator internals above 1350°F. When the inlet temperature was increased to 2100°F the ash melted and impacted on the walls of the inlet duct.

It was then discovered that some shakedown runs performed on coal water slurry combustion trials had temperature overruns because the mass flow controllers of combustion air and natural gas were out of calibration by as much as a factor of 2. Actual temperature measurements at the agglomerator were not recorded. The bottom flange of the agglomerator was disassembled to inspect the agglomerator stainless steel internals. It was discovered that

the stainless steel baffle was destroyed by the excessive temperatures. Also, the inlet collection electrodes were warped which prevented the insertion of the corona generating electrodes as prescribed in the original agglomerator design.

The damaged stainless steel baffle was removed and a ceramic (silicon carbide) baffle was installed. Replacement of collection electrodes as well as the labor involved for installation were considered too costly to be implemented. The decision was made to leave the agglomerator corona producing electrodes in the gas exit side of the agglomerator. The damaged inlet tube sheet and stainless steel collection electrodes were left intact.

Use of a fly ash slurry (fly ash from Nevada Power) was not possible at an agglomerator inlet temperature above 1800°F. The suspended fly ash particles were liquid and were captured by the transport duct leading to the agglomerator inlet. Disassembly of the agglomerator bottom flange revealed that the agglomerator inlet (2" ID) was acting as a glass blowing tube. A brown-green molten bulb of glass was attached to the agglomerator refractory at the inlet.

Injection of a fly ash slurry mixture proved to require more shakedown time than was available in the budget. A slurry of alumina in water was prepared to replace the fly ash slurry. Alumina has a melting point above 3000°F so the problem of ash melting was overcome.

As a consequence to the irreparable damage to the grounded electrodes and tube sheet of the inlet (concentrator) section the ESA configuration was no different than a tube type electrostatic precipitator. The concept of electrostatic agglomeration could not be tested within the budget appropriation. However, the testing of the tube type ESP system at temperatures of 1800°F and pressures up to 15 atmospheres was considered worthwhile.

A one week particle sampling shakedown plan was designed to examine the following variables affect on alumina collection efficiency:

1. gas velocity.

2. Particle inlet concentration.
3. ESP power on at 30 KV and power off.

Also, to be examined in the week long test period was the particle size distribution of the inlet and outlet and the particle charge-to-mass ratio at the outlet of the ESP. A Faraday cage type sampling device was designed and fabricated by Dr. Duane Pontius of SRI, International, Birmingham, Alabama for the purpose of obtaining charge-to-mass ratio data.

Atomizer Performance

Five atomizers were tested during the commissioning of the facility on CWS. The first nozzles tested were the two Parker-Hannifin atomizers. Both the normal and reduced air capacity designs were tested. Both atomizers became quickly plugged with CWS at the 0.05 inch orifices located inside the nozzle. Upon recommendation of the manufacturer, the CWS orifices were enlarged to 0.063 inches. This modification resulted in a significantly longer operating period on CWS without clogging. The CWS was injected for as long as an hour before the atomizer clogged. However, while slurry was injected at rates ranging from 0.4 to 2.0 lb/m, the flue gas instrumentation indicated that very little of the CWS was actually burning, i.e. only a small decrease in O_2 and slight increase in SO_2 was observed. After the atomizer became blocked, the furnace was depressurized and the ashpit was found to be full of moist slurry. Additionally, a large amount of coke was found deposited on the furnace refractory walls, indicating impingement of the slurry on the walls.

The Y-jet atomizers were then tested on the combustor. Impingement of the CWS on the refractory wall still occurred, even with the 15° angle Y-jet nozzle. Additionally, the slurry flow tended to be somewhat erratic indicating plugging of the passages in the Y-jet atomizers was also occurring. The slurry was injected for about 20 minutes after which time the slurry injection was stopped and the furnace was depressurized. Again, the ashpit was

found to contain moist slurry and coke was deposited on the furnace walls.

Another attempt was made to burn the CWS by further increasing the slurry holes in the Parker-Hannifin nozzle from 0.063" to 0.078".

When the combustor was fired using the modified Parker-Hannifin nozzle, a stable slurry flame was established for a period of approximately 30 minutes. A visible coal flame could be seen through the combustor sight glass and through the UV detector port. In time, the top portion of the combustor cooled and the flame became more diffuse, and after 20 minutes, the atomizer became blocked.

During the period the CWS was burning, the gaseous emissions remained relatively steady at 3% to 4% O_2 and 13% to 14% CO_2 , indicating that near complete burnout was achieved. These tests were conducted at a combustor pressure of 180 psia.

At the conclusion of the test, the combustor was examined. Considerable slag and coke was found along the combustor walls and the ashpit still contained wet, unburned slurry. These observations indicate that although the slurry was burning, a fraction of the slurry still impinged on the reactor walls.

Because of the project time and budget constraints, a decision was made to inject an ash slurry into the combustor while burning gas rather than continue improving the combustor performance on CWS. It was believed that very steady CWS combustion over at least an eight hour time period would be required to obtain acceptable agglomerator operating data. Based on the experience with firing CWS in the 5 inch combustor, the consensus was that achieving the required stability with CWS would demand more time than remained on the project.

The method chosen to generate the ash laden flue gas stream required to assess the agglomerator performance was injection of flyash into natural gas flue gases. A single hole Y-jet atomizer was used to inject an ash/water slurry along the axis of the combustor. Experiments were conducted injecting a 20% bituminous

coal slurry into the burner. The slurry was injected without problems for long periods of time (greater than 8 hours). However, measurements showed that the majority of the ash slagged on the refractory walls and was effectively removed from the flue gas stream.

Particulate Samples No. 1, 3 and 4 (Table I) were taken at the ESP inlet when the ash/water slurry was injected at the burner. When the ash was injected at the burner, an average of 97% of the injected ash did not reach the agglomerator inlet. Examination of the combustor, after injecting ash at the burner top, showed a heavy slag layer coating the furnace walls.

In order to inject the ash at lower temperatures, the slurry atomizer was moved to the clean-out port located directly opposite the horizontal duct leading into the ESA. Particulate Samples 2, 5 and 6 (Table I) were taken when the slurry was injected directly into the horizontal duct.

When the ash was injected directly into the horizontal duct leading into the ESP, a major fraction of the ash still formed slag on the walls unless the combustor load was reduced to lower the temperature. At reduced load, 40% of the injected ash was measured at the agglomerator inlet.

In order to operate the combustor at high temperatures while maintaining an acceptable ash loading into the ESP, a decision was made to use an $\text{Al}(\text{OH})_3$ /water slurry rather than a coal ash slurry. The $\text{Al}(\text{OH})_3$ slurry was injected at the side port using the single hole Y-jet atomizer. Assuming the aluminum hydroxide completely decomposes to Al_2O_3 , i.e. $2 (\text{Al}(\text{OH})_3) \rightarrow \text{Al}_2\text{O}_3 + 3\text{H}_2\text{O}$, approximately 80% of the injected solid was recovered at the agglomerator inlet.

ESA Operation with Particulate Matter

Sampling of particulate matter was conducted with a ceramic thimble as part of the ASME Method 17 filter train. Samples were collected before and after the ESA within 15 minutes of each other. Simultaneous sampling was not considered necessary since large

differences in capture efficiency with the electrostatic power on and power off were expected. All sampling was performed at isokinetic rates at a single point location in the 2" ID duct for 10 minutes.

The configuration of the agglomerator was that of an electrostatic precipitator. Therefore, the objective of sampling was to determine the capture efficiency across the agglomerator with the electrostatic power on and with the power off. The electrostatic DC power was set to 30 kV DC. Pulsed energization was not performed. The effects of ash loading, gas velocity, and electrostatic power on particle capture efficiency were tested. Also, attempts were made to test the particulate inlet and outlet size distribution as well as the charge-to-mass ratio of the particles exiting the agglomerator.

A chronological summary of all sampling data separated by major events is contained in Table I. Sample runs 1-6 utilized a slurry of 20% fly ash injected in the direction of gas flow (straight run) to the agglomerator. The lower ash slurry feed rates yielded a greater inlet particle loading to the agglomerator. Particle losses in the slurry injection system were greater with increased feed loadings. Also, inlet temperatures greater than 1800°F yielded molten ash particles that were removed by the duct between the burner and agglomerator.

Sample runs 7-11 were performed using a 10% alumina slurry in place of fly ash. Measurements for runs 7-11 were taken at the inlet of the agglomerator. An alumina slurry (10%) feed rate of 0.08 lb/min with 200 scfm flue gas flow proved to provide an adequate particle concentration in the range of 0.93 to 1.5 grains/dscf.

Sample numbers 12-15 were collected at the agglomerator exit using 10% alumina slurry. Sample #13 developed a leak therefore the test results are void. Sample numbers 16-40 represent data collected in the shakedown of the electrostatic precipitator while collecting alumina dust.

A summary of sample runs 16-40 is included as Table II. Two flow rates: a) 76 acfm and b) 114 acfm were used with the precipitator activated at 30 KV and also with the precipitator off. Ash loadings at the inlet ranged from 4.66 grains/dscf to 0.95 grains/dscf with all other conditions equal, at a charging voltage of 30 KV. The precipitator yielded a capture efficiency of 96.7% at 30 KV at a velocity of 4.9 ft/s. Physical parameters of the precipitator are listed as Table III.

A cascade impactor sample of the alumina at the precipitator inlet is included in Table IV. The MMD of the alumina was $2.9\ \mu\text{m}$ with a GSD of 2.9. One attempt was made to collect the outlet size distribution but the impactor did not pass a post sampling leak test. The pressurizing orifice valve had become eroded from the hot abrasive alumina particles. The damage to the orifice prevented additional data collection.

Two attempts were made to determine the particulate charge-to-mass ratio at the exit of the discharge section. Only one sample had meaningful results. Problems with the other sample were encountered from the current instability of the measurement device under the high temperature and pressure conditions. The coulomb measurement meter deflected off scale (+) midway through the sample event. The charge-to-mass ratio for the single valid run was on the order of $9\ \mu\text{C/g}$. Additional data collection attempts became impossible when the systems' pressurizing orifice valve eroded from the hot alumina as mentioned above.

5. Discussion and Conclusions

Attempts to validate the concept of electrostatic agglomeration were not possible in the shakedown program before budget constraints halted the program. What was learned was that electrostatic precipitation is feasible in the temperature range of 1600-1800°F and at pressures above 10 atmospheres. Thus particulate control from pressurized fluid bed combustors may be accomplished with an ESP. The nature of the ash physicochemical properties, such as melting point and ash adhesive force are

important to the successful demonstration of electrostatic agglomeration. Perhaps ash adhesion is even more important to agglomeration as compared to precipitation because ash adhesion is critical for success. Liquid ash particles will present a problem for electrostatic devices as well as barrier filters but sonic cleaning of an electrostatic device may be successful.

In order to demonstrate electrostatic agglomeration there needs to be developed a successful interface between the pressurized coal combustor and hot gas cleanup device. This project ran out of financing before a combustor was developed that could deliver fly ash to the hot gas cleanup device. Designing an electrostatic cleanup device to fit a bench scale combustor that has previously been field demonstrated will offer a greater chance for success.

Collection of the alumina particles under ESP conditions was expected to be on the order of 99% but the resistivity of alumina was on the order of 10^5 ohm-cm. Conductive particles are difficult to capture by an ESP. Also, the flow profile through the 4 collection electrodes was unknown. Uneven flow distribution through the gas passage will scour particles from the collection surface. Another variable that would work against efficient capture is ash adhesive properties. Alumina particles had poor adhesive characteristics at 1700°F. Particles were charged sufficiently ($9 \mu\text{C/g}$) as determined by the charge-to-mass measurement but did not stick together.

An increase in gas velocity reduces particle collection efficiency in an ESP and this relationship was observed in this program. Also, the precipitator had greater particle emissions with greater inlet ash loadings, from 1 to 4 grains/dscf and this was expected.

It is evident from the work conducted in this program that further research is needed for electrostatic applications in hot gas clean up technologies. Given the limitations of the systems shortcomings that the project was reduced to, there was successful demonstration of effective particle charging at 1700°F and 11 atmospheres. Also, the electrostatic system showed that higher

temperature and pressure applications were feasible (neglecting material limitations).

6. Recommendations for Future Designs

The major problem experienced during the execution of the test program was in achieving stable operation on coal water slurry. Two separate problems were encountered which prevented successful combustion of the slurry; atomizer plugging and impingement of the slurry on the combustor walls. Both the atomizer plugging and spray impingement problems can be primarily attributed to the relatively small scale of the facility.

Although, during the atomizer testing, considerable progress was made in reducing the frequency of atomizer plugging with CWS, the longest run with CWS was approximately one hour. Using a finer grind slurry with the modified Parker-Hannifin nozzle may result in an acceptable performance.

A more difficult problem with the slurry atomization is the impingement of the slurry on the 5 inch internal diameter combustor. The best solution to both the atomizer plugging and spray impingement problems would be to use pulverized coal rather than a slurry for small scale pressurized coal combustor designs. The use of pulverized coal eliminates the atomizer completely and also eliminates the possibility of wet slurry building up in the combustor.

Another consideration for future ESA testing is the difficulty in preventing the ash from slagging on the combustor and transfer piping and never reaching the ESA particularly at gas temperatures above 2000°F. Although removing the ash as slag in the combustor is a desirable feature of a commercial concept, the high levels of ash removal (greater than 95%) achieved with the current combustor design may create difficulties in assessing the ESA removal efficiency.

Jay M. Quimby
Project Manager

Table I

Summary of Sampling Data
Collected Under Phase II Shakedown

Tests	Date	Slurry Type	Slurry Rate (lb/min)	Ash/Alum Rate (lb/min)	Flue Gas Flowrate (SCFM) dry	Expected Loading (g/SCF)	ESP Inlet Temp. (F)	ESP Outlet Temp. (F)	ESP Pressure (Psig)	ESP Sample Port	ESP Power	Actual Loading (g/SCF)	Efficiency %
0	10/02	Ash	0.72	0.14	139.81	0.47	1605	1322	158	in	off	none	
1	10/15	Ash	0.77	0.15	175.83	0.40	862	548	154	in	off	0.0201	
2	10/15	Ash	0.70	0.14	170.30	0.37	862	551	156	in	off	0.0585	
3	10/16	Ash	0.98	0.20	245.21	0.36	1042	840	156	in	off	0.0152	
4	10/16	Ash	1.22	0.24	245.34	0.45	1279	788	155	in	off	0.0077	
5	10/18	Ash	1.40	0.28	178.73	0.71	1278	901	157	in	off	0.0143	
6	10/23	Ash	0.60	0.12	233.11	0.23	1687	1352	156	in	off	0.0921	

Tests	Date	Slurry Type	Slurry Rate (lb/min)	Ash/Alum Rate (lb/min)	Fue Gas Flowrate (SCFM) dry	Expected Loading (g/SCF)	ESP Inlet Temp. (F)	ESP Outlet Temp. (F)	ESP Pressure (psig)	ESP Sample Port	ESP Power	Actual Loading (g/SCF)	Efficiency %
7	10/23	Alumina	0.40	0.04	237.82	0.08	1678	1382	156	in	off	0.0096	
8	10/29	Alumina	0.72	0.07	192.71	0.17	1702	1425	184	in	off	0.0047	
9	10/29	Alumina	0.91	0.09	193.37	0.21	1732	1400	174	in	off	0.0567	
10	10/29	Alumina	0.84	0.08	199.66	0.19	1724	1380	178	in	off	0.0673	
11	10/29	Alumina	0.88	0.09	201.55	0.20	1762	1389	173	in	off	0.0960	
12	10/30	Alumina	0.77	0.08	200.31	0.17	1840	1409	169	out	off	0.0279	
13	10/30	Alumina	0.78	0.08	201.97	0.19	1830	1412	177	out	off	0.0079	
14	10/30	Alumina	1.00	0.10	202.07	0.22	1660	1386	178	out	off	0.0150	
15	10/30	Alumina	0.9	0.10	184.31	0.23	1760	1392	163	out	off	0.0286	

Tests	Date	Slurry Type	Slurry Rate (lb/min)	Ash/Alum Rate (lb/min)	Flue Gas Flowrate (SCFM) dry	Expected Loading (g/SCF)	ESP Inlet Temp. (F)	ESP Outlet Temp. (F)	ESP Pressure (Psig)	ESP Sample Port	ESP Power	Actual Loading (g/SCF)	Efficiency %
16	10/30	Alumina	0.87	0.09	184.34	0.21	1760	1392	163	in	off	0.3033	96.2
17	10/30	Alumina	0.82	0.08	185.42	0.20	1788	1414	172	out	on	0.0114	
18	10/30	Alumina	0.81	0.08	186.13	0.20	1788	1417	172	in	off	0.1071	80.6
19	10/31	Alumina	0.77	0.08	185.47	0.19	1739	1360	177	out	off	0.0208	
20	10/31	Alumina	0.75	0.08	186.16	0.18	1756	1330	174	out	on	0.0051	95.2
21	10/31	Alumina	0.76	0.08	191.41	0.18	1730	1390	171	in	off	0.0759	69.8
22	10/31	Alumina	0.74	0.07	190.70	0.18	1743	1390	171	out	off	0.0229	
23	10/31	Alumina	0.76	0.08	193.18	0.18	1732	1386	178	in	off	0.0778	97.6
24	10/31	Alumina	0.72	0.07	194.40	0.17	1736	1376	178	out	on	0.0019	
25	10/31	Alumina	0.73	0.07	194.50	0.17	1759	1376	169	in	off	0.0825	74.2
26	10/31	Alumina	0.72	0.07	194.21	0.17	1763	1383	167	out	off	0.0213	
27	10/31	Alumina	0.66	0.07	193.84	0.15	1768	1395	171	in	off	0.0620	97.9
28	10/31	Alumina	0.65	0.07	192.95	0.15	1773	1389	173	out	on	0.0013	

Tests	Date	Slurry Type	Slurry Rate (lb/min)	Ash/Alum Rate (lb/min)	Flue Gas Flowrate (SCFM) dry	Expected Loading (g/SCF)	ESP Inlet Temp. (F)	ESP Outlet Temp. (F)	ESP Pressure (Psig)	ESP Sample Port	ESP Power	Actual Loading (g/SCF)	Efficiency %
29	11/01	Alumina	1.21	0.12	277.86	0.20	1699	1367	172	in	off	0.1280	67.3
30	11/01	Alumina	1.20	0.12	276.88	0.20	1702	1363	170	out	off	0.0419	
31	11/01	Alumina	1.21	0.12	277.23	0.20	1704	1341	170	in	off	0.1002	92.2
32	11/01	Alumina	1.24	0.12	278.94	0.20	1710	1340	167	out	on	0.0078	
33	11/01	Alumina	1.18	0.12	278.49	0.19	1689	1341	166	in	off	0.1014	41.0
34	11/01	Alumina	1.20	0.12	279.10	0.20	1691	1336	166	out	off	0.0598	
#35	11/01	Alumina	1.47	0.15	281.40	0.24	1786	1355	168	in	off	0.1832	44.4
36	11/01	Alumina	1.34	0.13	280.75	0.22	1752	1351	169	out	off	0.1019	
37	11/01	Alumina	1.47	0.15	281.40	0.24	1786	1355	168	in	off	0.1832	88.8
38	11/01	Alumina	1.44	0.14	280.27	0.23	1749	1342	166	out	on	0.0206	
37	11/01	Alumina	1.47	0.15	281.40	0.24	1786	1355	168	in	off	0.1832	95.9
##39	11/01	Alumina	1.20	0.12	277.41	0.20	1774	1348	171	out	on	0.0075	
##40	11/01	Alumina	1.30	0.13	279.15	0.21	1734	1340	172	out	on	0.0087	95.3

Thimble RL3 of test #35 cracked, substituted test #35 with test #37

Particle Charge Measurement Test

Table II

Summary of ESP Collection Efficiency
Shakedown Testing Using Alumina

Date	Velocity fps	Inlet Load gr/DSCF	Pressure ATM	Inlet Temp F	Outlet Temp F	Voltage kV	Capture Efficiency	Water Vapor %
10/30/91	4.9	4.66	11.5	1795	1418	30	0.962	21
10/31/91	4.9	1.65	11.5	1795	1418	0	0.806	21
10/31/91	4.9	1.65	11.5	1765	1350	30	0.952	21
10/31/91	4.9	1.17	11.4	1741	1400	0	0.699	21
10/31/91	4.9	1.19	11.8	1740	1384	30	0.975	21
10/31/91	4.9	1.27	10.9	1776	1393	0	0.741	21
10/31/91	4.9	0.95	11.5	1760	1391	30	0.979	21
10/31/91	7.3	1.97	11.1	1707	1381	0	0.672	18
10/31/91	7.3	1.54	11.1	1707	1381	30	0.922	18
11/1/91	7.3	1.56	11.1	1692	1351	0	0.410	18
11/1/91	7.3	2.82	11.1	1773	1341	30	0.888	18
11/1/91	7.3	2.82	10.9	1769	1326	30	0.959	18
11/1/91	7.3	2.82	10.9	1763	1372	30	0.952	18

Table III

Summary of Physical Parameters
in Shakedown Testing

	Specific Collection Area	ESP Particulate Collection Effic.	Tube Velocity	Particle Residence Time	Mechanical Collection Effic.
High flow condition	181 min/ft	92.3% @30 kV/inch	7.3 ft/s	0.68 S	50.6%
Low flow condition	272 min/ft	96.7% @30 kV/inch	4.9 ft/s	1.02 sec	74.9%

Note: Collection tube area

4" ID = 0.33 ft

5' length = 5.18 ft²Total area (4 tubes) = 20.7 ft²

Table IV

Cascade Impactor Data of ESP Inlet Sampling Alumina
 Run #1, Nov 01, 1991
 Conditions 350° F, and 15 atm.

Impactor Stage	Tare (g)	Final (g)	Net (g)	% in Size Range	% Cumulative Less Than Size Range	Effective Cut Diameter
	30.7396	31.111	0.018			
1	21.0894	21.4863	0.3969	29.034	70.966	5.0
2	22.0720	22.3042	0.2322	16.986	53.980	3.1
3	22.5866	22.8277	0.2411	17.637	36.342	2.1
4	15.3450	15.4600	0.1150	8.413	27.930	1.5
5	11.1713	11.2213	0.0500	3.658	24.272	0.9
6	11.0905	11.1007	0.0102	0.746	23.526	0.5
7	11.2119	11.2150	0.0031	0.227	23.299	0.31
8	21.6190	21.6214	0.0024	0.176	23.124	0.21
Filter	0.164	0.4796	<u>0.3161</u>	23.124	0.000	
			1.3670			

END

**DATE
FILMED**

9/16/92