STA 4

AUG 25 1994

ENGINEERING DATA TRANSMITTAL

Page 1 of 1

1. EDT

600611

2. To: (Receiving Organization) Distribution		3. From: (Originating Organization) IRM Chemical & Waste Management Software Support		4. Related EDT No.: 159986							
5. Proj./Prog./Dept./Div.: 62610		6. Cog. Engr.: D. A. Barnes		7. Purchase Order No.: N/A							
8. Originator Remarks: Tank Monitor and Control System (TMACS) Software Test Procedures TP011 and TP012, for approval/release. See related TMACS Test Procedures in ECN 196862.				9. Equip./Component No.: N/A							
				10. System/Bldg./Facility: TMACS/2750E/200E							
11. Receiver Remarks:				12. Major Assm. Dwg. No.: N/A							
				13. Permit/Permit Application No.: N/A							
				14. Required Response Date: 5/31/94							
15. DATA TRANSMITTED											
(A) Item No.	(B) Document/Drawing No.	(C) Sheet No.	(D) Rev. No.	(E) Title or Description of Data Transmitted	(F) Impact Level	(G) Reason for Trans- mittal	(H) Origina- tor Dispo- sition	(I) Receiv- er Dispo- sition			
1	WHC-SD-WM-TRP-201	ALL	0	TP011: TMACS Panalarm Interface	Q	1	1				
2	WHC-SD-WM-TRP-202	ALL	0	TP012: Panalarm Software Bridge	Q	1	1				
16. KEY											
Impact Level (F)		Reason for Transmittal (G)			Disposition (H) & (I)						
1, 2, 3, or 4 (see MRP 5.43)		1. Approval 2. Release 3. Information 4. Review 5. Post-Review 6. Dist. (Receipt Acknow. Required)			1. Approved 2. Approved w/comment 3. Disapproved w/comment 4. Reviewed no/comment 5. Reviewed w/comment 6. Receipt acknowledged						
(G)	(H)	17. SIGNATURE/DISTRIBUTION (See Impact Level for required signatures)						(G)	(H)		
Reason	Disp.	(J) Name	(K) Signature	(L) Date	(M) MSIN	(J) Name	(K) Signature	(L) Date	(M) MSIN	Reason	Disp.
1	1	Cog. Eng. DA Barnes	<i>David Barnes</i>	6/6/94		IRM Manager RB Bass	<i>RB Bass</i>	6/3/94	41-01	1	1
1	1	Cog. Mgr. JS Schofield	<i>JS Schofield</i>	6/15/94		V&V Independent Reviewer JR Freer				1	
1	1	User, If Operations R Ni		7/16/94		I&C CC Scaief	<i>C.C. Scaief</i>	6-7-94		1	1
1	1	QA JA Warren	<i>JA Warren</i>	6/7/94		Software Project Manager DG Spurling	<i>DG Spurling</i>	6/3/94	RI-01	1	1
		Safety									
		Env.									
18. Signature of EDT Originator		19. Authorized Representative for Receiving Organization		20. Cognizant/Project Engineer's Manager		21. DOE APPROVAL (if required) Ltr. No. ☐ Approved ☐ Approved w/comments ☐ Disapproved w/comments					

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED
BD-7400-172-1 (07/91)

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

RELEASE AUTHORIZATION

Document Number: WHC-SD-WM-TRP-202, REV 0

Document Title: TMACS TEST PROCEDURE TP012: PANALARM SOFTWARE BRIDGE

Release Date: 8/25/94

* * * * *

This document was reviewed following the
procedures described in WHC-CM-3-4 and is:

APPROVED FOR PUBLIC RELEASE

* * * * *

WHC Information Release Administration Specialist:

Kara Broz

(Signature)

8/25/94

(Date)

SUPPORTING DOCUMENT		1. Total Pages 16
2. Title TMACS Test Procedure TP012: Panalarm Software Bridge	3. Number WHC-SD-WM-TRP-202	4. Rev No. 0
5. Key Words Software, Test Procedure, Tank Monitor and Control System, TMACS Software Project APPROVED FOR PUBLIC RELEASE <i>KMB 8/25/94</i>	6. Author Name: S. J. Washburn <i>Steven J Washburn</i> Signature Organization/Charge Code 62610/N46G1	
7. Abstract The TMACS Software Test Procedures translate the project's acceptance criteria into test steps. The TMACS Test Plan (WHC-SD-WM-TP-148) is fulfilled when all Test Cases are approved. This Test Procedure tests the TMACS Panalarm Interface functions.		
8. PURPOSE AND USE OF DOCUMENT - This document was prepared for use within the U.S. Department of Energy and its contractors. It is to be used only to perform, direct, or integrate work under U.S. Department of Energy contracts. This document is not approved for public release until reviewed. PATENT STATUS - This document copy, since it is transmitted in advance of patent clearance, is made available in confidence solely for use in performance of work under contracts with the U.S. Department of Energy. This document is not to be published nor its contents otherwise disseminated or used for purposes other than specified above before patent approval for such release or use has been secured, upon request, from the Patent Counsel, U.S. Department of Energy Field Office, Richland, WA. DISCLAIMER - This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.		10. RELEASE STAMP <div style="border: 1px solid black; padding: 5px; text-align: center;"> OFFICIAL RELEASE BY WHC DATE AUG 25 1994 <i>STA 4</i> </div>
9. Impact Level Q		

May 24, 1994

WHC-SD-WM-TRP-202 Rev. 0 Page 1

TP012 Rev. 0

TANK MONITOR AND CONTROL SYSTEM
(TMACS)
SOFTWARE PROJECT

TEST PROCEDURE TP012:
PANALARM SOFTWARE BRIDGE

Steven J. Washburn
IRM Chemical & Waste Management
Software Support

SIGN OFF:

<u>C.C. Scalf III</u>	<u>signature</u>	<u>6-7-94</u>
CC Scalf TMACS Program Engineer		Date
<u>DAVID BARNES</u>	<u>David Barnes</u>	<u>5/26/94</u>
DA Barnes TMACS Cognizant Engineer	signature	Date
<u>John Freer</u>	<u>signature</u>	<u>5/26/94</u>
WJ Jones IRM Software V&V		Date
<u>Dave Spurling</u>	<u>Dave Spurling</u>	<u>5/26/94</u>
DR Spurling TMACS Project Manager	signature	Date
<u>RB Bass</u>	<u>signature</u>	<u>6/3/94</u>
RB Bass IRM Manager		Date

May 24, 1994

TP012 Rev. 0

1.0 TEST ITEMS

This Test Procedure addresses the testing of the functionality of the TMACS Panalarm bridge software. The features to be tested are given in the test case below:

Table 1. Test Cases

5.1 Bridge Initialization Options	4
5.2 Bridge Communication	5
5.3 Bridge Performance	6
5.4 Testing Checksum Errors	7
5.5 Testing Command Reject Errors	7

2.0 ACCEPTANCE CRITERIA AND REQUIREMENTS

The acceptance criteria for this Test Procedure are taken from the requirements section of the Panalarm Bridge Software Action Plan.

Note: Verification of Test Cases 5.4 and 5.5 can not be performed, since emulation capability does not currently exist. These Test Cases will be waived to a later date.

3.0 TESTER INFORMATION

The TMACS system is an application built using the G2 Real-Time Expert System. The instructions for using the mouse, mouse buttons, and keyboard are given below.

The majority of user control of the system involves pointing at objects on the computer screen using the POINTER. The pointer is an arrow that is pointing to the upper left of the screen. When a user moves the mouse, the pointer moves on the screen.

The G2 system treats the left and right mouse buttons as if they were a single button. Whenever the use of a mouse button is required the user is free to use either of these buttons.

The following terms are used to describe actions performed with the mouse:

- To move the pointer, slide the mouse with no buttons pressed.
- To point to a push-button or object, move the pointer to the appropriate place on the screen.
- To click on an object, first move your mouse so that the screen pointer rests on the object. Then, press the mouse button and release immediately without moving the mouse.
- To drag an object with the mouse, first move the mouse so that the screen pointer rests on the object. Then, press the mouse button and move the mouse without releasing the button. The object moves along with the screen pointer as you move the mouse. Release the button when the object is in the desired place. To drag a window in TMACS place the

May 24, 1994

TP012 Rev. 0

mouse in a blank area around the margin of the window and drag. (Note: the drag function is not provided for all windows.)

If the G2 screen becomes unreadable or objects overwrite each other the screen can be redrawn by typing Control-C. (Hold down the "Control" key while typing the letter C).

4.0 PRE-TEST INSPECTION AND SETUP REQUIREMENTS

This Test Procedure uses G2 software developed for production use, and can be identified in three parts as `"/home/G2/TMACS/prod/TMACS_Release_x_x.KB"` (where `x_x` refers to the current revision number, with only one file in the directory matching the template), `"/home/G2/BRIDGE/acromag_brg"` (Acromag driver), `"/home/G2/BRIDGE/panalm_brg"` (Panalarm driver), `"/home/G2/BRIDGE/printer_brg"` (alarm printer driver) and on the SACS Sybase production machine (tfs8) the G2 Sybase bridge `"/local/G2/sybase/gsisyb3"`.

This Test Procedure interacts with one local Panalarm cabinet (number 1) which is connected to line 0 of a code operated switch through port 7 of the serial multiplexor attached to the TMACS slave workstation.

It is assumed that at least an 8 port serial multiplexor is attached to the "Slave" workstation and that the Panalarm bridge can function through each of its ports.

To communicate with the local Panalarm cabinet the Test Administrator, hereafter referred to as TA, must perform the following steps:

1. Make sure the TMACS Slave workstation which runs the Panalarm bridge software is connected to local Panalarm unit corresponding to port 7 of the serial multiplexer.
2. Connect the PC serial analyzer software into the communication link between the Sun workstation multiplexer and the Panalarm unit. Start the analyzer running so that both the Received and Transmitted data streams are displayed.
3. Start the Panalarm bridge from a Unix command tool on the TMACS Slave workstation. To do this you must go to the directory `"/home/G2/BRIDGE/PANALM"` and enter the command `"panalm_brg 23007"`.

May 24, 1994

TP012 Rev. 0

5.0 TEST STEPS WITH EXPECTED RESULTS

STEP	DESCRIPTION	VERIFY
5.1 Bridge Initialization Options		
1	<p>Select the PANALARM-WS workspace from the Main G2 Menu. Then select the PANALARM-PRODUCTION-INTERFACES subworkspace. Examine the PANALARM-INTERFACE-1 object and verify that the GSI Interface Connection string is as follows: "tcp-ip host 'tfs10' port number 23007". This indicates that communication between the bridge and device is through tcp-ip and the host computer is Slave workstation tfs10 communicating through serial port 23007. Also verify that the remote process initialization string on the Panalarm GSI interface object is as follows: "-d /dev/cuc7 -s 9600 -p n -b 8 -h 1 -j 0 -t n -q n -n 0 -e y -r 1". This indicates that the device name is /dev/cuc7, the baud rate is 9600, the parity is none, bits per character is 8, stop bits are 1, parity is not being used, no time stamping, no debug mode, return sensor value to G2 only when it has changed from previous value (exception reporting) and finally perform only 1 retry after command response rejection or checksum error.</p>	JRF
2	<p>The verify that the remote process initialization string on the Panalarm GSI interface object is as follows: "-d /dev/cuc7 -s 9600 -p n -b 8 -h 1 -j 0 -t n -q n -n 0 -e y -r 1". This indicates that the device name is /dev/cuc7, the baud rate is 9600, the parity is none, bits per character is 8, stop bits are 1, parity is not being used, no time stamping, no debug mode, return sensor value to G2 only when it has changed from previous value (exception reporting) and finally perform only 1 retry after command response rejection or checksum error.</p>	JRF

STEP	DESCRIPTION	VERIFY
5.2 Bridge Communication		
3	<p>Verify on the serial analyzer that <u>commands sent</u> by the Panalarm bridge to the Panalarm cabinet are in the form of hexadecimal (hex) binary digits:</p> <p style="text-align: center;">[AC][LINE][BL][CC][FCN][CS]</p> <p>where [AC] is the code operated switch arming character (which should be 01), [LINE] is the ASCII representation of the code switch line number to use (which should be 30, ASCII zero), [BL] is a 2 hex block length of the command in bytes, [CC] is a 2 hex digit Panalarm cabinet number (01), [FCN] is the Panalarm function number (23), [data....] is the hex digit data for each Panalarm alarm panel, and [CS] is the two hex digit checksum value of the command. A typical line should look as follows:</p> <p style="text-align: center;">[01][30][02][01][23][DC]</p> <p>where the square brackets are included to improve readability but should not appear in the command.</p> <p>Verify that the <u>command responses</u> from the Panalarm annunciator to the Panalarm bridge are in the form of hexadecimal digits as given below:</p> <p style="text-align: center;">[BL][CC][FCN][CPCNT][RCS][HCPS]...[CS]</p> <p>where [BL] is the block length of the response in bytes, [CC] is the cabinet number, [FCN] is the Panalarm function number data is being returned for, [CPCNT] is the number of CP cards in the cabinet, [RCS] is the number of rows and columns in, [HCPS]... is a stream of two hexadecimal digits representing the value for each card, and [CS] is the two digit hexadecimal checksum value of the command response. A typical line should look as follows:</p> <p style="text-align: center;">[54][01][23][50][2A][10][00][00][00]...[E2]</p> <p>where the square brackets are included to improve readability but should not appear in the command response.</p>	<p>JRF</p> <p>JRF</p> <p>JRF</p>

May 24, 1994

TP012 Rev. 0

STEP	DESCRIPTION	VERIFY
4	Have the TA select the PANALARM-DEVELOPMENT-CABINETS subworkspace of the PANALARM-WS. Then get the subworkspace of DEV-CAB-1 to pull up the Test Control Panel #1. Verify that all 8 sensors are green and not flashing and that their last recorded values are "0, valid indefinitely".	JMF
5	Have the test administrator change the state of 3 sensors on the local Panalarm Annunciator to be in alarm. Record the names of the three sensors here: Sensor Name #1: <u>Test-R1-C3</u> Sensor Name #2: <u>Test-R1-C5</u> Sensor Name #3: <u>Test-R2-C2</u> Verify that the states of these sensors change by observing that they turn to flashing red and their last recorded value is "1, valid indefinitely". Also observe that data agrees on the PC serial analyzer.	JMF
6	Have the test administrator change the state of the above 3 sensors on the local Panalarm Annunciator to normal. Verify that the states of these sensors change by observing that they turn to flashing green and their last recorded value is now "0, valid indefinitely".	JMF

5.3 Bridge Performance

7	From the PANALARM-WS workspace select the Panalarm-development cabinet subworkspace. On this workspace you will see several Panalarm cabinet objects set up for the development mode. Select one of the cabinets to examine and verify that the last recorded value attribute is 1 and has not expired. Also verify that the time of the last recorded value when updated does not increase by more than 3 seconds. This is with the Acromag bridge (port 5) running. With the bridge not running the update time will increase by less than 3 seconds.	JMF
---	---	-----

STEP	DESCRIPTION	VERIFY
5.4 Testing Checksum Errors		
8	Set up the Panalarm emulator to generate single checksum errors at a fixed time interval. Verify that every time a checksum is generated the Panalarm bridge does a retry.	See Exception
9	Set the emulator to generate two consecutive checksum errors for the same data request. Verify that when two consecutive checksum errors are sent for the same sensor that a white alarm stating a Checksum error has occurred is displayed on the G2 MOST RECENT ALARM window. Because of G2 internal data verification an internal alarm message will be generated stating TMACS has lost communication with that cabinet. This message will supersede the checksum error message on the "MOST RECENT ALARM" window. Therefore, to see the first white alarm (from the Bridge) you will need to get into the alarm summary paging mode by clicking on the "CURRENT ALARMS" button on the CONTROL PANEL. Then you will need to page through the alarms until you see the specified checksum error message.	Page 11 a.

5.5 Testing Command Reject Errors		
10	Set up the Panalarm emulator to generate a single command reject errors at a fixed time interval. Choose the error to be generated by examining the Appendix. Record the reject code to be tested _____. Verify that every time this reject error is generated by the emulator the Panalarm bridge does a retry.	See Exception Page 11 b.

May 24, 1994

TP012 Rev. 0

STEP	DESCRIPTION	VERIFY
11	<p>Set the emulator to generate two consecutive reject errors for the same data request.</p> <p>Verify that when two consecutive reject errors are sent for the same sensor that a white alarm stating a reject error has occurred is displayed on the G2 MOST RECENT ALARM window. Because of G2 internal data verification an internal alarm message will be generated stating TMACS has lost communication with that cabinet. This message will supersede the reject error message on the "MOST RECENT ALARM" window. Therefore, to see the first white alarm (from the Bridge) you will need to get into the alarm summary paging mode by clicking on the "CURRENT ALARMS" button on the CONTROL PANEL. Then you will need to page through the alarms until you see the specified reject error message.</p>	<p>See Exception p. 11 b</p>

6.0 REFERENCES

- [1] *RS422 Communications Option - Installation, Programming and Operating Instructions*, 1988, Document # 900316, Revision 10 (ECN 10623-02), Ametek Inc., Panalarm Division, Skokie, Illinois.
- [2] *Panalarm Series 90 Annunciator Systems Instruction and Operating Manual*, August 1992, Document # 900250, Revision 8 (ECN 11105), Ametek Inc., Panalarm Division, Skokie, Illinois.
- [3] *Code Operated Switch II*, December 1992, Document # SW590A-R2, Black Box Corp., Pittsburgh, Pennsylvania.

7.0 ATTACHMENTS

Appendix: Panalarm ERROR CODES/MESSAGES
 Acceptance Sheet
 Exception Sheets
 Data/Verification Sheet
 Test Log

APPENDIX: Panalarm Error Codes/Messages

Error Code	Error Message
01	[Panalarm Error]:01: The 90CPX Card in this Cabinet is not responding
02	[Panalarm Error]:02: Undefined Host Computer Request
03	[Panalarm Error]:03: The Hosts Command Checksum was in Error
04	[Panalarm Error]:04: 90CPC Transmit Fault, checksum or format
05	[Panalarm Error]:05: Requested FCN lost, no 90CPX RAM available
06	[Panalarm Error]:06: Not enough 90CPX RAM to store all data
07	[Panalarm Error]:07: Analog card clear, point monitoring down
08	[Panalarm Error]:08: 90CPX Checksum Fault detected by 90CPC
09	[Panalarm Error]:09: Cabinet PRIORITY mode enabled
10	[Panalarm Error]:10: Not Used - No Error
11	[Panalarm Error]:11: CP status not received on 2 consecutive polls
12	[Panalarm Error]:12: Invalid Error Code
13	[Panalarm Error]:13: Invalid Error Code
14	[Panalarm Error]:14: Invalid Error Code
15	[G2 Init Error]:15: Too Many Connections between G2 and Bridge
16	[G2 Init Error]:16: Invalid Acknowledge Checksum Specification
17	[G2 Init Error]:17: Invalid Max. Bits Per Character Specification
18	[G2 Init Error]:18: Invalid Exception Reporting Specification
19	[G2 Init Error]:19: Invalid Number of Stop Bits Specification
20	[G2 Init Error]:20: Invalid Parity Request Specification
21	[G2 Init Error]:21: Invalid Naptime Specification
22	[G2 Init Error]:22: Invalid Parity Type Specification
23	[G2 Init Error]:23: Invalid Debug Request Specification
24	[G2 Init Error]:24: Invalid Number of Retries Specification
25	[G2 Init Error]:25: Invalid Baud Rate Specification
26	[G2 Init Error]:26: Invalid Timestamping Request Specification

May 24, 1994

TP012 Rev. 0

Error Code	Error Message
27	[G2 Init Error]:27: Invalid Watchdog time Specification
28	[G2 Init Error]:28: Invalid Switch Setting Specified
29	[G2 Init Error]:29: Attempt to Connect to Port Failed
30	[G2 Error]:30: Illegal Code Switch Line Number Received
31	[G2 Error]:31: Illegal Panalarm Cabinet Number Received
32	[G2 Error]:32: Illegal Panalarm Row Number Received
33	[G2 Error]:33: Illegal Panalarm Column Number Received
34	[G2 Error]:34: Illegal Panalarm Slot Number Received
35	[G2 Error]:35: Creation of Panalarm Object Failed
36	[G2 Error]:36: Invalid Error Code
37	[G2 Error]:37: Invalid Error Code
38	[G2 Error]:38: Invalid Error Code
39	[G2 Error]:39: Invalid Error Code
40	[G2 Error]:40: Bad Read - unable to interpret Panalarm data
41	[G2 Error]:41: No GSI Object to correspond with this Object Index
42	[G2 Error]:42: The TMACS COULD NOT Communicate with this Cabinet
43	[G2 Error]:43: No Panalarm Object Defined for this GSI variable
44	[G2 Error]:44: Bad Unit
45	[G2 Error]:45: Failure in Accessing Cabinet: Check Cabinet Power
46	[G2 Error]:46: Checksum Error Received from Panalarm Cabinet
47	[G2 Error]:47: Unrecognized Function Code returned by Panalarm
48	[G2 Error]:48: Invalid Error Code
49	[G2 Error]:49: Invalid Error Code
50	[G2 Error]:50: Invalid Error Code

May 24, 1994

TP012 Rev. 0

EXCEPTION SHEET

TEST PROCEDURE NUMBER: TP012

STEP#: 5.4

DATE: 5/26/94

DESCRIPTION:

Panalarm emulator does not exist - so
testing could not be run

RESOLUTION:

DATE RESOLVED: 5/26/94

This feature will be tested in a future release. A Panalarm
emulator program is being developed similar to the Acromag
emulator program.

Note: This exception is not a result of a failure, but of an
inability to verify correct functionality.

APPROVAL:

Patrick Faulstich
TMACS Software Test Procedure Tester

5/26/94
Date

John Freer
TMACS Software Test Procedure Witness

5/26/94
Date

Steven J Washburn
SJ Washburn, TMACS Test Procedure Software Engineer

5/26/94
Date

Dave Spurling
DG Spurling, TMACS Software Project Manager

5/26/94
Date

May 24, 1994

TP012 Rev. 0

EXCEPTION SHEET

TEST PROCEDURE NUMBER: TP012

STEP#:

5.5 Testing (common) 10-11
ERAS Step

DATE:

5/26/94

DESCRIPTION:

Panalarm emulator does not exist - so
testing could not be run.

RESOLUTION:

DATE RESOLVED:

5/26/94

This feature could not be verified, since Panalarm communication
can not be emulated. This will be tested in a future release.

APPROVAL:

PATRICK SCANLAN Patrick Scanlan

Date

5/26/94

John Freer

Date

5/26/94

TMACS Software Test Procedure Witness

Steven J Washburn

Date

5/26/94

SJ Washburn, TMACS Test Procedure Software Engineer

Dave Spurling

Date

5/26/94

DG Spurling, TMACS Software Project Manager

May 24, 1994

TP012 Rev. 0

Note: Test Cases 5.4 (Checksum Testing) and 5.5 (Command Reject Errors) are being deferred to a ^{later} release. **ACCEPTANCE SHEET** AA

TEST PROCEDURE NUMBER: TP012

DATE: 5/26/94

ORGANIZATION NAME: Chem & Waste Mgmt SW Spt.

ORG#: 62610

EXCEPTION SHEETS FOR THIS TEST PROCEDURE:

TESTER	WITNESS	STEP	DATE	RESOLVED
PKS	JRF			
PKS	JRF	8-9	5/26/94	
PKS	JRF	10-11	5/26/94	

COMMENTS:

All of the test steps of this test procedure have been tested and exception sheets for this test procedure have been resolved.

APPROVAL:

 Patricia A. Seaman
 TMACS Software Test Procedure Tester
 Date: 5/26/94

 John Freese
 TMACS Software Test Procedure Witness
 Date: 5/26/94

 Steven J. Washburn
 SJ Washburn, TMACS Test Procedure Software Engineer
 Date: 5/26/94

 Dave Spurling
 DG Spurling, TMACS Software Project Manager
 Date: 5/26/94

 C. P. Scaief
 CC Scaief, TMACS Program Engineer
 Date: 6-7-94

May 24, 1994

TP012 Rev. 0

DATA/VERIFICATION SHEET

This Sheet provides a record of Personnel who are involved in testing, data recording, verifying, and evaluating the Test Procedure. This form needs to be completed before a formal test is begun.

DIRECTIONS:

Print the name, sign, initial, and date the below lines of the participants.

TEST PROCEDURE NUMBER: TP012

PAT SCANLAN Patrick Scanlan PKS 5/26/94
 Tester / Organization Initials Date

John Freer JF 5/26/94
 Witness / Organization Initials Date

Steven J Washburn sjw 5/26/94
 SJ Washburn, TMACS Test Procedure Software Engineer Initials Date

Dave Spurling DS 5/26/94
 DG Spurling, TMACS Software Project Manager Initials Date

 Name / Organization Initials Date

 Name / Organization Initials Date

 Name / Organization Initials Date

May 24, 1994

TP012 Rev. 0

TEST LOGTEST PROCEDURE NUMBER: TP012Date: 5/26/94TESTER: Patrick S. SullivanWITNESS: JNF**TEST LOG NOTES:**

Unable to run steps 8, 9, 10 & 11 because
no emulator exists.

COMMENTS: