OCRWM

DESIGN CALCULATION OR ANALYSIS COVER SHEET

1. QA: QA

2. Page 1

3. System

Monitored Geologic Repository

4. Document Identifier

000-HYC-MGR0-00100-000-00B

5. Title

GROA Airborne Release Dispersion Factor Calculation

6. Group

Preclosure Safety Analysis

7. Document Status Designation

Preliminary

Final

Cancelled

8. Notes/Comments

An interdisciplinary review (LP-2.14Q-BSC) is not required since the results of this calculation have no significant impact on the use of the technical output by other organizations.

Updated design of DTF, CHF, FHF, Aging Facilities and GROA layout are incorporated and conservative approach for event sequences from ground level releases are included in this Calculation. This is an extensive revision due to changes of cited reference designs.

Attachments

Total Number of Pages

Attachment I

17

Attachment II

18

Attachment III

3

Attachment IV (includes CD 1 of 1, all files dated 3/09/2005)

56

RECORD OF REVISIONS

9. No.	10. Reason For Revision	11. Total # of Pgs.	12. Last Pg. #	13. Originator (Print/Sign/Date)	14. Checker (Print/Sign/Date)	15. QER (Print/Sign/Date)	16. Approved/Accepted (Print/Sign)	17. Date
00A	Initial issue	125	IV-54	J Wang	Y Yuan	DJ Tunney	DC Richardson	9/7/2004
00B	Updated references to facility layouts and, updated related input parameters. Included the requested calculation results of 95 th percentile dispersion factor for use in event sequences assessments.(see block 8) Sketch references (Attachment II) have been changed to approved drawings in response to Condition Report 4353.	136	IV-56	J Wang <i>[Signature]</i> 3/21/2005	Y Yuan <i>[Signature]</i> 3/21/2005	DJ Tunney <i>[Signature]</i> 3/21/2005	DC Richardson <i>[Signature]</i> 3/21/2005	3/21/2005

INTENTIONALLY LEFT BLANK

CONTENTS

	Page
ACRONYMS.....	7
1. PURPOSE.....	8
2. QUALITY ASSURANCE	8
3. METHOD	8
3.1 ATMOSPHERIC DISPERSION FACTORS	8
3.2 ARCON96 MODEL	8
4. DESIGN INPUTS AND ASSUMPTIONS	9
4.1 DESIGN INPUTS.....	9
4.1.1 Receptors and Releases.....	9
4.1.2 Stack Radius	11
4.1.3 Intake Height.....	12
4.1.4 Building Height.....	12
4.1.5 Building Area.....	12
4.1.6 Elevation Difference	13
4.1.7 Release Flow.....	13
4.1.8 Meteorological Data	13
4.1.9 Area Source Modeling for Aging Facilities.....	14
4.1.10 Default Values	14
4.2 ASSUMPTIONS.....	15
4.2.1 Release Type.....	15
4.2.2 Building Design of Dry Transfer Facility #2.....	15
4.2.3 Release Height	15
4.2.4 Release Exit Velocity.....	16
4.2.5 Initial Vertical Diffusion Coefficient of Aging Facilities Releases.....	16
5. USE OF COMPUTER SOFTWARE.....	16
5.1 SOFTWARE APPROVED FOR QUALITY ASSURANCE WORK	16
5.2 EXEMPT SOFTWARE.....	17
6. CALCULATIONS AND RESULTS	17
6.1 INPUT AND OUTPUT FILENAMES.....	18
6.2 SUMMARY OF INPUT PARAMETER VALUES.....	18
6.3 χ/Q CALCULATION RESULTS	19
7. REFERENCES.....	39
8. ATTACHMENTS	42

FIGURES

	Page
Figure 1. Zone of Influence for Stacks.....	12
Figure II-1. Stack/Release and Intake Locations of GROA Facilities	II-1
Figure II-2a. DTF1 and Remediation Facilities General Arrangement (Operating Floor)	II-2
Figure II-2b. DTF1 and Remediation Facilities General Arrangement (Section P)	II-3
Figure II-2c. DTF1 and Remediation Facilities General Arrangement (Section A).....	II-4
Figure II-2d. DTF1 and Remediation Facilities General Arrangement (Section B).....	II-5
Figure II-2e. DTF1 and Remediation Facilities General Arrangement (Section G).....	II-6
Figure II-2f. DTF1 and Remediation Facilities General Arrangement (Section K).....	II-7
Figure II-2g. DTF1 and Remediation Facilities General Arrangement (Section M)	II-8
Figure II-3a. Canister Handling Facility General Arrangement (Second Floor)	II-9
Figure II-3b. Canister Handling Facility General Arrangement (Sections A & B)	II-10
Figure II-3c. Canister Handling Facility General Arrangement (Sections K & L).....	II-11
Figure II-4a. Fuel Handling Facility General Arrangement (Operating Floor)	II-12
Figure II-4b. Fuel Handling Facility General Arrangement (Section A).....	II-13
Figure II-4c. Fuel Handling Facility General Arrangement (Sections C, D & G).....	II-14
Figure II-5. Transportation Cask Receipt/Return & Waste Package Receipt Facility General Arrangement (Sections D, E, F & G).....	II-15
Figure II-6. DTF1/Remediation Facility Ventilation Flow Diagram	II-16
Figure II-7. Canister Handling Facility Ventilation Flow Diagram.....	II-17
Figure II-8. Fuel Handling Facility Ventilation Flow Diagram	II-18

TABLES

	Page
Table 1. Major Release and Receptor Locations	10
Table 2. Calculation of Building Cross-Section Area.....	13
Table 3. Summary of Input Parameter Values to Run ARCON96	18
Table 4. χ/Q Calculation Results of Release 110	20
Table 5. χ/Q Calculation Results of Release 120	21
Table 6. χ/Q Calculation Results of Release 17A1	22
Table 7. χ/Q Calculation Results of Release 17A2	23
Table 8. χ/Q Calculation Results of Release 17B.....	24
Table 9. χ/Q Calculation Results of Release 17C.....	25
Table 10. χ/Q Calculation Results of Release 17D	26
Table 11. χ/Q Calculation Results of Release 17E.....	27
Table 12. χ/Q Calculation Results of Release 17F	28
Table 13. χ/Q Calculation Results of Release 17G	29
Table 14. χ/Q Calculation Results of Release 17H	30
Table 15. χ/Q Calculation Results of Release 17J.....	31
Table 16. χ/Q Calculation Results of Release 190	32
Table 17. χ/Q Calculation Results of Release 210	33
Table 18. χ/Q Calculation Results of Release ECRB.....	34
Table 19. χ/Q Calculation Results of Release ER1	34
Table 20. χ/Q Calculation Results of Release ER2	34
Table 21. χ/Q Calculation Results of Release ES1.....	34
Table 22. χ/Q Calculation Results of Release ES2.....	35
Table 23. χ/Q Calculation Results of Release ES3.....	35
Table 24. χ/Q Calculation Results of Release 110X	36
Table 25. χ/Q Calculation Results of Release 120X	37
Table 26. χ/Q Calculation Results of Release 210X	38
Table 27. List of Attachments.....	42
Table I-1. Major Inputs for the Release Source of DTF1 (110 and 110X)	I-2
Table I-2. Major Inputs for the Release Source of DTF2 (120 and 120X)	I-3
Table I-3. Major Inputs for the Release Source of North Aging Facility 17A (17A1)	I-4
Table I-4. Major Inputs for the Release Source of South Aging Facility 17A (17A2)	I-5
Table I-5. Major Inputs for the Release Source of Aging Facility 17B	I-6
Table I-6. Major Inputs for the Release Source of Aging Facility 17C	I-7
Table I-7. Major Inputs for the Release Source of Aging Facility 17D	I-8
Table I-8. Major Inputs for the Release Source of Aging Facility 17E.....	I-9
Table I-9. Major Inputs for the Release Source of Aging Facility 17F	I-10

Table I-10.	Major Inputs for the Release Source of Aging Facility 17G	I-11
Table I-11.	Major Inputs for the Release Source of Aging Facility 17H	I-12
Table I-12.	Major Inputs for the Release Source of Aging Facility 17J.....	I-13
Table I-13.	Major Inputs for the Release Source of Canister Handling Facility (190)	I-14
Table I-14.	Major Inputs for the Release Source of Fuel Handling Facility (210 and 210X)	I-15
Table I-15.	Major Inputs for the Release Source of Subsurface ECRB Exhaust Shaft.....	I-16
Table I-16.	Major Inputs for the Release Source of Subsurface Exhaust Raise #1	I-16
Table I-17.	Major Inputs for the Release Source of Subsurface Exhaust Raise #2.....	I-16
Table I-18.	Major Inputs for the Release Source of Subsurface Exhaust Shaft #1	I-17
Table I-19.	Major Inputs for the Release Source of Subsurface Exhaust Shaft #2	I-17
Table I-20.	Major Inputs for the Release Source of Subsurface Exhaust Shaft #3	I-17
Table III-1.	Calculation of 95th Percentile CFD.....	III-2
Table III-2.	Listing of χ/Q Cumulative Frequency Distributions from Source 110 to Receptor 14A	III-3
Table IV-1.	Names of Input and Output File for Surface Facility Releases ARCON96 Runs	IV-1
Table IV-2.	Names of Input and Output File for Event Sequences Releases ARCON96 Runs ARCON96 Runs	IV-3
Table IV-3.	Names of Input and Output File for Subsurface Releases ARCON96 Runs.....	IV-3
Table IV-4.	Files Used for ARCON96 Calculations on the Compact Disk	IV-4

ACRONYMS

χ/Q atmospheric dispersion factor or relative atmospheric concentration

ALARA As low as is reasonably achievable

ARCON96 CONcentrations in Building Wakes, V.96

CFD cumulative frequency distribution

CFR Code of Federal Regulations

CHF Canister Handling Facility

DTF Dry Transfer Facility

DTF1 Dry Transfer Facility #1

DTF2 Dry Transfer Facility #2

FHF Fuel Handling Facility

GROA Geologic Repository Operations Area

ITS Important to Safety

NRC U.S. Nuclear Regulatory Commission

PCSA Preclosure Safety Analysis

1. PURPOSE

The purpose of this document is to calculate airborne release dispersion factors (χ/Q) for the surface and subsurface facilities at the Geological Repository Operations Area (GROA). The calculated χ/Q values may be used to estimate radiological consequences to workers for potential releases from normal operations and event sequences for License Application.

The scope of this document is to provide estimates of χ/Q values at potential onsite receptors from facility releases, under normal operating conditions and event sequences.

2 QUALITY ASSURANCE

This document was prepared in accordance with AP-3.12Q, *Design Calculations and Analyses*. Since the results of this calculation will be used to support Preclosure Safety Analysis, this report is subject to the requirements of *Quality Assurance Requirements and Description* (DOE 2004 [171539], Section 2.2.2).

3. METHOD

3.1 ATMOSPHERIC DISPERSION FACTORS

The atmospheric dispersion factor (χ/Q) is the time averaged normalized air concentration at the receptor. It represents the dilution of an airborne contamination from atmospheric mixing and turbulence based on the atmospheric conditions, the relative configuration of the release point and the receptor, and the distance from the release point to the receptor of interest. The χ/Q is the ratio of the average contaminant air concentration at the receptor to the contaminant release rate at the release point. The average χ/Q values for receptors are calculated using the U.S. Nuclear Regulatory Commission (NRC)-sponsored computer code, Atmospheric Relative CONcentrations in Building Wakes, V.96 (ARCON96) (Ramsdell and Simonen 1997 [164547]). This computer code has been baselined in accordance with LP-SI.11Q-BSC [171923], *Software Management* (see Section 5.1).

3.2 ARCON96 MODEL

ARCON96 was developed by Pacific Northwest National Laboratory for the NRC to calculate χ/Q values in plumes for nuclear power plants at control room air intakes in the vicinity of the release point (Ramsdell and Simonen 1997 [164547]). ARCON96 implements a straight-line Gaussian dispersion model with dispersion coefficients that are modified to account for low wind meander and building wake effects. The code calculates normalized concentrations (χ/Q) using hourly meteorological data. These hourly values are averaged to form χ/Q s for various time

periods ranging from 2 hours to a much longer duration. The calculated values for each period are then used to form cumulative frequency distributions (CFDs).

The ARCON96 code accounts for variations in the location of release points and plume dispersion due to building wakes and plume meander under low wind speed conditions. For each receptor of interest, a CFD of χ/Q is constructed by the code for various release time periods (e.g., 2 hours, 4 hours, 8 hours, 12 hours, etc., or longer time periods). The 8,760-hour probabilistic χ/Q distribution may be used to determine the annual mean and median (50th percentile weather probability) χ/Q values for the receptor of interest. The 95 percentile χ/Q values may be used to assess conservatively the potential consequences under event sequences.

4. DESIGN INPUTS AND ASSUMPTIONS

4.1 DESIGN INPUTS

This section discusses various design parameters used to prepare inputs to ARCON96 calculation. The major input parameters are summarized in Tables I-1 through I-20.

4.1.1 Receptors and Releases

The waste handling facilities of the repository consist of multiple buildings constructed near the North Portal to the underground repository. Major facilities considered in this document are shown in Table 1. To simplify the naming convention, area numbers are used to identify the locations of release sources and receptors for ARCON96 calculation. Areas without designated numbers (e.g., subsurface facilities) are identified using simple abbreviation. Further breakdown within an individual location is annotated with an extra ending number (e.g., 110_2 for Intake #2 of Dry Transfer Facility #1).

A receptor of interest in this calculation is either an intake of a facility or a location where an onsite worker may be potentially exposed to the contaminated air effluent. For Dry Transfer Facility #1 (DTF1), Dry Transfer Facility #2 (DTF2) and Fuel Handling Facility (FHF), releases through a vent (routine operations) and at ground level (event sequences) are both analyzed. Aging Facilities are modeled as area sources (see 4.1.9). For Aging pad 17A, the facility is further equally divided into north and south parts due to elongated geometry.

The layout of GROA facilities is shown in Figure II-1. Detailed general arrangement of DTF1, CHF and FHF are shown in Figures II-2a through II-8. The potential receptors and release points are labeled on Figure II-1.

Table 1. Major Release and Receptor Locations

Abbreviation	Facility Description ¹
Release Source	
110	Stack of Dry Transfer Facility #1 (110)
110X ²	Ground level release of Dry Transfer Facility #1
120	Stack of Dry Transfer Facility #2 (120)
120X ²	Ground level release of Dry Transfer Facility #2
190	Stack of Canister Handling Facility (190)
210	Stack of Fuel Handling Facilities
210X ²	Ground level release of Fuel Handling Facilities
17A1	Area Source of North Portion of Aging Facility 17A
17A2	Area Source of South Portion of Aging Facility 17A
17B	Area Source of Aging Facility 17B
17C	Area Source of Aging Facility 17C
17D	Area Source of Aging Facility 17D
17E	Area Source of Aging Facility 17E
17F	Area Source of Aging Facility 17F
17G	Area Source of Aging Facility 17G
17H	Area Source of Aging Facility 17H
17J	Area Source of Aging Facility 17J
ER1	Subsurface Exhaust Raise #1
ER2	Subsurface Exhaust Raise #2
ES1	Subsurface Exhaust Shaft #1
ES2	Subsurface Exhaust Shaft #2
ES3	Subsurface Exhaust Shaft #3
ECRB	Subsurface ECRB Exhaust Shaft
Receptor	
110_1	Dry Transfer Facility #1 (110) Intake No. 1 (west side of DTF1)
110_2	Dry Transfer Facility #1 (110) Intake No. 2 (south side of DTF1/Remediation)
110_3	Dry Transfer Facility #1 (110) Intake No. 3 (south side of DTF1/Remediation)
120_1	Dry Transfer Facility #2 (120) Intake No. 1 (west side of DTF2)
120_2	Dry Transfer Facility #2 (120) Intake No. 2 (south side of DTF2/Remediation)
120_3	Dry Transfer Facility #2 (120) Intake No. 3 (south side of DTF2/Remediation)
120_4	Roof Center of Dry Transfer Facility #2
14A	Receipt/Return Facility (was called Transportation Cask Receipt/Return Facility)
14B	Center of Transportation Cask Buffer Area
150	Waste Package Receipt Facility
160	Low Level Waste Handling
17A	Center of Aging Facility 17A
17BCDE	Center of Aging Facilities 17B, C, D, E
17FG	Center of Aging Facilities 17F, G
17HJ	Center of Aging Facilities 17H, J
190_1	Canister Handling Facility (190) Intake No. 1 (north side of CHF)
190_2	Canister Handling Facility (190) Intake No. 2 (north side of CHF)

190_3	Canister Handling Facility (190) Intake No. 3 (east side of CHF)
190_4	Canister Handling Facility (190) Intake No. 4 (east side of CHF)
210_1	Fuel Handling Facility (210) Intake No. 1
220	Heavy Equipment Maintenance Facility (220)
240	Control Facility (was called Central Control Center)
25A	Utility Facility (25A)
30A	Central Security Station (30A)
30B	Cask Receipt Security Station (30B)
30C	North Perimeter Security Station (30C)
620	Administration Facility (620)
63A	Fire, Rescue, Medical Facility (63A)
65A	Administration Security Station (65A)
65B	Administration Security Station (65B)
68AB	Warehouse/Storage (68A & 68B)
71AB	Craft Shop & Storage (71A & 71B)
NR ³	Emplacement Ramp (was called Subsurface North Ramp)
SR	South Service Ramp (was call Subsurface South Ramp)
NC	North Service Portal (was called Subsurface North Construction Portal)
IS1	Subsurface Intake Shaft #1
IS2	Subsurface Intake Shaft #2
IS3	Subsurface Intake Shaft #3

Notes:

1. See Figure II-1 for the locations of facilities.
2. Event sequences releases (110X, 120X, and 210X), without crediting stack height, may be used to evaluate potential dispersion factors for event sequences assessments. (See 4.1.7, 4.1.10, 4.2.1, and 4.2.3)
3. For subsurface releases, only subsurface intake receptors (NR, SR, NC, IS1, IS2, and IS3) are used to calculate χ/Q_s in this document. The Emplacement Ramp is conservatively used to represent all surface receptors. (See Section 6.3 and footnote of Tables I-15 to I-20)

The direction from the source to the receptor in ARCON96 is defined as: positive Y-axis (North) is the starting point (0°) and the direction increases clockwise. For a release from the southwest, the direction is 225°. For a release from the north, the direction is 360° (Ramsdell and Simonen 1997 [164547], Section 2.3.4).

The distances and directions from source to receptor are taken from Figure II-1, and are listed in columns 7 and 8 of Tables I-1 to I-20, respectively.

4.1.2 Stack Radius

If not available from design, stack radii for surface facilities are calculated based on the minimum design exit velocity (Assumption 4.2.4) and airflow rates (Section 4.1.7) by the formula: $\text{radius} = \sqrt{(\text{Flow} / \text{Velocity}) / \pi}$. For area sources (Aging Facilities), the equivalent virtual radius is discussed in 4.1.9. The radii of subsurface exhausts are obtained from *Ventilation Network Model Calculation* (BSC 2003 [164054], Table 2, column 3).

The stack radii are listed in column 6 of Tables I-1 to I-20.

4.1.3 Intake Height

The intake heights are based on building sketches: Figures II-2c to II-2g for DTF1, II-3b for CHF, II-4b and II-4c for FHF, and II-5 for 14A. Intake heights of DTF2 are assumed to be the same as that of DTF1 (Assumption 4.2.2). No intake heights for other facilities are considered.

The intake heights are listed in column 9 of Tables I-1 to I-20.

4.1.4 Building Height

The heights of surface facilities are based on building sketches: Figure II-2c for DTF1, II-3c for CHF, and II-4b for FHF. The building height of DTF2 is assumed to be the same as that of DTF1 (see Assumption 4.2.2). The building heights together with the building widths are used in calculating the building areas for building-wake effects (Section 4.1.5). No building height is considered for subsurface facilities.

The building heights are given in column 2 of Table 2.

4.1.5 Building Area

ARCON96 uses a building vertical cross-sectional area perpendicular to the wind direction to determine the building-wake effects (Regulatory Guide 1.194 [165736], Table A-2). The building areas of surface facilities are based on building section sketches: Figures II-2a and II-2c for DTF1, and II-3a and II-3c for CHF, II-4a and II-4b for FHF. The building areas of DTF2 are assumed to be the same as those of DTF1 (see Assumption 4.2.2). For considering the building wake, the receptor must be located within the influence zone of stack as shown in Figure 1. The characteristic length (L) is taken as the height or width, whichever is less, of the building cross-section perpendicular to the wind.

Source: Regulatory Guide 1.194 [165736], Figure 1.

Figure 1. Zone of Influence for Stacks

The building dimensions are listed in Table 2 and the building areas (cross section) are calculated in this Table. A value of 0.01 m^2 is used for no building-wake effect cases (Regulatory Guide 1.194 [165736], Table A-2). No building area is considered for subsurface facilities.

Table 2 Calculation of Building Cross-Section Area

Release Building	(1) Height (ft/m)	(2) Width 1 (ft/m)	(3) Width 2 (ft/m)	(4) Building Area 1 (m^2)	(5) Building Area 2 (m^2)
DTF1/DTF2	100/30	492/150	442/130	4600	4100
CHF	76/23	315/961	233/71	2200	1600
FHF	86/26	211/64	158/48	1700	1300

Notes: (1)(2)(3): from Figs. II-2 to II-7

(4) = (1) x (2)

(5) = (1) x (3)

The building areas are listed in column 3 of Tables I-1 to I-20.

4.1.6 Elevation Difference

There are several bench elevations available on the site layout (see Figure II-1). The subsurface intakes elevations are taken from *Underground Layout Configuration* (BSC 2003 [165572], Table 7). The elevation differences of the release points to the receptors are shown in column 10 of Tables I-1 to I-20.

4.1.7 Release Flow

The release flows of surface facilities for normal operations are taken from ventilation flow designs shown on Figures II-6, II-7, and II-8 for DTF1, CHF, and FHF, respectively. DTF2 is assumed to be the same as DTF1 (see Assumption 4.2.2). Zero ventilation flows are used for event sequences assessments (110X, 120X and 210X). The release flows from subsurface exhausts are obtained from *Ventilation Network Model Calculation* (BSC 2003 [164054], Table 11).

The input values are listed in column 5 of Tables I-1 to I-20.

4.1.8 Meteorological Data

Meteorological input data used to run ARCON96 is based on the onsite meteorological measurements made over the period from 1998 to 2002 at Air Quality and Meteorology Monitoring Site 1. Site 1 is a 60-m tower located approximately 1 km south-southwest of the North Portal. The data are accessible from the Technical Data Management System (DTN: MO0306ARCI9802.001 [164553], Table S03235_001).

The entire meteorological records over the period of 1998 to 2002 are in one input file. The original file name of the meteorological input file in the Technical Data Management System is

“ARCON96 98-02 Input.txt.” The file is renamed as “Site9802.MET” in this calculation to be consistent with the file extension of ARCON96 meteorological data files.

The heights of lower measurement and higher measurement are 10 m and 60 m, respectively. The wind speed input type is “1” corresponding to the unit of wind speed data in m/s (DTN: MO0306ARCI9802.001 [164553], Table S03235_001).

4.1.9 Area Source Modeling for Aging Facilities

In Aging Facilities, there could be potential releases from the resuspension of the surface residual contamination of the stored casks.

ARCON96 uses two initial diffusion coefficients, lateral σ_{y0} and vertical σ_{z0} , to represent the area source (see Ramsdell and Simonen 1997 [170503], pp. 36-37). To model area sources for Aging Facilities, area-equivalent circular sources with the same center are used. For example, the equivalent radius, r_A , of the Aging #17B area source is:

$$\pi r_A^2 = 242,000 \text{ m}^2$$

$$r_A = 280 \text{ m}$$

The initial lateral diffusion coefficient σ_{y0} is estimated by using Equation 2 of ARCON96 code manual (Ramsdell and Simonen 1997 [170503], p.37):

$$\sigma_{y0} = r_A/2.15 = 130 \text{ m}$$

The initial vertical diffusion coefficient σ_{z0} is conservatively assumed to be 2.5 m (Assumption 4.2.5).

The initial diffusion coefficients are listed in columns 11 and 12 of Tables I-1 to I-20.

4.1.10 Default Values

To evaluate annual average and median χ/Q values, 8,760 (annual) and 720 (2 months) during normal operations hours are used along with the first eight defaults (1, 2, 4, 8, 12, 24, 96, and 168) for hours in averages. For event sequences assessments (110X, 120X, 210X), the ARCON96 defaults are used (1, 2, 4, 8, 12, 24, 96, 168, 360, and 720) (Ramsdell and Simonen 1997 [170503], Figure 13). The default averaging sector width constant is 4.3 per Regulatory Guide 1.194 [165736] (Table A-2).

All other parameters of default values directly use the system defaults of ARCON96 averages (Ramsdell and Simonen 1997 [170503], Figure 13). They are:

$$\text{Surface Roughness Length (m)} = 0.1$$

$$\text{Minimum Wind Speed (m/s)} = 0.5$$

Initial lateral diffusion coefficient σ_{y0} (m) = 0.0 [Except for Aging Facilities, see 4.1.9]

Initial vertical diffusion coefficient σ_{z0} (m) = 0.0 [Except for Aging Facilities, see 4.1.9]

Minimum Number of Hours = 1 2 4 8 11 22 87 152 324 648

4.2 ASSUMPTIONS

4.2.1 Release Type

Vent release (type 2) is assumed for normal operational releases from surface facilities except for Aging Facilities, which are assumed to be ground level (type 1). Ground level release (type 1) is conservatively assumed for all subsurface releases. For event sequences assessments (110X, 120X, 210X), ground level release is also conservatively assumed. There is no need of verification for this assumption.

Basis: This assumption is conservative to calculate airborne release dispersion factors.

This assumption is used in Table 3 and column 13 of Tables I-1 to I-20.

4.2.2 Building Design of Dry Transfer Facility #2

The building design of DTF2 is assumed to be the same as that of the DTF1. The stack height, building area, flow, exit velocity, and intake height are assumed to be the same for both facilities. There is no need of verification for this assumption.

Basis: The DTF2 is expected to be similar to the DTF1.

This assumption is used in Section 4.1.

4.2.3 Release Height

For vent releases under normal operations, release heights of DTF, CHF and FHF are the stack heights taken from Figures II-2b, II-3c, and II-4b, respectively. Zero release height is assumed for all subsurface releases. Release heights for event sequences assessments of DTF1 and DTF2 (110X and 120X) release height are assumed to be the stack heights because the stacks are classified as ITS (Important to Safety) in *Q-List* (BSC 2005 [171190], p. A-9). Because the stack of FHF is not classified as ITS in the *Q-List* (BSC 2005 [171190], p. A-9), the release height of FHF is assumed to have the same height as the receptor height (Regulatory Guide 1.194. 2003 [165736], Table A-2). There is no need of verification for this assumption.

This assumption is conservative and is used in Table 3 and column 2 of Tables I-1 to I-20.

4.2.4 Release Exit Velocity

The exit velocities of subsurface exhausts are calculated from design flow rates and radii (see 4.1.2 and 4.1.7):

$$\text{Velocity} = \text{Flow Rate} / \text{Area} = \text{Flow Rate} / (\pi \times \text{Radius}^2).$$

Flow velocity of surface stack releases is conservatively assumed to be 13 m/s (2,500 ft/min) if not available from the designs. For event sequences assessments, exit velocity is conservatively assumed zero. The exit velocity is also conservatively assumed to be zero for all aging facilities.

Basis: The 13 m/s velocity during normal operation is specified as the design minimum flow velocity in *Project Design Criteria Document* (BSC 2004 [171599], Section 4.8.2.2.15). There is no need of verification for this assumption.

This assumption is used in Table 3 and column 4 of Tables I-3 to I-12.

4.2.5 Initial Vertical Diffusion Coefficient of Aging Facilities Releases

The initial vertical diffusion coefficient is conservatively assumed to be 2.5 m.

Basis: In Aging Facilities, the cask height could vary from 10 to 15 feet, and there is an additional 3 to 4 feet rise for the bottom concrete slab. The value of 2.5 m for the initial vertical diffusion coefficient in Aging Facilities is reasonably conservative. There is no need of verification for this assumption.

This assumption is used in Section 4.1.9 and column 12 of Tables I-3 to I-12.

5. USE OF COMPUTER SOFTWARE

5.1 SOFTWARE APPROVED FOR QUALITY ASSURANCE WORK

The ARCON96 code (BSC 2003 [164784]) is used to calculate the relative atmospheric concentrations (χ/Q) for receptors of interest. The software specifications are as follows:

- Program Name: ARCON
- Version/Revision Number: V. 96
- Platform/Operating System: PC/Windows 2000
- Software Tracking Number/Status: 10912-96-00/Qualified

- Computer Type: PC
- Central Processing Unit Number: 150482

In this document, ARCON96 is used for the χ/Q calculations of vent, ground and area source releases. The use was appropriate only within the range of validation as documented. (BSC 2002 [168741], Table 3, Table 4, and Attachment I: Tests 1, 2, and 5.) The software was obtained from Software Configuration Management in accordance with appropriate procedures.

The input and output files for the ARCON96 calculations are listed and contained on a compact disc, which is part of Attachment IV of this calculation.

5.2 EXEMPT SOFTWARE

To prepare the inputs of coordinates, Bentley View 08.01.02.18, a commercial off-the-shelf software, was used to read out coordinate data from the GROA CAD files (provided in the CD in Attachment IV). Per Section 2.1.6 of LP-SI.11Q-BSC, *Software Management*, Bentley View is exempt.

To facilitate calculation, the following computational support software is used for spreadsheets:

- Software title: Microsoft Excel
- Version/revision number: Microsoft Excel 2000.

The Excel spreadsheet program was used to perform simple numeric calculations as documented in Section 6 of this calculation. The user-defined formulas, input, and results are provided in sufficient detail in Section 6 and Attachment IV to allow independent verification of the various computations without recourse to the originator. This application program is considered exempt from the requirements of LP-SI.11Q-BSC [171923], *Software Management* (Section 2.1.6).

6. CALCULATIONS AND RESULTS

In this calculation, there are 682 ARCON96 runs: 17 surface releases with 38 receptors and 6 subsurface releases with 6 receptors. Each run is a dispersion calculation for a combination of Release-Receptor scenario. The input and output file names are described in Section 6.1 and listed on Tables IV-1, IV-2, and IV-3. The input parameter values and the calculation results are summarized in Sections 6.2 and 6.3, respectively.

6.1 INPUT AND OUTPUT FILENAMES

Input and output files are named with a consistent convention of release points and receptors (underscore connected in between). The abbreviations in Table 1 are used for the names of releases and receptors. The file extensions for input files, primary output files, and CFD files are "rsf," "log," and "cfd," respectively. For example, the input file, primary output file, and CFD file for the case with the release from DTF1 and the receptor at the Intake 2 of DTF2 are 110_120_2.rsaf, 110_120_2.log, and 110_120_2.cfd, respectively. The input and output file names are listed in Tables IV-1, IV-2, and IV-3.

6.2 SUMMARY OF INPUT PARAMETER VALUES

Table 3 summarizes the input parameters used to execute ARCON96.

Table 3. Summary of Input Parameter Values to Run ARCON96

Input Parameter	Value	Source
Number of Met Data Files	1	Section 4.1.8
Name of Met Data File	Site9802.MET	Section 4.1.8
Lower Measurement Height (m)	10.0	Section 4.1.8
Upper Measurement Height (m)	60.0	Section 4.1.8
Wind Speed Type	1	Section 4.1.8
Release Type	Column 13 of Tables I-1 to I-20	Assumption 4.2.1
Release Height (m)	Column 2 of Tables I-1 to I-20	Assumption 4.2.3
Building Area (m ²)	Column 3 of Tables I-1 to I-20	Section 4.1.5
Exit Vertical Velocity (m/s)	Column 4 of Tables I-1 to I-20	Assumption 4.2.4
Effluent Flow (m ³ /s)	Column 5 of Tables I-1 to I-20	Section 4.1.7
Stack Radius (m)	Column 6 of Tables I-1 to I-20	Section 4.1.2
Distance to Receptor (m)	Column 7 of Tables I-1 to I-20	Section 4.1.1, Fig. II-1
Intake Height (m)	Column 9 of Tables I-1 to I-20	Section 4.1.3
Terrain Elevation Difference (m)	Column 10 of Tables I-1 to I-20	Section 4.1.6, Fig. II-1
Direction to Source (degree)	Column 8 of Tables I-1 to I-20	Section 4.1.1, Fig. II-1
Primary output file name	Tables IV-1, IV-2, and IV-3	Section 6.1
CFD output file name	Tables IV-1, IV-2, and IV-3	Section 6.1
Expanded Output file	N	Default of ARCON96
Surface Roughness Length (m)	0.1	Default, Section 4.1.10
Minimum Wind Speed (m/s)	0.5	Default, Section 4.1.10
Averaging Sector Width Constant	4.3	Section 4.1.10
σ_{y0} (m)	Column 11 of Tables I-1 to I-20	Default, Sections 4.1.10 and 4.1.9
σ_{z0} (m)	Column 12 of Tables I-1 to I-20	Default, Sections 4.1.10 and 4.1.9

Hours in Averages	1 2 4 8 12 24 96 168 720 8760 (Normal)	Section 4.1.10
	1 2 4 8 12 24 96 168 360 720 (Event sequences)	
Minimum Number of Hours	1 2 4 8 11 22 87 152 324 648	Defaults, Section 4.1.10

6.3 χ/Q CALCULATION RESULTS

The calculated results of mean and median dispersion factors (χ/Q) are summarized in Tables 4 to 23 for normal operations releases from both surface and subsurface facilities. The calculated results of mean, median and 95th percentile 0 to 2 hours χ/Q s dispersion factors are summarized in Tables 23 through 26 for potential releases from the waste handling surface facilities under event sequences (110X, 120X, 210X). The maximum χ/Q s for each release (each Table) are also highlighted in bold.

The uncertainty of the calculated dispersion factor (χ/Q) is assessed in ARCON96 by constructing a cumulative probability distribution (see Attachment III) of the hourly χ/Q values. This cumulative probability distribution is then used to determine the median (50th percentile) and mean (arithmetic average) χ/Q for the locations of interest. For conservatism, the higher value of median and mean χ/Q is included in the last column of the tables as suggested value for consequence analysis. Maximum χ/Q at receptors for each release source are highlighted in bold face. The calculation approach to obtain these suggested values is illustrated in Attachment III. For subsurface release calculations, the χ/Q s calculated for Emplacement Ramp may be used conservatively to represent the dispersion factors for all other surface receptors.

All input files used and output files produced in this calculation are provided in Attachment IV.

The outputs are reasonable compared to the inputs. The dispersion factors calculated in this document are suitable to facilitate the radiological dose assessment for the operation of repository facilities.

Table 4. χ/Q Calculation Results of Release 110

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.1E-05	1.1E-05	1.1E-05
110_2	7.5E-06	7.6E-06	7.6E-06
110_3	4.8E-06	5.0E-06	5.0E-06
120_1	1.8E-05	1.8E-05	1.8E-05
120_2	1.9E-05	2.0E-05	2.0E-05
120_3	1.7E-05	1.9E-05	1.9E-05
120_4	4.7E-05	4.7E-05	4.7E-05
14A	1.3E-06	1.4E-06	1.4E-06
14B	1.7E-06	1.8E-06	1.8E-06
150	5.7E-07	5.9E-07	5.9E-07
160	5.5E-07	5.7E-07	5.7E-07
17A	8.3E-07	8.8E-07	8.8E-07
17BCDE	4.3E-06	4.2E-06	4.3E-06
17FG	6.4E-06	6.6E-06	6.6E-06
17HJ	5.5E-06	5.7E-06	5.7E-06
190_1	6.0E-07	6.7E-07	6.7E-07
190_2	1.7E-06	1.8E-06	1.8E-06
190_3	1.9E-06	1.9E-06	1.9E-06
190_4	2.1E-06	2.2E-06	2.2E-06
210_1	7.0E-07	7.3E-07	7.3E-07
25A	6.1E-07	6.5E-07	6.5E-07
220	1.0E-06	1.1E-06	1.1E-06
240	5.5E-07	5.7E-07	5.7E-07
30A	3.0E-07	3.2E-07	3.2E-07
30B	6.3E-07	6.3E-07	6.3E-07
30C	1.9E-06	2.0E-06	2.0E-06
620	2.9E-07	3.0E-07	3.0E-07
63A	2.9E-07	3.0E-07	3.0E-07
65A	3.0E-07	3.1E-07	3.1E-07
65B	2.7E-07	2.9E-07	2.9E-07
68AB	2.7E-07	2.8E-07	2.8E-07
71AB	2.6E-07	2.7E-07	2.7E-07
NC	4.8E-07	4.5E-07	4.8E-07
IS1	1.2E-07	1.2E-07	1.2E-07
IS2	2.0E-07	1.9E-07	2.0E-07
IS3	1.5E-07	1.6E-07	1.6E-07
NR	9.4E-07	9.9E-07	9.9E-07
SR	3.9E-07	4.0E-07	4.0E-07

Table 5. χ/Q Calculation Results of Release 120

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	8.3E-06	8.4E-06	8.4E-06
110_2	8.6E-06	8.8E-06	8.8E-06
110_3	8.6E-06	8.9E-06	8.9E-06
110_4	1.1E-05	1.1E-05	1.1E-05
120_1	7.2E-06	7.4E-06	7.4E-06
120_2	4.8E-06	5.0E-06	5.0E-06
120_3	1.7E-05	1.8E-05	1.8E-05
120_4	1.9E-06	1.9E-06	1.9E-06
120_5	6.1E-07	6.6E-07	6.6E-07
14A	6.8E-07	6.9E-07	6.9E-07
14B	7.1E-07	7.3E-07	7.3E-07
150	8.7E-07	9.0E-07	9.0E-07
160	3.6E-06	3.6E-06	3.6E-06
17A	7.1E-06	7.3E-06	7.3E-06
17BCDE	6.8E-06	7.0E-06	7.0E-06
17FG	9.2E-07	9.5E-07	9.5E-07
17HJ	2.8E-06	2.9E-06	2.9E-06
190_1	3.0E-06	3.1E-06	3.1E-06
190_2	3.1E-06	3.2E-06	3.2E-06
210_1	9.9E-07	1.0E-06	1.0E-06
25A	3.9E-07	4.2E-07	4.2E-07
220	1.2E-06	1.3E-06	1.3E-06
240	7.3E-07	7.6E-07	7.6E-07
30A	3.0E-07	3.1E-07	3.1E-07
30B	7.0E-07	7.3E-07	7.3E-07
30C	2.5E-06	2.8E-06	2.8E-06
620	3.2E-07	3.3E-07	3.3E-07
63A	3.4E-07	3.5E-07	3.5E-07
65A	3.6E-07	3.7E-07	3.7E-07
65B	2.9E-07	3.0E-07	3.0E-07
68AB	3.1E-07	3.3E-07	3.3E-07
71AB	2.9E-07	3.0E-07	3.0E-07
NC	4.5E-07	4.2E-07	4.5E-07
IS1	1.2E-07	1.2E-07	1.2E-07
IS2	1.9E-07	1.8E-07	1.9E-07
IS3	1.4E-07	1.5E-07	1.5E-07
NR	6.7E-07	7.0E-07	7.0E-07
SR	3.5E-07	3.6E-07	3.6E-07

Table 6. χ/Q Calculation Results of Release 17A1

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	5.1E-06	5.4E-06	5.4E-06
110_2	1.3E-05	1.3E-05	1.3E-05
110_3	1.1E-05	1.1E-05	1.1E-05
120_1	1.6E-06	1.7E-06	1.7E-06
120_2	2.5E-06	2.6E-06	2.6E-06
120_3	2.7E-06	2.9E-06	2.9E-06
120_4	1.9E-06	2.0E-06	2.0E-06
14A	5.5E-06	5.8E-06	5.8E-06
14B	5.9E-06	6.1E-06	6.1E-06
150	4.7E-06	5.0E-06	5.0E-06
160	5.4E-06	5.6E-06	5.6E-06
17A	1.3E-05	1.4E-05	1.4E-05
17BCDE	9.5E-07	8.8E-07	9.5E-07
17FG	9.1E-07	8.7E-07	9.1E-07
17HJ	7.0E-07	6.8E-07	7.0E-07
190_1	1.3E-05	1.4E-05	1.4E-05
190_2	1.1E-05	1.1E-05	1.1E-05
190_3	9.3E-06	9.7E-06	9.7E-06
190_4	9.0E-06	9.5E-06	9.5E-06
210_1	7.6E-06	7.9E-06	7.9E-06
25A	4.6E-06	4.9E-06	4.9E-06
220	3.1E-06	3.2E-06	3.2E-06
240	5.7E-06	6.0E-06	6.0E-06
30A	3.6E-06	3.8E-06	3.8E-06
30B	1.9E-06	2.0E-06	2.0E-06
30C	1.5E-06	1.5E-06	1.5E-06
620	3.3E-06	3.5E-06	3.5E-06
63A	3.3E-06	3.4E-06	3.4E-06
65A	2.7E-06	2.9E-06	2.9E-06
65B	3.3E-06	3.5E-06	3.5E-06
68AB	3.0E-06	3.2E-06	3.2E-06
71AB	3.0E-06	3.2E-06	3.2E-06
NC	4.6E-07	4.3E-07	4.6E-07
IS1	1.1E-07	1.1E-07	1.1E-07
IS2	2.1E-07	2.0E-07	2.1E-07
IS3	1.3E-07	1.4E-07	1.4E-07
NR	1.9E-06	2.0E-06	2.0E-06
SR	4.3E-07	4.4E-07	4.4E-07

Table 7. χ/Q Calculation Results of Release17A2

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	2.5E-06	2.6E-06	2.6E-06
110_2	5.8E-06	6.0E-06	6.0E-06
110_3	8.3E-06	8.7E-06	8.7E-06
120_1	1.3E-06	1.4E-06	1.4E-06
120_2	1.8E-06	1.9E-06	1.9E-06
120_3	1.8E-06	1.9E-06	1.9E-06
120_4	1.5E-06	1.5E-06	1.5E-06
14A	6.1E-06	6.4E-06	6.4E-06
14B	5.3E-06	5.5E-06	5.5E-06
150	4.9E-06	5.1E-06	5.1E-06
160	6.3E-06	6.6E-06	6.6E-06
17A	2.3E-05	2.4E-05	2.4E-05
17BCDE	9.6E-07	9.0E-07	9.6E-07
17FG	8.4E-07	8.0E-07	8.4E-07
17HJ	6.6E-07	6.5E-07	6.6E-07
190_1	1.4E-05	1.5E-05	1.5E-05
190_2	1.1E-05	1.2E-05	1.2E-05
190_3	1.0E-05	1.1E-05	1.1E-05
190_4	1.1E-05	1.1E-05	1.1E-05
210_1	9.7E-06	1.0E-05	1.0E-05
25A	4.5E-06	4.6E-06	4.6E-06
220	4.2E-06	4.4E-06	4.4E-06
240	7.1E-06	7.4E-06	7.4E-06
30A	3.6E-06	3.8E-06	3.8E-06
30B	2.1E-06	2.2E-06	2.2E-06
30C	1.3E-06	1.4E-06	1.4E-06
620	3.6E-06	3.7E-06	3.7E-06
63A	3.4E-06	3.5E-06	3.5E-06
65A	2.8E-06	2.9E-06	2.9E-06
65B	3.3E-06	3.5E-06	3.5E-06
68AB	3.2E-06	3.3E-06	3.3E-06
71AB	3.1E-06	3.2E-06	3.2E-06
NC	4.5E-07	4.2E-07	4.5E-07
IS1	1.1E-07	1.1E-07	1.1E-07
IS2	2.1E-07	2.0E-07	2.1E-07
IS3	1.4E-07	1.4E-07	1.4E-07
NR	2.4E-06	2.5E-06	2.5E-06
SR	4.4E-07	4.6E-07	4.6E-07

Table 8. χ/Q Calculation Results of Release 17B

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.4E-06	1.5E-06	1.5E-06
110_2	1.4E-06	1.5E-06	1.5E-06
110_3	1.3E-06	1.4E-06	1.4E-06
120_1	1.3E-06	1.4E-06	1.4E-06
120_2	1.3E-06	1.4E-06	1.4E-06
120_3	1.3E-06	1.4E-06	1.4E-06
120_4	1.3E-06	1.3E-06	1.3E-06
14A	1.1E-06	1.2E-06	1.2E-06
14B	1.2E-06	1.2E-06	1.2E-06
150	1.1E-06	1.1E-06	1.1E-06
160	1.1E-06	1.2E-06	1.2E-06
17A	1.7E-06	1.8E-06	1.8E-06
17BCDE	1.7E-06	1.7E-06	1.7E-06
17FG	5.7E-07	5.8E-07	5.8E-07
17HJ	2.9E-07	3.0E-07	3.0E-07
190_1	1.4E-06	1.5E-06	1.5E-06
190_2	1.3E-06	1.4E-06	1.4E-06
190_3	1.3E-06	1.4E-06	1.4E-06
190_4	1.3E-06	1.4E-06	1.4E-06
210_1	1.3E-06	1.3E-06	1.3E-06
25A	1.1E-06	1.1E-06	1.1E-06
220	1.1E-06	1.1E-06	1.1E-06
240	1.2E-06	1.2E-06	1.2E-06
30A	9.8E-07	1.0E-06	1.0E-06
30B	7.3E-07	7.7E-07	7.7E-07
30C	1.3E-06	1.3E-06	1.3E-06
620	9.2E-07	9.6E-07	9.6E-07
63A	9.1E-07	9.6E-07	9.6E-07
65A	8.4E-07	8.8E-07	8.8E-07
65B	9.2E-07	9.6E-07	9.6E-07
68AB	9.0E-07	9.5E-07	9.5E-07
71AB	9.1E-07	9.5E-07	9.5E-07
NC	4.7E-07	4.4E-07	4.7E-07
IS1	8.1E-08	8.1E-08	8.1E-08
IS2	1.7E-07	1.5E-07	1.7E-07
IS3	9.5E-08	1.0E-07	1.0E-07
NR	1.4E-06	1.5E-06	1.5E-06
SR	3.4E-07	3.5E-07	3.5E-07

Table 9. χ/Q Calculation Results of Release 17C

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.2E-06	1.2E-06	1.2E-06
110_2	1.2E-06	1.3E-06	1.3E-06
110_3	1.2E-06	1.2E-06	1.2E-06
120_1	1.0E-06	1.1E-06	1.1E-06
120_2	1.1E-06	1.2E-06	1.2E-06
120_3	1.1E-06	1.1E-06	1.1E-06
120_4	1.0E-06	1.1E-06	1.1E-06
14A	1.0E-06	1.1E-06	1.1E-06
14B	1.0E-06	1.1E-06	1.1E-06
150	9.9E-07	1.0E-06	1.0E-06
160	1.1E-06	1.1E-06	1.1E-06
17A	1.4E-06	1.5E-06	1.5E-06
17BCDE	1.6E-06	1.6E-06	1.6E-06
17FG	3.9E-07	4.1E-07	4.1E-07
17HJ	2.5E-07	2.6E-07	2.6E-07
190_1	1.2E-06	1.3E-06	1.3E-06
190_2	1.2E-06	1.2E-06	1.2E-06
190_3	1.2E-06	1.2E-06	1.2E-06
190_4	1.2E-06	1.2E-06	1.2E-06
210_1	1.2E-06	1.2E-06	1.2E-06
25A	9.5E-07	9.8E-07	9.8E-07
220	1.1E-06	1.1E-06	1.1E-06
240	1.1E-06	1.1E-06	1.1E-06
30A	9.0E-07	9.4E-07	9.4E-07
30B	7.1E-07	7.3E-07	7.3E-07
30C	9.4E-07	9.8E-07	9.8E-07
620	8.8E-07	9.1E-07	9.1E-07
63A	8.7E-07	9.1E-07	9.1E-07
65A	8.2E-07	8.6E-07	8.6E-07
65B	8.5E-07	8.8E-07	8.8E-07
68AB	8.4E-07	8.7E-07	8.7E-07
71AB	8.3E-07	8.7E-07	8.7E-07
NC	5.0E-07	4.7E-07	5.0E-07
IS1	8.5E-08	8.6E-08	8.6E-08
IS2	1.9E-07	1.8E-07	1.9E-07
IS3	1.0E-07	1.1E-07	1.1E-07
NR	1.4E-06	1.5E-06	1.5E-06
SR	3.9E-07	4.1E-07	4.1E-07

Table 10. χ/Q Calculation Results of Release 17D

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.2E-06	1.3E-06	1.3E-06
110_2	1.2E-06	1.3E-06	1.3E-06
110_3	1.2E-06	1.2E-06	1.2E-06
120_1	1.2E-06	1.3E-06	1.3E-06
120_2	1.2E-06	1.3E-06	1.3E-06
120_3	1.2E-06	1.3E-06	1.3E-06
120_4	1.2E-06	1.2E-06	1.2E-06
14A	9.9E-07	1.0E-06	1.0E-06
14B	1.1E-06	1.1E-06	1.1E-06
150	9.4E-07	9.7E-07	9.7E-07
160	9.9E-07	1.0E-06	1.0E-06
17A	1.4E-06	1.4E-06	1.4E-06
17BCDE	1.0E-06	1.1E-06	1.1E-06
17FG	5.6E-07	5.8E-07	5.8E-07
17HJ	3.2E-07	3.3E-07	3.3E-07
190_1	1.2E-06	1.3E-06	1.3E-06
190_2	1.1E-06	1.2E-06	1.2E-06
190_3	1.1E-06	1.2E-06	1.2E-06
190_4	1.1E-06	1.1E-06	1.1E-06
210_1	1.1E-06	1.1E-06	1.1E-06
25A	9.8E-07	1.0E-06	1.0E-06
220	9.2E-07	9.6E-07	9.6E-07
240	1.0E-06	1.1E-06	1.1E-06
30A	8.9E-07	9.3E-07	9.3E-07
30B	6.8E-07	7.2E-07	7.2E-07
30C	1.3E-06	1.4E-06	1.4E-06
620	8.4E-07	8.7E-07	8.7E-07
63A	8.3E-07	8.7E-07	8.7E-07
65A	7.7E-07	8.0E-07	8.0E-07
65B	8.5E-07	8.9E-07	8.9E-07
68AB	8.3E-07	8.7E-07	8.7E-07
71AB	8.3E-07	8.7E-07	8.7E-07
NC	5.7E-07	5.4E-07	5.7E-07
IS1	7.9E-08	8.1E-08	8.1E-08
IS2	1.6E-07	1.5E-07	1.6E-07
IS3	9.5E-08	1.0E-07	1.0E-07
NR	1.2E-06	1.2E-06	1.2E-06
SR	3.4E-07	3.6E-07	3.6E-07

Table 11. χ/Q Calculation Results of Release 17E

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.1E-06	1.1E-06	1.1E-06
110_2	1.1E-06	1.1E-06	1.1E-06
110_3	1.1E-06	1.1E-06	1.1E-06
120_1	1.0E-06	1.1E-06	1.1E-06
120_2	1.1E-06	1.1E-06	1.1E-06
120_3	1.0E-06	1.1E-06	1.1E-06
120_4	1.0E-06	1.0E-06	1.0E-06
14A	9.2E-07	9.6E-07	9.6E-07
14B	9.6E-07	1.0E-06	1.0E-06
150	9.0E-07	9.5E-07	9.5E-07
160	9.4E-07	9.7E-07	9.7E-07
17A	1.3E-06	1.3E-06	1.3E-06
17BCDE	4.8E-06	5.0E-06	5.0E-06
17FG	4.2E-07	4.5E-07	4.5E-07
17HJ	2.8E-07	2.9E-07	2.9E-07
190_1	1.1E-06	1.1E-06	1.1E-06
190_2	1.1E-06	1.1E-06	1.1E-06
190_3	1.0E-06	1.1E-06	1.1E-06
190_4	1.0E-06	1.1E-06	1.1E-06
210_1	1.0E-06	1.1E-06	1.1E-06
25A	9.0E-07	9.5E-07	9.5E-07
220	9.2E-07	9.6E-07	9.6E-07
240	9.9E-07	1.0E-06	1.0E-06
30A	8.3E-07	8.7E-07	8.7E-07
30B	6.7E-07	7.1E-07	7.1E-07
30C	1.0E-06	1.1E-06	1.1E-06
620	8.2E-07	8.6E-07	8.6E-07
63A	8.1E-07	8.6E-07	8.6E-07
65A	7.6E-07	7.9E-07	7.9E-07
65B	8.2E-07	8.6E-07	8.6E-07
68AB	7.8E-07	8.1E-07	8.1E-07
71AB	7.8E-07	8.1E-07	8.1E-07
NC	6.3E-07	6.0E-07	6.3E-07
IS1	8.5E-08	8.6E-08	8.6E-08
IS2	1.9E-07	1.8E-07	1.9E-07
IS3	1.0E-07	1.1E-07	1.1E-07
NR	1.2E-06	1.2E-06	1.2E-06
SR	3.8E-07	4.0E-07	4.0E-07

Table 12. χ/Q Calculation Results of Release 17F

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.1E-06	1.1E-06	1.1E-06
110_2	9.9E-07	1.0E-06	1.0E-06
110_3	9.7E-07	1.0E-06	1.0E-06
120_1	1.2E-06	1.3E-06	1.3E-06
120_2	1.1E-06	1.2E-06	1.2E-06
120_3	1.1E-06	1.1E-06	1.1E-06
120_4	1.1E-06	1.2E-06	1.2E-06
14A	8.2E-07	8.6E-07	8.6E-07
14B	9.4E-07	9.7E-07	9.7E-07
150	8.0E-07	8.4E-07	8.4E-07
160	7.7E-07	8.1E-07	8.1E-07
17A	8.7E-07	9.1E-07	9.1E-07
17BCDE	2.9E-07	3.0E-07	3.0E-07
17FG	5.5E-06	5.6E-06	5.6E-06
17HJ	8.9E-07	9.3E-07	9.3E-07
190_1	9.0E-07	9.5E-07	9.5E-07
190_2	9.0E-07	9.5E-07	9.5E-07
190_3	8.8E-07	9.3E-07	9.3E-07
190_4	8.5E-07	8.9E-07	8.9E-07
210_1	8.0E-07	8.4E-07	8.4E-07
25A	8.8E-07	9.2E-07	9.2E-07
220	6.3E-07	6.6E-07	6.6E-07
240	7.5E-07	7.9E-07	7.9E-07
30A	7.8E-07	8.1E-07	8.1E-07
30B	6.0E-07	6.3E-07	6.3E-07
30C	1.4E-06	1.5E-06	1.5E-06
620	7.5E-07	7.9E-07	7.9E-07
63A	7.2E-07	7.5E-07	7.5E-07
65A	6.9E-07	7.2E-07	7.2E-07
65B	7.9E-07	8.2E-07	8.2E-07
68AB	7.5E-07	7.9E-07	7.9E-07
71AB	7.6E-07	7.9E-07	7.9E-07
NC	3.0E-07	2.9E-07	3.0E-07
IS1	7.2E-08	7.6E-08	7.6E-08
IS2	1.1E-07	1.1E-07	1.1E-07
IS3	8.5E-08	9.0E-08	9.0E-08
NR	5.8E-07	6.1E-07	6.1E-07
SR	2.4E-07	2.5E-07	2.5E-07

Table 13. χ/Q Calculation Results of Release 17G

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.3E-06	1.3E-06	1.3E-06
110_2	1.1E-06	1.2E-06	1.2E-06
110_3	1.1E-06	1.1E-06	1.1E-06
120_1	1.4E-06	1.5E-06	1.5E-06
120_2	1.3E-06	1.4E-06	1.4E-06
120_3	1.3E-06	1.4E-06	1.4E-06
120_4	1.3E-06	1.4E-06	1.4E-06
14A	9.0E-07	9.5E-07	9.5E-07
14B	1.1E-06	1.1E-06	1.1E-06
150	8.9E-07	9.4E-07	9.4E-07
160	8.4E-07	8.8E-07	8.8E-07
17A	8.8E-07	9.2E-07	9.2E-07
17BCDE	2.6E-07	2.7E-07	2.7E-07
17FG	2.9E-06	2.9E-06	2.9E-06
17HJ	5.4E-07	5.6E-07	5.6E-07
190_1	9.9E-07	1.0E-06	1.0E-06
190_2	9.9E-07	1.0E-06	1.0E-06
190_3	9.8E-07	1.0E-06	1.0E-06
190_4	9.5E-07	9.9E-07	9.9E-07
210_1	8.7E-07	9.2E-07	9.2E-07
25A	9.9E-07	1.0E-06	1.0E-06
220	6.5E-07	6.8E-07	6.8E-07
240	7.8E-07	8.2E-07	8.2E-07
30A	8.7E-07	9.0E-07	9.0E-07
30B	6.4E-07	6.7E-07	6.7E-07
30C	1.7E-06	1.8E-06	1.8E-06
620	8.3E-07	8.7E-07	8.7E-07
63A	7.8E-07	8.1E-07	8.1E-07
65A	7.5E-07	7.9E-07	7.9E-07
65B	8.8E-07	9.3E-07	9.3E-07
68AB	8.2E-07	8.6E-07	8.6E-07
71AB	8.3E-07	8.7E-07	8.7E-07
NC	3.2E-07	3.0E-07	3.2E-07
IS1	7.2E-08	7.5E-08	7.5E-08
IS2	1.1E-07	1.1E-07	1.1E-07
IS3	8.2E-08	8.5E-08	8.5E-08
NR	5.4E-07	5.7E-07	5.7E-07
SR	2.4E-07	2.5E-07	2.5E-07

Table 14. χ/Q Calculation Results of Release 17H

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.5E-06	1.6E-06	1.6E-06
110_2	1.3E-06	1.3E-06	1.3E-06
110_3	1.3E-06	1.3E-06	1.3E-06
120_1	2.2E-06	2.3E-06	2.3E-06
120_2	1.8E-06	1.9E-06	1.9E-06
120_3	1.9E-06	2.0E-06	2.0E-06
120_4	2.2E-06	2.4E-06	2.4E-06
14A	1.2E-06	1.3E-06	1.3E-06
14B	1.7E-06	1.8E-06	1.8E-06
150	1.3E-06	1.4E-06	1.4E-06
160	1.0E-06	1.1E-06	1.1E-06
17A	8.4E-07	8.8E-07	8.8E-07
17BCDE	3.8E-07	4.0E-07	4.0E-07
17FG	1.1E-06	1.2E-06	1.2E-06
17HJ	5.3E-05	5.5E-05	5.5E-05
190_1	1.0E-06	1.1E-06	1.1E-06
190_2	1.1E-06	1.2E-06	1.2E-06
190_3	1.1E-06	1.2E-06	1.2E-06
190_4	1.1E-06	1.2E-06	1.2E-06
210_1	9.4E-07	9.8E-07	9.8E-07
25A	1.8E-06	1.9E-06	1.9E-06
220	7.4E-07	7.7E-07	7.7E-07
240	8.9E-07	9.4E-07	9.4E-07
30A	1.6E-06	1.7E-06	1.7E-06
30B	1.2E-06	1.3E-06	1.3E-06
30C	2.4E-06	2.6E-06	2.6E-06
620	1.5E-06	1.6E-06	1.6E-06
63A	1.3E-06	1.4E-06	1.4E-06
65A	1.4E-06	1.5E-06	1.5E-06
65B	1.7E-06	1.8E-06	1.8E-06
68AB	1.5E-06	1.6E-06	1.6E-06
71AB	1.7E-06	1.8E-06	1.8E-06
NC	3.6E-07	3.5E-07	3.6E-07
IS1	1.1E-07	1.2E-07	1.2E-07
IS2	1.6E-07	1.6E-07	1.6E-07
IS3	1.3E-07	1.4E-07	1.4E-07
NR	6.3E-07	6.6E-07	6.6E-07
SR	3.5E-07	3.6E-07	3.6E-07

Table 15. χ/Q Calculation Results of Release 17J

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	4.5E-07	4.7E-07	4.7E-07
110_2	3.9E-07	4.1E-07	4.1E-07
110_3	4.3E-07	4.4E-07	4.4E-07
120_1	6.4E-07	6.7E-07	6.7E-07
120_2	5.4E-07	5.6E-07	5.6E-07
120_3	5.8E-07	6.0E-07	6.0E-07
120_4	6.6E-07	6.8E-07	6.8E-07
14A	4.3E-07	4.5E-07	4.5E-07
14B	5.6E-07	5.8E-07	5.8E-07
150	4.8E-07	5.0E-07	5.0E-07
160	3.7E-07	3.9E-07	3.9E-07
17A	2.9E-07	3.0E-07	3.0E-07
17BCDE	1.5E-07	1.6E-07	1.6E-07
17FG	3.1E-07	3.2E-07	3.2E-07
17HJ	2.9E-06	2.9E-06	2.9E-06
190_1	3.5E-07	3.6E-07	3.6E-07
190_2	3.7E-07	3.9E-07	3.9E-07
190_3	3.8E-07	3.9E-07	3.9E-07
190_4	3.6E-07	3.7E-07	3.7E-07
210_1	3.3E-07	3.5E-07	3.5E-07
25A	6.3E-07	6.5E-07	6.5E-07
220	2.8E-07	2.9E-07	2.9E-07
240	3.2E-07	3.3E-07	3.3E-07
30A	6.1E-07	6.3E-07	6.3E-07
30B	4.9E-07	5.1E-07	5.1E-07
30C	6.4E-07	6.7E-07	6.7E-07
620	5.5E-07	5.8E-07	5.8E-07
63A	5.0E-07	5.2E-07	5.2E-07
65A	5.5E-07	5.8E-07	5.8E-07
65B	6.8E-07	7.2E-07	7.2E-07
68AB	6.0E-07	6.2E-07	6.2E-07
71AB	6.8E-07	7.1E-07	7.1E-07
NC	1.6E-07	1.6E-07	1.6E-07
IS1	6.6E-08	7.0E-08	7.0E-08
IS2	9.2E-08	8.9E-08	9.2E-08
IS3	7.3E-08	7.7E-08	7.7E-08
NR	2.4E-07	2.5E-07	2.5E-07
SR	1.7E-07	1.7E-07	1.7E-07

Table 16. χ/Q Calculation Results of Release 190

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	3.3E-05	3.5E-05	3.5E-05
110_2	4.5E-05	4.6E-05	4.6E-05
110_3	2.7E-05	2.8E-05	2.8E-05
120_1	2.0E-05	2.1E-05	2.1E-05
120_2	2.5E-05	2.6E-05	2.6E-05
120_3	2.1E-05	2.2E-05	2.2E-05
120_4	3.6E-05	3.8E-05	3.8E-05
14A	2.0E-06	2.1E-06	2.1E-06
14B	4.5E-07	4.7E-07	4.7E-07
150	9.3E-07	9.8E-07	9.8E-07
160	2.1E-06	2.3E-06	2.3E-06
17A	4.4E-06	4.6E-06	4.6E-06
17BCDE	6.5E-06	6.5E-06	6.5E-06
17FG	6.2E-06	6.4E-06	6.4E-06
17HJ	5.1E-06	5.3E-06	5.3E-06
190_1	1.1E-05	1.2E-05	1.2E-05
190_2	1.1E-05	1.1E-05	1.1E-05
190_3	4.2E-06	4.3E-06	4.3E-06
190_4	9.5E-06	1.0E-05	1.0E-05
210_1	8.9E-06	9.6E-06	9.6E-06
25A	2.4E-07	2.5E-07	2.5E-07
220	1.3E-06	1.4E-06	1.4E-06
240	2.3E-06	2.4E-06	2.4E-06
30A	3.5E-07	3.6E-07	3.6E-07
30B	8.8E-07	8.9E-07	8.9E-07
30C	2.0E-06	1.9E-06	2.0E-06
620	4.0E-07	4.2E-07	4.2E-07
63A	4.5E-07	4.7E-07	4.7E-07
65A	4.1E-07	4.2E-07	4.2E-07
65B	2.6E-07	2.7E-07	2.7E-07
68AB	3.5E-07	3.7E-07	3.7E-07
71AB	2.9E-07	3.0E-07	3.0E-07
NC	5.0E-07	4.6E-07	5.0E-07
IS1	1.3E-07	1.3E-07	1.3E-07
IS2	2.3E-07	2.2E-07	2.3E-07
IS3	1.6E-07	1.7E-07	1.7E-07
NR	2.7E-06	2.7E-06	2.7E-06
SR	4.9E-07	5.1E-07	5.1E-07

Table 17. χ/Q Calculation Results of Release 210

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
110_1	1.9E-05	1.9E-05	1.9E-05
110_2	2.8E-05	2.7E-05	2.8E-05
110_3	2.8E-05	2.8E-05	2.8E-05
120_1	1.0E-05	1.0E-05	1.0E-05
120_2	1.4E-05	1.4E-05	1.4E-05
120_3	1.3E-05	1.3E-05	1.3E-05
120_4	1.4E-05	1.5E-05	1.5E-05
14A	6.5E-06	6.8E-06	6.8E-06
14B	9.1E-07	9.6E-07	9.6E-07
150	2.7E-06	2.8E-06	2.8E-06
160	1.5E-05	1.6E-05	1.6E-05
17A	3.7E-06	3.8E-06	3.8E-06
17BCDE	3.4E-06	3.4E-06	3.4E-06
17FG	2.9E-06	3.0E-06	3.0E-06
17HJ	2.3E-06	2.4E-06	2.4E-06
190_1	5.9E-06	6.3E-06	6.3E-06
190_2	1.2E-05	1.3E-05	1.3E-05
190_3	1.3E-05	1.4E-05	1.4E-05
190_4	1.7E-05	1.8E-05	1.8E-05
210_1	7.1E-06	7.1E-06	7.1E-06
25A	5.4E-07	5.7E-07	5.7E-07
220	1.5E-06	1.7E-06	1.7E-06
240	2.8E-06	3.0E-06	3.0E-06
30A	8.2E-07	8.6E-07	8.6E-07
30B	8.0E-07	8.2E-07	8.2E-07
30C	1.8E-06	1.8E-06	1.8E-06
620	1.0E-06	1.1E-06	1.1E-06
63A	1.2E-06	1.2E-06	1.2E-06
65A	7.7E-07	8.1E-07	8.1E-07
65B	4.9E-07	5.1E-07	5.1E-07
68AB	7.9E-07	8.2E-07	8.2E-07
71AB	5.8E-07	6.1E-07	6.1E-07
NC	4.7E-07	4.4E-07	4.7E-07
IS1	1.3E-07	1.3E-07	1.3E-07
IS2	2.3E-07	2.2E-07	2.3E-07
IS3	1.6E-07	1.6E-07	1.6E-07
NR	2.8E-06	2.7E-06	2.8E-06
SR	4.8E-07	5.0E-07	5.0E-07

Table 18. χ/Q Calculation Results of Release ECRB

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
IS1	9.7E-07	9.4E-07	9.7E-07
IS2	3.7E-07	3.6E-07	3.7E-07
IS3	1.1E-06	1.2E-06	1.2E-06
NC	2.8E-07	2.9E-07	2.9E-07
NR	4.1E-07	4.3E-07	4.3E-07
SR	1.3E-06	1.4E-06	1.4E-06

Table 19. χ/Q Calculation Results of Release ER1

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
IS1	5.0E-06	4.7E-06	5.0E-06
IS2	5.7E-07	5.6E-07	5.7E-07
IS3	4.7E-06	5.0E-06	5.0E-06
NC	3.4E-07	3.6E-07	3.6E-07
NR	1.0E-06	1.1E-06	1.1E-06
SR	1.2E-06	1.3E-06	1.3E-06

Table 20. χ/Q Calculation Results of Release ER2

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
IS1	3.6E-07	3.8E-07	3.8E-07
IS2	1.1E-06	1.0E-06	1.1E-06
IS3	1.1E-06	1.1E-06	1.1E-06
NC	6.6E-07	6.8E-07	6.8E-07
NR	1.9E-06	2.0E-06	2.0E-06
SR	1.1E-06	1.2E-06	1.2E-06

Table 21. χ/Q Calculation Results of Release ES1

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested
IS1	1.5E-05	1.5E-05	1.5E-05
IS2	6.1E-07	6.3E-07	6.3E-07
IS3	2.5E-06	2.6E-06	2.6E-06
NC	4.4E-07	4.6E-07	4.6E-07
NR	1.2E-06	1.2E-06	1.2E-06
SR	1.0E-06	1.1E-06	1.1E-06

Table 22. χ/Q Calculation Results of Release ES2

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested ²
IS1	4.5E-07	4.7E-07	4.7E-07
IS2	1.3E-05	1.4E-05	1.4E-05
IS3	9.5E-07	1.0E-06	1.0E-06
NC	2.3E-06	2.4E-06	2.4E-06
NR	1.3E-06	1.4E-06	1.4E-06
SR	8.8E-07	9.2E-07	9.2E-07

Table 23. χ/Q Calculation Results of Release ES3

Receptor	χ/Q (s/m ³)		
	Mean	Median	Suggested ²
IS1	3.1E-07	3.0E-07	3.1E-07
IS2	2.3E-07	2.2E-07	2.3E-07
IS3	4.9E-07	4.7E-07	4.9E-07
NC	2.4E-07	2.4E-07	2.4E-07
NR	2.6E-07	2.7E-07	2.7E-07
SR	9.6E-07	1.0E-06	1.0E-06

Table 24. χ/Q Calculation Results of Release 110X

Receptor	χ/Q (s/m ³)		
	Mean	Median	0 to 2 hrs 95 th %
110_1	1.7E-05	1.7E-05	2.6E-04
110_2	5.5E-06	5.7E-06	1.3E-04
110_3	6.6E-06	6.9E-06	1.7E-04
120_1	1.5E-05	1.5E-05	1.3E-04
120_2	3.9E-05	3.9E-05	3.5E-04
120_3	7.9E-05	7.9E-05	7.0E-04
120_4	3.4E-05	3.4E-05	3.0E-04
14A	4.8E-06	5.0E-06	5.6E-05
14B	5.8E-05	6.0E-05	2.7E-04
150	6.6E-06	7.0E-06	4.8E-05
160	2.8E-06	3.0E-06	4.6E-05
17A	1.8E-06	1.8E-06	4.6E-05
17BCDE	7.5E-07	7.1E-07	1.2E-05
17FG	1.1E-06	1.1E-06	1.3E-05
17HJ	1.1E-06	1.0E-06	1.3E-05
190_1	2.8E-06	3.0E-06	7.9E-05
190_2	3.6E-06	3.8E-06	9.4E-05
190_3	3.7E-06	3.8E-06	8.9E-05
190_4	3.1E-06	3.2E-06	7.4E-05
210_1	2.2E-06	2.3E-06	5.5E-05
25A	1.9E-05	2.0E-05	3.0E-05
220	1.2E-06	1.3E-06	4.2E-05
240	1.9E-06	2.0E-06	8.3E-05
30A	8.2E-06	8.6E-06	4.0E-05
30B	2.5E-06	2.6E-06	1.9E-05
30C	5.4E-06	5.4E-06	5.2E-05
620	6.3E-06	6.6E-06	3.5E-05
63A	5.0E-06	5.3E-06	3.2E-05
65A	4.3E-06	4.5E-06	2.7E-05
65B	8.2E-06	8.6E-06	3.9E-05
68AB	5.7E-06	6.0E-06	3.2E-05
71AB	6.7E-06	7.1E-06	3.4E-05
NC	4.8E-07	4.5E-07	1.6E-06
IS1	1.2E-07	1.2E-07	2.7E-06
IS2	2.0E-07	1.9E-07	2.2E-06
IS3	1.5E-07	1.6E-07	5.5E-06
NR	9.4E-07	9.9E-07	1.8E-05
SR	3.9E-07	4.0E-07	5.2E-06

Table 25. χ/Q Calculation Results of Release 120X

Receptor	χ/Q (s/m ³)		
	Mean	Median	0 to 2 hrs 95 th %
110_1	2.9E-06	3.0E-06	7.9E-05
110_2	1.9E-06	1.9E-06	5.6E-05
110_3	2.1E-06	2.2E-06	5.8E-05
120_1	5.3E-06	5.5E-06	1.3E-04
120_2	6.6E-06	6.9E-06	1.7E-04
120_3	1.6E-05	1.6E-05	3.8E-04
120_4	5.5E-06	5.7E-06	7.3E-05
14A	2.5E-06	2.6E-06	3.3E-05
14B	1.4E-06	1.5E-06	3.1E-05
150	1.0E-06	1.0E-06	3.0E-05
160	5.1E-07	4.8E-07	1.0E-05
17A	1.1E-06	1.0E-06	1.4E-05
17BCDE	1.3E-06	1.3E-06	1.6E-05
17FG	1.5E-06	1.5E-06	4.3E-05
17HJ	1.8E-06	1.9E-06	4.7E-05
190_1	1.7E-06	1.7E-06	4.2E-05
190_2	1.5E-06	1.6E-06	3.8E-05
190_3	1.2E-06	1.3E-06	3.3E-05
190_4	6.9E-06	7.3E-06	4.8E-05
210_1	8.5E-07	8.9E-07	2.3E-05
25A	1.1E-06	1.2E-06	3.2E-05
220	4.6E-06	4.8E-06	1.8E-05
240	2.0E-06	2.1E-06	2.9E-05
30A	9.8E-06	9.5E-06	8.9E-05
30B	3.5E-06	3.7E-06	2.8E-05
30C	2.6E-06	2.7E-06	2.6E-05
620	2.9E-06	3.1E-06	2.3E-05
63A	5.7E-06	6.0E-06	3.2E-05
65A	3.9E-06	4.1E-06	2.7E-05
65B	4.8E-06	5.0E-06	2.9E-05
68AB	4.1E-07	3.9E-07	6.2E-06
71AB	1.2E-07	1.2E-07	2.5E-06
NC	1.9E-07	1.8E-07	2.0E-06
IS1	1.4E-07	1.5E-07	1.2E-05
IS2	6.7E-07	7.0E-07	4.8E-06
IS3	3.5E-07	3.6E-07	2.7E-06
NR	6.7E-07	7.0E-07	1.2E-05
SR	3.5E-07	3.6E-07	4.8E-06

Table 26. χ/Q Calculation Results of Release 210X

Receptor	χ/Q (s/m ³)		
	Mean	Median	0 to 2 hrs 95 th %
110_1	5.5E-06	5.5E-06	5.3E-05
110_2	8.8E-06	8.6E-06	7.7E-05
110_3	1.2E-05	1.1E-05	1.0E-04
120_1	2.8E-06	2.8E-06	2.8E-05
120_2	4.0E-06	3.9E-06	4.0E-05
120_3	4.1E-06	4.1E-06	4.2E-05
120_4	3.2E-06	3.2E-06	3.4E-05
14A	9.2E-05	9.6E-05	5.3E-04
14B	5.3E-06	5.5E-06	8.5E-05
150	3.5E-05	3.7E-05	1.9E-04
160	1.5E-04	1.6E-04	8.4E-04
17A	5.9E-06	5.8E-06	5.2E-05
17BCDE	9.3E-07	8.7E-07	1.0E-05
17FG	8.7E-07	8.2E-07	9.1E-06
17HJ	7.6E-07	7.3E-07	8.2E-06
190_1	2.0E-05	2.0E-05	1.7E-04
190_2	2.8E-05	2.9E-05	2.4E-04
190_3	4.1E-05	4.1E-05	3.6E-04
190_4	6.7E-05	6.7E-05	5.8E-04
210_1	8.4E-05	8.2E-05	9.1E-04
25A	6.1E-06	6.4E-06	7.9E-05
220	4.2E-06	4.3E-06	3.4E-04
240	1.7E-05	1.8E-05	8.1E-05
30A	1.2E-05	1.3E-05	6.5E-05
30B	3.9E-06	4.1E-06	2.0E-05
30C	2.0E-06	2.0E-06	2.1E-05
620	1.2E-05	1.2E-05	5.7E-05
63A	1.1E-05	1.2E-05	5.5E-05
65A	7.0E-06	7.3E-06	3.4E-05
65B	8.8E-06	9.1E-06	4.8E-05
68AB	9.0E-06	9.5E-06	4.4E-05
71AB	8.3E-06	8.7E-06	4.3E-05
NC	4.7E-07	4.4E-07	1.7E-06
IS1	1.3E-07	1.3E-07	2.8E-06
IS2	2.3E-07	2.2E-07	2.4E-06
IS3	1.6E-07	1.6E-07	5.2E-06
NR	2.8E-06	2.7E-06	4.9E-05
SR	4.8E-07	5.0E-07	6.3E-06

7. REFERENCES

168413 AP-3.12Q, Rev. 2, ICN 2. *Design Calculations and Analyses*. Washington, D.C.: U.S. Department of Energy, Office of Civilian Radioactive Waste Management. ACC: DOC.20040318.0002.

168741 BSC (Bechtel SAIC Company) 2002. *Software Implementation Report for ARCON V.96*. Document Number: 10912-SIR-96-00. Las Vegas, Nevada: Bechtel SAIC Company. ACC: MOL.20030127.0079.

164784 BSC (Bechtel SAIC Company) 2003. *Software Code: ARCON. V.96*. PC, Windows 2000. 10912-96-00.

165572 BSC (Bechtel SAIC Company) 2003. *Underground Layout Configuration*. 800-P0C-MGR0-00100-000-00E. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20031002.0007.

164054 BSC (Bechtel SAIC Company) 2003. *Ventilation Network Model Calculation*. 800-M0C-VU00-00100-000-00A. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20030714.0001.

172130 BSC (Bechtel SAIC Company) 2004. *Canister Handling Facility General Arrangement Second Floor Plan*. 190-P10-CH00-00105-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040914.0019.

171752 BSC (Bechtel SAIC Company) 2004. *Canister Handling Facility General Arrangement Section A & B*. 190-P10-CH00-00108-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040914.0020.

171813 BSC (Bechtel SAIC Company) 2004. *Canister Handling Facility General Arrangement Section K & L*. 190-P10-CH00-00113-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040915.0004.

170639 BSC (Bechtel SAIC Company) 2004. *Canister Handling Facility Tertiary Confinement HVAC Sys Exhaust Air Stacks Ventilation Flow Diagram*. 190-M50-VNT0-00601-000-00A. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040601.0001.

170195 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Operating Floor Key Plan*. 110-P10-WHS0-00103-000-00A. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040503.0004.

170381 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Section A*. 110-P10-WHS0-00128-000-00B. Las Vegas, Nevada: Bechtel

SAIC Company. ACC: ENG.20040623.0013.

170382 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Section B.* 110-P10-WHS0-00129-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040623.0014.

170387 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Section G.* 110-P10-WHS0-00134-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040623.0019.

170392 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Section K.* 110-P10-WHS0-00137-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040623.0022.

170394 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Section M.* 110-P10-WHS0-00139-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040623.0024.

170396 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 /Remediation Facility General Arrangement Section P.* 110-P10-WHS0-00141-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040623.0026.

171245 BSC (Bechtel SAIC Company) 2004. *Dry Transfer Facility #1 HVAC System Exhaust Air Stack Ventilation Flow Diagram.* 110-M50-VN00-00101-000-00A. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040318.0012.

171716 BSC (Bechtel SAIC Company) 2004. *Fuel Handling Facility General Arrangement Ground Floor Plan.* 210-P10-FH00-00102-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040914.0006.

171844 BSC (Bechtel SAIC Company) 2004. *Fuel Handling Facility General Arrangement Section A.* 210-P10-FH00-00108-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040914.0012.

171815 BSC (Bechtel SAIC Company) 2004. *Fuel Handling Facility General Arrangement Section C, D, & G.* 210-P10-FH00-00110-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040914.0014.

171246 BSC (Bechtel SAIC Company) 2004. *Fuel Handling Facility HVAC System Exhaust Air Stack Ventilation Flow Diagram.* 210-M50-VN00-00101-000-00A. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20040621.0008.

171816 BSC (Bechtel SAIC Company) 2004. *Geologic Repository Operations Area North Portal Site Plan.* 100-C00-MGR0-00101-000-00C. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20041007.0004.

172171 BSC (Bechtel SAIC Company) 2004. *Overall Monitored Geologic Repository Site Layout*. 000-C00-MGR0-00101-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20041007.0003.

171599 BSC (Bechtel SAIC Company) 2004. *Project Design Criteria Document*. 000-3DR-MGR0-00100-000-003. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20041124.0001.

172142 BSC (Bechtel SAIC Company) 2004. *Transp Cask Receipt/Return & Non-Nuclear Receipt Facilities General Arrangement Sections D, E, F & G*. 140-P10-WHS0-00112-000-00B. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20041006.0008.

171190 BSC (Bechtel SAIC Company) 2005. Q-List. 000-30R-MGR0-00500-000-001. Las Vegas, Nevada: Bechtel SAIC Company. ACC: ENG.20050217.0010.

171539 DOE (U.S. Department of Energy) 2004. *Quality Assurance Requirements and Description*. DOE/RW-0333P, Rev. 16. Washington, D.C.: U.S. Department of Energy, Office of Civilian Radioactive Waste Management. ACC: DOC.20040907.0002.

171923 LP-SI.11Q-BSC, Rev. 0, ICN 1. *Software Management*. Washington, D.C.: U.S. Department of Energy, Office of Civilian Radioactive Waste Management. ACC: DOC.20041005.0008.

164553 MO0306ARCI9802.001. Stability Class, Wind Speed, Wind Direction, and Delta Temperature Data for ARCON96 Input, 1998-2002. Submittal date: 06/05/2003.

170503 Ramsdell, J.V., Jr. 2004. "RE: Problem of ANRCON96 CFD." E-mail from J.V. Ramsdell, Jr. to J. Wang, July 9, 2004, with attachment. ACC: MOL.20040712.0177.

164547 Ramsdell, J.V., Jr. and Simonen, C.A. 1997. *Atmospheric Relative Concentrations in Building Wakes*. NUREG/CR-6331, Rev. 1. Washington, D.C.: U.S. Nuclear Regulatory Commission. TIC: 233690.

165736 Regulatory Guide 1.194. 2003. *Atmospheric Relative Concentrations for Control Room Radiological Habitability Assessments at Nuclear Power Plants*. Washington, D.C.: U.S. Nuclear Regulatory Commission. Readily available.

8. ATTACHMENTS

Table 27. List of Attachments

Attachments	Description	Pages
I	Major Inputs of ARCON96 Runs	17
II	Surface Facility Layout And Ventilation Design	18
III	Calculation of Mean and Median %/Q Values	3
IV	Electronic I/O Files and Workbooks on CD	56 and CD 1 of 1

I. Major Inputs of ARCON96 Runs

Major ARCON96 inputs for 682 combinations of releases and receptors (see Table 1) are shown in Tables I-1 to I-20. All the inputs and assumptions are described in Section 4 and summarized in Section 6.2.

Table I-1. Major Inputs for the Release Source of DTF1 (110 and 110X)

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_y	σ_z	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	42	4100	15 [0]	210 [0]	2.1	132	122	27	0.0	0.00	0.00	2 [1]
110_2	42	4100	15 [0]	210 [0]	2.1	186	89	27	0.0	0.00	0.00	2 [1]
110_3	42	4600	15 [0]	210 [0]	2.1	168	68	26	0.0	0.00	0.00	2 [1]
120_1	42	4600	15 [0]	210 [0]	2.1	226	190	27	0.0	0.00	0.00	2 [1]
120_2	42	4600	15 [0]	210 [0]	2.1	132	165	27	0.0	0.00	0.00	2 [1]
120_3	42	4600	15 [0]	210 [0]	2.1	90	177	26	0.0	0.00	0.00	2 [1]
120_4	42	4600	15 [0]	210 [0]	2.1	144	202	33	0.0	0.00	0.00	2 [1]
14A	42	4600	15 [0]	210 [0]	2.1	411	22	11	0.0	0.00	0.00	2 [1]
14B	42	4600	15 [0]	210 [0]	2.1	155	360	0	0.0	0.00	0.00	2 [1]
150	42	4100	15 [0]	210 [0]	2.1	456	11	0	0.0	0.00	0.00	2 [1]
160	42	4600	15 [0]	210 [0]	2.1	474	31	0	0.0	0.00	0.00	2 [1]
17A	42	4600	15 [0]	210 [0]	2.1	393	98	0	0.0	0.00	0.00	2 [1]
17BCDE	42	4600	15 [0]	210 [0]	2.1	1210	134	0	0.0	0.00	0.00	2 [1]
17FG	42	4100	15 [0]	210 [0]	2.1	1209	168	0	-4.3	0.00	0.00	2 [1]
17HJ	42	0.01	15 [0]	210 [0]	2.1	1298	193	0	-31.1	0.00	0.00	2 [1]
190_1	42	0.01	15 [0]	210 [0]	2.1	283	67	6.7	-37.8	0.00	0.00	2 [1]
190_2	42	0.01	15 [0]	210 [0]	2.1	266	56	17	-31.7	0.00	0.00	2 [1]
190_3	42	4600	15 [0]	210 [0]	2.1	284	51	17	0.0	0.00	0.00	2 [1]
190_4	42	4600	15 [0]	210 [0]	2.1	323	50	17	0.0	0.00	0.00	2 [1]
210_1	42	4600	15 [0]	210 [0]	2.1	405	49	5.1	0.0	0.00	0.00	2 [1]
25A	42	4600	15 [0]	210 [0]	2.1	311	347	0	0.0	0.00	0.00	2 [1]
220	42	4600	15 [0]	210 [0]	2.1	689	42	0	0.0	0.00	0.00	2 [1]
240	42	4100	15 [0]	210 [0]	2.1	503	43	0	11.0	0.00	0.00	2 [1]
30A	42	4600	15 [0]	210 [0]	2.1	546	351	0	-4.3	0.00	0.00	2 [1]
30B	42	4600	15 [0]	210 [0]	2.1	1287	358	0	0.0	0.00	0.00	2 [1]
30C	42	4600	15 [0]	210 [0]	2.1	410	185	0	13.1	0.00	0.00	2 [1]
620	42	4600	15 [0]	210 [0]	2.1	641	356	0	7.9	0.00	0.00	2 [1]
63A	42	4600	15 [0]	210 [0]	2.1	709	2	0	0.0	0.00	0.00	2 [1]
65A	42	4100	15 [0]	210 [0]	2.1	860	355	0	13.1	0.00	0.00	2 [1]
65B	42	4100	15 [0]	210 [0]	2.1	563	340	0	13.1	0.00	0.00	2 [1]
63AB	42	4100	15 [0]	210 [0]	2.1	705	351	0	13.1	0.00	0.00	2 [1]
71AB	42	4100	15 [0]	210 [0]	2.1	646	343	0	13.1	0.00	0.00	2 [1]
NC	42	4100	15 [0]	210 [0]	2.1	2091	150	0	13.1	0.00	0.00	2 [1]
IS1	42	4100	15 [0]	210 [0]	2.1	3847	106	0	13.1	0.00	0.00	2 [1]
IS2	0	0.01	15 [0]	210 [0]	2.1	3492	135	0	-68.7	0.00	0.00	1
IS3	0	0.01	15 [0]	210 [0]	2.1	2943	87	0	-332.6	0.00	0.00	1
NR	0	0.01	15 [0]	210 [0]	2.1	598	76	0	-292.6	0.00	0.00	1
SR	0	0.01	15 [0]	210 [0]	2.1	3117	26	0	-207.6	0.00	0.00	1

Note: The values in brackets are used for 110X. The rest values are the same for both 110 and 110X.

Table I-2. Major Inputs for the Release Source of DTF2 (120 and 120X)

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	42	4100	15 [0]	210 [0]	2.1	275	73	27	0.0	0.00	0.00	2 [1]
110_2	42	4100	15 [0]	210 [0]	2.1	370	66	27	0.0	0.00	0.00	2 [1]
110_3	42	4600	15 [0]	210 [0]	2.1	375	55	26	0.0	0.00	0.00	2 [1]
120_1	42	4600	15 [0]	210 [0]	2.1	132	123	27	0.0	0.00	0.00	2 [1]
120_2	42	4600	15 [0]	210 [0]	2.1	187	83	27	0.0	0.00	0.00	2 [1]
120_3	42	4600	15 [0]	210 [0]	2.1	168	68	26	0.0	0.00	0.00	2 [1]
120_4	42	4600	15 [0]	210 [0]	2.1	98	79	33	0.0	0.00	0.00	2 [1]
14A	42	4600	15 [0]	210 [0]	2.1	614	30	11	0.0	0.00	0.00	2 [1]
14B	42	4600	15 [0]	210 [0]	2.1	341	26	0	0.0	0.00	0.00	2 [1]
150	42	4100	15 [0]	210 [0]	2.1	645	22	0	0.0	0.00	0.00	2 [1]
160	42	4600	15 [0]	210 [0]	2.1	684	36	0	0.0	0.00	0.00	2 [1]
17A	42	4600	15 [0]	210 [0]	2.1	550	80	0	0.0	0.00	0.00	2 [1]
17BCDE	42	4600	15 [0]	210 [0]	2.1	1232	124	0	0.0	0.00	0.00	2 [1]
17FG	42	4100	15 [0]	210 [0]	2.1	1107	159	0	-4.3	0.00	0.00	2 [1]
17HJ	42	0.01	15 [0]	210 [0]	2.1	1122	187	0	-31.1	0.00	0.00	2 [1]
190_1	42	0.01	15 [0]	210 [0]	2.1	488	58	6.7	-37.8	0.00	0.00	2 [1]
190_2	42	0.01	15 [0]	210 [0]	2.1	478	51	17	-31.7	0.00	0.00	2 [1]
190_3	42	4600	15 [0]	210 [0]	2.1	498	48	17	0.0	0.00	0.00	2 [1]
190_4	42	4600	15 [0]	210 [0]	2.1	537	48	17	0.0	0.00	0.00	2 [1]
210_1	42	4600	15 [0]	210 [0]	2.1	619	48	5.1	0.0	0.00	0.00	2 [1]
25A	42	4600	15 [0]	210 [0]	2.1	462	10	0	11.0	0.00	0.00	2 [1]
220	42	4600	15 [0]	210 [0]	2.1	903	43	0	-4.3	0.00	0.00	2 [1]
240	42	4100	15 [0]	210 [0]	2.1	717	44	0	0.0	0.00	0.00	2 [1]
30A	42	4600	15 [0]	210 [0]	2.1	694	6	0	13.1	0.00	0.00	2 [1]
30B	42	4600	15 [0]	210 [0]	2.1	1442	4	0	7.9	0.00	0.00	2 [1]
30C	42	4600	15 [0]	210 [0]	2.1	282	156	0	0.0	0.00	0.00	2 [1]
620	42	4600	15 [0]	210 [0]	2.1	798	8	0	13.1	0.00	0.00	2 [1]
63A	42	4600	15 [0]	210 [0]	2.1	878	12	0	13.1	0.00	0.00	2 [1]
65A	42	4100	15 [0]	210 [0]	2.1	1012	5	0	13.1	0.00	0.00	2 [1]
65B	42	4100	15 [0]	210 [0]	2.1	683	357	0	13.1	0.00	0.00	2 [1]
68AB	42	4100	15 [0]	210 [0]	2.1	849	3	0	13.1	0.00	0.00	2 [1]
71AB	42	4100	15 [0]	210 [0]	2.1	771	357	0	13.1	0.00	0.00	2 [1]
NC	42	4100	15 [0]	210 [0]	2.1	2047	144	0	-68.7	0.00	0.00	1
IS1	42	4100	15 [0]	210 [0]	2.1	3956	103	0	-332.6	0.00	0.00	1
IS2	0	0.01	15 [0]	210 [0]	2.1	3498	132	0	-292.6	0.00	0.00	1
IS3	0	0.01	15 [0]	210 [0]	2.1	3105	84	0	-207.6	0.00	0.00	1
NR	0	0.01	15 [0]	210 [0]	2.1	788	68	0	-5.2	0.00	0.00	1
SR	0	0.01	15 [0]	210 [0]	2.1	3320	27	0	-42.7	0.00	0.00	1

Note: The values in brackets are used for 120X. The rest values are the same for both 120 and 120X.

Table I-3. Major Inputs for the Release Source of North Aging Facility 17A (17A1)

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	254	275	27	4.3	11.93	2.50	1
110_2	0	0.01	0	0	0	202	298	27	4.3	11.93	2.50	1
110_3	0	0.01	0	0	0	261	307	26	4.3	11.93	2.50	1
120_1	0	0.01	0	0	0	425	252	27	4.3	11.93	2.50	1
120_2	0	0.01	0	0	0	332	264	27	4.3	11.93	2.50	1
120_3	0	0.01	0	0	0	360	270	26	4.3	11.93	2.50	1
120_4	0	0.01	0	0	0	421	264	33	4.3	11.93	2.50	1
14A	0	0.01	0	0	0	517	336	11	4.3	11.93	2.50	1
14B	0	0.01	0	0	0	441	304	0	4.3	11.93	2.50	1
150	0	0.01	0	0	0	607	333	0	4.3	11.93	2.50	1
160	0	0.01	0	0	0	510	347	0	4.3	11.93	2.50	1
17A	0	0.01	0	0	0	47	33	0	4.3	11.93	2.50	1
17BCDE	0	0.01	0	0	0	903	146	0	4.3	11.93	2.50	1
17FG	0	0.01	0	0	0	1096	186	0	0.0	11.93	2.50	1
17HJ	0	0.01	0	0	0	1342	209	0	-26.8	11.93	2.50	1
190_1	0	0.01	0	0	0	226	333	6.7	-33.5	11.93	2.50	1
190_2	0	0.01	0	0	0	279	329	17	-27.4	11.93	2.50	1
190_3	0	0.01	0	0	0	309	332	17	4.3	11.93	2.50	1
190_4	0	0.01	0	0	0	322	339	17	4.3	11.93	2.50	1
210_1	0	0.01	0	0	0	362	351	5.1	4.3	11.93	2.50	1
25A	0	0.01	0	0	0	586	312	0	15.3	11.93	2.50	1
220	0	0.01	0	0	0	612	9	0	0.0	11.93	2.50	1
240	0	0.01	0	0	0	458	358	0	4.3	11.93	2.50	1
30A	0	0.01	0	0	0	775	325	0	17.4	11.93	2.50	1
30B	0	0.01	0	0	0	1438	344	0	12.2	11.93	2.50	1
30C	0	0.01	0	0	0	510	232	0	4.3	11.93	2.50	1
620	0	0.01	0	0	0	838	331	0	17.4	11.93	2.50	1
63A	0	0.01	0	0	0	868	337	0	17.4	11.93	2.50	1
65A	0	0.01	0	0	0	1045	335	0	17.4	11.93	2.50	1
65B	0	0.01	0	0	0	833	318	0	17.4	11.93	2.50	1
68AB	0	0.01	0	0	0	920	329	0	17.4	11.93	2.50	1
71AB	0	0.01	0	0	0	900	322	0	17.4	11.93	2.50	1
NC	0	0.01	0	0	0	1847	158	0	-64.4	11.93	2.50	1
IS1	0	0.01	0	0	0	3472	106	0	-328.3	11.93	2.50	1
IS2	0	0.01	0	0	0	3176	139	0	-288.3	11.93	2.50	1
IS3	0	0.01	0	0	0	2586	84	0	-203.3	11.93	2.50	1
NR	0	0.01	0	0	0	318	43	0	-0.9	11.93	2.50	1
SR	0	0.01	0	0	0	3064	19	0	-38.4	11.93	2.50	1

Table I-4. Major Inputs for the Release Source of South Aging Facility 17A (17A2)

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	304	260	27	4.3	11.93	2.50	1
110_2	0	0.01	0	0	0	226	275	27	4.3	11.93	2.50	1
110_3	0	0.01	0	0	0	269	288	26	4.3	11.93	2.50	1
120_1	0	0.01	0	0	0	495	246	27	4.3	11.93	2.50	1
120_2	0	0.01	0	0	0	392	254	27	4.3	11.93	2.50	1
120_3	0	0.01	0	0	0	412	260	26	4.3	11.93	2.50	1
120_4	0	0.01	0	0	0	480	256	33	4.3	11.93	2.50	1
14A	0	0.01	0	0	0	474	327	11	4.3	11.93	2.50	1
14B	0	0.01	0	0	0	447	293	0	4.3	11.93	2.50	1
150	0	0.01	0	0	0	567	325	0	4.3	11.93	2.50	1
160	0	0.01	0	0	0	453	339	0	4.3	11.93	2.50	1
17A	0	0.01	0	0	0	41	212	0	4.3	11.93	2.50	1
17BCDE	0	0.01	0	0	0	942	151	0	4.3	11.93	2.50	1
17FG	0	0.01	0	0	0	1175	188	0	0.0	11.93	2.50	1
17HJ	0	0.01	0	0	0	1429	209	0	-26.8	11.93	2.50	1
190_1	0	0.01	0	0	0	197	310	6.7	-33.5	11.93	2.50	1
190_2	0	0.01	0	0	0	252	311	17	-27.4	11.93	2.50	1
190_3	0	0.01	0	0	0	275	316	17	4.3	11.93	2.50	1
190_4	0	0.01	0	0	0	279	324	17	4.3	11.93	2.50	1
210_1	0	0.01	0	0	0	302	340	5.1	4.3	11.93	2.50	1
25A	0	0.01	0	0	0	577	304	0	15.3	11.93	2.50	1
220	0	0.01	0	0	0	532	5	0	0.0	11.93	2.50	1
240	0	0.01	0	0	0	389	350	0	4.3	11.93	2.50	1
30A	0	0.01	0	0	0	746	318	0	17.4	11.93	2.50	1
30B	0	0.01	0	0	0	1382	341	0	12.2	11.93	2.50	1
30C	0	0.01	0	0	0	593	229	0	4.3	11.93	2.50	1
620	0	0.01	0	0	0	800	325	0	17.4	11.93	2.50	1
63A	0	0.01	0	0	0	821	332	0	17.4	11.93	2.50	1
65A	0	0.01	0	0	0	1000	331	0	17.4	11.93	2.50	1
65B	0	0.01	0	0	0	813	313	0	17.4	11.93	2.50	1
68AB	0	0.01	0	0	0	884	324	0	17.4	11.93	2.50	1
71AB	0	0.01	0	0	0	873	317	0	17.4	11.93	2.50	1
NC	0	0.01	0	0	0	1900	160	0	-64.4	11.93	2.50	1
IS1	0	0.01	0	0	0	3449	107	0	-328.3	11.93	2.50	1
IS2	0	0.01	0	0	0	3202	140	0	-288.3	11.93	2.50	1
IS3	0	0.01	0	0	0	2534	86	0	-203.3	11.93	2.50	1
NR	0	0.01	0	0	0	232	47	0	-0.9	11.93	2.50	1
SR	0	0.01	0	0	0	2979	19	0	-38.4	11.93	2.50	1

Table I-5. Major Inputs for the Release Source of Aging Facility 17B

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_y	σ_z	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	914	316	27	31.1	52.48	2.50	1
110_2	0	0.01	0	0	0	921	322	27	31.1	52.48	2.50	1
110_3	0	0.01	0	0	0	988	323	26	31.1	52.48	2.50	1
120_1	0	0.01	0	0	0	936	303	27	31.1	52.48	2.50	1
120_2	0	0.01	0	0	0	932	310	27	31.1	52.48	2.50	1
120_3	0	0.01	0	0	0	979	311	26	31.1	52.48	2.50	1
120_4	0	0.01	0	0	0	999	306	33	31.1	52.48	2.50	1
14A	0	0.01	0	0	0	1256	332	11	31.1	52.48	2.50	1
14B	0	0.01	0	0	0	1157	320	0	31.1	52.48	2.50	1
150	0	0.01	0	0	0	1347	331	0	31.1	52.48	2.50	1
160	0	0.01	0	0	0	1237	336	0	31.1	52.48	2.50	1
17A	0	0.01	0	0	0	763	332	0	31.1	52.48	2.50	1
17BCDE	0	0.01	0	0	0	167	133	0	31.1	52.48	2.50	1
17FG	0	0.01	0	0	0	674	227	0	26.8	52.48	2.50	1
17HJ	0	0.01	0	0	0	1168	243	0	0.0	52.48	2.50	1
190_1	0	0.01	0	0	0	967	330	6.7	-6.7	52.48	2.50	1
190_2	0	0.01	0	0	0	1020	329	17	-0.6	52.48	2.50	1
190_3	0	0.01	0	0	0	1049	330	17	31.1	52.48	2.50	1
190_4	0	0.01	0	0	0	1060	332	17	31.1	52.48	2.50	1
210_1	0	0.01	0	0	0	1086	336	5.1	31.1	52.48	2.50	1
25A	0	0.01	0	0	0	1314	322	0	42.1	52.48	2.50	1
220	0	0.01	0	0	0	1271	347	0	26.8	52.48	2.50	1
240	0	0.01	0	0	0	1163	340	0	31.1	52.48	2.50	1
30A	0	0.01	0	0	0	1515	327	0	44.2	52.48	2.50	1
30B	0	0.01	0	0	0	2163	339	0	39.0	52.48	2.50	1
30C	0	0.01	0	0	0	846	292	0	31.1	52.48	2.50	1
620	0	0.01	0	0	0	1579	330	0	44.2	52.48	2.50	1
63A	0	0.01	0	0	0	1605	333	0	44.2	52.48	2.50	1
65A	0	0.01	0	0	0	1784	333	0	44.2	52.48	2.50	1
65B	0	0.01	0	0	0	1568	323	0	44.2	52.48	2.50	1
68AB	0	0.01	0	0	0	1661	329	0	44.2	52.48	2.50	1
71AB	0	0.01	0	0	0	1638	325	0	44.2	52.48	2.50	1
NC	0	0.01	0	0	0	1123	164	0	-37.6	52.48	2.50	1
IS1	0	0.01	0	0	0	2970	96	0	-301.5	52.48	2.50	1
IS2	0	0.01	0	0	0	2450	136	0	-261.5	52.48	2.50	1
IS3	0	0.01	0	0	0	2363	68	0	-176.5	52.48	2.50	1
NR	0	0.01	0	0	0	882	349	0	25.9	52.48	2.50	1
SR	0	0.01	0	0	0	3584	10	0	-11.6	52.48	2.50	1

Table I-6. Major Inputs for the Release Source of Aging Facility 17C

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1098	307	27	31.1	52.48	2.50	1
110_2	0	0.01	0	0	0	1087	312	27	31.1	52.48	2.50	1
110_3	0	0.01	0	0	0	1151	313	26	31.1	52.48	2.50	1
120_1	0	0.01	0	0	0	1149	296	27	31.1	52.48	2.50	1
120_2	0	0.01	0	0	0	1130	302	27	31.1	52.48	2.50	1
120_3	0	0.01	0	0	0	1175	303	26	31.1	52.48	2.50	1
120_4	0	0.01	0	0	0	1204	300	33	31.1	52.48	2.50	1
14A	0	0.01	0	0	0	1388	323	11	31.1	52.48	2.50	1
14B	0	0.01	0	0	0	1328	312	0	31.1	52.48	2.50	1
150	0	0.01	0	0	0	1482	322	0	31.1	52.48	2.50	1
160	0	0.01	0	0	0	1354	327	0	31.1	52.48	2.50	1
17A	0	0.01	0	0	0	904	318	0	31.1	52.48	2.50	1
17BCDE	0	0.01	0	0	0	167	227	0	31.1	52.48	2.50	1
17FG	0	0.01	0	0	0	870	238	0	26.8	52.48	2.50	1
17HJ	0	0.01	0	0	0	1390	247	0	0.0	52.48	2.50	1
190_1	0	0.01	0	0	0	1110	319	6.7	-6.7	52.48	2.50	1
190_2	0	0.01	0	0	0	1165	319	17	-0.6	52.48	2.50	1
190_3	0	0.01	0	0	0	1191	320	17	31.1	52.48	2.50	1
190_4	0	0.01	0	0	0	1195	321	17	31.1	52.48	2.50	1
210_1	0	0.01	0	0	0	1206	325	5.1	31.1	52.48	2.50	1
25A	0	0.01	0	0	0	1478	314	0	42.1	52.48	2.50	1
220	0	0.01	0	0	0	1347	337	0	26.8	52.48	2.50	1
240	0	0.01	0	0	0	1269	329	0	31.1	52.48	2.50	1
30A	0	0.01	0	0	0	1662	320	0	44.2	52.48	2.50	1
30B	0	0.01	0	0	0	2263	333	0	39.0	52.48	2.50	1
30C	0	0.01	0	0	0	1076	287	0	31.1	52.48	2.50	1
620	0	0.01	0	0	0	1714	323	0	44.2	52.48	2.50	1
63A	0	0.01	0	0	0	1728	326	0	44.2	52.48	2.50	1
65A	0	0.01	0	0	0	1908	326	0	44.2	52.48	2.50	1
65B	0	0.01	0	0	0	1725	317	0	44.2	52.48	2.50	1
68AB	0	0.01	0	0	0	1799	322	0	44.2	52.48	2.50	1
71AB	0	0.01	0	0	0	1788	319	0	44.2	52.48	2.50	1
NC	0	0.01	0	0	0	1083	177	0	-37.6	52.48	2.50	1
IS1	0	0.01	0	0	0	2728	97	0	-301.5	52.48	2.50	1
IS2	0	0.01	0	0	0	2286	140	0	-261.5	52.48	2.50	1
IS3	0	0.01	0	0	0	2138	66	0	-176.5	52.48	2.50	1
NR	0	0.01	0	0	0	959	335	0	25.9	52.48	2.50	1
SR	0	0.01	0	0	0	3551	6	0	-11.6	52.48	2.50	1

Table I-7. Major Inputs for the Release Source of Aging Facility 17D

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1091	324	27	31.1	52.48	2.50	1
110_2	0	0.01	0	0	0	1112	330	27	31.1	52.48	2.50	1
110_3	0	0.01	0	0	0	1180	330	26	31.1	52.48	2.50	1
120_1	0	0.01	0	0	0	1077	313	27	31.1	52.48	2.50	1
120_2	0	0.01	0	0	0	1094	319	27	31.1	52.48	2.50	1
120_3	0	0.01	0	0	0	1142	319	26	31.1	52.48	2.50	1
120_4	0	0.01	0	0	0	1150	316	33	31.1	52.48	2.50	1
14A	0	0.01	0	0	0	1462	336	11	31.1	52.48	2.50	1
14B	0	0.01	0	0	0	1340	326	0	31.1	52.48	2.50	1
150	0	0.01	0	0	0	1551	335	0	31.1	52.48	2.50	1
160	0	0.01	0	0	0	1450	340	0	31.1	52.48	2.50	1
17A	0	0.01	0	0	0	972	338	0	31.1	52.48	2.50	1
17BCDE	0	0.01	0	0	0	168	47	0	31.1	52.48	2.50	1
17FG	0	0.01	0	0	0	546	245	0	26.8	52.48	2.50	1
17HJ	0	0.01	0	0	0	1082	253	0	0.0	52.48	2.50	1
190_1	0	0.01	0	0	0	1171	335	6.7	-6.7	52.48	2.50	1
190_2	0	0.01	0	0	0	1223	335	17	-0.6	52.48	2.50	1
190_3	0	0.01	0	0	0	1253	335	17	31.1	52.48	2.50	1
190_4	0	0.01	0	0	0	1267	337	17	31.1	52.48	2.50	1
210_1	0	0.01	0	0	0	1299	340	5.1	31.1	52.48	2.50	1
25A	0	0.01	0	0	0	1501	327	0	42.1	52.48	2.50	1
220	0	0.01	0	0	0	1496	349	0	26.8	52.48	2.50	1
240	0	0.01	0	0	0	1381	343	0	31.1	52.48	2.50	1
30A	0	0.01	0	0	0	1712	331	0	44.2	52.48	2.50	1
30B	0	0.01	0	0	0	2378	341	0	39.0	52.48	2.50	1
30C	0	0.01	0	0	0	957	305	0	31.1	52.48	2.50	1
620	0	0.01	0	0	0	1781	334	0	44.2	52.48	2.50	1
63A	0	0.01	0	0	0	1813	337	0	44.2	52.48	2.50	1
65A	0	0.01	0	0	0	1990	336	0	44.2	52.48	2.50	1
65B	0	0.01	0	0	0	1758	328	0	44.2	52.48	2.50	1
68AB	0	0.01	0	0	0	1862	333	0	44.2	52.48	2.50	1
71AB	0	0.01	0	0	0	1832	329	0	44.2	52.48	2.50	1
NC	0	0.01	0	0	0	904	161	0	-37.6	52.48	2.50	1
IS1	0	0.01	0	0	0	2954	92	0	-301.5	52.48	2.50	1
IS2	0	0.01	0	0	0	2291	132	0	-261.5	52.48	2.50	1
IS3	0	0.01	0	0	0	2458	63	0	-176.5	52.48	2.50	1
NR	0	0.01	0	0	0	1109	351	0	25.9	52.48	2.50	1
SR	0	0.01	0	0	0	3811	9	0	-11.6	52.48	2.50	1

Table I-8. Major Inputs for the Release Source of Aging Facility 17E

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1249	315	27	31.1	52.48	2.50	1
110_2	0	0.01	0	0	0	1253	320	27	31.1	52.48	2.50	1
110_3	0	0.01	0	0	0	1320	321	26	31.1	52.48	2.50	1
120_1	0	0.01	0	0	0	1267	305	27	31.1	52.48	2.50	1
120_2	0	0.01	0	0	0	1267	311	27	31.1	52.48	2.50	1
120_3	0	0.01	0	0	0	1314	311	26	31.1	52.48	2.50	1
120_4	0	0.01	0	0	0	1332	308	33	31.1	52.48	2.50	1
14A	0	0.01	0	0	0	1577	328	11	31.1	52.48	2.50	1
14B	0	0.01	0	0	0	1490	318	0	31.1	52.48	2.50	1
150	0	0.01	0	0	0	1670	327	0	31.1	52.48	2.50	1
160	0	0.01	0	0	0	1551	331	0	31.1	52.48	2.50	1
17A	0	0.01	0	0	0	1086	326	0	31.1	52.48	2.50	1
17BCDE	0	0.01	0	0	0	168	313	0	31.1	52.48	2.50	1
17FG	0	0.01	0	0	0	774	253	0	26.8	52.48	2.50	1
17HJ	0	0.01	0	0	0	1318	256	0	0.0	52.48	2.50	1
190_1	0	0.01	0	0	0	1292	326	6.7	-6.7	52.48	2.50	1
190_2	0	0.01	0	0	0	1346	325	17	-0.6	52.48	2.50	1
190_3	0	0.01	0	0	0	1374	326	17	31.1	52.48	2.50	1
190_4	0	0.01	0	0	0	1382	327	17	31.1	52.48	2.50	1
210_1	0	0.01	0	0	0	1401	331	5.1	31.1	52.48	2.50	1
25A	0	0.01	0	0	0	1646	320	0	42.1	52.48	2.50	1
220	0	0.01	0	0	0	1561	340	0	26.8	52.48	2.50	1
240	0	0.01	0	0	0	1471	334	0	31.1	52.48	2.50	1
30A	0	0.01	0	0	0	1843	324	0	44.2	52.48	2.50	1
30B	0	0.01	0	0	0	2470	335	0	39.0	52.48	2.50	1
30C	0	0.01	0	0	0	1165	298	0	31.1	52.48	2.50	1
620	0	0.01	0	0	0	1902	327	0	44.2	52.48	2.50	1
63A	0	0.01	0	0	0	1923	330	0	44.2	52.48	2.50	1
65A	0	0.01	0	0	0	2103	330	0	44.2	52.48	2.50	1
65B	0	0.01	0	0	0	1899	322	0	44.2	52.48	2.50	1
68AB	0	0.01	0	0	0	1986	326	0	44.2	52.48	2.50	1
71AB	0	0.01	0	0	0	1967	323	0	44.2	52.48	2.50	1
NC	0	0.01	0	0	0	854	176	0	-37.6	52.48	2.50	1
IS1	0	0.01	0	0	0	2710	92	0	-301.5	52.48	2.50	1
IS2	0	0.01	0	0	0	2115	136	0	-261.5	52.48	2.50	1
IS3	0	0.01	0	0	0	2243	60	0	-176.5	52.48	2.50	1
NR	0	0.01	0	0	0	1171	339	0	25.9	52.48	2.50	1
SR	0	0.01	0	0	0	3779	6	0	-11.6	52.48	2.50	1

Table I-9. Major Inputs for the Release Source of Aging Facility 17F

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1236	352	27	37.8	52.48	2.50	1
110_2	0	0.01	0	0	0	1301	356	27	37.8	52.48	2.50	1
110_3	0	0.01	0	0	0	1364	355	26	37.8	52.48	2.50	1
120_1	0	0.01	0	0	0	1118	344	27	37.8	52.48	2.50	1
120_2	0	0.01	0	0	0	1192	348	27	37.8	52.48	2.50	1
120_3	0	0.01	0	0	0	1235	347	26	37.8	52.48	2.50	1
120_4	0	0.01	0	0	0	1208	344	33	37.8	52.48	2.50	1
14A	0	0.01	0	0	0	1680	356	11	37.8	52.48	2.50	1
14B	0	0.01	0	0	0	1476	349	0	37.8	52.48	2.50	1
150	0	0.01	0	0	0	1753	354	0	37.8	52.48	2.50	1
160	0	0.01	0	0	0	1699	359	0	37.8	52.48	2.50	1
17A	0	0.01	0	0	0	1247	5	0	37.8	52.48	2.50	1
17BCDE	0	0.01	0	0	0	749	53	0	37.8	52.48	2.50	1
17FG	0	0.01	0	0	0	115	348	0	33.5	52.48	2.50	1
17HJ	0	0.01	0	0	0	564	273	0	6.7	52.48	2.50	1
190_1	0	0.01	0	0	0	1404	359	6.7	0.0	52.48	2.50	1
190_2	0	0.01	0	0	0	1444	358	17	6.1	52.48	2.50	1
190_3	0	0.01	0	0	0	1476	358	17	37.8	52.48	2.50	1
190_4	0	0.01	0	0	0	1503	359	17	37.8	52.48	2.50	1
210_1	0	0.01	0	0	0	1561	1	5.1	37.8	52.48	2.50	1
25A	0	0.01	0	0	0	1635	348	0	48.8	52.48	2.50	1
220	0	0.01	0	0	0	1816	6	0	33.5	52.48	2.50	1
240	0	0.01	0	0	0	1661	2	0	37.8	52.48	2.50	1
30A	0	0.01	0	0	0	1869	349	0	50.9	52.48	2.50	1
30B	0	0.01	0	0	0	2601	353	0	45.7	52.48	2.50	1
30C	0	0.01	0	0	0	939	341	0	37.8	52.48	2.50	1
620	0	0.01	0	0	0	1961	351	0	50.9	52.48	2.50	1
63A	0	0.01	0	0	0	2018	353	0	50.9	52.48	2.50	1
65A	0	0.01	0	0	0	2180	351	0	50.9	52.48	2.50	1
65B	0	0.01	0	0	0	1884	346	0	50.9	52.48	2.50	1
68AB	0	0.01	0	0	0	2028	349	0	50.9	52.48	2.50	1
71AB	0	0.01	0	0	0	1969	346	0	50.9	52.48	2.50	1
NC	0	0.01	0	0	0	930	124	0	-30.9	52.48	2.50	1
IS1	0	0.01	0	0	0	3434	86	0	-294.8	52.48	2.50	1
IS2	0	0.01	0	0	0	2484	119	0	-254.8	52.48	2.50	1
IS3	0	0.01	0	0	0	3035	61	0	-169.8	52.48	2.50	1
NR	0	0.01	0	0	0	1467	12	0	32.6	52.48	2.50	1
SR	0	0.01	0	0	0	4241	15	0	-4.9	52.48	2.50	1

Table I-10. Major Inputs for the Release Source of Aging Facility 17G

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1007	353	27	37.8	52.48	2.50	1
110_2	0	0.01	0	0	0	1074	358	27	37.8	52.48	2.50	1
110_3	0	0.01	0	0	0	1137	356	26	37.8	52.48	2.50	1
120_1	0	0.01	0	0	0	890	342	27	37.8	52.48	2.50	1
120_2	0	0.01	0	0	0	963	348	27	37.8	52.48	2.50	1
120_3	0	0.01	0	0	0	1006	347	26	37.8	52.48	2.50	1
120_4	0	0.01	0	0	0	979	343	33	37.8	52.48	2.50	1
14A	0	0.01	0	0	0	1453	357	11	37.8	52.48	2.50	1
14B	0	0.01	0	0	0	1246	349	0	37.8	52.48	2.50	1
150	0	0.01	0	0	0	1525	355	0	37.8	52.48	2.50	1
160	0	0.01	0	0	0	1475	1	0	37.8	52.48	2.50	1
17A	0	0.01	0	0	0	1030	9	0	37.8	52.48	2.50	1
17BCDE	0	0.01	0	0	0	681	70	0	37.8	52.48	2.50	1
17FG	0	0.01	0	0	0	115	168	0	33.5	52.48	2.50	1
17HJ	0	0.01	0	0	0	553	249	0	6.7	52.48	2.50	1
190_1	0	0.01	0	0	0	1180	2	6.7	0.0	52.48	2.50	1
190_2	0	0.01	0	0	0	1218	360	17	6.1	52.48	2.50	1
190_3	0	0.01	0	0	0	1251	360	17	37.8	52.48	2.50	1
190_4	0	0.01	0	0	0	1278	1	17	37.8	52.48	2.50	1
210_1	0	0.01	0	0	0	1338	3	5.1	37.8	52.48	2.50	1
25A	0	0.01	0	0	0	1405	348	0	48.8	52.48	2.50	1
220	0	0.01	0	0	0	1599	8	0	33.5	52.48	2.50	1
240	0	0.01	0	0	0	1440	5	0	37.8	52.48	2.50	1
30A	0	0.01	0	0	0	1640	349	0	50.9	52.48	2.50	1
30B	0	0.01	0	0	0	2373	353	0	45.7	52.48	2.50	1
30C	0	0.01	0	0	0	713	338	0	37.8	52.48	2.50	1
620	0	0.01	0	0	0	1732	351	0	50.9	52.48	2.50	1
63A	0	0.01	0	0	0	1790	354	0	50.9	52.48	2.50	1
65A	0	0.01	0	0	0	1951	351	0	50.9	52.48	2.50	1
65B	0	0.01	0	0	0	1655	345	0	50.9	52.48	2.50	1
68AB	0	0.01	0	0	0	1799	349	0	50.9	52.48	2.50	1
71AB	0	0.01	0	0	0	1740	346	0	50.9	52.48	2.50	1
NC	0	0.01	0	0	0	1104	132	0	-30.9	52.48	2.50	1
IS1	0	0.01	0	0	0	3471	90	0	-294.8	52.48	2.50	1
IS2	0	0.01	0	0	0	2637	122	0	-254.8	52.48	2.50	1
IS3	0	0.01	0	0	0	2976	66	0	-169.8	52.48	2.50	1
NR	0	0.01	0	0	0	1260	16	0	32.6	52.48	2.50	1
SR	0	0.01	0	0	0	4037	16	0	-4.9	52.48	2.50	1

Table I-11. Major Inputs for the Release Source of Aging Facility 17H

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1330	14	27	31.7	46.20	2.50	1
110_2	0	0.01	0	0	0	1420	16	27	31.7	46.20	2.50	1
110_3	0	0.01	0	0	0	1471	15	26	31.7	46.20	2.50	1
120_1	0	0.01	0	0	0	1151	9	27	31.7	46.20	2.50	1
120_2	0	0.01	0	0	0	1257	11	27	31.7	46.20	2.50	1
120_3	0	0.01	0	0	0	1289	10	26	31.7	46.20	2.50	1
120_4	0	0.01	0	0	0	1237	7	33	31.7	46.20	2.50	1
14A	0	0.01	0	0	0	1780	12	11	31.7	46.20	2.50	1
14B	0	0.01	0	0	0	1529	8	0	31.7	46.20	2.50	1
150	0	0.01	0	0	0	1833	10	0	31.7	46.20	2.50	1
160	0	0.01	0	0	0	1823	15	0	31.7	46.20	2.50	1
17A	0	0.01	0	0	0	1440	25	0	31.7	46.20	2.50	1
17BCDE	0	0.01	0	0	0	1202	64	0	31.7	46.20	2.50	1
17FG	0	0.01	0	0	0	498	69	0	27.4	46.20	2.50	1
17HJ	0	0.01	0	0	0	121	322	0	0.6	46.20	2.50	1
190_1	0	0.01	0	0	0	1544	18	6.7	-6.1	46.20	2.50	1
190_2	0	0.01	0	0	0	1569	16	17	0.0	46.20	2.50	1
190_3	0	0.01	0	0	0	1600	16	17	31.7	46.20	2.50	1
190_4	0	0.01	0	0	0	1634	16	17	31.7	46.20	2.50	1
210_1	0	0.01	0	0	0	1707	18	5.1	31.7	46.20	2.50	1
25A	0	0.01	0	0	0	1670	5	0	42.7	46.20	2.50	1
220	0	0.01	0	0	0	1990	20	0	27.4	46.20	2.50	1
240	0	0.01	0	0	0	1813	18	0	31.7	46.20	2.50	1
30A	0	0.01	0	0	0	1904	4	0	44.8	46.20	2.50	1
30B	0	0.01	0	0	0	2652	4	0	39.6	46.20	2.50	1
30C	0	0.01	0	0	0	968	11	0	31.7	46.20	2.50	1
620	0	0.01	0	0	0	2007	5	0	44.8	46.20	2.50	1
63A	0	0.01	0	0	0	2083	7	0	44.8	46.20	2.50	1
65A	0	0.01	0	0	0	2222	4	0	44.8	46.20	2.50	1
65B	0	0.01	0	0	0	1891	1	0	44.8	46.20	2.50	1
68AB	0	0.01	0	0	0	2059	3	0	44.8	46.20	2.50	1
71AB	0	0.01	0	0	0	1979	1	0	44.8	46.20	2.50	1
NC	0	0.01	0	0	0	1341	110	0	-37.0	46.20	2.50	1
IS1	0	0.01	0	0	0	3926	86	0	-300.9	46.20	2.50	1
IS2	0	0.01	0	0	0	2896	113	0	-260.9	46.20	2.50	1
IS3	0	0.01	0	0	0	3499	64	0	-175.9	46.20	2.50	1
NR	0	0.01	0	0	0	1697	28	0	26.5	46.20	2.50	1
SR	0	0.01	0	0	0	4452	21	0	-11.0	46.20	2.50	1

Table I-12. Major Inputs for the Release Source of Aging Facility 17J

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	0	0.01	0	0	0	1177	22	27	31.7	52.48	2.50	1
110_2	0	0.01	0	0	0	1273	24	27	31.7	52.48	2.50	1
110_3	0	0.01	0	0	0	1318	21	26	31.7	52.48	2.50	1
120_1	0	0.01	0	0	0	983	17	27	31.7	52.48	2.50	1
120_2	0	0.01	0	0	0	1096	19	27	31.7	52.48	2.50	1
120_3	0	0.01	0	0	0	1123	17	26	31.7	52.48	2.50	1
120_4	0	0.01	0	0	0	1065	15	33	31.7	52.48	2.50	1
14A	0	0.01	0	0	0	1617	17	11	31.7	52.48	2.50	1
14B	0	0.01	0	0	0	1357	14	0	31.7	52.48	2.50	1
150	0	0.01	0	0	0	1663	14	0	31.7	52.48	2.50	1
160	0	0.01	0	0	0	1669	20	0	31.7	52.48	2.50	1
17A	0	0.01	0	0	0	1320	33	0	31.7	52.48	2.50	1
17BCDE	0	0.01	0	0	0	1238	75	0	31.7	52.48	2.50	1
17FG	0	0.01	0	0	0	577	92	0	27.4	52.48	2.50	1
17HJ	0	0.01	0	0	0	108	160	0	0.6	52.48	2.50	1
190_1	0	0.01	0	0	0	1401	25	6.7	-6.1	52.48	2.50	1
190_2	0	0.01	0	0	0	1420	23	17	0.0	52.48	2.50	1
190_3	0	0.01	0	0	0	1450	22	17	31.7	52.48	2.50	1
190_4	0	0.01	0	0	0	1486	23	17	31.7	52.48	2.50	1
210_1	0	0.01	0	0	0	1562	24	5.1	31.7	52.48	2.50	1
25A	0	0.01	0	0	0	1489	10	0	42.7	52.48	2.50	1
220	0	0.01	0	0	0	1850	25	0	27.4	52.48	2.50	1
240	0	0.01	0	0	0	1669	24	0	31.7	52.48	2.50	1
30A	0	0.01	0	0	0	1720	8	0	44.8	52.48	2.50	1
30B	0	0.01	0	0	0	2466	7	0	39.6	52.48	2.50	1
30C	0	0.01	0	0	0	808	21	0	31.7	52.48	2.50	1
620	0	0.01	0	0	0	1825	9	0	44.8	52.48	2.50	1
63A	0	0.01	0	0	0	1905	11	0	44.8	52.48	2.50	1
65A	0	0.01	0	0	0	2036	7	0	44.8	52.48	2.50	1
65B	0	0.01	0	0	0	1700	5	0	44.8	52.48	2.50	1
68AB	0	0.01	0	0	0	1872	7	0	44.8	52.48	2.50	1
71AB	0	0.01	0	0	0	1788	4	0	44.8	52.48	2.50	1
NC	0	0.01	0	0	0	1519	115	0	-37.0	52.48	2.50	1
IS1	0	0.01	0	0	0	4027	88	0	-300.9	52.48	2.50	1
IS2	0	0.01	0	0	0	3078	115	0	-260.9	52.48	2.50	1
IS3	0	0.01	0	0	0	3522	68	0	-175.9	52.48	2.50	1
NR	0	0.01	0	0	0	1587	35	0	26.5	52.48	2.50	1
SR	0	0.01	0	0	0	4311	23	0	-11.0	52.48	2.50	1

Table I-13. Major Inputs for the Release Source of Canister Handling Facility (190)

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	36	2200	11	21	0.62	318	211	27	0.0	0.00	0.00	2
110_2	36	2200	11	21	0.62	219	204	27	0.0	0.00	0.00	2
110_3	36	2200	11	21	0.62	183	221	26	0.0	0.00	0.00	2
120_1	36	2200	11	21	0.62	529	216	27	0.0	0.00	0.00	2
120_2	36	2200	11	21	0.62	408	216	27	0.0	0.00	0.00	2
120_3	36	2200	11	21	0.62	398	223	26	0.0	0.00	0.00	2
120_4	36	2200	11	21	0.62	471	224	33	0.0	0.00	0.00	2
14A	36	2200	11	21	0.62	213	326	11	0.0	0.00	0.00	2
14B	36	2200	11	21	0.62	279	260	0	0.0	0.00	0.00	2
150	36	1700	11	21	0.62	307	323	0	0.0	0.00	0.00	2
160	36	1700	11	21	0.62	203	352	0	0.0	0.00	0.00	2
17A	36	1700	11	21	0.62	281	156	0	0.0	0.00	0.00	2
17BCDE	36	1700	11	21	0.62	1202	150	0	0.0	0.00	0.00	2
17FG	36	1700	11	21	0.62	1386	181	0	-4.3	0.00	0.00	2
17HJ	36	0.01	11	21	0.62	1572	201	0	-31.1	0.00	0.00	2
190_1	36	0.01	11	21	0.62	95	188	6.7	-37.8	0.00	0.00	2
190_2	36	0.01	11	21	0.62	76	223	17	-31.7	0.00	0.00	2
190_3	36	2200	11	21	0.62	59	247	17	0.0	0.00	0.00	2
190_4	36	2200	11	21	0.62	27	281	17	0.0	0.00	0.00	2
210_1	36	2200	11	21	0.62	70	28	5.1	0.0	0.00	0.00	2
25A	36	1700	11	21	0.62	356	286	0	11.0	0.00	0.00	2
220	36	2200	11	21	0.62	361	31	0	-4.3	0.00	0.00	2
240	36	2200	11	21	0.62	177	24	0	0.0	0.00	0.00	2
30A	36	1700	11	21	0.62	491	313	0	13.1	0.00	0.00	2
30B	36	1700	11	21	0.62	1129	344	0	7.9	0.00	0.00	2
30C	36	2200	11	21	0.62	686	207	0	0.0	0.00	0.00	2
620	36	1700	11	21	0.62	540	324	0	13.1	0.00	0.00	2
63A	36	1700	11	21	0.62	561	334	0	13.1	0.00	0.00	2
65A	36	1700	11	21	0.62	740	332	0	13.1	0.00	0.00	2
65B	36	1700	11	21	0.62	567	305	0	13.1	0.00	0.00	2
68AB	36	1700	11	21	0.62	625	322	0	13.1	0.00	0.00	2
71AB	36	1700	11	21	0.62	620	312	0	13.1	0.00	0.00	2
NC	0	0.01	11	21	0.62	2156	159	0	-68.7	0.00	0.00	1
IS1	0	0.01	11	21	0.62	3650	110	0	-332.6	0.00	0.00	1
IS2	0	0.01	11	21	0.62	3461	141	0	-292.6	0.00	0.00	1
IS3	0	0.01	11	21	0.62	2665	91	0	-207.6	0.00	0.00	1
NR	0	0.01	11	21	0.62	314	102	0	-5.2	0.00	0.00	1
SR	0	0.01	11	21	0.62	2819	23	0	-42.7	0.00	0.00	1

Table I-14. Major Inputs for the Release Source of Fuel Handling Facility (210 and 210X)

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
110_1	36 (27)	1700	13 [0]	36 [0]	0.95	405	201	27	0.0	0.00	0.00	2 [1]
110_2	36 (27)	1700	13 [0]	36 [0]	0.95	314	193	27	0.0	0.00	0.00	2 [1]
110_3	36 (26)	1700	13 [0]	36 [0]	0.95	264	202	26	0.0	0.00	0.00	2 [1]
120_1	36 (27)	1700	13 [0]	36 [0]	0.95	608	209	27	0.0	0.00	0.00	2 [1]
120_2	36 (27)	1700	13 [0]	36 [0]	0.95	489	207	27	0.0	0.00	0.00	2 [1]
120_3	36 (26)	1700	13 [0]	36 [0]	0.95	470	212	26	0.0	0.00	0.00	2 [1]
120_4	36 (33)	1700	13 [0]	36 [0]	0.95	540	215	33	0.0	0.00	0.00	2 [1]
14A	36 (11)	1700	13 [0]	36 [0]	0.95	123	306	11	0.0	0.00	0.00	2 [1]
14B	36 (0)	1700	13 [0]	36 [0]	0.95	299	239	0	0.0	0.00	0.00	2 [1]
150	36 (0)	1300	13 [0]	36 [0]	0.95	218	310	0	0.0	0.00	0.00	2 [1]
160	36 (0)	1300	13 [0]	36 [0]	0.95	96	355	0	0.0	0.00	0.00	2 [1]
17A	36 (0)	1300	13 [0]	36 [0]	0.95	385	160	0	0.0	0.00	0.00	2 [1]
17BCDE	36 (0)	1300	13 [0]	36 [0]	0.95	1303	152	0	0.0	0.00	0.00	2 [1]
17FG	36 (0)	1300	13 [0]	36 [0]	0.95	1491	180	0	-4.3	0.00	0.00	2 [1]
17HJ	36 (0)	0.01	13 [0]	36 [0]	0.95	1665	199	0	-31.1	0.00	0.00	2 [1]
190_1	36 (6.7)	0.01	13 [0]	36 [0]	0.95	199	179	6.7	-37.8	0.00	0.00	2 [1]
190_2	36 (17)	0.01	13 [0]	36 [0]	0.95	164	192	17	-31.7	0.00	0.00	2 [1]
190_3	36 (17)	1700	13 [0]	36 [0]	0.95	133	196	17	0.0	0.00	0.00	2 [1]
190_4	36 (17)	1700	13 [0]	36 [0]	0.95	101	185	17	0.0	0.00	0.00	2 [1]
210_1	36 (5.1)	1300	13 [0]	36 [0]	0.95	67	130	5.1	0.0	0.00	0.00	2 [1]
25A	36 (0)	1300	13 [0]	36 [0]	0.95	324	269	0	11.0	0.00	0.00	2 [1]
220	36 (0)	1700	13 [0]	36 [0]	0.95	289	45	0	-4.3	0.00	0.00	2 [1]
240	36 (0)	1700	13 [0]	36 [0]	0.95	106	58	0	0.0	0.00	0.00	2 [1]
30A	36 (0)	1300	13 [0]	36 [0]	0.95	411	304	0	13.1	0.00	0.00	2 [1]
30B	36 (0)	1300	13 [0]	36 [0]	0.95	1023	343	0	7.9	0.00	0.00	2 [1]
30C	36 (0)	1700	13 [0]	36 [0]	0.95	774	202	0	0.0	0.00	0.00	2 [1]
620	36 (0)	1300	13 [0]	36 [0]	0.95	446	318	0	13.1	0.00	0.00	2 [1]
63A	36 (0)	1300	13 [0]	36 [0]	0.95	460	331	0	13.1	0.00	0.00	2 [1]
65A	36 (0)	1300	13 [0]	36 [0]	0.95	639	329	0	13.1	0.00	0.00	2 [1]
65B	36 (0)	1300	13 [0]	36 [0]	0.95	497	297	0	13.1	0.00	0.00	2 [1]
68AB	36 (0)	1300	13 [0]	36 [0]	0.95	533	317	0	13.1	0.00	0.00	2 [1]
71AB	36 (0)	1300	13 [0]	36 [0]	0.95	540	305	0	13.1	0.00	0.00	2 [1]
NC	0	0.01	13 [0]	36 [0]	0.95	2260	159	0	-68.7	0.00	0.00	1
IS1	0	0.01	13 [0]	36 [0]	0.95	3704	112	0	-332.6	0.00	0.00	1
IS2	0	0.01	13 [0]	36 [0]	0.95	3554	142	0	-292.6	0.00	0.00	1
IS3	0	0.01	13 [0]	36 [0]	0.95	2687	93	0	-207.6	0.00	0.00	1
NR	0	0.01	13 [0]	36 [0]	0.95	366	117	0	-5.2	0.00	0.00	1
SR	0	0.01	13 [0]	36 [0]	0.95	2730	24	0	-42.7	0.00	0.00	1

Note: The values in brackets are used for 210X. The rest values are the same for both 210 and 210X.

Table I-15. Major Inputs for the Release Source of Subsurface ECRB Exhaust Shaft

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
NC	0	0	7.8	394	4.0	3590	232	0	289	0	0	1
IS1	0	0	7.8	394	4.0	1460	187	0	25	0	0	1
IS2	0	0	7.8	394	4.0	3210	206	0	65	0	0	1
IS3	0	0	7.8	394	4.0	972	256	0	150	0	0	1
NR*	0	0	7.8	394	4.0	3310	266	0	352	0	0	1
SR	0	0	7.8	394	4.0	3490	314	0	315	0	0	1

Note: *The receptor location of Emplacement Ramp is used conservatively to represent other receptor locations of surface facilities.

Table I-16. Major Inputs for the Release Source of Subsurface Exhaust Raise #1

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
NC	0	0	9.5	186	2.5	2800	244	0	249	0	0	1
IS1	0	0	9.5	186	2.5	482	165	0	-15	0	0	1
IS2	0	0	9.5	186	2.5	2200	211	0	25	0	0	1
IS3	0	0	9.5	186	2.5	981	320	0	110	0	0	1
NR*	0	0	9.5	186	2.5	3080	284	0	312	0	0	1
SR	0	0	9.5	186	2.5	4050	327	0	275	0	0	1

Note: *The receptor location of Emplacement Ramp is used conservatively to represent other receptor locations of surface facilities.

Table I-17. Major Inputs for the Release Source of Subsurface Exhaust Raise #2

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
NC	0	0	9.5	186	2.5	1470	244	0	154	0	0	1
IS1	0	0	9.5	186	2.5	1330	85	0	-110	0	0	1
IS2	0	0	9.5	186	2.5	1330	176	0	-70	0	0	1
IS3	0	0	9.5	186	2.5	1440	23	0	15	0	0	1
NR*	0	0	9.5	186	2.5	221	306	0	217	0	0	1
SR	0	0	9.5	186	2.5	4090	346	0	180	0	0	1

Note: *The receptor location of Emplacement Ramp is used conservatively to represent other receptor locations of surface facilities.

Table I-18. Major Inputs for the Release Source of Subsurface Exhaust Shaft #1

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
NC	0	0	7.7	385	4.0	2740	263	0	284	0	0	1
IS1	0	0	7.7	385	4.0	411	351	0	20	0	0	1
IS2	0	0	7.7	385	4.0	1660	232	0	60	0	0	1
IS3	0	0	7.7	385	4.0	1820	333	0	145	0	0	1
NR*	0	0	7.7	385	4.0	3560	297	0	347	0	0	1
SR	0	0	7.7	385	4.0	4900	331	0	310	0	0	1

Note: *The receptor location of Emplacement Ramp is used conservatively to represent other receptor locations of surface facilities.

Table I-19. Major Inputs for the Release Source of Subsurface Exhaust Shaft #2

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
NC	0	0	7.7	385	4.0	1790	308	0	264	0	0	1
IS1	0	0	7.7	385	4.0	2230	34	0	0	0	0	1
IS2	0	0	7.7	385	4.0	427	360	0	40	0	0	1
IS3	0	0	7.7	385	4.0	3110	9	0	125	0	0	1
NR*	0	0	7.7	385	4.0	3580	328	0	327	0	0	1
SR	0	0	7.7	385	4.0	5820	349	0	290	0	0	1

Note: *The receptor location of Emplacement Ramp is used conservatively to represent other receptor locations of surface facilities.

Table I-20. Major Inputs for the Release Source of Subsurface Exhaust Shaft #3

Receptor	Release Height	Building Area	Exit Velocity	Flow	Radius	Distance	Direction	Intake Height	ΔZ	σ_{y0}	σ_{z0}	Release Type
(1)	(2) m	(3) m ²	(4) m/s	(5) m ³ /s	(6) m	(7) m	(8) °	(9) m	(10) m	(11) m	(12) m	(13)
NC	0	0	6.9	345	4.0	5050	210	0	214	0	0	1
IS1	0	0	6.9	345	4.0	3630	178	0	-50	0	0	1
IS2	0	0	6.9	345	4.0	5180	192	0	-10	0	0	1
IS3	0	0	6.9	345	4.0	2500	194	0	75	0	0	1
NR*	0	0	6.9	345	4.0	3850	231	0	277	0	0	1
SR	0	0	6.9	345	4.0	2210	276	0	240	0	0	1

Note: *The receptor location of Emplacement Ramp is used conservatively to represent other receptor locations of surface facilities.

II. LAYOUT AND VENTILATION DESIGN OF GROA FACILITIES

Sources: 000-C00-MGR0-00101-000-00B (left map) (BSC 2004 [172171]) and 100-C00-MGR0-00101-000-00C (right blowup) (BSC 2004 [171816])

Notes: The electronic files are provided on the compact disc of Attachment IV.

References and notes on the drawings are not relevant to this calculation.

Detailed locations for individual surface facilities are illustrated in the general arrangements on Figures II-a to 5.

Figure II-1. Stack/Release and Intake Locations of GROA Facilities

Sources: 110-P10-WHS0-00103-000-00A (BSC 2004 [170195])

Note: References and notes on the drawing are not relevant to this calculation.

Figure II-2a. DTF1 and Remediation Facilities General Arrangement (Operating Floor)

Figure II-2c. DTF1 and Remediation Facilities General Arrangement (Section A)

Sources: 110-P10-WHS0-00128-000-00B (BSC 2004 [170381])

Note: References and notes on the drawing are not relevant to this calculation.

Figure 11-2f. DTF1 and Remediation Facilities General Arrangement (Section K)

Sources: 110-P10-WHS0-00137-000-00B (BSC 2004 [170392])

Note: References and notes on the drawing are not relevant to this calculation.

ment (Sections A & B)

SEP 2004 [171752]]

100-P10-CH00-00108-000-00B (BSC 2004)

Figure 11-4b. Fuel Handling Facility General Arrangement (Section A)

Sources: 210-P10-FH00-00108-000-00B (BSC 2004 [171844])

Note: References and notes on the drawing are not relevant to this calculation.

Sources: 210-P10-FH00-00110-000-00B (BSC 2004 [171815])

Note: References and notes on the drawing are not relevant to this calculation.

Figure II-4c. Fuel Handling Facility General Arrangement (Sections C, D & G)

Sources: 110-M50-VN00-00101-000-00A (BSC 2004 [171245]).

Note: References and notes on the drawing are not relevant to this calculation.

Figure II-6. DTF1/Remediation Facility Ventilation Flow Diagram

Sources: 190-M50-VNT0-00601-000-00A (BSC 2004 [170639]).

Note: References and notes on the drawing are not relevant to this calculation.

Figure II-7. Canister Handling Facility Ventilation Flow Diagram

III. Calculation of Mean and Median χ/Q Values

The calculation of mean and median relative dispersion factors (χ/Q) is illustrated in this attachment. The mean and median χ/Q values are provided in the Excel Workbook LA_GROA_B.xls. Worksheet GROA_B extracts the CFD output results from 682 ARCON96 runs. Worksheet XOQGROA_B calculates the mean and median χ/Q , and worksheet XOQ prepares the results in final format ready to be used in this calculation document. The input parameters are discussed in Sections 4.1, 6.2, and Attachment I.

Verification of Mean χ/Q

The mean χ/Q is calculated by summing the probability weighted χ/Q dispersion factors as follows. For example, the mean χ/Q for Intake #1 of DTF1 from DTF1 release (110_110_1.cfd on CD) is calculated as the following:

$$\begin{aligned} \text{Mean } \chi/Q &= \left\{ \sum_i (\text{CFD}_i - \text{CFD}_{i-1}) \times (\chi/Q)_i \right\} / N \\ &= \{ (3970 - 0) \times 1.32\text{E-}5 + (24514 - 3970) \times 1.20\text{E-}5 + (37096 - 24514) \times 1.10\text{E-}5 + \\ &\quad (42310 - 37096) \times 1.00\text{E-}5 + (43177 - 42310) \times 9.12\text{E-}6 \} / 43177 \\ &= 1.1\text{E-}5 \text{ s/m}^3 \end{aligned}$$

where CFD_i = the i -th CFD value (number of hours) from the ARCON96 CFD output file;

$(\chi/Q)_i$ = the χ/Q corresponding to CFD_i ; and

N = the total number of hours (equal to the last CFD in each series).

Verification of Median χ/Q

The median χ/Q is calculated by interpolating the dispersion factors from the output CFD files as follows:

$$50^{\text{th}} \text{ percentile CFD} = 43177 \times 50\% = 21588.5 \text{ h}$$

The 50th percentile CFD of 21588.5 h falls between 3970 h and 24514 h. The corresponding χ/Q values are 1.20E-5 s/m³ and 1.10E-5 s/m³, respectively. Using a linear interpolation of Excel FORECAST function and these four bounding values, the median χ/Q can be obtained by:

$$\text{Median } \chi/Q = (\chi/Q)_1 + (\text{CFD}_m - \text{CFD}_1) \times [(\chi/Q)_2 - (\chi/Q)_1] / (\text{CFD}_2 - \text{CFD}_1)$$

$$= 1.20\text{E-}5 + (21588.5 - 3970) \times (1.10\text{E-}5 - 1.20\text{E-}5) / (24514 - 3970)$$

$$= 1.1\text{E-}5 \text{ s/m}^3$$

where $\text{CFD}_m = 50^{\text{th}}$ percentile CFD;

$\text{CFD}_1, \text{CFD}_2$ = two consecutive CFDs above and below the CFD_m ; and

$(\chi/Q)_1, (\chi/Q)_2$ = two consecutive χ/Q s corresponding to the $\text{CFD}_1/\text{CFD}_2$

Adjustment to CFD Output File

As confirmed by the author of ARCON96 (Ramsdell, 2004) that ARCON96 χ/Q cumulated frequency distribution (.cf) output file could be scaled incorrectly by a factor of 10 for time intervals greater than 8 hours in some cases. This discrepancy is illustrated in the output file of 110_14A.cfd (see Table III-2). As shown in the output file of 110_14A.log (see Attachment IV), the calculated 95th Percentile χ/Q values should decrease rather than increase with increasing the length of time interval. Table III-1 compares the output of the 95th Percentile χ/Q s listed on 110_14A.log with the calculated χ/Q s using the 110_14A.cfd output file. The comparison shows a consistent factor of 10 off for the 95th Percentile χ/Q values calculated for time intervals from 12 to 8760 hours using the 110_14A.cfd output file.

Table III-1. Calculation of 95th Percentile CFD

Averaging Period, hr (1)	1	2	4	8	12	24	96	168	720	8760
Total CFD, hr (2)	43374	43315	43200	42972	42957	42743	42815	42729	43501	43177
95th χ/Q , s/m ³ (3)	1.57E-5	1.47E-5	1.39E-5	1.16E-5	8.88E-6	6.24E-6	3.78E-6	3.24E-6	2.61E-6	1.68E-6
95th CFD, hr (4)	2169	2166	2160	2149	2148	2137	2141	2136	2175	2159
Calc. χ/Q , s/m ³ (5)	1.57E-5	1.47E-5	1.39E-5	1.16E-5	8.88E-5	6.24E-5	3.78E-5	3.24E-5	2.61E-5	1.68E-5
Adjusted χ/Q , s/m ³ (6)	1.57E-5	1.47E-5	1.39E-5	1.16E-5	8.88E-6	6.24E-6	3.78E-6	3.24E-6	2.61E-6	1.68E-6

Notes: (1)(2)(3) from 110_14A.log

(4) = (2) $\times$ (1 - 0.95)

(5) Linear interpolation with two adjacent data points from 110_14A.cfd (see Table III-2)

(6) = (5) for 1 to 8 hrs, = (5)/10 for 12 to 8760 hrs (Adjusted for correct scale)

Verification:

For the 95th percentile at 8760 hours, the (χ/Q) is interpolated linearly as:

$$(4) = \text{CFD}_{95} = 43177 \times (1 - 0.95) = 2159$$

$$(5) = (\chi/Q)_1 + (\text{CFD}_2 - \text{CFD}_{95}) \times [(\chi/Q)_2 - (\chi/Q)_1] / (\text{CFD}_2 - \text{CFD}_1)$$

$$= 1.738\text{E-}5 + (2159 - 38) \times (1.585\text{E-}5 - 1.738\text{E-}5) / (5936 - 38) = 1.68\text{E-}5 \text{ s/m}^3$$

$$(6) = 1.68\text{E-}5 / 10 = 1.68\text{E-}6 \text{ s/m}^3$$

In this calculation, the CFD outputs (for averaging time of 12, 24, 96, 168, 720, and 8760 hours) were checked and corrected, when such discrepancies were observed, by scaling down the

frequency values by a factor of 10. The CFD files required scale adjustment are marked with “*” in Tables IV-1, IV-2, and IV-3.

Table III-2. Listing of χ/Q Cumulative Frequency Distributions from Source 110 to Receptor 14A

XOQ	1	2	4	8	XOQ	12	24	96	168	720	***
Abv. Lim.	0.	0.	0.	0.	Abv. Lim.	0.	0.	0.	0.	0.	0.
9.120E-04	0.	0.	0.	0.	9.120E-04	0.	0.	0.	0.	0.	0.
8.318E-04	0.	0.	0.	0.	8.318E-04	0.	0.	0.	0.	0.	0.
7.586E-04	0.	0.	0.	0.	7.586E-04	0.	0.	0.	0.	0.	0.
6.918E-04	0.	0.	0.	0.	6.918E-04	0.	0.	0.	0.	0.	0.
6.310E-04	0.	0.	0.	0.	6.310E-04	0.	0.	0.	0.	0.	0.
5.754E-04	0.	0.	0.	0.	5.754E-04	0.	0.	0.	0.	0.	0.
5.248E-04	0.	0.	0.	0.	5.248E-04	1.	0.	0.	0.	0.	0.
4.786E-04	0.	0.	0.	0.	4.786E-04	6.	0.	0.	0.	0.	0.
4.365E-04	0.	0.	0.	0.	4.365E-04	10.	0.	0.	0.	0.	0.
3.981E-04	0.	0.	0.	0.	3.981E-04	14.	0.	0.	0.	0.	0.
3.631E-04	0.	0.	0.	0.	3.631E-04	19.	0.	0.	0.	0.	0.
3.311E-04	0.	0.	0.	0.	3.311E-04	26.	0.	0.	0.	0.	0.
3.020E-04	0.	0.	0.	0.	3.020E-04	35.	0.	0.	0.	0.	0.
2.754E-04	0.	0.	0.	0.	2.754E-04	39.	4.	0.	0.	0.	0.
2.512E-04	0.	0.	0.	0.	2.512E-04	62.	8.	0.	0.	0.	0.
2.291E-04	0.	0.	0.	0.	2.291E-04	80.	13.	0.	0.	0.	0.
2.089E-04	0.	0.	0.	0.	2.089E-04	117.	23.	0.	0.	0.	0.
1.905E-04	0.	0.	0.	0.	1.905E-04	139.	35.	0.	0.	0.	0.
1.738E-04	0.	0.	0.	0.	1.738E-04	196.	62.	0.	0.	0.	0.
1.585E-04	4.	2.	0.	0.	1.585E-04	280.	91.	0.	0.	0.	0.
1.445E-04	4.	2.	0.	0.	1.445E-04	376.	120.	0.	0.	0.	0.
1.318E-04	7.	2.	1.	0.	1.318E-04	517.	150.	0.	0.	0.	0.
1.202E-04	13.	3.	2.	0.	1.202E-04	745.	195.	0.	0.	0.	0.
1.096E-04	25.	3.	2.	0.	1.096E-04	1055.	243.	0.	0.	0.	0.
1.000E-04	25.	7.	3.	0.	1.000E-04	1428.	329.	4.	0.	0.	0.
9.120E-05	62.	8.	4.	0.	9.120E-05	1950.	449.	17.	0.	0.	0.
8.318E-05	94.	13.	4.	0.	8.318E-05	2611.	610.	41.	0.	0.	0.
7.586E-05	129.	21.	6.	1.	7.586E-05	3593.	904.	100.	0.	0.	0.
6.918E-05	177.	38.	8.	5.	6.918E-05	4596.	1371.	198.	0.	0.	0.
6.310E-05	241.	58.	15.	6.	6.310E-05	5634.	2040.	242.	13.	0.	0.
5.754E-05	286.	81.	20.	9.	5.754E-05	6785.	2792.	334.	99.	0.	0.
5.248E-05	339.	112.	35.	14.	5.248E-05	7672.	3676.	460.	230.	0.	0.
4.786E-05	388.	181.	48.	17.	4.786E-05	8471.	4726.	645.	388.	0.	0.
4.365E-05	453.	245.	63.	22.	4.365E-05	9316.	5857.	1044.	587.	0.	0.
3.981E-05	543.	331.	83.	26.	3.981E-05	9998.	7026.	1721.	921.	1.	0.
3.631E-05	590.	428.	109.	43.	3.631E-05	10687.	8086.	2451.	1380.	46.	0.
3.311E-05	716.	531.	157.	67.	3.311E-05	11505.	9151.	3286.	1954.	533.	0.
3.020E-05	831.	633.	222.	87.	3.020E-05	12125.	10066.	4383.	2746.	864.	0.
2.754E-05	976.	777.	314.	110.	2.754E-05	12880.	11079.	5828.	3984.	1762.	0.
2.512E-05	1135.	936.	391.	162.	2.512E-05	13534.	11955.	7481.	5614.	2438.	0.
2.291E-05	1302.	1085.	594.	218.	2.291E-05	14249.	12957.	9334.	7598.	3549.	0.
2.089E-05	1467.	1255.	788.	272.	2.089E-05	14958.	13975.	11075.	9553.	5106.	0.
1.905E-05	1646.	1467.	1005.	368.	1.905E-05	15527.	14870.	12980.	11766.	7457.	0.
1.738E-05	1921.	1743.	1331.	534.	1.738E-05	15974.	15643.	14933.	14036.	10202.	38.
1.585E-05	2146.	1933.	1693.	738.	1.585E-05	16672.	16658.	16711.	16433.	13415.	5936.
1.445E-05	2330.	2208.	2014.	981.	1.445E-05	17144.	17707.	18686.	18891.	17186.	11777.
1.318E-05	2490.	2596.	2380.	1349.	1.318E-05	17633.	18767.	20436.	21043.	21005.	26090.
1.202E-05	2670.	2983.	2776.	1890.	1.202E-05	18076.	19399.	21938.	23191.	25026.	41244.
1.096E-05	2859.	3452.	3250.	2487.	1.096E-05	18483.	20244.	23271.	24985.	28995.	43177.
...											
1.000E-07	10600.	11773.	13936.	18068.	1.000E-07	29047.	33316.	41680.	42645.	43501.	43177.
Belw. Lim.	1030.	3398.	6192.	9084.	Belw. Lim.	3318.	5942.	1087.	84.	0.	0.

IV. Electronic I/O Files and Workbooks on CD

The names of all input and output file are summarized in Tables IV-1, IV-2, IV-3. Electronic I/O files of ARCON96 calculations and Excel files are provided on a compact disk. The attributes of the electronic files are listed in Table IV-4. Each file is identified by its name, size (in bytes), date, time and description. The files can be read using text editor (e.g., Notepad) or MS Excel. The ARCON96 output results are processed in one Excel workbook, LA_GROA_B.xls for both surface and subsurface releases. Worksheets GA, Input, GROA_B, XOQGROA_B, and XOQ are used for General Layout of GROA_B, input parameters, output χ/Qs (extracted from cfd), calculation for mean and median χ/Qs , and preparation of χ/Qs for Tables 4 to 26, respectively. Some miscellaneous worksheets for intermediate processing and verification are also included.

Table IV-1. Names of Input and Output File for Surface Facility Releases ARCON96 Runs

	Source													
Receptor	110	120	190	210	17A1	17A2	17B	17C	17D	17E	17F	17G	17H	17J
110_1	110_110_1	120_110_1	190_110_1	210_110_1	17A1_110_1	17A2_110_1	17B_110_1	17C_110_1	17D_110_1	17E_110_1	17F_110_1	17G_110_1	17H_110_1	17J_110_1
110_2	110_110_2	120_110_2	190_110_2	210_110_2	17A1_110_2	17A2_110_2	17B_110_2	17C_110_2	17D_110_2	17E_110_2	17F_110_2	17G_110_2	17H_110_2	17J_110_2
110_3	110_110_3	120_110_3	190_110_3	210_110_3	17A1_110_3	17A2_110_3	17B_110_3	17C_110_3	17D_110_3	17E_110_3	17F_110_3	17G_110_3	17H_110_3	17J_110_3
120_1	110_120_1	120_120_1	190_120_1	210_120_1	17A1_120_1	17A2_120_1	17B_120_1	17C_120_1	17D_120_1	17E_120_1	17F_120_1	17G_120_1	17H_120_1	17J_120_1
120_2	110_120_2	120_120_2	190_120_2	210_120_2	17A1_120_2	17A2_120_2	17B_120_2	17C_120_2	17D_120_2	17E_120_2	17F_120_2	17G_120_2	17H_120_2	17J_120_2
120_3	110_120_3	120_120_3	190_120_3	210_120_3	17A1_120_3	17A2_120_3	17B_120_3	17C_120_3	17D_120_3	17E_120_3	17F_120_3	17G_120_3	17H_120_3	17J_120_3
120_4	110_120_4	120_120_4	190_120_4	210_120_4	17A1_120_4	17A2_120_4	17B_120_4	17C_120_4	17D_120_4	17E_120_4	17F_120_4	17G_120_4	17H_120_4	17J_120_4
14A	110_14A	120_14A	190_14A	210_14A	17A1_14A	17A2_14A	17B_14A	17C_14A	17D_14A	17E_14A	17F_14A	17G_14A	17H_14A	17J_14A
14B	110_14B	120_14B	190_14B	210_14B	17A1_14B	17A2_14B	17B_14B	17C_14B	17D_14B	17E_14B	17F_14B	17G_14B	17H_14B	17J_14B
150	110_150	120_150	190_150	210_150	17A1_150	17A2_150	17B_150	17C_150	17D_150	17E_150	17F_150	17G_150	17H_150	17J_150
160	110_160	120_160	190_160	210_160	17A1_160	17A2_160	17B_160	17C_160	17D_160	17E_160	17F_160	17G_160	17H_160	17J_160
17A	110_17A	120_17A	190_17A	210_17A	17A1A	17A2_17A	17B_17A	17C_17A	17D_17A	17E_17A	17F_17A	17G_17A	17H_17A	17J_17A
17BCDE	110_17BCDE	120_17BCDE	190_17BCDE	210_17BCDE	17A1_17BCDE	17A2_17BCDE	17B_17BCDE	17C_17BCDE	17D_17BCDE	17E_17BCDE	17F_17BCDE	17G_17BCDE	17H_17BCDE	17J_17BCDE
17FG	110_17FG	120_17FG	190_17FG	210_17FG	17A1_17FG	17A2_17FG	17B_17FG	17C_17FG	17D_17FG	17E_17FG	17F_17FG	17G_17FG	17H_17FG	17J_17FG
17HJ	110_17HJ	120_17HJ	190_17HJ	210_17HJ	17A1_17HJ	17A2_17HJ	17B_17HJ	17C_17HJ	17D_17HJ	17E_17HJ	17F_17HJ	17G_17HJ	17H_17HJ	17J_17HJ
190_1	110_190_1	120_190_1	190_190_1	210_190_1	17A1_190_1	17A2_190_1	17B_190_1	17C_190_1	17D_190_1	17E_190_1	17F_190_1	17G_190_1	17H_190_1	17J_190_1
190_2	110_190_2	120_190_2	190_190_2	210_190_2	17A1_190_2	17A2_190_2	17B_190_2	17C_190_2	17D_190_2	17E_190_2	17F_190_2	17G_190_2	17H_190_2	17J_190_2
190_3	110_190_3	120_190_3	190_190_3	210_190_3	17A1_190_3	17A2_190_3	17B_190_3	17C_190_3	17D_190_3	17E_190_3	17F_190_3	17G_190_3	17H_190_3	17J_190_3
190_4	110_190_4	120_190_4	190_190_4	210_190_4	17A1_190_4	17A2_190_4	17B_190_4	17C_190_4	17D_190_4	17E_190_4	17F_190_4	17G_190_4	17H_190_4	17J_190_4

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B Page: IV-2 of IV-56

210_1	110_210_1	120_210_1	190_210_1	210_210_1	17A1_210_1	17A2_210_1	17B_210_1	17C_210_1	17D_210_1	17E_210_1	17F_210_1	17G_210_1	17H_210_1	17J_210_1
25A	110_25A	120_25A	190_25A	210_25A	17A1_25A	17A2_25A	17B_25A	17C_25A	17D_25A	17E_25A	17F_25A	17G_25A	17H_25A	17J_25A
220	110_220	120_220*	190_220	210_220	17A1_220	17A2_220	17B_220	17C_220	17D_220	17E_220	17F_220	17G_220	17H_220	17J_220
240	110_240	120_240	190_240*	210_240*	17A1_240	17A2_240	17B_240	17C_240	17D_240	17E_240	17F_240	17G_240	17H_240	17J_240
30A	110_30A	120_30A	190_30A	210_30A	17A1_30A	17A2_30A	17B_30A	17C_30A	17D_30A	17E_30A	17F_30A	17G_30A	17H_30A	17J_30A
30B	110_30B	120_30B	190_30B	210_30B	17A1_30B	17A2_30B	17B_30B	17C_30B	17D_30B	17E_30B	17F_30B	17G_30B	17H_30B	17J_30B
30C	110_30C	120_30C	190_30C	210_30C*	17A1_30C	17A2_30C	17B_30C*	17C_30C	17D_30C*	17E_30C	17F_30C*	17G_30C	17H_30C	17J_30C*
620	110_620	120_620	190_620	210_620	17A1_620	17A2_620	17B_620	17C_620	17D_620	17E_620	17F_620	17G_620	17H_620	17J_620
63A	110_63A	120_63A	190_63A	210_63A	17A1_63A	17A2_63A	17B_63A	17C_63A	17D_63A	17E_63A	17F_63A	17G_63A	17H_63A	17J_63A
65A	110_65A	120_65A	190_65A	210_65A	17A1_65A	17A2_65A	17B_65A	17C_65A	17D_65A	17E_65A	17F_65A	17G_65A	17H_65A	17J_65A
65B	110_65B	120_65B	190_65B	210_65B	17A1_65B	17A2_65B	17B_65B	17C_65B	17D_65B	17E_65B	17F_65B	17G_65B	17H_65B	17J_65B
68AB	110_68AB	120_68AB	190_68AB	210_68AB	17A1_68AB	17A2_68AB	17B_68AB	17C_68AB	17D_68AB	17E_68AB	17F_68AB	17G_68AB	17H_68AB	17J_68AB
71AB	110_71AB	120_71AB	190_71AB	210_71AB	17A1_71AB	17A2_71AB	17B_71AB	17C_71AB	17D_71AB	17E_71AB	17F_71AB	17G_71AB	17H_71AB	17J_71AB
NC	110_NC	120_NC	190_NC	210_NC	17A1_NC	17A2_NC	17B_NC	17C_NC	17D_NC*	17E_NC*	17F_NC*	17G_NC	17H_NC	17J_NC
IS1	110_IS1	120_IS1	190_IS1	210_IS1	17A1_IS1	17A2_IS1	17B_IS1	17C_IS1	17D_IS1	17E_IS1	17F_IS1	17G_IS1	17H_IS1	17J_IS1
IS2	110_IS2	120_IS2	190_IS2	210_IS2	17A1_IS2	17A2_IS2	17B_IS2	17C_IS2	17D_IS2	17E_IS2	17F_IS2	17G_IS2	17H_IS2	17J_IS2
IS3	110_IS3	120_IS3	190_IS3	210_IS3	17A1_IS3	17A2_IS3	17B_IS3	17C_IS3	17D_IS3	17E_IS3	17F_IS3	17G_IS3	17H_IS3	17J_IS3
NR	110_NR	120_NR	190_NR*	210_NR	17A1_NR	17A2_NR	17B_NR*	17C_NR*	17D_NR	17E_NR	17F_NR	17G_NR	17H_NR	17J_NR
SR	110_SR	120_SR	190_SR	210_SR	17A1_SR	17A2_SR	17B_SR	17C_SR	17D_SR	17E_SR	17F_SR	17G_SR	17H_SR	17J_SR

Notes:

¹See Table 1 for the abbreviation description of all release sources and receptors used in this table.

²All entries in this table have the file extensions of RSF, LOG, and CFD for input file, primary output file, and cumulative frequency distribution (cfd) output file, respectively.

³Files marked with * indicate adjusted CFD scale. (see Attachment III)

Table IV-2. Names of Input and Output File for Event Sequences Releases ARCON96 Runs ARCON96 Runs

Receptor	Source			Receptor	Source		
	110X	120X	210X		110X	120X	210X
110_1	110X_110_1	120X_110_1	210X_110_1	210_1	110X_210_1	120X_210_1	210X_210_1
110_2	110X_110_2	120X_110_2	210X_110_2	25A	110X_25A*	120X_25A	210X_25A*
110_3	110X_110_3	120X_110_3	210X_110_3	220	110X_220	120X_220	210X_220*
120_1	110X_120_1	120X_120_1	210X_120_1	240	110X_240	120X_240	210X_240
120_2	110X_120_2	120X_120_2	210X_120_2	30A	110X_30A	120X_30A*	210X_30A
120_3	110X_120_3	120X_120_3	210X_120_3	30B	110X_30B	120X_30B	210X_30B
120_4	110X_120_4	120X_120_4	210X_120_4	30C	110X_30C	120X_30C	210X_30C
14A	110X_14A	120X_14A	210X_14A	620	110X_620	120X_620	210X_620
14B	110X_14B	120X_14B	210X_14B*	63A	110X_63A	120X_63A	210X_63A
150	110X_150	120X_150	210X_150	65A	110X_65A	120X_65A	210X_65A
160	110X_160	120X_160	210X_160	65B	110X_65B	120X_65B	210X_65B
17A	110X_17A	120X_17A	210X_17A	68AB	110X_68AB	120X_68AB	210X_68AB
17BCDE	110X_17BCDE	120X_17BCDE	210X_17BCDE	71AB	110X_71AB	120X_71AB	210X_71AB
17FG	110X_17FG	120X_17FG	210X_17FG	NC	110X_NC	120X_NC	210X_NC
17HJ	110X_17HJ	120X_17HJ	210X_17HJ	IS1	110X_IS1	120X_IS1	210X_IS1
190_1	110X_190_1*	120X_190_1	210X_190_1	IS2	110X_IS2	120X_IS2	210X_IS2
190_2	110X_190_2	120X_190_2	210X_190_2	IS3	110X_IS3	120X_IS3	210X_IS3
190_3	110X_190_3*	120X_190_3	210X_190_3	NR	110X_NR	120X_NR	210X_NR
190_4	110X_190_4	120X_190_4	210X_190_4	SR	110X_SR	120X_SR	210X_SR

Notes:

¹See Table 1 for the abbreviation descriptions of release sources and receptors.²All entries in this table have the file extensions of RSF, LOG, and CFD for input file, primary output file, and cumulative frequency distribution (cf) output file, respectively.³Files marked with * indicate adjusted CFD scale. (see Attachment III)

Table IV-3. Names of Input and Output File for Subsurface Releases ARCON96 Runs

Receptor	Source					
	ECRB	ER1	ER2	ES1	ES2	ES3
NC	ECRB_NC	ER1_NC	ER2_NC	ES1_NC	ES2_NC	ES3_NC
IS1	ECRB_IS1	ER1_IS1	ER2_IS1	ES1_IS1*	ES2_IS1	ES3_IS1
IS2	ECRB_IS2	ER1_IS2	ER2_IS2	ES1_IS2	ES2_IS2	ES3_IS2
IS3	ECRB_IS3	ER1_IS3	ER2_IS3	ES1_IS3	ES2_IS3	ES3_IS3
NR	ECRB_NR	ER1_NR	ER2_NR	ES1_NR	ES2_NR	ES3_NR
SR	ECRB_SR	ER1_SR	ER2_SR	ES1_SR	ES2_SR	ES3_SR

Note:

¹See Table 1 for the abbreviation description of all release sources and receptors used here.²All entries in this table have the file extensions of RSF, LOG, and CFD for input file, primary output file, and cumulative frequency distribution (cf) output file, respectively.³Files marked with * indicate adjusted CFD scale. (see Attachment III)

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-4 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk

Date	Time	Size (bytes)	File Name	Description
2005/3/9	03:30p	11,168	110X_110_1.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	03:32p	4,837	110X_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_110_2.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_110_3.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_1.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_2.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_3.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_4.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_14A.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_14B.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_150.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_150.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_160.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_160.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17A.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	335	110X_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17FG.cfd	ARCON96 Cumulative Frequency Distribution Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,837	110X_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_220.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_240.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-6 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	326	110X_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_620.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110X_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	323	110X_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation**Document Identifier:** 000-HYC-MGR0-00100-000-00B**Page:** IV-7 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	110_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_110_1.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_110_2.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_110_3.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_120_1.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_120_2.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_120_3.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_120_4.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_14A.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_14B.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_150.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_160.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_160.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_17A.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	110_17BCDE.rsfl	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	110_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	327	110_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_620.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	110_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-10 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,837	120X_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120X_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_160.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120X_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120X_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	335	120X_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-11 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	120X_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120X_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120X_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120X_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_220.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_240.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-12 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	326	120X_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_620.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120X_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120X_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	120X_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	323	120X_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	120_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_110_1.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_110_2.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_110_3.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_120_1.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_120_2.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_120_3.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_120_4.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_14A.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_14B.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_150.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_160.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_160.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_17A.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	120_17BCDE.rsfl	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-14 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	120_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation**Document Identifier:** 000-HYC-MGR0-00100-000-00B**Page:** IV-15 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	327	120_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_620.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	120_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	328	120_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	120_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-16 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17A1_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A1_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	332	17A1_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17A1_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A1_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A1_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A1_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A1_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17A1_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_620.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A1_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A1_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A1_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A1_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A1_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A1_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A1_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17A2_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17A2_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	332	17A2_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-20 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17A2_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A2_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A2_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A2_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A2_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17A2_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_620.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A2_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A2_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A2_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A2_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A2_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A2_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A2_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17B_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17B_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-23 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17B_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17B_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17B_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17B_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17B_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17B_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17C_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17C_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17C_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-26 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17C_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17C_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17C_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17C_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17C_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17C_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17C_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-28 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17D_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17D_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17D_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17D_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17D_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17D_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-30 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17D_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17D_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17D_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17D_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17E_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17E_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-32 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17E_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17E_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17E_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17E_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17E_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17E_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17E_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-34 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17F_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17F_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17F_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17F_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17F_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17F_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_240.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-36 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17F_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17F_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17F_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17F_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17F_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17F_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17F_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17F_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17G_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17G_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_160.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17G_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17G_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17G_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_240.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17G_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17G_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17G_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17G_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17G_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17G_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17G_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17G_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17G_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-40 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17H_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17H_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17H_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_150.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_160.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17H_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17H_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17H_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_220.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_240.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-42 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	322	17H_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_620.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17H_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17H_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17H_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17H_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17J_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17J_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_150.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_160.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17HJ.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-44 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17J_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17J_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17J_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_220.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_240.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_620.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_65A.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17J_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17J_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17J_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17J_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17J_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_110_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_3.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-46 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	190_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_150.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_160.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	190_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	190_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	190_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	190_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_210_1.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	331	190_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	190_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_620.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_IS2.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-48 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	190_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	190_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	190_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	190_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_110_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210X_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_160.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,837	210X_160.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210X_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	335	210X_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	331	210X_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	331	210X_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	334	210X_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	333	210X_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_220.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_240.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210X_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_30B.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-50 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	327	210X_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_620.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210X_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210X_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210X_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210X_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210X_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210X_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_110_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_110_1.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-51 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	210_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_150.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_160.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	210_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-52 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	210_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	333	210_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_620.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_65B.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation**Document Identifier:** 000-HYC-MGR0-00100-000-00B**Page:** IV-53 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	328	210_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	387	ECRB_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	386	ECRB_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	386	ECRB_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ECRB_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ECRB_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ECRB_SR.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-54 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	ER1_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ER1_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	386	ER1_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ER1_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER1_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER1_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	381	ER1_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ER2_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ER2_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ER2_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER2_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER2_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	381	ER2_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ES1_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ES1_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_IS3.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	ES1_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES1_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES1_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES1_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	382	ES1_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ES2_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES2_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES2_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES2_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES2_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	372	ES2_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES3_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES3_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES3_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	382	ES3_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	382	ES3_NR.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	ES3_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	381	ES3_SR.rsf	ARCON96 Primary Input
2005/3/9	08:50a	1,621,488	Site9802.MET	ARCON96 Meteorological Input from 1998 to 2002
2005/3/16	02:59p	6,297,600	LA_GROA_B.xls	MS Excel Workbook for Preparing ARCON96 Inputs and for Processing ARCON96 Results
2005/3/9	12:22p	20,559,872	OverallSitePlan.skt	Engineering CAD drawing for Overall GROA Site Plan
2005/3/9	12:22p	3,516,416	NoPortalSitePlan.skt	Engineering CAD drawing for Overall GROA Site Plan without Portal Construction

OCRWM

SPECIAL INSTRUCTION SHEET

1. QA: QA
Page 1 of 1

This is a placeholder page for records that cannot be scanned.

2. Record Date

03/21/2005

3. Accession Number

ATT-TO ENG.20050321.0001

λ

4. Author Name(s)

John Wang

5. Authorization Organization

BSC – Preclosure Safety Analysis

6. Title/Description

GROA Airborne Release Dispersion Factor Calculation

7. Document Number(s)

000-HYC-MGR0-00100-000-00B

8. Version Designator

00B

9. Document Type

Data

10. Medium

2 CDs

11. Access Control Code

PUB

12. Traceability Designator

000-HYC-MGR0-00100-000-00B / OCT# 44255 @ 3/22/05

13. Comments

The originator provided 1 original CD and 1 copy of the CD. Complete file transfer verified.

File listing is included.

THIS IS AN ELECTRONIC
ATTACHMENT

GA: QLA
3/22/05
Page 10 3/22/05

IV. Electronic I/O Files and Workbooks on CD

The names of all input and output file are summarized in Tables IV-1, IV-2, IV-3. Electronic I/O files of ARCON96 calculations and Excel files are provided on a compact disk. The attributes of the electronic files are listed in Table IV-4. Each file is identified by its name, size (in bytes), date, time and description. The files can be read using text editor (e.g., Notepad) or MS Excel. The ARCON96 output results are processed in one Excel workbook, LA_GROA_B.xls for both surface and subsurface releases. Worksheets GA, Input, GROA_B, XOQGROA_B, and XOQ are used for General Layout of GROA_B, input parameters, output χ/Qs (extracted from cfd), calculation for mean and median χ/Qs , and preparation of χ/Qs for Tables 4 to 26, respectively. Some miscellaneous worksheets for intermediate processing and verification are also included.

Table IV-1. Names of Input and Output File for Surface Facility Releases ARCON96 Runs

Receptor	Source															
	110	120	190	210	17A1	17A2	17B	17C	17D	17E	17F	17G	17H	17J		
110 1	110_110_1	120_110_1	190_110_1	210_110_1	17A1_110_1	17A2_110_1	17B_110_1	17C_110_1	17D_110_1	17E_110_1	17F_110_1	17G_110_1	17H_110_1	17J_110_1		
110 2	110_110_2	120_110_2	190_110_2	210_110_2	17A1_110_2	17A2_110_2	17B_110_2	17C_110_2	17D_110_2	17E_110_2	17F_110_2	17G_110_2	17H_110_2	17J_110_2		
110 3	110_110_3	120_110_3	190_110_3	210_110_3	17A1_110_3	17A2_110_3	17B_110_3	17C_110_3	17D_110_3	17E_110_3	17F_110_3	17G_110_3	17H_110_3	17J_110_3		
120 1	110_120_1	120_120_1	190_120_1	210_120_1	17A1_120_1	17A2_120_1	17B_120_1	17C_120_1	17D_120_1	17E_120_1	17F_120_1	17G_120_1	17H_120_1	17J_120_1		
120 2	110_120_2	120_120_2	190_120_2	210_120_2	17A1_120_2	17A2_120_2	17B_120_2	17C_120_2	17D_120_2	17E_120_2	17F_120_2	17G_120_2	17H_120_2	17J_120_2		
120 3	110_120_3	120_120_3	190_120_3	210_120_3	17A1_120_3	17A2_120_3	17B_120_3	17C_120_3	17D_120_3	17E_120_3	17F_120_3	17G_120_3	17H_120_3	17J_120_3		
120 4	110_120_4	120_120_4	190_120_4	210_120_4	17A1_120_4	17A2_120_4	17B_120_4	17C_120_4	17D_120_4	17E_120_4	17F_120_4	17G_120_4	17H_120_4	17J_120_4		
14A	110_14A	120_14A	190_14A	210_14A	17A1_14A	17A2_14A	17B_14A	17C_14A	17D_14A	17E_14A	17F_14A	17G_14A	17H_14A	17J_14A		
14B	110_14B	120_14B	190_14B	210_14B	17A1_14B	17A2_14B	17B_14B	17C_14B	17D_14B	17E_14B	17F_14B	17G_14B	17H_14B	17J_14B		
150	110_150	120_150	190_150	210_150	17A1_150	17A2_150	17B_150	17C_150	17D_150	17E_150	17F_150	17G_150	17H_150	17J_150		
160	110_160	120_160	190_160	210_160	17A1_160	17A2_160	17B_160	17C_160	17D_160	17E_160	17F_160	17G_160	17H_160	17J_160		
17A	110_17A	120_17A	190_17A	210_17A	17A7A	17A2_17A	17B_17A	17C_17A	17D_17A	17E_17A	17F_17A	17G_17A	17H_17A	17J_17A		
17BCDE	110_17BCDE	120_17BCDE	190_17BCDE	210_17BCDE	17A1_17BCDE	17A2_17BCDE	17B_17BCDE	17C_17BCDE	17D_17BCDE	17E_17BCDE	17F_17BCDE	17G_17BCDE	17H_17BCDE	17J_17BCDE		
17FG	110_17FG	120_17FG	190_17FG	210_17FG	17A1_17FG	17A2_17FG	17B_17FG	17C_17FG	17D_17FG	17E_17FG	17F_17FG	17G_17FG	17H_17FG	17J_17FG		
17HJ	110_17HJ	120_17HJ	190_17HJ	210_17HJ	17A1_17HJ	17A2_17HJ	17B_17HJ	17C_17HJ	17D_17HJ	17E_17HJ	17F_17HJ	17G_17HJ	17H_17HJ	17J_17HJ		
190 1	110_190_1	120_190_1	190_190_1	210_190_1	17A1_190_1	17A2_190_1	17B_190_1	17C_190_1	17D_190_1	17E_190_1	17F_190_1	17G_190_1	17H_190_1	17J_190_1		
190 2	110_190_2	120_190_2	190_190_2	210_190_2	17A1_190_2	17A2_190_2	17B_190_2	17C_190_2	17D_190_2	17E_190_2	17F_190_2	17G_190_2	17H_190_2	17J_190_2		
190 3	110_190_3	120_190_3	190_190_3	210_190_3	17A1_190_3	17A2_190_3	17B_190_3	17C_190_3	17D_190_3	17E_190_3	17F_190_3	17G_190_3	17H_190_3	17J_190_3		
190 4	110_190_4	120_190_4	190_190_4	210_190_4	17A1_190_4	17A2_190_4	17B_190_4	17C_190_4	17D_190_4	17E_190_4	17F_190_4	17G_190_4	17H_190_4	17J_190_4		

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B **Page: IV-2 of IV-56**

210_1	110_210_1	120_210_1	190_210_1	210_210_1	17A1_210_1	17A2_210_1	17B_210_1	17C_210_1	17D_210_1	17E_210_1	17F_210_1	17G_210_1	17H_210_1	17J_210_1
25A	110_25A	120_25A	190_25A	210_25A	17A1_25A	17A2_25A	17B_25A	17C_25A	17D_25A	17E_25A	17F_25A	17G_25A	17H_25A	17J_25A
220	110_220	120_220*	190_220	210_220	17A1_220	17A2_220	17B_220	17C_220	17D_220	17E_220	17F_220	17G_220	17H_220	17J_220
240	110_240	120_240	190_240*	210_240*	17A1_240	17A2_240	17B_240	17C_240	17D_240	17E_240	17F_240	17G_240	17H_240	17J_240
30A	110_30A	120_30A	190_30A	210_30A	17A1_30A	17A2_30A	17B_30A	17C_30A	17D_30A	17E_30A	17F_30A	17G_30A	17H_30A	17J_30A
30B	110_30B	120_30B	190_30B	210_30B	17A1_30B	17A2_30B	17B_30B	17C_30B	17D_30B	17E_30B	17F_30B	17G_30B	17H_30B	17J_30B
30C	110_30C	120_30C	190_30C	210_30C*	17A1_30C	17A2_30C	17B_30C*	17C_30C	17D_30C*	17E_30C	17F_30C*	17G_30C	17H_30C	17J_30C*
620	110_620	120_620	190_620	210_620	17A1_620	17A2_620	17B_620	17C_620	17D_620	17E_620	17F_620	17G_620	17H_620	17J_620
63A	110_63A	120_63A	190_63A	210_63A	17A1_63A	17A2_63A	17B_63A	17C_63A	17D_63A	17E_63A	17F_63A	17G_63A	17H_63A	17J_63A
65A	110_65A	120_65A	190_65A	210_65A	17A1_65A	17A2_65A	17B_65A	17C_65A	17D_65A	17E_65A	17F_65A	17G_65A	17H_65A	17J_65A
65B	110_65B	120_65B	190_65B	210_65B	17A1_65B	17A2_65B	17B_65B	17C_65B	17D_65B	17E_65B	17F_65B	17G_65B	17H_65B	17J_65B
68AB	110_68AB	120_68AB	190_68AB	210_68AB	17A1_68AB	17A2_68AB	17B_68AB	17C_68AB	17D_68AB	17E_68AB	17F_68AB	17G_68AB	17H_68AB	17J_68AB
71AB	110_71AB	120_71AB	190_71AB	210_71AB	17A1_71AB	17A2_71AB	17B_71AB	17C_71AB	17D_71AB	17E_71AB	17F_71AB	17G_71AB	17H_71AB	17J_71AB
NC	110_NC	120_NC	190_NC	210_NC	17A1_NC	17A2_NC	17B_NC	17C_NC	17D_NC*	17E_NC*	17F_NC*	17G_NC	17H_NC	17J_NC
IS1	110_IS1	120_IS1	190_IS1	210_IS1	17A1_IS1	17A2_IS1	17B_IS1	17C_IS1	17D_IS1	17E_IS1	17F_IS1	17G_IS1	17H_IS1	17J_IS1
IS2	110_IS2	120_IS2	190_IS2	210_IS2	17A1_IS2	17A2_IS2	17B_IS2	17C_IS2	17D_IS2	17E_IS2	17F_IS2	17G_IS2	17H_IS2	17J_IS2
IS3	110_IS3	120_IS3	190_IS3	210_IS3	17A1_IS3	17A2_IS3	17B_IS3	17C_IS3	17D_IS3	17E_IS3	17F_IS3	17G_IS3	17H_IS3	17J_IS3
NR	110_NR	120_NR	190_NR*	210_NR	17A1_NR	17A2_NR	17B_NR*	17C_NR*	17D_NR	17E_NR	17F_NR	17G_NR	17H_NR	17J_NR
SR	110_SR	120_SR	190_SR	210_SR	17A1_SR	17A2_SR	17B_SR	17C_SR	17D_SR	17E_SR	17F_SR	17G_SR	17H_SR	17J_SR

Notes:

¹See Table 1 for the abbreviation description of all release sources and receptors used in this table.

²All entries in this table have the file extensions of RSF, LOG, and CFD for input file, primary output file, and cumulative frequency distribution (cfd) output file, respectively.

³Files marked with * indicate adjusted CFD scale. (see Attachment III)

Table IV-2. Names of Input and Output File for Event Sequences Releases ARCON96 Runs ARCON96 Runs

Receptor	Source			Receptor	Source		
	110X	120X	210X		110X	120X	210X
110 1	110X 110 1	120X 110 1	210X 110 1	210 1	110X 210 1	120X 210 1	210X 210 1
110 2	110X 110 2	120X 110 2	210X 110 2	25A	110X 25A*	120X 25A	210X 25A*
110 3	110X 110 3	120X 110 3	210X 110 3	220	110X 220	120X 220	210X 220*
120 1	110X 120 1	120X 120 1	210X 120 1	240	110X 240	120X 240	210X 240
120 2	110X 120 2	120X 120 2	210X 120 2	30A	110X 30A	120X 30A*	210X 30A
120 3	110X 120 3	120X 120 3	210X 120 3	30B	110X 30B	120X 30B	210X 30B
120 4	110X 120 4	120X 120 4	210X 120 4	30C	110X 30C	120X 30C	210X 30C
14A	110X 14A	120X 14A	210X 14A	620	110X 620	120X 620	210X 620
14B	110X 14B	120X 14B	210X 14B*	63A	110X 63A	120X 63A	210X 63A
150	110X 150	120X 150	210X 150	65A	110X 65A	120X 65A	210X 65A
160	110X 160	120X 160	210X 160	65B	110X 65B	120X 65B	210X 65B
17A	110X 17A	120X 17A	210X 17A	68AB	110X 68AB	120X 68AB	210X 68AB
17BCDE	110X 17BCDE	120X 17BCDE	210X 17BCDE	71AB	110X 71AB	120X 71AB	210X 71AB
17FG	110X 17FG	120X 17FG	210X 17FG	NC	110X NC	120X NC	210X NC
17HJ	110X 17HJ	120X 17HJ	210X 17HJ	IS1	110X IS1	120X IS1	210X IS1
190 1	110X 190 1*	120X 190 1	210X 190 1	IS2	110X IS2	120X IS2	210X IS2
190 2	110X 190 2	120X 190 2	210X 190 2	IS3	110X IS3	120X IS3	210X IS3
190 3	110X 190 3*	120X 190 3	210X 190 3	NR	110X NR	120X NR	210X NR
190 4	110X 190 4	120X 190 4	210X 190 4	SR	110X SR	120X SR	210X SR

Notes:

¹See Table 1 for the abbreviation descriptions of release sources and receptors.²All entries in this table have the file extensions of RSF, LOG, and CFD for input file, primary output file, and cumulative frequency distribution (cf) output file, respectively.³Files marked with * indicate adjusted CFD scale. (see Attachment III)

Table IV-3. Names of Input and Output File for Subsurface Releases ARCON96 Runs

Receptor	Source					
	ECRB	ER1	ER2	ES1	ES2	ES3
NC	ECRB NC	ER1 NC	ER2 NC	ES1 NC	ES2 NC	ES3 NC
IS1	ECRB IS1	ER1 IS1	ER2 IS1	ES1 IS1*	ES2 IS1	ES3 IS1
IS2	ECRB IS2	ER1 IS2	ER2 IS2	ES1 IS2	ES2 IS2	ES3 IS2
IS3	ECRB IS3	ER1 IS3	ER2 IS3	ES1 IS3	ES2 IS3	ES3 IS3
NR	ECRB NR	ER1 NR	ER2 NR	ES1 NR	ES2 NR	ES3 NR
SR	ECRB SR	ER1 SR	ER2 SR	ES1 SR	ES2 SR	ES3 SR

Note:

¹See Table 1 for the abbreviation description of all release sources and receptors used here.²All entries in this table have the file extensions of RSF, LOG, and CFD for input file, primary output file, and cumulative frequency distribution (cf) output file, respectively.³Files marked with * indicate adjusted CFD scale. (see Attachment III)

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-4 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk

Date	Time	Size (bytes)	File Name	Description
2005/3/9	03:30p	11,168	110X_110_1.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	03:32p	4,837	110X_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_110_2.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_110_3.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_1.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_2.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_3.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_120_4.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_14A.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_14B.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_150.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_150.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_160.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_160.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17A.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution Output
2005/3/9	08:41a	4,837	110X_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	335	110X_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17FG.cfd	ARCON96 Cumulative Frequency Distribution Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-5 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,837	110X_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110X_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110X_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_220.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_240.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-6 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	326	110X_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_620.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110X_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110X_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110X_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110X_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	323	110X_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110X_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	110X_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	110X_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	110_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_160.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	110_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	110_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	110_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	110_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	327	110_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_620.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	110_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	110_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	110_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	110_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	110_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	110_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	110_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	110_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	110_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,837	120X_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120X_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_160.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120X_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120X_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	335	120X_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	120X_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120X_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120X_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120X_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120X_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_220.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_240.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-12 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	326	120X_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_620.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120X_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120X_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120X_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	120X_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120X_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	323	120X_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120X_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	120X_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	120X_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	120_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_160.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	120_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-14 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	120_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	120_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	120_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	327	120_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_620.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	120_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	328	120_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	120_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	120_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	120_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	120_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	120_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	120_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	120_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	120_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17A1_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A1_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	332	17A1_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-17 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17A1_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A1_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A1_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A1_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A1_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A1_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17A1_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_620.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A1_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A1_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A1_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A1_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A1_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A1_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A1_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A1_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A1_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A1_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A1_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17A2_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17A2_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	332	17A2_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17A2_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A2_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17A2_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17A2_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A2_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A2_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17A2_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_620.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17A2_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A2_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A2_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A2_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17A2_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17A2_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17A2_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17A2_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17A2_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17A2_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17A2_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17B_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17B_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17B_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-23 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17B_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17B_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17B_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17B_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17B_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17B_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17B_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17B_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17B_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17B_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17B_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17B_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-25 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17C_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_110_1.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_110_2.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_110_3.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_1.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_2.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_3.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_120_4.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_14A.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_14B.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_150.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_160.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17C_17A.rsfl	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17C_17BCDE.rsfl	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-26 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17C_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17C_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17C_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17C_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-27 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17C_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17C_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17C_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17C_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17C_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17C_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17C_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17C_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17C_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17D_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17D_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17D_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17D_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17D_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17D_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17D_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-30 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17D_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17D_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17D_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17D_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17D_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17D_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17D_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17D_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17D_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-31 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17E_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17E_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17E_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17E_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17E_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17E_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_220.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_240.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-33 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17E_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17E_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17E_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17E_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17E_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17E_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17E_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17E_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17E_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17F_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17F_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_160.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17F_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-35 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17F_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	17F_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17F_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17F_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_240.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17F_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17F_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17F_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17F_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17F_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17F_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17F_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17F_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17F_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17F_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17F_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17F_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17G_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17G_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_150.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_160.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17G_17BCDE.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-38 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17G_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17G_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17G_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17G_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_220.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_240.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17G_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_30C.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-39 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	323	17G_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_620.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17G_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17G_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17G_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17G_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17G_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17G_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17G_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17G_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17G_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17G_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17G_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17H_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17H_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17H_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_150.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_160.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_17BCDE.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17H_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17H_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17H_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17H_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_220.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_240.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_30C.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	322	17H_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_620.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17H_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17H_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17H_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17H_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17H_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17H_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17H_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17H_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17H_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_110_1.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-43 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	17J_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	327	17J_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_150.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_160.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_17HJ.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	324	17J_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17J_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	328	17J_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	329	17J_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_220.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_240.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_620.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_65A.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-45 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	17J_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	324	17J_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17J_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	326	17J_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	325	17J_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	323	17J_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	321	17J_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	17J_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	17J_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	322	17J_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_110_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_3.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	190_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_150.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_160.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	190_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	190_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	331	190_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	331	190_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	331	190_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_210_1.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-47 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	331	190_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	190_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_620.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	190_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	190_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	190_IS2.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	190_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	190_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	190_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	190_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	190_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	190_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	190_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_110_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_110_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210X_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_150.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_160.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-49 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,837	210X_160.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210X_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	335	210X_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	331	210X_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	331	210X_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	334	210X_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210X_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	333	210X_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_220.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_240.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210X_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_30B.log	ARCON96 Primary Output

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	327	210X_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_620.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_65B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210X_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210X_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210X_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210X_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210X_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210X_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210X_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210X_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,837	210X_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210X_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_110_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_110_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_110_1.rsf	ARCON96 Primary Input

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-51 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	210_110_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_110_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_110_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_110_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_110_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_110_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_120_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_120_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_120_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_14A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_14A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_14A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_14B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_14B.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_14B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_150.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_150.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_150.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_160.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_160.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210_160.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_17A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17BCDE.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17BCDE.log	ARCON96 Primary Output
2005/3/9	08:41a	336	210_17BCDE.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17FG.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17FG.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_17FG.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_17HJ.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_17HJ.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_17HJ.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_1.cfd	ARCON96 Cumulative Frequency Distribution

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,794	210_190_1.log	ARCON96 Primary Output
2005/3/9	08:41a	333	210_190_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_190_2.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_190_2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_190_3.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_190_3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_190_4.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_190_4.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_190_4.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_210_1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_210_1.log	ARCON96 Primary Output
2005/3/9	08:41a	332	210_210_1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_220.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_220.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_220.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_240.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_240.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210_240.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_25A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_25A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_25A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_30A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_30A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_30A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_30B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_30B.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_30B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_30C.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_30C.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_30C.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_620.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_620.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_620.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_63A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_63A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_63A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_65A.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_65A.log	ARCON96 Primary Output
2005/3/9	08:41a	328	210_65A.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_65B.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_65B.log	ARCON96 Primary Output

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-53 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	328	210_65B.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_68AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_68AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_68AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_71AB.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,794	210_71AB.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_71AB.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	330	210_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	329	210_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	327	210_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	325	210_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	210_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	210_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	326	210_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	387	ECRB_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	386	ECRB_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	386	ECRB_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ECRB_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ECRB_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ECRB_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ECRB_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ECRB_SR.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	ER1_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ER1_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	386	ER1_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ER1_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER1_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER1_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER1_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER1_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	381	ER1_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ER2_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ER2_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ER2_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER2_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ER2_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ER2_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ER2_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	381	ER2_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ES1_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ES1_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_IS3.cfd	ARCON96 Cumulative Frequency Distribution

Title: GROA Airborne Release Dispersion Factor Calculation

Document Identifier: 000-HYC-MGR0-00100-000-00B

Page: IV-55 of IV-56

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	4,802	ES1_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES1_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES1_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES1_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES1_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES1_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	382	ES1_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	384	ES2_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES2_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES2_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES2_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES2_NR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES2_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES2_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	372	ES2_SR.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_IS1.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_IS1.log	ARCON96 Primary Output
2005/3/9	08:41a	383	ES3_IS1.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_IS2.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_IS2.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES3_IS2.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_IS3.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_IS3.log	ARCON96 Primary Output
2005/3/9	08:41a	385	ES3_IS3.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_NC.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_NC.log	ARCON96 Primary Output
2005/3/9	08:41a	382	ES3_NC.rsf	ARCON96 Primary Input
2005/3/9	08:41a	11,168	ES3_NR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_NR.log	ARCON96 Primary Output
2005/3/9	08:41a	382	ES3_NR.rsf	ARCON96 Primary Input

Table IV-4. Files Used for ARCON96 Calculations on the Compact Disk (Continued)

Date	Time	Size (bytes)	Name	Description
2005/3/9	08:41a	11,168	ES3_SR.cfd	ARCON96 Cumulative Frequency Distribution
2005/3/9	08:41a	4,802	ES3_SR.log	ARCON96 Primary Output
2005/3/9	08:41a	381	ES3_SR.rsf	ARCON96 Primary Input
2005/3/9	08:50a	1,621,488	Site9802.MET	ARCON96 Meteorological Input from 1998 to 2002
2005/3/16	02:59p	6,297,600	LA_GROA_B.xls	MS Excel Workbook for Preparing ARCON96 Inputs and for Processing ARCON96 Results
2005/3/9	12:22p	20,559,872	OverallSitePlan.skt	Engineering CAD drawing for Overall GROA Site Plan
2005/3/9	12:22p	3,516,416	NoPortalSitePlan.skt	Engineering CAD drawing for Overall GROA Site Plan without Portal Construction